# EUROPEAN TELECOMMUNICATION STANDARD

**ETS 300 476-3**

**August 1996**

Source: ETSI TC-RES

Reference: DE/RES-03042-3

ICS: 33.020, 33.060.50

**Key words:** DECT, CI, PICS

# Radio Equipment and Systems (RES); Digital Enhanced Cordless Telecommunications (DECT); Common Interface (CI); Protocol Implementation Conformance Statement (PICS) proforma; Part 3: Medium Access Control (MAC) layer - Portable radio Termination (PT)

**ETSI**

European Telecommunications Standards Institute

**ETSI Secretariat**

**Postal address:** F-06921 Sophia Antipolis CEDEX - FRANCE
**Office address:** 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE
**X.400:** c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 92 94 42 00 - Fax: +33 93 65 47 16

**Copyright Notification:** No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1996. All rights reserved.

Whilst every care has been taken in the preparation and publication of this document, errors in content, typographical or otherwise, may occur. If you have comments concerning its accuracy, please write to "ETSI Editing and Committee Support Dept." at the address shown on the title page.

# Contents

Foreword ..... 13

1 Scope ..... 15

2 Normative references ..... 15

3 Definitions and abbreviations ..... 16
3.1 Definitions ..... 16
3.2 Abbreviations ..... 16

4 Conformance requirement to this PICS proforma specification ..... 16

Annex A (normative): PICS proforma for DECT MAC PT ..... 17

A.1 Introduction for completing the PICS proforma ..... 17
A.1.1 Purposes and structure ..... 17
A.1.2 Symbols, abbreviations and conventions ..... 17
A.1.3 Guidances for completing the PICS ..... 18

A.2 Identification of the implementation ..... 19
A.2.1 Date of statement ..... 19
A.2.2 Implementation Under Test (IUT) identification ..... 19
A.2.3 System Under Test (SUT) identification ..... 19
A.2.4 Product supplier ..... 19
A.2.5 Client identification ..... 20
A.2.6 Contact person ..... 20

A.3 Identification of the protocol ..... 20

A.4 Global statement of conformance ..... 20

A.5 Capabilities ..... 21
A.5.1 Services ..... 21
A.5.1.1 Connection oriented control services ..... 21
A.5.1.2 Broadcast control services ..... 22
A.5.1.3 Connectionless control services ..... 22
A.5.1.3.1 Downlink connectionless services ..... 22
A.5.1.3.2 Uplink connectionless services ..... 23
A.5.1.4 Multiplexing services ..... 23
A.5.1.5 Management services ..... 24
A.5.2 Procedures ..... 24
A.5.2.1 Connection procedures ..... 25
A.5.2.1.1 Connection setup procedures ..... 25
A.5.2.1.2 Connection modification procedures ..... 26
A.5.2.1.3 Connection data transfer procedures ..... 26
A.5.2.1.4 Handover procedures ..... 26
A.5.2.1.5 Connection release procedures ..... 27
A.5.2.2 Broadcast procedures ..... 27
A.5.2.3 Connectionless procedures ..... 27
A.5.2.3.1 Downlink connectionless procedures ..... 27
A.5.2.3.2 Uplink connectionless procedures ..... 27
A.5.2.4 CSF multiplexing procedures ..... 28
A.5.2.5 Layer management procedures ..... 28
A.5.3 Other capabilities ..... 28

A.6 Protocol parameters ..... 29

A.6.1 Timer support ..... 29
A.6.2 Protocol constants ..... 29
A.6.3 Channel selection parameters ..... 29
A.6.4 Channels supported ..... 30
A.6.5 Bearer types supported ..... 30
A.6.6 Slot types supported ..... 30

A.7 Messages ..... 30
A.7.1 A - field header ..... 31
A.7.1.1 A - field header - Tail Identification ..... 31
A.7.1.2 A - field header - “Q1/BCK” bit ..... 31
A.7.1.3 A - field header - B-field identification ..... 32
A.7.1.4 A - field header - “Q2” bit ..... 32
A.7.2 A - field identities information ($N_T$) message ..... 32
A.7.3 A - field system information ($Q_T$) messages ..... 33
A.7.4 A - field paging tail ($P_T$) messages ..... 33
A.7.4.1 Paging tail messages supported ..... 33
A.7.4.2 $P_T$ messages information type ..... 33
A.7.5 A - field MAC control ($M_T$) messages ..... 34
A.7.5.1 Mac control messages supported ..... 34
A.7.5.2 Basic connection control messages ..... 35
A.7.5.3 MAC layer test messages ..... 35
A.7.5.4 Advanced connection control messages ..... 36
A.7.5.5 Quality control messages ..... 37
A.7.5.6 Broadcast and connectionless (BCL) messages ..... 37
A.7.5.7 Encryption control (EC) messages ..... 38
A.7.6 B - Field Messages ..... 39
A.7.6.1 B - Field Messages supported ..... 39
A.7.6.2 B - Field Advanced connection control messages ..... 39
A.7.6.3 B - Field - Null messages ..... 40
A.7.6.4 B - Field - Quality control messages ..... 41
A.7.6.5 B - Field - GF-channel data packet messages ..... 42

A.8 MAC messages format and field value ..... 43
A.8.1 A - field identities information ($N_T$) message ..... 43
A.8.2 A - field system information ($Q_T$) messages ..... 44
A.8.2.1 QT - Static system information ..... 44
A.8.2.2 QT - Extended RF carrier information ..... 44
A.8.2.3 QT - Fixed part capability ..... 45
A.8.2.4 QT - Extended fixed part capabilities ..... 45
A.8.2.5 QT - Secondary access rights identities ..... 45
A.8.2.6 QT - Multi-frame number ..... 46
A.8.2.7 QT - escape ..... 46
A.8.3 A - field paging tail ($P_T$) messages ..... 46
A.8.3.1 $P_T$ message - Full page ..... 46
A.8.3.2 $P_T$ message - Long page ..... 46
A.8.3.3 $P_T$ message - Short page ..... 47
A.8.3.4 $P_T$ message - Zero length page ..... 47
A.8.3.5 $P_T$ messages - MAC info. element ..... 47
A.8.3.5.1 MAC info. element - Fill bits ..... 47
A.8.3.5.2 MAC info. element - Blind full slot ..... 47
A.8.3.5.3 MAC info. element - Other bearer ..... 48
A.8.3.5.4 MAC info. element - Recommended other bearer ..... 48
A.8.3.5.5 MAC info. element - Good RFP bearer ..... 48
A.8.3.5.6 MAC info. element - Dummy or C/L bearer position ..... 48
A.8.3.5.7 MAC info. element - RFP identity ..... 48
A.8.3.5.8 MAC info. element - Escape ..... 49
A.8.3.5.9 MAC info. element - Dummy or C/L bearer marker ..... 49
A.8.3.5.10 MAC info. element - Bearer handover information ..... 49
A.8.3.5.11 MAC info. element - RFP status ..... 49
A.8.4 A - field MAC control ($M_T$) messages ..... 50
A.8.4.1 Basic connection control messages ..... 50
A.8.4.1.1 Basic CC - access request ..... 50

A.8.4.1.2 Basic CC - bearer handover request ..... 50
A.8.4.1.3 Basic CC - connection handover request ..... 50
A.8.4.1.4 Basic CC - unconfirmed access request ..... 50
A.8.4.1.5 Basic CC - bearer confirm ..... 51
A.8.4.1.6 Basic CC - wait ..... 51
A.8.4.1.7 Basic CC - release ..... 51
A.8.4.2 MAC layer test messages ..... 52
A.8.4.2.1 MAC test - force transmit ..... 52
A.8.4.2.2 MAC test - loopback data ..... 53
A.8.4.2.3 MAC test - defeat antenna diversity ..... 53
A.8.4.2.4 MAC test - force bearer handover ..... 53
A.8.4.2.5 MAC test - escape ..... 54
A.8.4.2.6 MAC test - network test ..... 54
A.8.4.2.7 MAC test - clear test modes ..... 55
A.8.4.3 Advanced connection control messages ..... 55
A.8.4.3.1 Advanced CC - access request ..... 55
A.8.4.3.2 Advanced CC - bearer handover request ..... 56
A.8.4.3.3 Advanced CC - connection handover request ..... 56
A.8.4.3.4 Advanced CC - unconfirmed access request ..... 56
A.8.4.3.5 Advanced CC - bearer confirm ..... 57
A.8.4.3.6 Advanced CC - wait ..... 57
A.8.4.3.7 Advanced CC - Attributes_T request ..... 58
A.8.4.3.8 Advanced CC - Attributes_T confirm ..... 59
A.8.4.3.9 Advanced CC - Bandwidth_T request ..... 59
A.8.4.3.10 Advanced CC - Bandwidth_T confirm ..... 60
A.8.4.3.11 Advanced CC - Channel List ..... 61
A.8.4.3.12 Advanced CC - Unconfirmed_dummy ..... 61
A.8.4.3.13 Advanced CC - Unconfirmed_handover ..... 62
A.8.4.3.14 Advanced CC - release ..... 62
A.8.4.4 Quality control messages ..... 63
A.8.4.4.1 QC - antenna switch single bearer request ..... 63
A.8.4.4.2 QC - antenna switch all bearers request ..... 63
A.8.4.4.3 QC - bearer handover request ..... 64
A.8.4.4.4 QC - connection handover request ..... 64
A.8.4.4.5 QC - frequency control single bearer request ..... 65
A.8.4.4.6 QC - frequency control all bearers request ..... 65
A.8.4.5 Broadcast and connectionless (BCL) messages ..... 66
A.8.4.5.1 BCL - CLF, first of 2 transmissions, half slot ..... 66
A.8.4.5.2 BCL - CLF, first of 2 transmissions, full slot ..... 66
A.8.4.5.3 BCL - CLF, first of 2 transmissions, double slot ..... 66
A.8.4.5.4 BCL - CLF, last transmissions, half slot ..... 67
A.8.4.5.5 BCL - CLF, last transmissions, full slot ..... 67
A.8.4.5.6 BCL - CLF, last transmissions, double slot ..... 67
A.8.4.5.7 BCL - C/L single transmissions, no CF or CLS ..... 67
A.8.4.5.8 BCL - CLS service, first transmissions ..... 68
A.8.4.5.9 BCL - change dummy bearer position ..... 68
A.8.4.5.10 BCL - extended system info., A-field procedure ..... 68
A.8.4.5.11 BCL - extended system info., B-field procedure ..... 69
A.8.4.6 Encryption control (EC) messages ..... 69
A.8.4.6.1 EC - Encryption start ..... 69
A.8.4.6.2 EC - Encryption stop ..... 70
A.8.4.7 $M_T$ message - B - field setup ..... 72
A.8.4.8 $M_T$ message - Escape ..... 72
A.8.4.9 $M_T$ message - TARI ..... 72
A.8.5 B - Field Messages ..... 73
A.8.5.1 B - Field - Advanced CC messages ..... 73
A.8.5.1.1 B-field Advanced CC - Access request ..... 73
A.8.5.1.2 B-field Advanced CC - Bearer handover request ..... 74
A.8.5.1.3 B-field Advanced CC - Connection handover request ..... 75
A.8.5.1.4 B-field Advanced CC - Unconfirmed access request ..... 76
A.8.5.1.5 B-field Advanced CC - Bearer confirm ..... 77
A.8.5.1.6 B-field Advanced CC - Wait ..... 77
A.8.5.1.7 B-field Advanced CC - Attributes_B request ..... 78

A.8.5.1.8 B-field Advanced CC - Attributes_B confirm ..... 79
A.8.5.1.9 B-field Advanced CC - Bandwidth_B request ..... 80
A.8.5.1.10 B-field Advanced CC - Bandwidth_B confirm ..... 81
A.8.5.1.11 B-field Advanced CC - Channel List..... 82
A.8.5.1.12 B-field Advanced CC - Unconfirmed_Dummy ..... 83
A.8.5.1.13 B-field Advanced CC - Unconfirmed_Handover ..... 84
A.8.5.1.14 B-field Advanced CC - Release ..... 85
A.8.5.2 B-field - Null Messages (NM)..... 85
A.8.5.2.1 B-field - NM No $C_F$ or $CL_F$ data in the B-field..... 85
A.8.5.2.2 B-field - NM One B-subfield contains $C_F$ or $CL_F$ data..... 86
A.8.5.2.3 B-field - NM Two B-subfield contain $C_F$ or $CL_F$ data..... 87
A.8.5.2.4 B-field - NM Three B-subfield contain $C_F$ or $CL_F$ data..... 87
A.8.5.2.5 B-field - NM Four B-subfield contain $C_F$ or $CL_F$ data ..... 88
A.8.5.2.6 B-field - NM Five B-subfield contain $C_F$ or $CL_F$ data..... 89
A.8.5.2.7 B-field - NM Six B-subfield contain $C_F$ or $CL_F$ data..... 89
A.8.5.2.8 B-field - NM Seven B-subfield contain $C_F$ or $CL_F$ data ..... 90
A.8.5.2.9 B-field - NM Eight B-subfield contain $C_F$ or $CL_F$ data ..... 91
A.8.5.2.10 B-field - NM Nine B-subfield contain $C_F$ or $CL_F$ data ..... 91
A.8.5.3 B - Field - Quality control (QC) messages..... 92
A.8.5.3.1 B - Field - QC Antenna switch single bearer..... 92
A.8.5.3.2 B - Field - QC Antenna switch all bearers..... 93
A.8.5.3.3 B - Field - QC Bearer handover ..... 93
A.8.5.3.4 B - Field - QC Connection handover..... 94
A.8.5.3.5 B - Field - QC Frequency control single bearer..... 95
A.8.5.3.6 B - Field - QC Frequency control all bearers..... 95
A.8.5.3.7 B - Field - QC Reset request first TDMA half frame ..... 96
A.8.5.3.8 B - Field - QC Reset request second TDMA half frame..... 97
A.8.5.3.9 B - Field - QC Reset request both TDMA half frames ..... 97
A.8.5.3.10 B - Field - QC Reset confirm first TDMA half frame ..... 98
A.8.5.3.11 B - Field - QC Reset confirm second TDMA half frame..... 99
A.8.5.3.12 B - Field - QC Reset confirm both TDMA half frames ..... 99
A.8.5.3.13 B - Field - QC MOD2 ACK ..... 100
A.8.5.4 B - Field - Extended system information (ES) messages..... 101
A.8.5.4.1 B - Field - ES TARI message..... 101
A.8.5.5 B - Field - GF-channel data packet messages ..... 101
A.8.5.5.1 B - Field - GF-No $C_F$ data in the B-field..... 101
A.8.5.5.2 B - Field - GF-One B-subfield contains $C_F$ data ..... 102
A.8.5.5.3 B - Field - GF-Two B-subfield contain $C_F$ data..... 102
A.8.5.5.4 B - Field - GF-Three B-subfield contain $C_F$ data ..... 103
A.8.5.5.5 B - Field - GF-Four B-subfield contain $C_F$ data ..... 103
A.8.5.5.6 B - Field - GF-Five B-subfield contain $C_F$ data..... 104
A.8.5.5.7 B - Field - GF-Six B-subfield contain $C_F$ data..... 104
A.8.5.5.8 B - Field - GF-Seven B-subfield contain $C_F$ data..... 105
A.8.5.5.9 B - Field - GF-Eight B-subfield contain $C_F$ data..... 105
A.8.5.5.10 B - Field - GF-Nine B-subfield contain $C_F$ data ..... 106
A.8.5.6 B - Field - Escape message ..... 106

History..... 107

# Questions

Table A.1: Date of Statement ..... 19
Table A.2: IUT identification ..... 19
Table A.3: SUT identification ..... 19
Table A.4: Product supplier ..... 19
Table A.5: Client identification ..... 20
Table A.6: Contact person identification ..... 20
Table A.7: Identification of protocol ..... 20
Table A.8: Global statement of conformance ..... 20
Table A.9: Service groups supported ..... 21
Table A.10: Connection oriented control services ..... 21
Table A.11: Connection services ..... 21
Table A.12: Symmetric connection oriented services ..... 21
Table A.13: Asymmetric connection oriented services ..... 22
Table A.14: C-plane connection services ..... 22
Table A.15: Broadcast services ..... 22
Table A.16: Connectionless control services ..... 22
Table A.17: Downlink connectionless services ..... 22
Table A.18: Uplink connectionless services ..... 23
Table A.19: CSF multiplexing services ..... 23
Table A.20: D-MAP services ..... 23
Table A.21: B-MAP services ..... 23
Table A.22: E/U mux services ..... 24
Table A.23: C mux mapping services ..... 24
Table A.24: Management services ..... 24
Table A.25: Handover services management ..... 24
Table A.26: C/O single bearer setup procedures ..... 25
Table A.27: C/O multi-bearer symmetric setup procedures ..... 25
Table A.28: C/O multi-bearer asymmetric setup procedures ..... 25
Table A.29: C/O bearer setup procedures ..... 26
Table A.30: C/O connection modification procedures ..... 26
Table A.31: C/O data transfer procedures ..... 26
Table A.32: Handover procedures ..... 26
Table A.33: C/O connection release procedures ..... 27
Table A.34: Broadcast procedures ..... 27
Table A.35: Downlink connectionless procedures ..... 27
Table A.36: Uplink connectionless procedures ..... 27
Table A.37: CSF multiplexing procedures ..... 28
Table A.38: Layer management procedures ..... 28
Table A.39: Extended RF carriers supported ..... 28
Table A.40: Operation modes in Idle_locked state supported ..... 28
Table A.41: Timer supported ..... 29
Table A.42: Protocol constants support ..... 29
Table A.43: Channel selection parameters ..... 30
Table A.44: Channels supported ..... 30
Table A.45: Bearer types supported ..... 30
Table A.46: Slot types supported ..... 30
Table A.47: Tail Identification (Sending P to F) ..... 31
Table A.48: Tail Identification (Receipt F to P) ..... 31
Table A.49: Q1/BCK bit (Sending P to F) ..... 31
Table A.50: Q1/BCK bit (Receipt F to P) ..... 31
Table A.51: B-field identification (Sending P to F) ..... 32
Table A.52: B-field identification (Receipt F to P) ..... 32
Table A.53: Q2 bit (Sending P to F) ..... 32
Table A.54: Q2 bit (Receipt F to P) ..... 32
Table A.55: Identities information ($N_T$) message (Sending P to F) ..... 33
Table A.56: Identities information ($N_T$) message (Receipt F to P) ..... 33
Table A.57: System information ($Q_T$) message (Receipt F to P) ..... 33
Table A.58: Paging tail ($P_T$) messages (Receipt F to P) ..... 33

Table A.59: $P_T$ messages information supported (Receipt F to P) ..... 34
Table A.60: MAC control ($M_T$) messages (Sending P to F) ..... 34
Table A.61: MAC control ($M_T$) messages (Receipt F to P) ..... 34
Table A.62: Basic connection control (Sending P to F) ..... 35
Table A.63: Basic connection control (Receipt F to P) ..... 35
Table A.64: MAC layer test messages (Sending P to F) ..... 35
Table A.65: MAC layer test messages (Receipt F to P) ..... 36
Table A.66: Advanced connection control messages (Sending P to F) ..... 36
Table A.67: Advanced connection control messages (Receipt F to P) ..... 37
Table A.68: Quality control (QC) messages (Sending P to F) ..... 37
Table A.69: Quality control (QC) messages (Receipt F to P) ..... 37
Table A.70: Broadcast and connectionless (BCL) messages (Sending P to F) ..... 38
Table A.71: Broadcast and connectionless (BCL) messages (Receipt F to P) ..... 38
Table A.72: Encryption control (EC) messages (Sending P to F) ..... 38
Table A.73: Encryption control (EC) messages (Receipt F to P) ..... 39
Table A.74: B - Field messages supported (Sending P to F) ..... 39
Table A.75: B - Field messages supported (Receipt F to P) ..... 39
Table A.76: B - Field Advanced connection control messages (Sending P to F) ..... 40
Table A.77: B - Field Advanced connection control messages (Receipt F to P) ..... 40
Table A.78: B - Field - Null messages (Sending P to F) ..... 41
Table A.79: B - Field - Null messages (Receipt F to P) ..... 41
Table A.80: B - Field - Quality control messages (Sending P to F) ..... 42
Table A.81: B - Field - Quality control messages (Receipt F to P) ..... 42
Table A.82: B - Field - GF-channel data packet messages (Sending P to F) ..... 43
Table A.83: B - Field - GF-channel data packet messages (Receipt F to P) ..... 43
Table A.84: NT - Identities Information (Sending P to F) ..... 43
Table A.85: NT - Identities Information (Receipt F to P) ..... 44
Table A.86: QT - Static system information (Receipt F to P) ..... 44
Table A.87: QT - Extended RF carrier information (Receipt F to P) ..... 44
Table A.88: QT - Fixed part capability (Receipt F to P) ..... 45
Table A.89: QT - Extended fixed part capabilities (Receipt F to P) ..... 45
Table A.90: QT - Secondary access rights identities (Receipt F to P) ..... 45
Table A.91: QT - Multi-frame number (Receipt F to P) ..... 46
Table A.92: QT - escape (Receipt F to P) ..... 46
Table A.93: $P_T$ message - Full page (Receipt F to P) ..... 46
Table A.94: $P_T$ message - Long page (Receipt F to P) ..... 46
Table A.95: $P_T$ message - Short page (Receipt F to P) ..... 47
Table A.96.: $P_T$ message - Zero length page (Receipt F to P) ..... 47
Table A.97: MAC info. element - Fill bits (Receipt F to P) ..... 47
Table A.98: MAC info. element - Blind full slot (Receipt F to P) ..... 47
Table A.99.: MAC info. element - Other bearer (Receipt F to P) ..... 48
Table A.100: MAC info. element - Recommended other bearer (Receipt F to P) ..... 48
Table A.101: MAC info. element - Good RFP bearer (Receipt F to P) ..... 48
Table A.102: MAC info. element - Dummy or C/L bearer position (Receipt F to P) ..... 48
Table A.103.: MAC info. element - RFP identity (Receipt F to P) ..... 48
Table A.104: MAC info. element - Escape (Receipt F to P) ..... 49
Table A.105: MAC info. element - Dummy or C/L bearer marker (Receipt F to P) ..... 49
Table A.106: MAC info. element - Bearer handover information (Receipt F to P) ..... 49
Table A.107: MAC info. element - RFP status (Receipt F to P) ..... 49
Table A.108: Basic CC - access request (Sending P to F) ..... 50
Table A.109: Basic CC - bearer handover request (Sending P to F) ..... 50
Table A.110: Basic CC - connection handover request (Sending P to F) ..... 50
Table A.111: Basic CC - unconfirmed access request (Sending P to F) ..... 50
Table A.112: Basic CC - bearer confirm (Receipt F to P) ..... 51
Table A.113: Basic CC - wait (Sending P to F) ..... 51
Table A.114: Basic CC - wait (Receipt F to P) ..... 51
Table A.115: Basic CC - release (Sending P to F) ..... 51
Table A.116: Basic CC - release (Receipt F to P) ..... 52
Table A.117: MAC test - force transmit (Sending P to F) ..... 52
Table A.118: MAC test - force transmit (Receipt F to P) ..... 52
Table A.119: MAC test - loopback data (Sending P to F) ..... 53
Table A.120: MAC test - loopback data (Receipt F to P) ..... 53
Table A.121: MAC test - defeat antenna diversity (Sending P to F) ..... 53

Table A.122.: MAC test - force bearer handover (Sending P to F) ..... 53
Table A.123.: MAC test - force bearer handover (Receipt F to P) ..... 54
Table A.124: MAC test - escape (Sending P to F) ..... 54
Table A.125: MAC test - escape (Receipt F to P) ..... 54
Table A.126: MAC test - network test (Sending P to F) ..... 54
Table A.127: MAC test - network test (Receipt F to P) ..... 54
Table A.128: MAC test - clear test modes (Sending P to F) ..... 55
Table A.129: MAC test - clear test modes (Receipt F to P) ..... 55
Table A.130: Advanced CC - access request (Sending P to F) ..... 55
Table A.131: Advanced CC - access request (Receipt F to P) ..... 55
Table A.132: Advanced CC - bearer handover request (Sending P to F) ..... 56
Table A.133: Advanced CC - connection handover request (Sending P to F) ..... 56
Table A.134: Advanced CC - connection handover request (Receipt F to P) ..... 56
Table A.135: Advanced CC - unconfirmed access request (Sending P to F) ..... 56
Table A.136: Advanced CC - unconfirmed access request (Receipt F to P) ..... 57
Table A.137: Advanced CC - bearer confirm (Sending P to F) ..... 57
Table A.138: Advanced CC - bearer confirm (Receipt F to P) ..... 57
Table A.139: Advanced CC - wait (Sending P to F) ..... 57
Table A.140: Advanced CC - wait (Receipt F to P) ..... 58
Table A.141: Advanced CC - Attributes_T request (Sending P to F) ..... 58
Table A.142: Advanced CC - Attributes_T request (Receipt F to P) ..... 58
Table A.143: Advanced CC - Attributes_T confirm (Sending P to F) ..... 59
Table A.144: Advanced CC - Attributes_T confirm (Receipt F to P) ..... 59
Table A.145: Advanced CC - Bandwidth_T request (Sending P to F) ..... 59
Table A.146: Advanced CC - Bandwidth_T request (Receipt F to P) ..... 60
Table A.147: Advanced CC - Bandwidth_T confirm (Sending P to F) ..... 60
Table A.148: Advanced CC - Bandwidth_T confirm (Receipt F to P) ..... 60
Table A.149: Advanced CC - Channel List (Sending P to F) ..... 61
Table A.150: Advanced CC - Channel List (Receipt F to P) ..... 61
Table A.151: Advanced CC - Unconfirmed_dummy (Sending P to F) ..... 61
Table A.152: Advanced CC - Unconfirmed_dummy (Receipt F to P) ..... 61
Table A.153: Advanced CC - Unconfirmed_handover (Sending P to F) ..... 62
Table A.154: Advanced CC - Unconfirmed_handover (Receipt F to P) ..... 62
Table A.155: Advanced CC - release (Sending P to F) ..... 62
Table A.156: Advanced CC - release (Receipt F to P) ..... 62
Table A.157: QC - antenna switch single bearer request (Sending P to F) ..... 63
Table A.158: QC - antenna switch single bearer request (Receipt F to P) ..... 63
Table A.159: QC - antenna switch all bearers request (Sending P to F) ..... 63
Table A.160: QC - antenna switch all bearers request (Receipt F to P) ..... 64
Table A.161: QC - bearer handover request (Sending P to F) ..... 64
Table A.162: QC - bearer handover request (Receipt F to P) ..... 64
Table A.163: QC - connection handover request (Sending P to F) ..... 64
Table A.164: QC - connection handover request (Receipt F to P) ..... 65
Table A.165: QC - frequency control single bearer request (Sending P to F) ..... 65
Table A.166: QC - frequency control single bearer request (Receipt F to P) ..... 65
Table A.167: QC - frequency control all bearers request (Sending P to F) ..... 65
Table A.168: QC - frequency control all bearers request (Receipt F to P) ..... 66
Table A.169: BCL - CLF, first of 2 transmissions, half slot (Sending P to F) ..... 66
Table A.170: BCL - CLF first of 2 transmissions, full slot (Sending P to F) ..... 66
Table A.171: BCL - CLF first of 2 transmissions, double slot (Sending P to F) ..... 66
Table A.172: BCL - CLF, last transmissions, half slot (Sending P to F) ..... 67
Table A.173: BCL - CLF, last transmissions, full slot (Sending P to F) ..... 67
Table A.174: BCL - CLF, last transmissions, double slot (Sending P to F) ..... 67
Table A.175: BCL - C/L single transmissions, no CF or CLS (Sending P to F) ..... 67
Table A.176: BCL - CLS service, first transmission (Sending P to F) ..... 68
Table A.177: BCL - change dummy bearer position (Sending P to F) ..... 68
Table A.178: BCL - extended system info., A-field procedure (Sending P to F) ..... 68
Table A.179: BCL - extended system info., A-field procedure (Receipt F to P) ..... 68
Table A.180: BCL - extended system info., B-field procedure (Sending P to F) ..... 69
Table A.181: BCL - extended system info., B-field procedure (Receipt F to P) ..... 69
Table A.182: EC - Encryption start request (Sending P to F) ..... 69
Table A.183: EC - Encryption start request (Receipt F to P) ..... 69
Table A.184: EC - Encryption start grant (Sending P to F) ..... 70

Table A.185: EC - Encryption start grant (Receipt F to P) ..... 70
Table A.186: EC - Encryption start confirm (Sending P to F) ..... 70
Table A.187: EC - Encryption start confirm (Receipt F to P) ..... 70
Table A.188: EC - Encryption stop request (Sending P to F) ..... 70
Table A.189: EC - Encryption stop request (Receipt F to P) ..... 71
Table A.190: EC - Encryption stop grant (Sending P to F) ..... 71
Table A.191: EC - Encryption stop grant (Receipt F to P) ..... 71
Table A.192: EC - Encryption stop confim (Sending P to F) ..... 71
Table A.193: EC - Encryption stop confim (Receipt F to P) ..... 71
Table A.194: $M_T$ message - B - field setup (Sending P to F) ..... 72
Table A.195: $M_T$ message - Escape (Sending P to F) ..... 72
Table A.196: $M_T$ message - Escape (Receipt F to P) ..... 72
Table A.197: $M_T$ message - TARI request (Sending P to F) ..... 72
Table A.198: $M_T$ message - TARI reply (Receipt F to P) ..... 72
Table A.199: B-field Advanced CC - Access request (Sending P to F) ..... 73
Table A.200: B-field Advanced CC - Access request (Receipt F to P) ..... 73
Table A.201: B-field Advanced CC - Bearer handover request (Sending P to F) ..... 74
Table A.202: B-field Advanced CC - Bearer handover request (Receipt F to P) ..... 74
Table A.203: B-field Advanced CC - Connection handover request (Sending P to F) ..... 75
Table A.204: B-field Advanced CC - Connection handover request (Receipt F to P) ..... 75
Table A.205: B-field Advanced CC - Unconfirmed access request (Sending P to F) ..... 76
Table A.206: B-field Advanced CC - Unconfirmed access request (Receipt F to P) ..... 76
Table A.207: B-field Advanced CC - Bearer confirm (Sending P to F) ..... 77
Table A.208: B-field Advanced CC - Bearer confirm (Receipt F to P) ..... 77
Table A.209: B-field Advanced CC - Wait (Sending P to F) ..... 77
Table A.210: B-field Advanced CC - Wait (Receipt F to P) ..... 78
Table A.211: B-field Advanced CC - Attributes_B request (Sending P to F) ..... 78
Table A.212: B-field Advanced CC - Attributes_B request (Receipt F to P) ..... 78
Table A.213: B-field Advanced CC - Attributes_B confirm (Sending P to F) ..... 79
Table A.214: B-field Advanced CC - Attributes_B confirm (Receipt F to P) ..... 79
Table A.215: B-field Advanced CC - Bandwidth_B request (Sending P to F) ..... 80
Table A.216: B-field Advanced CC - Bandwidth_B request (Receipt F to P) ..... 80
Table A.217: B-field Advanced CC - Bandwidth_B confirm (Sending P to F) ..... 81
Table A.218: B-field Advanced CC - Bandwidth_B confirm (Receipt F to P) ..... 81
Table A.219: B-field Advanced CC - Channel List (Sending P to F) ..... 82
Table A.220: B-field Advanced CC - Channel List (Receipt F to P) ..... 82
Table A.221: B-field Advanced CC - Unconfirmed_Dummy (Sending P to F) ..... 83
Table A.222: B-field Advanced CC - Unconfirmed_Dummy (Receipt F to P) ..... 83
Table A.223: B-field Advanced CC - Unconfirmed_Handover (Sending P to F) ..... 84
Table A.224: B-field Advanced CC - Unconfirmed_Handover (Receipt F to P) ..... 84
Table A.225: B-field Advanced CC - Release (Sending P to F) ..... 85
Table A.226: B-field Advanced CC - Release (Receipt F to P) ..... 85
Table A.227: B-field - NM No $C_F$ or $CL_F$ data in the B-field (Sending P to F) ..... 85
Table A.228: B-field - NM No $C_F$ or $CL_F$ data in the B-field (Receipt F to P) ..... 86
Table A.229: B-field - NM One B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 86
Table A.230: B-field - NM One B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 86
Table A.231: B-field - NM Two B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 87
Table A.232: B-field - NM Two B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 87
Table A.233: B-field - NM Three B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 87
Table A.234: B-field - NM Three B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 88
Table A.235: B-field - NM Four B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 88
Table A.236: B-field - NM Four B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 88
Table A.237: B-field - NM Five B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 89
Table A.238: B-field - NM Five B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 89
Table A.239: B-field - NM Six B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 89
Table A.240: B-field - NM Six B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 90
Table A.241: B-field - NM Seven B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 90
Table A.242: B-field - NM Seven B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 90
Table A.243: B-field - NM Eight B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 91
Table A.244: B-field - NM Eight B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 91
Table A.245: B-field - NM Nine B-subfield contains $C_F$ or $CL_F$ data (Sending P to F) ..... 91
Table A.246: B-field - NM Nine B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P) ..... 92
Table A.247 : B-field QC - Antenna switch single bearer (Sending P to F) ..... 92

Table A.248 : B-field QC - Antenna switch single bearer (Receipt F to P)....92
Table A.249: B-field QC - Antenna switch all bearers (Sending P to F)....93
Table A.250: B-field QC - Antenna switch all bearers (Receipt F to P)....93
Table A.251: B-field QC - Bearer handover (Sending P to F)....93
Table A.252: B-field QC - Bearer handover (Receipt F to P)....94
Table A.253: B - Field - QC Connection handover (Sending P to F)....94
Table A.254: B - Field - QC Connection handover (Receipt F to P)....94
Table A.255: B-field QC - Frequency control single bearer (Sending P to F)....95
Table A.256: B-field QC - Frequency control single bearer (Receipt F to P)....95
Table A.257: B-field QC - Frequency control all bearers (Sending P to F)....95
Table A.258: B-field QC - Frequency control all bearers (Receipt F to P)....96
Table A.259: B - Field - QC Reset request first TDMA half frame (Sending P to F)....96
Table A.260: B - Field - QC Reset request first TDMA half frame (Receipt F to P)....96
Table A.261: B - Field - QC Reset request second TDMA half frame (Sending P to F)....97
Table A.262: B - Field - QC Reset request second TDMA half frame (Receipt F to P)....97
Table A.263: B - Field - QC Reset request both TDMA half frame (Sending P to F)....97
Table A.264: B - Field - QC Reset request both TDMA half frame (Receipt F to P)....98
Table A.265: B - Field - QC Reset confirm first TDMA half frame (Sending P to F)....98
Table A.266: B - Field - QC Reset confirm first TDMA half frame (Receipt F to P)....98
Table A.267: B - Field - QC Reset confirm second TDMA half frame (Sending P to F)....99
Table A.268: B - Field - QC Reset confirm second TDMA half frame (Receipt F to P)....99
Table A.269: B - Field - QC Reset confirm both TDMA half frame (Sending P to F)....99
Table A.270: B - Field - QC Reset confirm both TDMA half frame (Receipt F to P)....100
Table A.271: B - Field - QC MOD2 ACK (Sending P to F)....100
Table A.272: B - Field - QC MOD2 ACK (Receipt F to P)....100
Table A.273: B - Field - ES TARI message (Sending P to F)....101
Table A.274: B - Field - ES TARI message (Receipt F to P)....101
Table A.275: B - Field - GF-No $C_F$ data in the B-field (Sending P to F)....101
Table A.276: B - Field - GF-No $C_F$ data in the B-field (Receipt F to P)....101
Table A.277: B - Field - GF-One B-subfield contains $C_F$ data (Sending P to F)....102
Table A.278: B - Field - GF-One B-subfield contains $C_F$ data (Receipt F to P)....102
Table A.279: B - Field - GF-Two B-subfield contains $C_F$ data (Sending P to F)....102
Table A.280: B - Field - GF-Two B-subfield contains $C_F$ data (Receipt F to P)....102
Table A.281: B - Field - GF-Three B-subfield contains $C_F$ data (Sending P to F)....103
Table A.282: B - Field - GF-Three B-subfield contains $C_F$ data (Receipt F to P)....103
Table A.283: B - Field - GF-Four B-subfield contains $C_F$ data (Sending P to F)....103
Table A.284: B - Field - GF-Four B-subfield contains $C_F$ data (Receipt F to P)....103
Table A.285: B - Field - GF-Five B-subfield contains $C_F$ data (Sending P to F)....104
Table A.286: B - Field - GF-Five B-subfield contains $C_F$ data (Receipt F to P)....104
Table A.287: B - Field - GF-Six B-subfield contains $C_F$ data (Sending P to F)....104
Table A.288: B - Field - GF-Six B-subfield contains $C_F$ data (Receipt F to P)....104
Table A.289: B - Field - GF-Seven B-subfield contains $C_F$ data (Sending P to F)....105
Table A.290: B - Field - GF-Seven B-subfield contains $C_F$ data (Receipt F to P)....105
Table A.291: B - Field - GF-Eight B-subfield contains $C_F$ data (Sending P to F)....105
Table A.292: B - Field - GF-Eight B-subfield contains $C_F$ data (Receipt F to P)....105
Table A.293: B - Field - GF-Nine B-subfield contains $C_F$ data (Sending P to F)....106
Table A.294: B - Field - GF-Nine B-subfield contains $C_F$ data (Receipt F to P)....106
Table A.295: B - Field - GF-Nine B-subfield contains $C_F$ data (Sending P to F)....106
Table A.296: B - Field - GF-Nine B-subfield contains $C_F$ data (Receipt F to P)....106

Blank page

## Foreword

This European Telecommunication Standard (ETS) has been produced by the Radio Equipment and Systems (RES), Technical Committee of the European Telecommunications Standards Institute (ETSI).

The DECT Common interface Protocol Implementation Conformance Statement (PICS) proforma standard comprises seven parts as follows:

Part 1: "Network (NWK) layer - Portable radio Termination (PT)";

Part 2: "Data Link Control (DLC) layer - Portable radio Termination (PT)";

**Part 3: "Medium Access Control (MAC) layer - Portable radio Termination (PT)";**

Part 4: "Network (NWK) layer - Fixed radio Termination (FT)";

Part 5: "Data Link Control (DLC) layer - Fixed radio Termination (FT)";

Part 6: "Medium Access Control (MAC) layer - Fixed radio Termination (FT)";

Part 7: "Physical layer".

Annex A of this specification contains the PICS proforma for the PT medium access control layer.

| **Transposition dates** | |
|---|---|
| Date of adoption of this ETS: | 16 August 1996 |
| Date of latest announcement of this ETS (doa): | 30 November 1996 |
| Date of latest publication of new National Standard or endorsement of this ETS (dop/e): | 31 May 1997 |
| Date of withdrawal of any conflicting National Standard (dow): | 31 May 1997 |

Blank page

# 1 Scope

This European Telecommunication Standard (ETS) provides the Protocol Implementation Conformance Statement (PICS) proforma for the Digital Enhanced Cordless Telecommunications Medium Access Control layer at the Portable Termination as defined in ETS 300 175 Part 3 [3] in compliance with the relevant requirements and in accordance with the relevant guidance given in ISO/IEC 9646-7 [14].

# 2 Normative references

This ETS incorporates, by dated or undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this ETS only when incorporated in it by amendment or revision. For undated references the latest edition of the publication referred to applies.

[1] ETS 300 175-1: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 1: Overview".

[2] ETS 300 175-2: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 2: Physical Layer".

[3] ETS 300 175-3: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 3: Medium Access Control (MAC) layer".

[4] ETS 300 175-4: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 4: Data Link Control (DLC) layer".

[5] ETS 300 175-5: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 5: Network (NWK) layer".

[6] ETS 300 175-6: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 6: Identities and addressing".

[7] ETS 300 175-7: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 7: Security features".

[8] ETS 300 175-8: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 8: Speech coding and transmission".

[9] ETS 300 175-9: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 9: Public Access Profile (PAP)".

[10] ETS 300 406 (1995): "Methods for Testing and Specification (MTS); Protocol and profile conformance testing specifications; Standardization methodology".

[11] ISO/IEC 9646-1 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 1: General concepts".

[12] ISO/IEC 9646-7 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 7: Implementation Conformance Statements".

# 3 Definitions and abbreviations

## 3.1 Definitions

For the purposes of this ETS, the following terms and definitions apply:

- terms defined in ETS 300 175-1 [1]
- terms defined in ISO/IEC 9646-1 [11] and in ISO/IEC 9646-7 [12].

In particular, the following terms defined in ISO/IEC 9646-1 [11] apply:

**Implementation Conformance Statement (ICS):** A statement made by the supplier of an implementation or system claimed to conform to a given specification, stating which capabilities have been implemented. The ICS can take several forms: protocol ICS, profile ICS, profile specific ICS, information object ICS, etc.

**ICS proforma:** A document, in the form of a questionnaire, which when completed for an implementation or system becomes an ICS.

## 3.2 Abbreviations

For the purposes of this ETS, the abbreviations defined in ISO/IEC 9646-1 [11], the medium access control layer abbreviations defined in ETS 300 175-3 [3], and the following abbreviations apply.

| | |
|---|---|
| ICS | Implementation Conformance Statement |
| IUT | Implementation Under Test |
| PICS | Protocol Implementation Conformance Statement |
| SCS | System Conformance Statement |
| SUT | System Under Test |

# 4 Conformance requirement to this PICS proforma specification

The supplier of a protocol implementation which is claimed to conform to the portable termination specific requirements of ETS 300 175-3 [3] shall complete a copy of the PICS proforma provided in Annex A and shall provide the information necessary to identify both the supplier and the implementation.

An ICS which conforms to this ETS shall be a conforming PICS proforma completed in accordance with the guidances for completion given in clause A.1.

# Annex A (normative): PICS proforma for DECT MAC PT

Notwithstanding the provisions of the copyright clause related to the text of the present ETS (see front page), ETSI grants users of this ETS to freely reproduce the PICS Proforma in this annex so that it can be used for its intended purposes and may further publish the completed PICS.

## A.1 Introduction for completing the PICS proforma

### A.1.1 Purposes and structure

The purpose of this PICS is to provide a mechanism whereby a supplier of an implementation of the portable termination specific medium access control layer requirements of ETS 300 175-3 [3]: DECT Medium Access Control Layer may provide information in a standard form.

The PICS proforma is subdivided into subclauses for the following categories of information:

- guidances for completing the PICS proforma;
- identification of the implementation;
- identification of the protocol;
- services, procedures and functions;
- timers and protocol parameters;
- messages;

### A.1.2 Symbols, abbreviations and conventions

The PICS proforma contained in this annex is comprised of information in tabular form in accordance with the guidelines presented in ISO/IEC 9646-7 [12].

**Item column**

The item column contains a number which identifies the item in the table.

**Item description column**

The item description column describes in free text each respective item (e.g. parameters, timers, etc.). It implicitly means "is <item description> supported by the implementation?".

**Status column**

The following notations, defined in ISO/IEC 9646-7 [12], are used for the status column:

| | |
|---|---|
| m | mandatory - the capability is required to be supported. |
| o | optional - the capability may be supported or not (e.g. the capability is not allowed because the underlying DECT layers (service provider) cannot handle it or the requirement belongs to an application i.e. does not belong to the data link control layer) |
| n/a | not applicable - in the given context, it is impossible to use the capability. |
| x | prohibited (excluded) - there is a requirement not to use this capability in the given context. |
| o.i | qualified optional - for mutually exclusive or selectable options from a set. "i" is an integer which identifies an unique group of related optional items and the logic of their selection which is defined immediately following the table. |
| ci | conditional - the requirement on the capability ("m", "o", "x" or "n/a") depends on the support of other optional or conditional items. "i" is an integer identifying an unique conditional status expression which is defined immediately following the table. |

**Reference column**

The reference column gives reference to ETS 300 175-3 [3], except where explicitly stated otherwise.

**Support column**

The support column shall be filled in by the supplier of the implementation. The following common notations, defined in ISO/IEC 9646-7 [12], are used for the support column:

| | |
|---|---|
| Y or y | supported by the implementation |
| N or n | not supported by the implementation |
| N/A, n/a or - | no answer required (allowed only if the status is n/a, directly or after evaluation of a conditional status) |

In each context, the kind of "non-support" which is implemented at the receipt may be additionally indicated such as:

- Err the item is treated as a protocol error;
- lg the item is received and ignored (i.e. processed syntactically, but not semantically);
- rj the item is received and rejected.

NOTE: As stated in ISO/IEC 9646-7 [12], support for a received PDU requires the ability to parse all valid parameters of that PDU. Supporting a PDU while having no ability to parse a valid parameter is non-conformant. Support for a parameter on a PDU means that the semantics of that parameter are supported.

**Values allowed column**

The values allowed column contains the values or the ranges of values allowed. The range of value is defined as follows: [min value] .. [max value]. Alternative values are defined as follows:

[value1], [value 2], ..., [value n].

**EXAMPLE:** '00110000'B .. '01001011'B is the value range
from '00110000'B to '01001011'B

'00110000'B, '01001011'B the value can be '00110000'B or '01001011'B.

**Values supported column**

The values supported column shall be filled in by the supplier of the implementation. In this column, the values or the ranges of values supported by the implementation shall be indicated.

**Prerequisite line**

A prerequisite line takes the form: Prerequisite: <predicate>.

A prerequisite line before a table title indicates that the whole table is not required to be completed if the predicate is FALSE.

### A.1.3 Guidances for completing the PICS

The supplier of the implementation shall enter an explicit statement in each of the tables provided using the notation described in subclause A.1.2. If necessary, specific instruction is provided in the text which precedes each table.

## A.2 Identification of the implementation

### A.2.1 Date of statement

Identification of the Implementation Under Test (IUT) and the system in which it resides (the System Under Test (SUT)) should be filled in so as to provide as much detail as possible regarding version numbers and configuration options.

**Table A.1: Date of statement**

| Date of statement | | |
|---|---|---|
| **Day** | **Month** | **Year** |
| | | |

### A.2.2 Implementation Under Test (IUT) identification

The supplier of the implementation shall enter information necessary to uniquely identify the IUT in the table below.

**Table A.2: IUT identification**

| IUT identification | |
|---|---|
| IUT name | |
| IUT version | |

### A.2.3 System Under Test (SUT) identification

The supplier of the implementation shall enter information necessary to uniquely identify the SUT in the table below.

**Table A.3: SUT identification**

| IUT identification | |
|---|---|
| | |
| SUT name | International Portable Equipment Identity (IPEI): |
| Hardware configuration | |

### A.2.4 Product supplier

**Table A.4 : Product supplier**

| Product supplier | |
|---|---|
| Name | |
| Address | |
| Phone No. | |
| Fax No. | |
| E-mail address | |
| Additional information | |

### A.2.5 Client identification

The product supplier information and client information should both be filled in if they are different.

**Table A.5: Client identification**

| Client | |
|---|---|
| Name | |
| Address | |
| Phone No. | |
| Fax No. | |
| E-mail address | |
| Additional information | |

### A.2.6 Contact person

A person who can answer queries regarding information supplied in the PICS should be named as the contact person.

**Table A.6 : Contact person identification**

| Contact person | |
|---|---|
| Name | |
| Address | |
| Phone No. | |
| Fax No. | |

## A.3 Identification of the protocol

**Table A.7: Identification of protocol**

| Identification of protocol | |
|---|---|
| Title of specification | Radio Equipment and Systems Digital Enhanced Cordless Telecommunications Common Interface Part 3: Medium Access Control Layer |
| Reference no. | ETS 300 175-3 |
| Date of Publication | |

## A.4 Global statement of conformance

The supplier of the implementation shall state whether of not all mandatory capabilities are implemented for ETS 300 175-3 [3]: Medium Access Control Layer.

**Table A.8: Global statement of conformance**

| | |
|---|---|
| Are all mandatory capabilities implemented? | |

NOTE: Answering "No" to this question indicates non-conformance to the protocol specification. Non-supported mandatory capabilities are to be identified in the PICS, with an explanation of why the implementation is non-conforming.

## A.5 Capabilities

### A.5.1 Services

The supplier of the implementation shall state the support of the implementation for each of the following services, in the table below.

**Table A.9: Service groups supported**

| Item | Name of service | Ref. | Status | Support |
|---|---|---|---|---|
| 1 | Connection oriented control | 5.6 | o.901 | |
| 2 | Broadcast control | 5.7.1 | o.901 | |
| 3 | Connectionless control | 5.7.2 | o.901 | |
| 4 | Multipexing | 6 | m | |
| 5 | Management | 11 | m | |

o.901: It is mandatory to support at least one of this options

#### A.5.1.1 Connection oriented control services

**Table A.10: Connection oriented control services**

| Prerequisite: A.9/1 | | | | |
|---|---|---|---|---|
| **Item** | **Connection oriented control services** | **Ref.** | **Status** | **Supp.** |
| 1 | Basic connections | 5.6.1.1 | o.1001 | |
| 2 | Advanced symmetric connections | 5.6.2.1 | o.1001 | |
| 3 | Advanced asymmetric connections | 5.6.2.2 | o.1001 | |

o.1001: It is mandatory to support at least one of this options

**Table A.11: Connection services**

| Prerequisite: A.10/1 OR A.10/2 OR A.10/3 | | | | |
|---|---|---|---|---|
| **Item** | **Connection services** | **Ref.** | **Status** | **Support** |
| 1 | Connection setup | 10.2 | m | |
| 2 | Connection modification | 10.3 | c1101 | |
| 3 | Connection data transfer | 10.8 | m | |
| 4 | Connection release | 10.4 | m | |

c1101: IF A.9/2 OR A.9/3 THEN o ELSE n/a

**Table A.12: Symmetric connection oriented services**

| Prerequisite: A.10/2 | | | | |
|---|---|---|---|---|
| **Item** | **Symmetric connection oriented services** | **Ref.** | **Status** | **Support** |
| 1 | Type 1 IN_minimum_delay | 5.6.2.1 | o.1201 | |
| 2 | Type 2 IN_normal_delay | 5.6.2.1 | o.1201 | |
| 3 | Type 3 IP_error_detection | 5.6.2.1 | o.1201 | |
| 4 | Type 4 IP_error_correction | 5.6.2.1 | o.1201 | |

o.1201: It is mandatory to support at least one of this options

**Table A.13: Asymmetric connection oriented services**

| Prerequisite: A.10/3 | | | | |
|---|---|---|---|---|
| **Item** | **Asymmetric connection oriented services** | **Ref.** | **Status** | **Support** |
| 1 | Type 5 IN_normal_delay | 5.6.2.2 | o.1301 | |
| 2 | Type 6 IP_error_detection | 5.6.2.2 | o.1301 | |
| 3 | Type 7 IP_error_correction | 5.6.2.2 | o.1301 | |

o.1301: It is mandatory to support at least one of this options

**Table A.14: C-plane connection services**

| Prerequisite: A.10/1 OR A.10/2 OR A.10/3 | | | | |
|---|---|---|---|---|
| **Item** | **C-plane connection services** | **Ref.** | **Status** | **Support** |
| 1 | Only $C_S$ channel supported | 10.8.1 | o.1401 | |
| 2 | $C_S$ and $C_F$ channels supported | 10.8.1 | o.1401 | |
| 3 | Only $C_F$ channel supported | 10.8.1 | o.1401 | |

o.1401: It is mandatory to support at least one of this options

### A.5.1.2 Broadcast control services

**Table A.15: Broadcast services**

| Prerequisite: A.9/2 | | | | |
|---|---|---|---|---|
| **Item** | **Broadcast services** | **Ref.** | **Status** | **Support** |
| 1 | Continuous broadcast | 5.7.1.1 | m | |
| 2 | Non-continuous broadcast | 5.7.1.2 | o | |
| 3 | Paging broadcast | 9.1.3 | o | |

### A.5.1.3 Connectionless control services

**Table A.16: Connectionless control services**

| Prerequisite: A.9/2 | | | | |
|---|---|---|---|---|
| **Item** | **Broadcast services** | **Ref.** | **Status** | **Support** |
| 1 | Downlink connectionless | 5.7.2.1 | o | |
| 2 | Uplink connectionless | 5.7.2.2 | o | |

#### A.5.1.3.1 Downlink connectionless services

**Table A.17: Downlink connectionles services**

| Prerequisite: A.16/1 | | | | |
|---|---|---|---|---|
| **Item** | **Downlink connectionless services** | **Ref.** | **Status** | **Support** |
| 1 | CLS channel only, short simplex bearer | 5.7.2.1 | o.1701 | |
| 2 | CLS and CLF channels, long simplex bearer | 5.7.2.1 | o.1701 | |
| 3 | CLS and SIN channels, long simplex bearer | 5.7.2.1 | o.1701 | |

o.1701: It is mandatory to support at least one of this options

#### A.5.1.3.2 Uplink connectionless services

**Table A.18: Uplink connectionles services**

| Prerequisite: A.16/2 | | | | |
|---|---|---|---|---|
| **Item** | **Uplink connectionless services** | **Ref.** | **Status** | **Support** |
| 1 | CLS channel only, short simplex bearer | 5.7.2.2 | o.1801 | |
| 2 | CLS channel only, long simplex bearer | 5.7.2.2 | o.1801 | |
| 3 | CLF channel only, long simplex bearer | 5.7.2.2 | o.1801 | |
| 4 | No SDU, PMID only, short simplex bearer | 5.7.2.2 | o.1801 | |
| 5 | No SDU, PMID only, long simplex bearer | 5.7.2.2 | o.1801 | |

o.1801: It is mandatory to support at least one of this options

### A.5.1.4 Multiplexing services

**Table A.19: CSF multiplexing services**

| Prerequisite: A.9/4 | | | | |
|---|---|---|---|---|
| **Item** | **CSF multiplexing services** | **Ref.** | **Status** | **Support** |
| 1 | D-MAP | 6.2.1.1 | m | |
| 2 | A-MAP | 6.2.1.2 | m | |
| 3 | B-MAP | 6.2.1.3 | o | |
| 4 | T-MUX | 6.2.2.1 | m | |
| 5 | E/U-MUX | 6.2.2.2 | o | |
| 6 | C-MUX | 6.2.2.3 | o | |
| 7 | Encryption activation | 6.2.3 | o | |
| 8 | Encryption deactivation | 6.2.3 | o | |
| 9 | Scrambling | 6.2.4 | m | |
| 10 | Error control R-CRC | 6.2.5.1 | o | |
| 11 | Error control X-CRC | 6.2.5.3 | o | |
| 12 | Broadcast control | 6.2.6 | m | |

**Table A.20: D-MAP services**

| Prerequisite: A.19/1 | | | | |
|---|---|---|---|---|
| **Item** | **D-MAP** | **Ref.** | **Status** | **Support** |
| 1 | D-field MAP D80 | 6.2.1.1 | o.2001 | |
| 2 | D-field MAP D32 | 6.2.1.1 | o.2001 | |
| 3 | D-field MAP D08 | 6.2.1.1 | o.2001 | |
| 4 | D-field MAP D00 | 6.2.1.1 | o.2001 | |

o.2001: It is mandatory to support at least one of this options

**Table A.21: B-MAP services**

| Prerequisite: A.19/3 | | | | |
|---|---|---|---|---|
| **Item** | **B-MAP** | **Ref.** | **Status** | **Support** |
| 1 | B-field MAP unprotected format | 6.2.1.3 | o.2101 | |
| 2 | B-field MAP protected format | 6.2.1.3 | o.2101 | |

o.2101: It is mandatory to support at least one of this options

**Table A.22: E/U mux services**

| Prerequisite: A.19/5 | | | | |
|---|---|---|---|---|
| **Item** | **E/U MUX** | **Ref.** | **Status** | **Support** |
| 1 | E/U-mux E type | 6.2.2.2 | o.2201 | |
| 2 | E/U-mux U type | 6.2.2.2 | o.2201 | |

o.2201: It is mandatory to support at least one of this options

**Table A.23: C mux mapping services**

| Prerequisite: A.19/6 | | | | |
|---|---|---|---|---|
| **Item** | **Time multiplexers - C mux** | **Ref.** | **Status** | **Support** |
| 1 | C-mux double slot | 6.2.2.3.1 | o.2301 | |
| 2 | C-mux full slot | 6.2.2.3.1 | o.2301 | |
| 3 | C-mux half slot | 6.2.2.3.2 | o.2301 | |

o.2301: It is mandatory to support at least one of this options

### A.5.1.5 Management services

**Table A.24: Management services**

| Prerequisite: A.9/5 | | | | |
|---|---|---|---|---|
| **Item** | **Management services** | **Ref.** | **Status** | **Support** |
| 1 | Broadcasting | 11.1 | c2401 | |
| 2 | Extended system information | 11.2 | o | |
| 3 | PP states and state transition | 11.3 | m | |
| 4 | Phisical channel selection | 11.4 | m | |
| 5 | In-connection quality control | 11.5 | m | |
| 6 | RFP system load | 11.6 | m | |
| 7 | Receiver scan sequence | 11.9 | m | |
| 8 | Test messages | 12 | o | |
| 9 | SARI support | 7.2.3.6.2 | o | |
| 10 | TARI support | 7.2.5.10 | o | |

c2401: IF A.15/1 THEN m ELSE n/a

**Table A.25: Handover services management**

| **Item** | **Name of service** | **Ref.** | **Status** | **Supp.** |
|---|---|---|---|---|
| 1 | Connection handover | 10.2.4.1 | c2501 | |
| 2 | Bearer handover | 10.6 | o | |

c2501: IF A.9/1 THEN o ELSE n/a

### A.5.2 Procedures

The supplier of the implementation shall state the support of the implementation for each of the following procedures, in the tables below.

### A.5.2.1 Connection procedures

#### A.5.2.1.1 Connection setup procedures

**Table A.26: C/O single bearer setup procedures**

| Prerequisite: A.10/1 AND A.11/1 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Basic setup, single bearer basic connection of known service | 10.2.4.2 | o.2601 | |
| 2 | Normal setup, single bearer duplex connection known service | 10.2.4.2 | o.2601 | |
| 3 | Fast setup, single bearer duplex connection known service | 10.2.4.2 | o.2601 | |

o.2601: It is mandatory to support at least one of this options

**Table A.27: C/O multi-bearer symmetric setup procedures**

| Prerequisite: A.10/2 AND A.11/1 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Normal setup, multi-bearer symmetric connection | 10.2.4.3.1 | o.2701 | |
| 2 | Fast setup, multi-bearer symmetric connection | 10.2.4.3.1 | o.2701 | |

o.2701: It is mandatory to support at least one of this options

**Table A.28: C/O multi-bearer asymmetric setup procedures**

| Prerequisite: A.10/3 AND A.11/1 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Normal setup, multi-bearer fully asymmetric UL connection | 10.2.4.3.2 | o.2801 | |
| 2 | Fast setup, multi-bearer fully asymmetric UL connection | 10.2.4.3.2 | o.2801 | |
| 3 | Normal setup, multi-bearer fully asymmetric DL connection | 10.2.4.3.3 | o.2801 | |
| 4 | Fast setup, multi-bearer fully asymmetric DL connection | 10.2.4.3.3 | o.2801 | |

o.2801: It is mandatory to support at least one of this options

**Table A.29: C/O bearer setup procedures**

| Prerequisite: A.11/1 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Basic bearer setup | 10.5.1.1 | c2901 | |
| 2 | PT initiated - A-field advanced single bearer setup | 10.5.1.2.1 | c2902 | |
| 3 | PT initiated - B-field single bearer setup | 10.5.1.3.1 | c2902 | |
| 4 | FT initiated - A-field advanced single bearer setup | 10.5.1.2.2 | c2903 | |
| 5 | FT iniated - B-field single bearer setup | 10.5.1.3.2 | c2904 | |
| 6 | Double simplex bearer setup, indirect | 10.5.1.4 | c2905 | |
| 7 | Double simplex bearer setup, direct | 10.5.1.4 | c2905 | |
| 8 | Channel list | 10.5.2 | c2906 | |

c2901: IF A.26/1 THEN m ELSE n/a
c2902: IF A.26/2 OR A.27/1 OR A.28/1 OR A.28/3 THEN o.2901 ELSE n/a
c2903: IF A.28/4 THEN o for additionnal duplex bearers ELSE n/a
c2904: IF A.26/3 OR A.27/2 OR A.28/2 OR A.28/4 THEN m ELSE n/a
c2905: IF A.27/1 OR A.27/2 OR A.28/1 OR A.28/2 OR A.28/3 OR A.28/4 THEN o.2901 ELSE n/a
c2906: IF A.29/6 OR A.29/7 THEN m ELSE o
o.2901: It is mandatory to support at least one of this options

#### A.5.2.1.2 Connection modification procedures

**Table A.30: C/O connection modification procedures**

| Prerequisite: A.11/2 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Connection modification | 10.3 | m | |

#### A.5.2.1.3 Connection data transfer procedures

**Table A.31: C/O data transfer procedures**

| Prerequisite: A.11/3 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | ARQ procedure, Q1 and Q2 bit setting, for C-channel | 10.8.1 | m | |
| 2 | Cs - channel data | 10.8.1.1 | o | |
| 3 | Q1/Q2 setting for sliding collision / A-,B-field check (FT to PT) | 10.8.1.3 | m | |
| 4 | Antenna diversity (React on Q1 bit in direction PT to FT) | 10.8.1.3 | o | |
| 5 | Q2 bit settings | 10.8.1.3.1 | o | |
| 6 | Q1 bit settings | 10.8.1.3.2 | o | |
| 7 | BCK/Q2 bit setting for IP channel flow control, duplex bearer | 10.8.2.4 | o | |
| 8 | ACK/BCK bit setting for IP flow control, double simplex | 10.8.2.4 | o | |
| 9 | Bearer replacement | 10.8.2.5.1 | o | |
| 10 | Unilateral jump | 10.8.2.5.2 | o | |
| 11 | IP bearer reset | 10.8.2.5.3 | o | |

#### A.5.2.1.4 Handover procedures

**Table A.32: Handover procedures**

| Prerequisite: A.25 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Connection handover | 10.2.4.1 | c3201 | |
| 2 | Duplex bearer handover | 10.6.2 | c3202 | |
| 3 | Double simplex bearer handover | 10.6.3 | c3203 | |

c3201: IF A.25/1 THEN m ELSE n/a

c3202: IF A.25/2 AND A.29/1 THEN m ELSE n/a
c3203: IF A.25/2 AND (A.29/6 OR A.29/7) THEN m ELSE n/a

#### A.5.2.1.5 Connection release procedures

**Table A.33: C/O connection release procedures**

| Prerequisite: A.11/5 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Unacknowledge bearer release | 10.7.2.1 | m | |
| 2 | Acknowledge bearer release | 10.7.2.2 | o.3301 | |
| 3 | Fast bearer release | 10.7.2.3 | c3301 | |

c3301: IF A.11/5 THEN m ELSE n/a
o.3301: IF A.29/6 OR A.29/7 THEN m ELSE n/a

### A.5.2.2 Broadcast procedures

**Table A.34: Broadcast procedures**

| Prerequisite: A.15/3 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Normal paging | 9.1.3 | o.3401 | |
| 2 | Fast paging | 9.1.3 | o.3401 | |
| 3 | Downlink broadcast | 9.1.1.3 | m | |

o.3401: It is mandatory to support at least one of this options

### A.5.2.3 Connectionless procedures

#### A.5.2.3.1 Downlink connectionless procedures

**Table A.35: Downlink connectionless procedures**

| Prerequisite: A.16/1 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Downlink C/L | 9.1.2 | m | |

#### A.5.2.3.2 Uplink connectionless procedures

**Table A.36: Uplink connectionless procedures**

| Prerequisite: A.16/2 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Uplink C/L bearer selection | 9.2.2 | o | |
| 2 | Uplink C/L | 9.2.3 | o | |
| 3 | Request for specific Q-channel information, A-field procedure | 9.3.1 | c3601 | |
| 4 | Request for specific Q-channel information, B-field procedure | 9.3.1 | c3601 | |
| 5 | Request for new dummy bearer | 9.3.2 | o | |

c3601: IF A.24/2 THEN o.3601 ELSE n/a
o.3601: It is mandatory to support at least one of this options

### A.5.2.4 CSF multiplexing procedures

**Table A.37: CSF multiplexing procedures**

| Prerequisite: A.9/4 | | | | |
|---|---|---|---|---|
| **Item** | **CSF multiplexing procedures** | **Ref.** | **Status** | **Support** |
| 1 | Encryption | 6.2.3 | o | |
| 2 | Scrambling | 6.2.4 | m | |
| 3 | R-CRC generation | 6.2.5.2 | o | |
| 4 | R-CRC checking | 6.2.5.2 | o | |
| 5 | X-CRC generation | 6.2.5.4 | o | |
| 6 | X-CRC checking | 6.2.5.4 | o | |
| 7 | Broadcast control function | 6.2.6 | m | |

### A.5.2.5 Layer management procedures

**Table A.38: Layer management procedures**

| Prerequisite: A.9/5 | | | | |
|---|---|---|---|---|
| **Item** | **Name of procedure** | **Ref.** | **Status** | **Supp.** |
| 1 | Extented system information PP request | 11.2.1 | o | |
| 2 | Duplex bearer physical channel selection | 11.4.1 | m | |
| 3 | Double simplex bearer physical channel selection | 11.4.1 | o | |
| 4 | Simplex bearer physical channel selection | 11.4.1 | m | |
| 5 | RFPI handshake | 11.5.1 | m | |
| 6 | RFP measurement of frequency error | 11.5.2.1 | o | |
| 7 | RFP idle receiver scan sequence | 11.8 | o | |
| 8 | Test message procedures | 12 | o | |

### A.5.3 Other capabilities

The supplier of the implementation shall state whether or not extended RF carriers are supported.

**Table A.39: Extended RF carriers supported**

| **Item** | **Extended RF Carriers** | **Ref.** | **Status** | **Support** |
|---|---|---|---|---|
| 1 | Extended RF carriers | 7.2.3 | o | |

The supplier of the implementation shall state which modes of operation are supported by the PT in the Idle_locked state.

**Table A.40: Operation modes in Idle_locked state supported**

| **Item** | **Operation mode** | **Ref.** | **Status** | **Support** |
|---|---|---|---|---|
| 1 | Scanning mode | 4.3.1, 11.3 | m | |
| 2 | High duty cylce Idle_locked mode | 4.3.1, 11.3 | o.4001 | |
| 3 | Normal cylce Idle_locked mode | 4.3.1, 11.3 | o.4001 | |
| 4 | Low cylce Idle_locked mode | 4.3.1, 11.3 | o.4001 | |

o.4001: It is mandatory to support at least one of this options

## A.6 Protocol parameters

### A.6.1 Timer support

The supplier of the implementation shall provide information about the timers specified in the ETS 300 175-3 [3]: Medium Access Control Layer.

**Table A.41: Timer supported**

| Item | Name of timer | Ref. | Status | Support | Value Allowed | Value Supported |
|---|---|---|---|---|---|---|
| 1 | T200 | A.1 | o | | 3 seconds | |
| 2 | T201 | A.1 | o | | 5 seconds | |
| 3 | T202 | A.1 | o | | 3 seconds | |
| 4 | T203 | A.1 | o | | 16 frames | |
| 5 | T204 | A.1 | x | | 6 multi-frames | |
| 6 | T205 | A.1 | x | | 10 seconds | |
| 7 | T206 | A.1 | x | | 10 frames | |
| 8 | T207 | A.1 | o | | 5 seconds | |
| 9 | T208 | A.1 | o | | 20 seconds | |
| 10 | T209 | A.1 | o | | 30 seconds | |
| 11 | T210 | A.1 | o | | 2 seconds | |
| 12 | T211 | A.1 | c4101 | | 3 seconds | |
| 13 | T212 | A.1 | c4102 | | 20 frames | |
| 14 | T213 | A.1 | c4103 | | 20 frames | |
| 15 | T214 | A.1 | c4104 | | 20 frames | |
| 16 | T215 | A.1 | c4104 | | 6 multi-frames | |

c4101: IF A.26/10 THEN m ELSE x
c4102: IF A.29/3 OR A.29/4 THEN m ELSE x
c4103: IF A.29/9 THEN m ELSE x
c4104: IF A.18/1..5 THEN m ELSE x

### A.6.2 Protocol constants

The supplier of the implementation shall provide information about the protocol constants specified in the ETS 300 175-3 [3]: Medium Access Control Layer.

**Table A.42: Protocol constants support**

| Item | Protocol Constants | Ref. | Status | Support | Value Allowed | Value Supported |
|---|---|---|---|---|---|---|
| 1 | N200 | A.2 | o | | 10 | |
| 2 | N201 | A.2 | o | | 15 | |
| 3 | N202 | A.2 | o | | 10 | |
| 4 | N203 | A.2 | c4201 | | 6 | |

c4201: IF A.18/1..5.THEN m ELSE x

### A.6.3 Channel selection parameters

The supplier of the implementation shall state whether or not the following parameters specified by ETS 300 175-3 [3]: Medium Access Control Layer are supported and their type, value(s) and range(s), in the table below.

**Table A.43: Channel selection parameters**

| Item | Parameter | Ref. | Status | Supp. | Value Allowed | Value Supported |
|---|---|---|---|---|---|---|
| 1 | Lowest boundary of channel list | 11.4.1 | m | | <= -93 dBm | |
| 2 | Band resolution | 11.4.1 | m | | <= 6 dB | |
| 3 | RSSI variation between checking | 11.4.2 | m | | <= 12 dB | |

### A.6.4 Channels supported

**Table A.44: Channels supported**

| Item | Channels supported | Ref. | Status | Support |
|---|---|---|---|---|
| 1 | $B_S$ channel | 5.3.3.1 | o | |
| 2 | $C_S$ channel | 5.3.1.1 | o | |
| 3 | $C_F$ channel | 5.3.1.1 | o | |
| 4 | $G_F$ channel | 5.3.1.3 | o | |
| 5 | $SI_N$ channel | 5.3.2.2 | o | |
| 6 | $CL_S$ channel | 5.3.2.1 | o | |
| 7 | $CL_F$ channel | 5.3.2.1 | o | |
| 8 | $I_N$ channel | 5.3.1.2 | o | |
| 9 | $I_P$ channel | 5.3.1.2 | o | |

### A.6.5 Bearer types supported

**Table A.45: Bearer types supported**

| Item | Bearer types supported | Ref. | Status | Support |
|---|---|---|---|---|
| 1 | Short simplex | 5.5.1 | o.4501 | |
| 2 | Long simplex | 5.5.1 | o.4501 | |
| 3 | Duplex | 5.5.1 | o.4501 | |
| 4 | Double simplex | 5.5.1 | o.4501 | |

o.4501: It is mandatory to support at least one of this options

### A.6.6 Slot types supported

**Table A.46: Slot types supported**

| Item | Slot types supported | Ref. | Status | Support |
|---|---|---|---|---|
| 1 | Short slot | 6.2.1 | o.4601 | |
| 2 | Half slot | 6.2.1 | o.4601 | |
| 3 | Full slot | 6.2.1 | o.4601 | |
| 4 | Double slot | 6.2.1 | o.4601 | |

o.4601: It is mandatory to support at least one of this options

## A.7 Messages

The supplier of the implementation shall state whether or not the messages specified by ETS 300 175-3 [3]: Medium Access Control Layer are supported, in the tables below. The supplier shall indicate the status of support for sending and receiving each message.

### A.7.1 A - field header

#### A.7.1.1 A - field header - Tail Identification

**Table A.47: Tail Identification (Sending P to F)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **Tail Identification** | **Ref.** | **Status** | **Support** |
| 1 | CT data packet number 0 | 7.1.2 | m | |
| 2 | CT data packet number 1 | 7.1.2 | m | |
| 3 | Identities information on C/L bearer | 7.1.2 | x | |
| 4 | Identities information | 7.1.2 | m | |
| 5 | Multiframe syncronisation - system info. | 7.1.2 | x | |
| 6 | Escape | 7.1.2 | o | |
| 7 | MAC layer control | 7.1.2 | m | |
| 8 | Paging tail | 7.1.2 | x | |
| 9 | First PP transmission | 7.1.2 | m | |

**Table A.48: Tail Identification (Receipt F to P)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **Tail Identification** | **Ref.** | **Status** | **Support** |
| 1 | CT data packet number 0 | 7.1.2 | m | |
| 2 | CT data packet number 1 | 7.1.2 | m | |
| 3 | Identities information on C/L bearer | 7.1.2 | o | |
| 4 | Identities information | 7.1.2 | m | |
| 5 | Multiframe syncronisation - system info. | 7.1.2 | m | |
| 6 | Escape | 7.1.2 | o | |
| 7 | MAC layer control | 7.1.2 | m | |
| 8 | Paging tail | 7.1.2 | o | |
| 9 | First PP transmission | 7.1.2 | x | |

#### A.7.1.2 A - field header - “Q1/BCK” bit

**Table A.49: “Q1/BCK” bit (Sending P to F)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **“Q1/BCK” bit** | **Ref.** | **Status** | **Support** |
| 1 | BCK IP flow control (sliding collision) | 7.1.3 | m | |
| 2 | Q1 bearer quality control | 7.1.3 | x | |

**Table A.50: “Q1/BCK” bit (Receipt F to P)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **“Q1/BCK” bit** | **Ref.** | **Status** | **Support** |
| 1 | BCK IP flow control (sliding collision) | 7.1.3 | m | |
| 2 | Q1 bearer quality control | 7.1.3 | m | |

### A.7.1.3 A - field header - B-field identification

**Table A.51: B-field identification (Sending P to F)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **B-field identification** | **Ref.** | **Status** | **Support** |
| 1 | U-type, IN, SIN or IP packet number 0 | 7.1.4 | c5101 | |
| 2 | U-type, IP error detect or IP packet number 1 | 7.1.4 | c5101 | |
| 3 | E-type, all CF or CLF, packet number 0 | 7.1.4 | c5102 | |
| 4 | E-type, all CF, packet number 1 | 7.1.4 | c5102 | |
| 5 | E-type, not all CF or CLF; packet number 0 | 7.1.4 | c5102 | |
| 6 | E-type, not all CF; CF packet number 1 | 7.1.4 | c5102 | |
| 7 | E-type, all MAC control (unnumbered) | 7.1.4 | c5102 | |
| 8 | No B-field | 7.1.4 | o | |

c5101: IF 22/2 THEN o ELSE n/a
c5102: IF 22/1 THEN o ELSE n/a

**Table A.52: B-field identification (Receipt F to P)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **B-field identification** | **Ref.** | **Status** | **Support** |
| 1 | U-type, IN, SIN or IP packet number 0 | 7.1.4 | c5201 | |
| 2 | U-type, IP error detect or IP packet number 1 | 7.1.4 | c5201 | |
| 3 | E-type, all CF or CLF, packet number 0 | 7.1.4 | c5202 | |
| 4 | E-type, all CF, packet number 1 | 7.1.4 | c5202 | |
| 5 | E-type, not all CF or CLF; packet number 0 | 7.1.4 | c5202 | |
| 6 | E-type, not all CF; CF packet number 1 | 7.1.4 | c5202 | |
| 7 | E-type, all MAC control (unnumbered) | 7.1.4 | c5202 | |
| 8 | No B-field | 7.1.4 | m | |

c5201: IF 22/2 THEN o ELSE n/a
c5202: IF 22/1 THEN o ELSE n/a

### A.7.1.4 A - field header - “Q2” bit

**Table A.53: “Q2” bit (Sending P to F)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **“Q2” bit** | **Ref.** | **Status** | **Support** |
| 1 | Q2 bearer quality & flow control | 7.1.5 | m | |

**Table A.54: “Q2” bit (Receipt F to P)**

| Prerequisite: A.19/2 | | | | |
|---|---|---|---|---|
| **Item** | **“Q2” bit** | **Ref.** | **Status** | **Support** |
| 1 | Q2 bearer quality & flow control | 7.1.5 | m | |

### A.7.2 A - field identities information ($N_T$) message

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.55: Identities information ($N_T$) message (Sending P to F)**

| Prerequisite: A.24/1 | | | | |
|---|---|---|---|---|
| **Item** | **System information message** | **Ref.** | **Status** | **Support** |
| 1 | NT - Identities Information | 7.2.2 | m | |

**Table A.56: Identities information ($N_T$) message (Receipt F to P)**

| Prerequisite: A.24/1 | | | | |
|---|---|---|---|---|
| **Item** | **System information message** | **Ref.** | **Status** | **Support** |
| 1 | NT - Identities Information | 7.2.2 | m | |

### A.7.3 A - field system information ($Q_T$) messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.57: System information ($Q_T$) message (Receipt F to P)**

| Prerequisite: A.24/1 | | | | |
|---|---|---|---|---|
| **Item** | **System information message** | **Ref.** | **Status** | **Support** |
| 1 | QT - Static system information | 7.2.3.2 | m | |
| 2 | QT - Extended RF carrier information | 7.2.3.3 | c5701 | |
| 3 | QT - Fixed part capabilities | 7.2.3.4 | m | |
| 4 | QT - Extended fixed part capabilities | 7.2.3.5 | o | |
| 5 | QT - Secondary access rights identities | 7.2.3.6 | o | |
| 6 | QT - Multi-frame number | 7.2.3.7 | c5702 | |
| 7 | QT - escape | 7.2.3.8 | o | |

c5701: IF A.39/1 THEN m ELSE o
c5702: IF A.37/1 THEN m ELSE o

### A.7.4 A - field paging tail ($P_T$) messages

#### A.7.4.1 Paging tail messages supported

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.58: Paging tail ($P_T$) messages (Receipt F to P)**

| Prerequisite: 15/3 | | | | |
|---|---|---|---|---|
| **Item** | **Paging tail messages** | **Ref.** | **Status** | **Support** |
| 1 | Full page format | 7.2.4.1 | o.5801 | |
| 2 | Long page format | 7.2.4.1 | o.5801 | |
| 3 | Short page format | 7.2.4.1 | o.5801 | |
| 4 | Zero length page format | 7.2.4.1 | o.5801 | |

o.5801: It is mandatory to support at least one of this options

#### A.7.4.2 $P_T$ messages information type

The support of a $P_T$ message information element in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.59: $P_T$ messages information supported (Receipt F to P)**

| Prerequisite: A.58/3 OR A.58//4 | | | | |
|---|---|---|---|---|
| **Item** | **$P_T$ messages information type** | **Ref.** | **Status** | **Support** |
| 1 | 0000 - fill bits | 7.2.4.3.2 | o | |
| 2 | 0001 - blind full slot | 7.2.4.3.3 | o | |
| 3 | 0010 - other bearer | 7.2.4.3.4 | o | |
| 4 | 0011 - recommended other bearer | 7.2.4.3.4 | o | |
| 5 | 0100 - good RFP bearer | 7.2.4.3.4 | o | |
| 6 | 0101 - dummy or C/L bearer position | 7.2.4.3.4 | o | |
| 7 | 0110 - RFP identity | 7.2.4.3.5 | o | |
| 8 | 0111 - escape | 7.2.4.3.6 | o | |
| 9 | 1000 - dummy or C/L bearer marker | 7.2.4.3.7 | c5901 | |
| 10 | 1001 - bearer handover information | 7.2.4.3.8 | o | |
| 11 | 1010 - RFP status | 7.2.4.3.9 | o | |

c5901: Only on dummy or connectionless downlink bearer

### A.7.5 A - field MAC control ($M_T$) messages

#### A.7.5.1 Mac control messages supported

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.60: MAC control ($M_T$) messages (Sending P to F)**

| Prerequisite: A.9/1 OR A.9/2 OR A.9/3 OR A.9/4 OR A.9/5 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages** | **Ref.** | **Status** | **Supp.** |
| 1 | Basic connection control | 7.2.5.1 | c6004 | |
| 2 | MAC layer test messages | 7.2.5.1 | x | |
| 3 | Advanced connection control | 7.2.5.1 | c6002 | |
| 4 | Quality control | 7.2.5.1 | o | |
| 5 | Broadcast and connectionless services | 7.2.5.1 | c6005 | |
| 6 | Encryption control | 7.2.5.1 | c6003 | |
| 7 | B-field setup, first PT transmission | 7.2.5.1 | o | |
| 8 | MAC control escape | 7.2.5.1 | o | |
| 9 | TARI | 7.2.5.1 | o | |

c6001: IF A.38/8 THEN m ELSE n/a
c6002: IF A.29/2 OR A.29/4 THEN m ELSE n/a
c6003: IF A.37/1 THEN m ELSE n/a
c6004: IF A.9/1 THEN m ELSE o
c6005: IF A.9/2 OR A.9/3 THEN m ELSE o

**Table A.61: MAC control ($M_T$) messages (Receipt F to P)**

| Prerequisite: A.9/1 OR A.9/2 OR A.9/3 OR A.9/4 OR A.9/5 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages** | **Ref.** | **Status** | **Supp.** |
| 1 | Basic connection control | 7.2.5.1 | c6104 | |
| 2 | MAC layer test messages | 7.2.5.1 | c6101 | |
| 3 | Advanced connection control | 7.2.5.1 | c6102 | |
| 4 | Quality control | 7.2.5.1 | o | |
| 5 | Broadcast and connectionless services | 7.2.5.1 | c6105 | |
| 6 | Encryption control | 7.2.5.1 | c6103 | |
| 7 | B-field setup, first PT transmission | 7.2.5.1 | x | |
| 8 | MAC control escape | 7.2.5.1 | o | |
| 9 | TARI | 7.2.5.1 | o | |

c6101: IF A.38/8 THEN m ELSE n/a

c6102: IF A.29/2 OR 29/4 THEN m ELSE n/a
c6103: IF A.37/1 THEN m ELSE n/a
c6104: IF A.9/1 THEN m ELSE o
c6105: IF A.9/2 OR A.9/3 THEN m ELSE o

### A.7.5.2 Basic connection control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.62: Basic connection control (Sending P to F)**

| Prerequisite: A.60/1 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages -Basic connection control** | **Ref.** | **Status** | **Supp.** |
| 1 | Basic CC - access request | 7.2.5.2.2 | m | |
| 2 | Basic CC - bearer handover request | 7.2.5.2.2 | m | |
| 3 | Basic CC - connection handover request | 7.2.5.2.2 | m | |
| 4 | Basic CC - unconfirmed access request | 7.2.5.2.2 | c6201 | |
| 5 | Basic CC - bearer confirm | 7.2.5.2.2 | x | |
| 6 | Basic CC - release | 7.2.5.2.2 | m | |
| 7 | Basic CC - wait | 7.2.5.2.3 | m | |

c6201: IF A.29/7 THEN m ELSE o

**Table A.63: Basic connection control (Receipt F to P)**

| Prerequisite: A.61/1 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages -Basic connection control** | **Ref.** | **Status** | **Supp.** |
| 1 | Basic CC - access request | 7.2.5.2.2 | x | |
| 2 | Basic CC - bearer handover request | 7.2.5.2.2 | x | |
| 3 | Basic CC - connection handover request | 7.2.5.2.2 | x | |
| 4 | Basic CC - unconfirmed access request | 7.2.5.2.2 | x | |
| 5 | Basic CC - bearer confirm | 7.2.5.2.2 | m | |
| 6 | Basic CC - release | 7.2.5.2.2 | m | |
| 7 | Basic CC - wait | 7.2.5.2.3 | m | |

### A.7.5.3 MAC layer test messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.64: MAC layer test messages (Sending P to F)**

| | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - MAC layer test messages** | **Ref.** | **Status** | **Supp.** |
| 1 | MAC test - force transmit | 7.2.5.4.2 | x | |
| 2 | MAC test - loopback data | 7.2.5.4.3 | x | |
| 3 | MAC test - defeat antenna diversity | 7.2.5.4.4 | x | |
| 4 | MAC test - force bearer handover | 7.2.5.4.5 | x | |
| 5 | MAC test - escape | 7.2.5.4.6 | x | |
| 6 | MAC test - network test | 7.2.5.4.7 | x | |
| 7 | MAC test - clear test modes | 7.2.5.4.8 | x | |

**Table A.65: MAC layer test messages (Receipt F to P)**

| Prerequisite: A.61/2 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - MAC layer test messages** | **Ref.** | **Status** | **Supp.** |
| 1 | MAC test - force transmit | 7.2.5.4.2 | m | |
| 2 | MAC test - loopback data | 7.2.5.4.3 | m | |
| 3 | MAC test - defeat antenna diversity | 7.2.5.4.4 | c6501 | |
| 4 | MAC test - force bearer handover | 7.2.5.4.5 | o | |
| 5 | MAC test - escape | 7.2.5.4.6 | o | |
| 6 | MAC test - network test | 7.2.5.4.7 | o | |
| 7 | MAC test - clear test modes | 7.2.5.4.8 | m | |

c6501: IF A.31/4 THEN m ELSE x

### A.7.5.4 Advanced connection control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.66: Advanced connection control messages (Sending P to F)**

| Prerequisite: A.60/3 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Advanced connection control** | **Ref.** | **Status** | **Supp.** |
| 1 | Advanced CC - access request | 7.2.5.3.2 | m | |
| 2 | Advanced CC - bearer handover request | 7.2.5.3.3 | m | |
| 3 | Advanced CC - connection handover request | 7.2.5.3.4 | m | |
| 4 | Advanced CC - unconfirmed access request | 7.2.5.3.5 | c6601 | |
| 5 | Advanced CC - bearer confirm | 7.2.5.3.6 | m | |
| 6 | Advanced CC - wait | 7.2.5.3.7 | m | |
| 7 | Advanced CC - attributes_T.request | 7.2.5.3.8 | m | |
| 8 | Advanced CC - attributes_T.confirm | 7.2.5.3.8 | m | |
| 9 | Advanced CC - bandwidth_T.request | 7.2.5.3.9 | m | |
| 10 | Advanced CC - bandwidth_T.confirm | 7.2.5.3.9 | m | |
| 11 | Advanced CC - channel list | 7.2.5.3.10 | m | |
| 12 | Advanced CC - unconfirmed dummy | 7.2.5.3.11 | c6601 | |
| 13 | Advanced CC - unconfirmed handover | 7.2.5.3.12 | c6601 | |
| 14 | Advanced CC - release | 7.2.5.3.13 | m | |

c6601: IF 29/6 OR 29/7 THEN m ELSE n/a

**Table A.67: Advanced connection control messages (Receipt F to P)**

| Prerequisite: A.61/3 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Advanced connection control** | **Ref.** | **Status** | **Supp.** |
| 1 | Advanced CC - access request | 7.2.5.3.2 | m | |
| 2 | Advanced CC - bearer handover request | 7.2.5.3.3 | x | |
| 3 | Advanced CC - connection handover request | 7.2.5.3.4 | m | |
| 4 | Advanced CC - unconfirmed access request | 7.2.5.3.5 | c6701 | |
| 5 | Advanced CC - bearer confirm | 7.2.5.3.6 | m | |
| 6 | Advanced CC - wait | 7.2.5.3.7 | m | |
| 7 | Advanced CC - attributes_T.request | 7.2.5.3.8 | m | |
| 8 | Advanced CC - attributes_T.confirm | 7.2.5.3.8 | m | |
| 9 | Advanced CC - bandwidth_T.request | 7.2.5.3.9 | m | |
| 10 | Advanced CC - bandwidth_T.confirm | 7.2.5.3.9 | m | |
| 11 | Advanced CC - channel list | 7.2.5.3.10 | m | |
| 12 | Advanced CC - unconfirmed dummy | 7.2.5.3.11 | c6701 | |
| 13 | Advanced CC - unconfirmed handover | 7.2.5.3.12 | c6701 | |
| 14 | Advanced CC - release | 7.2.5.3.13 | m | |

c6701: IF 29/6 OR 29/7 THEN m ELSE n/a

### A.7.5.5 Quality control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.68: Quality control (QC) messages (Sending P to F)**

| Prerequisite: A.60/4 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Quality control** | **Ref.** | **Status** | **Supp.** |
| 1 | QC - antenna switch single bearer request | 7.2.5.5 | m | |
| 2 | QC - antenna switch all bearers request | 7.2.5.5 | m | |
| 3 | QC - bearer handover reject | 7.2.5.5 | m | |
| 4 | QC - connection handover reject | 7.2.5.5 | m | |
| 5 | QC - frequency control single bearer reject | 7.2.5.5 | m | |
| 6 | QC - frequency control all bearers reject | 7.2.5.5 | m | |

**Table A.69: Quality control (QC) messages (Receipt F to P)**

| Prerequisite: A.61/4 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Quality control** | **Ref.** | **Status** | **Supp.** |
| 1 | QC - antenna switch single bearer reject | 7.2.5.5 | m | |
| 2 | QC - antenna switch all bearers reject | 7.2.5.5 | m | |
| 3 | QC - bearer handover request | 7.2.5.5 | m | |
| 4 | QC - connection handover request | 7.2.5.5 | m | |
| 5 | QC - frequency control single bearer request | 7.2.5.5 | m | |
| 6 | QC - frequency control all bearers request | 7.2.5.5 | m | |

### A.7.5.6 Broadcast and connectionless (BCL) messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.70: Broadcast and connectionless (BCL) messages (Sending P to F)**

| Prerequisite: A.60/5 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Broadcast and connectionless services** | **Ref.** | **Status** | **Supp.** |
| 1 | CLF, first of 2 transmissions, half slot | 7.2.5.6 | o | |
| 2 | CLF first of 2 transmissions, full slot | 7.2.5.6 | o | |
| 3 | CLF first of 2 transmissions, double slot | 7.2.5.6 | o | |
| 4 | CLF, last transmissions, half slot | 7.2.5.6 | o | |
| 5 | CLF, last transmissions, full slot | 7.2.5.6 | o | |
| 6 | CLF, last transmissions, double slot | 7.2.5.6 | o | |
| 7 | C/L single transmissions, no CF or CLS | 7.2.5.6 | o | |
| 8 | CLS service, first transmissions | 7.2.5.6 | o | |
| 9 | change dummy bearer position | 7.2.5.6 | o | |
| 10 | extended system info., A-field procedure | 7.2.5.6 | c7001 | |
| 11 | extended system info., B-field procedure | 7.2.5.6 | c7002 | |

c7001: IF 36/3 THEN m ELSE n/a
c7002: IF 36/4 THEN m ELSE n/a

**Table A.71: Broadcast and connectionless (BCL) messages (Receipt F to P)**

| Prerequisite: A.61/5 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Broadcast and connectionless services** | **Ref.** | **Status** | **Supp.** |
| 1 | CLF, first of 2 transmissions, half slot | 7.2.5.6 | x | |
| 2 | CLF first of 2 transmissions, full slot | 7.2.5.6 | x | |
| 3 | CLF first of 2 transmissions, double slot | 7.2.5.6 | x | |
| 4 | CLF, last transmissions, half slot | 7.2.5.6 | x | |
| 5 | CLF, last transmissions, full slot | 7.2.5.6 | x | |
| 6 | CLF, last transmissions, double slot | 7.2.5.6 | x | |
| 7 | C/L single transmissions, no CF or CLS | 7.2.5.6 | x | |
| 8 | CLS service, first transmissions | 7.2.5.6 | x | |
| 9 | change dummy bearer position | 7.2.5.6 | x | |
| 10 | extended system info., A-field procedure | 7.2.5.6 | c7101 | |
| 11 | extended system info., B-field procedure | 7.2.5.6 | c7102 | |

c7101: IF 36/3 THEN m ELSE n/a
c7102: IF 36/4 THEN m ELSE n/a

### A.7.5.7 Encryption control (EC) messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.72: Encryption control (EC) messages (Sending P to F)**

| Prerequisite: A.60/6 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Encryption control** | **Ref.** | **Status** | **Supp.** |
| 1 | Encryption start request | 7.2.5.7 | m | |
| 2 | Encryption start confirm | 7.2.5.7 | m | |
| 3 | Encryption start grant | 7.2.5.7 | m | |
| 4 | Encryption stop request | 7.2.5.7 | o | |
| 5 | Encryption stop confirm | 7.2.5.7 | o | |
| 6 | Encryption stop grant | 7.2.5.7 | o | |

**Table A.73: Encryption control (EC) messages (Receipt F to P)**

| Prerequisite: A.61/6 | | | | |
|---|---|---|---|---|
| **Item** | **MAC control ($M_T$) messages - Encryption control** | **Ref.** | **Status** | **Supp.** |
| 1 | Encryption start request | 7.2.5.7 | m | |
| 2 | Encryption start confirm | 7.2.5.7 | m | |
| 3 | Encryption start grant | 7.2.5.7 | m | |
| 4 | Encryption stop request | 7.2.5.7 | o | |
| 5 | Encryption stop confirm | 7.2.5.7 | o | |
| 6 | Encryption stop grant | 7.2.5.7 | o | |

### A.7.6 B - Field Messages

#### A.7.6.1 B - Field Messages supported

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.74: B - Field messages supported (Sending P to F)**

| Prerequisite: A.9/5 OR A.10/2 OR A.10/3 | | | | |
|---|---|---|---|---|
| **Item** | **B - Field messages** | **Ref.** | **Status** | **Support** |
| 1 | X001 - Advanced connection control | 7.3.1 | m | |
| 2 | X010 - Null message | 7.3.1 | m | |
| 3 | X011 - Quality control | 7.3.1 | m | |
| 4 | X100 - Extended system information | 7.3.1 | m | |
| 5 | X101 - GF channel data packet | 7.3.1 | m | |
| 6 | X111 - B-field escape | 7.3.1 | m | |

**Table A.75: B - Field messages supported (Receipt F to P)**

| Prerequisite: A.9/5 OR A.10/2 OR A.10/3 | | | | |
|---|---|---|---|---|
| **Item** | **B - Field messages** | **Ref.** | **Status** | **Support** |
| 1 | X001 - Advanced connection control | 7.3.1 | m | |
| 2 | X010 - Null message | 7.3.1 | m | |
| 3 | X011 - Quality control | 7.3.1 | m | |
| 4 | X100 - Extended system information | 7.3.1 | m | |
| 5 | X101 - GF channel data packet | 7.3.1 | m | |
| 6 | X111 - B-field escape | 7.3.1 | m | |

#### A.7.6.2 B - Field Advanced connection control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.76: B - Field Advanced connection control messages (Sending P to F)**

| Prerequisite: A.74/1 | | | | |
|---|---|---|---|---|
| **Item** | **B - Field Advanced CC messages** | **Ref.** | **Status** | **Support** |
| 1 | Access request | 7.3.3.2 | m | |
| 2 | Bearer handover request | 7.3.3.2 | m | |
| 3 | Connection handover request | 7.3.3.2 | m | |
| 4 | Unconfirmed access request | 7.3.3.2 | o | |
| 5 | Bearer confirm | 7.3.3.3 | m | |
| 6 | Wait | 7.3.3.4 | m | |
| 7 | Attributes_B.request | 7.3.3.5 | m | |
| 8 | Attributes_B.confirm | 7.3.3.5 | m | |
| 9 | Bandwidth_B.request | 7.3.3.6 | m | |
| 10 | Bandwidth_B.confirm | 7.3.3.6 | m | |
| 11 | Channel list | 7.3.3.7 | m | |
| 12 | Unconfirmed dummy | 7.3.3.8 | o | |
| 13 | Unconfirmed handover | 7.3.3.9 | o | |
| 14 | Release | 7.3.3.10 | m | |

**Table A.77: B - Field Advanced connection control messages (Receipt F to P)**

| Prerequisite: A.75/1 | | | | |
|---|---|---|---|---|
| **Item** | **B - Field Advanced CC messages** | **Ref.** | **Status** | **Support** |
| 1 | Access request | 7.3.3.2 | m | |
| 2 | Bearer handover request | 7.3.3.2 | m | |
| 3 | Connection handover request | 7.3.3.2 | m | |
| 4 | Unconfirmed access request | 7.3.3.2 | o | |
| 5 | Bearer confirm | 7.3.3.3 | m | |
| 6 | Wait | 7.3.3.4 | m | |
| 7 | Attributes_B.request | 7.3.3.5 | m | |
| 8 | Attributes_B.confirm | 7.3.3.5 | m | |
| 9 | Bandwidth_B.request | 7.3.3.6 | m | |
| 10 | Bandwidth_B.confirm | 7.3.3.6 | m | |
| 11 | Channel list | 7.3.3.7 | m | |
| 12 | Unconfirmed dummy | 7.3.3.8 | o | |
| 13 | Unconfirmed handover | 7.3.3.9 | o | |
| 14 | Release | 7.3.3.10 | m | |

### A.7.6.3 B - Field - Null messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.78: B - Field - Null messages (Sending P to F)**

| Prerequisite: A.74/2 | | | | |
|---|---|---|---|---|
| **Item** | **B - Field - Null messages** | **Ref.** | **Status** | **Support** |
| 1 | No $C_F$ or $CL_F$ data in the B-field | 7.3.4 | m | |
| 2 | One B-subfield contains $C_F$ or $CL_F$ data | 7.3.4 | c7801 | |
| 3 | Two B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7802 | |
| 4 | Three B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7802 | |
| 5 | Four B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7802 | |
| 6 | Five B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7803 | |
| 7 | Six B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7803 | |
| 8 | Seven B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7803 | |
| 9 | Eight B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7803 | |
| 10 | Nine B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7803 | |

c7801: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a
c7802: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a
c7803: IF A.22/1 AND A.23/1 THEN m ELSE n/a

**Table A.79: B - Field - Null messages (Receipt F to P)**

| Prerequisite: A.75/2 | | | | |
|---|---|---|---|---|
| **Item** | **B - Field - Null messages** | **Ref.** | **Status** | **Support** |
| 1 | No $C_F$ or $CL_F$ data in the B-field | 7.3.4 | m | |
| 2 | One B-subfield contains $C_F$ or $CL_F$ data | 7.3.4 | c7901 | |
| 3 | Two B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7902 | |
| 4 | Three B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7902 | |
| 5 | Four B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7902 | |
| 6 | Five B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7903 | |
| 7 | Six B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7903 | |
| 8 | Seven B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7903 | |
| 9 | Eight B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7903 | |
| 10 | Nine B-subfield contain $C_F$ or $CL_F$ data | 7.3.4 | c7903 | |

c7901: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a
c7902: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a
c7903: IF A.22/1 AND A.23/1 THEN m ELSE n/a

### A.7.6.4 B - Field - Quality control messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.80: B - Field - Quality control messages (Sending P to F)**

| Prerequisite: A.74/3 | | | | |
|---|---|---|---|---|
| **Item** | **Quality control message** | **Ref.** | **Status** | **Support** |
| 1 | Antenna switch single bearer | 7.3.5.2 | m | |
| 2 | Antenna switch all bearers | 7.3.5.2 | m | |
| 3 | Bearer handover | 7.3.5.2 | m | |
| 4 | Connection handover | 7.3.5.2 | m | |
| 5 | Frequency control single bearer | 7.3.5.2 | m | |
| 6 | Frequency control all bearers | 7.3.5.2 | m | |
| 7 | Reset request first TDMA half frame | 7.3.5.3 | c8001 | |
| 8 | Reset request second TDMA half frame | 7.3.5.3 | c8001 | |
| 9 | Reset request both TDMA half frames | 7.3.5.3 | c8001 | |
| 10 | Reset confirm first TDMA half frame | 7.3.5.3 | c8001 | |
| 11 | Reset confirmt second TDMA half frame | 7.3.5.3 | c8001 | |
| 12 | Reset confirm both TDMA half frames | 7.3.5.3 | c8001 | |
| 13 | MOD2 ACK | 7.3.5.4 | m | |

c8001: IF A.12/4 OR A.13/3 THEN m ELSE x

**Table A.81: B - Field - Quality control messages (Receipt F to P)**

| Prerequisite: A.75/3 | | | | |
|---|---|---|---|---|
| **Item** | **Quality control message** | **Ref.** | **Status** | **Support** |
| 1 | Antenna switch single bearer | 7.3.5.2 | m | |
| 2 | Antenna switch all bearers | 7.3.5.2 | m | |
| 3 | Bearer handover | 7.3.5.2 | m | |
| 4 | Connection handover | 7.3.5.2 | m | |
| 5 | Frequency control single bearer | 7.3.5.2 | m | |
| 6 | Frequency control all bearers | 7.3.5.2 | m | |
| 7 | Reset request first TDMA half frame | 7.3.5.3 | c8101 | |
| 8 | Reset request second TDMA half frame | 7.3.5.3 | c8101 | |
| 9 | Reset request both TDMA half frames | 7.3.5.3 | c8101 | |
| 10 | Reset confirm first TDMA half frame | 7.3.5.3 | c8101 | |
| 11 | Reset confirmt second TDMA half frame | 7.3.5.3 | c8101 | |
| 12 | Reset confirm both TDMA half frames | 7.3.5.3 | c8101 | |
| 13 | MOD2 ACK | 7.3.5.4 | m | |

c8101: IF A.12/4 OR A.13/3 THEN m ELSE x

### A.7.6.5 B - Field - GF-channel data packet messages

The support of a message in sending or receiving side implies that the all message (sequencing, length and value of field) as described in corresponding subclause is supported.

**Table A.82: B - Field - GF-channel data packet messages (Sending P to F)**

| Prerequisite: A.74/5 | | | | |
|---|---|---|---|---|
| **Item** | **GF-channel data packet** | **Ref.** | **Status** | **Support** |
| 1 | No $C_F$ data in the B-field | 7.3.7 | m | |
| 2 | One B-subfield contains $C_F$ data | 7.3.7 | c8201 | |
| 3 | Two B-subfield contain $C_F$ data | 7.3.7 | c8202 | |
| 4 | Three B-subfield contain $C_F$ data | 7.3.7 | c8202 | |
| 5 | Four B-subfield contain $C_F$ data | 7.3.7 | c8202 | |
| 6 | Five B-subfield contain $C_F$ data | 7.3.7 | c8203 | |
| 7 | Six B-subfield contain $C_F$ data | 7.3.7 | c8203 | |
| 8 | Seven B-subfield contain $C_F$ data | 7.3.7 | c8203 | |
| 9 | Eight B-subfield contain $C_F$ data | 7.3.7 | c8203 | |
| 10 | Nine B-subfield contain $C_F$ data | 7.3.7 | c8203 | |

c8201: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a
c8202: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a
c8203: IF A.22/1 AND A.23/1 THEN m ELSE n/a

**Table A.83: B - Field - GF-channel data packet messages (Receipt F to P)**

| Prerequisite: A.75/5 | | | | |
|---|---|---|---|---|
| **Item** | **GF-channel data packet** | **Ref.** | **Status** | **Support** |
| 1 | No $C_F$ data in the B-field | 7.3.7 | m | |
| 2 | One B-subfield contains $C_F$ data | 7.3.7 | c8301 | |
| 3 | Two B-subfield contain $C_F$ data | 7.3.7 | c8302 | |
| 4 | Three B-subfield contain $C_F$ data | 7.3.7 | c8302 | |
| 5 | Four B-subfield contain $C_F$ data | 7.3.7 | c8302 | |
| 6 | Five B-subfield contain $C_F$ data | 7.3.7 | c8303 | |
| 7 | Six B-subfield contain $C_F$ data | 7.3.7 | c8303 | |
| 8 | Seven B-subfield contain $C_F$ data | 7.3.7 | c8303 | |
| 9 | Eight B-subfield contain $C_F$ data | 7.3.7 | c8303 | |
| 10 | Nine B-subfield contain $C_F$ data | 7.3.7 | c8303 | |

c8301: IF A.22/1 AND (A.23/1 OR A.23/2 OR A.23/3) THEN m ELSE n/a
c8302: IF A.22/1 AND (A.23/1 OR A.23/2) THEN m ELSE n/a
c8303: IF A.22/1 AND A.23/1 THEN m ELSE n/a

## A.8 MAC messages format and field value

### A.8.1 A - field identities information ($N_T$) message

**Table A.84: NT - Identities Information (Sending P to F)**

| Prerequisite: 55/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **NT - Identities Information** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | E | 7.2.2 | m | | '0'B, '1'B | |
| 2 | PARI | 7.2.2 | m | | 31 or 36 bits value | |
| 3 | RPN | 7.2.2 | m | | 3 or 8 bits value | |

**Table A.85: NT - Identities Information (Receipt F to P)**

| Prerequisite: 56/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **NT - Identities Information** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | E | 7.2.2 | m | | '0'B, '1'B | |
| 2 | PARI | 7.2.2 | m | | 31 or 36 bits value | |
| 3 | RPN | 7.2.2 | m | | 3 or 8 bits value | |

### A.8.2 A - field system information ($Q_T$) messages

#### A.8.2.1 QT - Static system information

**Table A.86: QT - Static system information (Receipt F to P)**

| Prerequisite: 57/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QT - Static system information** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $Q_T$ header | 7.2.3.2.1 | m | | '000'B | |
| 2 | Normal/reverse | 7.2.3.2.2 | m | | '0'B, '1'B | |
| 3 | Slot number | 7.2.3.2.3 | m | | '0000'B .. '1011'B | |
| 4 | Start position | 7.2.3.2.4 | m | | '00", '10'B | |
| 5 | Escape bit | 7.2.3.2.5 | m | | '0'B, '1'B | |
| 6 | Number of tranceivers | 7.2.3.2.6 | m | | '00'B .. '11'B | |
| 7 | Extended RF carrier | 7.2.3.2.7 | m | | '0'B, '1'B | |
| 8 | RF carriers available | 7.2.3.2.8 | m | | 10 bits value | |
| 9 | Spr 1 | 7.2.3.2.9 | m | | '00'B | |
| 10 | Carrier number | 7.2.3.2.10 | m | | '000000'B .. '001001'B | |
| 11 | Spr 2 | 7.2.3.2.11 | m | | '00'B | |
| 12 | PSCN | 7.2.3.2.12 | m | | '000000'B .. '001001'B | |

#### A.8.2.2 QT - Extended RF carrier information

**Table A.87: QT - Extended RF carrier information (Receipt F to P)**

| Prerequisite: 57/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QT - Extended RF carrier information** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $Q_T$ header | 7.2.3.3.1 | m | | '0010'B | |
| 2 | Reserved field | 7.2.3.3.1 | m | | 28 bits | |
| 3 | Spr | 7.2.3.3.1 | m | | '00'B | |
| 4 | Number of RF carriers | 7.2.3.3.1 | m | | 6 bits value | |

### A.8.2.3 QT - Fixed part capability

**Table A.88: QT - Fixed part capability (Receipt F to P)**

| Prerequisite: 57/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QT - Fixed part capability** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $Q_T$ header | 7.2.3.4.2 | m | | '0011'B | |
| 2 | Extended FP info. | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 3 | Reserved | 7.2.3.4.2 | m | | 1 bit | |
| 4 | Reserved | 7.2.3.4.2 | m | | 1 bit | |
| 5 | Double slot | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 6 | Half slot | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 7 | Full slot | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 8 | Frequency control | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 9 | Page repetition | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 10 | Dummy bearer setup | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 11 | C/L uplink | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 12 | C/L downlink | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 13 | Basic A-field setup | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 14 | Adv. A-field setup | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 15 | B-field setup | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 16 | CF messages | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 17 | IN minimum delay | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 18 | IN normal delay | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 19 | IP error detection | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 20 | IP error correction | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 21 | Multibearer connection | 7.2.3.4.2 | m | | '0'B, '1'B | |
| 22 | Higher layer info. | 7.2.3.4.2 | m | | 16 bits value | |

### A.8.2.4 QT - Extended fixed part capabilities

**Table A.89: QT - Extended fixed part capabilities (Receipt F to P)**

| Prerequisite: 57/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QT - Extended fixed part capabilities** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $Q_T$ header | 7.2.3.5.1 | m | | '0100'B | |
| 2 | Reserved field | 7.2.3.5.2 | m | | 36 bits value | |

### A.8.2.5 QT - Secondary access rights identities

**Table A.90: QT - Secondary access rights identities (Receipt F to P)**

| Prerequisite: 57/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QT - Secondary access rights identities** | **Ref.** | **Status** | **Supp.** | **Value** | **Value Supported** |
| 1 | $Q_T$ header | 7.2.3.6.1 | | | '0101'B | |
| 2 | SARI message | 7.2.3.6.2 | | | 36 bits value | |

#### A.8.2.6 QT - Multi-frame number

**Table A.91: QT - Multi-frame number (Receipt F to P)**

| Prerequisite: 57/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QT - Multi-frame number** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $Q_T$ header | 7.2.3.7.1 | m | | '0110'B | |
| 2 | Spare | 7.2.3.7.1 | m | | '1111 0000 1111'B | |
| 3 | Multiframe number | 7.2.3.7.2 | m | | 24 bits value | |

#### A.8.2.7 QT - escape

**Table A.92: QT - escape (Receipt F to P)**

| Prerequisite: 57/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QT - escape** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $Q_T$ header | 7.2.3.8.1 | m | | '0111'B | |
| 2 | Proprietary mess. | 7.2.3.8.2 | m | | 36 bits value | |

### A.8.3 A - field paging tail ($P_T$) messages

#### A.8.3.1 $P_T$ message - Full page

**Table A.93: $P_T$ message - Full page (Receipt F to P)**

| Prerequisite: 58/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$P_T$ message - Full page** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Extend flag | 7.2.4.2.2 | m | | '0'B, '1'B | |
| 2 | $B_S$ SDU length | 7.2.4.2.3 | m | | '010'B | |
| 3 | 36 bits $B_S$ data | 7.2.4.1.1 | m | | 36 bits value | |

#### A.8.3.2 $P_T$ message - Long page

**Table A.94: $P_T$ message - Long page (Receipt F to P)**

| Prerequisite: 58/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$P_T$ message - Long page** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Extend flag | 7.2.4.2.2 | m | | '0'B, '1'B | |
| 2 | $B_S$ SDU length | 7.2.4.2.3 | m | | '100'B .. '111'B | |
| 3 | 36 bits $B_S$ data | 7.2.4.1.1 | m | | 36 bits value | |

### A.8.3.3 $P_T$ message - Short page

**Table A.95: $P_T$ message - Short page (Receipt F to P)**

| Prerequisite: 58/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$P_T$ message - Short page** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Extend flag | 7.2.4.2.2 | m | | '0'B, '1'B | |
| 2 | $B_S$ SDU length | 7.2.4.2.3 | m | | '001'B | |
| 3 | 20 bits $B_S$ data | 7.2.4.1.2 | m | | 20 bits value | |
| 4 | Info type | 7.2.4.3.1 | m | | '0000'B .. '1010'B | |
| 5 | MAC info. element | 7.2.4.1.2 | m | | 12 bits value | |

### A.8.3.4 $P_T$ message - Zero length page

**Table A.96: $P_T$ message - Zero length page (Receipt F to P)**

| Prerequisite: 58/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$P_T$ message - Zero length page** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Extend flag | 7.2.4.2.2 | m | | '0'B, '1'B | |
| 2 | $B_S$ SDU length | 7.2.4.2.3 | m | | '000'B | |
| 3 | 20 LSB bits of RFPI | 7.2.4.1.2 | m | | 20 bits value | |
| 4 | Info type | 7.2.4.3.1 | m | | '0000'B .. '1010'B | |
| 5 | MAC info. element | 7.2.4.1.2 | m | | 12 bits value | |

### A.8.3.5 $P_T$ messages - MAC info. element

#### A.8.3.5.1 MAC info. element - Fill bits

**Table A.97: MAC info. element - Fill bits (Receipt F to P)**

| Prerequisite: 59/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Fill bits** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Fill bits | 7.2.4.3.2 | m | | '1111 0000 1111'B | |

#### A.8.3.5.2 MAC info. element - Blind full slot

**Table A.98: MAC info. element - Blind full slot (Receipt F to P)**

| Prerequisite: 59/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Blind full slot** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Slot {0,12} (a36) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 2 | Slot {1,13} (a37) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 3 | Slot {2,14} (a38) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 4 | Slot {3,15} (a39) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 5 | Slot {4,16} (a40) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 6 | Slot {5,17} (a41) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 7 | Slot {6,18} (a42) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 8 | Slot {7,19} (a43) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 9 | Slot {8,20} (a44) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 10 | Slot {9,21} (a45) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 11 | Slot {10,22} (a46) | 7.2.4.3.3 | m | | '0'B, '1'B | |
| 12 | Slot {11,23} (a47) | 7.2.4.3.3 | m | | '0'B, '1'B | |

#### A.8.3.5.3 MAC info. element - Other bearer

**Table A.99: MAC info. element - Other bearer (Receipt F to P)**

| Prerequisite: 59/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Other bearer** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Slot number | 7.2.3.2.3 | m | | '0000'B .. '1011'B | |
| 2 | Start position | 7.2.3.2.4 | m | | '00'B, '10'B | |
| 3 | Carrier number | 7.2.3.2.10 | m | | '000000'B .. '001001'B | |

#### A.8.3.5.4 MAC info. element - Recommended other bearer

**Table A.100: MAC info. element - Recommended other bearer (Receipt F to P)**

| Prerequisite: 59/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Recommended other bearer** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Slot number | 7.2.3.2.3 | m | | '0000'B .. '1011'B | |
| 2 | Start position | 7.2.3.2.4 | m | | '00'B, '10'B | |
| 3 | Carrier number | 7.2.3.2.10 | m | | '000000'B .. '001001'B | |

#### A.8.3.5.5 MAC info. element - Good RFP bearer

**Table A.101: MAC info. element - Good RFP bearer (Receipt F to P)**

| Prerequisite: 59/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Good RFP bearer** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Slot number | 7.2.3.2.3 | m | | '0000'B .. '1011'B | |
| 2 | Start position | 7.2.3.2.4 | m | | '00'B, '10'B | |
| 3 | Carrier number | 7.2.3.2.10 | m | | '000000'B .. '001001'B | |

#### A.8.3.5.6 MAC info. element - Dummy or C/L bearer position

**Table A.102: MAC info. element - Dummy or C/L bearer position (Receipt F to P)**

| Prerequisite: 59/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Dummy or C/L bearer position** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Slot number | 7.2.3.2.3 | m | | '0000'B .. '1011'B | |
| 2 | Start position | 7.2.3.2.4 | m | | '00'B, '10'B | |
| 3 | Carrier number | 7.2.3.2.10 | m | | '000000'B .. '001001'B | |

#### A.8.3.5.7 MAC info. element - RFP identity

**Table A.103: MAC info. element - RFP identity (Receipt F to P)**

| Prerequisite: 59/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - RFP identity** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | 12 LSB bits of RFPI | 7.2.4.3.5 | m | | 12 bits value | |

#### A.8.3.5.8 MAC info. element - Escape

**Table A.104: MAC info. element - Escape (Receipt F to P)**

| Prerequisite: 59/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Escape** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | 12 bits proprietary | 7.2.4.3.6 | m | | 12 bits value | |

#### A.8.3.5.9 MAC info. element - Dummy or C/L bearer marker

**Table A.105: MAC info. element - Dummy or C/L bearer marker (Receipt F to P)**

| Prerequisite: 59/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Dummy or C/L bearer marker** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Marker | 7.2.4.3.7 | m | | '1111 0000 1111'B | |

#### A.8.3.5.10 MAC info. element - Bearer handover information

**Table A.106: MAC info. element - Bearer handover information (Receipt F to P)**

| Prerequisite: 59/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - Bearer handover information** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | Info type | 7.2.4.3.8 | m | | '0000'B .. '0011'B | |
| 2 | Parameter | 7.2.4.3.8 | m | | '0000 1111'B or<br>12 bits 'bit mask' | |

#### A.8.3.5.11 MAC info. element - RFP status

**Table A.107: MAC info. element - RFP status (Receipt F to P)**

| Prerequisite: 59/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC info. element - RFP status** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | RFP status | 7.2.4.3.9 | m | | '0000'B .. '0011'B | |
| 2 | Spare | 7.2.4.3.9 | m | | '0000 1111'B | |

### A.8.4 A - field MAC control ($M_T$) messages

#### A.8.4.1 Basic connection control messages

##### A.8.4.1.1 Basic CC - access request

**Table A.108: Basic CC - access request (Sending P to F)**

| Prerequisite: 62/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '0000'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.2 | m | | 20 bits value | |

##### A.8.4.1.2 Basic CC - bearer handover request

**Table A.109: Basic CC - bearer handover request (Sending P to F)**

| Prerequisite: 62/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '0001'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.2 | m | | 20 bits value | |

##### A.8.4.1.3 Basic CC - connection handover request

**Table A.110: Basic CC - connection handover request (Sending P to F)**

| Prerequisite: 62/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC connection handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '0010'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.2 | m | | 20 bits value | |

##### A.8.4.1.4 Basic CC - unconfirmed access request

**Table A.111: Basic CC - unconfirmed access request (Sending P to F)**

| Prerequisite: 62/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC unconfirmed access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '0011'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.2 | m | | 20 bits value | |

#### A.8.4.1.5 Basic CC - bearer confirm

**Table A.112: Basic CC - bearer confirm (Receipt F to P)**

| Prerequisite: 63/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC bearer confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '0100'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.2 | m | | 20 bits value | |

#### A.8.4.1.6 Basic CC - wait

**Table A.113: Basic CC - wait (Sending P to F)**

| Prerequisite: 62/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC wait** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '1111'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.3 | m | | 20 bits value, '11110000 11110000 1111'B | |

**Table A.114: Basic CC - wait (Receipt F to P)**

| Prerequisite: 63/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC wait** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '1111'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.3 | m | | 20 bits value, '11110000 11110000 1111'B | |

#### A.8.4.1.7 Basic CC - release

**Table A.115: Basic CC - release (Sending P to F)**

| Prerequisite: 62/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC release** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '1111'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.2 | m | | 20 bits value | |

**Table A.116: Basic CC - release (Receipt F to P)**

| Prerequisite: 63/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Basic CC release** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.2.2 | m | | '0000'B | |
| 2 | Command | 7.2.5.2.2 | m | | '1111'B | |
| 3 | FMID | 7.2.5.2.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.2.2 | m | | 20 bits value | |

### A.8.4.2 MAC layer test messages

#### A.8.4.2.1 MAC test - force transmit

**Table A.117: MAC test - force transmit (Sending P to F)**

| Prerequisite: 64/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - force transmit** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.2 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.2 | m | | '0000'B | |
| 3 | Spr 1 | 7.2.5.4.2 | m | | '0101010'B | |
| 4 | KP | 7.2.5.4.2 | m | | '0'B, '1'B | |
| 5 | Handover disable | 7.2.5.4.2 | m | | '0'B, '1'B | |
| 6 | Spr2 | 7.2.5.4.2 | m | | '000'B | |
| 7 | Slot number | 7.2.5.4.2 | m | | '0000'B .. '1011'B | |
| 8 | Start position | 7.2.5.4.2 | m | | '00'B, '10'B | |
| 9 | Carrier number | 7.2.5.4.2 | m | | '000000'B .. '001001'B | |
| 10 | Spare | 7.2.5.4.2 | m | | '0000 1111" | |

**Table A.118: MAC test - force transmit (Receipt F to P)**

| Prerequisite: 65/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - force transmit** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.2 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.2 | m | | '0000'B | |
| 3 | Spr 1 | 7.2.5.4.2 | m | | '0101010'B | |
| 4 | KP | 7.2.5.4.2 | m | | '0'B, '1'B | |
| 5 | Handover disable | 7.2.5.4.2 | m | | '0'B, '1'B | |
| 6 | Spr2 | 7.2.5.4.2 | m | | '000'B | |
| 7 | Slot number | 7.2.5.4.2 | m | | '0000'B .. '1011'B | |
| 8 | Start position | 7.2.5.4.2 | m | | '00'B, '10'B | |
| 9 | Carrier number | 7.2.5.4.2 | m | | '000000'B .. '001001'B | |
| 10 | Spare | 7.2.5.4.2 | m | | '0000 1111" | |

#### A.8.4.2.2 MAC test - loopback data

**Table A.119: MAC test - loopback data (Sending P to F)**

| Prerequisite: 64/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - loopback data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.3 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.3 | m | | '0001'B | |
| 3 | Loopback data field | 7.2.5.4.3 | m | | 32 bits value | |

**Table A.120: MAC test - loopback data (Receipt F to P)**

| Prerequisite: 65/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - loopback data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.3 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.3 | m | | '0001'B | |
| 3 | Loopback data field | 7.2.5.4.3 | m | | 32 bits value | |

#### A.8.4.2.3 MAC test - defeat antenna diversity

**Table A.121: MAC test - defeat antenna diversity (Sending P to F)**

| Prerequisite: 64/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - defeat antenna diversity** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.4 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.4 | m | | '0010'B | |
| 3 | Defeat flag | 7.2.5.4.4 | m | | '0'B, '1'B | |
| 4 | Antenna number | 7.2.5.4.4 | m | | '000'B .. '111'B | |
| 5 | Spr | 7.2.5.4.4 | m | | '1111'B | |
| 6 | Spare 1 | 7.2.5.4.4 | m | | '0000 1111" | |
| 7 | Spare 2 | 7.2.5.4.4 | m | | '0000 1111" | |
| 8 | Spare 3 | 7.2.5.4.4 | m | | '0000 1111" | |

#### A.8.4.2.4 MAC test - force bearer handover

**Table A.122.: MAC test - force bearer handover (Sending P to F)**

| Prerequisite: 64/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - force bearer handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.5 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.5 | m | | '0011'B | |
| 3 | Spare 1 | 7.2.5.4.5 | m | | '0000 1111" | |
| 4 | Spare 2 | 7.2.5.4.5 | m | | '0000 1111" | |
| 5 | Spare 3 | 7.2.5.4.5 | m | | '0000 1111" | |
| 6 | Spare 4 | 7.2.5.4.5 | m | | '0000 1111" | |

**Table A.123.: MAC test - force bearer handover (Receipt F to P)**

| Prerequisite: 65/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - force bearer handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.5 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.5 | m | | '0011'B | |
| 3 | Spare 1 | 7.2.5.4.5 | m | | '0000 1111" | |
| 4 | Spare 2 | 7.2.5.4.5 | m | | '0000 1111" | |
| 5 | Spare 3 | 7.2.5.4.5 | m | | '0000 1111" | |
| 6 | Spare 4 | 7.2.5.4.5 | m | | '0000 1111" | |

### A.8.4.2.5 MAC test - escape

**Table A.124: MAC test - escape (Sending P to F)**

| Prerequisite: 64/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - escape** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.6 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.6 | m | | '0100'B | |
| 3 | Proprietary mess. | 7.2.5.4.6 | m | | 32 bits value | |

**Table A.125: MAC test - escape (Receipt F to P)**

| Prerequisite: 65/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - escape** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.6 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.6 | m | | '0100'B | |
| 3 | Proprietary mess. | 7.2.5.4.6 | m | | 32 bits value | |

### A.8.4.2.6 MAC test - network test

**Table A.126: MAC test - network test (Sending P to F)**

| Prerequisite: 64/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - network test** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.7 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.7 | m | | '0101'B | |
| 3 | Test message | 7.2.5.4.7 | m | | 32 bits value | |

**Table A.127: MAC test - network test (Receipt F to P)**

| Prerequisite: 65/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - network test** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.7 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.7 | m | | '0101'B | |
| 3 | Test message | 7.2.5.4.7 | m | | 32 bits value | |

#### A.8.4.2.7 MAC test - clear test modes

**Table A.128: MAC test - clear test modes (Sending P to F)**

| Prerequisite: 64/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - clear test modes** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.8 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.8 | m | | '1111'B | |
| 3 | Spare 1 | 7.2.5.4.8 | m | | '0000 1111" | |
| 4 | Spare 2 | 7.2.5.4.8 | m | | '0000 1111" | |
| 5 | Spare 3 | 7.2.5.4.8 | m | | '0000 1111" | |
| 6 | Spare 4 | 7.2.5.4.8 | m | | '0000 1111" | |

**Table A.129: MAC test - clear test modes (Receipt F to P)**

| Prerequisite: 65/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **MAC test - clear test modes** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.4.8 | m | | '0010'B | |
| 2 | Command | 7.2.5.4.8 | m | | '1111'B | |
| 3 | Spare 1 | 7.2.5.4.8 | m | | '0000 1111" | |
| 4 | Spare 2 | 7.2.5.4.8 | m | | '0000 1111" | |
| 5 | Spare 3 | 7.2.5.4.8 | m | | '0000 1111" | |
| 6 | Spare 4 | 7.2.5.4.8 | m | | '0000 1111" | |

### A.8.4.3 Advanced connection control messages

#### A.8.4.3.1 Advanced CC - access request

**Table A.130: Advanced CC - access request (Sending P to F)**

| Prerequisite: 66/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.2 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.2 | m | | '0000'B | |
| 3 | FMID | 7.2.5.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.2 | m | | 20 bits value | |

**Table A.131: Advanced CC - access request (Receipt F to P)**

| Prerequisite: 67/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.2 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.2 | m | | '0000'B | |
| 3 | FMID | 7.2.5.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.2 | m | | 20 bits value | |

#### A.8.4.3.2 Advanced CC - bearer handover request

**Table A.132: Advanced CC - bearer handover request (Sending P to F)**

| Prerequisite: 66/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.3 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.3 | m | | '0001'B | |
| 3 | FMID | 7.2.5.3.3 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.3 | m | | 20 bits value | |

#### A.8.4.3.3 Advanced CC - connection handover request

**Table A.133: Advanced CC - connection handover request (Sending P to F)**

| Prerequisite: 66/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - connection handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.4 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.4 | m | | '0010'B | |
| 3 | FMID | 7.2.5.3.4 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.4 | m | | 20 bits value | |

**Table A.134: Advanced CC - connection handover request (Receipt F to P)**

| Prerequisite: 67/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - connection handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.4 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.4 | m | | '0010'B | |
| 3 | FMID | 7.2.5.3.4 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.4 | m | | 20 bits value | |

#### A.8.4.3.4 Advanced CC - unconfirmed access request

**Table A.135: Advanced CC - unconfirmed access request (Sending P to F)**

| Prerequisite: 66/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - unconfirmed access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.5 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.5 | m | | '0011'B | |
| 3 | FMID | 7.2.5.3.5 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.5 | m | | 20 bits value | |

**Table A.136: Advanced CC - unconfirmed access request (Receipt F to P)**

| Prerequisite: 67/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - unconfirmed access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.5 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.5 | m | | '0011'B | |
| 3 | FMID | 7.2.5.3.5 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.5 | m | | 20 bits value | |

### A.8.4.3.5 Advanced CC - bearer confirm

**Table A.137: Advanced CC - bearer confirm (Sending P to F)**

| Prerequisite: 66/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - bearer confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.6 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.6 | m | | '0100'B | |
| 3 | FMID | 7.2.5.3.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.6 | m | | 20 bits value | |

**Table A.138: Advanced CC - bearer confirm (Receipt F to P)**

| Prerequisite: 67/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - bearer confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.6 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.6 | m | | '0100'B | |
| 3 | FMID | 7.2.5.3.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.6 | m | | 20 bits value | |

### A.8.4.3.6 Advanced CC - wait

**Table A.139: Advanced CC - wait (Sending P to F)**

| Prerequisite: 66/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - wait** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.7 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.7 | m | | '1111'B | |
| 3 | FMID | 7.2.5.3.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.7 | m | | 20 bits value, '11110000 11110000 1111'B | |

**Table A.140: Advanced CC - wait (Receipt F to P)**

| Prerequisite: 67/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - wait** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.7 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.7 | m | | '1111'B | |
| 3 | FMID | 7.2.5.3.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.7 | m | | 20 bits value, '11110000 11110000 1111'B | |

### A.8.4.3.7 Advanced CC - Attributes_T request

**Table A.141: Advanced CC - Attributes_T request (Sending P to F)**

| Prerequisite: 66/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Attributes_T request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.8 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.8 | m | | '0110'B | |
| 3 | ECN | 7.2.5.3.8 | m | | 4 bits value | |
| 4 | LBN | 7.2.5.3.8 | m | | 4 bits value | |
| 5 | Connection type | 7.2.5.3.8 | m | | '00'B .. '11'B | |
| 6 | Service type | 7.2.5.3.8 | m | | '000'B .. '100'B | |
| 7 | Maximum lifetime | 7.2.5.3.8 | m | | 3 bits value | |
| 8 | Slot type | 7.2.5.3.8 | m | | '0000'B .. '0010'B | |
| 9 | CF support flag | 7.2.5.3.8 | m | | '0'B, '1'B | |
| 10 | Spr | 7.2.5.3.8 | m | | '111'B | |
| 11 | Spare | 7.2.5.3.8 | m | | '0000 1111'B | |

Note to item 7: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.142: Advanced CC - Attributes_T request (Receipt F to P)**

| Prerequisite: 67/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Attributes_T request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.8 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.8 | m | | '0110'B | |
| 3 | ECN | 7.2.5.3.8 | m | | 4 bits value | |
| 4 | LBN | 7.2.5.3.8 | m | | 4 bits value | |
| 5 | Connection type | 7.2.5.3.8 | m | | '00'B .. '11'B | |
| 6 | Service type | 7.2.5.3.8 | m | | '000'B .. '100'B | |
| 7 | Maximum lifetime | 7.2.5.3.8 | m | | 3 bits value | |
| 8 | Slot type | 7.2.5.3.8 | m | | '0000'B .. '0010'B | |
| 9 | CF support flag | 7.2.5.3.8 | m | | '0'B, '1'B | |
| 10 | Spr | 7.2.5.3.8 | m | | '111'B | |
| 11 | Spare | 7.2.5.3.8 | m | | '0000 1111'B | |

Note to item 7: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.4.3.8 Advanced CC - Attributes_T confirm

**Table A.143: Advanced CC - Attributes_T confirm (Sending P to F)**

| Prerequisite: 66/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Attributes_T confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.8 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.8 | m | | '0111'B | |
| 3 | ECN | 7.2.5.3.8 | m | | 4 bits value | |
| 4 | LBN | 7.2.5.3.8 | m | | 4 bits value | |
| 5 | Connection type | 7.2.5.3.8 | m | | '00'B .. '11'B | |
| 6 | Service type | 7.2.5.3.8 | m | | '000'B .. '100'B | |
| 7 | Maximum lifetime | 7.2.5.3.8 | m | | 3 bits value | |
| 8 | Slot type | 7.2.5.3.8 | m | | '0000'B .. '0010'B | |
| 9 | CF support flag | 7.2.5.3.8 | m | | '0'B, '1'B | |
| 10 | Spr | 7.2.5.3.8 | m | | '111'B | |
| 11 | Spare | 7.2.5.3.8 | m | | '0000 1111'B | |

Note to item 7: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.144: Advanced CC - Attributes_T confirm (Receipt F to P)**

| Prerequisite: 67/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Attributes_T confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.8 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.8 | m | | '0111'B | |
| 3 | ECN | 7.2.5.3.8 | m | | 4 bits value | |
| 4 | LBN | 7.2.5.3.8 | m | | 4 bits value | |
| 5 | Connection type | 7.2.5.3.8 | m | | '00'B .. '11'B | |
| 6 | Service type | 7.2.5.3.8 | m | | '000'B .. '100'B | |
| 7 | Maximum lifetime | 7.2.5.3.8 | m | | 3 bits value | |
| 8 | Slot type | 7.2.5.3.8 | m | | '0000'B .. '0010'B | |
| 9 | CF support flag | 7.2.5.3.8 | m | | '0'B, '1'B | |
| 10 | Spr | 7.2.5.3.8 | m | | '111'B | |
| 11 | Spare | 7.2.5.3.8 | m | | '0000 1111'B | |

Note to item 7: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.4.3.9 Advanced CC - Bandwidth_T request

**Table A.145: Advanced CC - Bandwidth_T request (Sending P to F)**

| Prerequisite: 66/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Bandwidth_T request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.9 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.9 | m | | '1000'B | |
| 3 | spr 1 | 7.2.5.3.9 | m | | '000'B | |
| 4 | M-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 5 | spr 2 | 7.2.5.3.9 | m | | '000'B | |
| 6 | T-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 7 | spr 3 | 7.2.5.3.9 | m | | '000'B | |
| 8 | M-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 9 | spr 4 | 7.2.5.3.9 | m | | '000'B | |
| 10 | T-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |

**Table A.146: Advanced CC - Bandwidth_T request (Receipt F to P)**

| Prerequisite: 67/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Bandwidth_T request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.9 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.9 | m | | '1000'B | |
| 3 | spr 1 | 7.2.5.3.9 | m | | '000'B | |
| 4 | M-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 5 | spr 2 | 7.2.5.3.9 | m | | '000'B | |
| 6 | T-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 7 | spr 3 | 7.2.5.3.9 | m | | '000'B | |
| 8 | M-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 9 | spr 4 | 7.2.5.3.9 | m | | '000'B | |
| 10 | T-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |

### A.8.4.3.10 Advanced CC - Bandwidth_T confirm

**Table A.147: Advanced CC - Bandwidth_T confirm (Sending P to F)**

| Prerequisite: 66/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Bandwidth_T confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.9 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.9 | m | | '1001'B | |
| 3 | spr 1 | 7.2.5.3.9 | m | | '000'B | |
| 4 | M-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 5 | spr 2 | 7.2.5.3.9 | m | | '000'B | |
| 6 | T-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 7 | spr 3 | 7.2.5.3.9 | m | | '000'B | |
| 8 | M-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 9 | spr 4 | 7.2.5.3.9 | m | | '000'B | |
| 10 | T-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |

**Table A.148: Advanced CC - Bandwidth_T confirm (Receipt F to P)**

| Prerequisite: 67/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Bandwidth_T confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.9 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.9 | m | | '1001'B | |
| 3 | spr 1 | 7.2.5.3.9 | m | | '000'B | |
| 4 | M-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 5 | spr 2 | 7.2.5.3.9 | m | | '000'B | |
| 6 | T-up | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 7 | spr 3 | 7.2.5.3.9 | m | | '000'B | |
| 8 | M-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |
| 9 | spr 4 | 7.2.5.3.9 | m | | '000'B | |
| 10 | T-down | 7.2.5.3.9 | m | | '00000'B .. '11110'B | |

#### A.8.4.3.11 Advanced CC - Channel List

**Table A.149: Advanced CC - Channel List (Sending P to F)**

| Prerequisite: 66/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - channel List** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.10 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.10 | m | | '1010'B | |
| 3 | RPN | 7.2.5.3.10 | m | | 8 bits value | |
| 4 | Cmd | 7.2.5.3.10 | m | | '000'B .. '111'B | |
| 5 | S/D flag | 7.2.5.3.10 | m | | '0'B, '1'B | |
| 6 | Slot number | 7.2.5.3.10 | m | | '0000'B .. '1011'B | |
| 7 | Start position | 7.2.5.3.10 | m | | '00'B, '10'B | |
| 8 | Carrier number | 7.2.5.3.10 | m | | '000000'B .. '001001'B | |
| 9 | spare | 7.2.5.3.10 | m | | 8 bits value | |

**Table A.150: Advanced CC - Channel List (Receipt F to P)**

| Prerequisite: 67/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - channel List** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.10 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.10 | m | | '1010'B | |
| 3 | RPN | 7.2.5.3.10 | m | | 8 bits value | |
| 4 | Cmd | 7.2.5.3.10 | m | | '000'B .. '111'B | |
| 5 | S/D flag | 7.2.5.3.10 | m | | '0'B, '1'B | |
| 6 | Slot number | 7.2.5.3.10 | m | | '0000'B .. '1011'B | |
| 7 | Start position | 7.2.5.3.10 | m | | '00'B, '10'B | |
| 8 | Carrier number | 7.2.5.3.10 | m | | '000000'B .. '001001'B | |
| 9 | spare | 7.2.5.3.10 | m | | 8 bits value | |

#### A.8.4.3.12 Advanced CC - Unconfirmed_dummy

**Table A.151: Advanced CC - Unconfirmed_dummy (Sending P to F)**

| Prerequisite: 66/12 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Unconfirmed_dummy** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.11 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.11 | m | | '1011'B | |
| 3 | FMID | 7.2.5.3.11 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.11 | m | | 20 bits value | |

**Table A.152: Advanced CC - Unconfirmed_dummy (Receipt F to P)**

| Prerequisite: 67/12 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Unconfirmed_dummy** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.11 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.11 | m | | '1011'B | |
| 3 | FMID | 7.2.5.3.11 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.11 | m | | 20 bits value | |

#### A.8.4.3.13 Advanced CC - Unconfirmed_handover

**Table A.153: Advanced CC - Unconfirmed_handover (Sending P to F)**

| Prerequisite: 66/13 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Unconfirmed_handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.12 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.12 | m | | '1100'B | |
| 3 | FMID | 7.2.5.3.12 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.12 | m | | 20 bits value | |

**Table A.154: Advanced CC - Unconfirmed_handover (Receipt F to P)**

| Prerequisite: 67/13 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - Unconfirmed_handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.12 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.12 | m | | '1100'B | |
| 3 | FMID | 7.2.5.3.12 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.3.12 | m | | 20 bits value | |

#### A.8.4.3.14 Advanced CC - release

**Table A.155: Advanced CC - release (Sending P to F)**

| Prerequisite: 66/14 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - release** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.13 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.13 | m | | '1111'B | |
| 3 | spr | 7.2.5.3.13 | m | | '0000'B | |
| 4 | LBN | 7.2.5.3.13 | m | | 4 bits value | |
| 5 | reason | 7.2.5.3.13 | m | | '0000'B .. '1101'B | |
| 6 | PMID | 7.2.5.3.13 | m | | 20 bits value | |

**Table A.156: Advanced CC - release (Receipt F to P)**

| Prerequisite: 67/14 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **Advanced CC - release** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.3.13 | m | | '0001'B | |
| 2 | Command | 7.2.5.3.13 | m | | '1111'B | |
| 3 | spr | 7.2.5.3.13 | m | | '0000'B | |
| 4 | LBN | 7.2.5.3.13 | m | | 4 bits value | |
| 5 | reason | 7.2.5.3.13 | m | | '0000'B .. '1101'B | |
| 6 | PMID | 7.2.5.3.13 | m | | 20 bits value | |

### A.8.4.4 Quality control messages

#### A.8.4.4.1 QC - antenna switch single bearer request

**Table A.157: QC - antenna switch single bearer request (Sending P to F)**

| Prerequisite: 68/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - antenna switch single bearer request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0000'B | |
| 3 | spr | 7.2.5.5 | m | | '0000'B | |
| 4 | LBN | 7.2.5.5 | m | | 4 bits value | |
| 5 | param_2 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 7 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

**Table A.158: QC - antenna switch single bearer request (Receipt F to P)**

| Prerequisite: 69/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - antenna switch single bearer request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0000'B | |
| 3 | spr | 7.2.5.5 | m | | '0000'B | |
| 4 | LBN | 7.2.5.5 | m | | 4 bits value | |
| 5 | param_2 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 7 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

#### A.8.4.4.2 QC - antenna switch all bearers request

**Table A.159: QC - antenna switch all bearers request (Sending P to F)**

| Prerequisite: 68/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - antenna switch all bearers request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0001'B | |
| 3 | RPN | 7.2.5.5 | m | | 8 bits value | |
| 4 | param_2 | 7.2.5.5 | m | | '0000 1111'B | |
| 5 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

**Table A.160: QC - antenna switch all bearers request (Receipt F to P)**

| Prerequisite: 69/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - antenna switch all bearers request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0001'B | |
| 3 | RPN | 7.2.5.5 | m | | 8 bits value | |
| 4 | param_2 | 7.2.5.5 | m | | '0000 1111'B | |
| 5 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

### A.8.4.4.3 QC - bearer handover request

**Table A.161: QC - bearer handover request (Sending P to F)**

| Prerequisite: 68/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0010'B | |
| 3 | spr | 7.2.5.5 | m | | '0000'B | |
| 4 | LBN | 7.2.5.5 | m | | 4 bits value | |
| 5 | RPN | 7.2.5.5 | m | | 8 bits value or '0000 0000'B | |
| 6 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 7 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

**Table A.162: QC - bearer handover request (Receipt F to P)**

| Prerequisite: 69/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0010'B | |
| 3 | spr | 7.2.5.5 | m | | '0000'B | |
| 4 | LBN | 7.2.5.5 | m | | 4 bits value | |
| 5 | RPN | 7.2.5.5 | m | | 8 bits value or '0000 0000'B | |
| 6 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 7 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

### A.8.4.4.4 QC - connection handover request

**Table A.163: QC - connection handover request (Sending P to F)**

| Prerequisite: 68/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0011'B | |
| 3 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 4 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |
| 5 | Spare 3 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 4 | 7.2.5.5 | m | | '0000 1111'B | |

**Table A.164: QC - connection handover request (Receipt F to P)**

| Prerequisite: 69/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0011'B | |
| 3 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 4 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |
| 5 | Spare 3 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 4 | 7.2.5.5 | m | | '0000 1111'B | |

### A.8.4.4.5 QC - frequency control single bearer request

**Table A.165: QC - frequency control single bearer request (Sending P to F)**

| Prerequisite: 68/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - frequency control single bearer request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0100'B | |
| 3 | spr | 7.2.5.5 | m | | '0000'B | |
| 4 | LBN | 7.2.5.5 | m | | 4 bits value | |
| 5 | Frequency error | 7.2.5.5 | m | | 8 bits signed value | |
| 6 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 7 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

**Table A.166: QC - frequency control single bearer request (Receipt F to P)**

| Prerequisite: 69/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - frequency control single bearer request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0100'B | |
| 3 | spr | 7.2.5.5 | m | | '0000'B | |
| 4 | LBN | 7.2.5.5 | m | | 4 bits value | |
| 5 | Frequency error | 7.2.5.5 | m | | 8 bits signed value | |
| 6 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 7 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

### A.8.4.4.6 QC - frequency control all bearers request

**Table A.167: QC - frequency control all bearers request (Sending P to F)**

| Prerequisite: 68/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - frequency control all bearers request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0101'B | |
| 3 | RPN | 7.2.5.5 | m | | 8 bits value | |
| 4 | Frequency error | 7.2.5.5 | m | | 8 bits signed value | |
| 5 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

**Table A.168: QC - frequency control all bearers request (Receipt F to P)**

| Prerequisite: 69/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **QC - frequency control all bearers request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.5 | m | | '0011'B | |
| 2 | Command | 7.2.5.5 | m | | '0101'B | |
| 3 | RPN | 7.2.5.5 | m | | 8 bits value | |
| 4 | Frequency error | 7.2.5.5 | m | | 8 bits signed value | |
| 5 | Spare 1 | 7.2.5.5 | m | | '0000 1111'B | |
| 6 | Spare 2 | 7.2.5.5 | m | | '0000 1111'B | |

### A.8.4.5 Broadcast and connectionless (BCL) messages

#### A.8.4.5.1 BCL - CLF, first of 2 transmissions, half slot

**Table A.169: BCL - CLF, first of 2 transmissions, half slot (Sending P to F)**

| Prerequisite: 70/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - CLF, first of 2 transmissions, half slot** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '0000'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.2 BCL - CLF, first of 2 transmissions, full slot

**Table A.170: BCL - CLF first of 2 transmissions, full slot (Sending P to F)**

| Prerequisite: 70/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - CLF first of 2 transmissions, full slot** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '0001'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.3 BCL - CLF, first of 2 transmissions, double slot

**Table A.171: BCL - CLF first of 2 transmissions, double slot (Sending P to F)**

| Prerequisite: 70/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - CLF first of 2 transmissions, double slot** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '0010'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.4 BCL - CLF, last transmissions, half slot

**Table A.172: BCL - CLF, last transmissions, half slot (Sending P to F)**

| Prerequisite: 70/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - CLF, last transmissions, half slot** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '0100'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.5 BCL - CLF, last transmissions, full slot

**Table A.173: BCL - CLF, last transmissions, full slot (Sending P to F)**

| Prerequisite: 70/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - CLF, last transmissions, full slot** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '0101'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.6 BCL - CLF, last transmissions, double slot

**Table A.174: BCL - CLF, last transmissions, double slot (Sending P to F)**

| Prerequisite: 70/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - CLF, last transmissions, double slot** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '0110'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.7 BCL - C/L single transmissions, no CF or CLS

**Table A.175: BCL - C/L single transmissions, no CF or CLS (Sending P to F)**

| Prerequisite: 70/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - C/L single transmissions, no CF or CLS** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '1000'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.8 BCL - CLS service, first transmissions

**Table A.176: BCL - CLS service, first transmission (Sending P to F)**

| Prerequisite: 70/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - CLS service, first transmissions** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '1001'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.9 BCL - change dummy bearer position

**Table A.177: BCL - change dummy bearer position (Sending P to F)**

| Prerequisite: 70/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - change dummy bearer position** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '1100'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.10 BCL - extended system info., A-field procedure

**Table A.178: BCL - extended system info., A-field procedure (Sending P to F)**

| Prerequisite: 70/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - extended system info., A-field procedure** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '1110'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

**Table A.179: BCL - extended system info., A-field procedure (Receipt F to P)**

| Prerequisite: 71/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - extended system info., A-field procedure** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '1110'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

#### A.8.4.5.11 BCL - extended system info., B-field procedure

**Table A.180: BCL - extended system info., B-field procedure (Sending P to F)**

| Prerequisite: 70/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - extended system info., B-field procedure** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '1111'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

**Table A.181: BCL - extended system info., B-field procedure (Receipt F to P)**

| Prerequisite: 71/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **BCL - extended system info., B-field procedure** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.6 | m | | '0100'B | |
| 2 | Command | 7.2.5.6 | m | | '1111'B | |
| 3 | FMID | 7.2.5.6 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.6 | m | | 20 bits value | |

### A.8.4.6 Encryption control (EC) messages

#### A.8.4.6.1 EC - Encryption start

**Table A.182: EC - Encryption start request (Sending P to F)**

| Prerequisite: 72/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC- Encryption start** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0000'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.183: EC - Encryption start request (Receipt F to P)**

| Prerequisite: 73/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC- Encryption start** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0000'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.184: EC - Encryption start grant(Sending P to F)**

| Prerequisite: 72/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC- Encryption start** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0010'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.185: EC - Encryption start grant(Receipt F to P)**

| Prerequisite: 73/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC- Encryption start** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0010'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.186: EC - Encryption start confirm (Sending P to F)**

| Prerequisite: 72/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC- Encryption start** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0001'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.187: EC - Encryption start confirm (Receipt F to P)**

| Prerequisite: 73/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC- Encryption start** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0001'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

### A.8.4.6.2 EC - Encryption stop

**Table A.188: EC - Encryption stop request (Sending P to F)**

| Prerequisite: 72/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC - Encryption stop** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0100'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.189: EC - Encryption stop request (Receipt F to P)**

| Prerequisite: 73/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC - Encryption stop** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0100'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.190: EC - Encryption stop grant (Sending P to F)**

| Prerequisite: 72/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC - Encryption stop** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0110'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.191: EC - Encryption stop grant (Receipt F to P)**

| Prerequisite: 73/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC - Encryption stop** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0110'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.192: EC - Encryption stop confirm (Sending P to F)**

| Prerequisite: 72/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC - Encryption stop** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0101'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

**Table A.193: EC - Encryption stop confirm (Receipt F to P)**

| Prerequisite: 73/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **EC - Encryption stop** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.7 | m | | '0101'B | |
| 2 | Command | 7.2.5.7 | m | | '0101'B | |
| 3 | FMID | 7.2.5.7 | m | | 12 bits value | |
| 4 | PMID | 7.2.5.7 | m | | 20 bits value | |

### A.8.4.7 $M_T$ message - B - field setup

**Table A.194: $M_T$ message - B - field setup (Sending P to F)**

| Prerequisite: 60/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$M_T$ message - B - field setup** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.8 | m | | '0110'B | |
| 2 | 36 LSB bits of RFPI | 7.2.5.8 | m | | 36 bits value | |

### A.8.4.8 $M_T$ message - Escape

**Table A.195: $M_T$ message - Escape (Sending P to F)**

| Prerequisite: 60/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$M_T$ message - Escape** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.9 | m | | '0111'B | |
| 2 | Proprietary info. | 7.2.5.9 | m | | 36 bits value | |

**Table A.196: $M_T$ message - Escape (Receipt F to P)**

| Prerequisite: 61/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$M_T$ message - Escape** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.9 | m | | '0111'B | |
| 2 | Proprietary info. | 7.2.5.9 | m | | 36 bits value | |

### A.8.4.9 $M_T$ message - TARI

**Table A.197: $M_T$ message - TARI request (Sending P to F)**

| Prerequisite: 60/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$M_T$ message - TARI** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.10 | m | | '1000'B | |
| 2 | 36 bits field | 7.2.5.10 | m | | TARI | |

**Table A.198: $M_T$ message - TARI reply (Receipt F to P)**

| Prerequisite: 61/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **$M_T$ message - TARI** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_T$ header | 7.2.5.10 | m | | '1000'B | |
| 2 | 36 bits field | 7.2.5.10 | m | | TARI | |

### A.8.5 B - Field Messages

#### A.8.5.1 B - Field - Advanced CC messages

##### A.8.5.1.1 B-field Advanced CC - Access request

**Table A.199: B-field Advanced CC - Access request (Sending P to F)**

| Prerequisite: 76/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0000'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.200: B-field Advanced CC - Access request (Receipt F to P)**

| Prerequisite: 77/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0000'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.2 B-field Advanced CC - Bearer handover request

**Table A.201: B-field Advanced CC - Bearer handover request (Sending P to F)**

| Prerequisite: 76/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0001'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.202: B-field Advanced CC - Bearer handover request (Receipt F to P)**

| Prerequisite: 77/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bearer handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0001'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.3 B-field Advanced CC - Connection handover request

**Table A.203: B-field Advanced CC - Connection handover request (Sending P to F)**

| Prerequisite: 76/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Connection handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0010'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.204: B-field Advanced CC - Connection handover request (Receipt F to P)**

| Prerequisite: 77/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Connection handover request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0010'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.4 B-field Advanced CC - Unconfirmed access request

**Table A.205: B-field Advanced CC - Unconfirmed access request (Sending P to F)**

| Prerequisite: 76/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Unconfirmed access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0011'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.206: B-field Advanced CC - Unconfirmed access request (Receipt F to P)**

| Prerequisite: 77/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Unconfirmed access request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0011'B | |
| 3 | FMID | 7.3.3.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.2 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.2 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.2 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.2 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.2 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.2 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.2 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.2 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.5 B-field Advanced CC - Bearer confirm

**Table A.207: B-field Advanced CC - Bearer confirm (Sending P to F)**

| Prerequisite: 76/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bearer confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0100'B | |
| 3 | FMID | 7.3.3.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.3 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.3 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.3 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.3 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.3 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.3 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.3 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.3 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.208: B-field Advanced CC - Bearer confirm (Receipt F to P)**

| Prerequisite: 77/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bearer confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0100'B | |
| 3 | FMID | 7.3.3.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.3 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.3 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.3 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.3 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.3 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.3 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.3 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.3 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.6 B-field Advanced CC - Wait

**Table A.209: B-field Advanced CC - Wait (Sending P to F)**

| Prerequisite: 76/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Wait** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0101'B | |
| 3 | FMID | 7.3.3.4 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.4 | m | | 20 bits value or '1111 0000 1111 0000 1111'B | |
| 5 | Spare | 7.3.3.4 | m | | '0000 1111 0000 1111 0000 1111'B | |

**Table A.210: B-field Advanced CC - Wait (Receipt F to P)**

| Prerequisite: 77/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Wait** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0101'B | |
| 3 | FMID | 7.3.3.4 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.4 | m | | 20 bits value or '1111 0000 1111 0000 1111'B | |
| 5 | Spare | 7.3.3.4 | m | | '0000 1111 0000 1111 0000 1111'B | |

### A.8.5.1.7 B-field Advanced CC - Attributes_B request

**Table A.211: B-field Advanced CC - Attributes_B request (Sending P to F)**

| Prerequisite: 76/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Attributes_B request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0110'B | |
| 3 | FMID | 7.3.3.5 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.5 | m | | 20 bits value | |
| 5 | Spare | 7.3.3.5 | m | | '0000 1111'B | |
| 6 | Connection type | 7.3.3.5 | m | | '00'B .. '11'B | |
| 7 | Service type | 7.3.3.5 | m | | '000'B .. '100'B | |
| 8 | Maximum lifetime | 7.3.3.5 | m | | 3 bits value | |
| 9 | Slot type | 7.3.3.5 | m | | '0000'B .. '0010'B | |
| 10 | Spr | 7.3.3.5 | m | | '1111'B | |

Note to item 8: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.212: B-field Advanced CC - Attributes_B request (Receipt F to P)**

| Prerequisite: 77/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Attributes_B request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0110'B | |
| 3 | FMID | 7.3.3.5 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.5 | m | | 20 bits value | |
| 5 | Spare | 7.3.3.5 | m | | '0000 1111'B | |
| 6 | Connection type | 7.3.3.5 | m | | '00'B .. '11'B | |
| 7 | Service type | 7.3.3.5 | m | | '000'B .. '100'B | |
| 8 | Maximum lifetime | 7.3.3.5 | m | | 3 bits value | |
| 9 | Slot type | 7.3.3.5 | m | | '0000'B .. '0010'B | |
| 10 | Spr | 7.3.3.5 | m | | '1111'B | |

Note to item 8: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.8 B-field Advanced CC - Attributes_B confirm

**Table A.213: B-field Advanced CC - Attributes_B confirm (Sending P to F)**

| Prerequisite: 76/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Attributes_B confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0111'B | |
| 3 | FMID | 7.3.3.5 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.5 | m | | 20 bits value | |
| 5 | Spare | 7.3.3.5 | m | | '0000 1111'B | |
| 6 | Connection type | 7.3.3.5 | m | | '00'B .. '11'B | |
| 7 | Service type | 7.3.3.5 | m | | '000'B .. '100'B | |
| 8 | Maximum lifetime | 7.3.3.5 | m | | 3 bits value | |
| 9 | Slot type | 7.3.3.5 | m | | '0000'B .. '0010'B | |
| 10 | Spr | 7.3.3.5 | m | | '1111'B | |

Note to item 8: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.214: B-field Advanced CC - Attributes_B confirm (Receipt F to P)**

| Prerequisite: 77/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Attributes_B confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '0111'B | |
| 3 | FMID | 7.3.3.5 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.5 | m | | 20 bits value | |
| 5 | Spare | 7.3.3.5 | m | | '0000 1111'B | |
| 6 | Connection type | 7.3.3.5 | m | | '00'B .. '11'B | |
| 7 | Service type | 7.3.3.5 | m | | '000'B .. '100'B | |
| 8 | Maximum lifetime | 7.3.3.5 | m | | 3 bits value | |
| 9 | Slot type | 7.3.3.5 | m | | '0000'B .. '0010'B | |
| 10 | Spr | 7.3.3.5 | m | | '1111'B | |

Note to item 8: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.9 B-field Advanced CC - Bandwidth_B request

**Table A.215: B-field Advanced CC - Bandwidth_B request (Sending P to F)**

| Prerequisite: 76/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bandwidth_B request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1000'B | |
| 3 | FMID | 7.3.3.6 | m | | 12 bits value | |
| 4 | Spr 1 | 7.3.3.6 | m | | '1111 0000 1111'B | |
| 5 | Spr 2 | 7.3.3.6 | m | | '000'B | |
| 6 | Minimum no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 7 | Spr 3 | 7.3.3.6 | m | | '000'B | |
| 8 | Taget no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 9 | Spr 4 | 7.3.3.6 | m | | '000'B | |
| 10 | Minimum no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 11 | Spr 5 | 7.3.3.6 | m | | '000'B | |
| 12 | Taget no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |

**Table A.216: B-field Advanced CC - Bandwidth_B request (Receipt F to P)**

| Prerequisite: 77/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bandwidth_B request** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1000'B | |
| 3 | FMID | 7.3.3.6 | m | | 12 bits value | |
| 4 | Spr 1 | 7.3.3.6 | m | | '1111 0000 1111'B | |
| 5 | Spr 2 | 7.3.3.6 | m | | '000'B | |
| 6 | Minimum no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 7 | Spr 3 | 7.3.3.6 | m | | '000'B | |
| 8 | Taget no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 9 | Spr 4 | 7.3.3.6 | m | | '000'B | |
| 10 | Minimum no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 11 | Spr 5 | 7.3.3.6 | m | | '000'B | |
| 12 | Taget no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |

#### A.8.5.1.10 B-field Advanced CC - Bandwidth_B confirm

**Table A.217: B-field Advanced CC - Bandwidth_B confirm (Sending P to F)**

| Prerequisite: 76/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bandwidth_B confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1001'B | |
| 3 | FMID | 7.3.3.6 | m | | 12 bits value | |
| 4 | Spr 1 | 7.3.3.6 | m | | '1111 0000 1111'B | |
| 5 | Spr 2 | 7.3.3.6 | m | | '000'B | |
| 6 | Minimum no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 7 | Spr 3 | 7.3.3.6 | m | | '000'B | |
| 8 | Taget no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 9 | Spr 4 | 7.3.3.6 | m | | '000'B | |
| 10 | Minimum no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 11 | Spr 5 | 7.3.3.6 | m | | '000'B | |
| 12 | Taget no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |

**Table A.218: B-field Advanced CC - Bandwidth_B confirm (Receipt F to P)**

| Prerequisite: 77/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Bandwidth_B confirm** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1001'B | |
| 3 | FMID | 7.3.3.6 | m | | 12 bits value | |
| 4 | Spr 1 | 7.3.3.6 | m | | '1111 0000 1111'B | |
| 5 | Spr 2 | 7.3.3.6 | m | | '000'B | |
| 6 | Minimum no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 7 | Spr 3 | 7.3.3.6 | m | | '000'B | |
| 8 | Taget no. of uplink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 9 | Spr 4 | 7.3.3.6 | m | | '000'B | |
| 10 | Minimum no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |
| 11 | Spr 5 | 7.3.3.6 | m | | '000'B | |
| 12 | Taget no. of downlink simplex bearers | 7.3.3.6 | m | | '00000'B .. '11110'B | |

### A.8.5.1.11 B-field Advanced CC - Channel List

**Table A.219: B-field Advanced CC - Channel List (Sending P to F)**

| Prerequisite: 76/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Channel List** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1010'B | |
| 3 | RPN | 7.3.3.7 | m | | 8 bits value | |
| 4 | 1st: Command | 7.3.3.7 | m | | '000'B .. '111'B | |
| 5 | 1st: S/D-flag | 7.3.3.7 | m | | '0'B, '1'B | |
| 6 | 1st: Slot number | 7.3.3.7 | m | | '0000'B .. '1011'B | |
| 7 | 1st: Start position | 7.3.3.7 | m | | '00'B, '10'B | |
| 8 | 1st: Carrier number | 7.3.3.7 | m | | '000000'B .. '001001'B | |
| 9 | 2nd: Command | 7.3.3.7 | m | | '000'B .. '111'B | |
| 10 | 2nd: S/D-flag | 7.3.3.7 | m | | '0'B, '1'B | |
| 11 | 2nd: Slot number | 7.3.3.7 | m | | '0000'B .. '1011'B | |
| 12 | 2nd: Start position | 7.3.3.7 | m | | '00'B, '10'B | |
| 13 | 2nd: Carrier number | 7.3.3.7 | m | | '000000'B .. '001001'B | |
| 14 | 3rd: Command | 7.3.3.7 | m | | '000'B .. '111'B | |
| 15 | 3rd: S/D-flag | 7.3.3.7 | m | | '0'B, '1'B | |
| 16 | 3rd: Slot number | 7.3.3.7 | m | | '0000'B .. '1011'B | |
| 17 | 3rd: Start position | 7.3.3.7 | m | | '00'B, '10'B | |
| 18 | 3rd: Carrier number | 7.3.3.7 | m | | '000000'B .. '001001'B | |

**Table A.220: B-field Advanced CC - Channel List (Receipt F to P)**

| Prerequisite: 77/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Channel List** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1010'B | |
| 3 | RPN | 7.3.3.7 | m | | 8 bits value | |
| 4 | 1st: Command | 7.3.3.7 | m | | '000'B .. '111'B | |
| 5 | 1st: S/D-flag | 7.3.3.7 | m | | '0'B, '1'B | |
| 6 | 1st: Slot number | 7.3.3.7 | m | | '0000'B .. '1011'B | |
| 7 | 1st: Start position | 7.3.3.7 | m | | '00'B, '10'B | |
| 8 | 1st: Carrier number | 7.3.3.7 | m | | '000000'B .. '001001'B | |
| 9 | 2nd: Command | 7.3.3.7 | m | | '000'B .. '111'B | |
| 10 | 2nd: S/D-flag | 7.3.3.7 | m | | '0'B, '1'B | |
| 11 | 2nd: Slot number | 7.3.3.7 | m | | '0000'B .. '1011'B | |
| 12 | 2nd: Start position | 7.3.3.7 | m | | '00'B, '10'B | |
| 13 | 2nd: Carrier number | 7.3.3.7 | m | | '000000'B .. '001001'B | |
| 14 | 3rd: Command | 7.3.3.7 | m | | '000'B .. '111'B | |
| 15 | 3rd: S/D-flag | 7.3.3.7 | m | | '0'B, '1'B | |
| 16 | 3rd: Slot number | 7.3.3.7 | m | | '0000'B .. '1011'B | |
| 17 | 3rd: Start position | 7.3.3.7 | m | | '00'B, '10'B | |
| 18 | 3rd: Carrier number | 7.3.3.7 | m | | '000000'B .. '001001'B | |

#### A.8.5.1.12 B-field Advanced CC - Unconfirmed_Dummy

**Table A.221: B-field Advanced CC - Unconfirmed_Dummy (Sending P to F)**

| Prerequisite: 76/12 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Unconfirmed_Dummy** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1011'B | |
| 3 | FMID | 7.3.3.8 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.8 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.8 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.8 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.8 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.8 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.8 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.8 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.8 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.222: B-field Advanced CC - Unconfirmed_Dummy (Receipt F to P)**

| Prerequisite: 77/12 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Unconfirmed_Dummy** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1011'B | |
| 3 | FMID | 7.3.3.8 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.8 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.8 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.8 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.8 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.8 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.8 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.8 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.8 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.13 B-field Advanced CC - Unconfirmed_Handover

**Table A.223: B-field Advanced CC - Unconfirmed_Handover (Sending P to F)**

| Prerequisite: 76/13 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Unconfirmed_Handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1100'B | |
| 3 | FMID | 7.3.3.9 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.9 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.9 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.9 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.9 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.9 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.9 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.9 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.9 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

**Table A.224: B-field Advanced CC - Unconfirmed_Handover (Receipt F to P)**

| Prerequisite: 77/13 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Unconfirmed_Handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1100'B | |
| 3 | FMID | 7.3.3.9 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.9 | m | | 20 bits value | |
| 5 | ECN | 7.3.3.9 | m | | 4 bits value | |
| 6 | LBN | 7.3.3.9 | m | | 4 bits value | |
| 7 | Connection type | 7.3.3.9 | m | | '00'B .. '11'B | |
| 8 | Service type | 7.3.3.9 | m | | '000'B .. '100'B | |
| 9 | Maximum lifetime | 7.3.3.9 | m | | 3 bits value | |
| 10 | Slot type | 7.3.3.9 | m | | '0000'B .. '0010'B | |
| 11 | Spr | 7.3.3.9 | m | | '1111'B | |

Note to item 9: Unless the service is $I_P$_error_correction, this parameter is set to '000'.

#### A.8.5.1.14 B-field Advanced CC - Release

**Table A.225: B-field Advanced CC - Release (Sending P to F)**

| Prerequisite: 76/14 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Release** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1111'B | |
| 3 | FMID | 7.3.3.10 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.10 | m | | 20 bits value | |
| 5 | Spr | 7.3.3.10 | m | | '0000'B | |
| 6 | LBN | 7.3.3.10 | m | | 4 bits value | |
| 7 | Spare | 7.3.3.10 | m | | '0000 1111'B | |
| 8 | Reason | 7.3.3.10 | m | | '0000 0000'B .. '0000 1101'B | |

**Table A.226: B-field Advanced CC - Release (Receipt F to P)**

| Prerequisite: 77/14 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field Advanced CC - Release** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X001'B | |
| 2 | Command | 7.3.3.1 | m | | '1111'B | |
| 3 | FMID | 7.3.3.10 | m | | 12 bits value | |
| 4 | PMID | 7.3.3.10 | m | | 20 bits value | |
| 5 | Spr | 7.3.3.10 | m | | '0000'B | |
| 6 | LBN | 7.3.3.10 | m | | 4 bits value | |
| 7 | Spare | 7.3.3.10 | m | | '0000 1111'B | |
| 8 | Reason | 7.3.3.10 | m | | '0000 0000'B .. '0000 1101'B | |

### A.8.5.2 B-field - Null Messages (NM)

#### A.8.5.2.1 B-field - NM No $C_F$ or $CL_F$ data in the B-field

**Table A.227: B-field - NM No $C_F$ or $CL_F$ data in the B-field (Sending P to F)**

| Prerequisite: 78/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM No $C_F$ or $CL_F$ data in the B-field** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0000'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.228: B-field - NM No $C_F$ or $CL_F$ data in the B-field (Receipt F to P)**

| Prerequisite: 79/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM No $C_F$ or $CL_F$ data in the B-field** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0000'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

### A.8.5.2.2 B-field - NM One B-subfield contains $C_F$ or $CL_F$ data

**Table A.229: B-field - NM One B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM One B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0001'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.230: B-field - NM One B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM One B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0001'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

#### A.8.5.2.3 B-field - NM Two B-subfield contain $C_F$ or $CL_F$ data

**Table A.231: B-field - NM Two B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Two B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0010'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.232: B-field - NM Two B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Two B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0010'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

#### A.8.5.2.4 B-field - NM Three B-subfield contain $C_F$ or $CL_F$ data

**Table A.233: B-field - NM Three B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Three B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0011'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.234: B-field - NM Three B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Three B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0011'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

### A.8.5.2.5 B-field - NM Four B-subfield contain $C_F$ or $CL_F$ data

**Table A.235: B-field - NM Four B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Four B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0100'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.236: B-field - NM Four B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Four B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0100'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

#### A.8.5.2.6 B-field - NM Five B-subfield contain $C_F$ or $CL_F$ data

**Table A.237: B-field - NM Five B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Five B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0101'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.238: B-field - NM Five B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Five B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0101'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

#### A.8.5.2.7 B-field - NM Six B-subfield contain $C_F$ or $CL_F$ data

**Table A.239: B-field - NM Six B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Six B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0110'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.240: B-field - NM Six B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Six B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0110'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

### A.8.5.2.8 B-field - NM Seven B-subfield contain $C_F$ or $CL_F$ data

**Table A.241: B-field - NM Seven B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Seven B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0111'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.242: B-field - NM Seven B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Seven B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '0111'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

### A.8.5.2.9 B-field - NM Eight B-subfield contain $C_F$ or $CL_F$ data

**Table A.243: B-field - NM Eight B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Eight B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '1000'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.244: B-field - NM Eight B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Eight B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '1000'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

### A.8.5.2.10 B-field - NM Nine B-subfield contain $C_F$ or $CL_F$ data

**Table A.245: B-field - NM Nine B-subfield contains $C_F$ or $CL_F$ data (Sending P to F)**

| Prerequisite: 78/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Nine B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '1000'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

**Table A.246: B-field - NM Nine B-subfield contains $C_F$ or $CL_F$ data (Receipt F to P)**

| Prerequisite: 79/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field - NM Nine B-subfield contains $C_F$ or $CL_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X010'B | |
| 2 | NCF | 7.3.4 | m | | '1000'B | |
| 3 | Spare 1 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 4 | Spare 2 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 5 | Spare 3 | 7.3.4 | m | | '0000 1111 0000 1111'B | |
| 6 | Spare 4 | 7.3.4 | m | | '0000 1111'B | |

### A.8.5.3 B - Field - Quality control (QC) messages

#### A.8.5.3.1 B - Field - QC Antenna switch single bearer

**Table A.247: B-field QC - Antenna switch single bearer (Sending P to F)**

| Prerequisite: 80/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Antenna switch single bearer** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0000'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Spr | 7.3.5.2 | m | | '0000'B | |
| 6 | LBN | 7.3.5.2 | m | | 4 bits value | |
| 7 | Param 2 | 7.3.5.2 | m | | '0000 1111'B | |
| 8 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

**Table A.248: B-field QC - Antenna switch single bearer (Receipt F to P)**

| Prerequisite: 81/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Antenna switch single bearer** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0000'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Spr | 7.3.5.2 | m | | '0000'B | |
| 6 | LBN | 7.3.5.2 | m | | 4 bits value | |
| 7 | Param 2 | 7.3.5.2 | m | | '0000 1111'B | |
| 8 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

#### A.8.5.3.2 B - Field - QC Antenna switch all bearers

**Table A.249: B-field QC - Antenna switch all bearers (Sending P to F)**

| Prerequisite: 80/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Antenna switch all bearers** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0001'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | RPN | 7.3.5.2 | m | | 8 bits value | |
| 6 | Param 2 | 7.3.5.2 | m | | '0000 1111'B | |
| 7 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

**Table A.250: B-field QC - Antenna switch all bearers (Receipt F to P)**

| Prerequisite: 81/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Antenna switch all bearers** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0001'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | RPN | 7.3.5.2 | m | | 8 bits value | |
| 6 | Param 2 | 7.3.5.2 | m | | '0000 1111'B | |
| 7 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

#### A.8.5.3.3 B - Field - QC Bearer handover

**Table A.251: B-field QC - Bearer handover (Sending P to F)**

| Prerequisite: 80/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Bearer handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0010'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Spr | 7.3.5.2 | m | | '0000'B | |
| 6 | LBN | 7.3.5.2 | m | | 4 bits value | |
| 7 | RPN | 7.3.5.2 | m | | 8 bits value or '0000 0000'B | |
| 8 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

**Table A.252: B-field QC - Bearer handover (Receipt F to P)**

| Prerequisite: 81/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Bearer handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0010'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Spr | 7.3.5.2 | m | | '0000'B | |
| 6 | LBN | 7.3.5.2 | m | | 4 bits value | |
| 7 | RPN | 7.3.5.2 | m | | 8 bits value or '0000 0000'B | |
| 8 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

### A.8.5.3.4 B - Field - QC Connection handover

**Table A.253: B - Field - QC Connection handover (Sending P to F)**

| Prerequisite: 80/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Connection handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0011'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Param 1 | 7.3.5.2 | m | | '0000 1111'B | |
| 6 | Param 2 | 7.3.5.2 | m | | '0000 1111'B | |
| 7 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

**Table A.254: B - Field - QC Connection handover (Receipt F to P)**

| Prerequisite: 81/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Connection handover** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0011'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Param 1 | 7.3.5.2 | m | | '0000 1111'B | |
| 6 | Param 2 | 7.3.5.2 | m | | '0000 1111'B | |
| 7 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

#### A.8.5.3.5 B - Field - QC Frequency control single bearer

**Table A.255: B-field QC - Frequency control single bearer (Sending P to F)**

| Prerequisite: 80/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Frequency control single bearer** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0100'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Spr | 7.3.5.2 | m | | '0000'B | |
| 6 | LBN | 7.3.5.2 | m | | 4 bits value | |
| 7 | Frequency error | 7.3.5.2 | m | | 8 bits signed value | |
| 8 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

**Table A.256: B-field QC - Frequency control single bearer (Receipt F to P)**

| Prerequisite: 81/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Frequency control single bearer** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0100'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | Spr | 7.3.5.2 | m | | '0000'B | |
| 6 | LBN | 7.3.5.2 | m | | 4 bits value | |
| 7 | Frequency error | 7.3.5.2 | m | | 8 bits signed value | |
| 8 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

#### A.8.5.3.6 B - Field - QC Frequency control all bearers

**Table A.257: B-field QC - Frequency control all bearers (Sending P to F)**

| Prerequisite: 80/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Frequency control all bearers** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0101'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | RPN | 7.3.5.2 | m | | 8 bits value | |
| 6 | Frequency error | 7.3.5.2 | m | | 8 bits signed value | |
| 7 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

**Table A.258: B-field QC - Frequency control all bearers (Receipt F to P)**

| Prerequisite: 81/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B-field QC - Frequency control all bearers** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '0101'B | |
| 3 | FMID | 7.3.5.2 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.2 | m | | 20 bits value | |
| 5 | RPN | 7.3.5.2 | m | | 8 bits value | |
| 6 | Frequency error | 7.3.5.2 | m | | 8 bits signed value | |
| 7 | Spare | 7.3.5.2 | m | | '0000 1111'B | |

### A.8.5.3.7 B - Field - QC Reset request first TDMA half frame

**Table A.259: B - Field - QC Reset request first TDMA half frame (Sending P to F)**

| Prerequisite: 80/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset request first TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0001'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

**Table A.260: B - Field - QC Reset request first TDMA half frame (Receipt F to P)**

| Prerequisite: 81/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset request first TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0001'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

#### A.8.5.3.8 B - Field - QC Reset request second TDMA half frame

**Table A.261: B - Field - QC Reset request second TDMA half frame (Sending P to F)**

| Prerequisite: 80/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset request second TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0010'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

**Table A.262: B - Field - QC Reset request second TDMA half frame (Receipt F to P)**

| Prerequisite: 81/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset request second TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0010'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

#### A.8.5.3.9 B - Field - QC Reset request both TDMA half frames

**Table A.263: B - Field - QC Reset request both TDMA half frame (Sending P to F)**

| Prerequisite: 80/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset request both TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0011'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

**Table A.264: B - Field - QC Reset request both TDMA half frame (Receipt F to P)**

| Prerequisite: 81/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset request both TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0011'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

### A.8.5.3.10 B - Field - QC Reset confirm first TDMA half frame

**Table A.265: B - Field - QC Reset confirm first TDMA half frame (Sending P to F)**

| Prerequisite: 80/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset confirm first TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0101'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

**Table A.266: B - Field - QC Reset confirm first TDMA half frame (Receipt F to P)**

| Prerequisite: 81/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset confirm first TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0101'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

#### A.8.5.3.11 B - Field - QC Reset confirm second TDMA half frame

**Table A.267: B - Field - QC Resetconfirm second TDMA half frame (Sending P to F)**

| Prerequisite: 80/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset confirm second TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0110'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

**Table A.268: B - Field - QC Resetconfirm second TDMA half frame (Receipt F to P)**

| Prerequisite: 81/11 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset confirm second TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0110'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

#### A.8.5.3.12 B - Field - QC Reset confirm both TDMA half frames

**Table A.269: B - Field - QC Reset confirm both TDMA half frame (Sending P to F)**

| Prerequisite: 80/12 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset confirm both TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0111'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

**Table A.270: B - Field - QC Reset confirm both TDMA half frame (Receipt F to P)**

| Prerequisite: 81/12 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC Reset confirm both TDMA half frame** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1110'B | |
| 3 | FMID | 7.3.5.3 | m | | 12 bits value | |
| 4 | PMID | 7.3.5.3 | m | | 20 bits value | |
| 5 | Control | 7.3.5.3 | m | | '0111'B | |
| 6 | LBN | 7.3.5.3 | m | | 4 bits value | |
| 7 | Spare 1 | 7.3.5.3 | m | | '0000 1111'B | |
| 8 | Spare 2 | 7.3.5.3 | m | | '0000 1111'B | |

### A.8.5.3.13 B - Field - QC MOD2 ACK

**Table A.271: B - Field - QC MOD2 ACK (Sending P to F)**

| Prerequisite: 80/13 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC MOD2 ACK** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1111'B | |
| 3 | First half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK | 7.3.5.4 | m | | 28 bits value | |
| 4 | Second half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK | 7.3.5.4 | m | | 28 bits value | |

**Table A.272: B - Field - QC MOD2 ACK (Receipt F to P)**

| Prerequisite: 81/13 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - QC MOD2 ACK** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X011'B | |
| 2 | Command | 7.3.3.1 | m | | '1111'B | |
| 3 | First half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK | 7.3.5.4 | m | | 28 bits value | |
| 4 | Second half of TDMA frame - LBN1 to LBN14 Q1/BCK and Q2/ACK | 7.3.5.4 | m | | 28 bits value | |

### A.8.5.4 B - Field - Extended system information (ES) messages

#### A.8.5.4.1 B - Field - ES TARI message

**Table A.273: B - Field - ES TARI message (Sending P to F)**

| Prerequisite: 74/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - ES TARI messagea** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X100'B | |
| 2 | Command | 7.3.6.1 | m | | '0000'B | |
| 3 | TARI field | 7.3.6.2 | m | | 36 bits value | |
| 4 | Spr | 7.3.6.2 | m | | '1111'B | |
| 5 | Spare | 7.3.6.2 | m | | '0000 1111 0000 1111'B | |

**Table A.274: B - Field - ES TARI message (Receipt F to P)**

| Prerequisite: 75/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - ES TARI messagea** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X100'B | |
| 2 | Command | 7.3.6.1 | m | | '0000'B | |
| 3 | TARI field | 7.3.6.2 | m | | 36 bits value | |
| 4 | Spr | 7.3.6.2 | m | | '1111'B | |
| 5 | Spare | 7.3.6.2 | m | | '0000 1111 0000 1111'B | |

### A.8.5.5 B - Field - GF-channel data packet messages

#### A.8.5.5.1 B - Field - GF-No $C_F$ data in the B-field

**Table A.275: B - Field - GF-No $C_F$ data in the B-field (Sending P to F)**

| Prerequisite: 82/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-No $C_F$ data in the B-field** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0000'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.276: B - Field - GF-No $C_F$ data in the B-field (Receipt F to P)**

| Prerequisite: 83/1 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-No $C_F$ data in the B-field** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0000'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

### A.8.5.5.2 B - Field - GF-One B-subfield contains $C_F$ data

**Table A.277: B - Field - GF-One B-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-One B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0001'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.278: B - Field - GF-One B-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/2 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-One B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0001'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

### A.8.5.5.3 B - Field - GF-Two B-subfield contain $C_F$ data

**Table A.279: B - Field - GF-Two B-subfield contain $C_F$ data (Sending P to F)**

| Prerequisite: 82/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Two B-subfield contain $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0010'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.280: B - Field - GF-Two B-subfield contain $C_F$ data (Receipt F to P)**

| Prerequisite: 83/3 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Two B-subfield contain $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0010'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

#### A.8.5.5.4 B - Field - GF-Three B-subfield contain $C_F$ data

**Table A.281: B - Field - GF-Three B-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Three B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0011'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.282: B - Field - GF-Three B-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/4 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Three B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0011'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

#### A.8.5.5.5 B - Field - GF-Four B-subfield contain $C_F$ data

**Table A.283: B - Field - GF-Four B-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Four B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0100'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.284: B - Field - GF-Four B-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/5 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Four B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0100'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

### A.8.5.5.6 B - Field - GF-Five B-subfield contain $C_F$ data

**Table A.285: B - Field - GF-Five B-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Five B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0101'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.286: B - Field - GF-Five B-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Five B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0101'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

### A.8.5.5.7 B - Field - GF-Six B-subfield contain $C_F$ data

**Table A.287: B - Field - GF-Six B-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Six B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0110'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.288: B - Field - GF-Six B-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/7 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Six B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0110'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

#### A.8.5.5.8 B - Field - GF-Seven B-subfield contain $C_F$ data

**Table A.289: B - Field - GF-Seven B-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Seven B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0111'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.290: B - Field - GF-Seven B-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/8 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Seven B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '0111'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

#### A.8.5.5.9 B - Field - GF-Eight B-subfield contain $C_F$ data

**Table A.291: B - Field - GF-Eight B-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Eight B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '1000'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.292: B - Field - GF-Eight B-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/9 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Eight B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '1000'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

### A.8.5.5.10 B - Field - GF-Nine B-subfield contain $C_F$ data

**Table A.293: B - Field - GF-NineB-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 82/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Nine B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '1001'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

**Table A.294: B - Field - GF-NineB-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 83/10 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Nine B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X101'B | |
| 2 | NCF | 7.3.7 | m | | '1001'B | |
| 3 | GF channel SDU | 7.3.7 | m | | 56 bits value | |

### A.8.5.6 B - Field - Escape message

**Table A.295: B - Field - GF-NineB-subfield contains $C_F$ data (Sending P to F)**

| Prerequisite: 74/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Nine B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X111'B | |
| 2 | Escape information | 7.3.8 | m | | 60 bits value | |

**Table A.296: B - Field - GF-NineB-subfield contains $C_F$ data (Receipt F to P)**

| Prerequisite: 75/6 | | | | | | |
|---|---|---|---|---|---|---|
| **Item** | **B - Field - GF-Nine B-subfield contains $C_F$ data** | **Ref.** | **Status** | **Supp.** | **Value Allowed** | **Value Supported** |
| 1 | $M_{Bn}$ header | 7.3.1 | m | | 'X111'B | |
| 2 | Escape information | 7.3.8 | m | | 60 bits value | |

## History

| Document history | | | |
|---|---|---|---|
| June 1995 | Public Enquiry | PE 85: | 1995-06-05 to 1995-09-29 |
| May 1996 | Vote | V 102: | 1996-05-06 to 1996-08-09 |
| August 1996 | First Edition | | |
| | | | |
| | | | |

ISBN 2-7437-0873-5 - Edition complète
ISBN 2-7437-0882-4 - Partie 3
Dépôt légal : Août 1996