

PIC18F8722 Cheat-Sheet


Port	Use	Pin	Connection
RA	Analogue inputs	0	Rotary potentiometer
		1	(TMP36) Temp sensor
		2	LDR
	Digital outputs	4	transistor (Q ₃)
RB	Digital input	0	Push button (PB1)
RC	Digital input	2-5	Toggle Switch
RF	Digital outputs	0-7	LEDs and 7-Segment
RH	Digital outputs	0,1	Transistors (Q ₁ and Q ₂)
	Digital inputs	4-7	Toggle switches

1: hi 0: low 1: input 0: output

	LATx	TRISx
Port A	0xF89	0xF92
Port B	0xF8A	0xF93
Port C	0xF8B	0xF94
Port D	0xF8C	0xF95
Port E	0xF8D	0xF96
Port F	0xF8E	0xF97
Port G	0xF8F	0xF98
Port H	0xF90	0xF99
Port J	0xF91	0xF9A

- **MOVLW k**
↳ loads value k into W
- **MOVWF f**
↳ contents of W are copied to data memory at address f
- **MOVWF f, W**
↳ contents of Data memory f are copied into W
- **BRA inst-address**
↳ Branch/jump to specified line of code
- **ADDLW k**
↳ adds value k to the contents of W and stores output in W
- **ADDWF f, F**
↳ contents of Data location f and W are added and stored in location f
- **ADDWF f, W**
↳ contents of Data location f and W are added and stored in W
- **bgt x, b**
↳ toggle bit b in memory location x
- **bcl x, b**
↳ clear bit b in memory location f

7-segment display



b7	b6	b5	b4	b3	b2	b1	b0
128	64	32	16	8	4	2	1

Format	Prefixes	Suffixes
binary	—	B
hex	0x	h, H
octal		O, o, Q, q
Dec *		D, d,

Since radix is dec ('radix dec')
no prefix/suffix is needed