

Appendix 1

Modbus address table of Delta DVP series PLC.

Device	Range		Type	DVP address (Hex)	Modbus address (Dec)	Effective		
						ES/EX/SS	SA/SX/SC	EH
S	000~255		bit	0000~00FF	000001~000256	0~127	0~1024	0~1024
S	256~511		bit	0100~01FF	000247~000512			
S	512~767		bit	0200~02FF	000513~000768			
S	768~1023		bit	0300~03FF	000769~001024			
X	000~377		bit	0400~04FF	101025~101208	0~177	0~177	0~377
Y	000~377		bit	0500~05FF	001281~001536			
T	000~255		bit	0600~06FF	001537~001792	0~127	0~255	0~255
			Word	0600~06FF	401537~401792			
M	000~255		bit	0800~08FF	002049~002304	0~1279	0~4095	0~4095
M	256~511		bit	0900~09FF	002305~002560			
M	512~767		bit	0A00~0AFF	002561~002816			
M	768~1023		bit	0B00~0BFF	002817~003072			
M	1024~1279		bit	0C00~0CFF	003073~003328			
M	1280~1535		bit	0D00~0DFF	003329~003584			
M	1536~1791		bit	B000~B0FF	045057~045312	0~1279	0~4095	0~4095
M	1792~2047		bit	B100~B1FF	045313~045568			
M	2048~2303		bit	B200~B2FF	045569~045824			
M	2304~2559		bit	B300~B3FF	045825~046080			
M	2560~2815		bit	B400~B4FF	046081~046636			
M	2816~3071		bit	B500~B5FF	046637~046592			
M	3072~3327		bit	B600~B6FF	046593~046848			
M	3328~3583		bit	B700~B7FF	046849~047104			
M	3584~3839		bit	B800~B8FF	047105~047360			
M	3840~4095		bit	B900~B9FF	046361~047616			
C	0~199	16-bit	bit	0E00~0EC7	003585~003784	0~127	0~199	0~199
			Word	0E00~0EC7	403585~403784			
	200~255	32-bit	bit	0EC8~0EFF	003785~003840	232~255	200~255	200~255
			Dword	0EC8~0EFF	403785~403840			

Device	Range	Type	DVP address (Hex)	Modbus address (Dec)	Effective		
					ES/EX/SS	SA/SX/SC	EH
D	000~255	Word	1000~10FF	404097~404352	0~1311	0~4999	0~9999
D	256~511	Word	1100~11FF	404353~404608			
D	512~767	Word	1200~12FF	404609~404864			
D	768~1023	Word	1300~13FF	404865~405120			
D	1024~1279	Word	1400~14FF	405121~405376			
D	1280~1535	Word	1500~15FF	405377~405632			
D	1536~1791	Word	1600~16FF	405633~405888			
D	1792~2047	Word	1700~17FF	405889~406144			
D	2048~2303	Word	1800~18FF	406145~406400			
D	2304~2559	Word	1900~19FF	406401~406656			
D	2560~2815	Word	1A00~1AFF	406657~406912			
D	2816~3071	Word	1B00~1BFF	406913~407168			
D	3072~3327	Word	1C00~1CFF	407169~407424			
D	3328~3583	Word	1D00~1DFF	407425~407680			
D	3584~3839	Word	1E00~1EFF	407681~407936	0~1311	0~4999	0~9999
D	3840~4095	Word	1F00~1FFF	407937~408192			
D	4096~4351	Word	9000~90FF	408193~408448			
D	4352~4607	Word	9100~91FF	436865~437120			
D	4608~4863	Word	9200~92FF	437121~437376			
D	4864~5119	Word	9300~93FF	437377~437632			
D	5120~5375	Word	9400~94FF	437633~437888			
D	5376~5631	Word	9500~95FF	437889~438144			
D	5632~5887	Word	9600~96FF	438145~438400			
D	5888~6143	Word	9700~97FF	438401~438656			
D	6144~6399	Word	9800~98FF	438657~438912			
D	6400~6655	Word	9900~99FF	438913~439168			
D	6656~6911	Word	9A00~9AFF	439169~439424			
D	6912~7167	Word	9B00~9BFF	439425~439680			

Device	Range	Type	DVP address (Hex)	Modbus address (Dec)	Effective		
					ES/EX/SS	SA/SX/SC	EH
D	7168~7423	Word	9C00~9CFF	439937~440192	0~1311	0~4999	0~9999
D	7424~7679	Word	9D00~9DFF	440193~440448			
D	7680~7935	Word	9E00~9EFF	440449~440704			
D	7936~8191	Word	9F00~9FFF	440705~440960			
D	8192~8447	Word	A000~A0FF	440961~441216			
D	8448~8703	Word	A100~A1FF	441217~441472			
D	8704~8959	Word	A200~A2FF	441473~441728			
D	8960~9125	Word	A300~A3FF	441729~441984			
D	9126~9471	Word	A400~A4FF	441985~442240			
D	9472~9727	Word	A500~A5FF	442241~442496			
D	9728~9983	Word	A600~A6FF	442497~442752			
D	9984~9999	Word	A700~A70F	442753~443008			