

ZX-Flow: A Flexible Criterion for Deterministic Computation with ZX-Diagrams

Aleks Kissinger
University of Oxford
aleks.kissinger@ox.ac.uk

John van de Wetering
University of Amsterdam, QuSoft
john@vdwetering.name

arXiv:2603.09580v1 [quant-ph] 10 Mar 2026

Flow criteria are used to efficiently extract computations, either in the form of measurement patterns or quantum circuits, from ZX-diagrams. Existing criteria such as causal flow, generalised flow, and Pauli flow, were all originally formulated for graph states, so they require ZX-diagrams to be in a very particular graph-state-like form. This form is easily broken by applying basic ZX rules and makes establishing some desirable properties very complicated. Here, we introduce a new "ZX-native" flow criterion called ZX-flow, formulated using a new type of decoration of a ZX-diagram we call Pauli semiwebs. These are a generalisation of Pauli webs, which have recently been used extensively in reasoning about fault-tolerant computations in the ZX-calculus. We show that ZX-flow is straightforwardly preserved by all Clifford rewrites and furthermore that a ZX-diagram has ZX-flow if and only if it is Clifford-equivalent to a graph-like ZX-diagram with Pauli flow. Finally, we show that any diagram with ZX-flow can be readily interpreted either as a deterministic measurement-based computation or as a Clifford isometry followed by a sequence of Pauli exponentials. The latter can then be efficiently extracted to a quantum circuit.

1 Introduction

The ZX-calculus [8] is a graphical language for reasoning about quantum processes that has many applications in quantum computation. It allows one to represent a computation as a graph-like structure called a ZX-diagram and rewrite it according to a complete set of graphical rules [1, 29] to transform and simplify quantum computations. It has been used for instance to optimise and verify quantum circuits [9, 28, 11, 15, 27, 13], analyse parametrised quantum circuits [21, 31, 26, 25, 30], develop new constructions in measurement-based quantum computing [2, 14, 10, 20, 3], and design fault-tolerant quantum computations [32, 22, 23, 12, 4].

These methods benefit from the ZX-calculus because of its increased flexibility with respect to the standard quantum circuit notation, which allows representations of non-unitary operations including projections, ancilla preparations, measurements and post-selections. This additional flexibility does however come with a cost: when you produce a ZX-diagram representing a computation, it is usually not immediately clear how to translate this diagram into a representation that allows direct execution on quantum hardware. We have to first *extract* a circuit from the diagram. This circuit extraction problem is very hard in the most general case [5], but there are several known conditions on diagrams that allow efficient extraction of a circuit. These so-called *flow* conditions were borrowed from the field of measurement-base quantum computation (MBQC), where they were originally used to associate single-qubit measurements to certain "correction sets", which identify future measurements that can be adapted to obtain a deterministic result. The most well-known such conditions are called generalised flow and Pauli flow [7].

It turns out that these conditions also suffice to turn a ZX-diagram into a quantum circuit expressed in fixed basis of 1- and 2-qubit gates [9, 2, 24]. When optimising quantum circuits with the ZX-calculus, it is useful to preserve flow conditions to ensure that we can extract a circuit from the final, reduced