



Strong Zero Modes in Supersymmetry-Inspired Quantum Circuits

Alberto Zorzato,[1] Pietro Richelli,[2] Jiří Minář,[1] and Kareljan Schoutens[1]

[1] *Institute for Theoretical Physics, University of Amsterdam, Science Park 904, 1098 XH Amsterdam, The Netherlands*
QuSoft, Science Park 123, 1098 XG Amsterdam, The Netherlands
[2] *Kavli Institute of Nanoscience, Delft University of Technology, Lorentzweg 1, 2628 CJ, Delft, the Netherlands*

(Dated: July 14, 2026)

We investigate discrete dynamics in quantum circuits with gates corresponding to the S-matrix of a supersymmetric 1+1D quantum field theory. We show that for a brick-wall configuration such circuits support both localized and delocalized dynamically conserved operators known as strong zero modes (SZM), the number of which depends on the parameter regime. We demonstrate that, while some of the SZM remain localized at boundaries, other SZM propagate ballistically, guided by a choice of circuit parameters. Such propagation can be explained by a strong Dzyaloshinskii–Moriya term appearing in the dynamics. We describe how to exploit propagating SZM for quantum information transport and discuss the robustness to various types of noise.

arXiv:2607.11483v1 [quant-ph] 13 Jul 2026

Introduction – The rapid development of quantum hardware has stimulated a large bulk of recent work addressing different aspects of quantum dynamics. Noteworthy examples are Hamiltonian simulations and time-discretization techniques [1–3], the associated transitions to quantum chaos [4, 5], shortcuts to adiabaticity [6, 7], and random unitary quantum circuits, where gates are sampled from a probability distribution [8–14].

The known difficulty to simulate quantum dynamics on a classical computer suggests that this is a field where quantum advantage can be realized. Recent claims in this direction include the digital quantum computation of out-of-time ordered correlation functions [15] and the Hamiltonian dynamics of a transverse field Ising model using quantum annealing [16] or discretized time evolution [17] (see, however, [18, 19]).

Valuable insights on quantum dynamics can be gained if a circuit is endowed with additional structure. This is the case for dual time-unitary circuits [20] or for circuits constructed as discretized time evolutions of exactly solvable systems [21–28]. Such structure allows the derivation of analytical results for non-equilibrium steady states and correlation functions [29, 30], ballistic spin transport in Floquet setting [31] or the formulation of generalized hydrodynamics [32]. Here, the typical way of proceeding is to start from a Hamiltonian H and deriving a discrete Trotter decomposition [2, 33, 34] for its evolution operator $U(t) = e^{-iHt}$.

In this work we follow the inverse path: building on our previous results [35], we define a discrete-time evolution operator U_F by choosing the unitary scattering matrix of a (1+1)-dimensional supersymmetric quantum field theory (SUSY QFT) as the fundamental 2-qubit gate of a quantum circuit of brick-wall type, cf. Fig. 1(c). In the following we refer to U_F as the Floquet operator, although we don't study the effect of driving the system periodically. We find that such circuits feature so-called strong zero modes (SZM), which have their origin in the supersymmetry of the underlying 1+1D QFT. Typically, SZM are localized at system boundaries [36–46]. In this work we establish the existence of SZMs that propagate ballistically, guided by our choice of circuit parameters. We exploit this fact to construct protocols for routing quantum information, encoding such information in (pairs of) Majorana modes underpinning the SZM.

Strong zero modes – A working definition of SZMs was provided by Fendley [37]. In the context of quantum circuits, it assumes an evolution operator U_F, and a parity operator P. The conditions for Ψ to be a SZM read

$$[U_F, \Psi] = 0, \quad \{P, \Psi\} = 0, \quad \Psi^2 \propto 1. \tag{1}$$

The first condition states the exact conservation of such operators. We can relax this condition by requiring that the commutator vanishes exponentially in some parameter, leading to *approximate* SZM [42]. The second condition implies spectral pairing between parity-even and parity-odd states, implying that any state $|\psi\rangle$ has a partner $\Psi|\psi\rangle$ evolving with the same quasi-energy. The third property is needed for normalizability.

Fermionic quantum circuits – The central object of our protocols is a unitary scattering matrix $\check{S}(\alpha, \gamma, \theta)$, which in the original 1+1D SUSY QFT formulation describes elastic scattering of two particles (i and j) with masses $m_{i,j}$ and rapidities $\theta_{i,j}$ interacting with a strength α [35, 47], cf. Fig. 1(a). Considering two possible states at the input of the i-th channel as $|b(\theta_i)\rangle, |f(\theta_i)\rangle$ (and similarly for j), the scattering matrix can be written in the $\{|b(\theta_i)\rangle, |f(\theta_i)\rangle\} \otimes \{|b(\theta_j)\rangle, |f(\theta_j)\rangle\}$ basis, together with its coefficients:

$$\begin{aligned}
&\check{S}(\alpha, \gamma, \theta) = \\
&\frac{1}{2N}\left[\sum_{\mu=0}^{3} f^\mu X^\mu X^\mu + i(ZI + IZ) + g^+ XY + g^- YX\right], \\
&f^{0,3} = \pm\alpha \operatorname{csch}\frac{\theta}{2} + 2\alpha \cosh\frac{\gamma}{2} \operatorname{csch}\theta, \\
&f^1 = f^2 = i, \qquad g^\pm = \operatorname{sech}\frac{\theta}{2} \mp 2 \operatorname{csch}\theta \sinh\frac{\gamma}{2}, \\
&N = \sqrt{2\alpha^2(\cosh(\gamma)\operatorname{csch}^2(\theta) + \coth(\theta)\operatorname{csch}(\theta)) + 1}.
\end{aligned} \tag{2}$$

$X^\mu = I, X, Y, Z$, for $\mu = 0, \ldots, 3$, are the identity and Pauli matrices, respectively, θ is the difference of the incoming rapidities, $\theta = \theta_i - \theta_j$, and $\gamma = \log(m_i/m_j)$. Due to the elasticity of the scattering process, both the masses and the rapidities are preserved under $\check{S}$, meaning