




Signal processing techniques for efficient compilation of controlled rotations in trapped ions

Koen Groenland[1,2,*], **Freek Witteveen**[1,3], **Kareljan Schoutens**[1,2] and **Rene Gerritsma**[2]

[1] QuSoft and Centrum Wiskunde en Informatica (CWI), Science Park 123, 1098 XG Amsterdam, the Netherlands

[2] Institute of Physics, University of Amsterdam, Science Park 904, 1098 XH Amsterdam, the Netherlands

[3] Korteweg-de Vries Institute for Mathematics, University of Amsterdam, Science Park 105-107, 1098 XG Amsterdam, the Netherlands

∗ Contact: k.l.groenland@cwi.nl

arXiv:2001.05231v3 [quant-ph] 7 May 2020

Abstract: Quantum logic gates with many control qubits are essential in many quantum algorithms, but remain challenging to perform in current experiments. Trapped ion quantum computers natively feature the Mølmer-Sørensen (MS) entangling operation, which effectively applies an Ising interaction to all pairs of qubits at the same time. We consider a sequence of equal all-to-all MS operations, interleaved with single-qubit gates that act only on one special qubit. Using a connection with quantum signal processing techniques, we find that it is possible to perform an arbitray SU(2) rotation on the special qubit if and only if all other qubits are in the state $|1\rangle$. Such controlled rotation gates with $N-1$ control qubits require $2N$ applications of the MS gate, and can be mapped to a conventional Toffoli gate by demoting a single qubit to ancilla.

1. Introduction

Multiple-control gates arise in various quantum information processing tasks, ranging from basic arithmetic [1] to Grover's search method [2], which famously requires a gate that performs an inversion around just a single specific state. The prototypical example is the $\texttt{Toffoli}_N$ gate, which performs a bitflip (Pauli-X) on the *target* qubit if and only if $N-1$ *control* qubits are in the state $|1\rangle$.

Albeit conceptually simple, gates with many control qubits remain challenging to implement in current experimental quantum computers. Because single-qubit gates are typically more accurate than entangling operations, an important challenge is to decompose multiqubit operations into circuits with as few as possible two-qubit gates. To indicate, the $\texttt{Toffoli}_3$ requires at least 5 two-qubit gates [3], or when the CNOT gate is the only available entangling gate, then at least 6 CNOTs are needed [4]. For a larger number of qubits, the required number of basic operations or ancilla qubits grows steeply. The $\texttt{Toffoli}_N$ on N qubits can be constructed through a circuit of *depth* $O(\log(N))$, requiring $O(N)$ ancilla bits. With just a single ancilla, the best known circuits require $O(N)$ two-qubit gates [5–7]. If no ancillas may be used, then a quadratic number of CNOTs are required [8]. The size of these circuits has been prohibitive in scaling up quantum algorithms on current quantum computer prototypes: even though various systems with a few tens of qubits have been reported, the largest multiple-controlled gate ever performed is, to our best knowledge, the $\texttt{Toffoli}_4$ [9].