

2022–2024

arXiv:2205.05736v2 [quant-ph] 30 Oct 2023

Exact solution for the quantum and private capacities of bosonic dephasing channels

Ludovico Lami[1,2,3,4,*] and Mark M. Wilde[5,6,†]

[1]*Institut für Theoretische Physik und IQST, Universität Ulm, Albert-Einstein-Allee 11, D-89069 Ulm, Germany*
[2]*QuSoft, Science Park 123, 1098 XG Amsterdam, the Netherlands*
[3]*Korteweg–de Vries Institute for Mathematics, University of Amsterdam, Science Park 105-107, 1098 XG Amsterdam, the Netherlands*
[4]*Institute for Theoretical Physics, University of Amsterdam, Science Park 904, 1098 XH Amsterdam, the Netherlands*
[5]*Hearne Institute for Theoretical Physics, Department of Physics and Astronomy, and Center for Computation and Technology, Louisiana State University, Baton Rouge, Louisiana 70803, USA*
[6]*School of Electrical and Computer Engineering, Cornell University, Ithaca, New York 14850, USA*

(Dated: October 31, 2023)

The capacities of noisy quantum channels capture the ultimate rates of information transmission across quantum communication lines, and the quantum capacity plays a key role in determining the overhead of fault-tolerant quantum computation platforms. In the case of bosonic systems, central to many applications, no closed formulas for these capacities were known for bosonic dephasing channels, a key class of non-Gaussian channels modelling, e.g., noise affecting superconducting circuits or fiber-optic communication channels. Here we provide the first exact calculation of the quantum, private, two-way assisted quantum, and secret-key agreement capacities of all bosonic dephasing channels. We prove that that they are equal to the relative entropy of the distribution underlying the channel to the uniform distribution. Our result solves a problem that has been open for over a decade, having been posed originally by [Jiang & Chen, *Quantum and Nonlinear Optics* 244, 2010].

One of the great promises of quantum information science is that remarkable tasks can be achieved by encoding information into quantum systems [1]. In principle, algorithms executed on quantum computers can factor large integers [2], simulate complex physical dynamics [3], solve unstructured search problems with proven speedups [4], and perform linear-algebraic manipulations on large matrices encoded into quantum systems [5, 6]. Additionally, ordinary ("classical") information can be transmitted securely over quantum channels by means of quantum key distribution [7].

However, all of these possibilities are hindered in practice because all quantum systems are subject to decoherence [8]. A very simple decoherence process takes a density operator $\rho = \sum_{n,m} \rho_{nm} |n\rangle\langle m|$ to $\rho' = \sum_{n,m} \rho_{nm} e^{-\frac{\gamma}{2}(n-m)^2} |n\rangle\langle m|$, where $\gamma \geq 0$ measures the extent to which the off-diagonal elements are reduced in magnitude. This process is also called dephasing, because it reduces or eliminates relative phases. Decoherence is a ubiquitous phenomenon affecting all quantum physical systems. In fact, in various platforms for quantum computation, experimentalists employ the T2 time as a phenomenological quantity that roughly measures the time that it takes for a coherent superposition to decohere to a probabilistic mixture. Dephasing noise in some cases is considered to be the dominant source of errors affecting quantum information encoded into superconducting systems [9], as well as other platforms [10, 11]. If those systems are employed to carry out quantum computation, then the errors must be amended by means of error-correcting codes, which typically causes expensive overheads in the amount of physical qubits needed. Not only does dephasing affect quantum computers, but it also affects quantum communication systems. Indeed, temperature fluctuations [12] or Kerr non-linearities [13] in a fiber, imprecision in the path length of a fiber [14], or the lack of a common phase reference between sender and receiver [15] lead to decoherence as well, and this can affect quantum communication and key distribution schemes adversely.

Many of the aforementioned forms of decoherence can be unified under a single model, known as the bosonic dephasing channel (BDC) [16, 17]. The action of such a channel on the density operator ρ of a single-mode bosonic system is given by

$$\mathcal{N}_p(\rho) \coloneqq \int_{-\pi}^{\pi} d\phi \; p(\phi) \; e^{-ia^\dagger a \, \phi} \, \rho \, e^{ia^\dagger a \, \phi}, \tag{1}$$

where p is a probability density function on the interval $[-\pi, \pi]$ and $a^\dagger a$ is the photon number operator. Since each unitary operator $e^{-ia^\dagger a \, \phi}$ realizes a phase shift of the state ρ, the action of the channel $\mathcal{N}_p$ is to randomize the phase of this state according to the probability density p. Representing $\rho = \sum_{n,m} \rho_{nm} |n\rangle\langle m|$ in the photon number basis, it is a straightforward calculation to show that

$$\mathcal{N}_p(\rho) = \sum_{n,m} \rho_{nm} (T_p)_{nm} \, |n\rangle\langle m| \, , \tag{2}$$

where T_p is the infinite matrix with entries

$$(T_p)_{nm} \coloneqq \int_{-\pi}^{\pi} d\phi \; p(\phi) \, e^{-i\phi(n-m)}. \tag{3}$$

This channel thus generalizes the simple dephasing channel considered above. Its action preserves diagonal elements of ρ, but reduces the magnitude of the off-diagonal elements, a key signature of decoherence. As the name suggests, the BDC can be seen as a generalization to bosonic systems of the qudit dephasing channel [18].

* ludovico.lami@gmail.com
† wilde@cornell.edu