



State preparation by shallow circuits using feed forward

Harry Buhrman[1], Marten Folkertsma[1], Bruno Loff[2], and Niels M. P. Neumann[1,3]

[1]QuSoft, CWI & University of Amsterdam, Amsterdam, the Netherlands
[2]LASIGE & Department of Mathematics, University of Lisbon
[3]The Netherlands Organisation for Applied Scientific Research (TNO), Delft, the Netherlands

arXiv:2307.14840v5 [quant-ph] 4 Dec 2024

Fault tolerant quantum computers repetitively apply a four-step procedure: First, perform a few one and two-qubit quantum gates. Second, perform a syndrome measurement on a subset of the qubits. Third, perform fast classical computations to establish if and where errors occurred. And, fourth, correct the errors with a correction step. The next iteration applies the same procedure with new one and two-qubit gates. Even though current error-rates prohibit this procedure to work and fault tolerant quantum computing remains a distant goal, the same procedure can already prove useful today. In this work we make use of this four-step scheme not to carry out fault-tolerant computations, but to enhance short, *constant*-depth, quantum circuits that perform 1 qubit gates and *nearest-neighbor* 2 qubit gates.

We introduce a new computational model called *Local Alternating Quantum Classical Computations* (LAQCC). In this model, qubits are placed in a grid and they can only interact with their direct neighbors; the quantum circuits are of constant depth with intermediate measurements; a classical controller can perform log-depth computations on these intermediate measurement outcomes and control future quantum operations based on the outcome. This model fits naturally between quantum algorithms in the NISQ era and full-fledged fault-tolerant quantum computation. We first prove that any Clifford circuit has an equivalent LAQCC circuit, and that any LAQCC circuit can be simulated by a QNC[1] circuit. Next, we conjecture the non-simulatability of LAQCC by showing that LAQCC contains the class of Instantaneous Quantum Polynomial-time circuits. We also show that any LAQCC circuit with polynomial-sized quantum circuits and unbounded classical computations is contained in the class of quantum circuits equipped with post-selection gates with respect to the task of state preparation. We continue by presenting LAQCC implementations of different subroutines, including OR-gates, quantum Fourier transforms and Threshold gates. These subroutines prove vital in constructing three state preparation routines in the main part of this work. Preparing a uniform superposition uses constant-depth arithmetic gates, combined with an exact Grover implementation by Long. For the W-state, we employ a compress-uncompress method to switch between a binary and one-hot encoding. This method extends to the more generalized Dicke-states, the superposition of n-bit strings of Hamming weight k, for $k = \mathcal{O}(\sqrt{n})$, but fails for higher k due to the birthday paradox. We extend this protocol to a protocol that prepares many-body scar states, highly excited states with low entanglement and longer coherence times than states with the same energy density. We present a circuit for preparing Dicke-states for larger k requiring log-depth circuits that maps between the factoradic number system and the combinatorial number system.

1 Introduction

Current quantum hardware is unable to carry out universal quantum computations due to the buildup of errors that occur during the computation. The magnitude of the individual error is currently above the value that the Threshold Theorem requires in order to kick-start quantum

