

2024

QuSoft is named on page 40 of the paper.

Fault-tolerant quantum input/output

Matthias Christandl[1], Omar Fawzi[2], and Ashutosh Goswami[1]

[1]Department of Mathematical Sciences, University of Copenhagen, Denmark
[2]Université de Lyon, Inria, ENS de Lyon, UCBL, LIP, France
christandl@math.ku.dk, omar.fawzi@ens-lyon.fr, akg@math.ku.dk

arXiv:2408.05260v3 [quant-ph] 2 Dec 2025

Abstract

Usual scenarios of fault-tolerant computation are concerned with the fault-tolerant realization of quantum algorithms that compute classical functions, such as Shor's algorithm for factoring. In particular, this means that input and output to the quantum algorithm are classical. In contrast to stand-alone single-core quantum computers, in many distributed scenarios, quantum information might have to be passed on from one quantum information processing system to another one, possibly via noisy quantum communication channels with noise levels above fault-tolerant thresholds. In such situations, quantum information processing devices will have quantum inputs, quantum outputs or even both, which pass qubits among each other.

Working in the fault-tolerant framework of [Kitaev, 1997], we show that any quantum circuit with quantum input and output can be transformed into a fault-tolerant circuit that produces the ideal circuit with some controlled noise applied at the input and output. The framework allows the direct composition of the statements, enabling versatile future applications. We illustrate this with a concrete application, namely, communication over a noisy channel with faulty encoding and decoding operations [Christandl and Müller-Hermes, 2024]. For communication codes with linear minimum distance, we construct fault-tolerant encoders and decoders for general noise (including coherent errors). For the weaker, but standard, model of local stochastic noise, we obtain fault-tolerant encoders and decoders for any communication code that can correct a constant fraction random errors.

1 Introduction

1.1 Background

Many communication and computation scenarios involve black boxes, which implement a fixed quantum channel on an input-output space, while the user does not have control over their design and implementation. The user can only apply these boxes on a quantum input and receive the corresponding output. For example, in the communication setting, a noisy quantum channel, which is used as a resource to transmit information, acts as the black box [Hol72; Wil13; Wat18]. Another example is quantum learning, where an unknown quantum device, whose properties are to be determined, can be viewed as such a black box [GLM11; MW13; Eis+20; AD17]. In general, a protocol with black boxes is a composition of many instances of black boxes and quantum circuits, designed by the user to optimize the performance of the protocol. In the communication setting, the performance of the protocol can be the number of bits/qubits that are reliably transmitted using the noisy quantum channel. In the setting of quantum learning, it can be the number of black box uses needed to accurately estimate the parameters of interest.