



A Bravyi-König theorem for Floquet codes generated by locally conjugate instantaneous stabiliser groups

Jelena Mackeprang* and Jonas Helsen
QuSoft & CWI
Science Park 123, 1098XG Amsterdam, The Netherlands
(Dated: January 30, 2026)

The Bravyi-König (BK) theorem is an important no-go theorem for the dynamics of topological stabiliser quantum error correcting codes. It states that any logical operation on a D-dimensional topological stabiliser code that can be implemented by a short-depth circuit acts on the codespace as an element of the D-th level of the Clifford hierarchy. In recent years, a new type of quantum error correcting codes based on Pauli stabilisers, dubbed Floquet codes, has been introduced. In Floquet codes, syndrome measurements are arranged such that they dynamically generate a codespace at each time step. Here, we show that the BK theorem holds for a definition of Floquet codes based on locally conjugate stabiliser groups. Moreover, we introduce and define a class of generalised unitaries in Floquet codes that need not preserve the codespace at each time step, but that combined with the measurements constitute a valid logical operation. We derive a canonical form of these generalised unitaries and show that the BK theorem holds for them too.

arXiv:2601.21863v1 [quant-ph] 29 Jan 2026

I. INTRODUCTION

Quantum error correction (QEC) and fault tolerant quantum computing are crucial ingredients for universal quantum computation due to the inherent fragility of quantum hardware systems. A rich and well-studied framework is the Pauli stabiliser formalism, where the codespace is chosen to be the joint eigenspace of an abelian subgroup of the Pauli group - the stabiliser group or sometimes simply called the stabiliser - and errors change the sign of one or multiple elements of this group. A major bottleneck in designing good (stabiliser) quantum error correcting codes are high-weight measurements, i.e. ones that require addressing multiple qubits at once using possibly entangling operations. This problem motivates the development of codes allowing for higher-weight measurements to be decomposed into smaller ones, such as subsystem codes, where a subset of the logical qubits are turned into gauge qubits.
Dynamical codes (or Floquet codes), first introduced in [1, 2], pose another way to split up high-weight measurements. Here, one transitions from one stabiliser group to the next by measuring Pauli operators that anti-commute with a subset of stabilisers in the current one. Because the measured Pauli operators each anti-commute with at least one element of the stabiliser, no information is gained about the actual logical state. Logical information is preserved. The stabiliser groups between which one transitions in a Floquet code are dubbed *instantaneous stabiliser groups*, or short ISGs. One can view two consecutive ISGs and the measurements as a subsystem code (as mentioned in [3–5]), but as soon as a third ISG is present, the measurements in a dynamical code do not necessarily define a standard subsystem code measurement sequence. That is because there generally is no consistent logical subspace as for subsystem codes. In periodic dynamical codes, one periodically returns (up to stabiliser signs) to the initial codespace, but the measurement sequences generally introduce a non-trivial logical operation. Other dynamical codes have been introduced in [2–4, 6–9].

As far as we know, there is no universally agreed-upon definition of a dynamical code. In [8] and [9] the authors define topological dynamical codes as sequences of anyon condensations with respect to a parent anyon theory. Another approach to systematically construct dynamical codes is via the ZX calculus (see [4, 10, 11]). A very general approach to dynamical codes is discussed in [3], where the authors use a definition of Floquet codes consisting solely of the a priori prescription of the sequential measurements and derive an algorithm to compute different notions of distance.

In this work, we analyse the dynamical properties of Floquet codes. Namely, we want to know which logical operations can be implemented in a fault-tolerant manner. To do so, we first have to agree on a definition for Floquet codes. We refrain from the very broad notion of dynamical codes as an arbitrary sequence of measurements, as these fit within the broader framework of spacetime codes/spacetime error correction [12]. Instead, we base our definition on the concept of (locally) conjugate stabiliser group, as introduced in [13]. They are the building block of most previously introduced Floquet codes, such as in [1, 4, 6, 7, 9]. To be more precise, we view dynamical codes as a finite sequence of locally conjugate stabiliser groups $\mathcal{A}_1 \to \mathcal{A}_2 \to \ldots \to \mathcal{A}_\tau$, where one transitions from $\mathcal{A}_t$ to $\mathcal{A}_{t+1}$ by measuring specific generators of the respective subsequent stabiliser group, i.e. of $\mathcal{A}_{t+1}$. Most *topological* dynamical codes introduced so far, such as the ones in [1, 4, 6, 8, 9], are covered by this definition. However, our work should extend to these more general definitions of dynamical codes in a straightforward manner, as we will discuss in section VIII

Having narrowed down a precise definition, we ask

* jelena.mackeprang@gmail.com