

(Almost) quadruply optimal unitary designs in 1D

Guoding Liu [*] Jonas Helsen [†]

August 20, 2026

arXiv:2608.18650v1 [quant-ph] 19 Aug 2026

Abstract

We construct n-qubit approximate unitary k-designs in 1D systems, achieving circuit depth $\mathcal{O}(\log(n/\varepsilon) + k \log k)$ with relative error ε and requiring $\mathcal{O}(nk \log k)$ magic gates. This matches existing lower bounds $\Omega(\log(n/\varepsilon) + k)$ for circuit depth, and $\widetilde{\Omega}(nk)$ for the required number of T gates, up to a $\log k$ factor, achieving simultaneous near-optimality in all parameters. Our construction is based on a combination and refinement of two existing results. We reduce the required magic block size for breaking Clifford symmetries in the magic-augmented circuit construction of Zhang et al. (Ref. [1]) from $\mathcal{O}(k \log k)$ to $\mathcal{O}(\log k)$. We also improve the breakthrough construction of Chen et al. (Ref. [2]), to construct a generating set of 1D local constant-depth circuits for the unitary group with a constant spectral gap, making $\mathcal{O}(\log k)$-local random unitaries realizable in depth $\mathcal{O}(k \log k)$. As a by-product, we provide a constant-size 1D-local generating set for the Clifford group, which we expect to be of independent interest. Combining the two results with the gluing lemma, we prove the final result.

1 Introduction

Random unitaries are a foundational tool and object of study in quantum information science and quantum physics. Theoretically, they serve as indispensable tools for investigating quantum many-body dynamics [3, 4] and quantum gravity [5–7]. Practically, they support a wide range of quantum information processing tasks, including quantum learning [8], quantum metrology [9], device benchmarking [10, 11], quantum supremacy demonstrations [12], and quantum cryptography [13].

Given their ubiquitous applications, significant effort has been devoted to synthesizing random unitaries with minimal resource overhead. However, generating true Haar-random unitaries requires circuit depth or ancillary qubit counts that scale exponentially with the qubit number n. To circumvent this bottleneck, unitary k-designs are employed to mimic the Haar measure up to the k-th moment, rendering them statistically indistinguishable from Haar-random unitaries under k queries. For most practical protocols, an approximate unitary design suffices. Specifically, in any experiment querying a random unitary at most k times, an approximate unitary k-design with relative error ε guarantees an output accuracy within ε. While alternative error measures exist, such as additive or measurable errors, relative error provides the strongest guarantee when queries are restricted to U without access to its inverse [14].

Consequently, optimizing the circuit depth required to generate approximate unitary k-designs across various geometric constraints has become a central objective. Efforts have focused in particular on one-dimensional (1D) nearest-neighbor architectures, as 1D geometries represent the most



[*]Center for Quantum Information, Institute for Interdisciplinary Information Sciences, Tsinghua University, Beijing, lgd22@mails.tsinghua.edu.cn

[†]Centrum Wiskunde & Informatica (CWI) and QuSoft, Amsterdam, jonas@cwi.nl