2017–
2021

Reliable channel-adapted error correction: Bacon-Shor code recovery from amplitude damping

Álvaro Piedrafita[1,2] and Joseph M. Renes[1]
[1]*Institute for Theoretical Physics, ETH Zürich, Switzerland*
[2]*Qusoft and CWI, Amsterdam, The Netherlands*

We construct two simple error correction schemes adapted to amplitude damping noise for Bacon-Shor codes and investigate their prospects for fault-tolerant implementation. Both consist solely of Clifford gates and require far fewer qubits, relative to the standard method, to achieve correction to a desired order in the damping rate. The first, employing one-bit teleportation and single-qubit measurements, needs only one fourth as many physical qubits, while the second, using just stabilizer measurements and Pauli corrections, needs only half. We show that existing fault-tolerance methods can be employed for the latter, while the former can be made to avoid potential catastrophic errors and can easily cope with damping faults in ancilla qubits.

arXiv:1704.05857v1 [quant-ph] 19 Apr 2017

1 Introduction

The performance of quantum error correction over a given channel can be substantially improved by adapting the decoding algorithm to the channel. For the amplitude damping channel, which describes the effects of energy relaxation, Leung *et al.* illustrate this quite dramatically with a four qubit code capable of correcting single damping errors [1], one qubit fewer than the minimum number needed to recover from an arbitrary single-qubit error [2, 3]. However, there is no guarantee that the performance available to a given code and channel can be realized by simple correction circuits. For instance, although the Shor code [4] can in principle correct two amplitude damping errors [5], standard recovery based on stabilizer measurement and Pauli recovery operations will correct only one. And the problem of finding simple high-performance decoders is compounded when requiring the decoder to tolerate noise during its implementation. Nonetheless, reducing the qubit overhead needed for error correction would be tremendously useful in near term efforts to construct quantum information processors.

In this paper we investigate the performance of simple decoding schemes for the Bacon-Shor code family [6] adapted to amplitude damping noise. The (n,m) Bacon-Shor code combines two classical repetition codes, a length-n code for phase flips and a length-m code for bit flips, and by standard stabilizer recovery can correct up to $\min(\lfloor (n-1)/2 \rfloor, \lfloor (m-1)/2 \rfloor)$ arbitrary single-qubit errors. Duan *et al.* observe that for amplitude damping noise the $(t+1, t+1)$ code exactly satisfies the error-correcting conditions to order t in the damping probability γ [7], meaning Bacon-Shor codes can in principle correct twice as many damping errors as arbitrary single-qubit errors. Here we present an error correcting procedure using only Clifford operations that achieves this performance, as well as a syndrome-based procedure (requiring only stabilizer measurements) which perfectly recovers $(t+1, 2t+1)$ codewords to order t.

Furthermore, we also investigate the prospects for fault-tolerant implementation of the two correction schemes. Our syndrome correction method also corrects the Pauli twirl [2] of the amplitude damping channel, which makes it amenable to the use of standard fault-tolerant gadgets. The Clifford correction does not, however, complicating the analysis. Nevertheless, we find that while single, ill-timed damping events can be catastrophic for direct implementation of the correction procedure, this problem can be avoided by suitable alterations. Additionally, we show that damping errors in ancillas used for error correction propagate into the data as phase errors, and are therefore correctable by subsequent correction cycles. This would seem to require the use of the $(2t+1, 2t+1)$ code for syndrome correction, wiping out all qubit savings relative to standard decoding. But the

AP completed most of this work while at ETH Zürich.