

Scraftie — Troubleshooting Record

Scraftie — Personal Music Streaming Server • Initial Build Documentation

Scraftie Troubleshooting Record

This document preserves the actual problems encountered during the initial build.

1. Navidrome Installation Returned HTTP 404

Problem

The first Navidrome installation/download attempt returned:

```
HTTP 404
```

Investigation

The Navidrome GitHub release API was investigated instead of assuming the URL was correct.

The architecture was checked:

```
uname -m
```

Result:

```
amd64
```

The appropriate Debian amd64 release package was identified and installed.

Result

Navidrome installed successfully.

2. Navidrome Could Not Open Its Database

Problem

Navidrome failed with:

```
Error disabling foreign_keys
unable to open database file: no such file or directory
Database could not be opened!
```

Diagnosis

The configured data directory:

```
/var/lib/navidrome
```

was not available correctly for the service.

Fix

```
sudo mkdir -p /var/lib/navidrome
sudo chown -R navidrome:navidrome /var/lib/navidrome
sudo chown -R navidrome:navidrome /music/OG_SD_Card
sudo systemctl restart navidrome
```

Verification

Navidrome became active and scanned the library.

The web interface opened and an administrator account was created.

3. Sudo Access

Problem

cprquecian initially did not have expected sudo access.

Fix

A root shell was used to add the user to the sudo group:

```
usermod -aG sudo cprquecian
```

The user then logged out/reconnected or rebooted so group membership applied.

Sudo access subsequently worked.

4. Lid Closure Caused Server Availability Problems

Problem

Closing the Scraftie laptop lid caused the machine to stop responding over Tailscale.

Investigation

/etc/systemd/logind.conf contained:

```
#HandleLidSwitch=ignore
#HandleLidSwitchExternalPower=ignore
#HandleLidSwitchDocked=ignore
```

Configuration

The intended configuration became:

```
HandleLidSwitch=ignore
HandleLidSwitchExternalPower=ignore
HandleLidSwitchDocked=ignore
LidSwitchIgnoreInhibited=yes
```

5. Expected GNOME Lid Setting Did Not Exist

An expected key:

```
lid-close-ac-action
```

returned:

```
No such key "lid-close-ac-action"
```

The available GNOME power keys were inspected:

```
gsettings list-keys org.gnome.settings-daemon.plugins.power
```

Relevant keys:

```
sleep-inactive-ac-timeout
sleep-inactive-ac-type
sleep-inactive-battery-timeout
sleep-inactive-battery-type
```

Initial AC configuration:

```
sleep-inactive-ac-type = 'suspend'
sleep-inactive-ac-timeout = 900
```

Final configuration:

```
gsettings set org.gnome.settings-daemon.plugins.power sleep-inactive-ac-type 'nothing'
```

Verification:

```
gsettings get org.gnome.settings-daemon.plugins.power sleep-inactive-ac-type
```

Result:

```
'nothing'
```

6. Temporary GNOME Display Problem

During the power/lid troubleshooting, the physical display eventually showed a blinking underscore.

SSH continued working.

This established that the underlying server was still operational even though the local graphical display was not behaving normally.

7. Display Diagnostics

The following diagnostics were performed:

```
systemctl status gdm3 --no-pager
systemctl --user status gnome-session.target --no-pager
loginctl list-sessions
loginctl show-session 4 -p Type -p Display -p Remote -p State -p Desktop -p IdleHint
pgrep -a gnome-shell
```

Findings:

- GDM was active.
- GNOME session was active.
- GNOME Shell was running.
- The local session was Wayland.
- SSH remained operational.
- DRM-related messages appeared in the graphical session.

8. DRM Messages

Relevant messages included:

```
Cursor update failed: drmModeAtomicCommit: Invalid argument
```

and:

```
Failed to disable device '/dev/dri/card0': drmModeAtomicCommit: Permission denied
```

These messages are preserved as observed diagnostic output.

The build record does not establish either message as the definitive root cause of the display issue.

9. Recovery

A clean reboot restored the normal GNOME login screen and desktop.

The important conclusion was:

The server itself remained operational; the temporary issue affected the graphical display/session.

10. Remote Connectivity

Tailscale was tested with:

```
tailscale ping <SCARFTIE_TAILSCALE_IP>
```

and returned a successful pong.

SSH from Fedora to Scraftie was also verified.

11. Cellular Streaming

Ultrasonic successfully streamed music from Navidrome.

With Wi-Fi disabled on the Motorola Edge+ 2023, playback continued over cellular through Tailscale.

This verified the end-to-end remote path.

12. Useful Service Diagnostics

```
systemctl status navidrome  
systemctl status tailscaled  
systemctl status ssh
```

```
systemctl is-active navidrome tailscaled ssh
```

```
systemctl is-enabled navidrome
systemctl is-enabled tailscaled
systemctl is-enabled ssh
```

```
systemctl --failed
```

```
journalctl -u navidrome -n 50
journalctl -u navidrome -f
```

The first group checks service state; `is-active` provides a quick status check; `is-enabled` checks boot enablement; `systemctl --failed` identifies failed units; and `journalctl` provides Navidrome logs.

Troubleshooting Pattern

The initial build repeatedly followed:

```
Problem
↓
Inspect actual system state
↓
Identify cause
↓
Apply targeted fix
↓
Restart/retest when required
↓
Verify from the user's actual workflow
```

This process is intentionally preserved as part of the project record.