

No.	Device		Name	Description	I/O Type	IP address =192.168.10 0 20	Modbus Address	Data Type (16 bit Int / Boolean?)	Query Response time (sec)	Location	Qty	Remarks
1	12	D/G#1	Over Speed	On overspeed [806.4min-1(112%), 828 min-1(115%)]	Digital	IP address =192.168.10 0 20 Port = 502 Slave ID =	1	Boolean	0.5	GCP#1	1	Engine Trip
	12	D/G#2	Over Speed	On overspeed [806.4min-1(112%), 828 min-1(115%)]	Digital		401	Boolean	0.5	GCP#2	1	Engine Trip
	12	D/G#3	Over Speed	On overspeed [806.4min-1(112%), 828 min-1(115%)]	Digital		801	Boolean	0.5	GCP#3	1	Engine Trip
	12	D/G#4	Over Speed	On overspeed [806.4min-1(112%), 828 min-1(115%)]	Digital		1201	Boolean	0.5	GCP#4	1	Engine Trip
2	48T	D/G#1	Engine Start Failure	IN CASE OF (14) KEEPING-OFF AFTER 20 Sec FROM (88V) ACTIVATION	Digital		2	Boolean	0.5	GCP#1	1	
	48T	D/G#2	Engine Start Failure	IN CASE OF (14) KEEPING-OFF AFTER 20 Sec FROM (88V) ACTIVATION	Digital		402	Boolean	0.5	GCP#2	1	
	48T	D/G#3	Engine Start Failure	IN CASE OF (14) KEEPING-OFF AFTER 20 Sec FROM (88V) ACTIVATION	Digital		802	Boolean	0.5	GCP#3	1	
	48T	D/G#4	Engine Start Failure	IN CASE OF (14) KEEPING-OFF AFTER 20 Sec FROM (88V) ACTIVATION	Digital		1202	Boolean	0.5	GCP#4	1	
3	26EX2	D/G#1	Turbo-charger gas outlet temp switch (2nd)	On over 430° C	Digital		3	Boolean	0.5	GCP#1	1	As per "TCTO"(T/C outlet Temp), Engine Trip
	26EX2	D/G#2	Turbo-charger gas outlet temp switch (2nd)	On over 430° C	Digital		403	Boolean	0.5	GCP#2	1	As per "TCTO"(T/C outlet Temp), Engine Trip
	26EX2	D/G#3	Turbo-charger gas outlet temp switch (2nd)	On over 430° C	Digital		803	Boolean	0.5	GCP#3	1	As per "TCTO"(T/C outlet Temp), Engine Trip
	26EX2	D/G#4	Turbo-charger gas outlet temp switch (2nd)	On over 430° C	Digital		1203	Boolean	0.5	GCP#4	1	As per "TCTO"(T/C outlet Temp), Engine Trip
4	MDHH	D/G#1	Heavy fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "15"	Digital		4	Boolean	0.5	GCP#1	1	
	MDHH	D/G#2	Heavy fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "15"	Digital		404	Boolean	0.5	GCP#2	1	
	MDHH	D/G#3	Heavy fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "15"	Digital		804	Boolean	0.5	GCP#3	1	
	MDHH	D/G#4	Heavy fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "15"	Digital		1204	Boolean	0.5	GCP#4	1	
5	63Q2	D/G#1	L.O press.switch for engine (2nd)	ON BELOW 0.3MPa	Digital		5	Boolean	0.5	GCP#1	1	Engine Trip
	63Q2	D/G#2	L.O press.switch for engine (2nd)	ON BELOW 0.3MPa	Digital		405	Boolean	0.5	GCP#2	1	Engine Trip
	63Q2	D/G#3	L.O press.switch for engine (2nd)	ON BELOW 0.3MPa	Digital		805	Boolean	0.5	GCP#3	1	Engine Trip
	63Q2	D/G#4	L.O press.switch for engine (2nd)	ON BELOW 0.3MPa	Digital		1205	Boolean	0.5	GCP#4	1	Engine Trip
6	26WJ2	D/G#1	Jacket water thermal switch (2nd)	ON OVER 90° C	Digital		6	Boolean	0.5	GCP#1	1	Engine Trip
	26WJ2	D/G#2	Jacket water thermal switch (2nd)	ON OVER 90° C	Digital		406	Boolean	0.5	GCP#2	1	Engine Trip
	26WJ2	D/G#3	Jacket water thermal switch (2nd)	ON OVER 90° C	Digital		806	Boolean	0.5	GCP#3	1	Engine Trip
	26WJ2	D/G#4	Jacket water thermal switch (2nd)	ON OVER 90° C	Digital		1206	Boolean	0.5	GCP#4	1	Engine Trip
7	63QT2	D/G#1	L.O press.switch for turbo-charger(2nd)	ON BELOW 0.20MPa	Digital		7	Boolean	0.5	GCP#1	1	Engine Trip
	63QT2	D/G#2	L.O press.switch for turbo-charger(2nd)	ON BELOW 0.20MPa	Digital		407	Boolean	0.5	GCP#2	1	Engine Trip
	63QT2	D/G#3	L.O press.switch for turbo-charger(2nd)	ON BELOW 0.20MPa	Digital		807	Boolean	0.5	GCP#3	1	Engine Trip
	63QT2	D/G#4	L.O press.switch for turbo-charger(2nd)	ON BELOW 0.20MPa	Digital		1207	Boolean	0.5	GCP#4	1	Engine Trip
8	63WJ2	D/G#1	Jacket water press.switch (2nd)	ON BELOW 0.1MPa	Digital		8	Boolean	0.5	GCP#1	1	Engine Trip
	63WJ2	D/G#2	Jacket water press.switch (2nd)	ON BELOW 0.1MPa	Digital		408	Boolean	0.5	GCP#2	1	Engine Trip
	63WJ2	D/G#3	Jacket water press.switch (2nd)	ON BELOW 0.1MPa	Digital		808	Boolean	0.5	GCP#3	1	Engine Trip
	63WJ2	D/G#4	Jacket water press.switch (2nd)	ON BELOW 0.1MPa	Digital		1208	Boolean	0.5	GCP#4	1	Engine Trip
9		D/G#1	DC control power supply failure	DC24Vは PLC本体の電源のため出力不可 (DC100V電源異常のみの場合は可)	Digital		9	Boolean	0.5	GCP#1	1	
		D/G#2	DC control power supply failure		Digital		409	Boolean	0.5	GCP#2	1	
		D/G#3	DC control power supply failure		Digital		809	Boolean	0.5	GCP#3	1	
		D/G#4	DC control power supply failure		Digital		1209	Boolean	0.5	GCP#4	1	
10		D/G#1	GAC Abnormal	PLC本体の故障のため出力不可	Digital		10	Boolean	0.5	GCP#1	1	
		D/G#2	GAC Abnormal		Digital		410	Boolean	0.5	GCP#2	1	
		D/G#3	GAC Abnormal		Digital		810	Boolean	0.5	GCP#3	1	
		D/G#4	GAC Abnormal		Digital		1210	Boolean	0.5	GCP#4	1	
11	5E	D/G#1	Emergency stop		Digital		11	Boolean	0.5	GCP#1	1	To consider from drums a dry contact to GCP; purpose for the client to activate stop engine/open cb remotely
	5E	D/G#2	Emergency stop		Digital		411	Boolean	0.5	GCP#2	1	To consider from drums a dry contact to GCP; purpose for the client to activate stop engine/open cb remotely
	5E	D/G#3	Emergency stop		Digital		811	Boolean	0.5	GCP#3	1	To consider from drums a dry contact to GCP; purpose for the client to activate stop engine/open cb remotely
	5E	D/G#4	Emergency stop		Digital		1211	Boolean	0.5	GCP#4	1	To consider from drums a dry contact to GCP; purpose for the client to activate stop engine/open cb remotely

12	69WJ	D/G#1	Jacket water flow relay	ON BELOW 40m³/h	Digital	12	Boolean	0.5	GCP#1	1	Timer 10 Sec
	69WJ	D/G#2	Jacket water flow relay	ON BELOW 40m³/h	Digital	412	Boolean	0.5	GCP#2	1	Timer 10 Sec
	69WJ	D/G#3	Jacket water flow relay	ON BELOW 40m³/h	Digital	812	Boolean	0.5	GCP#3	1	Timer 10 Sec
	69WJ	D/G#4	Jacket water flow relay	ON BELOW 40m³/h	Digital	1212	Boolean	0.5	GCP#4	1	Timer 10 Sec
13		D/G#1	Over voltage GEN. PROTECTIVE RELAY OPERATION(ENGINE STOP)		Digital	13	Boolean	0.5	GCP#1	1	
		D/G#2	Over voltage GEN. PROTECTIVE RELAY OPERATION(ENGINE STOP)		Digital	413	Boolean	0.5	GCP#2	1	
		D/G#3	Over voltage GEN. PROTECTIVE RELAY OPERATION(ENGINE STOP)		Digital	813	Boolean	0.5	GCP#3	1	
		D/G#4	Over voltage GEN. PROTECTIVE RELAY OPERATION(ENGINE STOP)		Digital	1213	Boolean	0.5	GCP#4	1	
14		D/G#1	Under voltage AVR ABNORMAL		Digital	14	Boolean	0.5	GCP#1	1	
		D/G#2	Under voltage AVR ABNORMAL		Digital	414	Boolean	0.5	GCP#2	1	
		D/G#3	Under voltage AVR ABNORMAL		Digital	814	Boolean	0.5	GCP#3	1	
		D/G#4	Under voltage AVR ABNORMAL		Digital	1214	Boolean	0.5	GCP#4	1	
15		D/G#1	Gen differential GEN. PROTECTIVE RELAY OPERATION(VCB TRIP)		Digital	15	Boolean	0.5	GCP#1	1	
		D/G#2	Gen differential GEN. PROTECTIVE RELAY OPERATION(VCB TRIP)		Digital	415	Boolean	0.5	GCP#2	1	
		D/G#3	Gen differential GEN. PROTECTIVE RELAY OPERATION(VCB TRIP)		Digital	815	Boolean	0.5	GCP#3	1	
		D/G#4	Gen differential GEN. PROTECTIVE RELAY OPERATION(VCB TRIP)		Digital	1215	Boolean	0.5	GCP#4	1	
16		D/G#1	Reverse power SPARE		Digital	16	Boolean	0.5	GCP#1	1	
		D/G#2	Reverse power SPARE		Digital	416	Boolean	0.5	GCP#2	1	
		D/G#3	Reverse power SPARE		Digital	816	Boolean	0.5	GCP#3	1	
		D/G#4	Reverse power SPARE		Digital	1216	Boolean	0.5	GCP#4	1	
17		D/G#1	Field failure PROTECTION RELAY(86R)		Digital	17	Boolean	0.5	GCP#1	1	
		D/G#2	Field failure PROTECTION RELAY(86R)		Digital	417	Boolean	0.5	GCP#2	1	
		D/G#3	Field failure PROTECTION RELAY(86R)		Digital	817	Boolean	0.5	GCP#3	1	
		D/G#4	Field failure PROTECTION RELAY(86R)		Digital	1217	Boolean	0.5	GCP#4	1	
18	MDH	D/G#1	Light fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "10"	Digital	18	Boolean	0.5	GCP#1	1	
	MDH	D/G#2	Light fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "10"	Digital	418	Boolean	0.5	GCP#2	1	
	MDH	D/G#3	Light fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "10"	Digital	818	Boolean	0.5	GCP#3	1	
	MDH	D/G#4	Light fault of oil mist detector	ON WHEN OIL MIST LEVEL RED: "10"	Digital	1218	Boolean	0.5	GCP#4	1	
19	MDSY	D/G#1	Light fault of oil mist detector system failure	ON WHEN SYSTEM FAILURE OCCURS	Digital	19	Boolean	0.5	GCP#1	1	
	MDSY	D/G#2	Light fault of oil mist detector system failure	ON WHEN SYSTEM FAILURE OCCURS	Digital	419	Boolean	0.5	GCP#2	1	
	MDSY	D/G#3	Light fault of oil mist detector system failure	ON WHEN SYSTEM FAILURE OCCURS	Digital	819	Boolean	0.5	GCP#3	1	
	MDSY	D/G#4	Light fault of oil mist detector system failure	ON WHEN SYSTEM FAILURE OCCURS	Digital	1219	Boolean	0.5	GCP#4	1	
20	63Q1	D/G#1	LO press.switch for engine(1st)	ON BELOW 0.35MPa	Digital	20	Boolean	0.5	GCP#1	1	As per "PTLO"
	63Q1	D/G#2	LO press.switch for engine(1st)	ON BELOW 0.35MPa	Digital	420	Boolean	0.5	GCP#2	1	As per "PTLO"
	63Q1	D/G#3	LO press.switch for engine(1st)	ON BELOW 0.35MPa	Digital	820	Boolean	0.5	GCP#3	1	As per "PTLO"
	63Q1	D/G#4	LO press.switch for engine(1st)	ON BELOW 0.35MPa	Digital	1220	Boolean	0.5	GCP#4	1	As per "PTLO"
21	63QP	D/G#1	LO press.switch for priming	ON OVER 0.03MPa	Digital	21	Boolean	0.5	GCP#1	1	NO PRESS. AFTER 60-90sec. FROM PUMP START
	63QP	D/G#2	LO press.switch for priming	ON OVER 0.03MPa	Digital	421	Boolean	0.5	GCP#2	1	NO PRESS. AFTER 60-90sec. FROM PUMP START
	63QP	D/G#3	LO press.switch for priming	ON OVER 0.03MPa	Digital	821	Boolean	0.5	GCP#3	1	NO PRESS. AFTER 60-90sec. FROM PUMP START
	63QP	D/G#4	LO press.switch for priming	ON OVER 0.03MPa	Digital	1221	Boolean	0.5	GCP#4	1	NO PRESS. AFTER 60-90sec. FROM PUMP START
22	63WC	D/G#1	Cooler water press switch	ON BELOW 0.1MPa	Digital	22	Boolean	0.5	GCP#1	1	As per "PTCW"
	63WC	D/G#2	Cooler water press switch	ON BELOW 0.1MPa	Digital	422	Boolean	0.5	GCP#2	1	As per "PTCW"
	63WC	D/G#3	Cooler water press switch	ON BELOW 0.1MPa	Digital	822	Boolean	0.5	GCP#3	1	As per "PTCW"
	63WC	D/G#4	Cooler water press switch	ON BELOW 0.1MPa	Digital	1222	Boolean	0.5	GCP#4	1	As per "PTCW"
23	63QT1	D/G#1	L.O. press switch for turbo-charger (1st)	ON BELOW 0.25MPa	Digital	23	Boolean	0.5	GCP#1	1	As per "PTTLO"
	63QT1	D/G#2	L.O. press switch for turbo-charger (1st)	ON BELOW 0.25MPa	Digital	423	Boolean	0.5	GCP#2	1	As per "PTTLO"
	63QT1	D/G#3	L.O. press switch for turbo-charger (1st)	ON BELOW 0.25MPa	Digital	823	Boolean	0.5	GCP#3	1	As per "PTTLO"
	63QT1	D/G#4	L.O. press switch for turbo-charger (1st)	ON BELOW 0.25MPa	Digital	1223	Boolean	0.5	GCP#4	1	As per "PTTLO"
24	26WJ1	D/G#1	Jacket water thermal switch (1st)	ON OVER 85° C	Digital	24	Boolean	0.5	GCP#1	1	As per "TRJWO"
	26WJ1	D/G#2	Jacket water thermal switch (1st)	ON OVER 85° C	Digital	424	Boolean	0.5	GCP#2	1	As per "TRJWO"
	26WJ1	D/G#3	Jacket water thermal switch (1st)	ON OVER 85° C	Digital	824	Boolean	0.5	GCP#3	1	As per "TRJWO"
	26WJ1	D/G#4	Jacket water thermal switch (1st)	ON OVER 85° C	Digital	1224	Boolean	0.5	GCP#4	1	As per "TRJWO"
25	26WC	D/G#1	Cooler water thermal switch	ON OVER 50° C	Digital	25	Boolean	0.5	GCP#1	1	
	26WC	D/G#2	Cooler water thermal switch	ON OVER 50° C	Digital	425	Boolean	0.5	GCP#2	1	
	26WC	D/G#3	Cooler water thermal switch	ON OVER 50° C	Digital	825	Boolean	0.5	GCP#3	1	
	26WC	D/G#4	Cooler water thermal switch	ON OVER 50° C	Digital	1225	Boolean	0.5	GCP#4	1	
26	26Q	D/G#1	L.O. thermal switch	ON OVER 65° C	Digital	26	Boolean	0.5	GCP#1	1	
	26Q	D/G#2	L.O. thermal switch	ON OVER 65° C	Digital	426	Boolean	0.5	GCP#2	1	
	26Q	D/G#3	L.O. thermal switch	ON OVER 65° C	Digital	826	Boolean	0.5	GCP#3	1	

		26Q	D/G#4	L.O. thermal switch	ON OVER 65° C	Digital		1226	Boolean	0.5	GCP#4	1		
	27	33QSL	D/G#1	L.O. sump tank level switch	ON BELOW LOWER LIMIT	Digital		27	Boolean	0.5	GCP#1	1		Timer 5 sec
		33QSL	D/G#2	L.O. sump tank level switch	ON BELOW LOWER LIMIT	Digital		427	Boolean	0.5	GCP#2	1		Timer 5 sec
		33QSL	D/G#3	L.O. sump tank level switch	ON BELOW LOWER LIMIT	Digital		827	Boolean	0.5	GCP#3	1		Timer 5 sec
		33QSL	D/G#4	L.O. sump tank level switch	ON BELOW LOWER LIMIT	Digital		1227	Boolean	0.5	GCP#4	1		Timer 5 sec
	28	63WJ1	D/G#1	Jacket water press switch (1st)	ON BELOW 0.15MPa	Digital		28	Boolean	0.5	GCP#1	1		As per "PTJW"
		63WJ1	D/G#2	Jacket water press switch (1st)	ON BELOW 0.15MPa	Digital		428	Boolean	0.5	GCP#2	1		As per "PTJW"
		63WJ1	D/G#3	Jacket water press switch (1st)	ON BELOW 0.15MPa	Digital		828	Boolean	0.5	GCP#3	1		As per "PTJW"
		63WJ1	D/G#4	Jacket water press switch (1st)	ON BELOW 0.15MPa	Digital		1228	Boolean	0.5	GCP#4	1		As per "PTJW"
	29	63QD	D/G#1	L.O. filter differential press switch	ON OVER 0.09MPa	Digital		29	Boolean	0.5	GCP#1	1		
		63QD	D/G#2	L.O. filter differential press switch	ON OVER 0.09MPa	Digital		429	Boolean	0.5	GCP#2	1		
		63QD	D/G#3	L.O. filter differential press switch	ON OVER 0.09MPa	Digital		829	Boolean	0.5	GCP#3	1		
		63QD	D/G#4	L.O. filter differential press switch	ON OVER 0.09MPa	Digital		1229	Boolean	0.5	GCP#4	1		
	30	63QTD	D/G#1	T/C L.O filter differential press switch	ON OVER 0.06MPa	Digital		12	Boolean	0.5	GCP#1	1		
		63QTD	D/G#2	T/C L.O filter differential press switch	ON OVER 0.06MPa	Digital		412	Boolean	0.5	GCP#2	1		
		63QTD	D/G#3	T/C L.O filter differential press switch	ON OVER 0.06MPa	Digital		812	Boolean	0.5	GCP#3	1		
		63QTD	D/G#4	T/C L.O filter differential press switch	ON OVER 0.06MPa	Digital		1230	Boolean	0.5	GCP#4	1		
	31	33HF	D/G#1	F.O leak tank level switch	ON OVER UPPER LIMIT	Digital		31	Boolean	0.5	GCP#1	1		Timer 5 sec
		33HF	D/G#2	F.O leak tank level switch	ON OVER UPPER LIMIT	Digital		431	Boolean	0.5	GCP#2	1		Timer 5 sec
		33HF	D/G#3	F.O leak tank level switch	ON OVER UPPER LIMIT	Digital		831	Boolean	0.5	GCP#3	1		Timer 5 sec
		33HF	D/G#4	F.O leak tank level switch	ON OVER UPPER LIMIT	Digital		1231	Boolean	0.5	GCP#4	1		Timer 5 sec
	32	TCTO	D/G#1	EXH. GAS T/C OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40001	16 bit Int	0.5	GCP#1	1		As per "TCTO"
		TCTO	D/G#2	EXH. GAS T/C OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40101	16 bit Int	0.5	GCP#2	1		As per "TCTO"
		TCTO	D/G#3	EXH. GAS T/C OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40201	16 bit Int	0.5	GCP#3	1		As per "TCTO"
		TCTO	D/G#4	EXH. GAS T/C OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40301	16 bit Int	0.5	GCP#4	1		As per "TCTO"
	33	69WC	D/G#1	Cooler water flow relay	ON BELOW 40m³/h	Digital		32	Boolean	0.5	GCP#1	1		Timer 10 sec
		69WC	D/G#2	Cooler water flow relay	ON BELOW 40m³/h	Digital		432	Boolean	0.5	GCP#2	1		Timer 10 sec
		69WC	D/G#3	Cooler water flow relay	ON BELOW 40m³/h	Digital		832	Boolean	0.5	GCP#3	1		Timer 10 sec
		69WC	D/G#4	Cooler water flow relay	ON BELOW 40m³/h	Digital		1232	Boolean	0.5	GCP#4	1		Timer 10 sec
	34	63AC		Air receiver press switch for engine	On: Below 2.16MPa, Off: 2.94MPa	Digital		1601	Boolean	0.5	GCP	1		
		63AC		Air receiver press switch for engine	On: Below 2.16MPa, Off: 2.94MPa	Digital		1602	Boolean	0.5	GCP	1		
		63AC		Air receiver press switch for engine	On: Below 2.16MPa, Off: 2.94MPa	Digital		1603	Boolean	0.5	GCP	1		
	35	63AL		Air receiver press switch for engine	On: Below 1.77MPa	Digital		1604	Boolean	0.5	GCP	1		
		63AL		Air receiver press switch for engine	On: Below 1.77MPa	Digital		1605	Boolean	0.5	GCP	1		
		63AL		Air receiver press switch for engine	On: Below 1.77MPa	Digital		1606	Boolean	0.5	GCP	1		
	36	33WCH	D/G#1	Level switch for C.W. expansion tank	On: above ___L,	Digital		33	Boolean	0.5	GCP#1	1		
		33WCH	D/G#2	Level switch for C.W. expansion tank	On: above ___L,	Digital		433	Boolean	0.5	GCP#2	1		
		33WCH	D/G#3	Level switch for C.W. expansion tank	On: above ___L,	Digital		833	Boolean	0.5	GCP#3	1		
		33WCH	D/G#4	Level switch for C.W. expansion tank	On: above ___L,	Digital		1233	Boolean	0.5	GCP#4	1		
	37	33WCL	D/G#1	Level switch for C.W. expansion tank	On: below ___L,	Digital		34	Boolean	0.5	GCP#1	1		
		33WCL	D/G#2	Level switch for C.W. expansion tank	On: below ___L,	Digital		434	Boolean	0.5	GCP#2	1		
		33WCL	D/G#3	Level switch for C.W. expansion tank	On: below ___L,	Digital		834	Boolean	0.5	GCP#3	1		
		33WCL	D/G#4	Level switch for C.W. expansion tank	On: below ___L,	Digital		1234	Boolean	0.5	GCP#4	1		
	38	33WJH	D/G#1	Level switch for J.W. expansion tank	On: above ___L,	Digital		35	Boolean	0.5	GCP#1	1		Sensor by Ormin, timer 5 sec
		33WJH	D/G#2	Level switch for J.W. expansion tank	On: above ___L,	Digital		435	Boolean	0.5	GCP#2	1		Sensor by Ormin, timer 5 sec
		33WJH	D/G#3	Level switch for J.W. expansion tank	On: above ___L,	Digital		835	Boolean	0.5	GCP#3	1		Sensor by Ormin, timer 5 sec
		33WJH	D/G#4	Level switch for J.W. expansion tank	On: above ___L,	Digital		1235	Boolean	0.5	GCP#4	1		Sensor by Ormin, timer 5 sec
	39	33WJL	D/G#1	Level switch for J.W. expansion tank	On: below ___L,	Digital		36	Boolean	0.5	GCP#1	1		Sensor by Ormin, timer 5 sec
		33WJL	D/G#2	Level switch for J.W. expansion tank	On: below ___L,	Digital		436	Boolean	0.5	GCP#2	1		Sensor by Ormin, timer 5 sec
		33WJL	D/G#3	Level switch for J.W. expansion tank	On: below ___L,	Digital		836	Boolean	0.5	GCP#3	1		Sensor by Ormin, timer 5 sec
		33WJL	D/G#4	Level switch for J.W. expansion tank	On: below ___L,	Digital		1236	Boolean	0.5	GCP#4	1		Sensor by Ormin, timer 5 sec
	40	33FDH	D/G#1	Level switch for DO service tank level high	On: above ___L,	Digital		37	Boolean	0.5	GCP#1	1		timer 5 sec
		33FDH	D/G#2	Level switch for DO service tank level high	On: above ___L,	Digital		437	Boolean	0.5	GCP#2	1		timer 5 sec
		33FDH	D/G#3	Level switch for DO service tank level high	On: above ___L,	Digital		837	Boolean	0.5	GCP#3	1		timer 5 sec
		33FDH	D/G#4	Level switch for DO service tank level high	On: above ___L,	Digital		1237	Boolean	0.5	GCP#4	1		timer 5 sec
	41	33FDL	D/G#1	Level switch for DO service tank level low	On: below ___L,	Digital		38	Boolean	0.5	GCP#1	1		timer 5 sec
		33FDL	D/G#2	Level switch for DO service tank level low	On: below ___L,	Digital		438	Boolean	0.5	GCP#2	1		timer 5 sec
		33FDL	D/G#3	Level switch for DO service tank level low	On: below ___L,	Digital		838	Boolean	0.5	GCP#3	1		timer 5 sec

	33FDL	D/G#4	Level switch for DO service tank level low	On: below ___L,	Digital		1238	Boolean	0.5	GCP#4	1		timer 5 sec
42	33FDC	D/G	Level switch for DO service tank level control	On: below ___L, Off: above ____L	Digital		1607	Boolean	0.5	GCP	1		timer 5 sec
43	33SETH	D/G	Level switch for HO settling tank level high	On: above ___L,	Digital		1608	Boolean	0.5	GCP	1		timer 5 sec
44	33SETL	D/G	Level switch for HO settling tank level low	On: below ___L,	Digital		1609	Boolean	0.5	GCP	1		timer 5 sec
45	33SETC	D/G	Level switch for HO settling tank level control	On: below ___L, Off: above ____L	Digital		1610	Boolean	0.5	GCP	1		timer 5 sec
46	33SEL	D/G	Level switch for HO service tank level low	On: below ___L,	Digital		1611	Boolean	0.5	GCP	1		timer 5 sec
47	63F	D/G#1	F.O press.switch	ON BELOW 0.15MPa	Digital		39	Boolean	0.5	GCP#1	1		As per "PTFO"
	63F	D/G#2	F.O press.switch	ON BELOW 0.15MPa	Digital		439	Boolean	0.5	GCP#2	1		As per "PTFO"
	63F	D/G#3	F.O press.switch	ON BELOW 0.15MPa	Digital		839	Boolean	0.5	GCP#3	1		As per "PTFO"
	63F	D/G#4	F.O press.switch	ON BELOW 0.15MPa	Digital		1239	Boolean	0.5	GCP#4	1		As per "PTFO"
48	33FDRC	D/G	Level switch for F.O drain tank level control	On: below ___L, Off: above ____L	Digital		1612	Boolean	0.5	GCP	1		
49	33FDRH	D/G	Level switch for F.O drain tank	On: above ___L,	Digital		1613	Boolean	0.5	GCP	1		
50	63FB	D/G	Press switch for auto back wash filter	ON OVER 0.06MPa	Digital		1614	Boolean	0.5	D/G	1		
51		D/G#1	Display failure		Digital		40	Boolean	0.5	GCP#1	1		
		D/G#2	Display failure		Digital		440	Boolean	0.5	GCP#2	1		
		D/G#3	Display failure		Digital		840	Boolean	0.5	GCP#3	1		
		D/G#4	Display failure		Digital		1240	Boolean	0.5	GCP#4	1		
52		D/G#1	DC100V source abnormal AUXILIARY EQUIPMENT FAILURE		Digital		41	Boolean	0.5	GCP#1	1		
		D/G#2	DC100V source abnormal AUXILIARY EQUIPMENT FAILURE		Digital		441	Boolean	0.5	GCP#2	1		
		D/G#3	DC100V source abnormal AUXILIARY EQUIPMENT FAILURE		Digital		841	Boolean	0.5	GCP#3	1		
		D/G#4	DC100V source abnormal AUXILIARY EQUIPMENT FAILURE		Digital		1241	Boolean	0.5	GCP#4	1		
53		D/G#1	DC24V source abnormal COM. DC24V source abnormal		Digital		42	Boolean	0.5	GCP#1	1		
		D/G#2	DC24V source abnormal COM. DC24V source abnormal		Digital		442	Boolean	0.5	GCP#2	1		
		D/G#3	DC24V source abnormal COM. DC24V source abnormal		Digital		842	Boolean	0.5	GCP#3	1		
		D/G#4	DC24V source abnormal COM. DC24V source abnormal		Digital		1242	Boolean	0.5	GCP#4	1		
54		D/G#1	Auto synchro failure		Digital		43	Boolean	0.5	GCP#1	1		
		D/G#2	Auto synchro failure		Digital		443	Boolean	0.5	GCP#2	1		
		D/G#3	Auto synchro failure		Digital		843	Boolean	0.5	GCP#3	1		
		D/G#4	Auto synchro failure		Digital		1243	Boolean	0.5	GCP#4	1		
55		D/G#1	CB non-close AUXILIARY EQUIPMENT FAILURE		Digital		1615	Boolean	0.5	GCP#1	1		
		D/G#2	CB non-close		Digital		1616	Boolean	0.5	GCP#2	1		
		D/G#3	CB non-close		Digital		1617	Boolean	0.5	GCP#3	1		
		D/G#4	CB non-close		Digital		1618	Boolean	0.5	GCP#4	1		
56	63AS		Control air press.switch	ON BELOW 0.60MPa	Digital		44	Boolean	0.5	GCP	1		Timer 10 sec
	63AS		Control air press.switch	ON BELOW 0.60MPa	Digital		444	Boolean	0.5	GCP	1		Timer 10 sec
	63AS		Control air press.switch	ON BELOW 0.60MPa	Digital		844	Boolean	0.5	GCP	1		Timer 10 sec
	63AS		Control air press.switch	ON BELOW 0.60MPa	Digital		1244	Boolean	0.5	GCP	1		Timer 10 sec
60	12M	D/G#1	Over Speed (mechanical side)	ON OVER 113% (+0%, -3%) [813.6min-1(113%)]	Digital		45	Boolean	0.5	D/G#1	1		
	12M	D/G#2	Over Speed (mechanical side)	ON OVER 113% (+0%, -3%) [813.6min-1(113%)]	Digital		445	Boolean	0.5	D/G#2	1		
	12M	D/G#3	Over Speed (mechanical side)	ON OVER 113% (+0%, -3%) [813.6min-1(113%)]	Digital		845	Boolean	0.5	D/G#3	1		
	12M	D/G#4	Over Speed (mechanical side)	ON OVER 113% (+0%, -3%) [813.6min-1(113%)]	Digital		1245	Boolean	0.5	D/G#4	1		
61	26G1	D/G#1	Thermal switch for alternator beaing(Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		46	Boolean	0.5	GCP#1	1		
	26G1	D/G#2	Thermal switch for alternator beaing(Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		446	Boolean	0.5	GCP#2	1		
	26G1	D/G#3	Thermal switch for alternator beaing(Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		846	Boolean	0.5	GCP#3	1		
	26G1	D/G#4	Thermal switch for alternator beaing(Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		1246	Boolean	0.5	GCP#4	1		
62	26G2	D/G#1	Thermal switch for alternator beaing (Anti-Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		47	Boolean	0.5	GCP#1	1		
	26G2	D/G#2	Thermal switch for alternator beaing (Anti-Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		447	Boolean	0.5	GCP#2	1		
	26G2	D/G#3	Thermal switch for alternator beaing (Anti-Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		847	Boolean	0.5	GCP#3	1		
	26G2	D/G#4	Thermal switch for alternator beaing (Anti-Fly-wheel side)	ON OVER THE UPPER LIMIT	Digital		1247	Boolean	0.5	GCP#4	1		
65	13	D/G#1	RATED SPEED	ON OVER 90% [648min-1(90%)]	Digital		48	Boolean	0.5	GCP#1	1		
	13	D/G#2	RATED SPEED	ON OVER 90% [648min-1(90%)]	Digital		448	Boolean	0.5	GCP#2	1		

66	13	D/G#3	RATED SPEED	ON OVER 90% [648min-1(90%)]	Digital		848	Boolean	0.5	GCP#3	1		
	13	D/G#4	RATED SPEED	ON OVER 90% [648min-1(90%)]	Digital		1248	Boolean	0.5	GCP#4	1		
66	14	D/G#1	LOW SPEED	ON OVER 300min ⁻¹ [300min-1(41.67%)]	Digital		49	Boolean	0.5	GCP#1	1		
	14	D/G#2	LOW SPEED	ON OVER 300min ⁻¹ [300min-1(41.67%)]	Digital		449	Boolean	0.5	GCP#2	1		
	14	D/G#3	LOW SPEED	ON OVER 300min ⁻¹ [300min-1(41.67%)]	Digital		849	Boolean	0.5	GCP#3	1		
	14	D/G#4	LOW SPEED	ON OVER 300min ⁻¹ [300min-1(41.67%)]	Digital		1249	Boolean	0.5	GCP#4	1		
67	88V	D/G#1	STARTING SOLENOID VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		50	Boolean	0.5	GCP#1	1		
	88V	D/G#2	STARTING SOLENOID VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		450	Boolean	0.5	GCP#2	1		
	88V	D/G#3	STARTING SOLENOID VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		850	Boolean	0.5	GCP#3	1		
	88V	D/G#4	STARTING SOLENOID VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		1250	Boolean	0.5	GCP#4	1		
68	5V	D/G#1	FUEL SHUT DOWN DEVICE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		51	Boolean	0.5	GCP#1	1		
	5V	D/G#2	FUEL SHUT DOWN DEVICE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		451	Boolean	0.5	GCP#2	1		
	5V	D/G#3	FUEL SHUT DOWN DEVICE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		851	Boolean	0.5	GCP#3	1		
	5V	D/G#4	FUEL SHUT DOWN DEVICE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		1251	Boolean	0.5	GCP#4	1		
69	88L	D/G#1	FUEL CONTROL PISTON MAGNETIC VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		52	Boolean	0.5	GCP#1	1		
	88L	D/G#2	FUEL CONTROL PISTON MAGNETIC VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		452	Boolean	0.5	GCP#2	1		
	88L	D/G#3	FUEL CONTROL PISTON MAGNETIC VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		852	Boolean	0.5	GCP#3	1		
	88L	D/G#4	FUEL CONTROL PISTON MAGNETIC VALVE	WHEN START ENGINE, VALVE OPEN BY EXCITING DC24V, 15W	Digital		1252	Boolean	0.5	GCP#4	1		
70	5S	D/G#1	FUEL OIL CUT PISTON MAGNETIC VALVE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		53	Boolean	0.5	GCP#1	1		
	5S	D/G#2	FUEL OIL CUT PISTON MAGNETIC VALVE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		453	Boolean	0.5	GCP#2	1		
	5S	D/G#3	FUEL OIL CUT PISTON MAGNETIC VALVE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		853	Boolean	0.5	GCP#3	1		
	5S	D/G#4	FUEL OIL CUT PISTON MAGNETIC VALVE	WHEN STOP ENGINE, VALVE SHUT BY EXCITING DC24V, 15W	Digital		1253	Boolean	0.5	GCP#4	1		
71	MDMO	D/G#1	MONITORING OF OIL MIST LEVEL	0-2.0mg/L_4-20mA	Analog		40002	16 bit Int	0.5	GCP#1	1		
	MDMO	D/G#2	MONITORING OF OIL MIST LEVEL	0-2.0mg/L_4-20mA	Analog		40102	16 bit Int	0.5	GCP#2	1		
	MDMO	D/G#3	MONITORING OF OIL MIST LEVEL	0-2.0mg/L_4-20mA	Analog		40202	16 bit Int	0.5	GCP#3	1		
	MDMO	D/G#4	MONITORING OF OIL MIST LEVEL	0-2.0mg/L_4-20mA	Analog		40302	16 bit Int	0.5	GCP#4	1		
72	HS	D/G#1	GOVERNOR HANDLE SWITCH	ON: ENGINE START CONDITION	Digital		54	Boolean	0.5	GCP#1	1		
	HS	D/G#2	GOVERNOR HANDLE SWITCH	ON: ENGINE START CONDITION	Digital		454	Boolean	0.5	GCP#2	1		
	HS	D/G#3	GOVERNOR HANDLE SWITCH	ON: ENGINE START CONDITION	Digital		854	Boolean	0.5	GCP#3	1		
	HS	D/G#4	GOVERNOR HANDLE SWITCH	ON: ENGINE START CONDITION	Digital		1254	Boolean	0.5	GCP#4	1		
73	33T	D/G#1	TURNING HANDLE POSITION SWITCH(ON AT TURNING DEVICE OUT)	ON: ENGINE START CONDITION	Digital		55	Boolean	0.5	GCP#1	1		
	33T	D/G#2	TURNING HANDLE POSITION SWITCH(ON AT TURNING DEVICE OUT)	ON: ENGINE START CONDITION	Digital		455	Boolean	0.5	GCP#2	1		
	33T	D/G#3	TURNING HANDLE POSITION SWITCH(ON AT TURNING DEVICE OUT)	ON: ENGINE START CONDITION	Digital		855	Boolean	0.5	GCP#3	1		
	33T	D/G#4	TURNING HANDLE POSITION SWITCH(ON AT TURNING DEVICE OUT)	ON: ENGINE START CONDITION	Digital		1255	Boolean	0.5	GCP#4	1		
74	1B(U)	D/G#1	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK) 0℃～	Analog		40003	16 bit Int	0.5	GCP#1	1		
	1B(U)	D/G#2	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK) 0℃～	Analog		40103	16 bit Int	0.5	GCP#2	1		
	1B(U)	D/G#3	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK) 0℃～	Analog		40203	16 bit Int	0.5	GCP#3	1		
	1B(U)	D/G#4	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK) 0℃～	Analog		40303	16 bit Int	0.5	GCP#4	1		

75	2B(V)	D/G#1	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40004	16 bit Int	0.5	GCP#1	1		
	2B(V)	D/G#2	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40104	16 bit Int	0.5	GCP#2	1		
	2B(V)	D/G#3	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40204	16 bit Int	0.5	GCP#3	1		
	2B(V)	D/G#4	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40304	16 bit Int	0.5	GCP#4	1		
76	3B(W)	D/G#1	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40005	16 bit Int	0.5	GCP#1	1		
	3B(W)	D/G#2	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40105	16 bit Int	0.5	GCP#2	1		
	3B(W)	D/G#3	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40205	16 bit Int	0.5	GCP#3	1		
	3B(W)	D/G#4	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (WORK)	0℃～	Analog		40305	16 bit Int	0.5	GCP#4	1		
77	4B(U)	D/G#1	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#1	±		
	4B(U)	D/G#2	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#2	±		
	4B(U)	D/G#3	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#3	±		
	4B(U)	D/G#4	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#4	±		
78	5B(V)	D/G#1	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#1	±		
	5B(V)	D/G#2	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#2	±		
	5B(V)	D/G#3	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#3	±		
	5B(V)	D/G#4	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#4	±		
79	6B(W)	D/G#1	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#1	±		
	6B(W)	D/G#2	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#2	±		
	6B(W)	D/G#3	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#3	±		
	6B(W)	D/G#4	GENERATOR STATOR WINDING SEARCH COIL THERMAL SENSOR	PT 100Ω @ 0° C (SPARE)		Analog				0.5	GCP#4	±		
80	38G1	D/G#1	GENERATOR BEARING THERMAL SENSOR (FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40006	16 bit Int	0.5	GCP#1	1		
	38G1	D/G#2	GENERATOR BEARING THERMAL SENSOR (FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40106	16 bit Int	0.5	GCP#2	1		
	38G1	D/G#3	GENERATOR BEARING THERMAL SENSOR (FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40206	16 bit Int	0.5	GCP#3	1		
	38G1	D/G#4	GENERATOR BEARING THERMAL SENSOR (FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40306	16 bit Int	0.5	GCP#4	1		
81	38G2	D/G#1	GENERATOR BEARING THERMAL SENSOR (ANTI-FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40007	16 bit Int	0.5	GCP#1	1		
	38G2	D/G#2	GENERATOR BEARING THERMAL SENSOR (ANTI-FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40107	16 bit Int	0.5	GCP#2	1		
	38G2	D/G#3	GENERATOR BEARING THERMAL SENSOR (ANTI-FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40207	16 bit Int	0.5	GCP#3	1		
	38G2	D/G#4	GENERATOR BEARING THERMAL SENSOR (ANTI-FLY-WHEEL SIDE)	PT 100Ω @ 0° C	0℃～	Analog		40307	16 bit Int	0.5	GCP#4	1		
82	TC1	D/G#1	EXH. GAS No. 1 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40008	16 bit Int	0.5	GCP#1	1		
	TC1	D/G#2	EXH. GAS No. 1 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40108	16 bit Int	0.5	GCP#2	1		
	TC1	D/G#3	EXH. GAS No. 1 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40208	16 bit Int	0.5	GCP#3	1		
	TC1	D/G#4	EXH. GAS No. 1 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40308	16 bit Int	0.5	GCP#4	1		
83	TC2	D/G#1	EXH. GAS No. 2 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40009	16 bit Int	0.5	GCP#1	1		
	TC2	D/G#2	EXH. GAS No. 2 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40109	16 bit Int	0.5	GCP#2	1		
	TC2	D/G#3	EXH. GAS No. 2 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40209	16 bit Int	0.5	GCP#3	1		
	TC2	D/G#4	EXH. GAS No. 2 CYL, OUT	0～600° C THERMO-COUPLE K-TYPE JIS C1602		Analog		40309	16 bit Int	0.5	GCP#4	1		

84	TC3	D/G#1	EXH. GAS No. 3 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40010	16 bit Int	0.5	GCP#1	1		
	TC3	D/G#2	EXH. GAS No. 3 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40110	16 bit Int	0.5	GCP#2	1		
	TC3	D/G#3	EXH. GAS No. 3 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40210	16 bit Int	0.5	GCP#3	1		
	TC3	D/G#4	EXH. GAS No. 3 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40310	16 bit Int	0.5	GCP#4	1		
85	TC4	D/G#1	EXH. GAS No. 4 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40011	16 bit Int	0.5	GCP#1	1		
	TC4	D/G#2	EXH. GAS No. 4 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40111	16 bit Int	0.5	GCP#2	1		
	TC4	D/G#3	EXH. GAS No. 4 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40211	16 bit Int	0.5	GCP#3	1		
	TC4	D/G#4	EXH. GAS No. 4 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40311	16 bit Int	0.5	GCP#4	1		
86	TC5	D/G#1	EXH. GAS No. 5 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40012	16 bit Int	0.5	GCP#1	1		
	TC5	D/G#2	EXH. GAS No. 5 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40112	16 bit Int	0.5	GCP#2	1		
	TC5	D/G#3	EXH. GAS No. 5 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40212	16 bit Int	0.5	GCP#3	1		
	TC5	D/G#4	EXH. GAS No. 5 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40312	16 bit Int	0.5	GCP#4	1		
87	TC6	D/G#1	EXH. GAS No. 6 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40013	16 bit Int	0.5	GCP#1	1		
	TC6	D/G#2	EXH. GAS No. 6 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40113	16 bit Int	0.5	GCP#2	1		
	TC6	D/G#3	EXH. GAS No. 6 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40213	16 bit Int	0.5	GCP#3	1		
	TC6	D/G#4	EXH. GAS No. 6 CYL, OUT	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40313	16 bit Int	0.5	GCP#4	1		
88	TCT1	D/G#1	EXH. GAS T/C IN	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40014	16 bit Int	0.5	GCP#1	1		
	TCT1	D/G#2	EXH. GAS T/C IN	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40114	16 bit Int	0.5	GCP#2	1		
	TCT1	D/G#3	EXH. GAS T/C IN	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40214	16 bit Int	0.5	GCP#3	1		
	TCT1	D/G#4	EXH. GAS T/C IN	0~600° C THERMO-COUPLE K-TYPE JIS C1602	Analog		40314	16 bit Int	0.5	GCP#4	1		
89	FOT	D/G#1	D.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SERVICE TANK)	1 Litre/1 pulse	Analog		40051 40052	32 bit Int	0.5	GCP#1	1		
	FOT	D/G#2	D.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SERVICE TANK)	1 Litre/1 pulse	Analog		40151 40152	32 bit Int	0.5	GCP#2	1		
	FOT	D/G#3	D.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SERVICE TANK)	1 Litre/1 pulse	Analog		40251 40252	32 bit Int	0.5	GCP#3	1		
	FOT	D/G#4	D.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SERVICE TANK)	1 Litre/1 pulse	Analog		40351 40352	32 bit Int	0.5	GCP#4	1		
90	FOEI	D/G#1	D.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40053 40054	32 bit Int	0.5	GCP#1	1		
	FOEI	D/G#2	D.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40153 40154	32 bit Int	0.5	GCP#2	1		
	FOEI	D/G#3	D.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40253 40254	32 bit Int	0.5	GCP#3	1		
	FOEI	D/G#4	D.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40353 40354	32 bit Int	0.5	GCP#4	1		
91	FOEO	D/G#1	D.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40055 40056	32 bit Int	0.5	GCP#1	1		
	FOEO	D/G#2	D.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40155 40156	32 bit Int	0.5	GCP#2	1		
	FOEO	D/G#3	D.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40255 40256	32 bit Int	0.5	GCP#3	1		
	FOEO	D/G#4	D.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40355 40356	32 bit Int	0.5	GCP#4	1		
92	FOHT	D/G#1	H.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SETTLING TANK)	1 Litre/1 pulse	Analog		40057 40058	32 bit Int	0.5	GCP#1	1		
	FOHT	D/G#2	H.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SETTLING TANK)	1 Litre/1 pulse	Analog		40157 40158	32 bit Int	0.5	GCP#2	1		
	FOHT	D/G#3	H.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SETTLING TANK)	1 Litre/1 pulse	Analog		40257 40258	32 bit Int	0.5	GCP#3	1		
	FOHT	D/G#4	H.O. FLOW METER FOR TRANSFER LINE(FROM STORAGE TO SETTLING TANK)	1 Litre/1 pulse	Analog		40357 40358	32 bit Int	0.5	GCP#4	1		
93	FOHEI	D/G#1	H.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40059 40060	32 bit Int	0.5	GCP#1	1		
	FOHEI	D/G#2	H.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40159 40160	32 bit Int	0.5	GCP#2	1		
	FOHEI	D/G#3	H.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40259 40260	32 bit Int	0.5	GCP#3	1		
	FOHEI	D/G#4	H.O. FLOW METER FOR ENGINE INLET	1 Litre/1 pulse	Analog		40359 40360	32 bit Int	0.5	GCP#4	1		
	FOHEO	D/G#1	H.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40061 40062	32 bit Int	0.5	GCP#1	1		

94	FOHEO	D/G#2	H.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40160 40161	32 bit Int	0.5	GCP#2	1		
	FOHEO	D/G#3	H.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40260 40261	32 bit Int	0.5	GCP#3	1		
	FOHEO	D/G#4	H.O. FLOW METER FOR ENGINE OUTLET	1 Litre/1 pulse	Analog		40360 40361	32 bit Int	0.5	GCP#4	1		
95	PTFO	D/G#1	PRESS. SENSOR FOR FUEL OIL	0-1.0MPa / 4-20mA	Analog		40015	16 bit Int	0.5	GCP#1	1		
	PTFO	D/G#2	PRESS. SENSOR FOR FUEL OIL	0-1.0MPa / 4-20mA	Analog		40115	16 bit Int	0.5	GCP#2	1		
	PTFO	D/G#3	PRESS. SENSOR FOR FUEL OIL	0-1.0MPa / 4-20mA	Analog		40215	16 bit Int	0.5	GCP#3	1		
	PTFO	D/G#4	PRESS. SENSOR FOR FUEL OIL	0-1.0MPa / 4-20mA	Analog		40315	16 bit Int	0.5	GCP#4	1		
96	PTJW	D/G#1	PRESS. SENSOR FOR JACKET WATER	0-0.6MPa / 4-20mA	Analog		40016	16 bit Int	0.5	GCP#1	1		
	PTJW	D/G#2	PRESS. SENSOR FOR JACKET WATER	0-0.6MPa / 4-20mA	Analog		40116	16 bit Int	0.5	GCP#2	1		
	PTJW	D/G#3	PRESS. SENSOR FOR JACKET WATER	0-0.6MPa / 4-20mA	Analog		40216	16 bit Int	0.5	GCP#3	1		
	PTJW	D/G#4	PRESS. SENSOR FOR JACKET WATER	0-0.6MPa / 4-20mA	Analog		40316	16 bit Int	0.5	GCP#4	1		
97	PTCW	D/G#1	PRESS. SENSOR FOR COOLER WATER	0-0.6MPa / 4-20mA	Analog		40017	16 bit Int	0.5	GCP#1	1		
	PTCW	D/G#2	PRESS. SENSOR FOR COOLER WATER	0-0.6MPa / 4-20mA	Analog		40117	16 bit Int	0.5	GCP#2	1		
	PTCW	D/G#3	PRESS. SENSOR FOR COOLER WATER	0-0.6MPa / 4-20mA	Analog		40217	16 bit Int	0.5	GCP#3	1		
	PTCW	D/G#4	PRESS. SENSOR FOR COOLER WATER	0-0.6MPa / 4-20mA	Analog		40317	16 bit Int	0.5	GCP#4	1		
98	PTLO	D/G#1	PRESS. SENSOR FOR ENGINE L.O.	0-1.0MPa / 4-20mA	Analog		40018	16 bit Int	0.5	GCP#1	1		
	PTLO	D/G#2	PRESS. SENSOR FOR ENGINE L.O.	0-1.0MPa / 4-20mA	Analog		40118	16 bit Int	0.5	GCP#2	1		
	PTLO	D/G#3	PRESS. SENSOR FOR ENGINE L.O.	0-1.0MPa / 4-20mA	Analog		40218	16 bit Int	0.5	GCP#3	1		
	PTLO	D/G#4	PRESS. SENSOR FOR ENGINE L.O.	0-1.0MPa / 4-20mA	Analog		40318	16 bit Int	0.5	GCP#4	1		
99	PTTL0	D/G#1	PRESS. SENSOR FOR TURBO-CHARGER L.O.	0-1.0MPa / 4-20mA	Analog		40019	16 bit Int	0.5	GCP#1	1		
	PTTL0	D/G#2	PRESS. SENSOR FOR TURBO-CHARGER L.O.	0-1.0MPa / 4-20mA	Analog		40119	16 bit Int	0.5	GCP#2	1		
	PTTL0	D/G#3	PRESS. SENSOR FOR TURBO-CHARGER L.O.	0-1.0MPa / 4-20mA	Analog		40219	16 bit Int	0.5	GCP#3	1		
	PTTL0	D/G#4	PRESS. SENSOR FOR TURBO-CHARGER L.O.	0-1.0MPa / 4-20mA	Analog		40319	16 bit Int	0.5	GCP#4	1		
100	PTIA	D/G#1	PRESS. SENSOR FOR INTAKE-AIR	0-0.4MPa / 4-20mA	Analog		40020	16 bit Int	0.5	GCP#1	1		
	PTIA	D/G#2	PRESS. SENSOR FOR INTAKE-AIR	0-0.4MPa / 4-20mA	Analog		40120	16 bit Int	0.5	GCP#2	1		
	PTIA	D/G#3	PRESS. SENSOR FOR INTAKE-AIR	0-0.4MPa / 4-20mA	Analog		40220	16 bit Int	0.5	GCP#3	1		
	PTIA	D/G#4	PRESS. SENSOR FOR INTAKE-AIR	0-0.4MPa / 4-20mA	Analog		40320	16 bit Int	0.5	GCP#4	1		
101	26EX1	D/G#1	TURBO-CHARGER GAS OUTLET TEMP. SWITCH (1st)	On over 400° C	Digital		56	Boolean	0.5	GCP#1	1		T/C Outlet temperature
	26EX1	D/G#2	TURBO-CHARGER GAS OUTLET TEMP. SWITCH (1st)	On over 400° C	Digital		456	Boolean	0.5	GCP#2	1		T/C Outlet temperature
	26EX1	D/G#3	TURBO-CHARGER GAS OUTLET TEMP. SWITCH (1st)	On over 400° C	Digital		856	Boolean	0.5	GCP#3	1		T/C Outlet temperature
	26EX1	D/G#4	TURBO-CHARGER GAS OUTLET TEMP. SWITCH (1st)	On over 400° C	Digital		1256	Boolean	0.5	GCP#4	1		T/C Outlet temperature
102	TRJWI	D/G#1	TEMP. SENSOR FOR JACKET WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40021	16 bit Int	0.5	GCP#1	1		
	TRJWI	D/G#2	TEMP. SENSOR FOR JACKET WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40121	16 bit Int	0.5	GCP#2	1		
	TRJWI	D/G#3	TEMP. SENSOR FOR JACKET WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40221	16 bit Int	0.5	GCP#3	1		
	TRJWI	D/G#4	TEMP. SENSOR FOR JACKET WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40321	16 bit Int	0.5	GCP#4	1		
103	TRJWO	D/G#1	TEMP. SENSOR FOR JACKET WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40022	16 bit Int	0.5	GCP#1	1		
	TRJWO	D/G#2	TEMP. SENSOR FOR JACKET WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40122	16 bit Int	0.5	GCP#2	1		
	TRJWO	D/G#3	TEMP. SENSOR FOR JACKET WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40222	16 bit Int	0.5	GCP#3	1		
	TRJWO	D/G#4	TEMP. SENSOR FOR JACKET WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40322	16 bit Int	0.5	GCP#4	1		
104	TRCWI	D/G#1	TEMP. SENSOR FOR COOLER WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40023	16 bit Int	0.5	GCP#1	1		
	TRCWI	D/G#2	TEMP. SENSOR FOR COOLER WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40123	16 bit Int	0.5	GCP#2	1		
	TRCWI	D/G#3	TEMP. SENSOR FOR COOLER WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40223	16 bit Int	0.5	GCP#3	1		
	TRCWI	D/G#4	TEMP. SENSOR FOR COOLER WATER INLET	PT100Ω @ 0° C	0°C~	Analog	40323	16 bit Int	0.5	GCP#4	1		
105	TRCWO	D/G#1	TEMP. SENSOR FOR COOLER WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40024	16 bit Int	0.5	GCP#1	1		
	TRCWO	D/G#2	TEMP. SENSOR FOR COOLER WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40124	16 bit Int	0.5	GCP#2	1		
	TRCWO	D/G#3	TEMP. SENSOR FOR COOLER WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40224	16 bit Int	0.5	GCP#3	1		
	TRCWO	D/G#4	TEMP. SENSOR FOR COOLER WATER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40324	16 bit Int	0.5	GCP#4	1		
106	TRLOI	D/G#1	TEMP. SENSOR FOR L.O. COOLER INLET	PT100Ω @ 0° C	0°C~	Analog	40025	16 bit Int	0.5	GCP#1	1		
	TRLOI	D/G#2	TEMP. SENSOR FOR L.O. COOLER INLET	PT100Ω @ 0° C	0°C~	Analog	40125	16 bit Int	0.5	GCP#2	1		
	TRLOI	D/G#3	TEMP. SENSOR FOR L.O. COOLER INLET	PT100Ω @ 0° C	0°C~	Analog	40225	16 bit Int	0.5	GCP#3	1		
	TRLOI	D/G#4	TEMP. SENSOR FOR L.O. COOLER INLET	PT100Ω @ 0° C	0°C~	Analog	40325	16 bit Int	0.5	GCP#4	1		
107	TRLOO	D/G#1	TEMP. SENSOR FOR L.O. COOLER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40026	16 bit Int	0.5	GCP#1	1		
	TRLOO	D/G#2	TEMP. SENSOR FOR L.O. COOLER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40126	16 bit Int	0.5	GCP#2	1		
	TRLOO	D/G#3	TEMP. SENSOR FOR L.O. COOLER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40226	16 bit Int	0.5	GCP#3	1		
	TRLOO	D/G#4	TEMP. SENSOR FOR L.O. COOLER OUTLET	PT100Ω @ 0° C	0°C~	Analog	40326	16 bit Int	0.5	GCP#4	1		
108	TRCWB	D/G#1	TEMP. SENSOR FOR COOLER WATER BEFORE C.O. COOLER	PT100Ω @ 0° C	0°C~	Analog	40027	16 bit Int	0.5	GCP#1	1		
	TRCWB	D/G#2	TEMP. SENSOR FOR COOLER WATER BEFORE C.O. COOLER	PT100Ω @ 0° C	0°C~	Analog	40127	16 bit Int	0.5	GCP#2	1		

	TRCWB	D/G#3	TEMP. SENSOR FOR COOLER WATER BEFORE CO.	PT100Ω @ 0° C	0℃～	Analog		40227	16 bit Int	0.5	GCP#3	1		
	TRCWB	D/G#4	TEMP. SENSOR FOR COOLER WATER BEFORE CO.	PT100Ω @ 0° C	0℃～	Analog		40327	16 bit Int	0.5	GCP#4	1		
109	26F1S	D/G	Thermostat switch for line heater	On below 25℃, Off over 30℃		Digital		1619	Boolean	0.5	GCP	1		
110	(26F1A)		Thermostat switch for line heater	On over 60℃		Digital		1620	Boolean		GCP	1		
111	PTSA		PRESS SENSOR FOR AIR RECEIVER	0-5.0MPa / 4-20mA		Analog		40401	16 bit Int	0.5	GCP#1	1		
	PTSA		PRESS SENSOR FOR AIR RECEIVER	0-5.0MPa / 4-20mA		Analog		40402	16 bit Int	0.5	GCP#2	1		
	PTSA		PRESS SENSOR FOR AIR RECEIVER	0-5.0MPa / 4-20mA		Analog		40403	16 bit Int	0.5	GCP#3	1		
112	26F2S	D/G	Thermostat sensor for HO Settling tank	On below 60℃, Off over 65℃		Digital		1621	Boolean	0.5	GCP	1		
113	26F2A		(Thermostat sensor for HO Settling tank heater)	On: above 75℃		Digital		1622	Boolean		GCP	1		Overheat, heater stop operation
114	26F3S		Thermostat switch for HO Service tank heater	On below 90℃, Off over 95℃		Digital		1623	Boolean		GCP	1		
115	26F4		Thermostat switch for HO Service tank(upper)	On over 90℃, Off below 85℃		Digital		1624	Boolean		GCP	1		
116	26F3A		(Thermostat switch for HO Service tank heater)	On: above 105℃		Digital		1625	Boolean		GCP	1		Overheat, heater stop operation
117	26F7		Thermostat switch for HO Engine inlet	On below 110℃, Off over 115℃		Digital		1626	Boolean		GCP	1		
118	26F8		Thermostat switch for HO Engine inlet	On below 130℃, Off below 125℃		Digital		1627	Boolean		GCP	1		
119	63FH		Press switch for HO piping	On below 0.5MPa		Digital		1628	Boolean		GCP	1		
120	63FD		Press switch for DO piping	On below 0.35MPa		Digital		1629	Boolean		GCP	1		
121	LSDO	D/G#1	Limit switch for change over valve	On D.O.side		Digital		57	Boolean	0.5	GCP#1	1		
	LSDO	D/G#1	Limit switch for change over valve	On D.O.side		Digital		58	Boolean	0.5	GCP#1	1		
	LSDO	D/G#2	Limit switch for change over valve	On D.O.side		Digital		457	Boolean	0.5	GCP#2	1		
	LSDO	D/G#2	Limit switch for change over valve	On D.O.side		Digital		458	Boolean	0.5	GCP#2	1		
	LSDO	D/G#3	Limit switch for change over valve	On D.O.side		Digital		857	Boolean	0.5	GCP#3	1		
	LSDO	D/G#3	Limit switch for change over valve	On D.O.side		Digital		858	Boolean	0.5	GCP#3	1		
	LSDO	D/G#4	Limit switch for change over valve	On D.O.side		Digital		1257	Boolean	0.5	GCP#4	1		
	LSDO	D/G#4	Limit switch for change over valve	On D.O.side		Digital		1258	Boolean	0.5	GCP#4	1		
122	LSHO	D/G#1	Limit switch for change over valve	On H.O.side		Digital		59	Boolean	0.5	GCP#1	1		
	LSHO	D/G#1	Limit switch for change over valve	On H.O.side		Digital		60	Boolean	0.5	GCP#1	1		
	LSHO	D/G#2	Limit switch for change over valve	On H.O.side		Digital		459	Boolean	0.5	GCP#2	1		
	LSHO	D/G#2	Limit switch for change over valve	On H.O.side		Digital		460	Boolean	0.5	GCP#2	1		
	LSHO	D/G#3	Limit switch for change over valve	On H.O.side		Digital		859	Boolean	0.5	GCP#3	1		
	LSHO	D/G#3	Limit switch for change over valve	On H.O.side		Digital		860	Boolean	0.5	GCP#3	1		
	LSHO	D/G#4	Limit switch for change over valve	On H.O.side		Digital		1259	Boolean	0.5	GCP#4	1		
	LSHO	D/G#4	Limit switch for change over valve	On H.O.side		Digital		1260	Boolean	0.5	GCP#4	1		
123	26F9S		Thermostat switch for Drain Tank	On below 50℃, Off below 55℃		Digital		1630	Boolean		GCP	1		
124	26F9A		(Thermostat switch for Drain Tank Heater)	On: above 65℃		Digital		1631	Boolean		GCP	1		Overheat, heater stop operation
125	TRDI	D/G#1	TEMP. SENSOR for DO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40028	16 bit Int	0.5	GCP#1	1		
	TRDI	D/G#2	TEMP. SENSOR for DO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40128	16 bit Int	0.5	GCP#2	1		
	TRDI	D/G#3	TEMP. SENSOR for DO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40228	16 bit Int	0.5	GCP#3	1		
	TRDI	D/G#4	TEMP. SENSOR for DO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40328	16 bit Int	0.5	GCP#4	1		
126	TRDO	D/G#1	TEMP. SENSOR for DO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40029	16 bit Int	0.5	GCP#1	1		
	TRDO	D/G#2	TEMP. SENSOR for DO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40129	16 bit Int	0.5	GCP#2	1		
	TRDO	D/G#3	TEMP. SENSOR for DO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40229	16 bit Int	0.5	GCP#3	1		
	TRDO	D/G#4	TEMP. SENSOR for DO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40329	16 bit Int	0.5	GCP#4	1		
127	TRHI	D/G#1	TEMP. SENSOR for HO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40030	16 bit Int	0.5	GCP#1	1		
	TRHI	D/G#2	TEMP. SENSOR for HO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40130	16 bit Int	0.5	GCP#2	1		
	TRHI	D/G#3	TEMP. SENSOR for HO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40230	16 bit Int	0.5	GCP#3	1		
	TRHI	D/G#4	TEMP. SENSOR for HO Engine inlet	PT100Ω @ 0° C	0℃～	Analog		40330	16 bit Int	0.5	GCP#4	1		
128	TRHO	D/G#1	TEMP. SENSOR for HO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40031	16 bit Int	0.5	GCP#1	1		
	TRHO	D/G#2	TEMP. SENSOR for HO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40131	16 bit Int	0.5	GCP#2	1		
	TRHO	D/G#3	TEMP. SENSOR for HO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40231	16 bit Int	0.5	GCP#3	1		
	TRHO	D/G#4	TEMP. SENSOR for HO Engine outlet	PT100Ω @ 0° C	0℃～	Analog		40331	16 bit Int	0.5	GCP#4	1		
129		Viscosity controller	less than 230 CST		Digital		1632	Boolean	0.5		1			
				GCP取り込みなし										

130	TRRA1	D/G#1	TEMP. SENSOR FOR RADIATOR 1	Fault	0℃～	Digital Analog	40040	Boolean	0.5	D/G#1	1		
	TRRA1	D/G#2	TEMP. SENSOR FOR RADIATOR 1	Fault	0℃～	Digital Analog	40140	Boolean	0.5	D/G#2	1		
	TRRA1	D/G#3	TEMP. SENSOR FOR RADIATOR 1	Fault	0℃～	Digital Analog	40240	Boolean	0.5	D/G#3	1		
	TRRA1	D/G#4	TEMP. SENSOR FOR RADIATOR 1	Fault	0℃～	Digital Analog	40340	Boolean	0.5	D/G#4	1		
131	TRRA2	D/G#1	TEMP. SENSOR FOR RADIATOR 2	Fault	0℃～	Digital Analog	40041	Boolean	0.5	D/G#1	1		
	TRRA2	D/G#2	TEMP. SENSOR FOR RADIATOR 2	Fault	0℃～	Digital Analog	40141	Boolean	0.5	D/G#2	1		
	TRRA2	D/G#3	TEMP. SENSOR FOR RADIATOR 2	Fault	0℃～	Digital Analog	40241	Boolean	0.5	D/G#3	1		
	TRRA2	D/G#4	TEMP. SENSOR FOR RADIATOR 2	Fault	0℃～	Digital Analog	40341	Boolean	0.5	D/G#4	1		
132	TRRA3	D/G#1	TEMP. SENSOR FOR RADIATOR 3	Fault	0℃～	Digital Analog	40042	Boolean	0.5	D/G#1	1		
	TRRA3	D/G#2	TEMP. SENSOR FOR RADIATOR 3	Fault	0℃～	Digital Analog	40142	Boolean	0.5	D/G#2	1		
	TRRA3	D/G#3	TEMP. SENSOR FOR RADIATOR 3	Fault	0℃～	Digital Analog	40242	Boolean	0.5	D/G#3	1		
	TRRA3	D/G#4	TEMP. SENSOR FOR RADIATOR 3	Fault	0℃～	Digital Analog	40342	Boolean	0.5	D/G#4	1		
133	TRRA4	D/G#1	TEMP. SENSOR FOR RADIATOR 4	Fault	0℃～	Digital Analog	40043	Boolean	0.5	D/G#1	1		
	TRRA4	D/G#2	TEMP. SENSOR FOR RADIATOR 4	Fault	0℃～	Digital Analog	40143	Boolean	0.5	D/G#2	1		
	TRRA4	D/G#3	TEMP. SENSOR FOR RADIATOR 4	Fault	0℃～	Digital Analog	40243	Boolean	0.5	D/G#3	1		
	TRRA4	D/G#4	TEMP. SENSOR FOR RADIATOR 4	Fault	0℃～	Digital Analog	40343	Boolean	0.5	D/G#4	1		
134	HOPF		H.O. Purifier Abnormal			Digital	1633	Boolean	0.5	GCP	1		
135	LOPF		Lub.Oil Purifier Abnormal			Digital	1634	Boolean	0.5	GCP	1		
136	MD-SX	D/G#1	OMD ANALOG OUTPUT BOARD			Analog	40032	16 bit Int	0.5	D/G#1	1		
	MD-SX	D/G#2	OMD ANALOG OUTPUT BOARD			Analog	40132	16 bit Int	0.5	D/G#2	1		
	MD-SX	D/G#3	OMD ANALOG OUTPUT BOARD			Analog	40232	16 bit Int	0.5	D/G#3	1		
	MD-SX	D/G#4	OMD ANALOG OUTPUT BOARD			Analog	40332	16 bit Int	0.5	D/G#4	1		
137	33SD		Level Switch for Sludge Tank			Digital	1635	Boolean		GCP	1		
140		D/G#1	Voltage [Generator]	V	0～6240V	Analog	40033	16 bit Int	0.5	GCP#1	1		
		D/G#2	Voltage [Generator]	V	0～6240V	Analog	40133	16 bit Int	0.5	GCP#2	1		
		D/G#3	Voltage [Generator]	V	0～6240V	Analog	40233	16 bit Int	0.5	GCP#3	1		
		D/G#4	Voltage [Generator]	V	0～6240V	Analog	40333	16 bit Int	0.5	GCP#4	1		
141		D/G#1	Frequency [Generator]	Hz	55～65Hz	Analog	40034	16 bit Int	0.5	GCP#1	1		
		D/G#2	Frequency [Generator]	Hz	55～65Hz	Analog	40134	16 bit Int	0.5	GCP#2	1		
		D/G#3	Frequency [Generator]	Hz	55～65Hz	Analog	40234	16 bit Int	0.5	GCP#3	1		
		D/G#4	Frequency [Generator]	Hz	55～65Hz	Analog	40334	16 bit Int	0.5	GCP#4	1		
141A		D/G#1	Power Factor [Generator]		-50～100～50	Analog	40035	16 bit Int	0.5	GCP#1	1		
		D/G#2	Power Factor [Generator]		-50～100～50	Analog	40135	16 bit Int	0.5	GCP#2	1		
		D/G#3	Power Factor [Generator]		-50～100～50	Analog	40235	16 bit Int	0.5	GCP#3	1		
		D/G#4	Power Factor [Generator]		-50～100～50	Analog	40335	16 bit Int	0.5	GCP#4	1		
142	52G1		VCB Status [Generator][52G1]	Close		Digital	65	Boolean	0.5	GCP#1	1		
				Open		Digital	66	Boolean	0.5	GCP#1	1		
				Fault (Non-close)/trip		Digital	67	Boolean	0.5	GCP#1	1		
	52G2		VCB Status [Generator][52G1 52G2]	Close		Digital	465	Boolean	0.5	GCP#2	1		
				Open		Digital	466	Boolean	0.5	GCP#2	1		
				Fault (Non-close)/trip		Digital	467	Boolean	0.5	GCP#2	1		
	52G3		VCB Status [Generator][52G1 52G3]	Close		Digital	865	Boolean	0.5	GCP#3	1		
				Open		Digital	866	Boolean	0.5	GCP#3	1		
				Fault (Non-close)/trip		Digital	867	Boolean	0.5	GCP#3	1		
	52G4		VCB Status [Generator][52G1 52G4]	Close		Digital	1265	Boolean	0.5	GCP#4	1		
				Open		Digital	1266	Boolean	0.5	GCP#4	1		
				Fault (Non-close)/trip		Digital	1267	Boolean	0.5	GCP#4	1		
143		D/G#1	Current [Generator]	Amphere	0～400A	Analog	40036	16 bit Int	0.5	GCP#1	1		
		D/G#2	Current [Generator]	Amphere	0～400A	Analog	40136	16 bit Int	0.5	GCP#2	1		
		D/G#3	Current [Generator]	Amphere	0～400A	Analog	40236	16 bit Int	0.5	GCP#3	1		
		D/G#4	Current [Generator]	Amphere	0～400A	Analog	40336	16 bit Int	0.5	GCP#4	1		
144		D/G#1	Running hours [Generator]	hrs	0～999999.9hrs	Analog	40063 40064	32 bit Int	0.5	GCP#1	1		
		D/G#2	Running hours [Generator]	hrs	0～999999.9hrs	Analog	40163 40164	32 bit Int	0.5	GCP#2	1		
		D/G#3	Running hours [Generator]	hrs	0～999999.9hrs	Analog	40263 40264	32 bit Int	0.5	GCP#3	1		
		D/G#4	Running hours [Generator]	hrs		Analog	40363 40364	32 bit Int	0.5	GCP#4	1		
145		D/G#1	Rack Reading	mm		Analog			0.5	GCP#1	±		
		D/G#2	Rack Reading	mm		Analog			0.5	GCP#2	±		

		D/G#3	Rack Reading	mm	Analog				0.5	GCP#3	±		
		D/G#4	Rack Reading	mm	Analog				0.5	GCP#4	±		
146		D/G#1	Power [Generator]	kWe	0~3000kW	Analog	40038	16 bit Int	0.5	GCP#1	1		
		D/G#2	Power [Generator]	kWe	0~3000kW	Analog	40138	16 bit Int	0.5	GCP#2	1		
		D/G#3	Power [Generator]	kWe	0~3000kW	Analog	40238	16 bit Int	0.5	GCP#3	1		
		D/G#4	Power [Generator]	kWe	0~3000kW	Analog	40338	16 bit Int	0.5	GCP#4	1		
147		D/G#1	Engine RPM	min-1	0~1000	Analog	40039	16 bit Int	0.5	GCP#1	1		
		D/G#2	Engine RPM	min-1	0~1000	Analog	40139	16 bit Int	0.5	GCP#2	1		
		D/G#3	Engine RPM	min-1	0~1000	Analog	40239	16 bit Int	0.5	GCP#3	1		
		D/G#4	Engine RPM	min-1	0~1000	Analog	40339	16 bit Int	0.5	GCP#4	1		
154		D/G#1	Ready to start			Digital	68	Boolean	0.5	GCP#1	1		
		D/G#2	Ready to start			Digital	468	Boolean	0.5	GCP#2	1		
		D/G#3	Ready to start			Digital	868	Boolean	0.5	GCP#3	1		
		D/G#4	Ready to start			Digital	1268	Boolean	0.5	GCP#4	1		
155	IM1		No.1 Turning Motor	Abnormal trip		Digital	69	Boolean		GCP#1	1		
				FWD Running		Digital	70	Boolean		GCP#1	1		
				Rev Running		Digital	71	Boolean		GCP#1	1		
				Remote mode		Digital	72	Boolean		GCP#1	1		
			No.2 Turning Motor	Abnormal trip		Digital	469	Boolean		GCP#2	1		
				FWD Running		Digital	470	Boolean		GCP#2	1		
				Rev Running		Digital	471	Boolean		GCP#2	1		
				Remote mode		Digital	472	Boolean		GCP#2	1		
			No.3 Turning Motor	Abnormal trip		Digital	869	Boolean		GCP#3	1		
				FWD Running		Digital	870	Boolean		GCP#3	1		
				Rev Running		Digital	871	Boolean		GCP#3	1		
				Remote mode		Digital	872	Boolean		GCP#3	1		
			No.4 Turning Motor	Abnormal trip		Digital	1269	Boolean		GCP#4	1		
				FWD Running		Digital	1270	Boolean		GCP#4	1		
				Rev Running		Digital	1271	Boolean		GCP#4	1		
				Remote mode		Digital	1272	Boolean		GCP#4	1		
156	IM2		No.1 LO Priming Pump Motor status	Auto start [GCP]		Digital	73	Boolean		GCP#1	1		
				Auto Stop [GCP]		Digital	74	Boolean		GCP#1	1		
				Abnormal trip		Digital	75	Boolean		GCP#1	1		
				Running		Digital	76	Boolean		GCP#1	1		
				Auto mode		Digital	77	Boolean		GCP#1	1		
				Remote start [LCP]	GCP取り込みなし	Digital	78	Boolean		GCP#1	1		
				Remote Stop [LCP]		Digital	79	Boolean		GCP#1	1		
			No.2 LO Priming Pump Motor status	Auto start [GCP]		Digital	473	Boolean		GCP#2	1		
				Auto Stop [GCP]		Digital	474	Boolean		GCP#2	1		
				Abnormal trip		Digital	475	Boolean		GCP#2	1		
				Running		Digital	476	Boolean		GCP#2	1		
				Auto mode		Digital	477	Boolean		GCP#2	1		
				Remote start [LCP]	GCP取り込みなし	Digital	478	Boolean		GCP#2	1		
				Remote Stop [LCP]		Digital	479	Boolean		GCP#2	1		
			No.3 LO Priming Pump Motor status	Auto start [GCP]		Digital	873	Boolean		GCP#3	1		
				Auto Stop [GCP]		Digital	874	Boolean		GCP#3	1		
				Abnormal trip		Digital	875	Boolean		GCP#3	1		
				Running		Digital	876	Boolean		GCP#3	1		
				Auto mode		Digital	877	Boolean		GCP#3	1		
				Remote start [LCP]	GCP取り込みなし	Digital	878	Boolean		GCP#3	1		
				Remote Stop [LCP]		Digital	879	Boolean		GCP#3	1		
			No.4 LO Priming Pump Motor status	Auto start [GCP]		Digital	1273	Boolean		GCP#4	1		
				Auto Stop [GCP]		Digital	1274	Boolean		GCP#4	1		
				Abnormal trip		Digital	1275	Boolean		GCP#4	1		
				Running		Digital	1276	Boolean		GCP#4	1		
				Auto mode		Digital	1277	Boolean		GCP#4	1		
				Remote start [LCP]	GCP取り込みなし	Digital	1278	Boolean		GCP#4	1		
				Remote Stop [LCP]		Digital	1279	Boolean		GCP#4	1		
157	IM3		No.1 Air Compressor status	Auto start [GCP]		Digital	1636	Boolean		GCP	1		
				Auto Stop [GCP]		Digital	1637	Boolean		GCP	1		
				Abnormal trip		Digital	1638	Boolean		GCP	1		
				Running		Digital	1639	Boolean		GCP	1		
				Auto mode		Digital	1616	Boolean		GCP	1		
			No.2 Air Compressor status	Auto start [GCP]		Digital	1617	Boolean		GCP	1		
				Auto Stop [GCP]		Digital	1642	Boolean		GCP	1		
				Abnormal trip		Digital	1616	Boolean		GCP	1		
				Running		Digital	1644	Boolean		GCP	1		

			Auto mode	Digital		1645	Boolean		GCP	1		
158	IM4	No.1 Mist Fan	Auto start [GCP]	Digital		80	Boolean		GCP#1	1		
			Auto Stop [GCP]	Digital		81	Boolean		GCP#1	1		
			Abnormal trip	Digital		82	Boolean		GCP#1	1		
			Running	Digital		83	Boolean		GCP#1	1		
		No.2 Mist Fan	Auto mode	Digital		84	Boolean		GCP#1	1		
			Auto start [GCP]	Digital		480	Boolean		GCP#2	1		
			Auto Stop [GCP]	Digital		481	Boolean		GCP#2	1		
			Abnormal trip	Digital		482	Boolean		GCP#2	1		
			Running	Digital		483	Boolean		GCP#2	1		
			Auto mode	Digital		484	Boolean		GCP#2	1		
		No.3 Mist Fan	Auto start [GCP]	Digital		880	Boolean		GCP#3	1		
			Auto Stop [GCP]	Digital		881	Boolean		GCP#3	1		
			Abnormal trip	Digital		882	Boolean		GCP#3	1		
			Running	Digital		883	Boolean		GCP#3	1		
		No.4 Mist Fan	Auto mode	Digital		884	Boolean		GCP#3	1		
			Auto start [GCP]	Digital		1280	Boolean		GCP#4	1		
			Auto Stop [GCP]	Digital		1281	Boolean		GCP#4	1		
			Abnormal trip	Digital		1282	Boolean		GCP#4	1		
			Running	Digital		1283	Boolean		GCP#4	1		
			Auto mode	Digital		1284	Boolean		GCP#4	1		
159	IM5	No.1 DO Transfer Pump	Auto start [GCP]	Digital		1646	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1647	Boolean		GCP	1		
			Abnormal trip	Digital		1648	Boolean		GCP	1		
			Running	Digital		1649	Boolean		GCP	1		
		No.2 DO Transfer Pump	Auto mode	Digital		1650	Boolean		GCP	1		
			Auto start [GCP]	Digital		1651	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1652	Boolean		GCP	1		
			Abnormal trip	Digital		1653	Boolean		GCP	1		
			Running	Digital		1654	Boolean		GCP	1		
			Auto mode	Digital		1655	Boolean		GCP	1		
160	IM6	No.1 DO Feed Pump	Auto start [GCP]	Digital		1656	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1657	Boolean		GCP	1		
			Abnormal trip	Digital		1658	Boolean		GCP	1		
			Running	Digital		1659	Boolean		GCP	1		
		No.2 DO Feed Pump	Auto mode	Digital		1660	Boolean		GCP	1		
			Auto start [GCP]	Digital		1661	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1662	Boolean		GCP	1		
			Abnormal trip	Digital		1663	Boolean		GCP	1		
			Running	Digital		1664	Boolean		GCP	1		
161			Auto mode	Digital		1665	Boolean		GCP	1		
	IM7	No.1 HO Transfer Pump	Auto start [GCP]	Digital		1666	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1667	Boolean		GCP	1		
			Abnormal trip	Digital		1668	Boolean		GCP	1		
			Running	Digital		1669	Boolean		GCP	1		
			Auto mode	Digital		1670	Boolean		GCP	1		
		No.2 HO Transfer Pump	Auto start [GCP]	Digital		1671	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1672	Boolean		GCP	1		
			Abnormal trip	Digital		1673	Boolean		GCP	1		
			Running	Digital		1674	Boolean		GCP	1		
162			Auto mode	Digital		1675	Boolean		GCP	1		
	IM8	No.1 HO Pressure Pump	Auto start [GCP]	Digital		1676	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1677	Boolean		GCP	1		
			Abnormal trip	Digital		1678	Boolean		GCP	1		
			Running	Digital		1679	Boolean		GCP	1		
		No.2 HO Pressure Pump	Auto mode	Digital		1680	Boolean		GCP	1		
			Auto start [GCP]	Digital		1681	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1682	Boolean		GCP	1		
			Abnormal trip	Digital		1683	Boolean		GCP	1		
			Running	Digital		1684	Boolean		GCP	1		
			Auto mode	Digital		1685	Boolean		GCP	1		
163	IM9	No.1 HO Feed Pump	Auto start [GCP]	Digital		1686	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1687	Boolean		GCP	1		
			Abnormal trip	Digital		1688	Boolean		GCP	1		
			Running	Digital		1689	Boolean		GCP	1		
		No.2 HO Feed Pump	Auto mode	Digital		1690	Boolean		GCP	1		
			Auto start [GCP]	Digital		1691	Boolean		GCP	1		

			Auto Stop [GCP]	Digital		1692	Boolean		GCP	1		
			Abnormal trip	Digital		1693	Boolean		GCP	1		
			Running	Digital		1694	Boolean		GCP	1		
			Auto mode	Digital		1695	Boolean		GCP	1		
164	I10	No.1 FO Drain Pump	Auto start [GCP]	Digital		1696	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1697	Boolean		GCP	1		
			Abnormal trip	Digital		1698	Boolean		GCP	1		
			Running	Digital		1699	Boolean		GCP	1		
			Auto mode	Digital		1700	Boolean		GCP	1		
		No.2 FO Drain Pump	Auto start [GCP]	Digital		1701	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1702	Boolean		GCP	1		
			Abnormal trip	Digital		1703	Boolean		GCP	1		
			Running	Digital		1704	Boolean		GCP	1		
			Auto mode	Digital		1705	Boolean		GCP	1		
165	IM11	No.1 DO/HO change over valve [Engine inlet]	Energize	Digital		85	Boolean		GCP#1	1		
			De-energize	Digital		86	Boolean		GCP#1	1		
		No.2 DO/HO change over valve [Engine inlet]	Energize	Digital		485	Boolean		GCP#2	1		
			De-energize	Digital		486	Boolean		GCP#2	1		
		No.3 DO/HO change over valve [Engine inlet]	Energize	Digital		885	Boolean		GCP#3	1		
			De-energize	Digital		886	Boolean		GCP#3	1		
		No.4 DO/HO change over valve [Engine inlet]	Energize	Digital		1285	Boolean		GCP#4	1		
			De-energize	Digital		1286	Boolean		GCP#4	1		
		No.1 DO/HO change over valve [Engine outlet]	Energize	Digital		87	Boolean		GCP#1	1		
			De-energize	Digital		88	Boolean		GCP#1	1		
		No.2 DO/HO change over valve [Engine outlet]	Energize	Digital		487	Boolean		GCP#2	1		
			De-energize	Digital		488	Boolean		GCP#2	1		
		No.3 DO/HO change over valve [Engine outlet]	Energize	Digital		887	Boolean		GCP#3	1		
			De-energize	Digital		888	Boolean		GCP#3	1		
		No.4 DO/HO change over valve [Engine outlet]	Energize	Digital		1287	Boolean		GCP#4	1		
			De-energize	Digital		1288	Boolean		GCP#4	1		
166	IM12	No.1 Inlet Fan	Auto start [GCP]	Digital		1706	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1707	Boolean		GCP	1		
			Abnormal trip	Digital		1708	Boolean		GCP	1		
			Running	Digital		1709	Boolean		GCP	1		
			Auto mode	Digital		1710	Boolean		GCP	1		
		No.2 Inlet Fan	Auto start [GCP]	Digital		1711	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1712	Boolean		GCP	1		
			Abnormal trip	Digital		1713	Boolean		GCP	1		
			Running	Digital		1714	Boolean		GCP	1		
			Auto mode	Digital		1715	Boolean		GCP	1		
		No.3 Inlet Fan	Auto start [GCP]	Digital		1716	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1717	Boolean		GCP	1		
			Abnormal trip	Digital		1718	Boolean		GCP	1		
			Running	Digital		1719	Boolean		GCP	1		
			Auto mode	Digital		1720	Boolean		GCP	1		
		No.4 Inlet Fan	Auto start [GCP]	Digital		1721	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1722	Boolean		GCP	1		
			Abnormal trip	Digital		1723	Boolean		GCP	1		
			Running	Digital		1724	Boolean		GCP	1		
			Auto mode	Digital		1725	Boolean		GCP	1		
		No.5 Inlet Fan	Auto start [GCP]	Digital		1726	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1727	Boolean		GCP	1		
			Abnormal trip	Digital		1728	Boolean		GCP	1		
			Running	Digital		1729	Boolean		GCP	1		
			Auto mode	Digital		1730	Boolean		GCP	1		
167	IM13	No.1 Outlet Fan	Auto start [GCP]	Digital		1731	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1732	Boolean		GCP	1		
			Abnormal trip	Digital		1733	Boolean		GCP	1		
			Running	Digital		1734	Boolean		GCP	1		
			Auto mode	Digital		1735	Boolean		GCP	1		
		No.2 Outlet Fan	Auto start [GCP]	Digital		1736	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1737	Boolean		GCP	1		
			Abnormal trip	Digital		1738	Boolean		GCP	1		
			Running	Digital		1739	Boolean		GCP	1		
			Auto mode	Digital		1740	Boolean		GCP	1		
		No.3 Outlet Fan	Auto start [GCP]	Digital		1741	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1742	Boolean		GCP	1		
			Abnormal trip	Digital		1743	Boolean		GCP	1		
			Running	Digital		1744	Boolean		GCP	1		

			Auto mode	Digital		1745	Boolean		GCP	1		
		No.4 Outlet Fan	Auto start [GCP]	Digital		1746	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1747	Boolean		GCP	1		
			Abnormal trip	Digital		1748	Boolean		GCP	1		
			Running	Digital		1749	Boolean		GCP	1		
			Auto mode	Digital		1750	Boolean		GCP	1		
		No.5 Outlet Fan	Auto start [GCP]	Digital		1751	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1752	Boolean		GCP	1		
			Abnormal trip	Digital		1753	Boolean		GCP	1		
			Running	Digital		1754	Boolean		GCP	1		
168			Auto mode	Digital		1755	Boolean		GCP	1		
169	IM14	Overhead crane	Abnormal trip	Digital		1756	Boolean		GCP	1		
			Running	Digital		1757	Boolean		GCP	1		
169	IM15	Air conditioner	Fault	Digital		1758	Boolean		GCP	1		
170	IM16	Viscosity controller	Fault	Digital		1759	Boolean		GCP	1		
171	IM29	L.O makeup Pump	Abnormal trip	Digital		1760	Boolean		GCP	1		
			Running	Digital		1761	Boolean		GCP	1		
172	IM19	No.1 Alternator Space heater	Auto start [GCP]	Digital		89	Boolean		GCP#1	1		
			Auto Stop [GCP]	Digital		90	Boolean		GCP#1	1		
			Abnormal trip	Digital		91	Boolean		GCP#1	1		
			Running	Digital		92	Boolean		GCP#1	1		
			Auto mode	Digital		93	Boolean		GCP#1	1		
		No.2 Alternator Space heater	Auto start [GCP]	Digital		489	Boolean		GCP#2	1		
			Auto Stop [GCP]	Digital		490	Boolean		GCP#2	1		
			Abnormal trip	Digital		491	Boolean		GCP#2	1		
			Running	Digital		492	Boolean		GCP#2	1		
			Auto mode	Digital		493	Boolean		GCP#2	1		
		No.3 Alternator Space heater	Auto start [GCP]	Digital		889	Boolean		GCP#3	1		
			Auto Stop [GCP]	Digital		890	Boolean		GCP#3	1		
			Abnormal trip	Digital		891	Boolean		GCP#3	1		
			Running	Digital		892	Boolean		GCP#3	1		
			Auto mode	Digital		893	Boolean		GCP#3	1		
		No.4 Alternator Space heater	Auto start [GCP]	Digital		1289	Boolean		GCP#4	1		
			Auto Stop [GCP]	Digital		1290	Boolean		GCP#4	1		
			Abnormal trip	Digital		1291	Boolean		GCP#4	1		
			Running	Digital		1292	Boolean		GCP#4	1		
			Auto mode	Digital		1293	Boolean		GCP#4	1		
173	IM39	DO unloading pump	Abnormal trip	Digital		1762	Boolean		GCP	1		LCBD: Start, Stop Push button [manual]
			Running	Digital		1763	Boolean		GCP	1		
174	IM 22	HO unloading pump	Abnormal trip	Digital		1764	Boolean		GCP	1		LCBH: Start, Stop Push button [manual]
			Running	Digital		1765	Boolean		GCP	1		
175	IM18	Inline heater	Auto start [GCP]	Digital		1766	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1767	Boolean		GCP	1		
			Abnormal trip	Digital		1768	Boolean		GCP	1		
			Running	Digital		1769	Boolean		GCP	1		
			Auto mode	Digital		1770	Boolean		GCP	1		
176	IM23	HO settling tank heater	Auto start [GCP]	Digital		1771	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1772	Boolean		GCP	1		
			Abnormal trip	Digital		1773	Boolean		GCP	1		
			Running	Digital		1774	Boolean		GCP	1		
			Auto mode	Digital		1775	Boolean		GCP	1		
177	IM24	No.1 HO purifier Heater	Fault	Digital		1776	Boolean		GCP	1		
		No.2 HO purifier Heater	Fault	Digital		1777	Boolean		GCP	1		
178	IM25	No.1 HO purifier Pump	Abnormal trip	Digital		1778	Boolean		GCP	1		
			Running	Digital		1779	Boolean		GCP	1		
		No.1 HO purifier Pump	Abnormal trip	Digital		1780	Boolean		GCP	1		
			Running	Digital		1781	Boolean		GCP	1		
	IM27	No.1 HO service tank heater	Auto start [GCP]	Digital		1782	Boolean		GCP	1		
			Auto Stop [GCP]	Digital		1783	Boolean		GCP	1		
			Abnormal trip	Digital		1784	Boolean		GCP	1		
			Running	Digital		1785	Boolean		GCP	1		

179				Auto mode	Digital		1786	Boolean		GCP	1		
			No.2 HO service tank heater	Auto start [GCP]	Digital		1787	Boolean		GCP	1		
				Auto Stop [GCP]	Digital		1788	Boolean		GCP	1		
				Abnormal trip	Digital		1789	Boolean		GCP	1		
				Running	Digital		1790	Boolean		GCP	1		
				Auto mode	Digital		1791	Boolean		GCP	1		
180	IM17		HO line heater	Fault	Digital		1792	Boolean		GCP	1		
181	IM28		HO back wash filter	Fault	Digital		1793	Boolean		GCP	1		
182	I30		No.1 F.O drain tank heater	Auto start [GCP]	Digital		1794	Boolean		GCP	1		
				Auto Stop [GCP]	Digital		1795	Boolean		GCP	1		
				Abnormal trip	Digital		1796	Boolean		GCP	1		
				Running	Digital		1797	Boolean		GCP	1		
				Auto mode	Digital		1798	Boolean		GCP	1		
			No.2 F.O drain tank heater	Auto start [GCP]	Digital		1799	Boolean		GCP	1		
				Auto Stop [GCP]	Digital		1800	Boolean		GCP	1		
				Abnormal trip	Digital		1801	Boolean		GCP	1		
				Running	Digital		1802	Boolean		GCP	1		
				Auto mode	Digital		1803	Boolean		GCP	1		
183	IM26		No.1 HT Radiator Fan Motor	Auto start [GCP]	Digital		94	Boolean		GCP#1	1		
				Auto Stop [GCP]	Digital		95	Boolean		GCP#1	1		
				Abnormal trip	Digital		96	Boolean		GCP#1	1		
				Running	Digital		97	Boolean		GCP#1	1		
				Auto mode	Digital		98	Boolean		GCP#1	1		
			No.2 HT Radiator Fan Motor	Auto start [GCP]	Digital		494	Boolean		GCP#2	1		
				Auto Stop [GCP]	Digital		495	Boolean		GCP#2	1		
				Abnormal trip	Digital		496	Boolean		GCP#2	1		
				Running	Digital		497	Boolean		GCP#2	1		
				Auto mode	Digital		498	Boolean		GCP#2	1		
			No.3 HT Radiator Fan Motor	Auto start [GCP]	Digital		894	Boolean		GCP#3	1		
				Auto Stop [GCP]	Digital		895	Boolean		GCP#3	1		
				Abnormal trip	Digital		896	Boolean		GCP#3	1		
				Running	Digital		897	Boolean		GCP#3	1		
				Auto mode	Digital		898	Boolean		GCP#3	1		
			No.4 HT Radiator Fan Motor	Auto start [GCP]	Digital		1294	Boolean		GCP#4	1		
				Auto Stop [GCP]	Digital		1295	Boolean		GCP#4	1		
				Abnormal trip	Digital		1296	Boolean		GCP#4	1		
				Running	Digital		1297	Boolean		GCP#4	1		
				Auto mode	Digital		1298	Boolean		GCP#4	1		
184	IM38		No.1 LT Radiator Fan Motor	Auto start [GCP]	Digital		99	Boolean		GCP#1	1		
				Auto Stop [GCP]	Digital		100	Boolean		GCP#1	1		
				Abnormal trip	Digital		101	Boolean		GCP#1	1		
				Running	Digital		102	Boolean		GCP#1	1		
				Auto mode	Digital		103	Boolean		GCP#1	1		
			No.2 LT Radiator Fan Motor	Auto start [GCP]	Digital		499	Boolean		GCP#2	1		
				Auto Stop [GCP]	Digital		500	Boolean		GCP#2	1		
				Abnormal trip	Digital		501	Boolean		GCP#2	1		
				Running	Digital		502	Boolean		GCP#2	1		
				Auto mode	Digital		503	Boolean		GCP#2	1		
			No.3 LT Radiator Fan Motor	Auto start [GCP]	Digital		899	Boolean		GCP#3	1		
				Auto Stop [GCP]	Digital		900	Boolean		GCP#3	1		
				Abnormal trip	Digital		901	Boolean		GCP#3	1		
				Running	Digital		902	Boolean		GCP#3	1		
				Auto mode	Digital		903	Boolean		GCP#3	1		
			No.4 LT Radiator Fan Motor	Auto start [GCP]	Digital		1299	Boolean		GCP#4	1		
				Auto Stop [GCP]	Digital		1300	Boolean		GCP#4	1		
				Abnormal trip	Digital		1301	Boolean		GCP#4	1		
				Running	Digital		1302	Boolean		GCP#4	1		
				Auto mode	Digital		1303	Boolean		GCP#4	1		
185	IM31		Drain discharge pump	Abnormal trip	Digital		1804	Boolean		GCP	1		
				Running	Digital		1805	Boolean		GCP	1		
186	IM32		Make up water pump	Abnormal trip	Digital		1806	Boolean		GCP	1		
				Running	Digital		1807	Boolean		GCP	1		
	I20		No.1 LO purifier heater	Abnormal trip	Digital		104	Boolean		GCP	1		
				Running	Digital		105	Boolean		GCP	1		
			No.2 LO purifier heater	Abnormal trip	Digital		504	Boolean		GCP	1		

187				Running	Digital		505	Boolean		GCP	1		
			No.3 LO purifier heater	Abnormal trip	Digital		904	Boolean		GCP	1		
				Running	Digital		905	Boolean		GCP	1		
			No.4 LO purifier heater	Abnormal trip	Digital		1304	Boolean		GCP	1		
				Running	Digital		1305	Boolean		GCP	1		
188	IM21		No.1 LO purifier pump	Abnormal trip	Digital		106	Boolean		GCP	1		
				Running	Digital		107	Boolean		GCP	1		
			No.2 LO purifier pump	Abnormal trip	Digital		506	Boolean		GCP	1		
				Running	Digital		507	Boolean		GCP	1		
			No.3 LO purifier pump	Abnormal trip	Digital		906	Boolean		GCP	1		
				Running	Digital		907	Boolean		GCP	1		
			No.4 LO purifier pump	Abnormal trip	Digital		1306	Boolean		GCP	1		
				Running	Digital		1307	Boolean		GCP	1		
189	IM34		Sludge transfer pump	Auto start [GCP]	Digital		1824	Boolean		GCP	1		LCBS: Start, Stop Push button [manual]
				Auto Stop [GCP]	Digital		1825	Boolean		GCP	1		
				Abnormal trip	Digital		1826	Boolean		GCP	1		
				Running	Digital		1827	Boolean		GCP	1		
				Auto mode	Digital		1828	Boolean		GCP	1		
		Spare		Auto start [GCP]	Digital		1829	Boolean		GCP	1		
				Auto Stop [GCP]	Digital		1812	Boolean		GCP	1		
				Abnormal trip	Digital		1813	Boolean		GCP	1		
				Running	Digital		1832	Boolean		GCP	1		
190				Auto mode	Digital		1833	Boolean		GCP	1		
	IM35		No.1 Oily water drain pump	Abnormal trip	Digital		1834	Boolean		GCP	1		
				Running	Digital		1835	Boolean		GCP	1		
			No.2 Oily water drain pump	Abnormal trip	Digital		1836	Boolean		GCP	1		
				Running	Digital		1837	Boolean		GCP	1		
191	IM33		Water supply pump	Abnormal trip	Digital		1838	Boolean		GCP	1		
				Running	Digital		1839	Boolean		GCP	1		
192	IM37		Lighting for Engine room	Fault	Digital		1840	Boolean		GCP	1		
193			Control Panel	Fault	Digital		1841	Boolean		GCP	1		
194			No.1 OMD	Fault	Digital		1842	Boolean		GCP	1		
			No.2 OMD	Fault	Digital		1843	Boolean		GCP	1		
			No.3 OMD	Fault	Digital		1844	Boolean		GCP	1		
			No.4 OMD	Fault	Digital		1845	Boolean		GCP	1		
195			Heat trace No.1	Fault	Digital		1846	Boolean		GCP	1		
			Heat trace No.2	Fault	Digital		1847	Boolean		GCP	1		
			Heat trace No.3	Fault	Digital		1848	Boolean		GCP	1		
			Heat trace No.4	Fault	Digital		1849	Boolean		GCP	1		
			Heat trace No.5	Fault	Digital		1850	Boolean		GCP	1		
			Heat trace No.6	Fault	Digital		1851	Boolean		GCP	1		
			Heat trace No.7	Fault	Digital		1852	Boolean		GCP	1		
			Heat trace No.8	Fault	Digital		1853	Boolean		GCP	1		
			Heat trace No.9	Fault	Digital		1854	Boolean		GCP	1		
			Heat trace No.10	Fault	Digital		1855	Boolean		GCP	1		
			Heat trace No.11	Fault	Digital		1856	Boolean		GCP	1		
			Heat trace No.12	Fault	Digital		1857	Boolean		GCP	1		
			Heat trace No.13	Fault	Digital		1858	Boolean		GCP	1		
			Heat trace No.14	Fault	Digital		1859	Boolean		GCP	1		
			Heat trace No.15	Fault	Digital		1860	Boolean		GCP	1		
			Heat trace No.16	Fault	Digital		1861	Boolean		GCP	1		
			Heat trace No.17	Fault	Digital		1862	Boolean		GCP	1		
			Heat trace No.18	Fault	Digital		1863	Boolean		GCP	1		
			Heat trace No.19	Fault	Digital		1864	Boolean		GCP	1		
			Heat trace No.20	Fault	Digital		1865	Boolean		GCP	1		
			Heat trace No.21	Fault	Digital		1866	Boolean		GCP	1		
			Heat trace No.22	Fault	Digital		1867	Boolean		GCP	1		
			Heat trace No.23	Fault	Digital		1868	Boolean		GCP	1		
			Heat trace No.24	Fault	Digital		1869	Boolean		GCP	1		
196													
			Drums	Fault	Digital					GCP	1		DRUMS will provide fault dry contacts for DC Supply 1 and DC Supply 2 for its redundant power supply modules and there will be "No GCP connection fault" dry contact
197	50,51	D/G#1	VCB TRIP(50,51,51N,86,59,27,87G,40,32R,46,81)				108	Boolean	0.5	GCP#1	1		
	50,51	D/G#2	VCB TRIP(50,51,51N,86,59,27,87G,40,32R,46,81)				508	Boolean	0.5	GCP#2	1		
	50,51	D/G#3	VCB TRIP(50,51,51N,86,59,27,87G,40,32R,46,81)				908	Boolean	0.5	GCP#3	1		
	50,51	D/G#4	VCB TRIP(50,51,51N,86,59,27,87G,40,32R,46,81)				1308	Boolean	0.5	GCP#4	1		

[illegible]