

OCR:Relay1

MFR:ABBTag #:CTBase kVIf (kA)

Model:RET 615Phase:150:1

GND:150:1

OC Level: OC1

	Range	Setting
Phase TOC IEC Very Inverse		
Pickup (Tap)	0.05 - 5 xCT Sec	0.860
Time Dial		2.000
Phase INST Pickup	1 - 40 xCT Sec	9.540
Time Delay	0.02 - 200 Sec	0.490
Ground TOC ANSI Extremely Inverse		
Pickup (Tap)	0.01 - 5 xCT Sec	1.895
Time Dial		15.000
Ground INST Pickup	1 - 40 xCT Sec	9.740
Time Delay	0.02 - 200 Sec	3.840

OLR:Relay1

MFR:ABBTag #:CTBase kVIf (kA)

Model:RET 615Phase:150:1

GND:150:1

CB:CB2

MFR:ABBTag #:3-Phase kA:0.00Sym. (Calc.)

Model:E3HRating:220 kA, 0.415 kVLG kA:0.00Sym. (Calc.)

Size:3200Rated Amp:3200.000Base kV:0.000(Calc.)

LV Solid State Trip Device

MFR:ABB

Model:SACE PR111

Sensor:3200

	Phase Setting	Ground Setting
Long-Time LT Pickup	0.9	Ground Pickup0.4
LT Band	Curve A	Ground BandCurve C I ^{xt} =IN
Short-Time ST Pickup	10	
ST Band	Curve D I ^{xt} =OUT	

Protective Device Settings

CB: CB3

MFR:	ABB	Tag #:	3-Phase kA:	0.00	Sym. (Calc.)	
Model:	E2S(2005)	Rating:	187 kA, 0.415 kV	LG kA:	0.00	Sym. (Calc.)
Size:	1000	Rated Amp:	1000.000	Base kV:	0.000	(Calc.)

LV Solid State Trip Device

MFR: ABB
Model: SACE PR121/P (IEC)
Sensor: 1000
Rating Plug: 1000.00

Phase Setting

Ground Setting

Long-Time I1	1.00	Multiples t1	k/I^2	I4	0.2	
t1	54.0000			t4	0.1	I^xt=OUT
INST I3	15					

CB: CB4

MFR:	ABB	Tag #:	3-Phase kA:	0.00	Sym. (Calc.)	
Model:	E2S(2005)	Rating:	187 kA, 0.415 kV	LG kA:	0.00	Sym. (Calc.)
Size:	800	Rated Amp:	800.000	Base kV:	0.000	(Calc.)

LV Solid State Trip Device

MFR: ABB
Model: SACE PR121/P (IEC)
Sensor: 800
Rating Plug: 800.00

Phase Setting

Ground Setting

Long-Time I1	1.00	Multiples t1	k/I^2	I4	0.2	
t1	21.0000			t4	0.1	I^xt=OUT
INST I3	10					

CB: CB5

MFR:	ABB	Tag #:	3-Phase kA:	0.00	Sym. (Calc.)	
Model:	E2S(2005)	Rating:	187 kA, 0.415 kV	LG kA:	0.00	Sym. (Calc.)
Size:	1600	Rated Amp:	1600.000	Base kV:	0.000	(Calc.)

LV Solid State Trip Device

MFR: ABB
Model: SACE PR121/P (IEC)
Sensor: 1600
Rating Plug: 1600.00

Phase Setting

Ground Setting

Long-Time I1	0.73	Multiples t1	k/I^2	I4	0.2	
t1	9.0000			t4	0.1	I^xt=OUT
INST I3	5					