

Interfacing 'CM CCTV systems' deployed in 'PMI Electric buses CESL2 Projects' with DTC designated – QT Loads' – API Document

Content

Content	1
Introduction	2
1. Login Verification Interface	2
1.1 Verification Interface	2
2. Alarm Data Interface	3
2.1 Get alarm statistics information	3
2.2 Get alarm detail information	4
3. Device Status Data Interface	6
3.1 Get status data interface	6
3.2 Get device online / offline information	8
3.3 Get device final status information.....	9
4. Live Video Interface	10
4.1 Get video port information	10
4.2 Get video stream address (flv way)	11
5. History Video Interface	13
5.1 Get history video monthly calendar information	13
5.2 Get history video file information	14
5.3 Get historical video stream information (HIS way) [n9m]	16
6. Video Download Interface	17
6.1 Create video download task	17
6.2 Get video download task status.....	19
6.3 Query video file list of completed task	21
6.4 Download the recording file to the local	23
6.5 Delete video download task	23
7. Passenger flow data interface	25
7.1 Query passenger flow detail	25
8. Evidence Uploading Interface	27
8.1 Evidence search list no. Query	27
8.2 Evidence search list detail query.....	28
8.3 Get Specific evidence Image Information.....	32
8.4 Get specific Evidence details.....	33
8.5 Get a list of specific evidence Video.....	36
8.6 Generate Evidence File.....	38
8.7 Query server Information.....	39
8.8 Evidence Alarm Track.....	40
8.9 Special Notes	42
9 Two Way VOIP Calling	42

Introduction

1. The API is used for customer integration with "CM Server Application".
2. This document is being provided to M/s PMI & QT Loads (DTC designated Authority) for exclusive use & interfacing 'CM CCTV systems' deployed in 'PMI Electric buses CESL2 Projects'

1.Login Verification Interface

1.1 Verification Interface

function introduction	generate an authentication key through the username, password and verification code. key is the basis of all interfaces
address:	https://cmmipl.org:22056/api/v1/basic/key?username=XXXX&password=XXXX
request:	GET
request body:	None
parameter description:	Username: username Password: password
response:	<pre>{ • - "data": { "key": "123aaeq3jjkljrweoiu" }, • "errorcode": 200 }</pre>
response description:	data:data result key:[string]verify key errorcode:error code

2.Alarm Data Interface

2.1 Get The Alarm Statistics Information

function introduction	query the total number of alarms for vehicles under the authority at the specified time
address:	https://cmmipl.org:22056/api/v1/basic/alarm/count
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrqueoiu", • - "terid": [○ "AE99873120"], • "type": 13, • "starttime": "2026-04-19 00:00:00", • "endtime": "2026-04-19 23:59:59" }</pre>
parameter description:	key:[string] verify key terid:[string] The terminal number ID array type:[int] Alarm type starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss
response:	<pre>{ "data": [{ • "terid": "AE99873120", • "date": "2026-04-19", • "count": 5687 }] }</pre>

2.1 Get The Alarm Statistics Information	
	<pre>}], • "errorcode": 200 }</pre>
response description:	data:[]data array terid:[string] device serial number date:[string]date(yyyy-MM-dd) count:[int]count errorcode:error code
2.2 Get alarm detail information	
function introduction	query vehicle alarm information list under the authority
address:	https://cmmipl.org:22056/api/v1/basic/alarm/detail
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrqueoiu", • - "terid": [○ "AE99873120"], • - "type": [○ 13], • "starttime": "2026-04-19 00:00:00", • "endtime": "2026-04-20 00:00:00" }</pre>

2.2 Get alarm detail information	
parameter description:	key:[string]verify key terid:[string] The terminal number ID array type:[[int]] Array of alarm types, [] check all alarm types starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss
response:	<pre>{ • - "data": [○ - { "terid": "AE99873120", "gpstime": "2026-04-19 00:00:00", "altitude": 600, "direction": 45, "gpslat": "23.654123", "gpslng": "108.432143", "speed": 80, "recordspeed": 0, "state": 0, "time": "2026-04-19 00:00:00", "type": 13, "content": "EMR / Urgency", "cmdtype": 2 }], "errorcode": 200 }</pre>

2.2 Get alarm detail information

response description:	data:[data array altitude:[int] altitude direction:[int] directi gpslat:[string] latitude gpslng:[string] longitude gpstime:[string]GPS time (yyyy-MM-dd HH:mm:ss) speed:[int] speed recordspeed:[int] Tachograph speed state:[int]Status, temporarily unavailable Terid:[array] device ID time:[string]Server time(yyyy-MM-dd HH:mm:ss) type:[int] Alarm type content:Alarm content cmdtype:[int]Alarm state 2: alarm, 1: alarm relief errorcode:error code
-----------------------	--

3.Device Status Data Interface

3.1 Device Status Data Interface

function introduction	query the list of device online and offline information under the authority
address:	https://cmmpi.org:22056/api/v1/basic/state/log
request:	POST
request body:	<pre>{ "key": "123aaeq3jjkljrweoiu", - "terid": ["AE99873120"</pre>

3.1 Device Status Data Interface	
	<pre>], • "starttime": "2026-04-19 00:00:00", • "endtime": "2026-04-19 23:59:59" }</pre>
parameter description:	key:[string]verify key terid:[string] The terminal number ID array starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss
response:	<pre>{ • - "data": [○ - { • "terid": "AE99873120", • "time": "2026-04-19 00:23:59", • "type": 1 }], • "errorcode": 200 }</pre>
response description:	data:[]data array terid:[string] device serial number time:[string]state time(yyyy-MM-dd HH:mm:ss) type:[int]Status 0: offline, 1: online errorcode:error code

3.2 Get device online/offline information

function introduction	query whether the device under permission is online at this time
address:	https://cmmipl.org:22056/api/v1/basic/state/now
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • - "terid": [○ "AE99873120"] }</pre>
parameter description:	key:[string] verify key terid:[string] The terminal number ID array, If the current user is a super administrator and the terminal ID is an empty array, query all current online devices
response:	<pre>{ • - "data": [○ -] { • "terid": "AE99873120" } }, • "errorcode": 200 }</pre>

3.2 Get device online/offline information

response description:	data:[]data array
	terid:[string]Online terminal number
	errorcode:error code

3.3 Get device final status information

function introduction	query the time information of the last online status of the device under the authority
address:	https://cmmipl.org:22056/api/v1/basic/state/last
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • - "terid": [○ "AE99873120"] }</pre>
parameter description:	key:[string]verify key terid:[string] The terminal number ID array
response:	<pre>{ • - "data": [○ - { • "terid": "AE99873120", • "time": "2026-04-16 23:56:57" }], }</pre>

3.3 Get device final status information

	• "errorcode": 200
response description:	<pre> data:[]data array terid:[string] device serial number time:[string]state time(yyyy-MM-dd HH:mm:ss) errorcode:error code </pre>

4.Live Video Interface**4.1 Get video port information**

function introduction	query the list of video pass-through ports configured in the system
address:	https://cmmpi.org:22056/api/v1/basic/live/port
request:	GET
request header:	<pre> { • "key": "123aaeq3jjkljrweoiu" } </pre>
request body:	none
parameter description:	key:[string]verify key
response:	<pre> { • - "data": [○ - { • "port": 12060 }, ○ -] } </pre>

4.1 Get video port information

	<pre>{ "port": 12061 }, { "errorcode": 200 }</pre>
response description:	data:[]Number of sets of port data port:[int]port errorcode:error code

4.2 Get video stream address address ([flv way](#))[cms/n9m]

function introduction	obtain the address of the playable video stream according to the current interface protocol through the available port returned by the first interface. Note: A port can configure up to 4 channels
operation steps	step 1: pass log in to the authentication interface to obtain the unique identification key step 2: call the 'Get video port information' interface to get the available video ports step 3: call the 'Get device list' interface to return all device information, and then query the information of the device through the device number or license plate number, including the available channels of the device step 4: assemble the interface according to the interface rules, combined with the data returned in step 2 and step 3, and then initiate http/https requests to obtain the required data
address:	https://cmmipl.org:22056/api/v1/basic/live/video?terid=00830007CB&chl=1&audio=1&st=0&port=12060
request:	GET

4.2 Get video stream address address ([flv way](#))[cms/n9m]

request header:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu" }</pre>
remark:	PS:Because when playing video in HTTP continuous stream mode of FLV, the limit of the number of concurrent downloads will be received from the browser, and the limit is different from browser to browser. It is suggested to open 4-way video on one port and 16-way video at most at the same time
parameter description:	key:[string]verify key terid:[string] device serial number chl:[int]Channel audio:[int]Audio 0: none,1: yes st:[int]Codestream type 0: main codestream,1: sub codestream port:[int]Video port dt:[string]Device type, optional parameter,n9m device is not transmitted, CMS device is transmitted dt=MDVR
response:	<pre>{ • - "data": { • "url": <a "="" href="https://cmmipl.org:12060/live.flv?devid=006000E4C0&chl=1&st=1&audio=1&svrip=127.0.0.1&svrport=17891&token=jYZi%2FP%2FAJPTDkBH%2F9lejs6Wie0zTACJJbNvi7Smh2eNXq1g\">"https://cmmipl.org:12060/live.flv?devid=006000E4C0&chl=1&st=1&audio=1&svrip=127.0.0.1&svrport=17891&token=jYZi%2FP%2FAJPTDkBH%2F9lejs6Wie0zTACJJbNvi7Smh2eNXq1g\"" }, • "errorcode": 200 }</pre>
response description:	data:Video address url:[string]address errorcode:error code

5.History Video Interface

5.1 Get history video monthly calendar information

function introduction	query the date information containing the video from the device under the permission
address:	https://cmmipl.org:22056/api/v1/basic/record/calendar?terid=00830007CB&starttime=2017-01-01&st=1&pbt=1
request:	GET
request header:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu" }</pre>
request body:	none
parameter description :	key:[string]verify key terid:[string] device serial number starttime:[string]Start time (the month of this time is the query month) st:[string]Codestream type 0-sub stream; 1-main stream pbt:[string]Information Source,0:Device(default),1:Server
response:	<pre>{ • - "data": [• - { • "date": "2017-06-17", • "filetype": 1 }], • "errorcode": 200 }</pre>

5.1 Get history video monthly calendar information

response description :	data:[]data array date:[string]date(yyyy-MM-dd) filetype:[int]File type. 1 -- normal recording; 2 -- alarm recording errorcode:error code
------------------------	---

5.2 Get the historical video file information

function introduction	query the video file list information of the device under the specified date, channel, and stream under the permission. The year and month of the start time and end time can be obtained through the return value of the first interface
operation steps	step 1: pass log in to the authentication interface to obtain the unique identification key step 2: call the 'Get history video monthly calendar information' interface to get the historical video monthly calendar information of the specified device step 3: call the 'Get device list' interface to return all device information, and then query the information of the device through the device number or license plate number, including the available channels of the device step 4: assemble the interface according to the interface rules, combined with the data returned in step 2 and step 3, and then initiate http/https requests to obtain the required data
address:	https://cmmipl.org:22056/api/v1/basic/record/filelist?terid=00830007CB&starttime=2017-01-01 00:00:00&endtime=2017-01-01 23:59:59&chl=1,2,3,4&st=1&pbt=1
request:	GET
request header:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu" }</pre>
request body:	none

5.2 Get the historical video file information	
parameter description :	key:[string]verify key terid:[string] device serial number starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss chl:[string]Channel id(multiple, split) st:[string]Codestream type 0-sub stream; 1-main stream pbt:[string]Information Source,0:Device(default),1:Server
response:	<pre>{ • - "data": [○ - { ▪ "name": "0-1-0", ▪ "chn": 1, ▪ "filetype": 1, ▪ "starttime": "2017-06-19 07:57:26", ▪ "endtime": "2017-06-19 11:59:44" }], • "errorcode": 200 }</pre>

5.2 Get the historical video file information

response description :	data:[]data array name:[string]file name chn:[int]Channel number starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss filetype:[int]File type. 1 -- normal recording; 2 -- alarm recording errorcode:error code
------------------------	--

5.3 Get device historical video stream information ([HIS way](#))

function introduction	get the m3u8 video stream playback address, where the start time, end time, and channel can be obtained through the return value of the second interface
operation steps	step 1: pass log in to the authentication interface to obtain the unique identification key step 2: call the 'Get the historical video file information' interface to get historical video file information step 3: call the 'Get device list' interface to return all device information, and then query the information of the device through the device number or license plate number, including the available channels of the device step 4: assemble the interface according to the interface rules, combined with the data returned in step 2 and step 3, and then initiate http/https requests to obtain the required data
address:	https://cmmipl.org:22056/api/v1/basic/record/video?terid=00830007CB&starttime=2017-06-19 15:20:56&endtime=2017-06-19 16:20:22&chl=1&st=1
request:	GET
request header:	{ "key": "123aaeq3jjkljrqrweoiu" }
request body:	none

5.3 Get device historical video stream information ([HIS way](#))

parameter description:	key:[string]verify key terid:[string] device serial number starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss chl:[int]Channel st:[string]Codestream type 0-sub stream; 1-main stream
response:	<pre>{ • - "data": { ○ "url": "https://cmmipl.org:28090/play/00820000D6/1/20170626002056_20170626003022_main.m3u8" }, • "errorcode": 200 }</pre>
response description:	data:Video address url:[string]address errorcode:error code

6.Video Download Interface

6.1 Add Video Download Task

function introduction	create an ADS download task for the vehicle under the authority, and return a task taskid
address:	https://cmmipl.org:22056/api/v1/basic/record/task
request:	POST

6.1 Add Video Download Task

request body:

```
{  
  • "key": "123aaeq3jjkljrweoiu",  
  • "terid": "00830007CB",  
  • "starttime": "2026-04-01 00:00:00",  
  • "endtime": "2026-04-01 08:00:00",  
  • -  
  "chl": [  
    ○ 1,  
    ○ 2,  
    ○ 3,  
    ○ 4  
  ],  
  • "name": "test",  
  • "effective": 7,  
  • "netmode": 1,  
  • "tasktype": 0,  
  • "stream": 1  
}
```

6.1 Add Video Download Task

parameter description: key:[string] verify key

terid:[string] device serial number

starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss

endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss

chl:[[int]] Array of channel id Numbers

name:[string] Task name (15 characters)

effective:[int] effective days

netmode:[int] Network mode(1:LAN, 2:WIFI, 3:WIFI and LAN, 4:4G, 7:All modes, All modes when this field is empty or does not exist)

tasktype : [int] Task type(0:Black box , 1:Video recording , 2:All types , Note that the starttime and endtime passed when tasktype is 0 must be less than today's date)

stream:[int] stream type 1: main stream (default) 0: sub stream

response:

```
{
  • -
  "data": {
    ○ "taskid": 1
  },
  • "errorcode": 200
}
```

response description: data:response result

taskid:[int] task ID

errorcode:error code

6.2 Get the video download task status

function introduction query the download status of the task through the taskid returned after the ADS is successfully created

address: <https://cmimpl.org:22056/api/v1/basic/record/taskstate>

6.2 Get the video download task status	
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • - "parms": [○ - { ▪ "taskid": 1, ▪ "date": "2026-04-01" }] }</pre>
parameter description:	key:[string]verify key parms:[]Parameter set array taskid:[int]task ID date:[string]Date of the task

6.2 Get the video download task status	
response:	<pre>{ • - "data": [○ - { "percent": 85, "state": 3, "taskid": 1 }], • "errorcode": 200 }</pre>
response description:	data:[int]data array percent:[int]percentage state:[int]Status (-6 pause -5 limited number of connections - in 4 resolution -3 not completed -2 insufficient disk space -1 waiting for 0 resolution to complete 1 downloading 2 no video files 3 task completed 4 task failed 5 deletion 6 download failed 8 task expired) taskid:[int]task ID errorcode:error code
6.3 Get the completed task video files list	
function introduction	through the task taskid and task type, query the directory and file name of the completed task video file. Directory information is base64 encoded
address:	https://cmmipl.org:22056/api/v1/basic/record/taskfilelist?taskid=1&tasktype=1
request:	GET

6.3 Get the completed task video files list

request header:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu" }</pre>
request body:	none
parameter description:	key:[string]verify key taskid:[int]task ID tasktype : [int] Task type(0:Black box , 1:Video recording , 2:All types ,Note that if this value is not passed, the video recording will be queried by default)
response:	<pre>{ • - "data": [○ - { • "dir": "QzpcVmlkZW9ccXExMjM0XDlwMTctMDYtMTlccmVjb3JkXDE=", • "name": "qq1234-170619-000000-002000-01p401000000.264" }, ○ - { • "dir": "QzpcVmlkZW9ccXExMjM0XDlwMTctMDYtMTlccmVjb3JkXDE=", • "name": "qq1234-170619-000000-002000-01p401000000.mp4" }], • "errorcode": 200 }</pre>

6.3 Get the completed task video files list

	}
response description:	data:[]data array name:[string]file name dir:[string]directory errorcode:error code

6.4 Download the recording file to the local

function introduction	through querying the file directory and file name, download the task video in the completed state to the local. Among them, the task directory and file name can be obtained through the previous interface
address:	https://cmmipl.org:22056/api/v1/basic/record/download?key=123aaeq3jjkljrqrweoiu&dir=QzpcVmlkZW9ccXExMjM0XDIwMTctMDYtMTlccmVjb3JkXDE=&name=qq1234-170619-000000-002000-01p401000000.264
request:	GET
request body:	none
parameter description:	key:[string]verify key name:[string]file name dir:[string]directory
response:	[stream]
response description:	[stream]

6.5 Delete recording download task

function introduction	delete created tasks by task taskid
address:	https://cmmipl.org:22056/api/v1/basic/record/task
request:	DELETE

6.5 Delete recording download task	
request body:	<pre>{ • "key": "123aaeq3jjkljrqweoiu", • - "parms": [○ - { ▪ "taskid": 1 }] }</pre>
parameter description:	key:[string]verify key parms:[]task array taskid:[int]task ID
response:	<pre>{ • - "data": { ○ "result": true }, • "errorcode": 200 }</pre>
response description:	data:response data result:Operating results errorcode:error code

7.Passenger flow data interface

7.1 Query passenger flow detail

function introduction	query the vehicle passenger flow statistics list under the authority
address:	https://cmmipl.org:22056/api/v1/basic/passenger-count/detail
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu", • - "terid": [○ "661",], • "starttime": "2026-04-07 00:00:00", • "endtime": "2026-04-13 23:59:59", • "door": "" }</pre>
parameter description:	key:[string]verify key Terid:[array] device ID starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss Door:[string] car door name, the value is empty when the query is all
response:	<pre>{ • - "data": [○ -] { • "closetime": "2026-04-11 14:39:22",</pre>

7.1 Query passenger flow detail	
	<code>"door": ""</code>, <code>"off": 2</code>, <code>"on": 3</code>, <code>"opentime": "2026-04-11 14:39:22"</code>, <code>"sitename": "AAAAA"</code>, <code>"terid": "661"</code>, <code>"time": "2026-04-11 14:39:22"</code>, <code>"lat": 25.331</code>, <code>"lng": 115.5598</code> <code>}</code> <code>],</code> <code>"errorcode": 200</code> <code>}</code>
response description:	<code>data:[json]update result</code> <code>closetime:[string] closing time</code> <code>opentime:[string] Open time</code> <code>Door:[string] car door name, the value is empty when the query is all</code> <code>off:[int] Out of the car number</code> <code>on:[int] Get on the bus number</code> <code>sitename:[string] The site name</code> <code>terid:[string] equipment ID</code> <code>time:[string] time</code> <code>lat:[double] latitude</code> <code>lng:[double] longitude</code> <code>errorcode:[int]error code</code>

8.Evidence Center Interface

8.1 Evidence Search List Number Query	
function introduction	query the total number of vehicle evidence under the authority
address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/count
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • - "terid": [○ "008A000152"], • "starttime": "2026-04-30 00:00:00", • "endtime": "2026-04-02 23:59:59", • - "type": [○ 13], • "keytype": -1, • "keyword": "", • "timetype": 0 }</pre>
parameter description:	key:[string]verify key terid:[[string]] Device ID type:[[int]] Array of alarm types, [] check all alarm types starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss

8.1 Evidence Search List Number Query

	keytype:[int] Keyword type:-1 keyword does not take effect, 0 driver, 1 license plate, 2 evidence name keyword:[string] Keyword value timetype:[int]Evidence query time dimension, 0: alarm time, 1: evidence generation time (default 0)
response:	<pre>{ • - "data": { ○ "total": 4 }, • "errorcode": 200 }</pre>
response description:	data:response result total:[int] Total errorcode:[int]error code

8.2 Evidence Search List Detail Query

function introduction	query the list of vehicle evidence information under the authority
address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/list
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu", • - "terid": [</pre>

8.2 Evidence Search List Detail Query	
	<pre> ○ "008A000152"], • "starttime": "2026-04-30 00:00:00", • "endtime": "2026-04-02 23:59:59", • - "type": [○ 13], • "keytype": -1, • "keyword": "", • "page": 1, • "count": 10, • "context": "", • "timetype": 0 }</pre>
parameter description:	key:[string]verify key terid:[[string]] Device ID type:[[int]] Array of alarm types, [] check all alarm types starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss keytype:[int] Keyword type:-1 keyword does not take effect, 0 driver, 1 license plate, 2 evidence name keyword:[string] Keyword value page:[int] Number of pages, indicating the first few pages. -1 means no paging, return all results count:[int] The number of pages per page. context:[string] The context information returned from the last query can be empty for the first query. Note: The content returned in each query may change, that is, each query must use the context field returned by the previous query

8.2 Evidence Search List Detail Query	
	timetype:[int]Evidence query time dimension, 0: alarm time, 1: evidence generation time (default 0)
response:	<pre>{ • - "data": [○ - { "address": "", "alarmid": "008A000152_145_76", "alarmlevel": -1, "alarmtype": 13, "createtime": "2026-04-02 00:00:39", "driverlicense": "", "drivename": "", "driverphone": "", "driverphoto": "", "eid": "hdtgMmLzRLDp1HQMbfRXvtc%3D", "ename": "EMR / Urgency", "endtime": "2026-04-01 23:59:59", "gpslat": 0, "gpslng": 0, "pic": "QzovRXZpZGVuY2VEYXRhLzlwMTktMDktMDIvNC9DSDAxLTE5MDkwMi0wMDAwMTEtOTk2MTQ4MC5qcGc%3D", "sec": 3, "size": 7.78, "starttime": "2026-04-01 23:59:57", "terid": "008A000152", "time": "2026-04-02 00:00:02", }] }</pre>

8.2 Evidence Search List Detail Query

	▪ "vehicle": "008A000152", ▪ "evidencestatus": 5, ▪ "evidencestatusmsg": "transcoding", ▪ "evidenceservername": "", ▪ "direction": 251, ▪ "desc": "" <pre> }], • "context": "", • "errorcode": 200 } </pre>
response description:	data:response result eid:[string] Evidence ID ename:[string] Evidence Name alarmid:[string] Alarm ID alarmtype:[int] Alarm Type alarmlevel:[int] Alarm Level terid:[[string]] Device ID vehicle:[string] Carlicense drivername:[string] Driver Name driverphone:[string] Driver Phone driverImg:[string]Driver Image Path(base64 encoding) driverlicense:[string] Driver License time:[string] Evidence Time createtime:[string] Evidence Create Time starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss gpslng:[double] Longitude

8.2 Evidence Search List Detail Query

gpslat:[double] Latitude
 address:[string] Evidence Address
 size:[double] Evidence Size(in MB)
 sec:[int] Evidence Length(seconds)
 pic:[int] Cover image path (base64 encoding)
 evidencestatus:[int] Evidence status 0:evidence completed,1: Evidence failure1,2: Queuing,3: Downloading,4: Download completed,5: Transcoding
 evidencestatusmsg:[string] Evidence status description
 evidenceservername:[string] Evidence file storage server alias
 direction:[int] direction
 desc:[string] Describe the evidence
 errorcode:[int]error code
 context:[string] Context information generated by this query

8.3 Get Specified Evidence Image Information

function introduction	query the list of specified evidence pictures, where the evidence eid is obtained through the previous interface
address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/picture/list
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu", • "eid": "hdtgMmLzRLDp1HQMbfRXvtc%3D" }</pre>
parameter	key:[string]verify key eid:[string] Evidence ID

8.3 Get Specified Evidence Image Information

description:	
response:	<pre>{ • - "data": [○ - { "channel": 1, "path": "QzovRXZpZGVuY2VEYXRhLzlwMTktMDgtMzAvMS9DSDAxLTE5MDgzMC0yMDMzMTEtOTk2MTQ3Ny5qcGc%3D" }], "errorcode": 200 }</pre>
response description:	data:response result path:[int] Cover image path (base64 encoding) channel:[int]Channel errorcode:[int]error code

8.4 Get Specified Evidence Details

function introduction	query the detailed information list of the specified evidence
address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/detail
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • - }</pre>

8.4 Get Specified Evidence Details	
	<pre>"eid": [○ "hdtgMmLzRLDp1HQMbfRXvtc%3D"] }</pre>
parameter description:	key:[string]verify key eid:[[string]] Evidence ID
response:	<pre>{ • - "data": [○ - { ▪ "eid": "hdtgMmLzRLDp1HQMbfRXvtc%3D", ▪ "size": 2.54, ▪ "terid": "0098000094", ▪ "groupname": "20260406", ▪ "carlicense": "98k", ▪ "platecolor": 2, ▪ "alarmtype": 6, ▪ "speed": 0, ▪ "starttime": "2026-04-06 14:00:25", ▪ "endtime": "2026-04-06 14:00:29", ▪ "lat": 0, ▪ "lng": 0, ▪ "location": "", ▪ "drivername": "zhmh1111", ▪ "driverphone": "13983825164", ▪ "driverlicense": "zhmh1111",</pre>

8.4 Get Specified Evidence Details	
	<code>"driverimg": ""</code>, <code>"handleusername": "xxx"</code>, <code>"handletime": "2026-04-06 14:45:41"</code>, <code>"handlemethod": 6</code>, <code>"handlecontent": ""</code>, <code>"evidencestatus": 5</code>, <code>"evidencestatusmsg": "transcoding"</code> <code>}</code> <code>],</code> <code>"errorcode": 200</code> <code>}</code>
response description:	<code>data:response result</code> <code>eid:[string] Evidence ID</code> <code>size:[double] Evidence Size(in MB)</code> <code>terid:[[string]] Device ID</code> <code>groupname:[string]groupname</code> <code>carlicense:[string] Carlicense</code> <code>platecolor:[int]License plate color, default 1 (1: blue 2: yellow 3: black 4: white 5: green)</code> <code>alarmtype:[int] Alarm Type</code> <code>speed:[double]Speed</code> <code>starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss</code> <code>endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss</code> <code>lat:[double] latitude</code> <code>lng:[double] longitude</code> <code>position:[string]Position Information</code> <code>drivername:[string] Driver Name</code> <code>driverphone:[string] Driver Phone</code>

8.4 Get Specified Evidence Details

	driverlicense:[string] Driver License driverImg:[string]Driver Image Path(base64 encoding) handleusername:[string]The name of user who handled the driver handletime:[string]Handle Time handlemethod:[int]Handle Method handlecontent:[string]Handle Content evidencestatus:[int] Evidence status 0:evidence completed,1: Evidence failure1,2: Queuing,3: Downloading,4: Download completed,5: Transcoding evidencestatusmsg:[string] Evidence status description errorcode:[int]error code
--	---

8.5 Get a List of Specified Evidence Videos

function introduction	query the video list information of the specified evidence. The returned video path is base64 and url encoded
address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/video/list
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • "eid": "hdtgMmLzRLDp1HQMbfRXvtc%3D", • "type": 0 }</pre>
parameter description:	key:[string]verify key eid:[string] Evidence ID type:[int]Video type, 0:264, 1:mp4 (default mp4)
response:	<pre>{ • - "data": [</pre>

8.5 Get a List of Specified Evidence Videos	
	<pre> ○ - { ▪ "channel": 1, ▪ - "video": [▪ - { ▪ "starttime": "2026-04-30 20:33:05", ▪ "endtime": "2026-04-30 20:33:14", ▪ "path": "QzovRXZpZGVuY2VEYXRhLzlwMTktMDgtM zAvMS8wMDhBMDAwMTUyMDAwMDAwLT E5MDgzMCOyMDMzMDUtMjAzMzEOLTxcD lxMTAwMDAwMC4yNjQ%3D" }] }, • "errorcode": 200 } </pre>
response description:	data:response result channel:[int]Channel video:[array string]Video information starttime: [string] start time, the format YYYY-MM-dd HH:mm:ss endtime: [string] end time, the format YYYY-MM-dd HH:mm:ss path:[string]Video Path errorcode:[int]error code

8.6 Generate evidence file

function introduction	pack the specified evidence file to generate a zip archive, and return the base64 and url-encoded download address
address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/filepack
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • "serverip": "127.0.0.1", • "eid": "hdtgMmLzRLDp1HQMbfRXvtc%3D" }</pre>
parameter description:	key:[string]verify key serverip:[string]Server IP eid:[string] Evidence ID
response:	<pre>{ • - "data": { • "path": "QzovRXZpZGVuY2VEYXRhLzlwMTktMDgtMzAvMS8wMDhBMDAwMTUyMDAwMDAwLTE5MDgzMCOyMDMzMdUzMjAzMzE0LTxcDlxMTAwMDAwMC56aXA=" }, • "errorcode": 200 }</pre>
response description:	data:response result path:[string]Evidence compressed file path (base64 encoding and url encoding) errorcode:[int]error code

8.7 Query server information

function introduction	query the system evidence distributed server information, and the evidence in the evidence list matches the server information through servername
address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/evidenceserverinfo
request:	POST
request body:	<pre>{ • "key": "123aaeq3jjkljrqrweoiu" }</pre>
parameter description:	key:[string]verify key
response:	<pre>{ • - "data": [• - { • "serverip": "127.0.0.1", • "servername": "mainserver", • "serverrectport": 3113, • "wcms5port": 12056 }], • "errorcode": 200 }</pre>

8.7 Query server information

response description:	data:response result
	servername:[string] Evidence file storage server alias
	serverip:[string]Server IP
	wcms5port:[int]React service port
	errorcode:[int]error code

8.8 Evidence alarm track

function introduction	query the relevant alarm and trajectory information of the specified evidence
-----------------------	---

address:	https://cmmipl.org:22056/api/v1/basic/evidence-center/relatedgpsalarm
----------	---

request:	POST
----------	------

request body:	<pre>{ • "key": "123aaeq3jjkljrweoiu", • "eid": "hdtgMmLzRLDp1HQMbfRXvtc%3D" }</pre>
---------------	--

parameter description:	key:[string]verify key eid:[string] Evidence ID
------------------------	--

response:	<pre>{ • "errorcode": 200, • "errorcase": "Success!", • - "result": { • "relatedGpsLong": "", • "relatedGpsShort": "", • - "relatedAlarm": [• -] } }</pre>
-----------	--

8.8 Evidence alarm track

```
{
  "alarmType": 1,
  "isCurrent": 1,
  "lat": 23.593116,
  "lng": 104.11321,
  "loc": "",
  "time": "2026-04-19 11:03:05",
  "uuid": "0099002BB1_6_606"
}
```

```
response
description:
  errorcode:[int]error code
  errorcase:[string]Error description
  result:response result
  relatedGpsLong:[string]GPS information within 1 hour before and after the alarm:
    multiple GPS, separated by ';'
  relatedGpsShort:[string]GPS information within 5 minutes before and after the
    alarm: multiple GPSs, separated by ';'
  relatedAlarm:response result
  lat:[double] latitude
  lng:[double] longitude
  uuid:[string]Uniquely identifies
  time:[string]Alarm time
  alarmtype:[int] Alarm Type
  loc:[string]Alarm location
  isCurrent:[int]Whether it is an alarm of current evidence
```

8.9 Special Notes

1. Evidence Video is configured & to be used only for Alarm types

Alarm Description – Code

i) Emergency Alarm EMR – 13

ii) Abnormal storage alarm (Hard Disc Full / Missing) – 4

iii) illegal shutdown – 20

iv) Intrusion Alarm – 99

2. QT Loads is expected to access & download this information as soon as the alarm is generated.

3. QT Loads is expected to download all Evidence Video for the day latest by End of the shift.

4. Evidence Video information can also be downloaded using CM Client Application directly from the CM Server application.

9. Two Way Calling

Intercom function calling steps:

1、 Get authentication key , [Refer to the authentication interface description document](#)

```
https://cmmipl.org:22056/api/v1/basic/key?username=xxx&password=xxx
```

2、 Get the token of websocket

```
let url = https://cmmipl.org:22056/api/v1/basic/talk/token
let tokendata = await axios({
  method: 'post',
  url: url,
  params: {
    terid: xxx,
    key: xxx
  }
});
```

Field parsing:

terid:[string] Vehicle equipment number, the vehicle must meet two conditions: 1) the vehicle is online 2) the vehicle must be under the authority of the logged-in person

key:Key:

3.Introduce the html265.js file into the page, [Download html265 file](#)

```
<script src="./html265/html265.js"></script>
```

4.Call intercom method
Start talk:

```
let url = tokendata.data.url;
let svrip = tokendata.data.svrip;
let svrport = tokendata.data.svrport;
var talker = streamaxPlayer.default.createIntercom({
  mediaUrl: url,
  devId: devId,
  transIp: svrip,
  transPort: svrport,
  onLoad: () => {},
  onError: error => {
    console.error(error);
  },
  audioClose: () => {}
});
```

Field parsing:

mediaUrl:[string] websokect url

devId:[string] Vehicle equipment number, the vehicle must meet two conditions: 1) the vehicle is online 2) the vehicle must be under the authority of

the logged-in person

transIp:[string] Forward server IP or domain name

transPort:[number] Forward server port

onLoad:Call method on load

onError:onError:[function] Returns the error method, -1 indicates the stream url is wrong -2 indicates the decoder has not been initialized -3 indicates the stream failed -4 indicates the stream is interrupted

audioClose:Method called when closing intercom

End talk:

```
talker.stop();
```

```
talker = null
```

Special Note:

1. VOIP call to Driver can also be performed using CM Client Application, directly from the CM Server application, on Laptop & on Smart Phone using CM Mobile application