

Troubleshooting Flow: Wireless Mouse Unresponsive While Keyboard Works

Step 1: Check the mouse power and physical condition

- What I'm checking for: Whether the mouse itself has power or a hardware issue.
 - Confirm the mouse is switched on.
 - Replace or recharge the batteries.
 - Check for a blinking indicator light (if available).
 - Clean the sensor area and ensure the mouse is being used on a suitable surface.
 - If the mouse starts working: The issue was likely power-related.
 - If it remains unresponsive: Continue.
-

Step 2: Check the wireless connection

- What I'm checking for: Whether the mouse is communicating with the computer.
 - Confirm the USB wireless receiver/dongle is securely connected.
 - If the mouse has a pairing button, re-pair it with the receiver.
 - Move the mouse closer to the receiver to rule out signal interference.
 - Remove nearby devices that may cause wireless interference.
 - If the mouse reconnects: The issue was a lost wireless connection.
 - If not: Continue.
-

Step 3: Test the USB receiver and USB port

- What I'm checking for: Whether the USB port or receiver is causing the failure.
 - Remove the mouse receiver and plug it into a different USB port.
 - Test the original USB port with another device (such as a flash drive).
 - Test the mouse receiver on another computer if possible.
 - Results:
 - Mouse works on another USB port → original USB port may be faulty.
 - Other devices fail on the same USB port → USB port issue.
 - Receiver fails on another computer → receiver or mouse hardware issue.
-

Step 4: Check system settings and drivers

- What I'm checking for: Whether the operating system is preventing the mouse from functioning.
 - Open Device Manager and check under Mice and other pointing devices and USB controllers.
 - Look for warning symbols or disabled devices.
 - Update, reinstall, or roll back the mouse driver if needed.
 - Check that accessibility settings (such as mouse controls) are not affecting behavior.
 - If the mouse works after driver changes: The issue was software-related.
-

Step 5: Test with another mouse

- What I'm checking for: Whether the problem is isolated to the mouse or the computer.

- Connect another working wireless or wired mouse to the same computer.
- Results:
 - Another mouse works → original mouse or receiver is faulty.
 - Another mouse also fails → system settings, USB ports, or hardware issue.