

Installation and Operation Manual

SpliceDeck

for Universal Audio LUNA and Stream Deck +

By Recourse Software Inc.

October 2026 · Plugin version 1.0

macOS · LUNA 3.1 · Stream Deck +

Plugin languages: English, Deutsch, Español, Français, 日本語



Welcome

Thank you for choosing SpliceDeck for your LUNA recording setup.

When you record, the best ideas come quickly and leave just as quickly. SpliceDeck for LUNA keeps your hands on a Stream Deck + instead of hunting for the mouse: record, loop a passage, split and fade a clip, drop a coloured marker, balance a track, open a plug-in parameter or ride a fader into automation, all from eight keys and four dials.

SpliceDeck talks to LUNA directly, through the local servers LUNA itself runs on your Mac. It never pretends to be a keyboard, so it doesn't matter which window is in front or how you have set up your shortcuts. And because it reads LUNA all the time, every key and dial shows what is really going on: the bars and beats under the playhead, the selected track and its level, the plug-in in each slot, your markers and the Main Output meter.

The deck comes with a ready-made profile: a page for each LUNA view (LUNA Play, Timeline and Mixer) that follows LUNA as you switch views, plus a Session page and an Automation page one press away.

This manual explains how to install SpliceDeck for LUNA, how the pages are laid out and what every key and dial does, including all 38 actions. Start with **Getting Started** to be recording within a few minutes, then read the chapter for the page you use most.

We hope SpliceDeck becomes the part of your studio you stop noticing because it simply keeps up with you. Enjoy your session!

The SpliceDeck team at Recourse Software Inc.

Contents

Getting Started 5
What You Need 5
Installing the Plugin 6
The SpliceDeck for LUNA Profile 6
Getting a New Layout After an Update 7
Your First Minutes 7

Understanding SpliceDeck for LUNA 9
How It Works 9
Reading a Key 9
Reading the Touch Strip 10
The Five Pages 12
The Meters 13
Shift and Control 13

The LUNA Play Page 15
Keys 16
Dials 17

The Timeline Page 19
Keys 20
Dials 20

The Mixer Page 23
What Dials 2 and 3 Do 24
Keys 25
Dials 25

The Session Page 26
Keys 27
Dials 28

The Automation Page 29
Keys 30
Dials 30

The Jog Dial 32
Scrubbing 32
Splitting and Deleting Clips 33
Fades 33
Selecting Clips 34
Setting the Loop Length 35
Recolouring a Marker with the Jog 35

Markers 36
Adding Markers 36
Colours 36
Naming a Marker 37
Deleting a Marker 37
Which Marker? 37
Moving Between Markers 37

Tracks 38
Selecting a Track 38
R I S M on the Strip 38
Arming a Track 38
Adding a Track Below 39
Deleting a Track 39
Volume and Pan of the Selected Tracks 39
Extending a Clip Selection 40

Mixing and Automation 41
Input 41
Inserts and Rec FX 41
Sends and Cues 42
How a Ride Is Recorded 42
The Lanes 42
Automation Modes 43

More Actions and Your Own Layouts 44
Actions Not in the Profile 44
Changing the Profile 46
Your Own Profiles 46

Settings and Languages 47
SpliceDeck Settings 47
Per-Key Settings 47
Languages 47

Help and Troubleshooting 48
What the Keys Are Telling You 48
Short Messages After a Press 48
Common Problems 49
Known Limits 50

Quick Reference 51

Support and Legal 53
Getting Help 53
Your Data 53
Trademarks 53
Warranty and Disclaimer 53
Third-Party Software 54
About This Manual 55

Getting Started

SpliceDeck for LUNA is quick to set up. You install one plugin, open a session in LUNA, and the deck starts showing live information straight away. There is nothing to switch on in LUNA and no macOS permission to grant.

This section shows you what you need, how to install SpliceDeck for LUNA and its profile, and how to make your first moves with it.

What You Need

ITEM	REQUIREMENT
Stream Deck hardware	A **Stream Deck +**. The bundled profile is laid out for its eight keys, four dials and touch strip. The keys also work on other Stream Deck models, but the dials, and so the Jog, need a Stream Deck +.
Stream Deck software	Elgato Stream Deck app 6.9 or later.
Computer	A Mac with macOS 12 or later.
LUNA	Universal Audio LUNA 3.1, with a session open. SpliceDeck for LUNA was built and tested with LUNA 3.1.0.
Optional: Apollo	For the Monitor dial: a Universal Audio Apollo interface with UA Console installed. SpliceDeck reaches the monitor level through UA Mixer Engine, the service behind UA Console. Everything else works without an Apollo.


TIP SpliceDeck for LUNA reads your keyboard's **Shift** and **Control** keys for some dial gestures. It reads them from macOS directly, so you don't need to grant Accessibility or any other permission.

Installing the Plugin

1. Double-click the installer file, for example `SpliceDeck-for-LUNA-1.0.0.streamDeckPlugin`. The Stream Deck app opens and asks to install SpliceDeck for LUNA. Click **Install**.
2. In the action list on the right of the Stream Deck app, a new category called **SpliceDeck for LUNA** appears, with all 38 actions.
3. The app also installs the **SpliceDeck for LUNA** profile for your Stream Deck +: five ready-made pages for LUNA. Select it in the profile menu at the top of the Stream Deck app if it isn't selected already.
4. Start LUNA and open a session. The keys and dials come to life within a second or two.

The SpliceDeck for LUNA Profile

The profile has five pages. Three of them match LUNA's three main views, in the order of LUNA's own view selector: **LUNA Play**, **Timeline** and **Mixer**. Two more pages hold the things you need less often: the **Session** page (markers, saving, versions and export) and the **Automation** page (riding a track's controls).



The Timeline page of the profile. Eight keys at the top, the touch strip in the middle and four dials below it. Dial 1 is the Jog on every page.

The deck follows LUNA. Whenever LUNA changes view, whether you click LUNA's view selector, use a keyboard shortcut or press the View key on the deck, the Stream Deck + switches to the matching page. SpliceDeck only ever switches pages within its own profile, never in one of yours.

The profile opens on the Timeline page. Just after the plugin starts, the deck waits for the first view change before it starts following, so if the deck and LUNA don't match at first, press the **View** key or change the view in LUNA once.

Getting a New Layout After an Update

The Stream Deck app adds a plugin's bundled profile only when the plugin is installed for the first time. Installing a newer version of SpliceDeck for LUNA over an older one updates the actions, but keeps the profile you already have. When a new version comes with a changed layout, install it like this:

1. In the Stream Deck app, open the profile menu, select the **SpliceDeck for LUNA** profile and delete it.
2. Uninstall the SpliceDeck for LUNA plugin from the Stream Deck app's plugin list.
3. Double-click the new installer file. The plugin is installed fresh, and the new profile comes with it.

> **IMPORTANT** Deleting the profile also deletes any changes you made to it. If you have changed keys in the bundled profile, note them down first, or keep your own layout in a profile with a different name.

Your First Minutes

With LUNA open on a session and the deck on the Timeline page, try this:

1. Turn the **Jog** (dial 1). The playhead moves a 1/16 note per click and the counter on the strip follows as you turn. Spin it quickly to move by beats or bars. When you stop, LUNA's Timeline centres on the playhead.
2. Turn the **Track** dial (dial 4) to select a track. The strip shows its name, its **R I S M** buttons and its level. Tap **S** on the strip to solo it, tap again to unsolo.
3. Park the Jog in the middle of a clip and push it. The clips at the playhead are split. Press **Undo** to take it back.
4. Hold **Shift** on your keyboard and turn the Jog near the start of a clip. A fade-in appears and grows as you turn. Turn back to zero for no fade.
5. Press **Play**, then press **View**. LUNA switches to the Mixer and the deck follows. Hold **View** for half a second to reach the Session page, and press it there to come back.

Understanding SpliceDeck for LUNA

This section explains how SpliceDeck for LUNA connects to LUNA, how to read its keys and touch strip, how the five pages fit together and how the keyboard's Shift and Control keys change what the dials do.

How It Works

While LUNA is running, it keeps a few small servers open on your Mac: one for its user interface (commands, views, the transport and the counter) and one for the session itself (tracks, clips, fades, markers, the selection, the loop, tempo, key and plug-in controls). LUNA Play uses the same session server. SpliceDeck for LUNA connects to both and talks to LUNA directly.

- **No keystroke macros.** SpliceDeck doesn't type shortcuts into LUNA. Your keyboard layout and custom shortcuts don't matter, and the deck works whichever window is in front.
- **Nothing to switch on.** You don't need to enable anything in LUNA or grant any macOS permission.
- **Everything stays on your Mac.** SpliceDeck connects only to LUNA on your own computer, and to UA Mixer Engine for the Monitor dial. It doesn't connect to the internet.
- **Live in both directions.** SpliceDeck reads LUNA many times a second, so keys and dials also follow what you do with the mouse or keyboard in LUNA.


NOTE The interface SpliceDeck uses is internal to LUNA and not documented by Universal Audio. SpliceDeck is careful with it: when something it expects isn't there, the key concerned shows that it can't work rather than guessing. A future LUNA update may change this interface; check for a matching SpliceDeck update if keys stop working after you update LUNA.

Reading a Key


Every key is drawn live from LUNA's current state. A key shows its symbol, its name and, on many keys, a small live value underneath: the bar and beat on Play, the selected send and its level on Sends, the plug-in in the selected slot on Inserts.



Live value. The Sends key while it is held: send 2, at –10.0 dB.



Lit. Loop is lit while LUNA loops.



Recording. Record turns red and shows the selected track's input level.

- **Lit keys.** A key lights up while what it stands for is on: Play while LUNA plays (green), Record while it records (red), Loop, Click and Count-In while they are on, a Mixer element key while you hold it.
- **Dimmed keys.** A key dims when it has nothing to do: Undo and Redo when there is nothing to undo or redo, Sends when the selected send is off, Inserts when the plug-in in the slot is bypassed.
- **Confirmations.** After a press, some keys briefly show a short green confirmation, such as **Saved**, **Marker added** or **Split**.
- **Errors.** When LUNA can't do what a key asks, the key flashes a short red message for about a second, for example **No clip here** or **Not available**, and then returns to normal.

Reading the Touch Strip

The touch strip above the dials is split into four parts, one per dial. Each part shows the dial's name at the top left, its current value in large type, and a short hint or second value underneath.



The Track dial's part of the strip. Top: the page colour band. Top left: the group code and the name (**TRACK**). Top right: LUNA's current view. Centre: the selected track. Below: LUNA's R I S M buttons, lit while on, and the selected track's level. Along the bottom: the Main Output meter.

The page colour band

A thin band of colour runs across the top of the whole touch strip. Its colour is the colour of LUNA's current view: **teal** for LUNA Play, **orchid** for the Timeline and **azure** for the Mixer. The **View** key (key 8 on every page) is lit in the same colour and shows the view's name, so you can always see at a glance which page you are on.

Group colours and corner codes

Every action belongs to a group, and every group has its own colour. You see it in the key's symbol and in the strip. So that you never have to rely on colour alone, each key and each part of the strip also carries a small group code in its top-left corner: a row of up to three dots and dashes. The same code appears in the footer of the chapters of this manual that are about one group.

GROUP	CODE	COLOUR	ACTIONS
Core	–	Periwinkle	LUNA Status, Counter, LUNA Command
Transport	·	Coral	Play, Record, Stop, To Start, Loop, Click, Count-In, Jog, Speed
Markers	· ·	Orange	Marker key and dial, Previous and Next Marker
Edit	– –	Chartreuse	Undo, Redo, Separate Clips, Zoom
Tracks and Mixer	– ·	Azure	Track dial, Arm, Mute, Solo, Monitor, the Mixer and Automation keys and dials, Mixer Bank
View	– · ·	Orchid	View
Session	– – –	Mint	Save, New Version, Export Mix
LUNA Play	· · ·	Teal	LUNA Play Knob, LUNA Play Preset, Song

Red, amber and green are kept for status. Red means recording, an error or a question you must confirm (such as deleting a track). Green means playing or done. Amber is used for warnings.

Quick messages on the strip

While you turn a dial with a modifier or do something special, its part of the strip briefly shows what is happening instead of its normal face: **FADE IN 125 ms**, **SELECT 3 clips**, **LOOP 2 bars**, **TRACK VOLUME +1.0 dB**. About a second and a half after you stop, the normal face comes back.

The Five Pages

PAGE	HOW TO GET THERE	WHAT IT'S FOR
LUNA Play	LUNA shows LUNA Play	Capturing an idea fast: record, loop, keep time, and LUNA Play's own knobs, presets, tempo and key.
Timeline	LUNA shows the Timeline	Arranging and editing around the playhead: split, delete, fade, select, zoom, monitor level and tracks.
Mixer	LUNA shows the Mixer	One track at a time, every element: volume, pan, input trim and phase, sends, cues, inserts and record effects.
Session	Hold **View** on any of the three view pages	Markers, saving, new versions and export.
Automation	Hold **View** on the Session page	Riding a track's volume, pan, mute, a send or a plug-in parameter into automation.

The View key




View KEY 8 ON EVERY PAGE

Shows LUNA's current view, lit in its page colour, with the next view and **hold: session** underneath.

Press	On a view page: switch LUNA to the next view, LUNA Play → Timeline → Mixer → LUNA Play. The deck follows.
Hold	On a view page: go to the Session page.
On Session	The key reads **SESSION**. Press: back to the page of LUNA's current view. Hold: go to the Automation page.
On Automation	The key reads **AUTOMATION**. Press: back to the page of LUNA's current view.

"Hold" on the deck always means keeping a key or dial pressed for about half a second. On the Session and Automation pages, the strip's colour band keeps showing LUNA's current view, because LUNA stays in that view; the View key tells you which page you are on. If LUNA changes view while you are on the Session or Automation page, the deck follows LUNA to that view's page.

The Meters



The Track dial's strip with the selected track's level under the R I S M buttons, and the Main Output meter (two hairlines, left and right) along the bottom edge.

- **Main Output.** A stereo meter, two hairlines for left and right, runs along the bottom of the whole touch strip on every page, continuous across the four dials. It uses LUNA's own meter scale: green, then amber from 75% of the scale and red from 90%, with LUNA's held peak and a red clip light at the right end.
- **Selected track.** The selected track's level is shown under the R I S M buttons on the Track dial (Timeline, Mixer, Session and Automation pages) and on the Song dial while it is set to Track (LUNA Play page).
- **Record key.** While LUNA records, the Record key shows the selected track's input level along its bottom.

The meters refresh about 15 times a second while there is signal, and 4 times a second while LUNA is silent.


Shift and Control

Some dials do something else while you hold **Shift** or **Control** on your computer keyboard. SpliceDeck reads these keys from macOS directly, whichever app is in front, without any permission.

HOLD AND TURN	DOES
Shift + Jog	Over a clip: set the fade at its nearest edge. From a gap: select whole clips. (LUNA's Timeline view.)
Shift + Track	Extend a Shift + Jog clip selection across tracks. (Timeline view.)
Shift + Monitor	The volume of the selected track or tracks (Timeline page).
Control + Monitor	The pan of the selected track or tracks (Timeline page).
Shift + Zoom	Make all tracks taller or shorter (Timeline page).
Shift + Marker	Jump to the previous or next marker (Session page).
Shift + dial 2	The Apollo monitor level; Shift + push: monitor mute (Mixer page).

The LUNA Play Page

LUNA Play is LUNA's focused view for capturing an idea: record, play it back, loop a passage, choose a track preset, balance and export. The LUNA Play page of the deck is built around the same idea. Record comes first, a take review is two presses away, and the dials give you LUNA Play's own panel knobs and its song settings.



The LUNA Play page. The strip's colour band and the View key are teal.

KEYS

Record Start or stop recording	**Play** Play or pause	**To Start** Back to the session start	**Loop** Loop on or off; hold + Jog: loop length
Click Metronome on or off	**Count-In** Count-in on or off	**Undo** Undo, for example a bad take	**View** Next view; hold: Session

DIALS

Jog Scrub; push: to start	**Knob** LUNA Play knob, left of the pair	**Knob** LUNA Play knob, right of the pair	**Song** Track, Preset, Tempo, Key, Main Volume

Keys



Record KEY

Press	Start or stop recording. The key turns red while LUNA records and shows the selected track's input level along its bottom.



Play / Pause KEY

Press	Start or stop playback. The key is lit green and reads **Pause** while LUNA plays, and shows the current bar and beat. In LUNA Play, playback resumes from where you stopped, so reviewing a take is Record, then Play.



To Start KEY

Press	Move the playhead to the start of the session (LUNA's Return to Zero).



Loop KEY

Tap	Turn loop playback on or off. The key is lit while LUNA loops.
Hold + Jog	Set the loop length: the loop runs from where the playhead was when you pressed Loop to where you turn the Jog. It is set when you let go of Loop. See **The Jog Dial**.



Click KEY

Press	Turn the metronome on or off. Lit while on.



Count-In KEY

Press	Turn the record count-in on or off. Lit while on.



Undo KEY

Press	Undo the last change, for example to drop a bad take. The key dims when there is nothing to undo.

The **View** key is described in **Understanding SpliceDeck for LUNA**.

Dials



Jog DIAL 1

The strip shows the bars | beats | ticks counter, a beat ruler and the tempo.

Turn	Scrub the playhead: a 1/16 note per click, a beat or a bar when you spin.
Push	Return to the start of the session.
Hold Loop + turn	Set the loop length.

The Jog has a chapter of its own: **The Jog Dial**.



LUNA Play Knob DIALS 2 AND 3

The knobs of the selected track's LUNA Play panel, two at a time, across the whole chain in chain order. For a vocal track that is, for example, Tune Speed and Depth, then Dynamics Amount and EQ Low, then EQ High and Air, then Reverb Mix; for an acoustic guitar the Channel Strip's EQ and compressor, the drive and the plate reverb. The strip shows the knob's section and name (**TUNE · SPEED**), LUNA's own value text and a gauge, with the knob's section at the top right.

Turn	Turn the knob. Fine steps when you turn slowly, faster on a quick spin.
Push	Next pair of knobs. Pushing either dial moves both to the next pair.

If the selected track has no LUNA Play panel, the strip reads **No panel**. Plug-ins that report only raw values, such as the Century Channel Strip, show a percentage.




Song DIAL 4

LUNA Play's setup on one dial. The strip's title shows the current setting and its number at the top right, for example **1/5**.

Push	Next setting: **Track** → **Preset** → **Tempo** → **Key** → **Main Volume** → Track.
Track	Turn to select the track above or below, one per click. LUNA Play's selected tile and the knobs follow. The strip shows the track's name, its preset and its level.
Preset	Turn to step through the presets of the selected track's plug-in.
Tempo	Turn to change the tempo: 1 BPM per click, 5 BPM on a quick spin.
Key	Turn to change the key a semitone per click. Hold to switch between major and minor, keeping the same tonic.
Main Volume	Turn to move the Main Output fader.

The Timeline Page

The Timeline is where you arrange and edit, and the Timeline page is built to work at the playhead: scrub to the spot, split, fade, delete, zoom and pick the track, all without letting go of the dials. It is the page the profile opens on.



The Timeline page. The strip's colour band and the View key are orchid.

KEYS

Play Play or pause	**Record** Start or stop recording	**Loop** Loop on or off; hold + Jog: loop length	**To Start** Back to the session start
Click Metronome on or off	**Undo** Undo the last change	**Save** Save the session	**View** Next view; hold: Session

DIALS

Jog Scrub; push: split; hold: delete clip	**Monitor** Apollo monitor level; Shift: track volume; Control: pan	**Zoom** Zoom; push: fit selection; Shift: track height	**Track** Select track; R I S M; arm, add, delete

Keys

Play, Record, Loop, To Start, Click and Undo work as described in **The LUNA Play Page**. One key is new here:



Save KEY

Press	Save the session (LUNA's Save Bookmark). The key confirms with **Saved**.

Dials



Jog DIAL 1

The strip shows the counter, a beat ruler and **push: split**.


Turn	Scrub the playhead: a 1/16 note per click, a beat or a bar when you spin. When you stop, the Timeline centres on the playhead.
Push	Split the clips at the playhead.
Hold	Delete the clip under the playhead on the selected track.
Shift + turn	Over a clip: set the fade at its nearest edge. From a gap: select whole clips.
Hold Loop + turn	Set the loop length.

All of this is explained in detail in **The Jog Dial**.


Monitor DIAL 2

Your audio interface's monitor level: the Apollo's monitor knob, the same control LUNA shows in its toolbar. The strip shows the level, a gauge and the interface's name.


Turn	Change the monitor level: 1 dB per click, 3 dB on a quick spin.
Push	Mute or unmute the monitors, like pressing the knob on the Apollo. The strip reads **MUTED** while muted.
Shift + turn	The volume of the selected track or tracks instead: about 1 dB per click around 0 dB, 3 dB on a quick spin. All selected tracks move together.
Control + turn	The pan of the selected track or tracks: 1% per click, 5% on a quick spin.



Turn. The Apollo's monitor level.



Shift + turn. The selected track's volume.




Control + turn. Its pan, with LUNA's left and right values at the top right.

Without an Apollo, or while UA Console's mixer engine isn't running, the Monitor dial reads **no Apollo monitor**. Shift and Control still work for track volume and pan. **Tracks** explains track volume and pan in more detail.

Zoom DIAL 3

The strip shows the length of the current selection, or **Timeline** when nothing is selected.

Turn	Zoom the timeline in (clockwise) or out (anticlockwise).
Push	Zoom to fit the selection.
Shift + turn	Make all tracks taller or shorter, one LUNA height step per click. The strip shows the new height.



Shift + Zoom. The track height after the change.

Track DIAL 4

The selected track: its name, LUNA's **R I S M** buttons and its level.

Turn	Select the track above or below.
Tap R, I, S or M	Toggle Record arm, Input monitor, Solo or Mute for the selected track.
Push	Record-arm or disarm the track.
Push twice	Add a new track directly below, with the same settings but no clips.
Hold	Delete the track. The strip turns red and asks; push within 5 seconds to confirm.
Shift + turn	Extend a Shift + Jog clip selection across tracks.

The Track dial has a chapter of its own: **Tracks**.

The Mixer Page

The Mixer page works on one track at a time, but on every part of it. Dial 4 picks the track. The first five keys are that track's elements: **Input**, **Inserts**, **Sends**, **Cues** and **Rec FX**. With no key held, dials 2 and 3 are the track's volume and pan. Hold an element key, and dials 2 and 3 control that element instead.



The Mixer page with no key held: dial 2 is the volume and dial 3 the pan of the selected track. The colour band and the View key are azure.

KEYS

Input Hold: trim and phase	**Inserts** Hold: slot and parameters; tap: bypass	**Sends** Hold: send and level; tap: on / off	**Cues** Hold: cue and level; tap: on / off
Rec FX Hold: record-path plug-ins; tap: bypass	**Play** Play or pause	**Undo** Undo the last change	**View** Next view; hold: Session

DIALS

Jog Scrub; push: to start	**Dial 2** Volume, or the held element's choice	**Dial 3** Pan, or the held element's level or parameter	**Track** Select track; R I S M; arm, add, delete

What Dials 2 and 3 Do

KEY HELD	DIAL 2	DIAL 3
None	Volume of the selected track (push: 0 dB). **Shift**: the Apollo monitor level (Shift + push: monitor mute).	Pan (push: centre).
Input	Input trim (push: 0 dB).	Phase: any turn flips it.
Sends	Which send, 1 to 8.	That send's level (push: pre or post fader).
Cues	Which cue, 1 to 4.	That cue's level (push: pre or post fader).
Inserts	Which slot, 1 to 8. Shows the plug-in and whether it is on or bypassed (push: switch it).	Turn: pick a parameter. Push: edit its value; push again when done.
Rec FX	Which record-effects slot, 1 to 4, as Inserts.	As Inserts.

The moves you make during one spin of a dial are one undo step, so **Undo** takes back a whole gesture, not a single click. Volume and pan move all selected tracks together.



While **Sends** is held, its key is lit, dial 2 picks the send (**SEND 2**, 2 of 8, post fader) and dial 3 sets its level.

Keys



Track Element KEYS 1 TO 5

Five keys, one per element of the selected track. Each shows its element live: the input trim (with Ø when the phase is flipped), the selected send or cue and its level or **off**, the plug-in in the selected insert or record-effects slot or **empty**. A key dims while its send or cue is off or its plug-in is bypassed.

Hold	Dials 2 and 3 control this element while you hold the key. The key is lit.
Tap	Inserts and Rec FX: bypass the plug-in in the selected slot, or switch it back on. Sends and Cues: switch the selected send or cue on or off. Input: shows **hold + turn**.

Play, Undo and View work as on the other pages. **Mixing and Automation** describes each element in more detail.

Dials



Element Dial DIALS 2 AND 3

The strip's title changes with the key you hold: **VOLUME** and **PAN** with no key held, **INPUT TRIM** and **PHASE** with Input, **SENDS** and **SEND 2** with Sends, **INSERTS** and **PARAMETER** or **EDIT** with Inserts. The table above lists what each one does.

Volume	About 1 dB per click around 0 dB, 3 dB on a quick spin. Push: back to 0 dB.
Pan	1% per click, 5% on a quick spin. The strip shows the position (**C**, **20L**, **35R**) and LUNA's own left and right values. Push: centre. A stereo track goes back to full width (100L / 100R), a mono track to C.

The Jog and the Track dial work as on the Timeline page, except that pushing the Jog returns to the start of the session instead of splitting.

The Session Page

The Session page isn't a LUNA view. It collects what you need now and then, whatever view you are in: markers, saving, new versions and export. Hold **View** on any of the three view pages to get here, and press **View** here to go back to the page of LUNA's current view.



The Session page. The View key is mint and reads **SESSION**; the colour band shows LUNA's current view (here the Timeline).

KEYS

Marker Add a marker; hold + Jog: its colour	**Save** Save the session	**New Version** Save a new version	**Export Mix** Open Export Mixdown
Undo Undo the last change	**Redo** Redo	**Count-In** Count-in on or off	**View** Back; hold: Automation

DIALS

Jog Scrub; push: to start	**Marker** Colour, add, delete, name; Shift: previous / next	**Song** Tempo, Key, Main Volume, Track, Preset	**Track** Select track; R I S M; arm, add, delete

Keys



Marker KEY

Tap	Add a marker at the playhead in the colour last picked on the Marker dial, even while LUNA plays or records. The key shows the new marker's name and position.
Hold + Jog	Change the colour of the marker at the playhead, live, until you let go. If there is no marker at the playhead, one is added there first.



New Version KEY

Press	Save a new version of the session (LUNA's New Version). The key confirms with **New version**.



Export Mix KEY

Press	Open LUNA's Export Mixdown window for the session. Choose your settings and start the export in LUNA.



Redo KEY

Press	Redo what Undo took back. The key dims when there is nothing to redo.

Save, Undo and Count-In work as on the other pages.

Dials



Marker Dial DIAL 2

The strip shows the colour picked for the next marker, with a swatch, and where a push would add it (**push: add at 12 | 3**).

Turn	Pick the colour for the next marker. With the playhead on a marker's line: select that marker and change its colour, live.
Push	Add a marker at the playhead in that colour.
Push twice	Delete the marker.
Hold	Name the marker: a small box opens; type the name and press Return.
Shift + turn	Jump to the previous or next marker.

Markers explains all of this in detail.



The Marker dial: **Orange** is picked, and a push adds the marker at bar 12, beat 3.

Song (dial 3) is the same dial as on the LUNA Play page, but it starts on **Tempo**: push to step through Tempo → Key → Main Volume → Track → Preset. **Jog** and **Track** work as on the Mixer page.

The Automation Page

The Automation page lets you ride a control of the selected track while LUNA plays and keep the move as automation, the way you would ride a fader on a hardware console. Hold **View** on the Session page to get here, and press **View** to go back to the page of LUNA's current view.



The Automation page during a ride: Volume is held while LUNA plays, so the key and the Ride dial are red and the strip shows • **REC**.

KEYS

Volume Hold: ride the volume	**Pan** Hold: ride the pan	**Mute** Hold: ride the mute	**Send** Hold: ride a send's level
Plug-in Hold: ride a plug-in parameter	**Play** Play or pause	**Undo** Undo the last pass	**View** Back

DIALS

Jog Scrub; push: to start	**Ride** The held lane's value	**Automation** Mode; or which send / parameter	**Track** Select track; R I S M; arm, add, delete

Keys



Automation Lane KEYS 1 TO 5

Five keys, one per control you can ride: **Volume**, **Pan**, **Mute**, **Send** and **Plug-in**. Each shows the control's current value. A plain press does nothing.

Hold + dial 2	Ride the control. While LUNA plays, the ride is recorded: the key and the Ride dial turn red with ● **REC**. When you let go, it is written as automation over the stretch you rode, as one undo step, and the track plays it back.

Play, Undo and View work as on the other pages. Undo takes back the last pass.

Dials



Ride Dial DIAL 2


Shows the lane you are riding, or the last lane you rode, with its value and a gauge. At the top right: **hold a lane**, **play to rec** (lane held, LUNA stopped), or ● **REC**.

Turn	Move the lane's control: about 1 dB per click on volume and sends, 1% per click on pan and plug-in parameters, more on a quick spin. Any turn flips Mute.
Push	With no key held: show the next lane.




Automation Dial DIAL 3

Turn	Set the selected track's automation mode: **Off**, **Read**, **Touch**, **Latch** or **Write**.
Push	Back to **Read**.
Send held	Turn to pick which send, 1 to 8.
Plug-in held	Turn to pick the parameter. Push for the next insert slot.



Ride dial while a volume ride is recorded.



Automation dial: the selected track is in Touch.


Mixing and Automation explains how a ride is recorded and written.

The Jog Dial

Dial 1 is the Jog on every page. It scrubs the playhead smoothly, and on the Timeline it is also your main editing tool: push to split, hold to delete, and with Shift held it fades clip edges and selects clips. Together with the Loop and Marker keys it sets the loop and recolours markers.

GESTURE	DOES
Turn	Scrub the playhead: a 1/16 note per click, a beat or a bar when you spin.
Push	Timeline page: split the clips at the playhead. Other pages: return to start.
Hold	Timeline page: delete the clip under the playhead on the selected track.
Shift + turn, over a clip	Set the fade at the clip's nearest edge.
Shift + turn, from a gap	Select whole clips from where you started to the playhead.
Hold Loop + turn	Set the loop from where the playhead was to where you turn it.
Hold Marker + turn	Change the colour of the marker at the playhead.

Scrubbing



The Jog on the Timeline page: the counter in bars | beats | ticks, a beat ruler with the playhead, and **push: split** at the top right. On the other pages the top right shows the tempo.

Each click of the dial moves the playhead a 1/16 note. Spin it quickly and each click moves a beat; spin it fast and each click moves a bar. That way small turns are precise and you can still cross a whole song in a moment.

The counter on the strip updates the instant you turn, before LUNA has redrawn, so the dial always feels immediate. While LUNA plays, the counter follows the playback about 18 times a second.

The playhead moves exactly as it does with LUNA's own navigation: it moves the playback start point, so pressing Play plays from where you scrubbed to.

Keeping the playhead in view

On the Timeline, when you stop turning the Jog, LUNA's view centres on the playhead, at any window size or zoom. This happens once you stop, not continuously while you turn, because LUNA's display lags behind its session model while the playhead moves quickly.

The view isn't moved while LUNA plays, because LUNA's own Auto-Scroll follows the playhead then, or while a loop range is selected, because LUNA keeps the selected range in view itself.

Splitting and Deleting Clips

On the Timeline page, **push** the Jog to split the clips at the playhead, just like LUNA's Separate Clips. It works even while a loop range is selected: the split is made at the playhead, not at the edges of the range. The strip confirms with **Split**.


Hold the Jog to delete the clip under the playhead on the selected track. The strip confirms with **Deleted** and the clip's name, or shows **No clip here** if there is none. Undo brings the clip back.

> **TIP** To cut out a section, scrub to its start, push, scrub to its end, push again, then park inside the section and hold.


Fades

Hold **Shift** on your keyboard and turn the Jog with the playhead over a clip. SpliceDeck finds the clip edge nearest the playhead on the selected track, inside the clip or up to a beat outside it, and sets the fade there. If there is no fade yet, one is created.

- **Fade-in.** At the start of a clip, turn clockwise to lengthen the fade-in and anticlockwise to shorten it.
- **Fade-out.** At the end of a clip, the fade grows backwards from the clip's end, so turn anticlockwise to lengthen it and clockwise to shorten it.
- **Step size.** A 1/64 note per click, a 1/16 note on a quick spin.
- **No fade.** Roll the fade back to zero for no fade. The strip shows **Off**.
- **Undo.** One spin is one undo step.



FADE IN. The fade length in milliseconds and in notes, with the clip's name at the top right.




Off. A fade-out rolled all the way back: no fade.

If no clip edge is near the playhead, the strip shows **No clip edge**.

Selecting Clips

Hold Shift and turn the Jog starting from a gap, where there is no clip under the playhead on the selected track. SpliceDeck selects the whole clips from where you started to where the playhead is now. The strip shows how many clips and tracks the selection holds.

Keep holding Shift and turn the **Track** dial to extend the selection to the tracks above or below. Let go of Shift when you are done; the selection stays in LUNA, ready for you to copy, move or delete it there.



SELECT. Three clips on two tracks.

NOTE Whether Shift + Jog fades or selects is decided by your first turn: over a clip it fades, in a gap it selects. It keeps doing that until you let go of Shift. Shift + Jog works while LUNA shows its Timeline view.

Setting the Loop Length

On the LUNA Play and Timeline pages, hold the **Loop** key and turn the Jog. The loop runs from where the playhead was when you pressed Loop to where you turn it. While you turn, the strip shows the length of the loop in bars and beats.

The loop is set when you let go of Loop: looping is switched on and the playhead goes to the start of the loop. A quick tap on Loop, without turning the Jog, still just turns looping on and off.



Hold **Loop**…



…and turn the Jog: **2 bars**, set when you release Loop.

Recolouring a Marker with the Jog

On the Session page, hold the **Marker** key and turn the Jog to step the marker at the playhead around LUNA's marker colour wheel, live. If there is no marker at the playhead, one is added there on your first turn. The strip shows **MARKER COLOUR**, the colour and the marker's name. Let go of the key when you like the colour. **Markers** has more about colours.

Markers

Markers are quickest from the Session page: the **Marker** key drops one, and the Marker dial picks colours, adds, deletes and names them. Markers made from the deck are ordinary LUNA markers, in LUNA's own colours, so they look exactly like the ones you add with the mouse.

Adding Markers

- **Marker key.** Tap it to add a marker at the playhead in the colour last picked on the Marker dial. It works while LUNA is stopped, playing or recording, so you can mark the moments of a take as they happen.
- **Marker dial.** Push it to add a marker at the playhead in the colour shown on its strip.

New markers are named **Marker 1**, **Marker 2** and so on, the way LUNA names its own. The key or strip briefly shows the new marker's name and its position. After adding, the playhead is on the marker's line, so turning the Marker dial straight away recolours it.

Colours

The deck offers the 16 colours of LUNA's own Marker colour wheel, in wheel order, plus LUNA's default marker colour. They are exactly the colours LUNA stores when you click its wheel, so LUNA's Marker panel shows the matching slice.

Default	Orange	Amber
Yellow	Olive	Lime
Green	Forest	Teal
Cyan	Blue	Indigo
Violet	Purple	Plum
Rose	Red	

The swatches show the colours as the deck draws them, slightly brightened so they read well on the touch strip.

Turning the Marker dial does one of two things, depending on where the playhead is:

- **On a marker's line:** it selects that marker and steps its colour around the wheel, live. LUNA's Marker panel shows the slice as it changes. The strip shows the marker's name, the colour and **turn: colour · push twice: delete**.
- **Anywhere else:** it picks the colour for the next marker. The strip shows the colour's name and a swatch. The Marker key uses the same colour.

You can also hold the **Marker** key and turn the Jog to recolour the marker at the playhead, as described in **The Jog Dial**.

Naming a Marker

Hold the Marker dial. A small macOS box titled **SpliceDeck for LUNA** opens, with the marker's current name. Type the new name and press Return, or click **Rename**. The marker is renamed in LUNA and the strip confirms with **Renamed**. Click **Cancel** to leave the name as it is. LUNA comes back to the front afterwards.

> **NOTE** SpliceDeck uses its own small box because LUNA's name field can't take the keyboard when it is focused from outside LUNA. The box needs no permission. If you leave it open for two minutes, it closes by itself without renaming.

Deleting a Marker

Push the Marker dial twice, quickly, to delete the marker. The strip confirms with **Deleted** and the marker's name. Undo brings it back.

Which Marker?

Naming and deleting act on **the marker at the playhead, or else the last marker before it**. Recolouring by turning the Marker dial acts only on a marker whose line the playhead is on. If there is no marker to act on, the strip shows **No marker**.

Moving Between Markers

Hold Shift and turn the Marker dial to jump to the previous or next marker. The **Previous Marker** and **Next Marker** actions do the same from keys; they aren't in the bundled profile, but you can add them as described in **More Actions**.

Tracks

Dial 4 is the Track dial on the Timeline, Mixer, Session and Automation pages. It selects tracks and gives you LUNA's track buttons on the touch strip, and it adds and deletes tracks. On the LUNA Play page, the Song dial's Track setting selects tracks instead.

Selecting a Track

Turn the Track dial to select the track above or below. The selection is LUNA's own: LUNA's Timeline and Mixer highlight the track, and LUNA Play's selected tile follows. The strip shows the track's name and, at the top right, LUNA's current view.

R I S M on the Strip



The selected track **Vocal**, record-armed and soloed, with its level under the buttons.

Under the track's name, the strip shows LUNA's four track buttons, lit while on: **R** Record arm (red), **I** Input monitor (green), **S** Solo (amber) and **M** Mute (blue). Tap a button on the touch strip to switch it for the selected track. The buttons also follow changes you make in LUNA.

- Solo follows LUNA's solo mode, for example X-OR, so soloing one track can unsolo another, just as in LUNA.
- Record arm, Solo and Mute go through LUNA's own track commands, so LUNA's grouping applies.
- The track's level meter runs under the buttons.

Arming a Track


Push the Track dial to record-arm the selected track, or disarm it if it is armed.

Adding a Track Below

Push the Track dial twice, quickly, to add a new track directly below the selected one. The new track has the same settings as the selected track (plug-ins, preset, input and routing), but no clips and no automation. It is selected, ready to record on. The strip confirms with its name and **Track added**. One Undo removes it again.

Deleting a Track

1. **Hold** the Track dial. Its part of the strip turns red and asks **DELETE TRACK?**, with the track's name.
2. **Push** the dial within 5 seconds to delete the track. The neighbouring track is then selected.



The question. Push to delete; turn or tap to cancel.

To cancel, turn the dial or tap the strip (the strip shows **Kept**), or simply wait 5 seconds. If you delete a track by mistake, **Undo** brings it back.

Volume and Pan of the Selected Tracks

You can set the level and pan of the selected track, or of several selected tracks together, from two places:

WHERE	VOLUME	PAN
Timeline page, dial 2	**Shift** + turn	**Control** + turn
Mixer page, dials 2 and 3	Turn dial 2 (no key held)	Turn dial 3 (no key held)

- **Volume** moves the track faders about 1 dB per click around 0 dB, 3 dB on a quick spin. All selected tracks move together. The strip shows the level and the track's name, or the number of tracks.
- **Pan** moves 1% per click, 5% on a quick spin. The strip shows the position (**C**, **20L**, **35R**) and LUNA's own pan values. On a stereo track both sides move together, keeping the width until one side reaches the edge; a full-width track then narrows.
- One spin is one undo step.

Extending a Clip Selection

While a Shift + Jog clip selection is under way, keep holding Shift and turn the Track dial to extend the selection to the tracks above or below. **The Jog Dial** explains clip selection.

Mixing and Automation

This chapter looks more closely at the elements of a track on the Mixer page, and at how the Automation page turns your rides into automation.


Input

Hold **Input**. Dial 2 is the track's **input trim**: about 1 dB per click, 3 dB on a quick spin; push for 0 dB. Dial 3 is the **phase**: any turn flips it, and the strip shows **Ø** or **normal**. When the track's input trim is linked, both sides move together. The Input key shows the trim, with Ø while the phase is flipped.


Inserts and Rec FX

Inserts are the track's eight plug-in slots. **Rec FX** are its four record-path plug-in slots, such as Unison preamps on an Apollo input. Both work the same way. Hold the key, then:


1. **Pick the slot with dial 2.** The strip shows the plug-in in the slot, ● **ON** or ○ **BYPASSED**, and the slot number (**1/8**). Push dial 2 to switch the plug-in on or bypass it. An empty slot reads **empty**.
2. **Pick a parameter with dial 3.** Turn to step through the plug-in's parameters. The strip shows the parameter's name, its value and its number, for example **5/12**.
3. **Push dial 3 to edit it.** The title changes to **EDIT**. Turn to change the value, 1% per click, 5% on a quick spin. Push again when you are done.



Dial 2. Slot 1 holds a vocal suite, switched on.



Dial 3, turn. Parameter 5: Tune Speed.



Dial 3, pushed. Editing its value.

A **tap** on Inserts or Rec FX, without turning a dial, bypasses the plug-in in the selected slot or switches it back on. The key shows the slot number and the plug-in's name, and dims while it is bypassed.

Sends and Cues

Hold **Sends**. Dial 2 picks the send, 1 to 8; dial 3 sets its level, about 1 dB per click. Push dial 3 to switch the send between pre fader and post fader. **Cues** works the same way for the track's four cue mixes.

A **tap** on Sends or Cues switches the selected send or cue on or off. The key shows the send's number and level, or **off**.

> **TIP** The send, cue, slot and parameter you picked are remembered while you work, so the next time you hold the key, the dials pick up where you left off.

How a Ride Is Recorded

On the Automation page, each lane key stands for one control of the selected track. Hold the key and turn dial 2 to ride it.

1. **Press Play** and hold a lane key, for example **Volume**. While you hold it, the track's automation is switched off, so what you hear is the dial, not the automation already there.
2. **Turn dial 2.** While LUNA plays, the control's value at the playhead is recorded about 10 times a second and every time you turn. The key and the strip turn red with • **REC**.
3. **Let go of the key.** The pass is written as automation over the stretch you rode: the automation points in that stretch are replaced by your pass, using LUNA's own linear automation points. The whole pass is one undo step.
4. **Listen back.** The track plays the pass back. If the track was in Off or Read, it is set to Read; in Touch, Latch or Write it stays in that mode.

If LUNA is stopped, the Ride dial simply sets the control's value; nothing is recorded. The strip shows **play to rec** as a reminder.

The Lanes

LANE	RIDES
Volume	The track's fader, about 1 dB per click.
Pan	The track's pan, 1% per click. On a stereo track both sides move.

LANE	RIDES
Mute	The track's mute: any turn flips it between **MUTED** and **on air**. It is written as a step, not a ramp.
Send	The level of one send. Turn the Automation dial while Send is held to pick which send.
Plug-in	One parameter of the plug-in in an insert slot. While Plug-in is held, turn the Automation dial to pick the parameter, and push it for the next insert slot.

If you change the send or the parameter while you hold its lane, the pass on the old control is finished and a new one starts on the new control.

Automation Modes

With no lane held, turn the Automation dial (dial 3) to set the selected track's automation mode, from the safest to the most active: **Off**, **Read**, **Touch**, **Latch** and **Write**. Push it to go back to **Read**. These are LUNA's own modes.

> **NOTE** LUNA doesn't let an outside controller release a touched control, so SpliceDeck doesn't use LUNA's touch mechanism for its rides. It writes the automation points itself when you let go, the way LUNA's own automation assistant does. You don't need to set a mode before riding.

More Actions and Your Own Layouts

The bundled profile uses most of SpliceDeck for LUNA's 38 actions. A few more are in the **SpliceDeck for LUNA** category of the Stream Deck app, ready for you to add to the profile or to a profile of your own.

Actions Not in the Profile



LUNA Status KEY

Shows the name of the open session, or **NO SESSION** and **open a session**. When SpliceDeck can't reach LUNA, it shows why.

Press	Reconnect to LUNA.



Counter KEY

LUNA's bars | beats counter and the tempo, live.

Press	Return to the start of the session.



LUNA Command KEY

Runs any of LUNA's roughly 350 commands, the same ones listed in LUNA's **Help > Show Keyboard Shortcuts**. Choose the command in the key's settings under **Command**, and optionally type your own **Label**. The key lights up while LUNA reports the command as on.

Press	Run the command.



Stop KEY

Press	Stop playback, and recording.



Previous Marker · Next Marker KEYS

Press	Jump to the previous or next marker.



Separate Clips KEY

Press	Split the clips under the playhead, or at the edges of the selection (LUNA's Separate Clips).



Arm Track · Mute Track · Solo Track KEYS

Press	Record-arm, mute or solo the selected track or tracks, or switch it off again, like LUNA's **Shift** + **R**, **Shift** + **M** and **Shift** + **S**. LUNA Play uses exclusive solo.



Speed Dial DIAL

Turn	Change the playback speed between half, normal and double, to practise slowly or skim quickly.
Push	Back to normal speed (1×).

LUNA doesn't report the playback speed, so the strip shows the last speed set from the deck.



Mixer Bank Dial DIAL

Turn	Bank LUNA's mixer left or right.
Push	Show the Mixer.



LUNA Play Preset DIAL

Turn	Step through the presets of the selected track's plug-in. The strip shows the preset and the track. It does the same as the Song dial's Preset setting.

Changing the Profile

The bundled profile is an ordinary Stream Deck profile. Select any key or dial and drag a different action onto it, or change its settings, as with any profile. Keep in mind:

- **Page order matters.** SpliceDeck switches to the pages of the **SpliceDeck for LUNA** profile by position: LUNA Play, Timeline, Mixer, Session, Automation. Keep the five pages in this order.
- **Some keys belong together.** Loop + Jog and Marker + Jog need the Jog on the same page. The Mixer element keys work with the Element dials, and the Automation lane keys with the Ride and Automation dials, on the same page.
- **The View key knows its page.** The View keys on the Session and Automation pages are set up for those pages. To move them, copy them rather than adding a new View action.
- **Updates don't replace your profile.** See **Getting a New Layout After an Update** in **Getting Started**.

Your Own Profiles

You can also build your own profile from scratch: create a new profile in the Stream Deck app and drag actions from the **SpliceDeck for LUNA** category onto the keys and dials. The keys work on any Stream Deck model; the dial actions need a Stream Deck +.

NOTE Following LUNA's view only switches the pages of the bundled **SpliceDeck for LUNA** profile, and only on a Stream Deck +. Your own profiles never switch pages by themselves.

Settings and Languages

SpliceDeck for LUNA works without any setup. The few settings it has are for unusual setups.

SpliceDeck Settings

The plugin-wide settings are in the **SpliceDeck settings** section of a **LUNA Command** key's settings. Add a LUNA Command key anywhere to reach them; they apply to the whole plugin.

SETTING	WHAT IT DOES
LUNA address	Where SpliceDeck finds LUNA's user interface server. Leave it empty to use LUNA's standard address, `ws://127.0.0.1:4743/`.
Polling	How often SpliceDeck reads LUNA while keys are on screen. **Responsive** (the default) reads about 10 times a second, **Balanced** about 6 times and **Battery saver** about 4 times. With no SpliceDeck keys on screen, it reads much less often.

Changing either setting restarts SpliceDeck's connection to LUNA.

Per-Key Settings

Most actions have no settings: what they do comes from where they are in the profile. LUNA Command has its **Command** and **Label**. The Marker dial remembers the colour you picked last, and the Song dial remembers its setting, on each dial separately.

Languages

SpliceDeck for LUNA speaks **English**, **German**, **French**, **Spanish** and **Japanese**. It follows the language of the Stream Deck app: the keys, the touch strip, the action names and the tooltips all change with it. To change the language, change it in the Stream Deck app's preferences. For any other language, SpliceDeck uses English.

LUNA's own names, such as the names of your tracks, markers, plug-ins and parameters, are always shown as LUNA reports them.

Help and Troubleshooting

When SpliceDeck for LUNA can't work, the keys say so in plain words. This chapter explains what they mean, how to solve the most common problems, and what SpliceDeck can't do yet.

What the Keys Are Telling You

When SpliceDeck can't reach LUNA, or there is no session to work on, keys show a short word instead of their normal face. The LUNA Status key shows a second line that says what to do.

KEY SHOWS	LUNA STATUS SHOWS	WHAT IT MEANS AND WHAT TO DO
Connecting	Starting	SpliceDeck is starting. Wait a moment.
Offline	LUNA offline, Start LUNA	LUNA isn't running, or it isn't answering yet. Start LUNA; SpliceDeck reconnects by itself.
No session	No session, Open a LUNA session	LUNA is running, but no session is open. Open or create a session.
No link	No link, Update SpliceDeck for LUNA	LUNA answered, but refused the connection. This can happen after a LUNA update changes its interface. Check for a newer version of SpliceDeck for LUNA.
Reconnecting	Reconnecting, Link restarting	SpliceDeck's connection is restarting by itself. Wait a moment.

Short Messages After a Press

MESSAGE	WHAT IT MEANS
Not available	LUNA doesn't offer this right now, for example a command that is greyed out in LUNA's menus.
No clip here	Hold Jog: there is no clip under the playhead on the selected track.
No clip edge	Shift + Jog: no clip edge is near the playhead on the selected track.
No marker	Marker dial: there is no marker at or before the playhead.
No track	Hold Track: no track is selected.
empty	Inserts or Rec FX: the selected slot has no plug-in.

MESSAGE	WHAT IT MEANS
Timed out, Busy	LUNA didn't answer in time, for example while it loads or saves a large session. Try again.
Marker failed, Loop failed	LUNA refused to add the marker or set the loop. Try again.

Common Problems

The profile doesn't appear, or has the old layout

The Stream Deck app adds the bundled profile only on a fresh install, and only for a Stream Deck +. If it is missing, or still shows an older layout after an update, delete the **SpliceDeck for LUNA** profile, uninstall the plugin, then install it again, as described in **Getting a New Layout After an Update**.

The deck doesn't follow LUNA's view

- Check that the **SpliceDeck for LUNA** profile is the one selected for your Stream Deck +. SpliceDeck switches pages only in its own profile.
- Just after SpliceDeck starts, it waits for LUNA's first view change. Change the view once, or press **View**.
- Check that the five pages are still in their original order.

The Monitor dial shows "no Apollo monitor"

The Monitor dial needs a UA Apollo and UA Console's mixer engine (UA Mixer Engine) running on your Mac. Check that the Apollo is connected and UA Console works. Without an Apollo, use Shift and Control on dial 2 for track volume and pan; everything else works normally.

Keys look dim

A dim key usually means there is nothing for it to do right now: Undo with nothing to undo, a send that is off, a bypassed plug-in, or LUNA Status with no session open. It isn't a fault.

Shift or Control gestures don't work

- Hold the key on your Mac's keyboard **before** you turn the dial, and keep it held while you turn.
- Shift + Jog and Shift + Track work while LUNA shows its Timeline view.
- For a fade, the selected track must have a clip edge near the playhead. For a selection, start in a gap on the selected track.

The view jumps or doesn't centre

The Timeline centres on the playhead when you stop turning the Jog, not while you turn. It doesn't centre while LUNA plays (LUNA's Auto-Scroll follows then) or while a loop range is selected (LUNA keeps the range in view).

Something changed in LUNA but the deck shows the old value

Give it a moment: SpliceDeck reads LUNA many times a second. If the deck stays out of step, press the **LUNA Status** key (if you have one) to reconnect, or quit and reopen the Stream Deck app.

Known Limits

LUNA has no public interface for controllers like SpliceDeck, so a few things work differently from what you might expect, or aren't possible yet.

- **LUNA redraws outside changes about 10 times a second.** When you turn a dial fast, LUNA's own display can lag a little behind the deck. The deck shows the new value at once.
- **The view centres when you stop turning.** The Timeline doesn't scroll continuously with the Jog; it centres on the playhead once you stop.
- **A fade rolled back to zero leaves an empty fade.** The fade is silent, but LUNA keeps an empty fade object on the clip, because LUNA's Delete Fades command doesn't act on a fade picked from outside LUNA.
- **Playback speed isn't reported.** LUNA doesn't report the playback speed, so the Speed dial's strip shows the last speed set from the deck.
- **Names are typed in a separate box.** LUNA's own name field can't take the keyboard from outside, so markers are named in SpliceDeck's small macOS box.
- **macOS and LUNA 3.1.** SpliceDeck for LUNA runs on macOS only and has been tested with LUNA 3.1. A later LUNA version may change the interface it uses.

Quick Reference

All 38 actions of SpliceDeck for LUNA, by group. **Page** shows where each action is in the bundled profile: **P** LUNA Play, **T** Timeline, **M** Mixer, **S** Session, **A** Automation.

	ACTION	TYPE	PAGE	WHAT IT DOES
	LUNA Status	Key	–	The link to LUNA and the open session. Press: reconnect.
	Counter	Key	–	Bars | beats counter and tempo. Press: return to start.
	LUNA Command	Key	–	Any of LUNA's ~350 commands; lit while on. Holds the SpliceDeck settings.
	Play / Pause	Key	P T M A	Start or stop playback; lit while playing.
	Record	Key	P T	Start or stop recording; red with the input level while recording.
	Stop	Key	–	Stop playback and recording.
	Return to Start	Key	P T	Playhead to the session start.
	Loop	Key	P T	Tap: loop on or off. Hold + Jog: loop length.
	Click	Key	P T	Metronome on or off.
	Count-In	Key	P S	Record count-in on or off.
	Jog Dial	Dial	all	Scrub. Push: split (T) or to start. Hold: delete clip (T). Shift: fade or select.
	Speed Dial	Dial	–	Half, normal or double speed. Push: 1×.
	Add Marker	Key	S	Tap: marker in the picked colour. Hold + Jog: recolour.
	Marker Dial	Dial	S	Colour; push: add; twice: delete; hold: name; Shift: previous / next.
	Previous Marker	Key	–	Jump to the previous marker.
	Next Marker	Key	–	Jump to the next marker.
	Undo	Key	all	Undo; dims when there is nothing to undo.
	Redo	Key	S	Redo; dims when there is nothing to redo.

	ACTION	TYPE	PAGE	WHAT IT DOES
	Separate Clips	Key	–	Split at the playhead or the selection edges.
	Zoom Dial	Dial	T	Zoom; push: fit selection; Shift: track height.
	Track Dial	Dial	T M S A	Select; tap R I S M; push: arm; twice: new track below; hold: delete.
	Arm Track	Key	–	Record-arm the selected tracks.
	Mute Track	Key	–	Mute the selected tracks.
	Solo Track	Key	–	Solo the selected tracks.
	View	Key	all	Next view; hold: Session, then Automation; press there: back.
	Monitor Dial	Dial	T	Apollo monitor level; push: mute. Shift: track volume; Control: pan.
	Track Element	Key	M	Input, Inserts, Sends, Cues, Rec FX. Hold: dials 2 and 3 control it. Tap: bypass or on / off.
	Element Dial	Dial	M	Volume and pan, or the held element. Shift + dial 2: monitor level.
	Automation Lane	Key	A	Volume, Pan, Mute, Send, Plug-in. Hold + dial 2: ride it.
	Ride Dial	Dial	A	The held lane's value; push: next lane.
	Automation Dial	Dial	A	Automation mode; push: Read. Or which send or parameter.
	Mixer Bank Dial	Dial	–	Bank the mixer; push: show the Mixer.
	Save	Key	T S	Save the session.
	New Version	Key	S	Save a new version of the session.
	Export Mixdown	Key	S	Open Export Mixdown (on the key: Export Mix).
	LUNA Play Knob	Dial	P	The selected track's LUNA Play panel knobs, a pair at a time; push: next pair.
	LUNA Play Preset	Dial	–	Step the selected track's plug-in presets.
	Song Dial	Dial	P S	Track, Preset, Tempo, Key, Main Volume; push: next setting.

Support and Legal

Getting Help

The quickest way to solve most problems is **Help and Troubleshooting** in this manual. If you still need help, or you would like to suggest a feature or report a bug, please email Recourse Software Inc., the maker of SpliceDeck for LUNA, at **support@recoursellm.com**. To help us find the problem quickly, include:

- the SpliceDeck for LUNA version, shown in the Stream Deck app's plugin list;
- your macOS version and your Stream Deck app version;
- your LUNA version, and whether you use an Apollo;
- what you did, what you expected and what happened instead.

Your Data

SpliceDeck for LUNA runs entirely on your Mac. It talks to LUNA through LUNA's local servers, and to UA Mixer Engine for the Monitor dial, and doesn't connect to the internet. Your key settings and SpliceDeck's settings are stored by the Stream Deck app.

Trademarks

LUNA, Apollo, Unison and UA are trademarks of Universal Audio, Inc. Stream Deck and Elgato are trademarks of Corsair Memory, Inc. macOS and Mac are trademarks of Apple Inc. All other trademarks are the property of their respective owners.

SpliceDeck for LUNA is made by Recourse Software Inc. and is an independent product. It is not affiliated with, endorsed by or sponsored by Universal Audio, Corsair or Elgato. All SpliceDeck artwork is original. SpliceDeck, its artwork and this manual are copyright © 2026 Recourse Software Inc. All rights reserved.

Warranty and Disclaimer

SpliceDeck for LUNA is provided "as is", without warranty of any kind, express or implied, including the implied warranties of merchantability, fitness for a particular purpose and non-infringement. To the fullest extent permitted by law, Recourse Software Inc. is not liable for any claim, damages or other liability arising from the use of SpliceDeck for LUNA, including loss of data, lost work or interrupted sessions.

SpliceDeck for LUNA makes real changes to your LUNA sessions. Keys and dials that delete clips, markers and tracks or write automation do exactly what they say. Save your session and keep backups as you normally would. The **New Version** key saves a new version of your session at the press of a key.

> **IMPORTANT** Nothing in this disclaimer limits any rights you have under the consumer laws of your country that cannot be excluded.

Third-Party Software

SpliceDeck for LUNA includes the following open source software, each used under the MIT License:

COMPONENT	LICENCE
Elgato Stream Deck SDK (`@elgato/streamdeck`)	MIT License, Copyright (c) Corsair Memory Inc.
`@elgato/utils`	MIT License, Copyright (c) Corsair Memory Inc.
`ws` **WebSocket library**	MIT License, Copyright (c) 2011 Einar Otto Stangvik, Copyright (c) 2013 Arnout Kazemier and contributors, Copyright (c) 2016 Luigi Pinca and contributors

The text of the MIT License, which applies to each of these components together with its copyright notice above, is:

> Permission is hereby granted, free of charge, to any person obtaining a copy of this software and associated documentation files (the "Software"), to deal in the Software without restriction, including without limitation the rights to use, copy, modify, merge, publish, distribute, sublicense, and/or sell copies of the Software, and to permit persons to whom the Software is furnished to do so, subject to the following conditions:
>
> The above copyright notice and this permission notice shall be included in all copies or substantial portions of the Software.
>
> THE SOFTWARE IS PROVIDED "AS IS", WITHOUT WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, INCLUDING BUT NOT LIMITED TO THE WARRANTIES OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE AND NONINFRINGEMENT. IN NO EVENT SHALL THE AUTHORS OR COPYRIGHT HOLDERS BE LIABLE FOR ANY CLAIM, DAMAGES OR OTHER LIABILITY, WHETHER IN AN ACTION OF CONTRACT, TORT OR OTHERWISE, ARISING FROM, OUT OF OR IN CONNECTION WITH THE SOFTWARE OR THE USE OR OTHER DEALINGS IN THE SOFTWARE.

About This Manual

This manual describes SpliceDeck for LUNA plugin version 1.0, tested with LUNA 3.1.0 on macOS. Features and the appearance of keys may change in later versions. If something on your deck looks different from this manual, check that you have the latest version of SpliceDeck for LUNA.

SpliceDeck for LUNA Installation and Operation Manual. Copyright © 2026 Recourse Software Inc. All rights reserved.