

epsn_vp_CB_EB_Powerlite_Brightlink_Series

Command reference — **generated based on the Python file**

device/epsn_vp_CB_EB_Powerlite_Brightlink_Series.py. This document was produced automatically by parsing the driver module (no vendor documentation was available for this device); it lists the control/status commands the module implements.

Generated 2026-07-17

Device information

Property	Value
Device type	projector
Models	BrightLink 695Wi, EB-695Wi, CB-695Wi, EB-685WT, BrightLink 685Wi, EB-685Wi, CB-685Wi, BrightLink 680Wi, EB-695WT, EB-680Wi, CB-680Wi, BrightLink 675Wi, EB-675Wi, CB-675Wi, EB-685W, PowerLite 685W, CB-685W, PowerLite 675W, EB-675W, CB-675W, EB-680, PowerLite 680, CB-680, PowerLite 670, EB-670, CB-670, EB-595Wi
Connection	com_type=Network, protocol=TCP, net_port=3629, service_port=0

Commands

Command	Set	Update	Allowed values / Parameters
AVMute	Yes	Yes	On, Off
AspectRatio	Yes	Yes	-
AutoImage	Yes	-	-
DeviceStatus	-	Yes	-
Freeze	Yes	Yes	On, Off
Input	Yes	Yes	Input 1 (RGB), Input 1 (Component), Input 2 (RGB), Input 2 (Component), HDMI 1, Video (RCA), USB Display, USB, LAN, HDMI 2, HDMI 3
LampMode	Yes	Yes	Normal, Eco
LampUsage	-	Yes	-
MenuNavigation	Yes	-	Menu, Escape, Enter, Up, Down, Left, Right
MicLevel	Yes	Yes	-
Power	Yes	Yes	On, Off
Volume	Yes	Yes	-

Command strings

Raw command / query strings sent to the device, extracted from each Set/Update method (control characters shown as Python escapes, e.g. \r).

SetAVMute

```
'MUTE {0}\r'.format(...)
```

values: On→ON, Off→OFF

SetAspectRatio

```
'ASPECT {0}\r'.format(...)
```

SetAutoImage

'KEY 4A\r'

SetFreeze

'FREEZE {0}\r'.format(...)

values: On→ON, Off→OFF

SetInput

'SOURCE {0}\r'.format(...)

values: Input 1 (RGB)→11, Input 1 (Component)→14, Input 2 (RGB)→21, Input 2 (Component)→24, HDMI 1→30, Video (RCA)→41, USB Display→51, USB→52, LAN→53, HDMI 2→A0, HDMI 3→C0

SetLampMode

'LUMINANCE {0}\r'.format(...)

values: Normal→00, Eco→01

SetMenuNavigation

'KEY {0}\r'.format(...)

values: Menu→03, Escape→05, Enter→16, Up→35, Down→36, Left→37, Right→38

SetMicLevel

'MICLEVEL {0}\r'.format(...)

values: Min→0, Max→5

SetPower

'PWR {0}\r'.format(...)

values: On→ON, Off→OFF

SetVolume

'VOL {0}\r'.format(...)

values: Min→0, Max→20

UpdateAVMute

'MUTE?\r'

UpdateAspectRatio

'ASPECT?\r'

UpdateDeviceStatus

'ERR?\r'

UpdateFreeze

'FREEZE?\r'

UpdateInput

'SOURCE?\r'

UpdateLampMode

'LUMINANCE?\r'

UpdateLampUsage

'LAMP?\r'

UpdateMicLevel

'MICLEVEL?\r'

UpdatePower

'PWR?\r'

UpdateVolume

'VOL?\r'