

extr_cs_ShareLink

Command reference — **generated based on the Python file** `device/extr_cs_ShareLink.py`. This document was produced automatically by parsing the driver module (no vendor documentation was available for this device); it lists the control/status commands the module implements.

Generated 2026-07-17

Device information

Property	Value
Device type	wireless
Models	ShareLink Pro 2000, ShareLink Pro 1100
Connection	com_type=Network, protocol=SSH, net_port=22023, service_port=0

Commands

Command	Set	Update	Allowed values / Parameters
AccessMode	Yes	Yes	Full Control, Moderated, Run-time
AllPendingUserConnections	Yes	-	Approve, Reject, Pending
AllUsersConnectionTime	-	-	Params: Button
AllUsersContentSharingStatus	-	-	Params: Button
AllUsersContentType	-	-	Params: Button
AllUsersIdleTime	-	-	Params: Button
AllUsersName	-	-	Params: Button
AllUsersNavigation	Yes	-	-
AllUsersNumberOfContentShared	-	-	Params: Button
AudioMute	Yes	Yes	On, Off
ChannelPresetRecall	Yes	Yes	-
ChannelPresetRecallStep	Yes	-	Next, Previous
ClosedCaption	Yes	Yes	On, Off
ConfirmationCode	-	Yes	-
ConfirmationCodeMode	-	Yes	-
ConnectedUserConnectionTime	-	-	Params: Button
ConnectedUserContentSharingStatus	-	-	Params: Button
ConnectedUserIdleTime	-	-	Params: Button
ConnectedUserName	-	-	Params: Button
ConnectedUserNavigation	Yes	-	-
ConnectedUserNumberOfContentShared	-	-	Params: Button
CurrentSourceItem	-	Yes	-
DisconnectAllUsers	Yes	-	-
DisconnectUser	Yes	-	Params: Group, Button
ExecutiveMode	Yes	Yes	On, Off

Command	Set	Update	Allowed values / Parameters
ExpoMode	Yes	Yes	Off, Lock-Out, Temporary
FileName	-	-	Params: Button
FileNavigation	Yes	-	-
FullScreenSharedContent	Yes	-	Params: Group, Button
FullScreenSharedContentRevert	Yes	-	-
FullScreenSharedContentStatus	-	Yes	-
FullScreenSharedContentUserName	-	Yes	-
HDCPInputAuthorization	Yes	Yes	On, Off
HDCPInputStatus	-	Yes	-
HDCPMode	Yes	Yes	Follow Input, Always Encrypt, Follow Input (with continuous DVI trials), Always Encrypt (with continuous DVI trials), Disable Authentication
HDCPOutputStatus	-	Yes	-
HDMIInputPassThrough	Yes	Yes	Enabled, Disabled
HDMIInputWindow	Yes	Yes	Enabled, Disabled
Hostname	-	Yes	-
IPAddress	-	Yes	-
InputSignalStatus	-	Yes	-
LabelVisibility	Yes	Yes	Params: Label Show, Hide
LoopPlay	Yes	Yes	On, Off
NumberOfContentSharedonOutput	-	-	-
NumberOfUsersConnected	-	-	-
NumberOfUsersNotSharing	-	-	-
NumberOfUsersPending	-	-	-
NumberOfUsersSharing	-	-	-
OutputResolution	Yes	Yes	640x480 (60 Hz), 800x600 (60 Hz), 1024x768 (60 Hz), 1280x768 (60 Hz), 1280x800 (60 Hz), 1280x1024 (60 Hz), 1360x768 (60 Hz), 1366x768 (60 Hz), 1440x900 (60 Hz), 1400x1050 (60 Hz), 1600x900 (60 Hz), 1680x1050 (60 Hz), 1600x1200 (60 Hz), 1920x1200 (60 Hz), 480p (60 Hz), 480p (59.94 Hz), 576p (50 Hz), 720p (60 Hz), 720p (59.94 Hz), 720p (50 Hz), 720p (30 Hz), 720p (29.97 Hz), 720p (25 Hz), 1080i (60 Hz), 1080i (59.94 Hz), 1080i (50 Hz), 1080p (60 Hz), 1080p (59.94 Hz), 1080p (50 Hz), 1080p (30 Hz), 1080p (29.97 Hz), 1080p (25 Hz), 1080p (24 Hz), 1080p (23.98 Hz), 2K 2048x1080 (60 Hz), 2K 2048x1080 (59.94 Hz), 2K 2048x1080 (50 Hz), 2K 2048x1080 (30 Hz), 2K 2048x1080 (29.97 Hz), 2K 2048x1080 (25 Hz), 2K 2048x1080 (24 Hz), 2K 2048x1080 (23.98 Hz), 2048x1200 (60 Hz), 2048x1536 (60 Hz), 2560x1080 (60 Hz), 2560x1440 (60 Hz), 2560x1600 (60 Hz), 4K 3840x2160 (60 Hz), 4K 3840x2160 (59.94 Hz), 4K 3840x2160 (50 Hz), 4K 3840x2160 (30 Hz), 4K 3840x2160 (29.97 Hz), 4K 3840x2160 (25 Hz), 4K 3840x2160 (24 Hz), 4K 3840x2160 (23.98 Hz), 4096x2160 (60 Hz), 4096x2160 (59.94 Hz), 4096x2160 (50 Hz), 4096x2160 (30 Hz), 4096x2160 (29.97 Hz), 4096x2160 (25 Hz), 4096x2160 (24 Hz), 4096x2160 (23.98 Hz)
PendingUserConnection	Yes	-	Params: Group, Button Approve, Reject, Pending
PendingUserName	-	-	Params: Button
PendingUserNavigation	Yes	-	-
Playback	Yes	Yes	Play, Pause, Stop, Next, Previous

Command	Set	Update	Allowed values / Parameters
PlayerStatus	-	Yes	-
Reboot	Yes	-	-
RefreshAllUsers	Yes	-	-
RefreshConnectedUsers	Yes	-	-
RefreshFiles	Yes	-	-
RefreshPendingUsers	Yes	-	-
RefreshSharingUsers	Yes	-	-
Response	-	-	-
Restart	Yes	-	-
ScreenSaverStatus	-	Yes	-
SharingUserContentType	-	-	Params: Button
SharingUserName	-	-	Params: Button
SharingUserNavigation	Yes	-	-
SharingUserNumberOfContentShared	-	-	Params: Button
StatusBar	Yes	Yes	Always Visible, Always Hidden, Hide when one content is shared, Hide whenever content is shared
StopAllShares	Yes	-	-
StopIndividualShare	Yes	-	Params: Group, Button
StopShare	Yes	-	Params: Group, Button
VideoMute	Yes	Yes	On, Off, On with Sync
Volume	Yes	Yes	-

Command strings

Raw command / query strings sent to the device, extracted from each Set/Update method (control characters shown as Python escapes, e.g. \r).

SetAccessMode

'wM{ }SHAR\r\n'.format(...)

values: Full Control→1, Moderated→2, Run-time→3

SetAllPendingUserConnections

'\x1bC0*{ }SHAR\r\n'.format(...)

values: Approve→1, Reject→0, Pending→2

SetAudioMute

'1*{ }Z'.format(...)

values: On→1, Off→0

SetChannelPresetRecall

'{0}T'.format(...)

SetChannelPresetRecallStep

'{0}T'.format(...)

values: Next→+, Previous→-

SetClosedCaption

'wE1*{0}SUBT\r\n'.format(...)
values: On→1, Off→0

SetDisconnectAllUsers

'\x1bD0SHAR\r\n'

SetDisconnectUser

'\x1bD{}SHAR\r\n'.format(...)

SetExecutiveMode

values: On→1X, Off→0X

SetExpoMode

'wP{}SHAR\r\n'.format(...)
values: Off→0, Lock-Out→1, Temporary→2

SetFullScreenSharedContent

'wF{}*1SHAR\r\n'.format(...)

SetFullScreenSharedContentRevert

'wF0SHAR\r\n'

SetHDCPInputAuthorization

'\x1bE1*{}HDCP\r\n'.format(...)
values: On→1, Off→0

SetHDCPMode

'\x1bS1*{}HDCP\r\n'.format(...)
values: Follow Input→0, Always Encrypt→1, Follow Input (with continuous DVI trials)→2, Always Encrypt (with continuous DVI trials)→3, Disable Authentication→4

SetHDMIInputPassThrough

'{}!'.format(...)
values: Enabled→1, Disabled→0

SetHDMIInputWindow

'\x1b{}PIPS\r\n'.format(...)
values: Enabled→1, Disabled→0

SetLabelVisibility

'wV{}*{}OSDL\r\n'.format(...)
values: Show→1, Hide→0
values: Hostname→1, IP Address→2, Message Text→5, Code→4, Date/Time→7, Notifications/Messages→6

SetLoopPlay

'wR1*{0}PLYR\r\n'.format(...)
values: On→1, Off→0

SetOutputResolution

'w1*{}RATE\r\n'.format(...)

SetPendingUserConnection

'\x1bC{}*{}SHAR\r\n'.format(...)
values: Approve→1, Reject→0, Pending→2

SetPlayback

'{0}PLYR\r\n'.format(...)
values: Play→wS1*1, Pause→wE1, Stop→wO1, Next→wN1, Previous→wP1

SetReboot

'\x1b1B00T\r\n'

SetRefreshFiles

'wLF\r'

SetRestart

'\x1b2B00T\r\n'

SetStatusBar

'wM{}OSDL\r\n'.format(...)
values: Always Visible→1, Always Hidden→3, Hide when one content is shared→2, Hide whenever content is shared→0

SetStopAllShares

'\x1bS0SHAR\r\n'

SetStopIndividualShare

'\x1bS{}*{}SHAR\r\n'.format(...)

SetStopShare

'\x1bS{}SHAR\r\n'.format(...)

SetVideoMute

'1*{0}b'.format(...)
values: On→1, Off→0, On with Sync→2

SetVolume

'{0}V'.format(...)
values: Min→-100, Max→0

UpdateAccessMode

'wMSHAR\r\n'

UpdateAudioMute

'1Z'

UpdateChannelPresetRecall

'T'

UpdateClosedCaption

'wE1SUBT\r\n'

UpdateConfirmationCode

'\x1bVPINC\r\n'

UpdateConfirmationCodeMode

'\x1bMPINC\r\n'

UpdateCurrentSourceItem

'wU1PLYR\r\n'

UpdateExecutiveMode

'X'

UpdateExpoMode

'wPSHAR\r\n'

UpdateFullScreenSharedContentStatus

'wFSHAR\r\n'

UpdateHDCPInputAuthorization

'\x1bE1HDCP\r\n'

UpdateHDCPInputStatus

'\x1bI1HDCP\r\n'

UpdateHDCPMode

'\x1bS1HDCP\r\n'

UpdateHDCPOutputStatus

'\x1bO1HDCP\r\n'

UpdateHDMIInputPassThrough

'!'

UpdateHDMIInputWindow

'\x1bPIPS\r\n'

UpdateHostname

'\x1bHZCON\r\n'

UpdateIPAddress

'w1CISG\r\n'

UpdateInputSignalStatus

'\x1b0LS\r\n'

UpdateLabelVisibility

'wV{}0SDL\r\n'.format(...)

values: Hostname→1, IP Address→2, Message Text→5, Code→4, Date/Time→7, Notifications/Messages→6

UpdateLoopPlay

'wR1PLYR\r\n'

UpdateOutputResolution

'w1RATE\r\n'

UpdatePlayback

'wY1PLYR\r\n'

UpdatePlayerStatus

'wQSHAR\r\n'

UpdateScreenSaverStatus

'wS1SSAV\r\n'

UpdateStatusBar

'wMOSDL\r\n'

UpdateVideoMute

'1b'

UpdateVolume

'v'