

extr_switcher_DTP3_T_212_D_v1_0_0_0

Command reference — **generated based on the Python file** device/extr_switcher_DTP3_T_212_D_v1_0_0_0.py.
This document was produced automatically by parsing the driver module (no vendor documentation was available for this device); it lists the control/status commands the module implements.

Generated 2026-07-17

Commands

Command	Set	Update	Allowed values / Parameters
AudioInputFormat	Yes	Yes	Params: Input
AudioMute	Yes	Yes	-
AutoswitchMode	Yes	Yes	-
HDCPInputAuthorization	Yes	Yes	Params: Input
HDCPInputStatus	-	Yes	Params: Input
HDCPOutputStatus	-	Yes	-
Input	Yes	Yes	-
InputSignalStatus	-	Yes	Params: Input
VideoMute	Yes	Yes	-

Command strings

Raw command / query strings sent to the device, extracted from each Set/Update method (control characters shown as Python escapes, e.g. `\r`).

SetAudioInputFormat

```
'wI{0}*{1}AFMT\r'.format(...)
```

values: Auto→0, Digital→1, Analog→2

SetAudioMute

```
'{0}Z'.format(...)
```

values: On→1, Off→0

SetAutoswitchMode

```
'w{0}AUSw\r'.format(...)
```

values: Highest Active Input→1, Lowest Active Input→2, Off→0

SetHDCPInputAuthorization

```
'wE{0}*{1}HDCP\r'.format(...)
```

values: On→1, Off→0

SetInput

values: 1→1!, 2→2!

SetVideoMute

```
'{0}B'.format(...)
```

values: On→1, On with Sync→2, Off→0

UpdateAudioInputFormat

'wIAFMT\r'

UpdateAudioMute

'Z'

UpdateAutoswitchMode

'wAUSW\r'

UpdateHDCPInputAuthorization

'wEHDCP\r'

UpdateHDCPInputStatus

'wIHDCP\r'

UpdateHDCPOutputStatus

'wOHDCP\r'

UpdateInput

'!'

UpdateInputSignalStatus

'wLS\r'

UpdateVideoMute

'B'