

infc_tdisplay_INF8640e

Command reference — **generated based on the Python file** `device/infc_tdisplay_INF8640e.py`. This document was produced automatically by parsing the driver module (no vendor documentation was available for this device); it lists the control/status commands the module implements.

Generated 2026-07-17

Device information

Property	Value
Device type	display
Models	INF6540e, INF7540e, INF8640e
Connection	com_type=Serial

Commands

Command	Set	Update	Allowed values / Parameters
AspectRatio	Yes	-	Full (16:9), Normal (4:3), P2P
AudioMute	Yes	Yes	On, Off
Input	Yes	Yes	OPS, AV, HDMI, HDMI 1, HDMI 2, HDMI 3, HDMI 4, VGA, DisplayPort, Android, Android+
Power	Yes	Yes	On, Off
Volume	Yes	Yes	-

Command strings

Raw command / query strings sent to the device, extracted from each Set/Update method (control characters shown as Python escapes, e.g. `\r`).

SetAspectRatio

values: Full (16:9)→:01S;000 , Normal (4:3)→:01S;001 , P2P→:01S;002

SetAudioMute

values: On→:01S9001 , Off→:01S9000

SetInput

values: OPS→:01S:103 , AV→:01S:003 , HDMI→:01S:001 , HDMI 1→:01S:001 , HDMI 2→:01S:002 , HDMI 3→:01S:021 , HDMI 4→:01S:022 , VGA→:01S:000 , DisplayPort→:01S:007 , Android→:01S:101 , Android+→:01S:102

SetPower

values: On→:01S0003 , Off→:01S0002

SetVolume

`' :01S8{0:03}\r'.format(...)`
values: Min→0, Max→100

UpdateAudioMute

' : 01G9000\r '

values: 1→On, 0→Off

UpdateInput

' : 01G:000\r '

values: 103→OPS, 003→AV, 001→HDMI 1, 002→HDMI 2, 021→HDMI 3, 022→HDMI 4, 000→VGA, 007→DisplayPort, 101→Android, 102→Android+

UpdatePower

' : 01G0000\r '

values: 1→On, 2→Off, 0→Standby

UpdateVolume

' : 01G8000\r '