

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Switcher
Manufacturer: Vaddio
Firmware Version: N/A
Model(s): AV Bridge 2x1

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.16.0000-b013	2.17.0

Version History

Module Version	Date	Notes
1_0_5_0	12/1/2022	Initial Version

Module Notes

- Unidirectional variable must be set to 'True' if status is not required. Default value is 'False'.
Example: `InterfaceName.Unidirectional = 'True'`
- connectionCounter variable must be set to the number of queries that will be sent to the device before displaying 'Disconnected' if no response is received. Default value is 15.
Example: `InterfaceName.connectionCounter = 5`
- If login credentials are required, devicePassword and deviceUsername must be set accordingly. devicePassword and deviceUsername default values are password and admin respectively.
Example: `InterfaceName.devicePassword = 'extron'`

Supported Classes and Examples

SerialClass
<code>InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='AV Bridge 2x1')</code>
SerialOverEthernetClass
<code>InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='AV Bridge 2x1')</code>
EthernetClass
<code>InterfaceName = ModuleName.EthernetClass('192.168.254.254', 23, Model='AV Bridge 2x1')</code>

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command AudioCrosspointGain	Value -12 to 12 in steps of 1 dB		
Qualifier Key 'Output'	Qualifier Value 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
Qualifier Key 'Input'	Qualifier Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Left' 'Dante In 2'	Qualifier Value 'Line In 2' 'HDMI In 1 Left' 'Dante In 4' 'Dante In 1'	Qualifier Value 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 3' 'HDMI In 2 Right'
# AudioCrosspointGain example InterfaceName.Set('AudioCrosspointGain', 12, {'Output': 'Line Out 1', 'Input': 'Line In 1'})			
Command AudioMute	Value 'On'	Value 'Off'	
Qualifier Key 'Channel'	Qualifier Value 'Master' 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 2' 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Right' 'Dante In 3' 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'Line In 2' 'HDMI In 2 Left' 'Dante In 1' 'Dante In 4' 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
# AudioMute example InterfaceName.Set('AudioMute', 'On', {'Channel': 'Master'})			
Command AudioRoute	Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Left' 'Dante In 2'	Value 'Line In 2' 'HDMI In 1 Left' 'HDMI In 2 Right' 'Dante In 3'	Value 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 1' 'Dante In 4'
Qualifier Key 'Channel'	Qualifier Value 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
# AudioRoute example InterfaceName.Set('AudioRoute', 'Line In 1', {'Channel': 'Line Out 1'})			

Global Scripter Module
Communication Sheet

Revision: 12/1/2022

Command AudioVolume	Value -50 to 20 in steps of 1 dB		
Qualifier Key 'Channel'	Qualifier Value 'Master' 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 2' 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Right' 'Dante In 3' 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'Line In 2' 'HDMI In 2 Left' 'Dante In 1' 'Dante In 4' 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
# AudioVolume example InterfaceName.Set('AudioVolume', 20, {'Channel': 'Master'})			
Command CameraStandby	Value 'On'	Value 'Off'	
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
# CameraStandby example InterfaceName.Set('CameraStandby', 'On', {'Camera': '1'})			
Command Focus	Value 'Near'	Value 'Far'	Value 'Stop'
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
Qualifier Key 'Focus Speed'	Qualifier Value '1' – '8'		
# Focus example InterfaceName.Set('Focus', 'Near', {'Camera': '1', 'Focus Speed': '1'})			
Command FocusMode	Value 'Auto'	Value 'Manual'	
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
# FocusMode example InterfaceName.Set('FocusMode', 'Auto', {'Camera': '1'})			
Command Home	Value None		
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
# Home example InterfaceName.Set('Home', None, {'Camera': '1'})			
Command Input	Value '1' – '2'		
# Input example InterfaceName.Set('Input', '1')			
Command IPStreaming	Value 'On'	Value 'Off'	
# IPStreaming example InterfaceName.Set('IPStreaming', 'On')			

Command Pan	Value 'Left'	Value 'Right'	Value 'Stop'
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
Qualifier Key 'Pan Speed'	Qualifier Value '1' – '24'		
# Pan example InterfaceName.Set('Pan', 'Left', {'Camera': '1', 'Pan Speed': '1'})			
Command PIPLayout	Value 'Upper Right' 'Upper Left'	Value 'Lower Right' 'Top Bottom'	Value 'Lower Left' 'Left Right'
# PIPLayout example InterfaceName.Set('PIPLayout', 'Upper Right')			
Command PIPMode	Value 'On'	Value 'Off'	Value 'Toggle'
# PIPMode example InterfaceName.Set('PIPMode', 'On')			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command PresetRecall	Value '1' – '16'		
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
# PresetRecall example InterfaceName.Set('PresetRecall', '1', {'Camera': '1'})			
Command PresetSave	Value '1' – '16'		
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
# PresetSave example InterfaceName.Set('PresetSave', '1', {'Camera': '1'})			
Command Tilt	Value 'Up'	Value 'Down'	Value 'Stop'
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
Qualifier Key 'Tilt Speed'	Qualifier Value '1' – '20'		
# Tilt example InterfaceName.Set('Tilt', 'Up', {'Camera': '1', 'Tilt Speed': '1'})			
Command Trigger ¹	Value 'On'	Value 'Off'	
Qualifier Key 'Index'	Qualifier Value '1' – '10'		
Qualifier Key 'Block'	Qualifier Value 0 – 999		
# Trigger example InterfaceName.Set('Trigger', 'On', {'Index': '1', 'Block': 999})			

Command VideoMute	Value 'On'	Value 'Off'	
Qualifier Key 'Channel'	Qualifier Value 'Master'	Qualifier Value 'Input 1'	Qualifier Value 'Input 2'
# VideoMute example InterfaceName.Set('VideoMute', 'On', {'Channel': 'Master'})			
Command VideoType	Value 'Camera'	Value 'Video'	
Qualifier Key 'Channel'	Qualifier Value 'Input 1'	Qualifier Value 'Input 2'	
# VideoType example InterfaceName.Set('VideoType', 'Camera', {'Channel': 'Input 1'})			
Command Zoom	Value 'In'	Value 'Out'	Value 'Stop'
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
Qualifier Key 'Zoom Speed'	Qualifier Value '1' – '7'		
# Zoom example InterfaceName.Set('Zoom', 'In', {'Camera': '1', 'Zoom Speed': '1'})			

¹ This command has no effect if the specified trigger has not been defined. If the web interface's macro/trigger test mode is in use, this command is disabled. When Block value is set to '0' this parameter is ignored.

Status Available

For all commands, call Update to receive the latest status. ConnectionStatus does not support the Update function and is triggered by the device providing a successful response to other Update function calls.

Format with Qualifier:

```
InterfaceName.Update(Command, {'Qualifier Key': 'Qualifier Value'})
Value = InterfaceName.ReadStatus(Command, {'Qualifier Key': 'Qualifier Value'})
InterfaceName.SubscribeStatus(Command, {'Qualifier Key': 'Qualifier Value'},
```

FeedbackHandler)

FeedbackHandler will be called only when the specified qualifier gets a new status.

Format without Qualifier:

```
InterfaceName.Update(Command)
Value = InterfaceName.ReadStatus(Command)
InterfaceName.SubscribeStatus(Command, None, FeedbackHandler)
FeedbackHandler will be called when any qualifier gets a new status.
```

Command AudioCrosspointGain	Value -12 to 12 in steps of 1 dB		
Qualifier Key 'Output'	Qualifier Value 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
Qualifier Key 'Input'	Qualifier Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Left' 'Dante In 2'	Qualifier Value 'Line In 2' 'HDMI In 1 Left' 'Dante In 4' 'Dante In 1'	Qualifier Value 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 3' 'HDMI In 2 Right'
# AudioCrosspointGain example InterfaceName.Update('AudioCrosspointGain', {'Output': 'Line Out 1', 'Input': 'Line In 1'}) Value = InterfaceName.ReadStatus('AudioCrosspointGain', {'Output': 'Line Out 1', 'Input': 'Line In 1'}) InterfaceName.SubscribeStatus('AudioCrosspointGain', None, FeedbackHandler)			
Command AudioMute	Value 'On'	Value 'Off'	
Qualifier Key 'Channel'	Qualifier Value 'Master' 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 2' 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Right' 'Dante In 3' 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'Line In 2' 'HDMI In 2 Left' 'Dante In 1' 'Dante In 4' 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
# AudioMute example InterfaceName.Update('AudioMute', {'Channel': 'Master'}) Value = InterfaceName.ReadStatus('AudioMute', {'Channel': 'Master'}) InterfaceName.SubscribeStatus('AudioMute', None, FeedbackHandler)			

Global Scripter Module
Communication Sheet

Revision: 12/1/2022

Command AudioRoute	Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Left' 'Dante In 2'	Value 'Line In 2' 'HDMI In 1 Left' 'HDMI In 2 Right' 'Dante In 3'	Value 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 1' 'Dante In 4'
Qualifier Key 'Channel'	Qualifier Value 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
# AudioRoute example InterfaceName.Update('AudioRoute', {'Channel': 'Line Out 1'}) Value = InterfaceName.ReadStatus('AudioRoute', {'Channel': 'Line Out 1'}) InterfaceName.SubscribeStatus('AudioRoute', None, FeedbackHandler)			
Command AudioVolume	Value -50 to 20 in steps of 1 dB		
Qualifier Key 'Channel'	Qualifier Value 'Master' 'USB3 Playback Left' 'HDMI In 1 Right' 'Dante In 2' 'Line Out 1' 'USB3 Record Right' 'HDMI Out Left' 'Dante Out 2'	Qualifier Value 'Line In 1' 'USB3 Playback Right' 'HDMI In 2 Right' 'Dante In 3' 'Line Out 2' 'IP Out Left' 'HDMI Out Right' 'Dante Out 3'	Qualifier Value 'Line In 2' 'HDMI In 2 Left' 'Dante In 1' 'Dante In 4' 'USB3 Record Left' 'IP Out Right' 'Dante Out 1' 'Dante Out 4'
# AudioVolume example InterfaceName.Update('AudioVolume', {'Channel': 'Master'}) Value = InterfaceName.ReadStatus('AudioVolume', {'Channel': 'Master'}) InterfaceName.SubscribeStatus('AudioVolume', None, FeedbackHandler)			
Command CameraStandby	Value 'On'	Value 'Off'	
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
# CameraStandby example InterfaceName.Update('CameraStandby', {'Camera': '1'}) Value = InterfaceName.ReadStatus('CameraStandby', {'Camera': '1'}) InterfaceName.SubscribeStatus('CameraStandby', None, FeedbackHandler)			
Command ConnectionStatus	Value 'Connected'	Value 'Disconnected'	
# ConnectionStatus example Value = InterfaceName.ReadStatus('ConnectionStatus') InterfaceName.SubscribeStatus('ConnectionStatus', None, FeedbackHandler)			
Command FocusMode	Value 'Auto'	Value 'Manual'	
Qualifier Key 'Camera'	Qualifier Value '1' – '2'		
# FocusMode example InterfaceName.Update('FocusMode', {'Camera': '1'}) Value = InterfaceName.ReadStatus('FocusMode', {'Camera': '1'}) InterfaceName.SubscribeStatus('FocusMode', None, FeedbackHandler)			

Command Input	Value '1' – '2'		
# Input example InterfaceName.Update('Input') Value = InterfaceName.ReadStatus('Input') InterfaceName.SubscribeStatus('Input', None, FeedbackHandler)			
Command IPStreaming	Value 'On'	Value 'Off'	
# IPStreaming example InterfaceName.Update('IPStreaming') Value = InterfaceName.ReadStatus('IPStreaming') InterfaceName.SubscribeStatus('IPStreaming', None, FeedbackHandler)			
Command Power	Value 'On'	Value 'Off'	
# Power example InterfaceName.Update('Power') Value = InterfaceName.ReadStatus('Power') InterfaceName.SubscribeStatus('Power', None, FeedbackHandler)			
Command StreamingSettingStatus	Value 'String'		
Qualifier Key 'Type'	Qualifier Value 'IP Custom Frame Rate' 'IP MTU' 'IP Preset Resolution' 'IP Video Mode' 'USB Frame Rate'	Qualifier Value 'IP Custom Resolution' 'IP Port' 'IP Protocol' 'USB Active' 'USB Resolution'	Qualifier Value 'IP Enabled' 'IP Preset Quality' 'IP URL' 'USB Device' 'USB Version'
# StreamingSettingStatus example InterfaceName.Update('StreamingSettingStatus', {'Type': 'IP Custom Frame Rate'}) Value = InterfaceName.ReadStatus('StreamingSettingStatus', {'Type': 'IP Custom Frame Rate'}) InterfaceName.SubscribeStatus('StreamingSettingStatus', None, FeedbackHandler)			
Command VideoMute	Value 'On'	Value 'Off'	
Qualifier Key 'Channel'	Qualifier Value 'Master'	Qualifier Value 'Input 1'	Qualifier Value 'Input 2'
# VideoMute example InterfaceName.Update('VideoMute', {'Channel': 'Master'}) Value = InterfaceName.ReadStatus('VideoMute', {'Channel': 'Master'}) InterfaceName.SubscribeStatus('VideoMute', None, FeedbackHandler)			
Command VideoType	Value 'Camera'	Value 'Video'	
Qualifier Key 'Channel'	Qualifier Value 'Input 1'	Qualifier Value 'Input 2'	
# VideoType example InterfaceName.Update('VideoType', {'Channel': 'Input 1'}) Value = InterfaceName.ReadStatus('VideoType', {'Channel': 'Input 1'}) InterfaceName.SubscribeStatus('VideoType', None, FeedbackHandler)			

Cable and Adapter Requirements

Captive Screw to RJ-45 RS-232 Serial Cable

Notes for the Device

- Supports Authentication, Default Username is “admin” and default Password is “password”.

Serial communication

Port Type: RS-232

Baud Rate: 38400


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
RxD	←	7	TxD
TxD	→	8	RxD
GND	→	6	GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet (TCP)

Default Port: 23

Logon Credentials Supported: Yes

Default Username: admin

Default Password: password

Multi-Connection: Undetermined

Capabilities:

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

- Telnet Access must be enabled for module to work properly. This setting can be found under Security page in the device's embedded webpage.

Appendix A. Set Commands

Audio Crosspoint Gain 12 Output Dante Out 1 Input Dante In 1	audio dante_out_1 crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input Dante In 1	audio dante_out_1 crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input Dante In 2	audio dante_out_1 crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input Dante In 2	audio dante_out_1 crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input Dante In 3	audio dante_out_1 crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input Dante In 3	audio dante_out_1 crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input Dante In 4	audio dante_out_1 crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input Dante In 4	audio dante_out_1 crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input HDMI In 1 Left	audio dante_out_1 crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input HDMI In 1 Left	audio dante_out_1 crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input HDMI In 1 Right	audio dante_out_1 crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input HDMI In 1 Right	audio dante_out_1 crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input HDMI In 2 Left	audio dante_out_1 crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input HDMI In 2 Left	audio dante_out_1 crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input HDMI In 2 Right	audio dante_out_1 crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input HDMI In 2 Right	audio dante_out_1 crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input Line In 1	audio dante_out_1 crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input Line In 1	audio dante_out_1 crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input Line In 2	audio dante_out_1 crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input Line In 2	audio dante_out_1 crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input USB3 Playback Left	audio dante_out_1 crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input USB3 Playback Left	audio dante_out_1 crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 1 Input	audio dante_out_1 crosspoint-gain

Global Scriptor Module
Communication Sheet

USB3 Playback Right	usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 1 Input USB3 Playback Right	audio dante_out_1 crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input Dante In 1	audio dante_out_2 crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input Dante In 1	audio dante_out_2 crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input Dante In 2	audio dante_out_2 crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input Dante In 2	audio dante_out_2 crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input Dante In 3	audio dante_out_2 crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input Dante In 3	audio dante_out_2 crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input Dante In 4	audio dante_out_2 crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input Dante In 4	audio dante_out_2 crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input HDMI In 1 Left	audio dante_out_2 crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input HDMI In 1 Left	audio dante_out_2 crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input HDMI In 1 Right	audio dante_out_2 crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input HDMI In 1 Right	audio dante_out_2 crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input HDMI In 2 Left	audio dante_out_2 crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input HDMI In 2 Left	audio dante_out_2 crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input HDMI In 2 Right	audio dante_out_2 crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input HDMI In 2 Right	audio dante_out_2 crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input Line In 1	audio dante_out_2 crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input Line In 1	audio dante_out_2 crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input Line In 2	audio dante_out_2 crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input Line In 2	audio dante_out_2 crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 2 Input USB3 Playback Left	audio dante_out_2 crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input USB3 Playback Left	audio dante_out_2 crosspoint-gain usb3_playback_left set -12\x0D\x0A

Global Scripter Module
Communication Sheet

Audio Crosspoint Gain 12 Output Dante Out 2 Input USB3 Playback Right	audio dante_out_2 crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 2 Input USB3 Playback Right	audio dante_out_2 crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input Dante In 1	audio dante_out_3 crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input Dante In 1	audio dante_out_3 crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input Dante In 2	audio dante_out_3 crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input Dante In 2	audio dante_out_3 crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input Dante In 3	audio dante_out_3 crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input Dante In 3	audio dante_out_3 crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input Dante In 4	audio dante_out_3 crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input Dante In 4	audio dante_out_3 crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input HDMI In 1 Left	audio dante_out_3 crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input HDMI In 1 Left	audio dante_out_3 crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input HDMI In 1 Right	audio dante_out_3 crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input HDMI In 1 Right	audio dante_out_3 crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input HDMI In 2 Left	audio dante_out_3 crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input HDMI In 2 Left	audio dante_out_3 crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input HDMI In 2 Right	audio dante_out_3 crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input HDMI In 2 Right	audio dante_out_3 crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input Line In 1	audio dante_out_3 crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input Line In 1	audio dante_out_3 crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input Line In 2	audio dante_out_3 crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input Line In 2	audio dante_out_3 crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input USB3 Playback Left	audio dante_out_3 crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input	audio dante_out_3 crosspoint-gain

Global Scriptor Module Communication Sheet

Revision: 12/1/2022

USB3 Playback Left	usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 3 Input USB3 Playback Right	audio dante_out_3 crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 3 Input USB3 Playback Right	audio dante_out_3 crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input Dante In 1	audio dante_out_4 crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input Dante In 1	audio dante_out_4 crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input Dante In 2	audio dante_out_4 crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input Dante In 2	audio dante_out_4 crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input Dante In 3	audio dante_out_4 crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input Dante In 3	audio dante_out_4 crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input Dante In 4	audio dante_out_4 crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input Dante In 4	audio dante_out_4 crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input HDMI In 1 Left	audio dante_out_4 crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input HDMI In 1 Left	audio dante_out_4 crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input HDMI In 1 Right	audio dante_out_4 crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input HDMI In 1 Right	audio dante_out_4 crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input HDMI In 2 Left	audio dante_out_4 crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input HDMI In 2 Left	audio dante_out_4 crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input HDMI In 2 Right	audio dante_out_4 crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input HDMI In 2 Right	audio dante_out_4 crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input Line In 1	audio dante_out_4 crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input Line In 1	audio dante_out_4 crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input Line In 2	audio dante_out_4 crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input Line In 2	audio dante_out_4 crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input USB3 Playback Left	audio dante_out_4 crosspoint-gain usb3_playback_left set 12\x0D\x0A

Audio Crosspoint Gain -12 Output Dante Out 4 Input USB3 Playback Left	audio dante_out_4 crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Dante Out 4 Input USB3 Playback Right	audio dante_out_4 crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Dante Out 4 Input USB3 Playback Right	audio dante_out_4 crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input Dante In 1	audio hdmi_out_left crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input Dante In 1	audio hdmi_out_left crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input Dante In 2	audio hdmi_out_left crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input Dante In 2	audio hdmi_out_left crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input Dante In 3	audio hdmi_out_left crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input Dante In 3	audio hdmi_out_left crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input Dante In 4	audio hdmi_out_left crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input Dante In 4	audio hdmi_out_left crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input HDMI In 1 Left	audio hdmi_out_left crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input HDMI In 1 Left	audio hdmi_out_left crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input HDMI In 1 Right	audio hdmi_out_left crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input HDMI In 1 Right	audio hdmi_out_left crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input HDMI In 2 Left	audio hdmi_out_left crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input HDMI In 2 Left	audio hdmi_out_left crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input HDMI In 2 Right	audio hdmi_out_left crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input HDMI In 2 Right	audio hdmi_out_left crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input Line In 1	audio hdmi_out_left crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input Line In 1	audio hdmi_out_left crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input Line In 2	audio hdmi_out_left crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input Line In 2	audio hdmi_out_left crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left	audio hdmi_out_left crosspoint-gain

Input USB3 Playback Left	usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input USB3 Playback Left	audio_hdmi_out_left_crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Left Input USB3 Playback Right	audio_hdmi_out_left_crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Left Input USB3 Playback Right	audio_hdmi_out_left_crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input Dante In 1	audio_hdmi_out_right_crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input Dante In 1	audio_hdmi_out_right_crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input Dante In 2	audio_hdmi_out_right_crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input Dante In 2	audio_hdmi_out_right_crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input Dante In 3	audio_hdmi_out_right_crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input Dante In 3	audio_hdmi_out_right_crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input Dante In 4	audio_hdmi_out_right_crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input Dante In 4	audio_hdmi_out_right_crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input HDMI In 1 Left	audio_hdmi_out_right_crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input HDMI In 1 Left	audio_hdmi_out_right_crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input HDMI In 1 Right	audio_hdmi_out_right_crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input HDMI In 1 Right	audio_hdmi_out_right_crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input HDMI In 2 Left	audio_hdmi_out_right_crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input HDMI In 2 Left	audio_hdmi_out_right_crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input HDMI In 2 Right	audio_hdmi_out_right_crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input HDMI In 2 Right	audio_hdmi_out_right_crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input Line In 1	audio_hdmi_out_right_crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input Line In 1	audio_hdmi_out_right_crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input Line In 2	audio_hdmi_out_right_crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input Line In 2	audio_hdmi_out_right_crosspoint-gain line_in_2 set -12\x0D\x0A

Audio Crosspoint Gain 12 Output HDMI Out Right Input USB3 Playback Left	audio hdmi_out_right crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input USB3 Playback Left	audio hdmi_out_right crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output HDMI Out Right Input USB3 Playback Right	audio hdmi_out_right crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output HDMI Out Right Input USB3 Playback Right	audio hdmi_out_right crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input Dante In 1	audio ip_out_left crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input Dante In 1	audio ip_out_left crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input Dante In 2	audio ip_out_left crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input Dante In 2	audio ip_out_left crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input Dante In 3	audio ip_out_left crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input Dante In 3	audio ip_out_left crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input Dante In 4	audio ip_out_left crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input Dante In 4	audio ip_out_left crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input HDMI In 1 Left	audio ip_out_left crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input HDMI In 1 Left	audio ip_out_left crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input HDMI In 1 Right	audio ip_out_left crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input HDMI In 1 Right	audio ip_out_left crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input HDMI In 2 Left	audio ip_out_left crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input HDMI In 2 Left	audio ip_out_left crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input HDMI In 2 Right	audio ip_out_left crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input HDMI In 2 Right	audio ip_out_left crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input Line In 1	audio ip_out_left crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input Line In 1	audio ip_out_left crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input Line In 2	audio ip_out_left crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input	audio ip_out_left crosspoint-gain line_in_2 set

Line In 2	-12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input USB3 Playback Left	audio ip_out_left crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input USB3 Playback Left	audio ip_out_left crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Left Input USB3 Playback Right	audio ip_out_left crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Left Input USB3 Playback Right	audio ip_out_left crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input Dante In 1	audio ip_out_right crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input Dante In 1	audio ip_out_right crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input Dante In 2	audio ip_out_right crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input Dante In 2	audio ip_out_right crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input Dante In 3	audio ip_out_right crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input Dante In 3	audio ip_out_right crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input Dante In 4	audio ip_out_right crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input Dante In 4	audio ip_out_right crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input HDMI In 1 Left	audio ip_out_right crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input HDMI In 1 Left	audio ip_out_right crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input HDMI In 1 Right	audio ip_out_right crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input HDMI In 1 Right	audio ip_out_right crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input HDMI In 2 Left	audio ip_out_right crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input HDMI In 2 Left	audio ip_out_right crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input HDMI In 2 Right	audio ip_out_right crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input HDMI In 2 Right	audio ip_out_right crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input Line In 1	audio ip_out_right crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input Line In 1	audio ip_out_right crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input Line In 2	audio ip_out_right crosspoint-gain line_in_2 set 12\x0D\x0A

Audio Crosspoint Gain -12 Output IP Out Right Input Line In 2	audio ip_out_right crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input USB3 Playback Left	audio ip_out_right crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input USB3 Playback Left	audio ip_out_right crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output IP Out Right Input USB3 Playback Right	audio ip_out_right crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output IP Out Right Input USB3 Playback Right	audio ip_out_right crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input Dante In 1	audio line_out_1 crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input Dante In 1	audio line_out_1 crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input Dante In 2	audio line_out_1 crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input Dante In 2	audio line_out_1 crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input Dante In 3	audio line_out_1 crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input Dante In 3	audio line_out_1 crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input Dante In 4	audio line_out_1 crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input Dante In 4	audio line_out_1 crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input HDMI In 1 Left	audio line_out_1 crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input HDMI In 1 Left	audio line_out_1 crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input HDMI In 1 Right	audio line_out_1 crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input HDMI In 1 Right	audio line_out_1 crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input HDMI In 2 Left	audio line_out_1 crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input HDMI In 2 Left	audio line_out_1 crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input HDMI In 2 Right	audio line_out_1 crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input HDMI In 2 Right	audio line_out_1 crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input Line In 1	audio line_out_1 crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input Line In 1	audio line_out_1 crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input	audio line_out_1 crosspoint-gain line_in_2 set

Global Scriptor Module
Communication Sheet

Line In 2	12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input Line In 2	audio line_out_1 crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input USB3 Playback Left	audio line_out_1 crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input USB3 Playback Left	audio line_out_1 crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 1 Input USB3 Playback Right	audio line_out_1 crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 1 Input USB3 Playback Right	audio line_out_1 crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input Dante In 1	audio line_out_2 crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input Dante In 1	audio line_out_2 crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input Dante In 2	audio line_out_2 crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input Dante In 2	audio line_out_2 crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input Dante In 3	audio line_out_2 crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input Dante In 3	audio line_out_2 crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input Dante In 4	audio line_out_2 crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input Dante In 4	audio line_out_2 crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input HDMI In 1 Left	audio line_out_2 crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input HDMI In 1 Left	audio line_out_2 crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input HDMI In 1 Right	audio line_out_2 crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input HDMI In 1 Right	audio line_out_2 crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input HDMI In 2 Left	audio line_out_2 crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input HDMI In 2 Left	audio line_out_2 crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input HDMI In 2 Right	audio line_out_2 crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input HDMI In 2 Right	audio line_out_2 crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input Line In 1	audio line_out_2 crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input Line In 1	audio line_out_2 crosspoint-gain line_in_1 set -12\x0D\x0A

Audio Crosspoint Gain 12 Output Line Out 2 Input Line In 2	audio line_out_2 crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input Line In 2	audio line_out_2 crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input USB3 Playback Left	audio line_out_2 crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input USB3 Playback Left	audio line_out_2 crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output Line Out 2 Input USB3 Playback Right	audio line_out_2 crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output Line Out 2 Input USB3 Playback Right	audio line_out_2 crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input Dante In 1	audio usb3_record_left crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input Dante In 1	audio usb3_record_left crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input Dante In 2	audio usb3_record_left crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input Dante In 2	audio usb3_record_left crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input Dante In 3	audio usb3_record_left crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input Dante In 3	audio usb3_record_left crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input Dante In 4	audio usb3_record_left crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input Dante In 4	audio usb3_record_left crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input HDMI In 1 Left	audio usb3_record_left crosspoint-gain hdmi_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input HDMI In 1 Left	audio usb3_record_left crosspoint-gain hdmi_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input HDMI In 1 Right	audio usb3_record_left crosspoint-gain hdmi_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input HDMI In 1 Right	audio usb3_record_left crosspoint-gain hdmi_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input HDMI In 2 Left	audio usb3_record_left crosspoint-gain hdmi_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input HDMI In 2 Left	audio usb3_record_left crosspoint-gain hdmi_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input HDMI In 2 Right	audio usb3_record_left crosspoint-gain hdmi_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input HDMI In 2 Right	audio usb3_record_left crosspoint-gain hdmi_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input Line In 1	audio usb3_record_left crosspoint-gain line_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left	audio usb3_record_left crosspoint-gain line_in_1

Global Scriptor Module
Communication Sheet

Input Line In 1	set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input Line In 2	audio usb3_record_left crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input Line In 2	audio usb3_record_left crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input USB3 Playback Left	audio usb3_record_left crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input USB3 Playback Left	audio usb3_record_left crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Left Input USB3 Playback Right	audio usb3_record_left crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Left Input USB3 Playback Right	audio usb3_record_left crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input Dante In 1	audio usb3_record_right crosspoint-gain dante_in_1 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input Dante In 1	audio usb3_record_right crosspoint-gain dante_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input Dante In 2	audio usb3_record_right crosspoint-gain dante_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input Dante In 2	audio usb3_record_right crosspoint-gain dante_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input Dante In 3	audio usb3_record_right crosspoint-gain dante_in_3 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input Dante In 3	audio usb3_record_right crosspoint-gain dante_in_3 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input Dante In 4	audio usb3_record_right crosspoint-gain dante_in_4 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input Dante In 4	audio usb3_record_right crosspoint-gain dante_in_4 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input HDMI In 1 Left	audio usb3_record_right crosspoint-gain hdm_i_in_1_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input HDMI In 1 Left	audio usb3_record_right crosspoint-gain hdm_i_in_1_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input HDMI In 1 Right	audio usb3_record_right crosspoint-gain hdm_i_in_1_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input HDMI In 1 Right	audio usb3_record_right crosspoint-gain hdm_i_in_1_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input HDMI In 2 Left	audio usb3_record_right crosspoint-gain hdm_i_in_2_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input HDMI In 2 Left	audio usb3_record_right crosspoint-gain hdm_i_in_2_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input HDMI In 2 Right	audio usb3_record_right crosspoint-gain hdm_i_in_2_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input HDMI In 2 Right	audio usb3_record_right crosspoint-gain hdm_i_in_2_right set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input Line In 1	audio usb3_record_right crosspoint-gain line_in_1 set 12\x0D\x0A

**Global Scriptor Module
Communication Sheet**

Audio Crosspoint Gain -12 Output USB3 Record Right Input Line In 1	audio usb3_record_right crosspoint-gain line_in_1 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input Line In 2	audio usb3_record_right crosspoint-gain line_in_2 set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input Line In 2	audio usb3_record_right crosspoint-gain line_in_2 set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input USB3 Playback Left	audio usb3_record_right crosspoint-gain usb3_playback_left set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input USB3 Playback Left	audio usb3_record_right crosspoint-gain usb3_playback_left set -12\x0D\x0A
Audio Crosspoint Gain 12 Output USB3 Record Right Input USB3 Playback Right	audio usb3_record_right crosspoint-gain usb3_playback_right set 12\x0D\x0A
Audio Crosspoint Gain -12 Output USB3 Record Right Input USB3 Playback Right	audio usb3_record_right crosspoint-gain usb3_playback_right set -12\x0D\x0A
Audio Mute Off Channel Dante In 1	audio dante_in_1 mute off\x0D\x0A
Audio Mute Off Channel Dante In 2	audio dante_in_2 mute off\x0D\x0A
Audio Mute Off Channel Dante In 3	audio dante_in_3 mute off\x0D\x0A
Audio Mute Off Channel Dante In 4	audio dante_in_4 mute off\x0D\x0A
Audio Mute Off Channel Dante Out 1	audio dante_out_1 mute off\x0D\x0A
Audio Mute Off Channel Dante Out 2	audio dante_out_2 mute off\x0D\x0A
Audio Mute Off Channel Dante Out 3	audio dante_out_3 mute off\x0D\x0A
Audio Mute Off Channel Dante Out 4	audio dante_out_4 mute off\x0D\x0A
Audio Mute Off Channel HDMI In 1 Right	audio hdmi_in_1_right mute off\x0D\x0A
Audio Mute Off Channel HDMI In 2 Left	audio hdmi_in_2_left mute off\x0D\x0A
Audio Mute Off Channel HDMI In 2 Right	audio hdmi_in_2_right mute off\x0D\x0A
Audio Mute Off Channel HDMI Out Left	audio hdmi_out_left mute off\x0D\x0A
Audio Mute Off Channel HDMI Out Right	audio hdmi_out_right mute off\x0D\x0A
Audio Mute Off Channel IP Out Left	audio ip_out_left mute off\x0D\x0A
Audio Mute Off Channel IP Out Right	audio ip_out_right mute off\x0D\x0A
Audio Mute Off Channel Line In 1	audio line_in_1 mute off\x0D\x0A
Audio Mute Off Channel Line In 2	audio line_in_2 mute off\x0D\x0A
Audio Mute Off Channel Line Out 1	audio line_out_1 mute off\x0D\x0A
Audio Mute Off Channel Line Out 2	audio line_out_2 mute off\x0D\x0A
Audio Mute Off Channel Master	audio master mute off\x0D\x0A
Audio Mute Off Channel USB3 Playback Left	audio usb3_playback_left mute off\x0D\x0A
Audio Mute Off Channel USB3 Playback Right	audio usb3_playback_right mute off\x0D\x0A
Audio Mute Off Channel USB3 Record Left	audio usb3_record_left mute off\x0D\x0A
Audio Mute Off Channel USB3 Record Right	audio usb3_record_right mute off\x0D\x0A
Audio Mute On Channel Dante In 1	audio dante_in_1 mute on\x0D\x0A
Audio Mute On Channel Dante In 2	audio dante_in_2 mute on\x0D\x0A
Audio Mute On Channel Dante In 3	audio dante_in_3 mute on\x0D\x0A
Audio Mute On Channel Dante In 4	audio dante_in_4 mute on\x0D\x0A
Audio Mute On Channel Dante Out 1	audio dante_out_1 mute on\x0D\x0A
Audio Mute On Channel Dante Out 2	audio dante_out_2 mute on\x0D\x0A
Audio Mute On Channel Dante Out 3	audio dante_out_3 mute on\x0D\x0A

**Global Scriptor Module
Communication Sheet**

Audio Mute On Channel Dante Out 4	audio dante_out_4 mute on\x0D\x0A
Audio Mute On Channel HDMI In 1 Right	audio hdmi_in_1_right mute on\x0D\x0A
Audio Mute On Channel HDMI In 2 Left	audio hdmi_in_2_left mute on\x0D\x0A
Audio Mute On Channel HDMI In 2 Right	audio hdmi_in_2_right mute on\x0D\x0A
Audio Mute On Channel HDMI Out Left	audio hdmi_out_left mute on\x0D\x0A
Audio Mute On Channel HDMI Out Right	audio hdmi_out_right mute on\x0D\x0A
Audio Mute On Channel IP Out Left	audio ip_out_left mute on\x0D\x0A
Audio Mute On Channel IP Out Right	audio ip_out_right mute on\x0D\x0A
Audio Mute On Channel Line In 1	audio line_in_1 mute on\x0D\x0A
Audio Mute On Channel Line In 2	audio line_in_2 mute on\x0D\x0A
Audio Mute On Channel Line Out 1	audio line_out_1 mute on\x0D\x0A
Audio Mute On Channel Line Out 2	audio line_out_2 mute on\x0D\x0A
Audio Mute On Channel Master	audio master mute on\x0D\x0A
Audio Mute On Channel USB3 Playback Left	audio usb3_playback_left mute on\x0D\x0A
Audio Mute On Channel USB3 Playback Right	audio usb3_playback_right mute on\x0D\x0A
Audio Mute On Channel USB3 Record Left	audio usb3_record_left mute on\x0D\x0A
Audio Mute On Channel USB3 Record Right	audio usb3_record_right mute on\x0D\x0A
Audio Route Dante In 1 Channel Dante Out 1	audio dante_out_1 route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel Dante Out 2	audio dante_out_2 route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel Dante Out 3	audio dante_out_3 route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel Dante Out 4	audio dante_out_4 route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel HDMI Out Left	audio hdmi_out_left route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel HDMI Out Right	audio hdmi_out_right route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel IP Out Left	audio ip_out_left route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel IP Out Right	audio ip_out_right route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel Line Out 1	audio line_out_1 route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel Line Out 2	audio line_out_2 route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel USB3 Record Left	audio usb3_record_left route set dante_in_1\x0D\x0A
Audio Route Dante In 1 Channel USB3 Record Right	audio usb3_record_right route set dante_in_1\x0D\x0A
Audio Route Dante In 2 Channel Dante Out 1	audio dante_out_1 route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel Dante Out 2	audio dante_out_2 route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel Dante Out 3	audio dante_out_3 route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel Dante Out 4	audio dante_out_4 route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel HDMI Out Left	audio hdmi_out_left route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel HDMI Out Right	audio hdmi_out_right route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel IP Out Left	audio ip_out_left route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel IP Out Right	audio ip_out_right route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel Line Out 1	audio line_out_1 route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel Line Out 2	audio line_out_2 route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel USB3 Record Left	audio usb3_record_left route set dante_in_2\x0D\x0A
Audio Route Dante In 2 Channel USB3 Record Right	audio usb3_record_right route set dante_in_2\x0D\x0A

Global Scripter Module
Communication Sheet

Audio Route Dante In 3 Channel Dante Out 1	audio dante_out_1 route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel Dante Out 2	audio dante_out_2 route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel Dante Out 3	audio dante_out_3 route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel Dante Out 4	audio dante_out_4 route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel HDMI Out Left	audio hdmi_out_left route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel HDMI Out Right	audio hdmi_out_right route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel IP Out Left	audio ip_out_left route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel IP Out Right	audio ip_out_right route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel Line Out 1	audio line_out_1 route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel Line Out 2	audio line_out_2 route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel USB3 Record Left	audio usb3_record_left route set dante_in_3\x0D\x0A
Audio Route Dante In 3 Channel USB3 Record Right	audio usb3_record_right route set dante_in_3\x0D\x0A
Audio Route Dante In 4 Channel Dante Out 1	audio dante_out_1 route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel Dante Out 2	audio dante_out_2 route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel Dante Out 3	audio dante_out_3 route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel Dante Out 4	audio dante_out_4 route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel HDMI Out Left	audio hdmi_out_left route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel HDMI Out Right	audio hdmi_out_right route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel IP Out Left	audio ip_out_left route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel IP Out Right	audio ip_out_right route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel Line Out 1	audio line_out_1 route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel Line Out 2	audio line_out_2 route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel USB3 Record Left	audio usb3_record_left route set dante_in_4\x0D\x0A
Audio Route Dante In 4 Channel USB3 Record Right	audio usb3_record_right route set dante_in_4\x0D\x0A
Audio Route HDMI In 1 Left Channel Dante Out 1	audio dante_out_1 route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel Dante Out 2	audio dante_out_2 route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel Dante Out 3	audio dante_out_3 route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel Dante Out 4	audio dante_out_4 route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel HDMI Out Left	audio hdmi_out_left route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel HDMI Out Right	audio hdmi_out_right route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel IP Out Left	audio ip_out_left route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel IP Out Right	audio ip_out_right route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel Line Out 1	audio line_out_1 route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel Line Out 2	audio line_out_2 route set hdmi_in_1_left\x0D\x0A
Audio Route HDMI In 1 Left Channel USB3 Record Left	audio usb3_record_left route set hdmi_in_1_left\x0D\x0A

Global Scripter Module
Communication Sheet

Audio Route HDMI In 1 Left Channel USB3 Record Right	audio usb3_record_right route set hdm_i_n_1_left\x0D\x0A
Audio Route HDMI In 1 Right Channel Dante Out 1	audio dante_out_1 route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel Dante Out 2	audio dante_out_2 route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel Dante Out 3	audio dante_out_3 route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel Dante Out 4	audio dante_out_4 route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel HDMI Out Left	audio hdm_i_out_left route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel HDMI Out Right	audio hdm_i_out_right route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel IP Out Left	audio ip_out_left route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel IP Out Right	audio ip_out_right route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel Line Out 1	audio line_out_1 route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel Line Out 2	audio line_out_2 route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel USB3 Record Left	audio usb3_record_left route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 1 Right Channel USB3 Record Right	audio usb3_record_right route set hdm_i_n_1_right\x0D\x0A
Audio Route HDMI In 2 Left Channel Dante Out 1	audio dante_out_1 route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel Dante Out 2	audio dante_out_2 route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel Dante Out 3	audio dante_out_3 route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel Dante Out 4	audio dante_out_4 route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel HDMI Out Left	audio hdm_i_out_left route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel HDMI Out Right	audio hdm_i_out_right route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel IP Out Left	audio ip_out_left route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel IP Out Right	audio ip_out_right route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel Line Out 1	audio line_out_1 route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel Line Out 2	audio line_out_2 route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel USB3 Record Left	audio usb3_record_left route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Left Channel USB3 Record Right	audio usb3_record_right route set hdm_i_n_2_left\x0D\x0A
Audio Route HDMI In 2 Right Channel Dante Out 1	audio dante_out_1 route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel Dante Out 2	audio dante_out_2 route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel Dante Out 3	audio dante_out_3 route set hdm_i_n_2_right\x0D\x0A

Audio Route HDMI In 2 Right Channel Dante Out 4	audio dante_out_4 route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel HDMI Out Left	audio hdm_i_out_left route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel HDMI Out Right	audio hdm_i_out_right route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel IP Out Left	audio ip_out_left route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel IP Out Right	audio ip_out_right route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel Line Out 1	audio line_out_1 route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel Line Out 2	audio line_out_2 route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel USB3 Record Left	audio usb3_record_left route set hdm_i_n_2_right\x0D\x0A
Audio Route HDMI In 2 Right Channel USB3 Record Right	audio usb3_record_right route set hdm_i_n_2_right\x0D\x0A
Audio Route Line In 1 Channel Dante Out 1	audio dante_out_1 route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel Dante Out 2	audio dante_out_2 route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel Dante Out 3	audio dante_out_3 route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel Dante Out 4	audio dante_out_4 route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel HDMI Out Left	audio hdm_i_out_left route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel HDMI Out Right	audio hdm_i_out_right route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel IP Out Left	audio ip_out_left route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel IP Out Right	audio ip_out_right route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel Line Out 1	audio line_out_1 route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel Line Out 2	audio line_out_2 route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel USB3 Record Left	audio usb3_record_left route set line_in_1\x0D\x0A
Audio Route Line In 1 Channel USB3 Record Right	audio usb3_record_right route set line_in_1\x0D\x0A
Audio Route Line In 2 Channel Dante Out 1	audio dante_out_1 route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel Dante Out 2	audio dante_out_2 route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel Dante Out 3	audio dante_out_3 route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel Dante Out 4	audio dante_out_4 route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel HDMI Out Left	audio hdm_i_out_left route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel HDMI Out Right	audio hdm_i_out_right route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel IP Out Left	audio ip_out_left route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel IP Out Right	audio ip_out_right route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel Line Out 1	audio line_out_1 route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel Line Out 2	audio line_out_2 route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel USB3 Record Left	audio usb3_record_left route set line_in_2\x0D\x0A
Audio Route Line In 2 Channel USB3 Record Right	audio usb3_record_right route set line_in_2\x0D\x0A
Audio Route USB3 Playback Left Channel Dante Out 1	audio dante_out_1 route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel Dante Out 2	audio dante_out_2 route set usb3_playback_left\x0D\x0A

Audio Route USB3 Playback Left Channel Dante Out 3	audio dante_out_3 route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel Dante Out 4	audio dante_out_4 route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel HDMI Out Left	audio hdmi_out_left route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel HDMI Out Right	audio hdmi_out_right route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel IP Out Left	audio ip_out_left route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel IP Out Right	audio ip_out_right route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel Line Out 1	audio line_out_1 route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel Line Out 2	audio line_out_2 route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel USB3 Record Left	audio usb3_record_left route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Left Channel USB3 Record Right	audio usb3_record_right route set usb3_playback_left\x0D\x0A
Audio Route USB3 Playback Right Channel Dante Out 1	audio dante_out_1 route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel Dante Out 2	audio dante_out_2 route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel Dante Out 3	audio dante_out_3 route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel Dante Out 4	audio dante_out_4 route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel HDMI Out Left	audio hdmi_out_left route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel HDMI Out Right	audio hdmi_out_right route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel IP Out Left	audio ip_out_left route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel IP Out Right	audio ip_out_right route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel Line Out 1	audio line_out_1 route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel Line Out 2	audio line_out_2 route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel USB3 Record Left	audio usb3_record_left route set usb3_playback_right\x0D\x0A
Audio Route USB3 Playback Right Channel USB3 Record Right	audio usb3_record_right route set usb3_playback_right\x0D\x0A
Audio Volume 20 Channel Dante In 1	audio dante_in_1 volume set 20\x0D\x0A
Audio Volume 20 Channel Dante In 2	audio dante_in_2 volume set 20\x0D\x0A
Audio Volume 20 Channel Dante In 3	audio dante_in_3 volume set 20\x0D\x0A
Audio Volume 20 Channel Dante In 4	audio dante_in_4 volume set 20\x0D\x0A
Audio Volume 20 Channel Dante Out 1	audio dante_out_1 volume set 20\x0D\x0A

**Global Scriptor Module
Communication Sheet**

Audio Volume 20 Channel Dante Out 2	audio dante_out_2 volume set 20\x0D\x0A
Audio Volume 20 Channel Dante Out 3	audio dante_out_3 volume set 20\x0D\x0A
Audio Volume 20 Channel Dante Out 4	audio dante_out_4 volume set 20\x0D\x0A
Audio Volume 20 Channel HDMI In 1 Right	audio hdmi_in_1_right volume set 20\x0D\x0A
Audio Volume 20 Channel HDMI In 2 Left	audio hdmi_in_2_left volume set 20\x0D\x0A
Audio Volume 20 Channel HDMI In 2 Right	audio hdmi_in_2_right volume set 20\x0D\x0A
Audio Volume 20 Channel HDMI Out Left	audio hdmi_out_left volume set 20\x0D\x0A
Audio Volume 20 Channel HDMI Out Right	audio hdmi_out_right volume set 20\x0D\x0A
Audio Volume 20 Channel IP Out Left	audio ip_out_left volume set 20\x0D\x0A
Audio Volume 20 Channel IP Out Right	audio ip_out_right volume set 20\x0D\x0A
Audio Volume 20 Channel Line In 1	audio line_in_1 volume set 20\x0D\x0A
Audio Volume 20 Channel Line In 2	audio line_in_2 volume set 20\x0D\x0A
Audio Volume 20 Channel Line Out 1	audio line_out_1 volume set 20\x0D\x0A
Audio Volume 20 Channel Line Out 2	audio line_out_2 volume set 20\x0D\x0A
Audio Volume 20 Channel Master	audio master volume set 20\x0D\x0A
Audio Volume 20 Channel USB3 Playback Left	audio usb3_playback_left volume set 20\x0D\x0A
Audio Volume 20 Channel USB3 Playback Right	audio usb3_playback_right volume set 20\x0D\x0A
Audio Volume 20 Channel USB3 Record Left	audio usb3_record_left volume set 20\x0D\x0A
Audio Volume 20 Channel USB3 Record Right	audio usb3_record_right volume set 20\x0D\x0A
Audio Volume -50 Channel Dante In 1	audio dante_in_1 volume set -50\x0D\x0A
Audio Volume -50 Channel Dante In 2	audio dante_in_2 volume set -50\x0D\x0A
Audio Volume -50 Channel Dante In 3	audio dante_in_3 volume set -50\x0D\x0A
Audio Volume -50 Channel Dante In 4	audio dante_in_4 volume set -50\x0D\x0A
Audio Volume -50 Channel Dante Out 1	audio dante_out_1 volume set -50\x0D\x0A
Audio Volume -50 Channel Dante Out 2	audio dante_out_2 volume set -50\x0D\x0A
Audio Volume -50 Channel Dante Out 3	audio dante_out_3 volume set -50\x0D\x0A
Audio Volume -50 Channel Dante Out 4	audio dante_out_4 volume set -50\x0D\x0A
Audio Volume -50 Channel HDMI In 1 Right	audio hdmi_in_1_right volume set -50\x0D\x0A
Audio Volume -50 Channel HDMI In 2 Left	audio hdmi_in_2_left volume set -50\x0D\x0A
Audio Volume -50 Channel HDMI In 2 Right	audio hdmi_in_2_right volume set -50\x0D\x0A
Audio Volume -50 Channel HDMI Out Left	audio hdmi_out_left volume set -50\x0D\x0A
Audio Volume -50 Channel HDMI Out Right	audio hdmi_out_right volume set -50\x0D\x0A
Audio Volume -50 Channel IP Out Left	audio ip_out_left volume set -50\x0D\x0A
Audio Volume -50 Channel IP Out Right	audio ip_out_right volume set -50\x0D\x0A
Audio Volume -50 Channel Line In 1	audio line_in_1 volume set -50\x0D\x0A
Audio Volume -50 Channel Line In 2	audio line_in_2 volume set -50\x0D\x0A
Audio Volume -50 Channel Line Out 1	audio line_out_1 volume set -50\x0D\x0A
Audio Volume -50 Channel Line Out 2	audio line_out_2 volume set -50\x0D\x0A
Audio Volume -50 Channel Master	audio master volume set -50\x0D\x0A
Audio Volume -50 Channel USB3 Playback Left	audio usb3_playback_left volume set -50\x0D\x0A
Audio Volume -50 Channel USB3 Playback Right	audio usb3_playback_right volume set -50\x0D\x0A
Audio Volume -50 Channel USB3 Record Left	audio usb3_record_left volume set -50\x0D\x0A
Audio Volume -50 Channel USB3 Record Right	audio usb3_record_right volume set -50\x0D\x0A
Camera Standby Off Camera 1	camera 1 standby off\x0D\x0A

Global Scriptor Module Communication Sheet

Camera Standby Off Camera 2	camera 2 standby off\x0D\x0A
Camera Standby On Camera 1	camera 1 standby on\x0D\x0A
Camera Standby On Camera 2	camera 2 standby on\x0D\x0A
Focus Far Camera 1 Focus Speed 1	camera 1 focus far 1\x0D\x0A
Focus Far Camera 1 Focus Speed 8	camera 1 focus far 8\x0D\x0A
Focus Far Camera 2 Focus Speed 1	camera 2 focus far 1\x0D\x0A
Focus Far Camera 2 Focus Speed 8	camera 2 focus far 8\x0D\x0A
Focus Mode Auto Camera 1	camera 1 focus mode auto\x0D\x0A
Focus Mode Auto Camera 2	camera 2 focus mode auto\x0D\x0A
Focus Mode Manual Camera 1	camera 1 focus mode manual\x0D\x0A
Focus Mode Manual Camera 2	camera 2 focus mode manual\x0D\x0A
Focus Near Camera 1 Focus Speed 1	camera 1 focus near 1\x0D\x0A
Focus Near Camera 1 Focus Speed 8	camera 1 focus near 8\x0D\x0A
Focus Near Camera 2 Focus Speed 1	camera 2 focus near 1\x0D\x0A
Focus Near Camera 2 Focus Speed 8	camera 2 focus near 8\x0D\x0A
Focus Stop Camera 1 Focus Speed 1	camera 1 focus stop\x0D\x0A
Focus Stop Camera 1 Focus Speed 8	camera 1 focus stop\x0D\x0A
Focus Stop Camera 2 Focus Speed 1	camera 2 focus stop\x0D\x0A
Focus Stop Camera 2 Focus Speed 8	camera 2 focus stop\x0D\x0A
Home None Camera 1	camera 1 home\x0D\x0A
Home None Camera 2	camera 2 home\x0D\x0A
Input 1	video program source set input1\x0D\x0A
Input 2	video program source set input2\x0D\x0A
IP Streaming Off	streaming ip enable off\x0D\x0A
IP Streaming On	streaming ip enable on\x0D\x0A
Pan Left Camera 1 Pan Speed 1	camera 1 pan left 1\x0D\x0A
Pan Left Camera 1 Pan Speed 24	camera 1 pan left 24\x0D\x0A
Pan Left Camera 2 Pan Speed 1	camera 2 pan left 1\x0D\x0A
Pan Left Camera 2 Pan Speed 24	camera 2 pan left 24\x0D\x0A
Pan Right Camera 1 Pan Speed 1	camera 1 pan right 1\x0D\x0A
Pan Right Camera 1 Pan Speed 24	camera 1 pan right 24\x0D\x0A
Pan Right Camera 2 Pan Speed 1	camera 2 pan right 1\x0D\x0A
Pan Right Camera 2 Pan Speed 24	camera 2 pan right 24\x0D\x0A
Pan Stop Camera 1 Pan Speed 1	camera 1 pan stop\x0D\x0A
Pan Stop Camera 1 Pan Speed 24	camera 1 pan stop\x0D\x0A
Pan Stop Camera 2 Pan Speed 1	camera 2 pan stop\x0D\x0A
Pan Stop Camera 2 Pan Speed 24	camera 2 pan stop\x0D\x0A
PIP Layout Left Right	video program pip layout left_right\x0D\x0A
PIP Layout Lower Left	video program pip layout lower_left\x0D\x0A
PIP Layout Lower Right	video program pip layout lower_right\x0D\x0A
PIP Layout Top Bottom	video program pip layout top_bottom\x0D\x0A
PIP Layout Upper Left	video program pip layout upper_left\x0D\x0A
PIP Layout Upper Right	video program pip layout upper_right\x0D\x0A
PIP Mode Off	video program pip off\x0D\x0A

Global Scriptor Module
Communication Sheet

PIP Mode On	video program pip on\x0D\x0A
PIP Mode Toggle	video program pip toggle\x0D\x0A
Power Off	system standby on\x0D\x0A
Power On	system standby off\x0D\x0A
Preset Recall 1 Camera 1	camera 1 preset recall 1\x0D\x0A
Preset Recall 1 Camera 2	camera 2 preset recall 1\x0D\x0A
Preset Recall 16 Camera 1	camera 1 preset recall 16\x0D\x0A
Preset Recall 16 Camera 2	camera 2 preset recall 16\x0D\x0A
Preset Save 1 Camera 1	camera 1 preset store 1\x0D\x0A
Preset Save 1 Camera 2	camera 2 preset store 1\x0D\x0A
Preset Save 16 Camera 1	camera 1 preset store 16\x0D\x0A
Preset Save 16 Camera 2	camera 2 preset store 16\x0D\x0A
Tilt Down Camera 1 Tilt Speed 1	camera 1 tilt down 1\x0D\x0A
Tilt Down Camera 1 Tilt Speed 20	camera 1 tilt down 20\x0D\x0A
Tilt Down Camera 2 Tilt Speed 1	camera 2 tilt down 1\x0D\x0A
Tilt Down Camera 2 Tilt Speed 20	camera 2 tilt down 20\x0D\x0A
Tilt Stop Camera 1 Tilt Speed 1	camera 1 tilt stop\x0D\x0A
Tilt Stop Camera 1 Tilt Speed 20	camera 1 tilt stop\x0D\x0A
Tilt Stop Camera 2 Tilt Speed 1	camera 2 tilt stop\x0D\x0A
Tilt Stop Camera 2 Tilt Speed 20	camera 2 tilt stop\x0D\x0A
Tilt Up Camera 1 Tilt Speed 1	camera 1 tilt up 1\x0D\x0A
Tilt Up Camera 1 Tilt Speed 20	camera 1 tilt up 20\x0D\x0A
Tilt Up Camera 2 Tilt Speed 1	camera 2 tilt up 1\x0D\x0A
Tilt Up Camera 2 Tilt Speed 20	camera 2 tilt up 20\x0D\x0A
Trigger Off Index 1 Block 0	trigger 1 off\x0D\x0A
Trigger Off Index 1 Block 999	trigger 1 off block 999\x0D\x0A
Trigger Off Index 10 Block 0	trigger 10 off\x0D\x0A
Trigger Off Index 10 Block 999	trigger 10 off block 999\x0D\x0A
Trigger On Index 1 Block 0	trigger 1 on\x0D\x0A
Trigger On Index 1 Block 999	trigger 1 on block 999\x0D\x0A
Trigger On Index 10 Block 0	trigger 10 on\x0D\x0A
Trigger On Index 10 Block 999	trigger 10 on block 999\x0D\x0A
Video Mute Off Channel Input 1	video input1 mute off\x0D\x0A
Video Mute Off Channel Input 2	video input2 mute off\x0D\x0A
Video Mute Off Channel Master	video master mute off\x0D\x0A
Video Mute On Channel Input 1	video input1 mute on\x0D\x0A
Video Mute On Channel Input 2	video input2 mute on\x0D\x0A
Video Mute On Channel Master	video master mute on\x0D\x0A
Video Type Camera Channel Input 1	video input1 type set camera\x0D\x0A
Video Type Camera Channel Input 2	video input2 type set camera\x0D\x0A
Video Type Video Channel Input 1	video input1 type set video\x0D\x0A
Video Type Video Channel Input 2	video input2 type set video\x0D\x0A
Zoom In Camera 1 Zoom Speed 1	camera 1 zoom in 1\x0D\x0A
Zoom In Camera 1 Zoom Speed 7	camera 1 zoom in 7\x0D\x0A

Global Scripter Module Communication Sheet

Zoom In Camera 2 Zoom Speed 1	camera 2 zoom in 1\x0D\x0A
Zoom In Camera 2 Zoom Speed 7	camera 2 zoom in 7\x0D\x0A
Zoom Out Camera 1 Zoom Speed 1	camera 1 zoom out 1\x0D\x0A
Zoom Out Camera 1 Zoom Speed 7	camera 1 zoom out 7\x0D\x0A
Zoom Out Camera 2 Zoom Speed 1	camera 2 zoom out 1\x0D\x0A
Zoom Out Camera 2 Zoom Speed 7	camera 2 zoom out 7\x0D\x0A
Zoom Stop Camera 1 Zoom Speed 1	camera 1 zoom stop\x0D\x0A
Zoom Stop Camera 1 Zoom Speed 7	camera 1 zoom stop\x0D\x0A
Zoom Stop Camera 2 Zoom Speed 1	camera 2 zoom stop\x0D\x0A
Zoom Stop Camera 2 Zoom Speed 7	camera 2 zoom stop\x0D\x0A

Appendix B. Update Commands

Audio Crosspoint Gain Output Dante Out 1 Input Dante In 1	audio dante_out_1 crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input Dante In 2	audio dante_out_1 crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input Dante In 3	audio dante_out_1 crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input Dante In 4	audio dante_out_1 crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input HDMI In 1 Left	audio dante_out_1 crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input HDMI In 1 Right	audio dante_out_1 crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input HDMI In 2 Left	audio dante_out_1 crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input HDMI In 2 Right	audio dante_out_1 crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input Line In 1	audio dante_out_1 crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input Line In 2	audio dante_out_1 crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input USB3 Playback Left	audio dante_out_1 crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 1 Input USB3 Playback Right	audio dante_out_1 crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input Dante In 1	audio dante_out_2 crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input Dante In 2	audio dante_out_2 crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input Dante In 3	audio dante_out_2 crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input Dante In 4	audio dante_out_2 crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input HDMI In 1 Left	audio dante_out_2 crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input HDMI In 1 Right	audio dante_out_2 crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input HDMI In 2 Left	audio dante_out_2 crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input HDMI In 2 Right	audio dante_out_2 crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input Line In 1	audio dante_out_2 crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input Line In 2	audio dante_out_2 crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input	audio dante_out_2 crosspoint-gain

Global Scriptor Module
Communication Sheet

USB3 Playback Left	usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 2 Input USB3 Playback Right	audio dante_out_2 crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input Dante In 1	audio dante_out_3 crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input Dante In 2	audio dante_out_3 crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input Dante In 3	audio dante_out_3 crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input Dante In 4	audio dante_out_3 crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input HDMI In 1 Left	audio dante_out_3 crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input HDMI In 1 Right	audio dante_out_3 crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input HDMI In 2 Left	audio dante_out_3 crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input HDMI In 2 Right	audio dante_out_3 crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input Line In 1	audio dante_out_3 crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input Line In 2	audio dante_out_3 crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input USB3 Playback Left	audio dante_out_3 crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 3 Input USB3 Playback Right	audio dante_out_3 crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input Dante In 1	audio dante_out_4 crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input Dante In 2	audio dante_out_4 crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input Dante In 3	audio dante_out_4 crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input Dante In 4	audio dante_out_4 crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input HDMI In 1 Left	audio dante_out_4 crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input HDMI In 1 Right	audio dante_out_4 crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input HDMI In 2 Left	audio dante_out_4 crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input HDMI In 2 Right	audio dante_out_4 crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input Line In 1	audio dante_out_4 crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input Line In 2	audio dante_out_4 crosspoint-gain line_in_2 get\x0D\x0A

Audio Crosspoint Gain Output Dante Out 4 Input USB3 Playback Left	audio dante_out_4 crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output Dante Out 4 Input USB3 Playback Right	audio dante_out_4 crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input Dante In 1	audio hdmi_out_left crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input Dante In 2	audio hdmi_out_left crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input Dante In 3	audio hdmi_out_left crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input Dante In 4	audio hdmi_out_left crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input HDMI In 1 Left	audio hdmi_out_left crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input HDMI In 1 Right	audio hdmi_out_left crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input HDMI In 2 Left	audio hdmi_out_left crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input HDMI In 2 Right	audio hdmi_out_left crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input Line In 1	audio hdmi_out_left crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input Line In 2	audio hdmi_out_left crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input USB3 Playback Left	audio hdmi_out_left crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Left Input USB3 Playback Right	audio hdmi_out_left crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input Dante In 1	audio hdmi_out_right crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input Dante In 2	audio hdmi_out_right crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input Dante In 3	audio hdmi_out_right crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input Dante In 4	audio hdmi_out_right crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input HDMI In 1 Left	audio hdmi_out_right crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input HDMI In 1 Right	audio hdmi_out_right crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input HDMI In 2 Left	audio hdmi_out_right crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input HDMI In 2 Right	audio hdmi_out_right crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input Line In 1	audio hdmi_out_right crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input	audio hdmi_out_right crosspoint-gain line_in_2

Global Scripter Module
Communication Sheet

Line In 2	get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input USB3 Playback Left	audio hdmi_out_right crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output HDMI Out Right Input USB3 Playback Right	audio hdmi_out_right crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input Dante In 1	audio ip_out_left crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input Dante In 2	audio ip_out_left crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input Dante In 3	audio ip_out_left crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input Dante In 4	audio ip_out_left crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input HDMI In 1 Left	audio ip_out_left crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input HDMI In 1 Right	audio ip_out_left crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input HDMI In 2 Left	audio ip_out_left crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input HDMI In 2 Right	audio ip_out_left crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input Line In 1	audio ip_out_left crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input Line In 2	audio ip_out_left crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input USB3 Playback Left	audio ip_out_left crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output IP Out Left Input USB3 Playback Right	audio ip_out_left crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input Dante In 1	audio ip_out_right crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input Dante In 2	audio ip_out_right crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input Dante In 3	audio ip_out_right crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input Dante In 4	audio ip_out_right crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input HDMI In 1 Left	audio ip_out_right crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input HDMI In 1 Right	audio ip_out_right crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input HDMI In 2 Left	audio ip_out_right crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input HDMI In 2 Right	audio ip_out_right crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input Line In 1	audio ip_out_right crosspoint-gain line_in_1 get\x0D\x0A

Audio Crosspoint Gain Output IP Out Right Input Line In 2	audio ip_out_right crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input USB3 Playback Left	audio ip_out_right crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output IP Out Right Input USB3 Playback Right	audio ip_out_right crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input Dante In 1	audio line_out_1 crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input Dante In 2	audio line_out_1 crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input Dante In 3	audio line_out_1 crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input Dante In 4	audio line_out_1 crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input HDMI In 1 Left	audio line_out_1 crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input HDMI In 1 Right	audio line_out_1 crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input HDMI In 2 Left	audio line_out_1 crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input HDMI In 2 Right	audio line_out_1 crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input Line In 1	audio line_out_1 crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input Line In 2	audio line_out_1 crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input USB3 Playback Left	audio line_out_1 crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output Line Out 1 Input USB3 Playback Right	audio line_out_1 crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input Dante In 1	audio line_out_2 crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input Dante In 2	audio line_out_2 crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input Dante In 3	audio line_out_2 crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input Dante In 4	audio line_out_2 crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input HDMI In 1 Left	audio line_out_2 crosspoint-gain hdmi_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input HDMI In 1 Right	audio line_out_2 crosspoint-gain hdmi_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input HDMI In 2 Left	audio line_out_2 crosspoint-gain hdmi_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input HDMI In 2 Right	audio line_out_2 crosspoint-gain hdmi_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input Line	audio line_out_2 crosspoint-gain line_in_1

Global Scriptor Module
Communication Sheet

Revision: 12/1/2022

In 1	get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input Line In 2	audio_line_out_2 crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input USB3 Playback Left	audio_line_out_2 crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output Line Out 2 Input USB3 Playback Right	audio_line_out_2 crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input Dante In 1	audio usb3_record_left crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input Dante In 2	audio usb3_record_left crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input Dante In 3	audio usb3_record_left crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input Dante In 4	audio usb3_record_left crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input HDMI In 1 Left	audio usb3_record_left crosspoint-gain hdm_i_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input HDMI In 1 Right	audio usb3_record_left crosspoint-gain hdm_i_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input HDMI In 2 Left	audio usb3_record_left crosspoint-gain hdm_i_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input HDMI In 2 Right	audio usb3_record_left crosspoint-gain hdm_i_in_2_right get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input Line In 1	audio usb3_record_left crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input Line In 2	audio usb3_record_left crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input USB3 Playback Left	audio usb3_record_left crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Left Input USB3 Playback Right	audio usb3_record_left crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input Dante In 1	audio usb3_record_right crosspoint-gain dante_in_1 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input Dante In 2	audio usb3_record_right crosspoint-gain dante_in_2 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input Dante In 3	audio usb3_record_right crosspoint-gain dante_in_3 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input Dante In 4	audio usb3_record_right crosspoint-gain dante_in_4 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input HDMI In 1 Left	audio usb3_record_right crosspoint-gain hdm_i_in_1_left get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input HDMI In 1 Right	audio usb3_record_right crosspoint-gain hdm_i_in_1_right get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input HDMI In 2 Left	audio usb3_record_right crosspoint-gain hdm_i_in_2_left get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input HDMI In 2 Right	audio usb3_record_right crosspoint-gain hdm_i_in_2_right get\x0D\x0A

**Global Scriptor Module
Communication Sheet**

Audio Crosspoint Gain Output USB3 Record Right Input Line In 1	audio usb3_record_right crosspoint-gain line_in_1 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input Line In 2	audio usb3_record_right crosspoint-gain line_in_2 get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input USB3 Playback Left	audio usb3_record_right crosspoint-gain usb3_playback_left get\x0D\x0A
Audio Crosspoint Gain Output USB3 Record Right Input USB3 Playback Right	audio usb3_record_right crosspoint-gain usb3_playback_right get\x0D\x0A
Audio Mute Channel Dante In 1	audio dante_in_1 mute get\x0D\x0A
Audio Mute Channel Dante In 2	audio dante_in_2 mute get\x0D\x0A
Audio Mute Channel Dante In 3	audio dante_in_3 mute get\x0D\x0A
Audio Mute Channel Dante In 4	audio dante_in_4 mute get\x0D\x0A
Audio Mute Channel Dante Out 1	audio dante_out_1 mute get\x0D\x0A
Audio Mute Channel Dante Out 2	audio dante_out_2 mute get\x0D\x0A
Audio Mute Channel Dante Out 3	audio dante_out_3 mute get\x0D\x0A
Audio Mute Channel Dante Out 4	audio dante_out_4 mute get\x0D\x0A
Audio Mute Channel HDMI In 1 Right	audio hdmi_in_1_right mute get\x0D\x0A
Audio Mute Channel HDMI In 2 Left	audio hdmi_in_2_left mute get\x0D\x0A
Audio Mute Channel HDMI In 2 Right	audio hdmi_in_2_right mute get\x0D\x0A
Audio Mute Channel HDMI Out Left	audio hdmi_out_left mute get\x0D\x0A
Audio Mute Channel HDMI Out Right	audio hdmi_out_right mute get\x0D\x0A
Audio Mute Channel IP Out Left	audio ip_out_left mute get\x0D\x0A
Audio Mute Channel IP Out Right	audio ip_out_right mute get\x0D\x0A
Audio Mute Channel Line In 1	audio line_in_1 mute get\x0D\x0A
Audio Mute Channel Line In 2	audio line_in_2 mute get\x0D\x0A
Audio Mute Channel Line Out 1	audio line_out_1 mute get\x0D\x0A
Audio Mute Channel Line Out 2	audio line_out_2 mute get\x0D\x0A
Audio Mute Channel Master	audio master mute get\x0D\x0A
Audio Mute Channel USB3 Playback Left	audio usb3_playback_left mute get\x0D\x0A
Audio Mute Channel USB3 Playback Right	audio usb3_playback_right mute get\x0D\x0A
Audio Mute Channel USB3 Record Left	audio usb3_record_left mute get\x0D\x0A
Audio Mute Channel USB3 Record Right	audio usb3_record_right mute get\x0D\x0A
Audio Route Channel Dante Out 1	audio dante_out_1 route get\x0D\x0A
Audio Route Channel Dante Out 2	audio dante_out_2 route get\x0D\x0A
Audio Route Channel Dante Out 3	audio dante_out_3 route get\x0D\x0A
Audio Route Channel Dante Out 4	audio dante_out_4 route get\x0D\x0A
Audio Route Channel HDMI Out Left	audio hdmi_out_left route get\x0D\x0A
Audio Route Channel HDMI Out Right	audio hdmi_out_right route get\x0D\x0A
Audio Route Channel IP Out Left	audio ip_out_left route get\x0D\x0A
Audio Route Channel IP Out Right	audio ip_out_right route get\x0D\x0A
Audio Route Channel Line Out 1	audio line_out_1 route get\x0D\x0A
Audio Route Channel Line Out 2	audio line_out_2 route get\x0D\x0A
Audio Route Channel USB3 Record Left	audio usb3_record_left route get\x0D\x0A
Audio Route Channel USB3 Record Right	audio usb3_record_right route get\x0D\x0A
Audio Volume Channel Dante In 1	audio dante_in_1 volume get\x0D\x0A

**Global Scriptor Module
Communication Sheet**

Audio Volume Channel Dante In 2	audio dante_in_2 volume get\x0D\x0A
Audio Volume Channel Dante In 3	audio dante_in_3 volume get\x0D\x0A
Audio Volume Channel Dante In 4	audio dante_in_4 volume get\x0D\x0A
Audio Volume Channel Dante Out 1	audio dante_out_1 volume get\x0D\x0A
Audio Volume Channel Dante Out 2	audio dante_out_2 volume get\x0D\x0A
Audio Volume Channel Dante Out 3	audio dante_out_3 volume get\x0D\x0A
Audio Volume Channel Dante Out 4	audio dante_out_4 volume get\x0D\x0A
Audio Volume Channel HDMI In 1 Right	audio hdmi_in_1_right volume get\x0D\x0A
Audio Volume Channel HDMI In 2 Left	audio hdmi_in_2_left volume get\x0D\x0A
Audio Volume Channel HDMI In 2 Right	audio hdmi_in_2_right volume get\x0D\x0A
Audio Volume Channel HDMI Out Left	audio hdmi_out_left volume get\x0D\x0A
Audio Volume Channel HDMI Out Right	audio hdmi_out_right volume get\x0D\x0A
Audio Volume Channel IP Out Left	audio ip_out_left volume get\x0D\x0A
Audio Volume Channel IP Out Right	audio ip_out_right volume get\x0D\x0A
Audio Volume Channel Line In 1	audio line_in_1 volume get\x0D\x0A
Audio Volume Channel Line In 2	audio line_in_2 volume get\x0D\x0A
Audio Volume Channel Line Out 1	audio line_out_1 volume get\x0D\x0A
Audio Volume Channel Line Out 2	audio line_out_2 volume get\x0D\x0A
Audio Volume Channel Master	audio master volume get\x0D\x0A
Audio Volume Channel USB3 Playback Left	audio usb3_playback_left volume get\x0D\x0A
Audio Volume Channel USB3 Playback Right	audio usb3_playback_right volume get\x0D\x0A
Audio Volume Channel USB3 Record Left	audio usb3_record_left volume get\x0D\x0A
Audio Volume Channel USB3 Record Right	audio usb3_record_right volume get\x0D\x0A
Camera Standby Camera 1	camera 1 standby get\x0D\x0A
Camera Standby Camera 2	camera 2 standby get\x0D\x0A
Focus Mode Camera 1	camera 1 focus mode get\x0D\x0A
Focus Mode Camera 2	camera 2 focus mode get\x0D\x0A
Input	video program source get\x0D\x0A
IP Streaming	streaming ip enable get\x0D\x0A
Power	system standby get\x0D\x0A
Streaming Setting Status Type IP Custom Frame Rate	streaming settings get\x0D\x0A
Streaming Setting Status Type IP Custom Resolution	streaming settings get\x0D\x0A
Streaming Setting Status Type IP Enabled	streaming settings get\x0D\x0A
Streaming Setting Status Type IP MTU	streaming settings get\x0D\x0A
Streaming Setting Status Type IP Port	streaming settings get\x0D\x0A
Streaming Setting Status Type IP Preset Quality	streaming settings get\x0D\x0A
Streaming Setting Status Type IP Preset Resolution	streaming settings get\x0D\x0A
Streaming Setting Status Type IP Protocol	streaming settings get\x0D\x0A
Streaming Setting Status Type IP URL	streaming settings get\x0D\x0A
Streaming Setting Status Type IP Video Mode	streaming settings get\x0D\x0A
Streaming Setting Status Type USB Active	streaming settings get\x0D\x0A
Streaming Setting Status Type USB Device	streaming settings get\x0D\x0A
Streaming Setting Status Type USB Frame Rate	streaming settings get\x0D\x0A
Streaming Setting Status Type USB Resolution	streaming settings get\x0D\x0A

Global Scriptor Module Communication Sheet

Streaming Setting Status Type USB Version	streaming settings get\x0D\x0A
Video Mute Channel Input 1	video input1 mute get\x0D\x0A
Video Mute Channel Input 2	video input2 mute get\x0D\x0A
Video Mute Channel Master	video master mute get\x0D\x0A
Video Type Channel Input 1	video input1 type get\x0D\x0A
Video Type Channel Input 2	video input2 type get\x0D\x0A