

Bit 2 **GPIOCEN**: IO port C clock enable

Set and cleared by software.

0: IO port C clock disabled

1: IO port C clock enabled

Bit 1 **GPIOBEN**: IO port B clock enable

Set and cleared by software.

0: IO port B clock disabled

1: IO port B clock enabled

Bit 0 **GPIOAEN**: IO port A clock enable

Set and cleared by software.

0: IO port A clock disabled

1: IO port A clock enabled

9.8.18 RCC AHB3 peripheral clock enable register(RCC_AHB3ENR)

Address offset: 0x050

Reset value: 0x0000 0000

Access: no wait state, word, half-word and byte access

Note: *When the peripheral clock is not active, the peripheral registers read or write access is not supported.*

31	30	29	28	27	26	25	24	23	22	21	20	19	18	17	16
Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.	Res.
15	14	13	12	11	10	9	8	7	6	5	4	3	2	1	0
Res.	Res.	Res.	Res.	Res.	Res.	Res.	OCTOSPI1EN	Res.	Res.	Res.	Res.	Res.	Res.	Res.	FMCEN
							rw								rw

Bits 31:9 Reserved, must be kept at reset value.

Bit 8 **OCTOSPI1EN**: OCTOSPI1 memory interface clock enable

Set and cleared by software.

0: OCTOSPI1 clock disabled

1: OCTOSPI1 clock enabled

Bits 7:1 Reserved, must be kept at reset value.

Bit 0 **FMCEN**: Flexible memory controller clock enable

Set and cleared by software.

0: FMC clock disabled

1: FMC clock enabled