

Binary RIS ■■■■■

R94 → R156 ■■■■

■ Patch Antenna Surrogate-in-the-loop Transition

■■■■■■■■

■■■■■2026-05-03

Branch: ricky/modernize

■■■156 rounds, 200+ commits

Author: Ricky × Claude (Opus 4.7, /loop session)

Binary RIS ■■■■■■R94 → R156 ■■■■

■■■■■2026-05-03

■■■R94 (worst-case loss baseline) → R156 (multi-freq broadband + visualization)

patch antenna surrogate-in-the-loop transition

Branch **ricky/modernize** 200+ commits

0. ■■■■

■ R94 ■■■■ RIS pattern ■■■■max-max loss ■ metric■■■■■■■■■■

■■■■■■■■ deployment methodology■

- **Loss** ■■■ worst-case + ripple + mean(side) ■■■■■■■■■■■■■■■■■■■■■■
- **Recipe selector** ■ 4D ■■ `select_1bit_recipe(n, inc, freq, width)` ■ grid search ■■■
- **Joint early-stop** ■ trajectory ■■■■ worst ■■■ flat-top OK ■■ snapshot
- **Surrogate-in-the-loop** ■■■■ + warm-start + noise ■■■■ transferable
- **Multi-freq broadband** ■ sum loss across freqs ■■■■ patch ■ BW spec

■ pipeline ■ 4 ■ aperture (n=15/31/51/71) × ■ inc × ■ freq × ■ width ■

■■■■■■■■■■ surrogate weights ■ 20% Gaussian noise ■■■■ work■■

1.1 R57-R63 ■■■■■


```
metric report: worst suppression = +30.99 dB ↔ ██████ ██████: main beam ██████ binary ██████
████████ worst = -18.21 dB ↔ ██████
```

surrogate + HFSS ■■■■■■

→ R94 loss_{main} + sidelobe

2. ■■■■■■

R94 → R156: 3-phase development timeline



Key takeaways

Loss design

soft-min main vs soft-max side + ripple + mean(side)
framework-agnostic; transfers to surrogate AND broadband

Recipe selector

`select_1bit_recipe(n, inc, freq, width)`
decision tree from R119/R129/R131/R133/R135
validated envelope: $n \in [15, 31, 51, 71]$, $w \in [10, 30]^\circ$

Joint early-stop

max worst AMONG flat-top-valid trajectory snapshots
the critical safety net for surrogate-in-the-loop
survives 20% surrogate weight perturbation

Multi-freq broadband

loss summed across freqs: 10% BW clean PASS
joint > single-freq EVEN at design freq
32%+ BW needs aperture upgrade

Cumulative: 156 rounds, 200+ commits, branch risky/modernize. 1-bit RIS + 4-axis selector + joint early-stop + multi-freq BW = patch-transition-ready methodology.

Figure: Development timeline

3 ■ phase■

- 1. **Phase 1 (R94-R141)**■RIS playground methodology ■■■■■■■■ loss ■■■■
recipe selector■joint early-stop■deployment API
 - 2. **Phase 2 (R142-R149)**■Surrogate-in-the-loop ■■■■■■ 4 ■■■■■ R146
warm-start trick ■■
 - 3. **Phase 3 (R150-R156)**■Patch transition ■■ + multi-freq broadband ■■
- 156 ■ round■~25 ■■■■■■ milestone■■ timeline ■■■■■■

3. Architecture deployment pipeline




Figure: Pipeline architecture

■■■■ call flow ■■■ input config ■ binary pattern output
 ■5 ■ loss component ■■■■■ + ■■ round

3.1 ■■■■■ R150 unified

```

def optimize_ris_1bit( n, # aperture {15, 31, 51, 71} inc_deg, # incidence angle [0, 70]
  freq_hz, # operating freq [5.8e9, 60e9] width_deg, # main beam width [10, 30] n_restarts=5,
  gd_steps=1500, steering_center_deg=0, forward_fn=None, # default = analytical sim; can pass
  surrogate eval_fn=None, # default = analytical sim; truth for joint early-stop ): ... return {
  "recipe": dict(rw, lambda_mean, tier), "best": dict(worst, side_mean, ripple, flat_top),
  "n_flat_top": int, "seed_results": list, }
  
```

3.2 ■■■■ (selector → optimizer → joint early-stop)

INPUT ↓ select_1bit_recipe(n, inc, freq, width) → (rw, lambda_mean) recipe tier ↓
 forward_fn(params) ← analytical sim or surrogate ↓ loss = worst-case + ripple + mean(side) ↓
 Adam(lr=0.05) × N restarts × 1500 GD steps ↓ every 50 steps: joint early-stop (eval_fn truth) →
 track best worst AMONG flat-valid snapshots ↓ quantize → binary pattern (0 or π only) ↓ OUTPUT

4. Loss

4.1

```
loss = -(soft_min(main) - soft_max(side)) # R94: worst-case + rw * (soft_max(main) -
soft_min(main)) # R94: ripple penalty + lambda_m * side.mean() # R119: distribution
```

4.2

Component		
<code>soft_min(main) - soft_max(side)</code>	main side	main
<code>rw * (max(main) - min(main))</code>	main ripple	metric
<code>lambda_m * side.mean()</code>	sidelobe	sidelobe

soft_min / soft_max logsumexp $\beta=20$ GD
hard min/max

4.3 mean(side) R118

R118 4 sidelobe formulation

Loss	side_mean	side_l2	flat-top
A: baseline (R94)	-15.75	280	OK
B: + mean(side) $\lambda=0.3$	-23.12	178	OK
C: + L2 (side ²) $\lambda=0.05$	-19.12	220	OK
D: + ReLU(side - threshold) $\lambda=0.3$	-16.83	268	OK

B (mean) sidelobe distribution worst-case flat-top
L2 ReLU trade-off

4.4 recipe

Figure 1 — Recipe progression: R94 baseline -> R121 CHAMPION (n=51, 38GHz, inc=51deg, broadside)




Figure: Recipe progression

R94 → R119 → R121 ■■ recipe ■ worst / side_max / side_mean ■■ metric ■■

strict improvement■■■ metric ■■■■■■

- worst: +1.92 → +3.65 → +3.45 dB

- side_max: -4.51 → -6.60 → -6.05 dB

- side_mean: -15.75 → -23.70 → -30.84 dB■■■ **-15 dB**■

■■■ **trade-off**■■■ **design improvement**■

5. Recipe Selector ■4D ■■■■

`select_1bit_recipe(n, inc, freq, width)` ■■■■ grid search ■■■■

```
def select_1bit_recipe(n, inc_deg, freq_hz, width_deg): if width_deg > 30: raise ValueError("out
of envelope") if n not in (31, 51, 71): raise ValueError("not validated") # n=71 branch if n ==
71: if inc_deg == 0 and freq_hz >= 50e9: return rw=5.0, lambda=0.3 # R133 inc=0+60GHz rescue if
width_deg <= 15: return rw=5.0, lambda=0.5 # R141 n=71 narrow extrapolation return rw=7.0,
lambda=0.5 # n=71 wide # n=51 branch if width_deg > 12: # R135 boundary refinement if width_deg
<= 20: return rw=3.0, lambda=1.0 # R129 wide cap return rw=3.0, lambda=0.5 # R129 marginal if
inc_deg == 0 and freq_hz >= 20e9: if freq_hz >= 50e9: raise ValueError("use n=71") if freq_hz >=
35e9: return rw=2.0, lambda=0.5 # R131 38GHz rescue return rw=2.0, lambda=0.3 # R131 28GHz
rescue return rw=2.0, lambda=1.0 # R119 baseline
```

■■ branch ■■■■ round ■ grid search ■■■■

6. Validation Results

6.1 4 universal R123-R127, 2-bit champion




Figure: 4-axis universal validation

R121 CHAMPION (2-bit + $\lambda=1$) 4 PASS 1-bit baseline
R121 2-bit (4 phase levels) 1-bit $0/\pi$ hardware constraint
R128 methodology
deployable 1-bit §6.2 (R128/R130/R141)

6.2 1-bit R128/R130/R141, 2-bit

1-bit RIS validation across 3 axes -- POST R128 hardware-realistic results

Replacing R121 (2-bit) with R128 / R130 / R141 (1-bit, deployment-spec)



Figure: 1-bit validation across 3 axes

R128 ■■■■■■ 1-bit ■■■■

- (a) Width x Steering (R128) ■ narrow cap (10°) ■ steering ■ robust ■ wide cap broadside ■■
- (b) Inc x Freq grid (R130) ■ 13/16 PASS, ■■■■■■ inc=0 + mmWave ■ R131 ■■ rescue recipes
- (c) R141 deployment 6/6 PASS ■ selector + joint early-stop ■■■■■■

6.2 R141 deployment API 6/6 PASS

Config	Recipe	Worst	Flat	Verdict
n=51 inc=30° 28GHz w=10°	R119	+3.13	OK	PASS
n=51 inc=70° 60GHz w=10°	R119	+2.72	OK	PASS
n=51 inc=51° 38GHz w=15°	R129 wide	+1.74	OK	PASS ★ (was R134 fail)
n=51 inc=51° 38GHz w=20°	R129 wide	+1.72	OK	PASS
n=71 inc=30° 28GHz w=10°	n=71 extrap	+4.19	OK	PASS

n=71 inc=51° 38GHz w=10°	n=71 extrap	+5.46	OK	PASS ★
-----------------------------	-------------	-------	----	--------

6.3 ■■■ binary pattern + ■■■■■■■■ 2-bit■

(D) n=71, broadside (recipe over-shoots, flat-top) flat-top, +30 deg steering (boundary @±51, +30 deg steering (last universal point) n=51, broadside (R121 sweet spot)




Figure: Inference examples

4 ■■■ 4 ■■■ config ■■■■■■■■ 2-bit phase
quantization ■■■■■■■■ 1-bit hardware spec ■■■ 4 ■ phase ■
0/π/2/π/3π/2 ■■■■■■■■ 0 ■ π ■■■■■■■■ 1-bit deployable patterns
■■■ §6.2 fig9 + §6.4 selector tree ■■■ deployment pipeline ■■■
■■■■■■■■ valid ■■■
- ■ 3 ■■■ main ■■■■■■■■ case
- D ■■■ main ■■■■■■■■ -3 dB ■■■ case ■■■ max-max ■■■ loss ■■■■■

6.4 1-bit Recipe Selector ■■■■

1-bit Recipe Selector -- select_1bit_recipe(n, inc, freq, width)

decision tree distilled from R119, R129, R131, R133, R135




Figure: 1-bit selector decision tree

select_1bit_recipe(n, inc, freq, width) ■ 4D ■■■■■■■■■■

- ■■■■ zone■■■n=71 large aperture ■■
- ■■■■ zone■■■n=51/31 medium aperture ■■
- ■■■■ (recipe) ■■■■ (rw, λ_{mean}) + ■■ round (R119/R129/R131/R133)
- ERROR ■■■■ envelope ■■

6.5 Joint Early-Stop ■■ (R140 promotion)

Joint early-stop (R140) -- beats final-step AND avoids simple-ES flat-top crash

Trajectory selection: "best worst" alone sacrifices flat-top in 3/4 recipes; joint criterion preserves both




Figure: Joint early-stop comparison

R138-R140 trajectory selection ■■■■

- ■■■■ config ■ mean worst-case ■■ (final / simple-ES / joint-ES)
- ■■■■ strategy ■ flat-top compliance bar
- ■■ **callout**■
- Config A ■ joint-ES ■ flat-top ■ 4/5 ■■■ 5/5■IMPROVED■
- **Config B/C**■simple-ES ■ flat-top ■■ 1/5■CRASH ■■ cross-hatch■joint-ES ■■ 5/5
- **PROMOTION verdict**■4 configs ■ PASS■joint-ES ■■ R140 ■■

7. Phase 2 ■ Surrogate-in-the-loop

7.1 4 ■ negative ■■ turning point

Round	Approach	R ²	■■
R142	■■■ CNN, random data	≈ 0	stuck on mean
R143	Physics-aware, random data	-0.74	overfit
R144	Physics-aware, trajectory data	-3.21	dynamic range ■■■■■■
R145	Warm-start (■ indexing bug)	-0.97	bug ■■■■
R146	Warm-start (fixed)	1.000000	■■■■■ sufficient
R147	Surrogate-loop opt	delta=+0.02	methodology transfers

7.2 Warm-start ■■ insight (R146)

Analytical RIS sim ■■■■■■

```
af = pre_calAF * exp(j * pattern * pi) AF = |sum_k af| response = 20 * log10(AF / max(AF))
```

→ ■■■■ (W_{re} + i*W_{im}) * (cos(phase) + i*sin(phase)) ■■ magnitude + log■

■ sim.pre_calAF[0] ■■■■■■ surrogate weights → **untrained R² = 1.000000**,
mean abs err = 0.000002 dB■

7.3 Robustness ■■ (R148-R149)

■ Gaussian noise ■ surrogate weights■■ surrogate-loop ■ work ■■

Noise	R ²	mean worst	flat	Verdict
0%	1.0000	+0.68	5/5	PASS
5%	0.9778	+0.84	5/5	PASS
10%	0.9267	+0.87	5/5	PASS
20%	0.7845	+0.94	5/5	PASS

■■■■■ surrogate noise ■■ improves mean worst■■vs analytical truth +0.66■■■

■■■■■ noise ■ exploration regularization■ joint early-stop ■ truth eval

filter ■ noise-induced bad patterns■■■■ noise-helped ■■ local minima ■■ patterns■

R149 4 selector configs ALL PASS surrogate config beat analytical baseline




Figure: Surrogate robustness summary

- panel R148 noise 0/5/10/20% PASS mean worst noise regularization
- panel R149 4 configs surrogate beat truth +0.67 dB gain truth fail config D -1.32 → -0.66

8. Phase 3 ■ Multi-frequency broadband




Figure: Multi-frequency summary

8.1 R154 — Multi-freq joint > single-freq

■ ■ ■ n=51, inc=51°, w=10° broadside, freqs = 36/38/40 GHz (~10% rel BW) ■

Loss = sum over freqs of R119 recipe ■

■ ■ @38GHz ■ 36GHz ■ ■ mean +1.66 → +0.80, ■ ■ seed ■ ■ fail ■ ■

■ ■ joint ■ freq ■ mean ~+2.0+ ■ ■ ■ 38GHz ■ ■ ■ ■ (0.46 dB) ■

→ Joint optimization ■ regularization ■

8.2 R155 — Bandwidth limit

BW	per-freq means	flat	Verdict
~10%	+2.44, +2.47, +2.27	3/3, 3/3, 3/3	PASS
~32%	+1.36, +2.01, +2.18	1/3, 1/3, 2/3	FAIL flat-top
~53%	+1.51, +1.19, +1.64	1-2/3	FAIL

Patch BW ■ ■ ■ ■

Patch BW spec	RIS methodology	Action
5-10% (■ ■ patch)	clean PASS	■ ■ deploy
20-30% (broadband)	flat-top boundary	■ bigger n
30%+ (UWB)	architectural	■ ■ ■ ■ spec

9. visualization supporting figures

9.1 R120 — R94 vs R119

`outputs/r120_baseline_vs_winner.png` — main beam pattern + sidelobe histogram
mean(side) penalty distribution -8 dB

9.2 R122 — recipe pattern

`outputs/r122_three_recipes.png` — R94 / R119 / R121
binary pattern + far-field + sidelobe histogram distribution
-10~-40 dB -30~-40 dB tight cluster

9.3 R126 — +45° boundary probe

`outputs/report_fig3_45deg_boundary.png` — 5 recipe (R121/3-bit/rw=3/ λ =1.5/continuous)
+45° steering continuous phase +1.32 dB aperture limit
hardware quantization

9.4 R127 — Aperture scaling

`outputs/report_fig4_aperture_scaling.png` — n=31/51/71 broadside vs +45°
worst-case scaling bigger aperture break +45° boundary
+0.42 → +1.17 → +2.32 dB R141 recipe n=71 broadside flat-top
→ R134 selector n=71 extrapolation branch

10. ■■ validation ■■

■	■■	■■	■■ round
Loss design	worst+ripple+mean	✓	R94, R118-R121
Phase resolution	1-bit (0 or π only)	✓ deploy spec	R128 onwards
Aperture (n)	15, 31, 51, 71	✓	R127, R141, R153
Incidence	0°, 30°, 51°, 70°	✓ universal	R123
Frequency	5.8, 28, 38, 60 GHz	✓ universal	R124
Steering	-30° to +30°	✓ universal	R125
Steering $\pm 45^\circ$	physical limit	flagged	R126, R127
Width	10°, 12°, 15°, 18°, 20°, 30°	✓ with selector	R128, R135
Width 30°	recipe boundary	flagged	R129
Inc=0 + mmWave	needs rescue	✓ rescue found	R131, R133
Multi-target	T1+T2	~5 dB cost	R102, R113
Fab tolerance	up to 5% phase noise	✓	R136
Compute budget	800-1500 GD steps	✓	R137
Joint early-stop	worst AND flat-top	✓ promoted	R140
Held-out validation	6 configs	✓ 6/6 PASS	R141
Surrogate fit	warm-start $R^2=1.0$	✓	R146
Surrogate-loop	analytical equivalent	✓	R147
Surrogate noise	up to 20% weight noise	✓	R148, R149
Multi-freq broadband	up to 10% rel BW	✓	R154
Multi-freq BW limit	32%+ FAIL	flagged	R155

11. ■■■■■■■■■■ R94 ■■

■■■■■

Round	■■	■■
R94	worst-case loss + ripple penalty	Phase 1 ■■■■replaces max-max
R109	width axis sweep (5°-45°)	■■ width effects
R114-R115	phase resolution scaling (1/2/3-bit)	■■ 3-bit ■ cost-perf sweet
R118-R119	discover mean(side) penalty	■■■ distribution-level loss
R121	2-bit + $\lambda=1$ CHAMPION	side_mean -30.84 dB
R123-R125	universal validation across inc/freq/steering	4-axis robustness
R126-R127	aperture rescue for +45° boundary	physical limit characterization
R128	■■■■ → 1-bit only	deployment-realistic
R129	wide-cap re-grid (rw, λ)	width-aware recipe
R131-R133	inc=0+mmWave rescues + n=71	4D recipe map
R134-R135	codify selector + width=12 boundary fix	unified function
R136-R137	fab tolerance + compute budget validate	deployment-ready
R138-R140	joint early-stop (worst AND flat-top)	trajectory selection
R141	wrapped optimize_ris_1bit()	6/6 PASS deployment API
R142-R145	surrogate scaffolding 4 negative attempts	identify failure modes
R146	warm-start untrained $R^2=1.0$	architecture confirm sufficient
R147	surrogate-loop = analytical	methodology transfers
R148	surrogate noise robustness	20% noise OK
R149	cross-config surrogate-loop	universal across configs
R150	unified API (forward_fn argument)	analytical/surrogate same code

R151	patch infrastructure audit + bridge plan	path to actual patch
R152-R153	n=15 small-aperture extension	4× n range covered
R154	multi-freq joint optimization	broadband mode
R155	bandwidth limit characterization	explicit BW budget
R156	visualization + report	this document

12. ■■■■

■	■■	■■■■
Pipeline architecture	outputs/report_arch_pipeline.png	\$3
Development timeline	outputs/report_arch_timeline.png	\$2
Recipe progression	outputs/report_fig1_recipe_progression.png	\$4.1
4-axis universal validation (2-bit)	outputs/report_fig2_4axis_validation.png	\$6.1
+45° boundary probe	outputs/report_fig3_45deg_boundary.png	\$9.3
Aperture scaling	outputs/report_fig4_aperture_scaling.png	\$9.4
Inference examples (2-bit, ■■)	outputs/report_fig5_inference_examples.png	\$6.3
1-bit selector tree (NEW)	outputs/report_fig6_selector_tree.png	\$6.4
Joint early-stop comparison (NEW)	outputs/report_fig7_early_stop.png	\$6.5
Surrogate robustness (NEW)	outputs/report_fig8_surrogate_robustness.png	\$7.3
1-bit validation 3 axes (NEW)	outputs/report_fig9_1bit_validation.png	\$6.2
R94 vs R119 visual	outputs/r120_baseline_vs_winner.png	\$9.1
Three-recipe progression	outputs/r122_three_recipes.png	\$9.2
Multi-freq summary	outputs/r156_multifreq_summary.png	\$8

13. Phase 3 ■■■■

Phase 1-2 ■■■■ Phase 3 ■■ HFSS ■■■■ methodology ■ derisk ■

1. **R154-R155 ■■■ broadband adaptation** ■ multi-freq joint loss ■■■■
patch S-parameter ■■ spec
2. **R148-R149 ■■■ noise robustness** ■ HFSS surrogate ■■ $R^2 \sim 0.85-0.95$ ■ envelope ■
3. **R150 unified API ■ ready** ■■■■ HFSSNet/EnhancedHFSSUNet ■■

■■ patch deployment ■■■

- R157+: HFSS access window ■■ ~50-200 patterns ■ dataset

- R158+: ■ patch surrogate ■■ selector + joint early-stop

- R159+: HFSS validation + active learning loop

■■ methodology ■ RIS playground ■ derisk ■■ patch transition ■ data

engineering ■■ methodology ■■■

14. ■■■■■■■■■■

■■■■■■■■■ timeline■■■■■■■■■■■■■■■■■■■■■ [outputs/EXPERIMENT_LESSONS.md](#)

■cleanup agent ■ R156 ■■■■■~290 ■ / 10 ■■■■■■■■

■■■■■ by THEME■

- Loss design lessons
 - Optimizer & trajectory selection lessons (early stopping pitfalls)
 - Surrogate engineering lessons (cold-start ■■■■■■)
 - Hardware constraint lessons (1-bit pivot, fab tolerance margins)
 - Selector design lessons (when to grid-search vs extrapolate)
 - Multi-freq broadband lessons (joint > single, BW limit physics)
 - Failure-mode catalog (12 dead-ends ■■■■■■■■■■)
 - "If you only read 5 things" 5-bullet ■■
-

15. ■■

■ R57-R63 ■ max-max loss ■ metric ■ R156 ■ deployment API +
broadband ■ + surrogate noise robustness ■ 156 ■ round ■
■ 4 ■ surrogate-noise robust ■ broadband-aware ■
1-bit RIS ■

■ ■ deliverables ■

- `optimize_ris_1bit()` API
- `select_1bit_recipe()` 4D decision tree
- Joint early-stop trajectory selection
- Loss design (worst + ripple + mean) framework-agnostic
- Multi-freq sum extension for broadband

Loss ■■■ optimization workflow ■ worst-case ■■■ framework-agnostic ■
 ■■■ patch (surrogate-in-the-loop) ■■■ patch antenna ■■
 ■■■■■■■■■■■■■■■■■