

# SDRuno CAT Installation

StationFinder v3.0+ · Real-time frequency and mode sharing

---

This document covers connecting StationFinder v3.0 (or higher) to SDRuno for real-time frequency and mode sharing.

```
[ StationFinder browser ]
    | Web Serial API (virtual COM port)
    |
    [ SDRuno ]
```

When you tune SDRuno, StationFinder follows when in tracking mode. When you click a row in StationFinder, SDRuno tunes to that frequency and sets the correct demodulation mode (if in the database).

## Requirements

---

- Windows 8.1, 10, or 11
- SDRuno ([sdrplay.com/sdruno](https://sdrplay.com/sdruno))
- com0com ([sourceforge.net/projects/com0com](https://sourceforge.net/projects/com0com)) — creates a virtual COM port pair
- StationFinder v2.0 or higher — open in Chrome or Edge only

**NOTE** Firefox and Safari do not support the Web Serial API. Use Chrome or Edge.

## Step 1 — Install com0com

---

Download and install com0com from: [sourceforge.net/projects/com0com/](https://sourceforge.net/projects/com0com/)

During setup, create a virtual COM port pair — for example COM8 and COM9. Note both port numbers.

## Step 2 — Configure SDRuno CAT

---

In SDRuno:

1. Open the RX CONTROL panel
2. Click SETT
3. Select the CAT tab
4. Set **Port** to one end of your com0com pair (e.g. COM8)
5. Set **Baud** to **9600**

6. Enable **Rx Mode CTL**
7. Enable CAT

## Step 3 — Connect StationFinder

8. Open StationFinder in Chrome or Edge
9. Click the connection drop-down (shows 127.0.0.1 by default) and select **SDRuno CAT**
10. The browser's COM port picker appears — select the **other end** of your com0com pair (e.g. COM9, the end SDRuno is **not** using)
11. StationFinder connects automatically

The frequency display appears immediately showing SDRuno's current frequency.

## Using StationFinder with SDRuno

| Action               | Result                                           |
|----------------------|--------------------------------------------------|
| Click Fetch          | One-shot frequency read from SDRuno              |
| Click Track          | StationFinder follows SDRuno continuously        |
| Click a schedule row | SDRuno tunes to that frequency and sets the mode |

## Supported Demodulation Modes

| Schedule File Mode | SDRuno Mode |
|--------------------|-------------|
| AM / SAM           | AM          |
| USB                | USB         |
| LSB                | LSB         |
| CW                 | CW          |
| NFM / WFM          | FM          |
| FSK / DIG          | FSK         |

## Troubleshooting

---

### “Web Serial not supported”

You are using Firefox or Safari. Switch to Chrome or Edge.

### COM port picker shows no ports

com0com may not be installed or the port pair was not created. Reinstall com0com and create the pair.

### Frequency display shows nothing after connecting

SDRuno CAT is not enabled or is set to the wrong COM port. Confirm SDRuno SETT → CAT is enabled and using the correct com0com port — not the one StationFinder selected.

### Frequency not updating in Track mode

Confirm SDRuno CAT is enabled.

### Clicking a row does not tune SDRuno

Confirm StationFinder is connected (frequency display visible) and SDRuno CAT is enabled.

## License

---

GNU General Public License v3 or later.

Copyright © 2026 Roger Need