


HDC Chamber Connections



Heated Bed



Bed




Chamber



Fan chamber



Earth Ground



HDC, 1 2 3

From	Cable colour/size	To Pin
Heated bed L	Used Supplied? Via thermal Fuse	1
Heated bed N	Used Supplied	2
Aluminium Bed	Green silicon/18	3
N/C		4
N/C		5
Heater Bed Thermistor	Used Supplied	6
Heater Bed Thermistor	Used Supplied	7
N/C		8
Anvil Sensor	white/22	9
Anvil Sensor	white/22	10


From	Cable colour/size	To pin
Chamber Thermister	White/22	1
Chamber Thermister	White/22	2
FAN Tacho	yellow/22	3
Fan PWM	Blue/ 22	4
Fan Chamber +12	Red /18	5
Fan Chamber gnd	Black/18	6

From	Cable colour/size	To Pin
Chamber Heater L	Brown Silicone/18	1
Chamber Heater N	Blue Silicone/18	2
Chamber Heater E	Green Silicone/18	3
N/C		4
N/C		5
N/C		6


HDC Connector Assembly

See Drawing Mains connections


HDC 3



Socket view of screw terminals




Plug view of screw terminals




SSR Bed heater

From Pin	To
1	SSR Terminal 2
2	Blue Terminal Block
3	Earth Terminal Block
4	N/C
5	N/C
6	TENP 3/VSSA
7	TENP 3/temp3
8	N/C
9	IO_2/io1in
10	IO_2/GND

HDC 2



Socket view of screw terminals




Plug view of screw terminals


FromPin	To
1	TEMP 2/VSSA
2	TEMP 2/temp2
3	out6.tach
4	out6_out
5	Yellow Terminal Block
6	Black Terminal Block

HDC 1

See Drawing Mains connections



Plug view of screw terminals



Socket view of screw terminals



SSR Chamber

From pin	To
1	SSR Terminal 2
2	Blue Terminal Block
3	Earth Terminal Block
4	N/C
5	N/C
6	N/C

Place a blob of RTV over the L and N connections , safety precaution in case the screws come loose!