

# PAX CASE TO RIM BOX CABLE

## Cable Prep, PAX Case End

|                  | Jacket/Foil/Braid Strip | Wire Strip | Heat Shrink length (dia. x length) | Shield Ground Wire Length (gray) |
|------------------|-------------------------|------------|------------------------------------|----------------------------------|
| Cryo Power       | 2"                      | 1/4"       | 3/16 x 1/2"                        | -                                |
| Dewar Temp.      | 1-1/2"                  | 1/4"       | 3/16 x 1/2"                        | -                                |
| Cryo Temp.       | 1-1/4"                  | 1/4"       | 3/16 x 1/2"                        | -                                |
| TEC Power        | 1-1/2"                  | 1/4"       | 3/16 x 1/2"                        | -                                |
| TEC Control      | 2"                      | 1/4"       | 1/4 x 5/8"                         | -                                |
| Ion Pump Control | 2-1/4"                  | 1/4"       | 1/4 x 5/8"                         | -                                |
| PAX control      | 2-3/8"                  | 1/4"       | 1/4 x 3/4"                         | -                                |
| Ground Wire      | N/A                     | 3/16"      | N/A                                | -                                |

## Cable Prep, Rim Box End

|                  |        |           |             |        |
|------------------|--------|-----------|-------------|--------|
| Cryo Power       | 2"     | 1/16-1/8" | 3/16 x 3/4" | 4-1/2" |
| Dewar Temp.      | 1-1/2" | 1/16-1/8" | 3/16 x 3/4" | 4"     |
| Cryo Temp.       | 1-1/2" | 1/16-1/8" | 1/4 x 3/4"  | 4"     |
| TEC Power        |        |           |             |        |
| TEC Control      |        |           |             |        |
| Ion Pump Control |        |           |             |        |
| PAX control      |        |           |             |        |
| Ground Wire      | -      | 1/8"      | -           | -      |
|                  |        |           |             |        |
|                  |        |           |             |        |

### Cable Assembly Notes

Cut back braid and foil

Cut back unused wire in Dewar and Cryo temp cables

18-22 gage wires work in Amphenol crimp contacts

Cryo Power uses two wires for positive and two for negative

Cryo Power / Rim Box end, double wires merge at one crimp socket, don't over crimp

Amphe-Lite plastic install & extract tool work well, but have short life span

Tinned copper mesh sleeving dia. 25/32"