

Module 1: Overview & Transmission Fundamentals

OSI vs. TCP/IP, Impairments, Nyquist & Shannon Theorems

Module I: Data Communications & Networking Overview — Topics Covered

1. Five Components of Data Communication
2. Network Topologies (Mesh, Star, Bus, Ring)
3. OSI 7-Layer vs. TCP/IP 4-Layer Architecture
4. Transmission Impairments (Attenuation, Delay, Noise)
5. Nyquist Maximum Data Rate Theorem
6. Shannon Channel Capacity Theorem & SNR (dB)

1. Layered Network Models: OSI vs. TCP/IP

OSI Layer	Protocol Data Unit (PDU)	Key Responsibilities	TCP/IP Equivalent
7. Application	Messages / Data	Network virtual terminal, HTTP, FTP, SMTP, DNS	Application Layer
6. Presentation	Formatted Data	Translation, Encryption (SSL/TLS), Compression	
5. Session	Dialog Tokens	Session establishment, Dialog control, Sync checkpoints	
4. Transport	Segments (TCP) / Datagrams (UDP)	Port addressing, Segmentation, Flow/Error/Congestion control	Transport Layer
3. Network	Packets	Logical IP addressing, Subnet routing, Path determination	Internet Layer
2. Data Link	Frames	Physical MAC addressing, Framing, Error detection (CRC)	Network Access Layer
1. Physical	Bits	Bit transmission over copper/fiber/radio, signal levels	

2. Channel Capacity Theorems

2.1 Nyquist Theorem (Noiseless Channel)

$$C = 2B \log_2(M) \text{ bps}$$

where B is channel bandwidth in Hertz and M is the number of discrete signal voltage levels.

2.2 Shannon Theorem (Noisy Channel)

$$C = B \log_2(1 + \text{SNR}) \text{ bps}$$

where $\text{SNR} = \frac{P_{\text{signal}}}{P_{\text{noise}}}$. Given $\text{SNR}_{\text{dB}} = 10 \log_{10}(\text{SNR}) \implies \text{SNR} = 10^{(\text{SNR}_{\text{dB}}/10)}$.

 BIT Mesra Mid-Sem Exam Numerical (8 Marks)

Problem: A telephone line has a bandwidth of 4 kHz and a signal-to-noise ratio of 30 dB. Calculate the theoretical Shannon maximum channel capacity.

Solution:

$$\text{SNR}_{\text{dB}} = 30 \implies 10 \log_{10}(\text{SNR}) = 30 \implies \text{SNR} = 10^3 = 1000$$

$$C = B \log_2(1 + \text{SNR}) = 4000 \times \log_2(1001) \approx 4000 \times 9.967 = \mathbf{39,869 \text{ bps}} \approx \mathbf{39.87 \text{ kbps}}$$