SICK App Designer 1.0.1 release note

Revision history

Status	RELEASED
Version	1.0.1
Last update	09 Oct 2026
Revision comments	

Summary

SICK App Designer is the Software Development Kit for the creation of application software for programmable sensors, released as an extension in the Visual Studio Code marketplace. This document pertains to the version 1.0.1, released on 09 Oct 2026 .

Table of contents

- Bugfixes
- New Feature
- Task
- Improvement
- Changelog
  - 1.0.1 - 09 Oct 2026
    - Changes
- Limitations
- Known issues
  - Workspace & building
  - Language server
  - UI-Builder
  - Device connectivity
  - Device / App Model
  - Device console
  - Debugging
  - Device file system
- Supported hardware & software
- Installation
  - Components
  - System requirements
  - Installation instructions & first steps

Bugfixes

- [SDK-372] - Experimental CROWN API are not colored/marked accordingly in SICK App Designer
- [SDK-373] - Emulator won't start properly with default workspace
- [SDK-375] - Jira issue collector is not accessible
- [SDK-379] - DCX fails to initialize
- [SDK-388] - Startup issues
- [SDK-390] - Images inside tables not shown in viewer during debugging
- [SDK-391] - Debug viewer shows images incorrectly when watching several images of different size
- [SDK-398] - Copy Value in Debug Variable Scope
- [SDK-411] - Link behind "read our docs" not working
- [SDK-412] - Incorrect FirmwareVersion displayed when starting debugger without active device selection

New Feature

- [SDK-42] - Setting to enable Hidden CROWNs in LuaLS

Task

- [SDK-376] - Disable USB support

Improvement

- [SDK-377] - Add coloring of CROWNs to SICK App Designer
- [SDK-392] - Device model from builtin manifest repository if device description upload fails
- [SDK-403] - Lua language server respects luarc.json
- [SDK-413] - Remove existing device list entry for emulator when starting/stopping emulator

Changelog

1.0.1 - 09 Oct 2026

Changes

Limitations

Limitation	Description
Protect SensorApp	Protection settings for your SensorApp to restrict reading the source code by others or duplicating the app from one sensor to another are currently not available. The source code of all sensor apps build with this version are readable by others.
Import app from device	Only unprotected apps can be imported form a device.

Known issues

Workspace & building

Issue	Description	Workaround
Build watcher does not register changes	The watcher does NOT work for symlinked **files** it only works for directories.	If possible, include the parent directory as symlink.
Multiple build triggered	After removing a symlinked directory, the VSCode watcher still triggers the change event as if the symlink was never removed. This shouldn't have any bad side effects, except for performance (unnecessary rebuilds)	Restart VSCode
Name conflicts in project manifest are not validated	Name conflicts in the project.mf.xml are not displayed as error to the users and are not validated when building SAR or SAPK files. This can lead to unpredictable behavior.	None
Building SAPK fails	Deploying apps to a device or building SAPK fails. In the SICK App Designer Log output channel a message shows up: "Failed to build msdd" This error message is caused by a corrupted UIBuilder control-library	1. Close vscode. 2. In the file system, navigate to `%APPDATA%\SICK\AppSpace\ui-builder\control-library` and delete the folder with the version number, eg. '5.0.2'. 3. Restart vscode. The UIBuilder will reinstall the control-library, this takes a moment.

Language server

Issue	Description	Workaround
Custom path structure not loaded	Directories defined by *Lua.workspace.library* are not loaded.	A further *scripts* folder must be placed in which the Lua code must be placed.
No effect of certain *Lua.format.** options	The old formatter was replaced by a new one including the settings options.	Use *Lua.format.defaultConfig* instead.

UI-Builder

Issue	Description	Workaround
Missing parameter bindings	"Parameter Bindings" work only with parameters in the workspace. Parameters from the device are not loaded.	
Unexpected behavior on shortcut	Changed keyboard shortcuts are not respected by the UI-Builder.	If changed one should add *activeCustomEditorId != 'sickag.ui-builder-plugin.HtmlEditor'* to the *When* condition in Keyboard Shortcuts.
Unexpected behavior with edit menu	It is not recommended to use VSCode menu Edit > operations with UIBuilder as ○ Cut-copy-paste operates on VSCode's history and not the UIBuilder's. ○ Other operations should have no effect.	Use the built-in functionality of the UI-Builder.
No log output for broken MSDD builds	There is no error log in OUTPUT > SICK AppDesigner Log (Build), if your .msdd build breaks.	Open Help > Toggle Developer Tool to display UI logs.
App not updated though build process changed	App change not detected when switching msdd build from legacy sopasjs to new sail build	Delete app from device and retry

Issues with sick-viewer2d and sick-viewer3d	• click "Options" then click "Fullscreen" options menu is mispaced • click "Fullscreen" type errors "Element is not connected" and "Permissions check failed" may appear	

Device connectivity

Issue	Description	Workaround
"Failed to activate extension"	Possible reasons: 1. VSCode has been closed during the installation of the device connectivity services. The installation might be corrupt.	If the device connectivity services fail to start, a webview should open and perform several diagnostics. Try to resolve the issue with the offered solutions (buttons). Possible solution (manual): Restart VSCode if this does not help, reset SickConnectX: 1. Check the log of the device connectivity (see output channel) The blocked ports should be listed in the log. 2. Delete the following folder: • Windows: '%APPDATA%/SICK/AppSpace/MaxwellConnect/instances/scx-runtime-3.2.0' • Linux: '~/.config/SICK/AppSpace/MaxwellConnect/instances/scx-runtime-3.2.0' 3. Restart VSCode
Device list empty after update	Currently updates of the "Device connectivity" results in a loss of the device list/configuration. Migration is currently not supported	Populate the device list again
WSL: Devices are not reachable	USB Support might be blocked by the IT device connectivity refuses to work	Disable USB capability of the device-connectivity by setting the environment variable *NASRT_ENABLE_USB* to false, e.g. via *.bashrc:* echo "export NASRT_ENABLE_USB=false" >> $HOME/.bashrc Or via windows variables (this is mandatory if VSCode is not started via WSL terminal!): NASRT_ENABLE_USB=false WSLENV=NASRT_ENABLE_USB

Device / App Model

Issue	Description	Workaround
Device manifest not loaded	Device must be in the same network and accessible from the current device.	• Ensure device is in the same network • Add device IP to NO_PROXY environment variable • Remove and add the device again
Device manifest not loaded (SAE 1.6.x, - 1.8.0)	The device manifest can currently not be loaded from those SAE versions	None

Device console

Issue	Description	Workaround
No output received anymore for selected device	The device console stopped printing console messages	Internal connection to the device lost (SCX does not support an event for this at the moment) 1. Unselect the device 2. Select the device again
No output printed after (re-selecting) device	The device console does not print any more messages after following these steps: 1. View device console 2. Unselect device from list 3. Select device again	Restart VSCode **Note** As the device connectivity is shared between all instances, all VSCode instances with active SICK App Designer have to be restarted.
No device console output of any selected device	No matter which device is connected or how often VSCode was restarted, no output is printed	Reset SickConnectX: 1. Close all VSCode instances 2. Delete your MaxwellConnect instance **Linux:** '~/.config/SICK/AppSpace/MaxwellConnect/instances/scx-runtime-3.2.0' **Windows:** '%APPDATA%/SICK/AppSpace/MaxwellConnect/instances/scx-runtime-3.2.0' 3. Restart VSCode Device Connectivity will be reinstalled

Debugging

Issue	Description	Workaround
2D/3D viewer shapes are drawn incorrectly		None
Debugging does not start	After starting the debugger VSCode stays in a loop indicating the debugger is starting but nothing happens	Reset SickConnectX: 1. Close all VSCode instances 2. Delete your MaxwellConnect instance **Linux:** '~/.config/SICK/AppSpace/MaxwellConnect/instances/scx-runtime-3.2.0' **Windows:** '%APPDATA%/SICK/AppSpace/MaxwellConnect/instances/scx-runtime-3.2.0' 3. Restart VSCode Device Connectivity will be reinstalled

Device file system

Issue	Description	Workaround
Create new file on device file system shows error	When creating a new file on the "Device filesystem" an error message is shown. The file is created regardless, but not shown in the UI until refresh.	Refresh the "File explorer" view after the error message appeared.
Files with special symbols in name are no longer accessible	If you create or rename a file with special non-ASCII symbols in their name, they will no longer be accessible.	None. Be cautious when choosing file names.

Supported hardware & software

This release supports the following SICK AppEngine based devices:

Product family	Part number	Device type
SICK AppEngine	1613796	SICK AppEngine (x64)

InspectorP61x	1116350	V2D611P-MMSCE4
	1114809	V2D611P-MMSBE4
InspectorP62x	1110847	V2D621P-2MSFBB5
	1110848	V2D621P-2MSFFB5
	1110849	V2D621P-2MDFGB5
InspectorP63x	1082298	V2D631P-2MXCXB0
	1082299	V2D631P-2MXSXB0
	1082300	V2D632P-2MXCXB0
	1082301	V2D632P-2MXSXB0
InspectorP64x	1082302	V2D642P-2MCXXA6
InspectorP65x	1082303	V2D652P-2MCXXA6
	1082304	V2D654P-2MCXXA6
	1082305	V2D652P-2MEWHA6
	1082306	V2D654P-2MEWHA6
MRS1000P	1104278	MRS1104P-111011
RFU61x	1091102	RFU610-10600
	1099890	RFU610-10601
	1101394	RFU610-10605
	1104441	RFU610-10614
	1104443	RFU610-10603
	1104444	RFU610-10604
	1104445	RFU610-10613
	1104446	RFU610-10610
	1104447	RFU610-10607
	1104448	RFU610-10618
	1104449	RFU610-10609
RFU62x	1062599	RFU620-10100
	1062600	RFU620-10400
	1062601	RFU620-10500
	1062602	RFU620-10101
	1062603	RFU620-10401
	1062604	RFU620-10501
	1068727	RFU620-10107
	1068728	RFU620-10105
	1069453	RFU620-10503
	1069677	RFU620-10104
	1070407	RFU620-10504
	1077860	RFU620-10505
	1077863	RFU620-10514
	1083557	RFU620-10510

	1083976	RFU620-10507
	1084997	RFU620-10111
	1086439	RFU620-10110
	1088871	RFU620-10508
	1091355	RFU620-10103
	1092037	RFU620-10112
	1094605	RFU620-10108
	1096414	RFU620-10114
	1101686	RFU620-10118
	1101700	RFU620-10102
RFU63x	1054396	RFU630-13100
	1054397	RFU630-13101
	1057943	RFU630-13105
	1058117	RFU630-04100
	1058775	RFU630-13102
	1059999	RFU630-04101
	1061498	RFU630-13107
	1067133	RFU630-13106
	1067473	RFU630-13103
	1068569	RFU630-04106
	1068726	RFU630-13104
	1070903	RFU630-13108
	1070904	RFU630-04108
	1073196	RFU630-04105
	1073376	RFU630-04102
	1073377	RFU630-04109
	1073442	RFU630-13110
	1074302	RFU630-13112
	1077861	RFU630-13113
	1077862	RFU630-13111
	1083558	RFU630-13115
	1087776	RFU630-04117
	1093152	RFU630-04104
	1095224	RFU630-13114
	1104670	RFU630-04103
RFU65x	1073556	RFU650-10100
	1076522	RFU650-10101
	1083559	RFU650-10105
	1083560	RFU650-10106
	1087587	RFU650-10102

	1092036	RFU650-10104
	1096413	RFU650-10103
SID	1098321	SID120
	1101360	SID70
SIM10xx	1097816	SIM1000-0P0B100
	1098146	SIM1012-0P0G200
	1111314	SIM1012-0P0G200S01
	1098148	SIM1004-0P0G311
SIM2x00	1080579	SIM2000-0A10A00
	1081902	SIM2000-2P04G10
	1092673	SIM2500-2P03G10
SIM10xx|Flexi Soft	1097817	SIM1000-0P0B110
SIM4x00	1078787	SIM4000-0P03G10
TIM8xxP	1090292	TIM881P-2100101
TriSpectorP1000	1091318	V3T11P-MR12A8
	1091319	V3T12P-MR32A8
	1091320	V3T13P-MR62A8
	1091321	V3T12P-MR32A7
	1091322	V3T11P-MR12A7
	1091323	V3T13P-MR62A7
Visionary-T AP	1102953	V3S140-2AAAAAA
	1102954	V3S140-2AABAAB
Visionary-S AP	1114319	V3S142-1AAAAAA
	1114320	V3S142-1AABAAB

Installation

Components

SICK App Deisgner	1.0.1
Code samples	https://gitlab.com/sick-appspace/samples
UI Builder	3.5.0, WYSIWYM and web programming tool for creating app UIs, based on DaVinci basic elements 5.6.4

System requirements

OS	Windows 10 x86_64 Windows 11 x86_64 Ubuntu 22.04 x86_64
HDD	min 1 GB
RAM	min 4 GB, 8 GB recommended
Processor	1 GHz CPU
Browser	Chrome for support of WebGL and WebSockets
IDE	Microsoft Visual Studio Code v1.92

Installation instructions & first steps

Please find installation instructions and first steps tutorials here: SICK App Designer Docs