ABB Register Map

This map assumes a base zero offset.

The A8810 acts as a RTU to TCP converter for the PVMET-330S, PVMET-150S and Si-RS485 reference cell.
The SCADA system needs to be able to write to the rainfall register to reset it daily or must track rollovers.
Irradiance calibration registers are adjusted when new sensors are installed or if they have been recalibrated. It is best if the SCADA can update these.

Device	Paramter	Units	Gain	MB Address	Register Type	Data Type	Register Number	Number of Registers	Notes
PVMET-330S	Air Temperature	°C	0.1	60	Input Register	int16	3	1	
PVMET-330S	Relative Humidity	%	1	60	Input Register	int16	4	1	
PVMET-330S	Barometric Pressure	hPa	0.1	60	Input Register	int16	5	1	
PVMET-330S	Wind Speed (5min)	m/s	0.1	60	Input Register	int16	8	1	
PVMET-330S	Wind Direction (5min)	°	1	60	Input Register	int16	9	1	
PVMET-330S	WindGust (5min)	m/s	0.1	60	Input Register	int16	10	1	
PVMET-330S	Wind Gust Direction	°	1	60	Input Register	int16	11	1	
PVMET-330S	Rainfall	count (0.01" per count)	1	60	Input Register	int16	12	1	Write access to reset. Roll over at 65536
PVMET-330S	B.O.M Temperature 1	°C	0.1	60	Input Register	int16	13	1	
PVMET-330S	B.O.M Temperature 2	°C	0.1	60	Input Register	int16	14	1	
PVMET-150S	Global Irradiance	W/m^2	1	61	Holding Register	uint16	85	1	
PVMET-150S	Plane of Array Irradiance	W/m^2	1	61	Holding Register	uint16	86	1	
PVMET-150S	Air Temperature	°C	0.1	61	Holding Register	int16	72	1	
PVMET-150S	B.O.M Temperature 1	°C	0.1	61	Holding Register	int16	92	1	
PVMET-150S	B.O.M Temperature 2	°C	0.1	61	Holding Register	int16	93	1	
PVMET-150S	Global Sensitivity Constant	uV/W/m^2	0.01	61	Holding Register	uint16	202	1	Write access for calibration
PVMET-150S	POA Sensitivity Constant	uV/W/m^2	0.01	61	Holding Register	uint16	203	1	Write access for calibration
Si-RS485	Irradiance	W/m^2	0.1	63	Input Register	uint16	1	1	
Si-RS485	Cell Temperature	°C	0.1	63	Input Register	int16	8	1	