

Logical Network Configuration File Manual

BASE24[®]



© 2011 by ACI Worldwide, Inc. All rights reserved.

All information contained in this documentation, as well as the software described in it, is confidential and proprietary to ACI Worldwide, Inc., or one of its subsidiaries, is subject to a license agreement, and may be used or copied only in accordance with the terms of such license. Except as permitted by such license, no part of this documentation may be reproduced, stored in a retrieval system, or transmitted in any form or by electronic, mechanical, recording, or any other means, without the prior written permission of ACI Worldwide, Inc., or one of its subsidiaries.

ACI, ACI Worldwide, and the ACI product names used in this documentation are trademarks or registered trademarks of ACI Worldwide, Inc., or one of its subsidiaries.

Other companies' trademarks, service marks, or registered trademarks and service marks are trademarks, service marks, or registered trademarks and service marks of their respective companies.

Contents

What's New	vii
Preface	xiii
Conventions Used in This Manual	xix
1: Introduction	1-1
LCONF Assigns and Params	1-2
LCONF Assigns	1-2
LCONF Params	1-2
LCONF Specifications	1-4
File Security	1-4
File Creation	1-4
LCONF LD Program	1-5
Duplicating an Existing LCONF	1-6
Creating a New LCONF	1-6
Accessing the LCONF	1-8
Pseudo Process Names	1-9
2: Logical Network Configuration File (LNCf) Screens	2-1
LNCf Screens	2-2
LNCf Printing Screen	2-2
LNCf Assign Screen	2-2
LNCf Param Screen	2-2
LNCf Edit Screen	2-2
LNCf Screen Access	2-3
Function Keys	2-4
Help Screens	2-5

3: LNCF Printing Screen	3-1
Function Keys	3-2
Screen Description	3-3
Procedures	3-6
Displaying the LNCF Assign, LNCF Param, or LNCF Edit Screen	3-6
Sending Reports to a Spooler Location	3-6
LCONF Reports	3-8
Assign Report	3-9
Index of LCONF Assigns	3-10
Param Report	3-12
Index of LCONF Params	3-13
 4: LNCF Assign Screen	 4-1
Function Keys	4-2
Screen Description	4-3
Procedures	4-6
Displaying the Assign Screen	4-6
Searching for an Assign	4-6
Reading a Specific Assign	4-6
Reading Forward Through Multiple Assigns	4-7
Updating an Assign	4-7
Adding an Assign	4-8
Deleting an Assign	4-9
Sending an Assign to a Spooler Location	4-9
Exiting from the LNCF Assign Screen	4-9
 5: LNCF Param Screen	 5-1
Function Keys	5-2
Screen Description	5-3
Procedures	5-6
Displaying the LNCF Param Screen	5-6
Searching for a Param	5-6
Reading a Specific Param	5-6
Reading Forward Through Multiple Params	5-7
Updating a Param	5-7

Procedures <i>continued</i>	
Adding a Param	5-8
Deleting a Param.	5-8
Sending a Param to a Spooler Location	5-9
Exiting from the LNCF Param Screen	5-9
6: LNCF Edit Screen	6-1
Function Keys	6-2
Screen Description	6-3
Procedures.	6-5
Displaying the LNCF Edit Screen	6-5
Updating System, Volume, or Subvolume Names	6-5
Exiting from the Edit Screen	6-6
7: General Assigns and Params.	7-1
Assigns	7-2
Params.	7-41
8: BASE24-atm Assigns and Params.	8-1
Assigns	8-2
Params.	8-24
9: BASE24-billpay Assigns and Params	9-1
Process Name	9-2
Generic Program and Server Class Names	9-2
Specific Program or Server Process Names	9-3
Time Intervals	9-6
Assigns	9-7
Params.	9-9
10: BASE24-card Assigns and Params	10-1
Assigns	10-2
Params.	10-5

11: BASE24 Customer Service Assigns	11-1
Assigns	11-2
12: BASE24-from host maintenance Assigns and Params	12-1
Assigns	12-2
Params.....	12-4
13: BASE24-inventory Assigns and Params	13-1
Assigns	13-2
Params.....	13-4
14: BASE24-mail Assigns and Params	14-1
Assigns	14-2
Params.....	14-4
15: BASE24-pos Assigns and Params	15-1
Assigns	15-2
Params.....	15-22
16: BASE24-telebanking Assigns and Params	16-1
Assigns	16-2
Params.....	16-29
17: BASE24-teller Assigns and Params	17-1
Assigns	17-2
Params.....	17-10
18: Object-Oriented Application Assigns and Params	18-1
Assigns	18-2
Params.....	18-10
Index	Index-1
Index by Assign Name	Index-3
Index by Param Name	Index-9

What's New

The following table highlights the major changes that have been made in the most recent update to the *BASE24 Logical Network Configuration File Manual*. The first column of the table lists the sections and appendixes in which major changes have been made. The second column of the table describes the major changes for each section or appendix.

November 2011

Section/ Appendix	Major Changes
----------------------	---------------

7	Adds new params for migration processing support:
---	---

MIGR-ATM-ADVC-DEST_{xx}
MIGR-ATM-ENABLE
MIGR-ATM-HISO-DEST
MIGR-ATM-PROCESSING-OPTS
MIGR-FHM-HISO-ENABLE
MIGR-HISO-ENABLE
MIGR-HISO-NAME
MIGR-INTF-DPC-NUM
MIGR-POS-ADVC-DEST_{xx}
MIGR-POS-ENABLE
MIGR-POS-HISO-DEST
MIGR-POS-PROCESSING-OPTS

Adds new params for switch mandate support:

DSCV-VER-IND
EXTRN-RQST-TIMEOUT
INSTL-TXN-DATA-OFST
MDS-SPPT-NON-EMV-PIN-CHANGE
SWI-ENHNCD-ILF-MATCH-ACQ
SWI-ENHNCD-ILF-MATCH-ISS
SWI-MDS-SPPT-CCA-ADVC-RVSL
SWI-VISA-MAP-EXPAND-AVS-TO-BASIC
SWI-VISA-MVV-IN-AUTO-SUBSTAN-TKN
SW-BNET-SPPT-INSTL-TXN
SW-SPN2-USING-STA-SATELLITES

Adds SAMA SPAN2 interface to list of interfaces that support these params:

SWI-ACQ-CVD2-DATA-SUPPRS
SWI-ACQ-DISCR-DATA-SUPPRS
SWI-ISS-CVD2-DATA-SUPPRS
SWI-ISS-DISCR-DATA-SUPPRS

September 2011

Section/ Appendix	Major Changes
----------------------	---------------

- | | |
|----|--|
| 7 | Adds missing description for existing param EXTRN-RQST-TIMEOUT. |
| 15 | Adds new param POS-DH-KSN-ANSI-STD-OPT to indicate whether the Standard POS Device Handler (SPDH) module should follow the ANSI standard for validating KSN values or follow the current method of validation. |

September 2010

Section/ Appendix	Major Changes
----------------------	---------------

- | | |
|----|---|
| 7 | Adds a description of the SW-BNET-LOG-ONLY-COMPL-ADVICE param. This param contains a flag indicating whether a log-only message should be sent to the BASE24-pos Router/Authorization process when a response to an automated fuel dispense completion advice is received from Banknet. |
| 15 | Corrects the valid values and default value for the ADJ-ADVICE-RC param. The valid values are 1–3 instead of 0–2 and the default value is 1. |

December 2009

Section/ Appendix	Major Changes
----------------------	---------------

- | | |
|----|--|
| 7 | <p>Updates the ENHANCED-EMV-RC-MAPPING param to include the Host Interface.</p> <p>Updates the SW-RPT-STARTUP param to correct the time format.</p> <p>Adds the PRE-VERIFIED-PIN-PAD-CHAR, PSEUDO-3DES-CBC-MAC-TYPE, and RACAL-ANSI-METHOD params.</p> |
| 8 | <p>Updates the ATM-NIDFEMT assigns to include the BASE24-atm Diebold Device Handler.</p> <p>Updates the ATM-LN-CUTOVER, ATM-SETL-RPT0-STARTUP, and ATM-SETL-RPT1-STARTUP params to correct the time format.</p> |
| 12 | <p>Updates the FHM-LN-CUTOVER and FHM-RPT-STARTUP params to correct the time format.</p> |
| 13 | <p>Updates the INV-LN-CUTOVER param to correct the time format.</p> |
| 14 | <p>Updates the MAIL-LN-CUTOVER param to correct the time format.</p> |
| 15 | <p>Updates the POS-LN-CUTOVER and POS-SETL-REPORTS params to correct the time format.</p> <p>Adds the ADJ-ADVICE-RC, POS-DH-PTD-NFTY-PCNT, and POS-ISS-AVS-BLANK-ZIP-CDE-ALWD params.</p> |
| 17 | <p>Updates the TLR-LN-CUTOVER param to correct the time format.</p> |

Preface

The BASE24 Logical Network Configuration File (LCONF) enables institutions to define files, processes, and spooler locations at the network, product, process, and device level. The LCONF also enables institutions to define processing parameters at the network, product, process, and device level. Institutions make these definitions by configuring assigns and params in the LCONF.

This manual provides an introduction to the LCONF, discusses the screens used to access the LCONF, and describes the assigns and params used by BASE24 products.

Audience

This manual is intended for the BASE24 institution personnel responsible for configuring and maintaining the LCONF.

Prerequisites

Readers of this manual should be familiar with the entire manual set for their respective products, with emphasis on the transaction processing manuals. LCONF assigns and params can impact all phases of transaction processing.

Additional Documentation

The BASE24 documentation set is arranged so that each BASE24 manual presents a topic or group of related topics in detail. When one BASE24 manual presents a topic that has already been covered in detail in another BASE24 manual, the topic is summarized and the reader is directed to the other manual for additional information. Information has been arranged in this manner to be more efficient for readers who do not need the additional detail and at the same time provide the source for readers who require the additional information.

This manual contains references to the following BASE24 publications:

- The ***BASE24 CRT Access Manual*** provides detailed information on accessing screens and standard function keys.
- The ***BASE24 Tokens Manual*** contains additional information regarding default actions taken when the TKN assign is not present in the LCONF or contains an invalid value.
- The ***BASE24 Remote Banking End-of-Period Processing Manual*** contains information on archive groups and cleanup groups and their use in processing. These groups are specified in the BP-ARCHIVE-GROUP and BP-CLEANUP-GROUP params, respectively.
- The ***BASE24 Transaction Security Manual*** provides detailed information on User Field values for the SECURE-DEV1 and SECURE-DEV2 assigns.
- The ***BASE24 Transaction Security Services Processing Guide*** provides detailed information on configuring security-related LCONF assigns and params when using the Transaction Security Services process.
- The ***BASE24-billpay Tables Maintenance Manual*** contains information on archive groups and cleanup groups and their use in the Cleanup Configuration Table (CLPT).
- The ***BASE24-billpay Billing Application Manual*** contains information on initial configuration requirements and daily operating procedures.
- The ***BASE24 Remote Banking End-of-Period Processing and Reporting Manual*** provides detailed information on archive groups and cleanup groups and their use in the Cleanup Configuration Table (CLPT).
- The ***Remote Application Manager Implementation and Installation Guide*** provides information on configuring the Remote Application Manager (RAM) process.

This manual contains references to the following Thales e-Security (Racal) publication for information on the console command used to obtain the encrypted key for the RSM-TERM-MASTER-KEY param: ***Host Security Module RG7000 Programmer's Manual***.

This manual contains references to the following Atalla publications for information on defining a security policy for the A8000, A8100, A9000, A9100, and A10100 model NSPs: ***A8000 Installation, Operations, and Command Reference Guide***, ***A9000 Installation, Operations, and Command Reference Guide***, ***Installation and Operations Guide for A10100***, and the ***Banking Command Reference Manual***.

This manual also contains references to the following International Organization for Standardization (ISO) publications:

- The ISO 3166 standard, *Codes for the Representation of Names of Countries*, describes country codes.
- The ISO 4217 standard, *Codes for the Representation of Currencies and Funds*, describes currency codes.

Software

This manual documents standard processing as of its publication date. Software that is not current and custom software modifications (CSMs) may result in processing that differs from the material presented in this manual. The customer is responsible for identifying and noting these changes.

Manual Summary

The following is a summary of the contents of this manual.

“Conventions Used in This Manual” follows this preface and describes notation and documentation conventions necessary to understand the information in the manual.

Section 1, “Introduction,” provides an introduction to the Logical Network Configuration File (LCONF) and its file maintenance screens, and defines the terms assign, param, and pseudo process names.

Section 2, “Logical Network Configuration File (LNCf) Screens,” introduces the LNCf screens used to maintain the LCONF.

Section 3, “LNCf Printing Screen,” describes the LNCf Printing screen, which is the initial point of access to the LCONF. This section includes an example of the LNCf Printing screen, descriptions of each field on the screen, descriptions of the function keys that can be used on the screen, and procedures for performing tasks from the screen.

Section 4, “LNCf Assign Screen,” describes the LNCf Assign screen, which allows specific functions to be performed on assigns. This section includes an example of the LNCf Assign screen, descriptions of each field on the screen, descriptions of the function keys that can be used on the screen, and procedures for performing tasks from the screen.

Section 5, “LNCF Param Screen,” describes the LNCF Param screen, which allows specific functions to be performed on params. This section includes an example of the LNCF Param screen, descriptions of each field on the screen, descriptions of the function keys that can be used on the screen, and procedures for performing tasks from the screen.

Section 6, “LNCF Edit Screen,” describes the LNCF Edit screen, which allows the necessary LCONF assign changes to be made quickly when a large number of files are moved to a new system, volume, or subvolume at one time. This section includes an example of the LNCF Edit screen, descriptions of each field on the screen, descriptions of the function keys that can be used on the screen, and procedures for performing tasks from the screen.

Section 7, “General Assigns and Params,” describes the assigns and params used by two or more BASE24 products and those used by Interchange Interface processes and the ISO Host Interface process.

Section 8, “BASE24-atm Assigns and Params,” describes the assigns and params used exclusively by the BASE24-atm product.

Section 9, “BASE24-billpay Assigns and Params,” describes the assigns and params used exclusively by the BASE24-billpay product.

Section 10, “BASE24-card Assigns and Params,” describes the assigns and params used exclusively by the BASE24-card product.

Section 11, “BASE24 Customer Service Assigns,” describes the assigns used exclusively by the BASE24 Customer Service product.

Section 12, “BASE24-from host maintenance Assigns and Params,” describes the assigns and params used exclusively by the BASE24-from host maintenance product.

Section 13, “BASE24-inventory Assigns and Params,” describes the assigns and params used exclusively by the BASE24-inventory product.

Section 14, “BASE24-mail Assigns and Params,” describes the assigns and params used exclusively by the BASE24-mail product.

Section 15, “BASE24-pos Assigns and Params,” describes the assigns and params used exclusively by the BASE24-pos product.

Section 16, “BASE24-telebanking Assigns and Params,” describes the assigns and params used exclusively by the BASE24-telebanking product.

Section 17, “BASE24-teller Assigns and Params,” describes the assigns and params used exclusively by the BASE24-teller product.

Section 18, “Object-Oriented Application Assigns and Params,” describes the assigns and params used exclusively by the Integrated Endpoint process and kernel objects with BASE24 products.

Readers can use the index by assign name to locate information about a particular assign and the index by param name to locate information about a particular param.

Publication Identification

Three entries appearing at the bottom of each page uniquely identify this BASE24 publication. The publication number (for example, BA-AE000-10 for the ***BASE24 Logical Network Configuration File Manual***) appears on every page to assist readers in identifying the manual from which a page of information was printed. The publication date (for example, Nov-2011 for November, 2011) indicates the issue of the manual. The software release information (for example, R6.0v10 for release 6.0, version 10) specifies the software that the manual describes. This information matches the document information on the copyright page of the manual.

ACI Worldwide, Inc.

Conventions Used in This Manual

This section explains the different terminology used to describe Enscribe files and Structured Query Language (SQL) tables, how field descriptions are documented in this manual, and how assigns and params are documented in this manual.

Enscribe Files and SQL Tables

Throughout this manual, specific terminology is used when discussing Enscribe files or SQL tables. For Enscribe files, the terms field, record, and file are used. For SQL tables, the analogous terms of column, row, and table are used, respectively.

Field Descriptions

Each field appearing on an LCONF screen is listed by name and then described. Field descriptions in this manual briefly summarize the contents, purpose, and permissible values, as shown in the following example taken from the LCONF Assign screen.

Example

ASSIGN NAME — The name of the assign. Examples are NEG, IDF, and SAF. A logical file name consists of alphanumeric characters and the special symbols (^), (-) and (_).

Field Length:	1–32 alphanumeric characters
Required Field:	Yes, except when using the F6 key.
Default Value:	No default value
Data Name:	LCONF.LCONF-KEY.ITEM-NAME

Explanation

Each field description is completed by one or more of the following items of information:

Example	Illustrates a possible entry for the field to further clarify the value or values that can be entered.
Field Length	Specifies the size of the field and the type of characters that can be entered. This length refers to the field and valid values for the file maintenance screen, not the field in the DDLs. Possible values are alphabetic, alphanumeric, hexadecimal, and numeric. The term <i>alphanumeric</i> includes all alphabetic, numeric, and special characters that can be entered from a keyboard without using a control sequence. The term <i>hexadecimal</i> includes all numbers and the letters A through F. When a field value cannot be modified by the operator, the field length is <i>System protected</i>.
Occurs	Indicates the number of times the field can be displayed on the screen. This information is provided only when the field can be displayed multiple times.
Required Field	Specifies whether a value has to be entered in the field. Possible values are Yes and No. Some fields are required only under certain conditions. In this case, the entry is Yes, followed by the conditions that determine when the field is required.
Default Value	Specifies the value that is automatically placed in the field when the screen is first displayed or when the F8 key is pressed to clear the screen.
Data Name	Provides the DDL name associated with the field appearing on the screen. Data names are included in the documentation to assist in communicating screen and field issues to your technical staff. Note that screen data is not always stored in the BASE24 database as it appears on the screen or as it is described in the field description. If you need information on how screen data is actually stored, consult the DDLs.

Assign Documentation

Assigns are documented using a standard format which is described below. Each assign is listed by name and then described. Descriptions in this manual define the assign, identify the processes that use the assign, and provide an example of the value that can be used to link the assign to a physical file name, spooler location, or device, as shown in the following example taken from section 7.

Example

SAF — The fully qualified file name of a Store-and-Forward File (SAF). This assign is used by the following processes:

ISO Host Interface process
 Super Extract process
 Banknet Interchange Interface process
 BIC ISO Interchange Interface process
 EPS-Net Interchange Interface process
 Generic Interchange Interface process
 LINK ISO Interchange Interface process
 MDS ISO Interchange Interface process
 PLUS ISO Interchange Interface process
 VisaNet ISO Interchange Interface process

Examples:	\B24.\$DATA.PRO1DATA.SAF1 (data file name) \B24.\$DATA.PRO1TPLT.SAF (template file name)
Usage Codes:	ATM, BASE, POS, TB, TLR
Read By:	A symbolic name (for example, P1A^HISO1, P2A^BASE) is required in this field because the dates of the SAFs may vary from process to process.
Template File:	Required because the SAF is created periodically by BASE24.

Explanation

Each assign description is completed by one or more of the following items of information:

Example(s)	Provides an example of a valid value and template file value (if applicable) for the assign.
------------	--

Usage Codes	In sections 7 and 16, these are the usage codes that are appropriate for this assign. The other sections are product-specific; the usage codes for the product-specific sections are noted at the beginning of the assign descriptions in these sections.
Read By	Indicates that the assign can, or must, be associated with a symbolic name of a specific process. This information is present only if a process that reads the LCONF for the assign, reads it for an assign that is associated with its symbolic process name. For the BASE24-billpay product, this item can also indicate a program or server class name associated with the assign.
Template File	Indicates that a template file is either required or optional for this assign. Certain files are created periodically by BASE24 processes, and those files must have a template file present. If the template file is not present or has been deleted, some BASE24 processes use the current active file or the previous day's log file as a template. Other BASE24 processes require that the template file exist. The template file information is present only if a template file is required for this assign.
User Field	A description of the values for the user field. This information is present only if information is required in the user field for the assign. Note: The User Field is not required for the SAF assign.
Assign Default	The default value of the assign. When a process, server process, or report program cannot find an assign, or finds an assign with an invalid value, the process, server process, or report program assumes the default value indicated in this field. Note: Default values are not set by the LNCF server program. Default values are set by the individual processes, server processes, or programs as they attempt to read the LCONF.

Param Documentation

Params are documented using a standard format which is described below. Each param is listed by name and then described. Descriptions in this manual define the param, identify the processes that use the param, and describe the values associated with the param, as shown in the following example taken from section 7.

Example

SW-RPT-STARTUP — The time of day (hh:mm) that an Interchange Interface process runs its report obey file. The following Interchange Interface processes use this param:

Banknet Interchange Interface process
 BIC ISO Interchange Interface process
 EPS-Net Interchange Interface process
 Generic Interchange Interface process
 LINK ISO Interchange Interface process
 MDS ISO Interchange Interface process
 PLUS ISO Interchange Interface process
 VisaNet ISO Interchange Interface process

Valid values are 00:00 through 23:59, based on 24-hour time.

If the SW-RPT-STARTUP param is not present or contains an invalid value, the processes listed above do not run reports.

Usage Codes:	ATM, BASE, POS
Read By:	A symbolic name (for example, P1A^BIC, P1A^BICI) is required in this field.
Param Default:	No default value

Explanation

Each param description is completed by one or more of the following items of information:

Example(s)	Provides an example of a valid value for the param.
------------	---

Usage Codes	In sections 7 and 16, this indicates the usage codes that are appropriate for this param. The other sections are product-specific; usage codes for product-specific sections are noted at the beginning of the param section.
Read By	Indicates that the param can, or must, be associated with a symbolic name of a specific process. This information is present only if a process that reads the LCONF for the param, reads it for a param that is associated with its symbolic process name. For the BASE24-billpay product, this item can also indicate a program or server class name associated with the param.
Param Default	The default value of the param. When a process, server process, or report program cannot find a param, or finds a param with an invalid value, the process, server process, or report program assumes the default value indicated in this field. Note: Default values are not set by the LNCF server program. Default values are set by the individual processes, server processes, or programs as they attempt to read the LCONF.

1: Introduction

The Logical Network Configuration File (LCONF) is the central location of file information and processing information for BASE24, and for this reason, it is one of the main components of every BASE24 logical network. One LCONF exists for each logical network. The records in LCONFs are classified as either assigns or params.

This section explains the general concepts of the LCONF. It includes a definition of the terms assign and param, LCONF specifications, information on how processes access the LCONF, the relationship assigns and params have with pseudo process names, and how changed assigns and params can begin to be used in processing.

LCONF Assigns and Params

Records in the LCONF are classified as either assigns or params, depending on their function. The following subsections define these two terms and explain the functionality of each.

LCONF Assigns

Assigns link the physical names of objects in the logical network to names used in BASE24 code. Most assigns link either actual physical Enscribe files to file names or actual physical Structured Query Language (SQL) tables to table names as they are referenced in BASE24 program code. An example is the Institution Definition File (IDF). In order to access the IDF, a process or server process must know the fully qualified name of the file as it exists in a logical network. The LCONF must contain an assign linking IDF to the actual physical Enscribe file (for example, \BNK1.\$DATA.PRO1DATA.IDF).

Other assigns link the physical names for different hardware to the names as they are referenced in BASE24 program code. Examples of types of hardware that are referenced in BASE24 program code are spooler locations, terminal locations, and security devices.

Note: BASE24 products that use SQL tables may use SQL defines instead of, or in addition to, LCONF assigns to link actual physical SQL tables to table names. These defines are specified when a process is SQL-compiled.

LCONF Params

Params set processing values at the logical network level. In some instances, when param information is not present, a process abends during initialization; however, not every param is critical to processing.

For example, when the BASE24-atm Settlement Initiator process initializes, it accesses the LCONF for certain param information. If the ATM-SETL-LN-CUTOVER-LEAD-TIME param is not present, or contains invalid information, BASE24 substitutes a default value of 30 minutes. However, if the ATM-SETL-RPT1-STARTUP param is not present, or contains an invalid value, BASE24 cannot substitute a default value, and the Settlement Initiator process abends during initialization.

Note: Most params used by the BASE24 retail products (that is, BASE24-check auth, BASE24-frequent shopper, and BASE24-refunds) are configured in the Application Configuration Table (ACT), rather than the LCONF.

LCONF Specifications

The LCONF is a key-sequenced file that is maintained using a series of data entry screens provided by the LNCF Requester and LNCF Server processes. A key-sequenced file is a structured file that has its records ordered according to one or more key fields of a record. A key field is a field in a record used to reference specific assign or param information. By ordering these key fields, BASE24 processes and server processes can access LCONF information quickly and efficiently.

The LNCF screens are described in sections 2 through 6 of this manual.

File Security

The LNCF screens are secured like other BASE24 files maintenance screens. For more information on setting up screen security, refer to the ***BASE24 CRT Access Manual***.

File Creation

If an LCONF is needed for a test system or another new logical network, the LCONF can be created by copying the existing LCONF using the HP NonStop File Utility Program (FUP) DUP command. After the file is duplicated, you can modify assign and param records as needed using the LNCF screens.

If an LCONF is needed for a new system, ACI provides a FUP in file (BAxxMISC.LCONFFUP, where *xx* is the number of the current release) that you can use to create an empty LCONF. After the empty LCONF is created, you can use the LCONFLD program provided by ACI to load the minimum set of required assigns and params needed to run a BASE24 Pathway system. Once the Pathway system is started, the LNCF screens can be used to add all other LCONF assigns and params.

Procedures for duplicating an existing LCONF and creating a new LCONF are provided on the following pages.

LCONFLD Program

The LCONF must exist and contain the minimum set of required assigns and params before the BASE24 Pathway system can be started. ACI provides an interactive TAL program called LCONFLD, which allows you to load the following assigns and params into an empty LCONF. The LCONFLD program is executed by obeying the LCONFLDR command file, which is located on the BAxxMISC subvolume, where xx is the number of the current release.

OMF	An assign specifying the location of the Online Maintenance File (OMF) and the template file location. If you are converting an LCONF from a previous release, verify that the OMF assign has a filename in the same format as the template filename. The LNCF server expects the filename in the assign to be in AYYMMDDX format.
OMF-AUDIT	A param controlling the extent of record or row logging to the Online Maintenance File (OMF) by file maintenance server processes, table maintenance server processes, or other processes, or row logging to the Online Maintenance Table (OMT) by table maintenance server processes.
LOGICAL-NET	A param specifying the name of the logical network.
SEC	An assign specifying the location of the Security File (SEC).
UFIR	An assign specifying the location of the User/FIID Relation File (UFIR)
UPFR	An assign specifying the location of the User/Product Files Relation File (UPFR).

When the LCONFLD program is run, it prompts you for the name of the LCONF to be loaded as well as the values to load for each of the above assigns and params. Only the assigns and params listed above can be added using this program and the LCONF must be empty for the program to work.

Note: All filenames entered using the LCONFLD program must be fully qualified, including the system name. In addition, the files referenced must exist on the same HP NonStop system as the LCONF being loaded.

To execute the LCONFLD program, move to the BAxxMISC subvolume, enter the following command at a TACL prompt, and follow the prompts displayed on the screen:

Syntax

O [BEY] LCONFLDR

Once the program completes, you will be able to start the Pathway system for the logical network specified and use the LNCF screens to add all other LCONF assigns and params.

Duplicating an Existing LCONF

To duplicate an existing LCONF, perform the following steps:

1. Determine the name and location of the new LCONF.
2. Log on to the HP NonStop system as the user that owns the BASE24 network and enter the following command at a TACL prompt. In this command *existing-lconf* is the fully qualified location of the existing LCONF to be duplicated and *new-lconf* is the fully qualified location of the new LCONF.

```
FUP DUP existing-lconf, new-lconf
```
3. Verify that the new LCONF was duplicated successfully.
4. Access the LNCF Printing screen for the existing network and enter the location and name of the new LCONF in the FILE-NAME field.
5. Enter the value E in the ITEM TYPE field and press the **F1** key.
6. Using the LNCF Edit screen, modify the system, volume, or subvolume names as needed for the assigns in the new LCONF.
7. Modify individual assigns and params as needed using the LNCF Assign and Param screens.

Creating a New LCONF

To create a new LCONF, perform the following steps:

1. Determine the name and location of the new LCONF.
2. Log on to the HP NonStop system as a SUPER user.

3. Edit the BAxxMISC.LNCFFUP file to contain the name of the new LCONF to be created as well as the number of primary and secondary extents needed for the new LCONF.
4. Create an empty LCONF using the LNCFFUP FUP in file.

```
FUP/IN $vol.BA60MISC.LNCFFUP/
```
5. Load the required minimum assigns and params in the newly created empty LCONF using the LCONFLD TAL program.
6. Start the Pathway system for the new network and add individual assigns and params using the LNCF screens. Verify that the FILE-NAME field on the LNCF Printing screen contains the name of the LCONF you want to access, and change it if necessary.

Accessing the LCONF

The BASE24 LCONF is accessed by BASE24 processes, objects, server processes, and report programs. Each process, object, server process, and report program builds a table in memory of the LCONF assigns and params required for its own internal processing.

When a process, object, server process, or report program is initialized or reinitialized, it builds its table in memory from information in the LCONF. If information is not found in the LCONF, the process, object, server process, or report program either substitutes a default value for the missing information, or it abends, depending on the severity of the problem.

Most assigns and params can be read by any process, object, server process, or report program. However, a number of assigns and params can be read only by a specific process. These assigns and params are associated with the symbolic name of a specific process. (The documentation for each assign and param, starting in section 7, indicates whether the assign or param can or must be associated with a symbolic process name.)

By associating an assign or param with the name of a specific process, individual processes can have their own separate set of file locations and processing parameters. If an assign or param is not found that is associated with the symbolic name of the process, the process either abends or makes a second attempt to read the LCONF for an assign or param that can be referenced by a number of processes. If an assign or param cannot be found in either case, then the process either attempts to substitute a default value or abends.

Note: In addition to associating an assign or param with the symbolic name of a process, the BASE24-billpay product also allows an assign or param to be associated with the specific name of a server class or program.

Pseudo Process Names

An assign or param that is not currently used should not be deleted from an LCONF; however, the assign or param should be associated with a pseudo process name.

A pseudo process is a process name that the LNCf data entry screens consider to be legitimate, but is not a process that is defined to the XPNET system.

By associating an assign or param that is not currently used with a pseudo process, the information on the assign or param can be retained for later use. Comments should be added to indicate the reason why the assign or param is not used.

For example, if CRT Authorization is not being used by the logical network, the POS-CRT-AUTH-PRF assign should not be present in the LCONF. If the assign were present, it would cause the BASE24-pos Device Handler/Router/Authorization processes to write to the PRF, even though it is not necessary. However, rather than deleting the POS-CRT-AUTH-PRF assign, the assign should be associated with a pseudo process (for example, Z^NOT^USED). This way, the information on the param is retained, and, if necessary, the param can be used at a later date.

Because the READ BY field is part of the primary key to the LCONF, an existing assign or param cannot be updated with a symbolic process name. To associate an assign or param with a symbolic process, you must add the assign or param with the process name and then delete the old assign or param.

ACI Worldwide, Inc.

2: Logical Network Configuration File (LNCF) Screens

This section introduces the Logical Network Configuration File (LNCF) screens used to maintain the Logical Network Configuration File (LCONF) from a BASE24 Pathway system. Using these screens you can perform the following:

- Access the LCONF for the current logical network or for another logical network
- Print LCONF reports
- Read, add, update, and delete assigns
- Read, add, update, and delete params
- Update a given system name, volume name, or subvolume name for every assign in an LCONF

The LNCF screens are supported by the LNCF Requester and LNCF Server processes, which are incorporated into the BASE24 CRT access system. Like all other BASE24 file maintenance screens, security access to the LNCF screens is provided through the BASE24 CRT access system.

LNCf Screens

The following screens allow you to access the LCONF for maintenance.

LNCf Printing Screen

The LNCf Printing screen provides the main entry point into LCONF maintenance functions. From this screen, you can print all or part of the LCONF and access the Assign, Param, and Edit screens. The LNCf Printing screen is described in section 3.

LNCf Assign Screen

The LNCf Assign screen allows you to read, add, update, delete, search, and print individual assign records in the LCONF. The LNCf Assign screen is described in section 4.

LNCf Param Screen

The LNCf Param screen allows you to read, add, update, delete, search, and print individual param records in the LCONF. The LNCf Param screen is described in section 5.

LNCf Edit Screen

The LNCf Edit screen allows you to update a given system name, volume name, or subvolume name for every assign in the LCONF. You can use this screen when a large number of files are moved and the LCONF assigns need to be updated to reflect the new locations. The LNCf Edit screen is described in section 6.

LNCF Screen Access

The LNCF data entry screens are accessed from the Base Product Menu, which can be accessed from the BASE24 Virtual Menu. The LNCF entry provides access to the LNCF Printing screen, which in turn, provides access to all the other LNCF data entry screens. On the Base Product Menu, you will only see the entries available to you. A sample Base Product Menu listing all possible entries is shown below. The order in which the entries are displayed is dependent on the order in which you were given access to them.

You can access an entry listed on the menu by placing the cursor beside an individual item and pressing the **F1** key. You can also access an entry listed on the menu by typing the file acronym in the FILE DESTINATION field at the bottom of the screen and pressing the **F1** key. More detailed instructions for accessing screens are provided in the *BASE24 CRT Access Manual*.

```
BASE24-ADMN  MENU                      LLLL      MM/DD/YY  HH:MM  01 OF 01
                        B A S E  P R O D U C T  M E N U

      APCF           ARF           ATT           CAF
      CPF           ECF           EMF           ERF
      HCF           ICF           ICFE          IDF
      IPCF          KEYA          KEYD          KEY6
      KEYF          KEYI          LNCF          NCSP
      NEG           PBF           PDF           PRE
      SEC           SPF           STF           SURF
      TCF           TKN           UAF
```

```
***** BASE24 *****
                        FILE DESTINATION:
F1-ENTER DATA  F9-NEXT PAGE  F11-PREVIOUS PAGE  F10-PRINT  F12-HELP
```

Function Keys

The standard BASE24 function keys are used on LNCf maintenance screens. These function keys are described in the ***BASE24 CRT Access Manual***. When the use of these keys differs for a particular LNCf screen, the differences are noted in the section of the manual that describes the screen.

BASE24 products also provide an online Help screen which lists the function keys that apply on each screen. The Help screen is displayed by pressing the **F12** key.

Help Screens

BASE24 products provide online Help screens that list the function keys that apply on each screen. The Help screens are displayed by pressing the **F12** key.

Help screens are not available for the Logon screen or the Virtual Menu. However, the function keys that are available on these screens are listed at the bottom of the screens.

An example of a Help screen for the LNCf Printing screen is shown below.

```
BASE24-BASE LOGICAL NET CONFIG FILE LLLL YY/MM/DD HH:MM 01 OF 04
FUNCTION KEYS FOR 6520/6530 (3270)
```

```

      F1 (ENTER) - SELECT ITEM TYPE
      F7 (PF7)  - GOTO NEW PAGE
      F8 (PF8)  - CLEAR SCREEN
      F9 (PF9)  - NEXT SCREEN
      F10 (PF10) - PRINT SCREEN
      SF10 (PA1) - GENERATE REPORT
      F11 (PF11) - PREVIOUS SCREEN
      F12 (PF12) - DISPLAY HELP SCREEN
      F13 (PF13) - CHANGE CURRENT LOGICAL NET
      F16 (PF16) - EXIT OR GOTO FILE
      SF16 (PA2) - LOGOFF
```

```
***** BASE24 *****
NEW PAGE:          FILE DESTINATION:          NEW LOGICAL NETWORK ID:
ANY FUNCTION KEY EXCEPT SF9-SF16, F10, OR F16 RETURNS. F10 PRINTS AND RETURNS
```

ACI Worldwide, Inc.

3: LNCF Printing Screen

The LNCF Printing screen (LNCF screen 1) provides the initial point of access to the Logical Network Configuration File (LCONF) and allows you to perform several general operations. These operations include the following:

- Displaying the LNCF Assign, LNCF Param, and LNCF Edit screens
- Specifying where LCONF reports are to be printed
- Generating LCONF reports

This section describes the LNCF Printing screen and its function keys, along with the various procedures that you can perform from the screen.

Function Keys

The use of two function keys on the LNCf Printing screen varies from the standard function keys explained in the ***BASE24 Base Files Maintenance Manual*** and the ***BASE24 CRT Access Manual***. The use of these function keys is explained below.

The first column shows the BASE24 function keys. The second column describes the functions that can be accomplished with these keys.

Key	Description
F1	Select Item Type — Displays the LNCf screen specified by the value entered in the ITEM TYPE field.
Shift-F10	Generate Report — Prints all appropriate assigns and params in the file depending on the values entered in the ITEM TYPE and ENTER DESIRED USAGE CODES fields. Note: A hyphen connecting two keys indicates that the keys are to be pressed simultaneously. For example, Shift-F10 indicates that the Shift and F10 keys are pressed at the same time.

Screen Description

After you select the LNCF entry on the Base Product Menu or enter LNCF in the FILE DESTINATION field of a BASE24 screen, the LNCF Printing screen is displayed. The LNCF Printing screen is shown below, followed by descriptions of its fields.

```

BASE24-BASE  LOGICAL NET CONFIG FILE  LLLL          YY/MM/DD  HH:MM  01 OF 04

                                LNCF PRINTING

FILE-NAME:  \SYS1.$DATA.PRO1CNTL.L1CONF
ITEM TYPE:  A   (A)SSIGN, (P)ARAM, (E)DIT
REPORT LOCATION:  $S.#LCONF

ENTER DESIRED USAGE CODES (USED FOR PRINTING ONLY):

____ _
____ _
____ _
____ _
____ _
____ _

SF10 USES 'ITEM TYPE' AND/OR 'USAGE CODES' TO DETERMINE REPORT CONTENT

***** BASE24 *****
NEW PAGE:          FILE DESTINATION:          NEW LOGICAL NETWORK ID:
F1 - SELECT ITEM TYPE          SF10 - GENERATE REPORT          F12-HELP

```

FILE-NAME — The fully qualified name of an LCONF to be accessed. This field defaults to the LCONF for the current logical network. Unlike most BASE24 file maintenance screens, you do not have to be logged on to the same logical network as the LCONF you want to access. Thus, you can enter the fully qualified name of any LCONF on the system, without having to change to that logical network, or even if the LCONF is not associated with a logical network.

Field Length: 1–35 alphanumeric characters
 Required Field: Yes
 Default Value: The fully qualified name of the LCONF for the current logical network.

ITEM TYPE — A code indicating the type of screen to access or the type of information to be sent to the printer. Values are as follows:

A = Assign
E = Edit
P = Param

Note: The **SF10** keys are not valid when used in conjunction with the value E.

Field Length: 1 alphabetic character
Required Field: Yes, except when printing an LCONF report.
Default Value: A

REPORT LOCATION — The spooler, terminal, or file location to which report information is sent. The value of the LCONF-RPT-LOC assign determines the value displayed in this field when you initially access the LCONF. If the LCONF-RPT-LOC assign is not used, this field displays a value of \$\$.#LCONF.

You can temporarily override the print location displayed for the current session by entering a different value in this field.

Note: If you generate more than one report to the same print location, the reports are concatenated.

Field Length: 1–35 alphanumeric characters
Required Field: No
Default Value: LCONF-RPT-LOC assign value or \$\$.#LCONF

ENTER DESIRED USAGE CODES (USED FOR PRINTING

ONLY) — The BASE24 usage code fields. These fields are used exclusively when printing assigns or params. They are not used for any other processing.

You can add your own usage codes or modify existing usage code values by editing the usage code values in the prod_ind_nam_tbl in the BAxxAFT.LNCFTBLS file, where xx is the number of the current release, and recompiling the LNCf Server process. Usage codes must be entered in all uppercase characters in this table and the LNCf Server process must be recompiled before you can use the new usage codes in this field. If you enter a usage code that is not defined in this table, the message “INVALID USAGE CODE. VERIFY INPUT” is displayed on the screen.

The following usage codes have been defined for BASE24 applications:

ATM	= BASE24-atm
BASE	= BASE24 Base
BPAY	= BASE24-billpay
CARD	= BASE24-card
CHKA	= BASE24-check auth
CHKD	= BASE24-refunds Check Disbursement
CORE	= BASE24 ITS Core objects
CUST	= BASE24 Customer Service
EMV	= Europay/MasterCard/Visa
FHM	= BASE24-from host maintenance
FRSH	= BASE24-frequent shopper
INV	= BASE24-inventory
KNL	= BASE24 ITS Kernel and Integrated Endpoint (IEP) objects
MAIL	= BASE24-mail
NCD	= BASE24-atm Non-Currency Dispense
POS	= BASE24-pos
PRM	= ACI Proactive Risk Manager components
RFND	= BASE24-refunds
SSB	= BASE24-atm self-service banking
TB	= BASE24-telebanking
TLR	= BASE24-teller
****	= Operator functions, undefined

Field Length:	2–4 alphabetic characters
Occurs:	105 times
Required Field:	No
Default Value:	No default value

Procedures

The following describes the various procedures you can perform from the LNCf Printing screen.

Displaying the LNCf Assign, LNCf Param, or LNCf Edit Screen

To display the LNCf Assign, LNCf Param, or LNCf Edit screen from the LNCf Printing screen, perform the following steps:

1. Verify that the FILE-NAME field contains the name of the LCONF you want to access, and change it if necessary. This field defaults to the LCONF for the current logical network.
2. Enter the appropriate code in the ITEM TYPE field. Valid values are as follows:
A = Access the LNCf Assign screen (LNCf screen 2)
P = Access the LNCf Param screen (LNCf screen 3)
E = Access the LNCf Edit screen (LNCf screen 4)
3. Verify that the REPORT LOCATION field contains the name of the spooler location to which you want to send reports, and change it if necessary. If you do not intend to produce reports, you can enter blanks in this field.
4. Press the **F1** key.

The terminal displays the requested screen. If an error occurs, an error message is displayed on the screen, and the cursor is placed in the field in question.

Note: You can also access the LNCf Assign, Param, and Edit screens by using the **F9** and **F11** keys to move forward and backward among LNCf screens 1 through 4.

Sending Reports to a Spooler Location

To send a report to a spooler location from the LNCf Printing screen, perform the following steps:

1. Verify that the FILE-NAME field contains the name of the LCONF you want to access, and change it if necessary. This field defaults to the LCONF for the current logical network.

2. Enter the appropriate alphabetic character in the ITEM TYPE field. If you want to generate a report of the entire LCONF, this field must be blank; otherwise, you must enter the value A (for assigns only) or P (for params only).
3. Verify that the REPORT LOCATION field contains the name of the spooler location to which you want to send the reports, and change it if necessary.
4. Verify that the ENTER DESIRED USAGE CODES fields specify the usage codes you want to be reported. If you want a report of the entire LCONF, these fields should remain blank; otherwise, enter one or more appropriate usage codes to produce reports of assigns or params associated with one or more usage codes.
5. Press the **Shift-F10** keys to generate the LCONF report.

If a report is sent to the spooler location, the system returns the message “Print completed O.K. xxx record(s) printed.” Otherwise, an error message is displayed, and the cursor is placed in the field in question.

LCONF Reports

From the LNCF Printing screen, you can request reports containing all of the assigns and params in the LCONF, only the assigns, only the params, all the assigns and params by usage codes, only the assigns by usage codes, or only the params by usage codes. Assigns are printed on the Assign Report and params are printed on the Params Report. Both of these reports include indexes.

You can print out individual assign and param descriptions by reading the assign or param on the LNCF Assign or LNCF Param screens and pressing the **F10** key. A screen print is sent to the spooler location.

Assign Report

The following is an example of the Assign report for the LCONF. The format of each assign listed on the report is the same. Assigns are reported in alphabetical order by assign name. Field descriptions are provided following the example.

```

PAGE    1  \SYS.$DATA.PRO1DATA.LCONF          DD, YYYY - HH:MM:SS A.M.
          LOGICAL NETWORK CONFIGURATION FILE
-----
Assign Name: *.ACCOUNT-NUM-RPT
Location/ID: \B24.$S.#ACCT
Usage Codes: BASE, CARD
Comments: REPORT LOCATION (SPOOLER) FOR THE BASE24-CARD 5.1 ACCOUNT
          NUMBER REPORT.
Timestamp: YY/MM/DD  HH:MM
-----
Assign Name: *.ADRT
Location/ID: \B24.$DATA.PRO1DATA.ADRT
Usage Codes: TB
Comments: THE FULLY-QUALIFIED FILE NAME OF THE ADDRESS/PHONE NUMBER TABLE.
          USED BY THE ADRT SERVER AND THE EMT BUILD PROCESS.
Timestamp: YY/MM/DD  HH:MM
-----
Assign Name: *.ALT-COLL
Location/ID: \B24.$0
Usage Codes: KNL, TB
Comments: THE FULLY-QUALIFIED PPD NAME OF THE ALTERNATE EMS COLLECTOR.
          USED BY THE FOLLOWING: EXTENDED MEMORY TABLE BUILD, SQL REFRESH
          PROCESS, BASE24-TELEBANKING ISSUER REPORTING PROGRAM, AND
          EVENT OBJECT.
Timestamp: YY/MM/DD  HH:MM
-----

```

Assign Name — The name of the assign. This is the value entered in the ASSIGN NAME field on the LNCf Assign screen. This field is displayed for every assign.

If the assign is associated with a process, the symbolic name of the process (for example, P1A^EXTR) and a period are prefixed to the assign name; otherwise, an asterisk and period (for example, *.) are prefixed to the assign name. Assigns associated with a specific process are placed at the end of the report.

For the BASE24-billpay product, assign names can also be prefixed with a program name or server class, and a period.

Location/ID — The value of the assign. This is the value entered in the LOCATION/ID field on the LNCf Assign screen. This field is displayed for every assign.

Template File — The value of a template file for this assign. This is the value entered in the TEMPLATE FILE field on the LNCF Assign screen. This field is displayed only if a template file was specified for the assign.

Usage Codes — The usage codes for applications that use this assign. These are the values entered in the USAGE CODES fields on the LNCF Assign screen. This field is displayed only if at least one usage code was specified for the assign.

Comments — Up to four lines of user-defined comments for the assign. This is the information entered in the COMMENTS field on the LNCF Assign screen. If no comments were entered, this field is not displayed.

User Field — An additional user data area that may be required for a given assign. It is a generic field for assigns that require additional information. (For example, for Atalla security devices, this field indicates the model type: A4 or NSP). This is the value entered in the USER FIELD on the LNCF Assign screen. If a user field value was not entered, this field is not displayed. Note that this field is not displayed in the example.

Timestamp — The date and time, in YY/MM/DD hh:mm format, this assign was entered or last updated. This field is displayed for every assign.

Index of LCONF Assigns

At the end of the Assign report, an index is provided for all assigns included in the report. Assigns are indexed in alphabetical order by assign name. An example of the assign index is shown below, followed by descriptions of its fields.

PAGE	nn \SYS.\$DATA.PRO1DATA.LCONF	DD, YYYY - HH:MM:SS A.M.
INDEX OF LNCF ASSIGNS		
Assign Name	Process Name	Page

ACCOUNT-NUM-RPT	*	1
ADRT	*	1
ALT-COLL	*	1

Assign Name — The name of an assign included in this report.

Process Name — The symbolic name of a process associated with this assign. For the BASE24-billpay product, this field can also display a program or server class name associated with the assign. If no process, program, or server class is associated with the assign, an asterisk (*) is displayed.

Page — The page number of the report where the assign description can be found.

Param Report

The following is an example of the Param report for the LCONF. The format of each param listed on the report is the same. Params are reported in alphabetical order by param name. Field descriptions are provided following the example.

```

PAGE    1  \SYS.$DATA.PRO1DATA.LCONF          DD, YYYY - HH:MM:SS A.M.
          LOGICAL NETWORK CONFIGURATION FILE
-----
Param Name: *.ACCT-NUM-TYP
Text: D
Usage Codes: BASE, ATM, POS, TLR, FHM
Comments: INDICATES THE FORMAT OF ACCOUNT NUMBERS. VALUES: B - BINARY (UP
TO 28 DIGITS) D - DECIMAL (UP TO 19 DIGITS). USED BY ADMN, CAF,
CHF,NEG,NBF,PBF,PRDF,PTLF,SPF,TTLF,& WHFF SERVERS,ATM SETL,EXTR,
REFR,DH/RTR*/AUTH,REPORTS,BIC ANSI/ISO,AND FHM PROCESS.
Timestamp: YY/MM/DD  HH:MM
-----
Param Name: *.ALT-TIM-LMT
Text: 300
Usage Codes: KNL, TB
Comments: THE AMOUNT OF TIME (IN HUNDREDTHS OF SECONDS) TO WAIT FOR I/OS
TO COMPLETE ON THE ALTERNATE EMS COLLECTOR.  VALID VALUES ARE 0
- 2147483647. USED BY EMT BUILD UTILITY, TELEBANKING ISSUER
REPORTING PROGRAM, EVENT OBJECT, SQL REFRESH.
Timestamp: YY/MM/DD  HH:MM
-----
Param Name: *.APCFEMT-WARM
Text: P1A^ATAUTH06
Timestamp: YY/MM/DD  HH:MM
-----
Param Name: *.APCFEMT-WARM01
Text: P1A^ATAUTH07
Timestamp: YY/MM/DD  HH:MM
-----

```

Param Name — The name of the param. This is the value entered in the PARAM NAME field on the LNCf Param screen. This field is displayed for every param.

If the param is associated with a process, the symbolic name of the process (for example, P1A^EXTR) and a period are prefixed to the param name; otherwise, an asterisk and period (for example, *.) are prefixed to the param name. Params associated with a specific process are placed at the end of the report.

For the BASE24-billpay product, param names can also be prefixed with a program name or server class, and a period.

Text — The value of the param. This is the value entered in the TEXT field on the LNCF Param screen. This field is displayed for every param.

Usage Codes — The usage codes for applications that use this param. These are the values entered in the USAGE CODES fields on the LNCF Param screen. This field is displayed only if at least one usage code was specified for the param.

Comments — Up to four lines of user-defined comments for the assign. This is the information entered in the COMMENTS field on the LNCF Param screen. If no comments were entered, this field is not displayed.

Timestamp — The date and time, in YY/MM/DD hh:mm format, this param was entered or last updated. This field is displayed for every param.

Index of LCONF Params

At the end of the Param report, an index is provided for all params included in the report. Params are indexed in alphabetical order by param name. An example of a param index is shown below, followed by descriptions of its fields.

PAGE	nn \SYS.\$DATA.PRO1DATA.LCONF	DD, YYYY - HH:MM:SS A.M.
INDEX OF LNCF PARAMS		
Param Name	Process Name	Page
-----	-----	-----
ACCT-NUM-TYP	*	1
ALT-TIM-LMT	*	1
APCFEMT-WARM	*	1
APCFEMT-WARM01	*	1

Param Name — The name of a param included in this report.

Process Name — The symbolic name of a process associated with this param. For the BASE24-billpay product, this field can also display a program or server class name associated with the param. If no process, program, or server class is associated with the param, an asterisk (*) is displayed.

Page — The page number of the report where the param description can be found.

ACI Worldwide, Inc.

4: LNCF Assign Screen

The LNCF Assign screen allows you to perform various operations on assigns in the LCONF. These operations include the following:

- Reading an assign
- Searching for an assign
- Updating an assign
- Adding an assign
- Deleting an assign
- Printing an assign

This section describes the LNCF Assign screen and its function keys, along with the various procedures that you can perform from the screen.

Function Keys

The use of three function keys on the LNCf Assign screen varies from the standard function keys explained in the ***BASE24 Base Files Maintenance Manual*** and the ***BASE24 CRT Access Manual***. The use of these function keys is explained below.

The first column of information below shows the BASE24 keys. The second column describes the functions that can be accomplished with these keys.

Key	Description
F1	Validate Data or Continue Search — If a search is currently running, this key searches for the next match. Otherwise, it validates data.
Shift-F2	Search-For-Match — Searches for assigns that contain the character string entered in the ASSIGN NAME field. After the first match is found, press the F1 key to find the next match and all subsequent matches. Press the F16 key to terminate the search. Note: A hyphen connecting two keys indicates that the keys are to be pressed simultaneously. For example, Shift-F2 indicates that the Shift and F2 keys are pressed at the same time.
F16	Exit or Go to File — If a search is currently running, this key stops the search. If a search is currently running and the FILE DESTINATION field contains a valid value, this key stops the search and exits to the specified destination. Otherwise, this key provides standard functionality.

Screen Description

The LNCF Assign screen is shown below, followed by descriptions of its fields.

```

BASE24-BASE  LOGICAL NET CONFIG FILE  LLLL          YY/MM/DD  HH:MM  02 OF 04
                                LNCF ASSIGN SCREEN
                                READ BY: *****
                                ASSIGN NAME:
                                LOCATION/ID:
                                TEMPLATE FILE:
USAGE CODES:
____
____
____
____
____
____
____
____
COMMENTS:

USER FIELD:

***** BASE24 *****
NEW PAGE:          FILE DESTINATION:          NEW LOGICAL NETWORK ID:
SF2 - SEARCH-FOR-MATCH          F12-HELP

```

READ BY — The symbolic name of a process for those assigns associated with a specific process. For example, all Store-and-Forward Files (SAFs) must have a Host Interface or Interchange Interface process name associated with them.

For the BASE24-billpay product, this field can also be used to associate an assign to one or more program names or server classes depending on whether the server process runs under XPNET or Pathway. If an assign is used by more than one type of BASE24-billpay program or server class, the value BILLPAY should be used in this field. If an assign is used by all processes for a particular BASE24-billpay program or all server processes in a server class, the generic program name (for example, ACHCLEAR) or server class name (for example, STI) should be used. If an assign is used by a particular program or server process, the specific program name (for example, ACHCLEAR1) or server process name should be used. Refer to section 9 for the information to place in this field when a program name, server class name, or the value BILLPAY is required for the BASE24-billpay product.

This field accepts all alphanumeric characters and the following special symbols: caret (^), hyphen (-), and underbar (_).

Note: The value entered in the READ BY field becomes part of the key to the assign record. This allows for defining multiple versions of a particular assign record with unique settings for the individual processes, programs, or server classes that use them. This also means that the value of this field cannot be changed for a given record. To change the value of this field, you must create a new record and then delete the old one.

Field Length: 0–16 alphanumeric characters
Required Field: No
Default Value: *****
Data Name: LCONF.LCONF-KEY.PRO-NAME

ASSIGN NAME — The name of the assign. Examples are NEG, IDF, and SAF. A logical file name consists of alphanumeric characters and the special symbols (^), (-) and (_).

Field Length: 1–32 alphanumeric characters
Required Field: Yes, except when using the **F6** key.
Default Value: No default value
Data Name: LCONF.LCONF-KEY.ITEM-NAME

LOCATION/ID — The value associated with the assign. Refer to sections 7 through 16 for the information required in this field for each assign.

Field Length: 0–35 alphanumeric characters
Required Field: Yes, when using the **F3** and **F5** keys.
Default Value: No default value
Data Name: LCONF.ASSIGN-MSG.FILE-NAME

TEMPLATE FILE — The fully qualified file name of the template file associated with this assign. Template files are used by the system to routinely create and recreate files. The template file is used as a model for establishing the attributes of the new file. If a template file is required or optional for a specific assign, it is noted as such in the description of the assign.

The value entered in this field must be different from the value entered in the LOCATION/ID field.

If the template file is not present, some processes use the current active file as a template. Other processes require that the template file exist.

Field Length: 0–35 alphanumeric characters
Required Field: No, unless the file is created programmatically.
Default Value: No default value
Data Name: LCONF.ASSIGN-MSG.TEMPLATE

USAGE CODES — The usage codes indicating the applications that use the assign. These codes are used only when printing LCONF assigns from the LNCF Printing screen. Refer to the ENTER DESIRED USAGE CODES field description in section 3 for a list of valid usage codes.

Field Length: 2–4 alphabetic characters
Occurs: 105 times
Required Field: No
Default Value: No default value
Data Name: LCONF.PROD-IND
LCONF.PROD-IND-ADNL

COMMENTS — A free-format area for assign descriptions or miscellaneous documentation for informational purposes. Information in this field is left-justified.

Field Length: 0–64 alphanumeric characters
Occurs: 4 times
Required Field: No
Default Value: No default value
Data Name: LCONF.COMMENTS

USER FIELD — A text field used for additional information required for some assigns. For example, a security device may require that a model number be entered in this field.

Field Length: 0–35 alphanumeric characters
Required Field: No
Default Value: No default value
Data Name: LCONF.ASSIGN-MSG.USER-FIELD

Procedures

The following describes the various LNCF Assign screen procedures that you can perform.

Displaying the Assign Screen

To display the LNCF Assign screen, perform one of the following:

- Enter the letter A in the ITEM TYPE field on the LNCF Printing screen and press the **F1** key.
- Use the **F9** and **F11** keys to navigate to the LNCF Assign screen from any other LNCF screen.

For a description of the LNCF Printing screen, refer to section 3.

Searching for an Assign

To search for an assign from the LNCF Assign screen, perform the following steps:

1. Enter a portion of the assign name in the ASSIGN NAME field. (Placing a value in the READ BY field is not allowed).
2. Press the **Shift-F2** keys. The first assign in the LCONF containing the portion of the assign name that you entered is displayed on the screen.
3. Press the **F1** key to search for the next match and all subsequent matches.
4. Press the **F16** key to terminate the search. At the end of a search, the system returns the message “End of search.”

Reading a Specific Assign

To read a specific assign from the LNCF Assign screen, perform the following steps:

1. Enter the process name, program name, or server class value of the assign that you want to read in the READ BY field. If the assign is not associated with a process, program, or server class, you can leave asterisks in the field.

2. Enter the name of the assign in the ASSIGN NAME field. Refer to sections 7 through 16 for all assign names.
3. Press the **F2** key.

If the record exists in the LCONF, the system returns the record information to the screen and the message “Record Read O.K.” is displayed. Otherwise, an error message is displayed, and the cursor is placed in the field in question.

Reading Forward Through Multiple Assigns

To read through multiple assigns, in alphabetical order, from the LNCF Assign screen, perform the following steps:

1. Identify the record at which you want to start reading by performing one of the following steps.
 - To start at the beginning of the LCONF, place asterisks in the READ BY field and leave the ASSIGN NAME field blank.
 - To start with a specific record, enter a process name, program name, or server class value in the READ BY field (if needed) and a full or partial assign name in the ASSIGN NAME field.
 - To read assigns associated with a specific process, program, or server class, place the process, program, or server class name value in the READ BY field and leave the ASSIGN NAME field blank.
2. Press the **F6** key. If the next assign is read, the information on the next assign is displayed on the screen; otherwise, an error message is displayed, and the cursor is placed in the field in question.
3. Press the **F6** key to continue reviewing the assigns in alphabetical order.

Updating an Assign

To update an assign from the LNCF Assign screen, perform the following steps:

1. Read the assign to be updated.
2. Enter the fields to be updated. The following fields can be updated:
 - LOCATION/ID
 - TEMPLATE FILE
 - USAGE CODES

- COMMENTS
 - USER FIELD
3. Verify that the information on the screen is correct and complete.
 4. Press the **F5** key.

If the record was updated, the system returns the message “Record updated O.K.”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Adding an Assign

To add a new assign from the LNCF Assign screen, perform the following steps:

1. Enter the process, program, or server class name associated with this assign in the READ BY field. If an assign is not associated with a specific process, program, or server class, you can place asterisks in this field. Refer to sections 7 through 16 to determine whether an associated process, program, or server class name must be entered for the assign.
2. Enter the name of the assign in the ASSIGN NAME field.
3. Enter the value to be associated with the assign in the LOCATION/ID field. It is best to fully qualify this information wherever possible. Refer to sections 7 through 16 to determine the value to enter for the assign.
4. Determine if a value must be entered in the TEMPLATE FILE field for the assign being added by referencing the documentation on the specific assign.
5. Enter the appropriate usage codes in the USAGE CODES fields. The usage codes of the applications that access the file should be entered, so you can generate reports by usage code. Refer to section 3 for a list of valid usage codes.
6. Enter pertinent information in the COMMENTS field.
7. Enter any user data required for the assign in the USER FIELD. Refer to sections 7 through 16 to determine whether specific user data is required for the assign.
8. Verify that the information on the screen is correct and complete.
9. Press the **F3** key.

If the assign was added to the LCONF, the system returns the message “Record added O.K.”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Deleting an Assign

To delete an assign from the LNCF Assign screen, perform the following steps:

1. Read the assign to be deleted.
2. Verify that the information read is the information to be deleted.
3. Press the **F4** key.

If the assign record was deleted, the system returns the message “Record deleted”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Sending an Assign to a Spooler Location

To send an individual assign to a spooler location from the LNCF Assign screen, perform the following steps:

1. Read the assign to be printed.
2. Verify that the information read is the information to be printed.
3. Press the **F10** key.

If the assign record was sent to the spooler location, the system returns the message “Print completed O.K.”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Exiting from the LNCF Assign Screen

Press the **F16** key from the LNCF Assign screen to return to the previous screen or menu. Press the **Shift-F16** keys from the LNCF Assign screen to log off the CRT access system.

ACI Worldwide, Inc.

5: LNCF Param Screen

The LNCF Param screen allows you to perform various operations on params in the LCONF. These operations include the following:

- Reading a param
- Searching for a param
- Updating a param
- Adding a param
- Deleting a param
- Printing a param

This section describes the LNCF Param screen and its function keys, along with the various procedures that you can perform from the screen.

Function Keys

The use of three function keys on the LNCf Param screen varies from the standard function keys explained in the *BASE24 Base Files Maintenance Manual* and the *BASE24 CRT Access Manual*. The use of these function keys is explained below.

The first column of information below shows the BASE24 keys. The second column describes the functions that can be accomplished with these keys.

Key	Description
F1	Validate Data or Continue Search — If a search is currently running, this key searches for the next match. Otherwise, it validates data.
Shift-F2	Search-For-Match — Searches for params that contain the character string entered in the PARAM NAME field. After the first match is found, press the F1 key to find the next match and all subsequent matches. Press the F16 key to terminate the search. Note: A hyphen connecting two keys indicates that the keys are to be pressed simultaneously. For example, Shift-F2 indicates that the Shift and F2 keys are pressed at the same time.
F16	Exit or Go to File — If a search is currently running, this key stops the search. If a search is currently running and the FILE DESTINATION field contains a valid value, this key stops the search and exits to the specified destination. Otherwise, this key provides standard functionality.

Screen Description

The LNCF Param screen is shown below, followed by descriptions of its fields.

```

BASE24-BASE LOGICAL NET CONFIG FILE LLLL YY/MM/DD HH:MM 03 OF 04
                LNCF PARAM SCREEN
    READ BY: *****
    PARAM NAME:
    TEXT:

    USAGE CODES:
    _____
    _____
    _____
    _____
    _____
    _____
    _____
    _____
    COMMENTS:

***** BASE24 *****
NEW PAGE:          FILE DESTINATION:          NEW LOGICAL NETWORK ID:
SF2 - SEARCH-FOR-MATCH          F12-HELP
                                0000

```

READ BY — The symbolic name of a process for those params associated with a specific process.

For the BASE24-billpay product, this field can also be used to associate a param to one or more program names or server classes depending on whether the server process runs under XPNET or Pathway. If a param is used by more than one type of BASE24-billpay program or server class, the value BILLPAY should be used in this field. If a param is used by all processes for a particular BASE24-billpay program or all server processes in a server class, the generic program name (for example, ACHCLEAR) or server class name (for example, STI) should be used. If a param is used by a particular program or server process, the specific program name (for example, ACHCLEAR1) or server process name should be used. Refer to section 9 for the information to place in this field when a program name, server class name, or the value BILLPAY is required for the BASE24-billpay product.

This field accepts all alphanumeric characters and the special symbols: caret (^), hyphen (-), and underbar (_).

Note: The value entered in the READ BY field becomes part of the key to the param record. This allows for defining multiple versions of a particular param record with unique settings for the individual processes, programs, or server classes that use them. This also means that the value of this field cannot be changed for a given record. To change the value of this field, you must create a new record and then delete the old one.

Field Length: 0–16 alphanumeric characters
Required Field: No
Default Value: *****
Data Name: LCONF.LCONF-KEY.PRO-NAME

PARAM NAME — The name of the param.

This field accepts all alphanumeric characters and the special symbols (^), (-) and (_).

Field Length: 1–32 alphanumeric characters
Required Field: Yes, except when using the **F6** key.
Default Value: No default value
Data Name: LCONF.LCONF-KEY.ITEM-NAME

TEXT — The value associated with the param. Refer to sections 7 through 15 for the information required in this field for each param.

Field Length: 1–78 alphanumeric characters
Required Field: Yes, when using the **F3** and **F5** keys.
Default Value: No default value
Data Name: LCONF.PARAM-MSG.PTXT

USAGE CODES — The usage codes, indicating the applications that use the param. These codes are used only when printing LCONF params from the LNCF Printing screen. Refer to the ENTER DESIRED USAGE CODES field description in section 3 for a list of valid usage codes.

Field Length: 2–4 alphanumeric characters
Occurs: 105 times

Required Field: No
Default Value: No default value
Data Name: LCONF.PROD-IND
LCONF.PROD-IND-ADNL

COMMENTS — An unstructured text field for comments that provide additional information about the param. Information in this field is left-justified and blank-filled.

Field Length: 0–64 alphanumeric characters
Occurs: 4 times
Required Field: No
Default Value: No default value
Data Name: LCONF.COMMENTS

Procedures

The following describes the various LNCF Param screen procedures that you can perform.

Displaying the LNCF Param Screen

To display the LNCF Param screen, perform one of the following:

- Enter the letter **P** in the ITEM TYPE field on the LNCF Printing screen and press the **F1** key.
- Use the **F9** and **F11** keys to navigate to the LNCF Param screen from any other LNCF screen.

For a description of the LNCF Printing screen, refer to section 3.

Searching for a Param

To search for a param from the LNCF Param screen, perform the following steps:

1. Enter a portion of the param name in the PARAM NAME field.
2. Press the **Shift-F2** keys. The first param in the LCONF containing the portion of the param name that you entered is displayed on the screen.
3. Press the **F1** key to search for the next match and all subsequent matches.
4. Press the **F16** key to terminate the search. At the end of a search, the system returns the message “End of search.”

Reading a Specific Param

To read a specific param from the LNCF Param screen, perform the following steps:

1. Enter the process, program, or server class name value of the param that you want to read in the READ BY field. If the param is not associated with a specific process, program, or server class, you can leave asterisks in the field.
2. Enter the name of the param in the PARAM NAME field. Refer to sections 7 through 16 for all param names.

3. Press the **F2** key.

If the record exists in the LCONF, the system returns the record information on the screen and the message “Record Read O.K.” is displayed; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Reading Forward Through Multiple Params

To read through multiple params, in alphabetical order, from the LNCF Param screen, perform the following steps.

1. Identify the record at which you want to start reading by performing one of the following steps.
 - To start at the beginning of the LCONF, place asterisks in the READ BY field and leave the PARAM NAME field blank.
 - To start with a specific record, enter a process, program, or server class name value in the READ BY field (if needed) and a full or partial param name in the PARAM NAME field.
 - To read params associated with a specific process, program, or server class, place the process, program, or server class name value in the READ BY field and leave the PARAM NAME field blank.
2. Press the **F6** key. If the param is read, the information on the param is displayed on the screen; otherwise, an error message is displayed, and the cursor is placed in the field in question.
3. Press the **F6** key to continue reviewing the params in alphabetical order.

Updating a Param

To update a param, perform the following steps:

1. Read the param to be updated.
2. Enter the fields to be updated. The following fields can be updated:
 - TEXT
 - USAGE CODES
 - COMMENTS

3. Verify that the information on the screen is correct and complete.
4. Press the **F5** key.

If the record was updated, the system returns the message “Record updated O.K.”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Adding a Param

To add a new param from the LNCF Param screen, perform the following steps:

1. Enter the name of the process, program, or server class associated with this param in the READ BY field. If a param is not associated with a specific process, program, or server class, you can place asterisks in this field. Refer to sections 7 through 16 to determine whether an associated process, program, or server class name must be entered for the param.
2. Enter the name of the param in the PARAM NAME field.
3. Enter the value of the param in the TEXT field. Refer to sections 7 through 16 to determine the value to enter for the param.
4. Enter appropriate usage codes in the USAGE CODES fields. The applications that use the param should be entered so that you can generate separate reports by usage code.
5. Enter pertinent information in the COMMENTS field.
6. Verify that the information on the screen is correct and complete.
7. Press the **F3** key.

If the param was added to the LCONF, the system returns the message “Record added O.K.”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Deleting a Param

To delete a param from the LNCF Param screen, perform the following steps:

1. Read the param to be deleted.
2. Verify that the information read is the information to be deleted.
3. Press the **F4** key.

If the param record was deleted, the system returns the message “Record deleted”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Sending a Param to a Spooler Location

To send an individual param to a spooler location from the LNCF Param screen, perform the following steps:

1. Read the param to be printed.
2. Verify that the information read is the information to be printed.
3. Press the **F10** key.

If the param record was sent to the spooler location, the system returns the message “Print completed O.K.”; otherwise, an error message is displayed, and the cursor is placed in the field in question.

Exiting from the LNCF Param Screen

Press the **F16** key from the LNCF Param screen to return to the previous screen or menu. Press the **Shift-F16** keys from the LNCF Param screen to log off the CRT access system.

ACI Worldwide, Inc.

6: LNCF Edit Screen

The LNCF Edit screen allows you to update a given system name, volume name, or subvolume name for every assign in the LCONF. This screen can be used when a large number of files are being moved and the LCONF assigns need to be updated to reflect the new locations. Using this screen eliminates the need to update each of the assign records individually.

Updates from this screen affect the LOCATION/ID and TEMPLATE FILE fields in the assign records.

This section describes the LNCF Edit screen and its function keys, along with the various procedures that you can perform from the screen.

Function Keys

The use of one function key on the LNCF Assign screen varies from the standard function keys explained in the ***BASE24 Base Files Maintenance Manual*** and the ***BASE24 CRT Access Manual***. The use of this function key is explained below.

The first column of information below shows the BASE24 key. The second column describes the functions that can be accomplished with this key.

Key	Description
F1	Validate and Update — Validates data entered on the screen. If valid, this function also updates all assign records that match the data.

Screen Description

The LNCF Edit screen is shown below, followed by descriptions of its fields.

```

BASE24-BASE LOGICAL NET CONFIG FILE LLLL          YY/MM/DD HH:MM 04 OF 04
                                LNCF EDIT
This screen allows the user to perform mass ASSIGN file changes on any or all
of the following elements: SYSTEM NAME, VOLUME NAME, and/or the first four
characters of the SUBVOL NAME (e.g., PRO1xxxx to TES1xxxx).

(1) CHANGE SYSTEM NAME [          ] TO [          ]
(2) CHANGE VOLUME NAME [          ] TO [          ]
(3) CHANGE SUBVOL NAME [          ] TO [          ]

NOTE:
Only ASSIGNS which match exactly what is entered above will be changed
For example, if the user enters \SYST.$DATA1 TO \TEST.$DATA, an ASSIGN
of \SYST.$DATA1.SUBVOL.FILE would be changed, since both system and
volume names match, but \SYST.$PRO1.SUBVOL.FILE would not be changed,
since only the system name matches.

***** BASE24 *****
NEW PAGE:          FILE DESTINATION:          NEW LOGICAL NETWORK ID:
F1 - VALIDATE AND UPDATE          F12-HELP

```

CHANGE SYSTEM NAME — The current system name to be changed. The system name must begin with a backslash (\). The second character must be an alphabetic character and can be followed by up to six additional alphanumeric characters.

Field Length: 2–8 alphanumeric characters
 Required Field: No
 Default Value: No default value

TO — The new system name. The system name must begin with a backslash (\). The second character must be an alphabetic character and can be followed by up to six additional characters.

Field Length: 2–8 alphanumeric characters
 Required Field: No
 Default Value: No default value

CHANGE VOLUME NAME — The current volume name to be changed. The volume name must begin with a dollar sign (\$). The second character must be an alphabetic character and can be followed by up to six alphanumeric characters.

Field Length: 2–8 alphanumeric characters
Required Field: No
Default Value: No default value

TO — The new volume name. The volume name must begin with a dollar sign (\$). The second character must be an alphabetic character and can be followed by up to six alphanumeric characters.

Field Length: 2–8 alphanumeric characters
Required Field: No
Default Value: No default value

CHANGE SUBVOL NAME — The first four characters of the current subvolume name to be changed. Only the first four characters of the subvolume name can be changed. The subvolume name must begin with an alphabetic character, followed by three alphanumeric characters.

Field Length: 4 alphanumeric characters
Required Field: No
Default Value: No default value

TO — The first four characters of the new subvolume name. Only the first four characters of the subvolume name can be changed. The subvolume name must begin with an alphabetic character, followed by three alphanumeric characters.

Field Length: 4 alphanumeric characters
Required Field: No
Default Value: No default value

Procedures

The following describes the various LNCF Edit screen procedures that you can perform.

Displaying the LNCF Edit Screen

To display the LNCF Edit screen, perform one of the following:

- Enter the letter E in the ITEM TYPE field on the LNCF Printing screen and press the **F1** key.
- Use the **F9** and **F11** keys to navigate to the LNCF Param screen from any other LNCF screen.

For a description of the LNCF Printing screen, refer to section 3.

Updating System, Volume, or Subvolume Names

To update the system, volume, or subvolume names for all the assign records in an LCONF, perform the following steps from the LNCF Edit screen.

Note: This procedure updates the information found in both the LOCATION/ID and TEMPLATE FILE fields on the LNCF Assign screen.

1. To change the system name, enter the system name to be updated in the CHANGE SYSTEM NAME field and the new system name in the corresponding TO field.
2. To change the volume name, enter the volume name to be updated in the CHANGE VOLUME NAME field and the new volume name in the corresponding TO field.
3. To change the subvolume name, enter the first four characters of the subvolume name to be updated in the CHANGE SUBVOL NAME field and the first four characters of the new subvolume name in the corresponding TO field.
4. Press the **F1** key. A screen edit is performed and, if successful, the system response area contains the message “All formats correct; press the **F1** key to invoke changes, any other key to cancel.”

5. Verify that the fields entered are correct.
6. Press the **F1** key to make the name changes.

If the file name is updated, the system returns the message “File update complete. xxx record(s) changed”; otherwise, an error message is displayed and the cursor is placed in the field in question.

Exiting from the Edit Screen

Press the **F16** key from the LNCF Edit screen to return to the previous screen or menu. Press the **Shift-F16** keys from the LNCF Edit screen to log off the CRT access system.

7: General Assigns and Params

The following pages document the assigns and params used by two or more BASE24 products. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

This section also includes assigns and params used by Interchange Interface processes and the ISO Host Interface process.

The following usage codes identify the BASE24 applications that use an assign or param described in this section:

ATM	=	BASE24-atm
BASE	=	Multiple BASE24 products
BPAY	=	BASE24-billpay
CARD	=	BASE24-card
CHKA	=	BASE24-check auth
EMV	=	Europay, MasterCard, Visa
FHM	=	BASE24-from host maintenance
FRSH	=	BASE24-frequent shopper
KNL	=	BASE24 ITS Kernel and Integrated Endpoint (IEP) object
MAIL	=	BASE24-mail
MIGR	=	Migration from BASE24 to BASE24-eps
NETW	=	Networks First
POS	=	BASE24-pos
RFND	=	BASE24-refunds
TB	=	BASE24-telebanking
TLR	=	BASE24-teller

Assigns

The assigns in this section are general assigns because they are accessed by more than one product.

The assigns are listed in alphabetical order. Each assign includes a definition of the assign, the values to which the assign name can be linked, and the product codes of the products that access the assign.

ALT-COLL — The fully qualified PPD name of the alternate EMS Collector process. This assign is used by the following:

- Base Extended Memory Table Build utility
- ITS Kernel Extended Memory Table Build utility
- SQL Refresh process
- BASE24-telebanking Issuer Reporting program
- BASE24-pos Stored Value Dormancy/Escheatment program
- Event object

If this assign is not present in the LCONF or contains an invalid value, ITS Kernel Extended Memory Table Build utility, SQL Refresh process, BASE24-telebanking Issuer Reporting program, and the processes that contain the Event object use a default value of \$0. The Base Extended Memory Table Build utility abends without generating an event message.

Example: \B24.\$0
Usage Codes: BASE, KNL, TB

APCF — The fully qualified file name of the Acquirer Processing Code File (APCF). The APCF assign is used by the following:

- Acquirer Processing Code File Server process
- Base Extended Memory Table Build utility
- BASE24-pos Hypercom Device Handler module
- BASE24-pos Standard POS Device Handler module

If this assign is not present in the LCONF or contains an invalid value, these processes abend at initialization.

Example: \B24.\$DATA.PRO1DATA.APCF
Usage Codes: ATM, BASE, POS

APCFEMT — The fully qualified file name of the Acquirer Processing Code File (APCF) extended memory table, which contains APCF records. The following processes and modules use this assign:

Base Extended Memory Table Build utility

BASE24-atm Diebold 10XX/478X Device Handler process

BASE24-atm NCR 5XXX Device Handler process

BASE24-pos Standard POS Device Handler module

BASE24-pos Hypercom Device Handler module

BASE24-pos Router/Authorization module

Banknet Interchange Interface process

BIC ISO Interchange Interface process

MDS ISO Interchange Interface process

PLUS ISO Interchange Interface process

VisaNet ISO Interchange Interface process

If this assign is not present in the LCONF or contains an invalid value, the Base Extended Memory Table Build utility displays an error message indicating that the assign needs to be corrected, and the other processes listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.APCFEMT

Usage Codes: ATM, BASE, POS

ARF — The fully qualified file name of the Account Routing File (ARF). The ARF assign is required only if one or more FIIDs support either the BASE24-teller interbank routing feature or the BASE24-atm self-service banking (SSB) Enhanced Check Application. The ARF assign is used by the following processes:

BASE24-atm Authorization process (with the SSB Enhanced Check Application)

BASE24-teller Authorization process (with interbank routing)

Account Routing File Server process

Example: \B24.\$DATA.PRO1DATA.ARF

Usage Codes: ATM, TLR

ATT — The fully qualified file name of the Account Type Table File (ATT). The Account Type Table Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Account Type Table Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.ATT
Usage Codes: ATM, BASE, POS, TB

BNIIF — The fully qualified file name of the Banknet Institution Identifier File (BNIIF). The following processes require this assign:

Banknet Institution Identifier File Server process
Banknet Interchange Interface process

Example: \B24.\$DATA.PRO1DATA.BNIIF
Usage Codes: BASE

BNRLF — The fully qualified file name of the Banknet Request Log File (BNRLF). The following processes require this assign:

Banknet Request Log File Server process
Banknet Interchange Interface process

The Banknet Interchange Interface process uses this assign to retrieve the name of the template when creating a new BNRLF.

Example: \B24.\$DATA.PRO1DATA.BNRLF (data file name)
 \B24.\$DATA.PRO1TPLT.BNRLF (template file name)
Usage Codes: BASE
Read By: A symbolic name (for example, P1A^BNET1, P2A^BNET2)
 is required in this field for the Banknet Interchange Interface
 process.
Template File: Required because the BNRLF is created periodically by
 BASE24.

BRIDGE-NAME — The name of the Bridge-Server Emulation process. This assign allows the EPS-Net Interchange Interface process to communicate with the Bridge process that is configured with the ASSOCIATIVE ON param in the Pathway Configuration File (PATHCONF).

Example: \B24.\$DATA.XN30B24.BRIDGE
Usage Codes: BASE

CAF*identifier* — The fully qualified file name of the Cardholder Authorization File (CAF). This assign can include an optional *identifier* to specify assigns used for different CAFs in the same logical network.

The Enscribe Refresh process uses this assign to retrieve the name of the template file during full-file refreshes.

The Enscribe Refresh process first reads the Institution Definition File (IDF) for the fully qualified file name of the CAF used by all institutions in the refresh group. The Enscribe Refresh process then reads the LCONF to find a CAF assign that has a matching file name in the LOCATION/ID field. If no matching CAF assign is found, the Enscribe Refresh process abends during initialization.

If a matching CAF assign is found, the Enscribe Refresh process builds the new CAF using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.CAF (data file name)
 \B24.\$DATA.PRO1TPLT.CAF (template file name)
Usage Codes: BASE
Template File: Required to build the new file during full-file refreshes.

CPCONF — The fully qualified file name of the XPNET Command Profile Configuration file (CPConf). The Network Control Supervisor Profile Server process uses this assign.

Example: \SYS.\$DATA.PRODDATA.CPCONF
Usage Codes: BASE

CPF — The fully qualified file name of the Card Prefix File (CPF). The CPF assign is used by the following processes:

Card Prefix File Server process
Generic Simulator process

BASE24-atm Authorization process

BASE24-card Account Number Generation Server process
BASE24-card Card Management Functions Server process
BASE24-card Plastic Card Generation Server process

BASE24-pos Device Handler/Router/Authorization process

BASE24-pos Stored Value Dormancy/Escheatment program

BASE24-teller Authorization process

The BASE24-teller Authorization process uses this assign based on the setting in the TLR-PROCESS-CRD-PIN param, a param specific to BASE24-teller. See section 17 for more information on BASE24-teller assigns and params. All other processes listed above require this assign. If this assign is not present in the LCONF or contains an invalid value, these processes abend at initialization.

Example: \B24.\$DATA.PRO1DATA.CPF
Usage Codes: ATM, BASE, CARD, POS, TLR

CPFEMT — The fully qualified file name of the Card Prefix File (CPF) extended memory table, which contains CPF base segment records. The following processes use this assign:

Customer/Cardholder Information File Server process
Customer Information Screens Server process
Customer Service Transaction Perusal Server process
ITS Kernel Extended Memory Table Build utility

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility displays an error message indicating that the assign needs to be corrected, and the Customer/Cardholder Information File Server process, Customer Information Screens Server process, and Merchant Interface processes do not initialize.

Example: \B24.\$DATA.PRO1DATA.CPFEMT
Usage Codes: CUST, FRSH, KNL

DCCD — The fully qualified file name of the Dynamic Currency Conversion Data file. The following processes use this assign:

Base Extended Memory Table Build utility
Dynamic Currency Conversion Data Server process

This assign is used only with the Dynamic Currency Conversion add-on products for BASE24-atm.

Examples: \B24.\$DATA.PRO1DATA.DCCD
Usage Codes: BASE

DCCDEMT — Defines the location of the Dynamic Currency Conversion Data (DCCD) extended memory table to be used by this logical network. This assign is used only with the Dynamic Currency Conversion add-on products for the following processes and modules:

Base Extended Memory Table Build utility
BASE24-atm Authorization process

Example: \B24.\$DATA.PRO1DATA.DCCDEMT
Usage Codes: ATM, BASE

DCT-LOG — The network logging location for event messages generated by the Device Control Terminal Server process for products other than BASE24-teller.

This assign identifies Sudoterm's PPD name or \$0.

For BASE24-teller event messages, the Device Control Terminal Server process logs to the location identified in the TLR-DCT-LOG assign. See section 17 for more information on BASE24-teller assigns and params.

Examples: \B24.\$PLGR.#P1DCT
 \$SUDO
 \$0
Usage Codes: BASE

ECF — The fully qualified file name of the Extract Configuration File (ECF). The following processes use this assign:

Super Extract process
Extract Configuration File Server process
BASE24-atm Settlement Initiator process
BASE24-pos Settlement Initiator process

Example: \B24.\$DATA.PRO1DATA.ECF
Usage Codes: ATM, BASE, POS, TB, TLR

EMF — The fully qualified file name of the External Message File (EMF). The following processes use this assign:

BASE24-pos NCR NDP Device Handler process
BIC ISO Interface process
External Message File Server process

From Host Maintenance process
ISO Host Interface process
ITS Kernel Extended Memory Table Build utility

Example: \B24.\$DATA.PRO1DATA.EMF
Usage Codes: ATM, BASE, FHM, POS, TB, TLR

EMF5 — The fully qualified file name of the External Message File (EMF) for Interchange Interface processes running under release 3.4/4.0 (i.e., the BASE24-REL param is set to a value of 40). The following processes use this assign:

BIC ISO Interface process
External Message File Server process

Example: \B24.\$DATA.PRO1DATA.EMF5
Usage Codes: ATM, BASE, POS, TLR

EMT-SWAPVOL — The fully qualified name of the swap volume in which the following objects and utilities store data when building extended memory tables:

Account Access object
Base and ITS Kernel Extended Memory Table Build utilities
Transaction Security object

If this assign is not present in the LCONF or contains an invalid value, the default volume is used and an error message is generated indicating that the assign needs to be corrected.

Example: \B24.\$DATA
Usage Codes: BASE, KNL, TB

ERF — The fully qualified file name of the Exchange Rate File (ERF). The following processes use this assign:

Base Extended Memory Table Build utility
Exchange Rate File Server process

This assign is used only with the Multiple Currency add-on products for BASE24-atm and BASE24-pos.

Example: \B24.\$DATA.PRO1DATA.ERF
Usage Codes: ATM, BASE, POS

ERFEMT — Defines the location of the Exchange Rate File (ERF) extended memory table to be used by this logical network. This assign is used by the Currency Conversion utilities. This assign is used only with the Multiple Currency add-on products for the following BASE24-atm and BASE24-pos processes and modules:

Base Extended Memory Table Build utility

BASE24-atm Authorization process

BASE24-atm Diebold 10XX/478X Device Handler process

BASE24-atm NCR 5XXX Device Handler process

BASE24-pos Standard POS Device Handler module

BASE24-pos APACS 30/40 Device Handler module

BASE24-pos Router/Authorization module

Example: \B24.\$DATA.PRO1DATA.ERFEMT

Usage Codes: ATM, BASE, POS

ERIIF — The name of the EPS-Net Institution Identification File (ERIIF). If this name is not fully qualified, the system, volume, and subvolume default to where the LCONF resides. The following processes use this assign:

EPS-Net Institution Identification File (ERIIF) Server process

EPS-Net Interchange Interface processes use this assign.

Example: \B24.\$DATA.PRO1DATA.ERIIF

Usage Codes: BASE

FRLF — The fully qualified file name of the Visa File Request Log File (FRLF). The following processes require this assign:

Visa File Request Log File Server process

VisaNet ISO Interchange Interface process

Example: \B24.\$DATA.PRO1DATA.FRLF

Usage Codes: BASE

FUP-FILE-NAME — The fully qualified name of the File Utility Program (FUP) process if it is to be run from a location other than \$SYSTEM.SYSTEM.FUP. The Enscribe Refresh process uses this assign.

Example: \B24.\$SYSTEM.PRO1SYS.FUP
Usage Codes: BASE

FUP-OUTFILE-NAME — The output location for the File Utility Program (FUP) process started by the Enscribe Refresh process if it is to be sent to a location other than \$0.

Example: \$\$.#FUP
Usage Codes: BASE

GENSIM-SIMCMDS — The fully qualified file name of the simulator commands file. The Generic Simulator Interface module requires this assign.

Example: \B24.\$DATA.TES1DATA.SIMCMDS
Usage Codes: BASE

HCF — The fully qualified file name of the Host Configuration File (HCF). The following processes use this assign:

ISO Host Interface process
Host Configuration File Server process
Mail process

Example: \B24.\$DATA.PRO1DATA.HCF
Usage Codes: ATM, BASE, FHM, MAIL, POS, TB, TLR

ICF — The fully qualified file name of the Interchange Configuration File (ICF). The following processes use this assign:

BASE24-pos Daily Report program (B24POS01)
Interchange Configuration File Server process
Super Extract process
ATM and POS Transaction Analysis utilities

BCGI Interface process
BIC ISO Interface process
EPS-Net Interchange Interface process

Generic Interchange Interface process
Banknet Interchange Interface process*
BIC ISO Interchange Interface process*
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process*
PLUS ISO Interchange Interface process*
PLUS ISO Administrative Messages Server process*
VisaNet ISO Interchange Interface process*

* These Interchange Interface processes use the ICF instead of the ICFE only if running under the previous software release.

Example: \B24.\$DATA.PRO1DATA.ICF
Usage Codes: ATM, BASE, POS

ICFE — The fully qualified file name of the Enhanced Interchange Configuration File (ICFE). The following processes use this assign:

Enhanced Interchange Configuration File Server process
Super Extract process
ATM and POS Transaction Analysis utilities

Banknet Interchange Interface process
BIC ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
PLUS ISO Administrative Messages Server process
VisaNet ISO Interchange Interface process

Example: \B24.\$DATA.PRO1DATA.ICFE
Usage Codes: ATM, BASE, POS

IDF — The fully qualified file name of the Institution Definition File (IDF). The following processes and objects use this assign:

BASE24-atm Authorization process
BASE24-atm Device Handler processes
BASE24-atm report programs
BASE24-atm Settlement Initiator process

BASE24-card Card Management Functions Server process
BASE24-card Cardholder List Server process
BASE24-card Plastic Card Generation Server process

BASE24-pos Device Handler/Router/Authorization process
BASE24-pos report programs
BASE24-pos Main and Secondary Settlement processes
CAF/PBF Cleanup process (CAFPBF)
BASE24-mail ISO Host Interface process
BASE24-mail Mail process
BASE24-pos Stored Value Dormancy/Escheatment program

BASE24-telebanking Issuer Reporting program

BASE24-teller Authorization process
BASE24-teller Device Handler processes
BASE24-teller report programs
BASE24-teller Settlement Initiator process

Cardholder Authorization File Server process
Card History File Server process
Card Prefix File Server process
Device Control Terminal Server process
Interchange Configuration File Server process
Institution Definition File Server process
Negative File Server process
No Book File Server process
Positive Balance File Server process
Stop Payment File Server process
Usage Accumulation File Server process
Warning/Hold/Float File Server process

Customer/Cardholder Information File Server process
Customer Information Screens Server process

Base Extended Memory Table Build utility
Enscribe Refresh process
From Host Maintenance process
Generic Simulator process
Super Extract process
BASE24-atm, BASE24-pos, BASE24 Remote Banking, and BASE24-teller
Transaction Analysis utilities

End-of-Period Process object
ITS Kernel Extended Memory Table Build utility
Financial Institution Access object

If this assign is not present in the LCONF or contains an invalid value, the processes and programs listed above and the processes that contain the Financial Institution Access or End-of-Period Process objects do not initialize.

Example: \B24.\$DATA.PRO1DATA.IDF
Usage Codes: ATM, BASE, FHM, POS, TB, TLR

IDFEMT — The fully qualified file name of the Institution Definition File (IDF) extended memory table. The following processes, modules, and objects use this assign:

Base Extended Memory Table Build utility

BASE24-atm Diebold 10XX/478X Device Handler processes
BASE24-atm NCR 5XXX Device Handler process

Financial Institution Access object

If this assign is not present in the LCONF, the ITS Kernel Extended Memory Table Build utility and the processes that contain the Financial Institution Access object do not initialize.

Example: \B24.\$DATA.PRO1DATA.IDFEMT
Usage Codes: ATM, BASE, CORE, KNL

ILF — The fully qualified file name of the Interchange Log File (ILF). The following processes use this assign:

BCGI Interface process
BIC ISO Interchange Interface process
Banknet Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process

VisaNet ISO Interchange Interface process
EPS-Net Interchange Interface process
Super Extract process

Example: \B24.\$DATA.PRO1DATA.ILYYMMDD (data file name)
 \B24.\$DATA.PRO1TPLT.ILF (template file name)
Usage Codes: BASE
Template File: Required because the ILF is created periodically by
 BASE24.
Read By: A symbolic name (for example, P1A^BIC) is required in this
 field.

IPCF — The fully qualified file name of the Issuer Processing Code File (IPCF).
The following processes use this assign:

Issuer Processing Code File Server process
Base Extended Memory Table Build utility

If this assign is not present in the LCONF or contains an invalid value, these
processes abend at initialization.

Example: \B24.\$DATA.PRO1DATA.IPCF
Usage Codes: ATM, BASE, POS

IPCFEMT — The fully qualified file name of the Issuer Processing Code File
(IPCF) extended memory table, which contains IPCF records. The following
processes use this assign:

Base Extended Memory Table Build utility
Banknet Interchange Interface process
BIC ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

If this assign is not present in the LCONF or contains an invalid value, the Base
Extended Memory Table Build utility displays an error message indicating that the
assign needs to be corrected, and the other processes listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.IPCFEMT
Usage Codes: BASE

ITF — The fully qualified file name of the BIC Interchange Totals File (ITF). The BIC ISO Interface process uses this assign.

Example: \B24.\$DATA.PRO1DATA.ITF (data file name)
 \B24.\$DATA.PRO1TPLT.ITF (template file name)
 Usage Codes: BASE
 Template File: Required to create a new ITF.

KEY5 — The fully qualified file name of the Key File (KEYF) for Interchange Interface processes running under release 3.4/4.0 (i.e., the BASE24-REL param is set to a value of 40). The following processes and utilities use this assign:

BIC ISO Interface process
 Host and Interchange Interface utilities
 Key File Server process

Example: \B24.\$DATA.PRO1DATA.KEY5
 Usage Codes: BASE

KEY6 — The fully qualified file name of the Key 6 File (KEY6) for Interchange Interface processes supporting triple DES to single DES PIN translation. The KEY6 allows for double-length encryption keys, which are required when translating PINs from encryption under a double-length key using the Triple Data Encryption algorithm (T-DEA) to encryption under a single-length key using the Data Encryption algorithm (DEA) and vice versa.

If the DES-TRIPLE-SINGLE param is present and set to a value of Y, the processes listed below require the KEY6 assign. If the DES-TRIPLE-SINGLE param is set to a value of N or is not configured, the processes listed below require the KEYF assign instead.

The following processes and utilities use this assign:

Banknet Interchange Interface process
 BIC ISO Interface process
 EPS-Net Interchange Interface process
 Host and Interchange Interface utilities
 ISO Host Interface process
 LINK ISO Interchange Interface process
 MDS ISO Interchange Interface process
 VisaNet ISO Interchange Interface process
 Key 6 File Server process *

- * This process always requires the KEY6 assign, regardless of the DES-TRIPLE-SINGLE param setting.

If this assign is required but is not present in the LCONF or contains an invalid value, the processes listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.KEY6
Usage Codes: BASE

KEYA — The fully qualified file name of the Key Authorization File (KEYA).
The following processes use this assign:

BASE24-atm Authorization process
BASE24-card Plastic Card Generation Server process
BASE24-pos Device Handler/Router/Authorization process
BASE24-teller Authorization process
ITS Kernel Extended Memory Table Build utility
Key Authorization File Server process

The BASE24-teller Authorization process uses this assign based on the setting in the TLR-PROCESS-CRD-PIN param, a BASE24-teller specific param. All other processes listed above require this assign. If this assign is not present in the LCONF or contains an invalid value, these processes log a message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.KEYA
Usage Codes: ATM, BASE, CARD, POS, TB, TLR

KEYF — The fully qualified file name of the Key File (KEYF).

If the DES-TRIPLE-SINGLE param is set to a value of N or is not configured, the processes listed below require the KEYF assign. If the DES-TRIPLE-SINGLE param is present and set to a value of Y, the processes listed below require the KEY6 assign instead.

The following processes use this assign:

Banknet Interchange Interface process
BIC ISO Interface process
EPS-Net Interchange Interface process
Host and Interchange Interface utilities
ISO Host Interface process
LINK ISO Interchange Interface process

MDS ISO Interchange Interface process
VisaNet ISO Interchange Interface process
Key File Server process*

* This process always requires the KEY6 assign, regardless of the DES-TRIPLE-SINGLE param setting.

If this assign is required but is not present in the LCONF or contains an invalid value, the processes listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.KEYF
Usage Codes: BASE

KEYI — The fully qualified name of the ICC Key File (KEYI). The following processes or modules use this assign to open the KEYI and read the KEYI data into extended memory:

BASE24-atm Authorization process
BASE24-pos Router/Authorization module
KEYI File Server process

This assign is used only with the EMV add-on products for BASE24-atm and BASE24-pos.

Example: \B24.\$DATA.PRO1DATA.KEYI
Usage Codes: ATM, BASE, EMV, POS

LCONF-RPT-LOC — The spooler, terminal, or file location to which Logical Network Configuration File (LCONF) report information is sent. The value from this assign is displayed in the REPORT LOCATION field on the LNCF Printing screen. The Logical Network Configuration File (LNCF) Server process uses this assign.

If this assign is not set, a default value of \$\$.#LCONF is displayed in this field.

Example: \$\$.#LCONF1
Usage Codes: BASE

LMCF — The fully qualified file name of the Log Message Configuration File (LMCF). The LMCF assign is used by all of the application processes and, optionally, any XPNET process that can alter event messages.

Example: \B24.\$DATA.PRODCNTL.LMCF
Usage Codes: ATM, BASE, FHM, POS, TLR

MOF — The fully qualified file name of the Mobile Operator File (MOF). The MOF contains one record for each Mobile Operator. The MOF assign is used by the following:

ATM Pre-Pay Transaction Context Manager
POS Pre-Pay Transaction Context Manager

If this assign is not present in the LCONF or contains an invalid value, these processes abend at initialization.

Example: \B24.\$DATA00.PRO1DATA.MOF
Usage Codes: ATM, BASE, POS

NCSP — The fully qualified file name of the Network Control Supervisor Profile File (NCSP). The Network Control Supervisor Profile Server process uses this assign.

Example: \B24.\$DATA.PRO1DATA.NCSP
Usage Codes: BASE

NCSS — The fully qualified file name of the Network Control Supervisor Security File (NCSS). The Network Control Supervisor Security File Server process uses this assign.

Example: \B24.\$DATA.PRO1DATA.NCSS
Usage Codes: BASE

NEG*identifier* — The fully qualified file name of the Negative Card File (NEG). This assign can include an optional *identifier* to specify assigns used for different NEGs in the same logical network.

The Enscribe Refresh process uses this assign to retrieve the name of the template file during full-file refreshes of a NEG.

The Enscribe Refresh process first reads the Institution Definition File (IDF) for the fully qualified file name of the NEG used by all institutions in the refresh group. The Enscribe Refresh process then reads the LCONF to find a NEG assign that has a matching file name in the LOCATION/ID field. If no matching NEG assign is found, the Enscribe Refresh process abends during initialization.

If a matching NEG assign is found, the Enscribe Refresh process builds the new NEG using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process abends during initialization.

Example: \B24.\$DATA.PRO1TPLT.NEG (template file name)
 \B24.\$DATA.PRO1DATA.NEG (data file name)
Usage Codes: ATM, BASE, POS
Template File: Required to build the new file during full-file refreshes.

NETLIST-PROG — The fully qualified file name of the Netlist emulation process. The following processes require this assign:

ITS Kernel Extended Memory Table Build utility
Base Transaction Analysis utility

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility and the Base Transaction Analysis utility log an error message to their report files and stop.

Example: \B24.\$SYSTEM.SPANNET.NETLIST
 \B24.\$SYSTEM.XN30B24.NETLIST
Usage Codes: BASE, KNL, TB

OMF — The fully qualified file name of the Online Maintenance File (OMF). The following processes use this assign:

Super Extract process
Base Control Server process
ITS Kernel Control Server process
Enhanced Interchange Configuration File Server process
Interchange Configuration File Server process
Institution Data File Server process
Logical Network Configuration File Server process
Security Server process
BASE24 COBOL utilities
BASE24 Configuration Manager process

OMFs are created with a file name of *Ayyymmddx*, where *yymmdd* is the current date and *x* is a number from 0 through 9. When the current OMF becomes full, another OMF is created for the current date appended with the next available number.

If the BASE24 Configuration Manager is used, the BCM library routines in files maintenance servers use the template file specified for this assign to create OMFs when files maintenance changes are made on BASE24 production files that require OMF auditing.

Note: The BASE24 Pathway system will not initialize without this assign defined in the LCONF.

Examples: \B24.\$DATA.PRO1OMFS.AYYMMDDX (data file name)
 \B24.\$DATA.PRO1TPLT.AYYMMDDX (template file name)
Usage Codes: ATM, BPAY, BASE, POS, TB, TLR
Template File: Required because BASE24 creates an OMF daily.

PAM — The fully qualified file name of the PLUS Administrative Message File (PAM). The following processes use this assign:

PLUS ISO Interchange Interface process
PLUS Administrative Message File Server process

Examples: \B24.\$DATA.PRO1DATA.PAM
Usage Codes: BASE

PBF*identifier* — The fully qualified file name of the Positive Balance File (PBF). This assign can include an optional *identifier* to specify assigns used for different PBFs in the same logical network.

The Enscribe Refresh process uses this assign to retrieve the name of the template file during full-file refreshes of a PBF.

The Enscribe Refresh process first reads the Institution Definition File (IDF) for the fully qualified file name of the PBF used by all institutions in the refresh group. The Enscribe Refresh process then reads the LCONF to find a PBF assign that has a matching file name in the LOCATION/ID field. If no matching PBF assign is found, the Enscribe Refresh process does not initialize.

If a matching PBF assign is found, the Enscribe Refresh process builds the new PBF using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process does not initialize.

Examples: \B24.\$DATA.PRO1DATA.PBF (data file name)
 \B24.\$DATA.PRO1TPLT.PBF (template file name)
Usage Codes: ATM, BASE, POS, TB, TLR
Template File: Required to build the new file during full-file refreshes.

PCT-LOG — The network location for event messages generated by the Process Control Terminal Server process. This process provides a limited portion of Device Control Terminal Server process functionality.

This assign identifies the Sudoterm PPD name or \$0.

Examples: \$SUDO
 \$0
Usage Codes: BASE

PDF — The fully qualified name of the Processing Code Description File (PDF). This is an optional file that contains descriptions of the processing codes used in the Acquirer Processing Code File (APCF) or Issuer Processing Code File (IPCF). The Processing Code Description File Server process uses this assign.

Example: \B24.\$DATA.PRO1DATA.PDF
Usage Codes: ATM, BASE, POS

PISO-ISF — The fully qualified file name of the PLUS ISO/Interlink Services File (PISF). The following processes use this assign:

PLUS ISO Interchange Interface process
PLUS ISO/Interlink Services File Server process

The PLUS ISO Interchange Interface process uses the template defined for this assign to create PISFs. This assign is required.

Example: \B24.\$DATA.PRO1DATA.PISF (data file name)
 \B24.\$DATA.PRO1TPLT.PISF (template file name)
Usage Codes: BASE
Template File: Required to create PISFs.

PISO-MLF — The fully qualified file name of the PLUS Maintenance Log File (PMLF). The following processes use this assign:

PLUS ISO Interchange Interface process
PLUS File Maintenance Log File Server process

The PLUS ISO Interchange Interface process uses the template defined for this assign to create PMLFs. This assign is required.

Example: \B24.\$DATA.PRO1DATA.PMLF (data file name)
 \B24.\$DATA.PRO1TPLT.PMLF (template file name)
Usage Codes: BASE
Template File: Required to create PMLFs.

PLUS-PPF — The fully qualified file name of the PLUS Proprietary Member Center File (PPF). The following processes require this assign:

PLUS ISO Interchange Interface process
PLUS Proprietary Member Center File Maintenance Server process

Example: \B24.\$DATA.PRO1DATA.PPF
Usage Codes: BASE

PRI-COLL — The fully qualified PPD name of the primary EMS Collector process. This assign is used by the following:

Base Extended Memory Table Build utility
ITS Kernel Extended Memory Table Build utility
SQL Refresh process
BASE24-telebanking Issuer Reporting program
Event object

BASE24-pos Stored Value Dormancy/Escheatment program

If this assign is not present in the LCONF or contains an invalid value, the process, programs, and object listed above abend without generating an event message.

Example: \B24.\$0
Usage Codes: BASE, KNL, TB

PRM-PTBL — The fully qualified file name of the PRISM Routing Table. This assign is required if transactions are to be sent to the ACI Proactive Risk Manager product. The following processes use this assign:

BASE24-atm Authorization process

BASE24-pos Device Handler/Router/Authorization process

Each authorization process can have its own PRM-PTBL assign defined in the LCONF or one PRM-PTBL assign can be used for all BASE24-atm and BASE24-pos Authorization processes. This assign is required for transactions to be sent to the Scoring Engine Input process for the ACI Proactive Risk Manager product.

Example: \B24.\$DATA.PRO1DATA.PTBL

Usage Codes: ATM, POS, PRM

RAM-CNFG — The fully qualified file name of the Remote Application Manager (RAM) configuration file. At initialization, the Remote Application Manager process reads required parameter, station, and Application Service Group (ASG) information contained in this edit file. The RAM configuration file delivered at installation is merely an example of how the file could look. The file must be edited after installation to match your site-specific requirements. The Remote Application Manager process requires this assign.

The RAM process allows BASE24 applications to interface with remote applications, such as hardware security modules connected using the TCP/IP protocol. For more information on the RAM process, refer to the *Remote Application Manager Implementation and Installation Guide*.

Example: \B24.\$DATA.BAxxRAM.RAMCNFG, where xx is the
 number of the current release

Usage Codes: ATM, BASE, POS, TLR

RGCF — The fully qualified name of the Refresh Group Control File (RGCF). The Enscribe and SQL Refresh processes use this assign for all refreshes.

Example: \B24.\$DATA.PRO1DATA.RGCF

Usage Codes: BASE, TB

RPT — The fully qualified name of the BASE24 reports file that contains BASE24 and interchange reports. The following processes use this assign:

BASE24 Report Perusal Server process
BASE24-atm Settlement Initiator process
Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

The BASE24-atm Settlement Initiator process uses this assign to create the RPT using the naming convention specified in this assign and the file specifications in the RPT template file. The Interchange Interface processes use this assign to run interchange reports.

This assign is required if the BASE24-atm Settlement Initiator process is to run reports. If reports are to be produced but this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process abends during initialization.

Example: \B24.\$DATA.PRO1ARPT.RPYMMDD (data file name)
 \B24.\$DATA.PRO1TPLT.RPYMMDD (template file name)
Usage Codes: ATM, BASE, POS
Template File: Required because BASE24 periodically creates BASE24-atm
 reports and Interchange reports.

RPT-ERROR-FILE — The spooler location or network logging location for event messages generated by the Interchange report programs. The following processes use this assign:

BASE24-atm Settlement Initiator process
Transaction Based Pricing Report Initiator process
Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

This assign identifies the Sudoterm PPD name or \$0.

Examples: \B24.\$\$.#ATMERR (spooler location)
 \$SUDO (network logging location)
 \$0 (network logging location)

Usage Codes: ATM, BASE

RPTR — The spooler location to which the Enscribe Refresh process sends the refresh reports for refreshes of all files except the national negative files. The Enscribe Refresh process uses this assign.

The BASE24-pos BP-RPTR assign identifies the spooler location for the national negative files.

Example: \B24.\$\$.#REFR

Usage Codes: ATM, BASE, POS, TB, TLR

RSAF — The fully qualified file name of the Resubmittal Store-and-Forward File (RSAF). The following processes use this assign:

Generic Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Examples: \B24.\$DATA.PRO1DATA.RSAF (data file name)
 \B24.\$DATA.PRO1TPLT.RSAF (template file name)

Usage Codes: ATM, BASE, POS, TB, TLR

Read By: A symbolic name (for example, P1A^PISO1, P2A^VISA) is required in this field.

Template File: Required because the RSAF is created periodically by BASE24.

SAF — The fully qualified file name of a Store-and-Forward File (SAF). This assign is used by the following processes:

ISO Host Interface process
Super Extract process
Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process

LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Examples: \B24.\$DATA.PRO1DATA.SAF1 (data file name)
 \B24.\$DATA.PRO1TPLT.SAF (template file name)
Usage Codes: ATM, BASE, POS, TB, TLR
Read By: A symbolic name (for example, P1A^HISO1, P2A^BASE) is
 required in this field because the dates of the SAFs may vary
 from process to process.
Template File: Required because the SAF is created periodically by
 BASE24.

SDF — The fully qualified file name of the Switch Dispute File (SDF). The following processes use this assign:

Enscribe Refresh process
Banknet Interchange Interface process
MDS ISO Interchange Interface process
Generic Interchange Interface process
VisaNet ISO Interchange Interface process
VisaNet ISO Switch Dispute File Server process

The Enscribe Refresh process uses this assign to retrieve the name of the template file during partial-file refreshes of the SDF. The Enscribe Refresh process uses this assign to create the SDF if it does not exist when a partial-file refresh of the SDF is started.

Example: \B24.\$DATA.PRO1DATA.SDF (data file name)
 \B24.\$DATA.PRO1TPLT.SDF (template file name)
Usage Codes: ATM, BASE, POS
Template File: The Enscribe Refresh process requires that the template file
 be identified for this file.

SEC — The fully qualified file name of the Security File (SEC). The Security File Server process uses this assign.

Note: The BASE24 Pathway system will not initialize without this assign defined in the LCONF.

Example: \B24.\$DATA.PRO1DATA.SEC
Usage Codes: BASE

SECURE-DEV1 — The name of the primary security device, the name of the interface module used with the primary security device, or the process pair directory (PPD) name of the primary Transaction Security Services process used for PIN management, message authentication processing, and security module key management. The Transaction Security Services process is required when implementing system-wide triple DES or when upgrading Atalla firmware to support the new Atalla key block format.

When using the Transaction Security Services process, the USER FIELD for the SECURE-DEV1 assign on the LNCf Assign screen must be left blank. The security utilities bound into BASE24 processes use this value to define the device subtype. Since there are no valid device subtypes associated with calls to the Transaction Security Services process, the utilities generate an error event message when a value is present.

Also, when using the Transaction Security Services process, the SECURE-DEV1 assign is ignored if the SECURE-DEV-ACCESS-TYP param is present and set to the value 1. Refer to the ***BASE24 Transaction Security Services Processing Guide*** for more information about using this assign with the Transaction Security Services process.

For the Atalla A8000 and A8100 security devices, this assign specifies the SYSGEN utility or DSC name of the primary security device. For Atalla A9000, A9100, A10000E, and A10100 security devices, this assign specifies the name given to the A9000, A9100, A10000E, or A10100 interface module used with the primary security device. The device name or interface module name used must be compatible with the HP NonStop Expand product.

For Thales e-Security security devices other than the RG7100 security device using Transmission Control Protocol/Internet Protocol (TCP/IP) or the RG7300 security device using synchronous data-link control (SDLC) emulation, this assign specifies the SYSGEN utility or DSC name of the primary security device. For an RG7100 device using TCP/IP, this assign specifies the process name and application service group defined for the Remote Application Manager process (for example, \$RAM.#SECURE1). The Remote Application Manager process PPD name is defined in the Network Environment File (NEF) and the application

service group is defined in the Remote Application Manager Configuration File. For an RG7300 device using SDLC, this assign specifies the process name given to the HSM Interface process (for example, \$HIP).

When a Thales e-Security security device is used with the BASE24-card product, the USER FIELD of this LCONF assign record must contain a value of RG6000 or RG7000 to indicate whether a Version 6000 or Version 7000 security device is being used. (The Version 7000 device accepts a PIN-Length parameter to generate a variable-length PIN. The Version 6000 device only creates four-digit PINs.) If the User Field is blank, the Plastic Card Generation Server (SVPCGEN) process assumes a Version 7000 device is being used.

Note: The SVPCGEN process attempts to read this LCONF assign with a process name of SVPCGEN. If no match is found, the process attempts to find this assign with a default process name of all asterisks (*****).

This assign is used by security procedures bound into the following processes:

BASE24-atm Authorization process
BASE24-atm Device Handler process

BASE24-card Plastic Card Generation Server (SVPCGEN) process

BASE24-pos Device Handler/Router/Authorization process

BASE24-teller Authorization process
BASE24-teller Device Handler processes

Host Interface processes
Interchange Interface processes

The following processes also use this assign:

ICC Key File Server process
 Key Authorization File Server process
 Token File Server process

Examples: \B24.\$SECDVA (for an Atalla A8000 or A8100 security device, this assign specifies the HP NonStop SYSGEN device name)

 \B24.\$BOX1 (for Atalla A9000, A9100, A10000E, and A10100 security devices, this assign specifies the PPD name of the Boxcar interface module)

 \B24.\$RAM.#SECURE1 (for a Thales e-Security RG7100 device using TCP/IP, this assign specifies the PPD name and application service group defined for the Remote Application Manager process)

 \B24.\$TSEC1 (when implementing the Transaction Security Services process, this assign specifies the PPD name of the Transaction Security Services process)

Usage Codes: ATM, BASE, CARD, POS, TLR

Read By: A symbolic name (for example, P1A^AUTH01, P2B^BASE02, P2A^SPDH03, SVPCGEN) is required in this field if each process uses a different physical device as its primary security module.

User Field: Required for Atalla Network Security Processors (NSPs). For the A8000 or A8100 NSP, the User Field can be set to A4 or NSP. For the A9000 or A9100 NSP, the User Field must be set to a value of A4. For all other NSP security devices, the User Field must be set to NSP.

 The value in the User Field identifies the Atalla security device being used and the security functions available. For a detailed description of how these values are used, refer to the ***BASE24 Transaction Security Manual***.

 When a Thales e-Security security device is used with the BASE24-card product, the values RG6000 or RG7000 indicate whether a Version 6000 or Version 7000 security device is being used. If a value is not specified, it defaults to RG7000.

SECURE-DEV2 — The name of the secondary security device, the name of the interface module used with the secondary security device, or the process pair directory (PPD) name of the secondary Transaction Security Services process that provides PIN management, message authentication processing, and security

module key management. The Transaction Security Services process is required when implementing system-wide triple DES or when upgrading Atalla firmware to support the new Atalla key block format.

When using the Transaction Security Services process, the USER FIELD for the SECURE-DEV1 assign on the LNCf Assign screen must be left blank. The security utilities bound into BASE24 processes use this value to define the device subtype. Since there are no valid device subtypes associated with calls to the Transaction Security Services process, the utilities generate an error event message when a value is present.

Also, when using the Transaction Security Services process, the SECURE-DEV2 assign is ignored if the SECURE-DEV-ACCESS-TYP param is present and set to the value 1. Refer to the ***BASE24 Transaction Security Services Processing Guide*** for more information about using this assign with the Transaction Security Services process.

For the Atalla A8000 and A8100 security devices, this assign specifies the HP NonStop SYSGEN or DSC name of the secondary security device or the PPD name of the Transaction Security Services process. For Atalla A9000, A9100, A10000E, and A10100 security devices, this assign specifies the name given to the A9000, A9100, A10000E, or A10100 interface module used with the secondary security device or the PPD name of the Transaction Security Services process. The device name or interface module name used must be compatible with the HP NonStop Expand product.

For Thales e-Security security devices other than the RG7100 security device using Transmission Control Protocol/Internet Protocol (TCP/IP) or the RG7300 security device using synchronous data-link control (SDLC) emulation, this assign specifies the SYSGEN utility or DSC name of the primary security device. For an RG7100 device using TCP/IP, this assign specifies the process name and application service group defined for the Remote Application Manager process (for example, \$RAM.#SECURE2). The Remote Application Manager process PPD name is defined in the Network Environment File (NEF) and the application service group is defined in the Remote Application Manager Configuration File. For an RG7300 device using SDLC, this assign specifies the process name given to the HSM Interface process (for example, \$HIP).

When a Thales e-Security security device is used with the BASE24-card product, the User Field of this LCONF assign record must contain a value of RG6000 or RG7000 to indicate whether a Version 6000 or Version 7000 security device is being used. (The Version 7000 device accepts a PIN-Length parameter to generate

a variable-length PIN. The Version 6000 device only creates four-digit PINs.) If the User Field is blank, the Plastic Card Generation Server (SVPCGEN) process assumes a Version 7000 device is being used.

Note: The SVPCGEN process attempts to read this LCONF assign with a process name of SVPCGEN. If no match is found, the process attempts to find this assign with a default process name of all asterisks (*****).

This assign is used by security procedures bound into the following processes:

Host Interface processes
Interchange Interface processes

BASE24-atm Authorization process
BASE24-atm Device Handler process

BASE24-card Plastic Card Generation Server (SVPCGEN) process

BASE24-pos Device Handler/Router/Authorization process

BASE24-teller Authorization process
BASE24-teller Device Handler processes

Examples:	\B24.\$SECDVA (for an Atalla A8000 or A8100 security device, this assign specifies the HP NonStop SYSGEN device name)
	\B24.\$BOX1 (for Atalla A9000, A9100, A10000E, and A10100 security devices, this assign specifies the PPD name of the Boxcar interface module)
	\B24.\$RAM.#SECURE2 (for a Thales e-Security RG7100 device using TCP/IP, this assign specifies the process name and application service group defined for the Remote Application Manager process)
Usage Codes:	ATM, BASE, CARD, POS, TLR
Read By:	A symbolic name (for example, P1A^AUTH01, P2B^BASE02, P2A^SPDH03, SVPCGEN) is required in this field if each process uses a different physical device as its secondary security module.

User Field: Required for Atalla Network Security Processors (NSPs). For the A8000 or A8100 NSP, the User Field can be set to A4 or NSP. For the A9000 or A9100 NSP, the User Field must be set to a value of A4. For all other NSP security devices, the User Field must be set to NSP.

The value in the User Field identifies the Atalla security device being used and the security functions available. For a detailed description of how these values are used, refer to the ***BASE24 Transaction Security Manual***.

When a Thales e-Security security device is used with the BASE24-card product, the values RG6000 or RG7000 indicate whether a Version 6000 or Version 7000 security device is being used. If a value is not specified, it defaults to RG7000.

SECURE-DEV-xx — The process pair director (PPD) name of the Transaction Security Services process used for PIN management, message authentication processing, and security module key management. The Transaction Security Services process is required when implementing system-wide triple DES or when upgrading Atalla firmware to support the new Atalla key block format.

This assign is used when configuring the round-robin method for accessing the Transaction Security Services processes. The SECURE-DEV-ACCESS-TYP param value of 1 indicates that the round-robin method is used. The SECURE-DEV-xx assign identifies the PPD name of a security device in the round-robin list.

The round-robin method of access works on a rotating basis and allows for better load balancing, as well as reducing the performance impact if one Transaction Security Services process becomes unavailable. Once a Transaction Security Services process has received a message for processing, the next process on the list is available for the next message, etc. This method continues through the end of the list, and then loops back to the beginning. If a Transaction Security Services process is unavailable, that Transaction Security Services process is skipped and the message is then forwarded to the next Transaction Security Services process on the list.

Each SECURE-DEV-xx assign contains the PPD name of one Transaction Security Services process. When multiple processes are named in the round-robin list, this assign includes an identifier to specify params used for different processes in the same logical network. The identifier is usually a number, but can be any unique pair of characters that has not already been declared by another SECURE-

DEV-xx assign. For example, SECURE-DEV-01 could contain \B24.\$SEC1 and SECURE-DEV-02 could contain \B24.\$TSEC2. One assign is present for each device and a maximum of 20 devices can be supported.

When using the Transaction Security Services process, the USER FIELD for the SECURE-DEV-xx assign on the LNCf Assign screen must be left blank. The security utilities bound into BASE24 processes use this value to define the device subtype. Since there are no valid device subtypes associated with calls to the Transaction Security Services process, the utilities generate an error event message when a value is present. Refer to the *BASE24 Transaction Security Services Processing Guide* for more information.

This assign is used by security procedures bound into the following processes:

Host Interface processes
Interchange Interface processes

BASE24-atm Authorization process
BASE24-atm Device Handler process

BASE24-pos Device Handler/Router/Authorization process.

Examples: \B24.\$TSEC1, \B24.\$TSEC2
Usage Codes: ATM, BASE, POS

SEMF — The fully qualified file name of the Scoring Engine Master File (SEMF). The SEMF contains cardholder information that the Scoring Engine Input process adds to the transaction for the corresponding cardholder before the transaction is scored. The following processes use this assign:

Enscribe Refresh process
From Host Maintenance process
Scoring Engine Input process

Example: \B24.\$DATA.PRO1DATA.SEMF
Usage Codes: BASE, PRM

SNF — The fully qualified file name of the Station Name File (SNF). The following processes use this assign:

BCGI Interface process
PLUS ISO Interchange Interface process
MDS ISO Interchange Interface process

Generic Interchange Interface process
Station Name File Server process
VisaNet ISO Interchange Interface process

Example: \B24.\$DATA.PRO1DATA.SNF
Usage Codes: BASE

SPANCTL — The fully qualified file name of the SPROUTE File. The SPANCTL assign is used by the following processes:

BASE24-atm Authorization process
BASE24-atm Transaction Context Manager process
BASE24-pos Device Handler/Router/Authorization process (the BASE24-pos Router module reads the assign during initialization.)
Golden Database Edit File process

XPNET process
ITS Kernel Extended Memory Table Build utility

Example: \B24.\$SYSTEM.PRODCNTL.SPROUTE
Usage Codes: ATM, BASE, POS

SPF*identifier* — The fully qualified file name of the Stop Payment File (SPF). This assign can include an optional *identifier* to specify assigns used for different SPFs in the same logical network. This assign is required only if one or more institutions in the logical network are using BASE24-teller or the BASE24-atm self-service banking (SSB) Enhanced Check Application.

The Enscribe Refresh process uses the SPF assign to retrieve the name of the template file during full-file refreshes.

The Enscribe Refresh process first reads the Institution Definition File (IDF) for the fully qualified file name of the SPF used by all institutions in the refresh group. The Enscribe Refresh process then reads the LCONF to find an SPF assign that has a matching file name in the LOCATION/ID field. If no matching SPF assign is found, the Enscribe Refresh process abends during initialization.

If a matching SPF assign is found, the Enscribe Refresh process builds the new SPF using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.SPF (data file name)
 \B24.\$DATA.PRO1TPLT.SPF (template file name)
Usage Codes: BASE, TLR
Template File: Required to build the new file during full-file refreshes.

STF — The fully qualified file name of the Switch Terminal File (STF). The following processes use this assign:

Banknet Interchange Interface process
Generic Interchange Interface process
Switch Terminal File Server process

Example: \B24.\$DATA.PRO1DATA.STF
Usage Codes: ATM, BASE, POS

STRF — The fully qualified file name of the Split Transaction Routing File (STRF). The following processes use this assign:

Split Transaction Routing File Server process
Base Extended Memory Table Build utility

Example: \B24.\$DATA.PRO1DATA.STRF
Usage Codes: ATM, BASE

STRFEMT — The fully qualified file name of the Split Transaction Routing File (STRF) extended memory table, which contains STRF records. The following processes use this assign:

BASE24-atm Transaction Context Manager process
Base Extended Memory Table Build utility

If this assign is not present in the LCONF or contains an invalid value, the Base Extended Memory Table Build utility displays an error message indicating that the assign needs to be corrected and the BASE24-atm Transaction Context Manager does not initialize.

Example: \B24.\$DATA.PRO1DATA.STRFEMT
Usage Codes: ATM, BASE

SURF — The fully qualified file name of the Surcharge File (SURF). There should only be one SURF for the entire logical network. The following processes use this assign when the Surcharge add-on product is installed:

BASE24-atm Authorization process
Surcharge File Server process

Example: \B24.\$DATA.PRO1DATA.SURF
Usage Codes: ATM, BASE

SW-RPT-OBEY-FILE — The fully qualified file name of the report obey file for an Interchange Interface process. The following processes use this assign:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Example: \B24.\$DATA.PRO1DATA.SRYMMDD
Usage Codes: BASE
Read By: A symbolic name (for example, P1A^BIC) is required in this field.

SW-RPT01-PROG-NAME — The fully qualified file name of the executable object code that generates the Interchange Clearings Statement Report (SETL01). The following processes use this assign:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Example: \B24.\$DATA.SWxxOBJ.SWRPT01, where xx is the number
 of the current release
Usage Codes: BASE
Read By: A symbolic name (for example, P1A^BIC) is required in this
 field.

SW-RPT09-PROG-NAME — The fully qualified file name of the executable
object code for the Interchange Transaction Detail Report (STAT09). The
following processes use this assign:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Example: \B24.\$DATA.SWxxOBJ.SWRPT09, where xx is the number
 of the current release
Usage Codes: BASE
Read By: A symbolic name (for example, P1A^BIC) is required in this
 field.

SWCH-IIF — The fully qualified file name of the Institution Identification File
(IIF). The following processes use this assign:

Institution Identification File Server process
Generic Interchange Interface process

Example: \B24.\$DATA.PRO1DATA.IIF
Usage Codes: BASE

TCF — The fully qualified name of the Transaction Code Description File (TCF). This is an optional file that contains descriptions of the ISO transaction codes used in the Acquirer Processing Code File (APCF) or Issuer Processing Code File (IPCF). The Transaction Code Description File Server process uses this assign.

Example: \B24.\$DATA.PRO1DATA.TCF
Usage Codes: ATM, BASE, POS

TKN — The fully qualified file name of the Token File (TKN). The TKN Requester and Server processes require this assign. If this assign is not present in the LCONF or contains invalid values, the TKN Requester and Server processes abend during initialization.

This assign is used optionally by other BASE24 processes listed below. If a process cannot locate the TKN assign, the process performs the default action for the token data for that process. For example, when a process that requires the TKN to configure what token data must be logged (such as the BASE24-atm Authorization process), and cannot locate the TKN using the TKN assign, by default the process logs all token data present in the internal message. Refer to the ***BASE24 Tokens Manual*** for additional information regarding default actions that are taken.

The following processes and objects use this assign:

BASE24-atm Authorization process
BASE24-atm Settlement Initiator process
BASE24-atm Transaction Context Manager process
BASE24-pos Device Handler/Router/Authorization process
BASE24-teller Device Handler process
BASE24-teller Authorization process
BIC ISO Interface processes
EPS-Net Interchange Interface process
Host and Interchange Interface utilities
Internal Message Translation object
ISO Host Interface process

LINK ISO Interchange Interface process
Super Extract process
Token File Server process

Example: \B24.\$DATA.PRO1DATA.TKN
Usage Codes: ATM, BASE, POS, TB, TLR

TSRF — The fully qualified file name of the Transaction Code Subtype Relationship File (TSRF). This file is used to assign alphanumeric descriptions to transaction subtypes as well as to associate the transaction subtype to one or more ISO transaction codes. The following processes use this assign:

BASE24-atm Authorization process
BASE24-atm Transaction Context Manager process
Transaction Code Subtype Relationship File Server process
Base Extended Memory Table Build utility

Example: \B24.\$DATA.PRO1DATA.TSRF
Usage Codes: ATM, BASE

UFIR — The fully qualified file name of the User/FIID Relation File (UFIR). The Security File Server process uses this assign.

Note: The BASE24 Pathway system will not initialize without this assign defined in the LCONF.

Example: \B24.\$DATA.PRO1DATA.UFIR
Usage Codes: BASE

UPFR — The fully qualified file name of the User/Product File Relation File (UPFR). The Security File Server process uses this assign.

Note: The BASE24 Pathway system will not initialize without this assign defined in the LCONF.

Example: \B24.\$DATA.PRO1DATA.UPFR
Usage Codes: BASE

VISA-ISF — The fully qualified file name of the VisaNet ISO Interlink Services File (VISF). The following processes use this assign:

VisaNet ISO Interchange Interface process

VisaNet ISO VISF Server process

Example: \B24.\$DATA.PRO1DATA.VISF

Usage Codes: BASE

Params

The params in this section are general params because they are accessed by more than one product.

The params are listed in alphabetical order. Each param includes a definition of the param, the values for the param, and the product codes of the products which access the param.

ACCT-NUM-TYP — A code indicating whether account numbers are stored in binary or display format. Valid values are as follows:

B = Binary format (not currently supported)
D = Display format

The binary format allows the account number to be up to 28 digits in length. The display format allows the account number to be up to 19 digits in length. The following processes use this param:

BASE24-atm report programs
BASE24-atm ISO Host Interface process
BASE24-atm Settlement Initiator process

BASE24-card Cardholder List Server process

BASE24-pos Device Handler/Router/Authorization process
BASE24-pos ISO Host Interface process
BASE24-pos report programs

Administrative Card File Server process
Cardholder Authorization File Server process
Card History File Server process
CRT Authorization Usage File Server process
Negative Card File Server process
No Book File Server process
Positive Balance File Server process
POS Retailer Definition File Server process
POS Transaction Log File Server process
Stop Payment File Server process
Teller Transaction Log File Server process
Transaction Log File Server process
Usage Accumulation File Server process
Warning/Hold/Float File Server process

From Host Maintenance process
Banknet Interchange Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process
Interchange report programs
Super Extract process

Usage Codes: ATM, BASE, CARD, FHM, POS, TB, TLR
Param Default: D

ADDL-DATA-SEND — A value indicating whether the additional data field is sent in BASE requests and reversals. The VisaNet ISO Interchange Interface process uses this param. Valid values are as follows:

Y = Yes, send additional data field.
N = No, do not send additional data field.

Usage Codes: BASE
Param Default: N

AFT-PAN-DIGITS — A 3-digit value indicating how to mask PANs displayed on Pathway screens. Descriptions of the values are as follows:

Digit Number	Description	Default Value
1	The maximum number of left most digits to be displayed unmasked.	0
2	The minimum number of digits to be masked.	9
3	The number of rightmost digits to be displayed unmasked.	4

Usage Codes: ATM, BASE, POS
Param Default: 094

ALT-TIM-LMT — The maximum time, in hundredths of seconds, the application waits for the call to the WRITE procedure to complete. This param is used when logging to the alternate EMS Collector process. Valid values are 0 through 2,147,483,647.

The following processes and objects use this param:

Base Extended Memory Table Build utility
ITS Kernel Extended Memory Table Build utility
BASE24-telebanking Issuer Reporting program
Event object
SQL Refresh process

Usage Codes: BASE, KNL, TB
Param Default: 300

APCFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Acquirer Processing Code File extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table.

Usage Codes: ATM, BASE, POS
Param Default: 127

APCFEMT-WARM*Identifier* — The symbolic name of a process to receive a warmboot command when the Acquirer Processing Code File (APCF) extended memory table is warmbooted from the Device Control Terminal (DCT). The Process Control Terminal Server process uses this param. The following processes or modules can be warmbooted:

BASE24-atm Diebold 10XX/478X Device Handler process
BASE24-atm NCR 5XXX Device Handler process

BASE24-pos Hypercom Device Handler module
BASE24-pos Standard POS Device Handler module
BASE24-pos Router/Authorization module

Banknet Interchange Interface process
BIC ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

The Device Control Terminal Server process retrieves all APCFEMT-WARM*Identifier* params when a network control operator issues a command to reinitialize the APCF extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another APCFEMT-WARM*Identifier* param. For example, APCFEMT-WARM01 could contain the P1A^C10001 process and APCFEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 APCFEMT-WARM*Identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one APCFEMT-WARM*Identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples:	P1A^C10001 P1A^N* P1A^SPDH2 P2A^BICI
Usage Codes:	ATM, BASE, POS
Param Default:	No default value

ATM-BALANCE-OPTION — A value indicating the field that international issuers should use for balance amounts in the response message. The VisaNet ISO Interchange Interface process uses this param. Valid values are as follows:

Y = International issuers should use field 54 to send the balance amount in the response.
N = International issuers can use field 6 to send the balance amount in the response.

Note: U.S. issuers are allowed to use field 54 and the default for param is to use field 54. Therefore, U.S. issuers do not need to configure this param.

Usage Codes:	BASE
Param Default:	Y

BAL-ENQ-SUPPORT — A code indicating the level of support for the balance enquiry service provided by the Europay member. Valid values are as follows:

A = Acquirer-only participation
 B = Both acquirer and issuer participation
 I = Issuer-only participation
 N = Neither acquirer nor issuer participation

This param is not currently used by the EPS-Net Interchange Interface process.

Usage Codes: BASE
 Param Default: N

BASE-CURRENCY-CODE — The ISO currency code of the Base currency to be used by this logical network. This code must match the Base currency code as set in the COBNAMES file at installation. Each code consists of a three-digit value. For the currency code values, refer to the ISO 4217 standard, *Codes for the Representation of Currencies and Funds*. This param is used by the Currency Conversion utilities. This param is used only with the Multiple Currency add-on products for BASE24-atm and BASE24-pos. The following processes use this param:

BASE24-atm Authorization process
 BASE24-atm 10XX/478X Device Handler process
 BASE24-atm NCR 5XXX Device Handler process

BASE24-pos Router/Authorization module
 BASE24-pos SPDH Device Handler module
 BASE24-pos APACS Device Handler module

Usage Codes: ATM, BASE, POS
 Param Default: 840

BASE24-REL — A code indicating whether the BASE24 logical network is currently running release 3.4/4.0, release 5.x, or release 6.0 or later. The following processes use this param to determine whether to use release 6.0 or later processing parameters or previous release processing parameters:

BASE24-atm Transaction Analysis utility
 External Message File (EMF) Server process
 Interchange Interface processes
 Key File (KEYF) Server process
 BASE24-pos Transaction Analysis utility

This param must be set to 60 if the BASE24 network being used is release 6.0 or later.

Interchange Interface processes retrieve LCONF assigns and params according to how the BASE24-REL param is configured. Valid values are as follows:

40 = Release 3.4/4.0
50 = Release 5.x
60 = Release 6.0 or greater

Usage Codes: BASE
Param Default: 60 (for processes residing on release 6.0 subvolumes)
 50 (for processes residing on release 5.x subvolumes)

BASE24-TAPE-LBL-PROC-USED — A code indicating whether BASE24 processes or the HP NonStop TAPECOM utility performs tape label processing during file or table refreshes or extracts. Valid values are as follows:

Y = Yes, the BASE24 Enscribe or SQL Refresh, National Negative Refresh (Base or INAS), or Super Extract processes perform tape label processing.

N = No, the BASE24 Enscribe or SQL Refresh, National Negative Refresh (Base or INAS), and Super Extract processes do not perform tape label processing. Use the HP NonStop TAPECOM utility to perform tape label processing.

The following processes use this param:

Enscribe Refresh process
SQL Refresh process
Base National Negative Refresh process
INAS National Negative Refresh process
Super Extract process

Usage Codes: BASE, TB
Param Default: Y

BNRLF-NOTIFY-INTERVAL — The number of writes made to the Banknet File Request Log File (BNRLF) before calculating the percentage of file full. Each time a write is made to the BNRLF, a counter is increased by one. When the

counter is equal to the value specified in this param, the Banknet Interchange Interface process performs a calculation to determine how full the BNRLF is. The counter is then reset to zero.

When the file reaches the percent full specified in the BNRLF-NOTIFY-PERCENTAGE param, the Banknet Interchange Interface process generates an event message indicating the file is becoming full. The Banknet Interchange Interface process continues to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more since the preceding calculation, the Banknet Interchange Interface process generates another event message indicating that the file is becoming full. Valid values are 10 through 32,766.

Usage Codes: BASE
Param Default: 50

BNRLF-NOTIFY-PERCENTAGE — The percentage of file full at which the Banknet Interchange Interface process generates an event message indicating that the Banknet File Request File (BNRLF) is becoming full. The Banknet Interchange Interface process calculates the percentage of file full and continues to calculate the percentage at the interval indicated in the BNRLF-NOTIFY-INTERVAL param as described in the following paragraphs. If the percentage has increased by one percent or more since the preceding calculation, the Banknet Interchange Interface process generates another event message indicating that the file is becoming full.

If the calculation results in the percentage specified in the BNRLF-NOTIFY-PERCENTAGE param, or more, of its capacity, the Banknet Interchange Interface process generates an event message indicating the condition. Thereafter, the Banknet Interchange Interface process continues to calculate the percentage of file full at the interval indicated by the ILF-NOTIFY-INTERVAL param. When the calculated percentage of file full is less than the value of this param, the processes stop generating events.

Valid values are 10 through 99.

Usage Codes: BASE
Param Default: 80

BP-DATE-FORMAT — The format in which dates are displayed or entered for the BASE24-billpay product. The value of this param is displayed on table maintenance and customer service representative (CSR) screens to show how dates are entered and displayed. The value of this param does not determine the format

of the date displayed in the header (first line of the screen) of all customer service representative (CSR) and table maintenance screens, which is always YY/MM/DD. Valid values are as follows:

YYYYMMDD = Four-digit year, month, day
YYMMDD = Two-digit year, month, day
MMDDYY = Month, day, two-digit year
MMDDYYYY = Month, day, four-digit year
YYYYDDMM = Four-digit year, day, month
YYDDMM = Two-digit year, day, month
DDMMYY = Day, month, two-digit year
DDMMYYYY = Day, month, four-digit year

The following processes use this param:

Security File (SEC) Server process
Super Extract process
All BASE24-billpay processes

If this param is not present in the LCONF or contains an invalid value, the default value is used.

Usage Codes: BASE, BPAY
Read By: BILLPAY (for BASE24-billpay processes only)
Param Default: YYYYMMDD

BRIDGE-WAIT-TIME — The amount of time, in hundredths of seconds, the EPS-Net Interchange Interface process waits for a message response from the Bridge process before the message is considered to have timed out. This param is used by the EPS-Net Interchange Interface process. Valid values are 0 through 32,766.

Usage Codes: BASE
Param Default: 2000 (20 seconds)

BROADCAST-DELAY — This param is used by the Enscribe Refresh process as the number of seconds to delay after broadcasting to the notify list before impacting finishes, and is used by the Settlement Initiator process as the number of

seconds to delay after file creation before broadcasting to the notify list. Valid values are 1 through 300 seconds for the Enscribe Refresh process and 1 through 120 seconds for the Settlement Initiator process.

Usage Codes: ATM, BASE, POS

Param Default: 1

BROADCAST-NOTIFY — A code that defines whether the process uses the broadcast facility. This param is used by the Enscribe Refresh process and the Settlement Initiator process. Valid values are as follows:

- 0 = The Enscribe Refresh process or Settlement Initiator process does not use the broadcast facility.
- 1 = Set the broadcast flag to a value of 1 (broadcast to all service providers) for notify messages sent by the Enscribe Refresh process or the Settlement Initiator process.
- 2 = Set the broadcast flag to a value of 2 (broadcast to running service providers) for notify messages sent by the Enscribe Refresh process or the Settlement Initiator process.

For broadcast notification with the Enscribe Refresh process, the BROADCAST-NOTIFY param must be set to a value of 2 and all processes requiring a refresh notify message must have a service configured that matches the entry in the appropriate refresh notification param. The BROADCAST-DELAY param is optional.

For broadcast notification with the Settlement Initiator process, the BROADCAST-NOTIFY param must be set to a value of 2 and all processes requiring a settlement notify message must have a service configured that matches the entry in the appropriate settlement notification param. The BROADCAST-DELAY param is optional.

If broadcast notification is used with both the Refresh process and the Settlement Initiator process, the same service name can be used in the refresh and settlement notification params. However, if broadcast notification is used with the Refresh process or the Settlement Initiator process individually, one service must be defined for the refresh notification params and a different service must be defined for the settlement notification params.

Services can be configured in the following LCONF params: ATM-HDWRSTAT-NOTIFY, ATM-SETL-MIDNIGHT-NOTIFY, ATM-SETL-NOTIFY, POS-PREF-NOTIFY, POS-SETL-EAF-NOTIFY, POS-SETL-MIDNIGHT-NOTIFY, POS-SETL-NOTIFY, REF-NOTIFY, REF-SWI-NOTIFY, REF-TLR-NOTIFY, and SEMF-NOTIFY.

If the BROADCAST-NOTIFY param is missing or contains an invalid value, the refresh and settlement notification params listed above must identify individual processes instead of services.

For more information about service-based routing, including broadcast messages, see the *NET24-XPNET Network Control Operations Guide*.

Usage Codes: ATM, BASE, POS

Param Default: 0

CACT-PRESENT — A flag indicating whether the Customer/Account Relation Table (CACT) is supported. The following processes and objects use this param:

Billpay Server process
Customer Access object
Customer Table Server process

This param must be set to the value Y if the BASE24-billpay product is installed. Valid values are as follows:

Y = Yes, the Customer/Account Relation Table (CACT) is supported.

N = No, the Customer/Account Relation Table (CACT) is not supported.

If this param is not present in the LCONF or contains an invalid value, the processes and objects listed above use the default value.

Usage Codes: BPAY, TB

Param Default: Y

CAF-SCND-CRD-PROMOTE — A flag indicating whether the second card is automatically promoted to the primary card. This param is used by the BASE24-atm Authorization process and the BASE24-pos Device Handler/Router/Authorization process.

If this value is set to Y, BASE24 automatically promotes the second card to primary when the first transaction is received from the second card. The current primary card is removed from the system. If this value is set to N, BASE24 does not automatically promote the second card to primary, requiring the institution to do so manually. Valid values are as follows:

Y = Yes, automatically promote the second card to primary.

N = No, do not automatically promote the second card to primary.

Usage Codes: Base
Param Default: N

CASH-WDL-AUTH-PROD — A value specifying whether the EPS-Net Interchange Interface process routes cash withdrawals from terminals in bank branches to BASE24-atm (current processing) or BASE24-pos for authorization. The EPS-Net Interchange Interface process uses this param. Valid values are as follows:

ATM = Route cash withdrawals to BASE24-atm for authorization.
POS = Route cash withdrawals to BASE24-pos for authorization.

Usage Codes: BASE
Param Default: ATM

CHK-RTG-GRP — The check routing group used by the VisaNet ISO Interchange Interface process for routing electronic check authorization transactions. This param can contain up to 11 characters.

Usage Codes: BASE
Param Default: 000000000000

CICS-ID-OFFSET — The message offset at which the ISO Host Interface process starts checking for control messages when it receives a message from an IBM CICS host. If the message value starting at the indicated offset is DFH or DFS, the message is a control message and is ignored. This param is used for DPCs using the SNA/CICS protocol.

Usage Codes: BASE
Param Default: 0

CONSOLE-PRT — Indicates whether EMS event messages are printed on the operator console if the EMS compatibility distributor is used. Valid values are as follows:

TRUE = EMS event messages are printed on the operator console.
FALSE = EMS event messages are not printed on the operator console.

The following processes and objects use this param:

Base Extended Memory Table Build utility
ITS Kernel Extended Memory Table Build utility
BASE24-telebanking Issuer Reporting program
Event object
SQL Refresh process

Usage Codes: BASE, KNL, TB
Param Default: TRUE

COUNTER-UPDATE-INTERVAL — The number of transactions an Interchange Interface process processes before updating the Interchange Log File (ILF) trace record. Valid values are 0 through 32,767. The following processes use this param:

BCGI Interface process
VisaNet ISO Interchange Interface
Generic Interchange Interface process

Usage Codes: BASE
Param Default: 500

CPF-REC-SIZE — The maximum size of a Card Prefix File (CPF) record. The following processes use this param during initialization to determine the number of records in the CPF and the CPF record size.

BASE24-atm Authorization process
BASE24-pos Device Handler/Router/Authorization process
BASE24-teller Authorization process

Using this information, the processes shown above calculate the amount of extended memory required to hold all of the CPF records. The recommended values for this param range from 340, which is the size of the Base segment of the CPF record, to the maximum size of the CPF record as it is configured at the customer site. The maximum size of the CPF record depends on which BASE24 products are installed at the customer site.

For example, if BASE24-atm, BASE24-pos, and BASE24-atm self-service banking (SSB) are installed, the CPF record would have a Base segment of size 340, a BASE24-atm segment of 98, a BASE24-pos segment of 164, and a BASE24-atm SSB segment of 52 for a maximum CPF record size of 654 (that is, $340 + 98 + 164 + 52 = 654$). If only BASE24-atm and BASE24-atm SSB are

installed, the CPF record would have a Base segment of size 340, a BASE24-atm segment of 98, and a BASE24-atm SSB segment of 52 for a maximum CPF size of 490 (that is, $340 + 98 + 52 = 490$).

Usage Codes: ATM, POS, TLR

Param Default: For BASE24-atm, the default is the length of the Base segment of the CPF plus the length of the BASE24-atm segment of the CPF.

For BASE24-pos, the default is the length of the Base segment of the CPF plus the length of the BASE24-pos segment of the CPF.

For BASE24-teller, the default is the length of the Base segment of the CPF. The CPF does not contain a BASE24-teller segment.

CPIT-PRESENT — A flag indicating whether the Customer/Personal Information Relation Table (CPIT) is supported. The following processes and objects use this param:

Billpay Server process

Customer Access object

Customer Table Server process

Personal Information Table Server process

Remittance Generator process

This param must be set to the value Y if the BASE24-billpay product is installed. Valid values are as follows:

Y = Yes, the Customer/Personal Information Relation Table (CPIT) is supported.

N = No, the Customer/Personal Information Relation Table (CPIT) is not supported.

If this param is not present in the LCONF or contains an invalid value, the processes and objects listed above use the default value.

Usage Codes: BPAY, TB

Param Default: Y

CPS-ATM — A code indicating whether the VisaNet ISO Interchange Interface process uses the Custom Payment Service (CPS) for BASE24-atm transactions. If this param is set to a value of N, the process does not include the Payment Service (P-62) data element in BASE24-atm transactions. Valid values are as follows:

N = No, the VisaNet ISO Interchange Interface process does not use the Custom Payment Service for BASE24-atm transactions.

Y = Yes, the VisaNet ISO Interchange Interface process does use the Custom Payment Service for BASE24-atm transactions.

Usage Codes: ATM, BASE

Param Default: Y

CURRENCY-CODE — A code indicating the primary type of currency the logical network uses (for example, 840). Each code consists of a three-digit value. For the currency code values, refer to the ISO 4217 standard, *Codes for the Representation of Currencies and Funds*. The following processes use this param:

BASE24-atm Settlement Initiator process

BIC ISO Interchange Interface process

Docutel ETS 5100/5200 Device Handler process

LINK ISO Interchange Interface process

BASE24 Remote Banking Transaction Analysis utility

This param is also used with the Multiple Currency add-on products for BASE24-atm and BASE24-pos. The BASE24-billpay product (that is, Bank Advice, Billpay Server, and Scheduled Transaction Initiator processes) uses this param to fill in the currency code in various BASE24-telebanking Standard Internal Message (BSTM) or Internal Transaction Data (ITD) messages sent from BASE24-billpay processes to BASE24-telebanking processes.

The currency code in this param should match one of the values specified in the CURRENCY-CODE-TABLE in the COBNAMES file.

Usage Codes: ATM, BASE, BPAY, POS

Param Default: 840 (U.S. dollars)

CURRENCY-CONVERSION-ACQ — A code indicating whether the Interchange Interface process performs currency conversion as an acquirer. The following processes use this param:

Banknet Interchange Interface process
Visa ISO Interchange Interface process

Y = Yes, the Interchange Interface process converts the amount to U.S. dollars.
N = No, the Interchange Interface process does not convert the amount to U.S. dollars.

Usage Codes: BASE
Param Default: N

CURRENCY-CONVERSION-ISS — A value indicating whether the Interchange Interface process performs currency conversion as an issuer. The Banknet and Visa ISO Interchange Interface processes use this param.

Y = Yes, the Interchange Interface process converts the amount to local BASE24 currency.
N = No, the Interchange Interface process does not convert the amount to local BASE24 currency.

International Interlink issuers must set this param to a value of N.

Usage Codes: BASE
Param Default: N

CVV-ON-BASE24 — A code indicating whether the VisaNet ISO Interchange Interface process declines a transaction request from VisaNet or routes the request to the appropriate Authorization process when VisaNet has already determined the card verification value (CVV) to be bad. Valid values are as follows:

Y = Pass the request to the Authorization process.
N = Decline the request.

Usage Codes: BASE
Param Default: N

DATE-DISPLAY-FORMAT — The format used to display dates on screens and print dates on reports. This param applies to fields that include only the month and day or month and year, as well as to fields that include all three portions of the date. Valid values are as follows:

DDMMYY = Day, month, two-digit year
DDYYMM = Day, two-digit year, month
MMDDYY = Month, day, two-digit year
MMYYDD = Month, two-digit year, day
YYMMDD = Two-digit year, month, day
YYDDMM = Two-digit year, day, month

The following processes use this param:

Base Extended Memory Table Build utility
ITS Kernel Extended Memory Table Build utility
Customer Service Transaction Perusal Server process

Usage Codes: ATM, BASE, KNL, POS
Param Default: YYMMDD

DATE-DISPLAY-TYPE — A code indicating the format of the month and day portion of the dates on reports and BASE24-atm Device Handler receipts. When dates include the year, the year portion is not affected by this param. In order to override the default value, this param must be added for each Fujitsu Device Handler process. Valid values are as follows:

1 = Day before month (for example, DDMM or DDMMM)
2 = Month before day (for example, MMDD or MMMDD)

The following processes use this param:

BASE24-atm Diebold 10XX/478X Device Handler process
BASE24-atm Diebold 910 Device Handler process
BASE24-atm Fujitsu 7000 Device Handler process
BASE24-atm NCR 5XXX Device Handler process
BASE24-atm Settlement Initiator process
BASE24-atm Tidel Device Handler process
Transaction Log File Server process

BASE24-pos report programs
POS Transaction Log File Server process

BASE24-telebanking Issuer Reporting program
ITS Transaction Log File Server process
BASE24 Remote Banking Transaction Analysis utility

BASE24-teller report programs
Teller Transaction Log File Server process

BASE24-atm Transaction Analysis utility
BCGI Interface process
BIC ISO Interface process
Banknet Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
Interchange report programs
ITS Transaction Log File Server process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
BASE24-pos Transaction Analysis utility
PLUS ISO Interchange Interface process
Super Extract process
BASE24-teller Transaction Analysis utility
Transaction Based Pricing ATM Daily Transaction Volume Report
Transaction Based Pricing POS Daily Transaction Volume Report
Transaction Based Pricing Teller Daily Transaction Volume Report
Visa File Request Log File Server process
VisaNet ISO Interchange Interface process

Usage Codes: ATM, BASE, POS, TB, TLR
Param Default: 2

DCC-CRNCY-RATE-SOURCE — The source of Dynamic Currency Conversion (DCC) currency rates. This information may be required for display at the ATM and for printing on receipts. This param is used by the BASE24-atm Authorization process.

Examples: BANK OF XXX WHOLESALE RATE
Usage Codes: ATM

DCCDEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Dynamic Currency Conversion Data (DCCD) extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory

Table Build utility for the table. The Base Extended Memory Table Build utility uses this param. This param is used only with the Dynamic Currency Conversion add-on product for BASE24-atm.

Usage Codes: ATM, BASE

Param Default: 127

DCCDEMT-WARM*identifier* — The symbolic name of a process to receive a warmboot command when the Dynamic Currency Conversion Data (DCCD) extended memory table is warmbooted from the Device Control Terminal (DCT). The following processes or modules can be warmbooted:

BASE24-atm Authorization process

The Process Control Terminal Server process retrieves all DCCDEMT-WARM*identifier* params when a network control operator issues a command to reinitialize the DCCD extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another DCCDEMT-WARM*identifier* param. For example, DCCDEMT-WARM01 could contain the P1A^C10001 process and DCCDEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 DCCDEMT-WARM*identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one DCCDEMT-WARM*identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples: P1A^C10001

P1A^N*

P1A^SPDH2

P2A^BICI

Usage Codes: ATM, BASE

Param Default: No default value

DEBIT-CARD-TYPES — A list of up to 23 card types supported by the EPS-Net Interchange Interface process. Each card type value must be two characters in length, with each value separated by a semicolon (;) character. A space character

is only allowed for the second character of a card type value and the param list should not end with a semicolon character. In the example, the *b* character represents a blank space.

Example: AA;BB;C*b*;DD
Usage Codes: BASE
Param Default: No default value

DEFAULT-ISSUER-FEE — The default issuer fee (in fractional currency units) placed in the Transaction Processing Fee Amount field (P-30) in 0210 response messages sent to the LINK interchange. This param is optional. The LINK ISO Interchange Interface process uses this param. Valid values are 1 through 8 numeric digits.

Usage Codes: BASE
Param Default: No default value

DEFAULT-MEMBER-NUMBER — The default member number used for inbound BASE24-pos transactions when no track data is present. The PLUS ISO Interchange Interface process uses this param. Valid values are 0 through 32,766.

Usage Codes: BASE, POS
Param Default: 0

DES-TRIPLE-SINGLE — A code indicating whether an Interchange Interface process translates PINs from encryption under a double length key using the Triple Data Encryption algorithm (T-DEA) to encryption under a single length key using the Data Encryption algorithm (DEA) and vice versa. Valid values are as follows:

Y = Yes, translate PINs from T-DEA encryption to DEA encryption and vice versa.
N = No, do not translate PINs from T-DEA encryption to DEA encryption and vice versa.

The following processes use this param:

Banknet Interchange Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
ISO Host Interface process

Link Interchange Interface process
MDS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Read By: A symbolic name (for example, P1A^HISO01,
 P2B^HISO02, P2A^BIC03) is required in this field if
 interchanges have different PIN translation requirements.
Param Default: N

DSCV-VER-IND — The release number of the Discover Network ISO message,
in the following format:

VV = Discover Network ISO Version
YY = Year of release
R = Release number within current year

The following process uses this param:

Discover ISO Interchange Interface process

Usage Codes: BASE
Param Default: 03052

DUAL-SITE-DISPLAY — A code that defines whether the Transaction Log File
(TLF) Server uses a process-specific TLF assign and the POS Transaction Log File
(PTLF) Server uses a process-specific PTLF assign. Valid values are as follows:

Y = The servers use process-specific assigns for the TLF and PTLF. Both
 servers identify remote records with “REMOTE TXN” on the detail
 display.
N = The servers do not use process-specific assigns for the TLF and PTLF.

Usage Codes: ATM, POS
Param Default: N

DUAL-SITE-MODE — A code that specifies the dual site mode for the Settlement Initiator process and the Device Control Terminal (DCT) Server process. Valid values are as follows:

- L = Local records only to be processed by the Settlement Initiator process. SERVER-DCT Dual Site processing is activated.
- R = Remote records only to be processed by the Settlement Initiator process. SERVER-DCT Dual Site processing is deactivated.
- A = All records to be processed by the Settlement Initiator process. SERVER-DCT Dual Site processing is deactivated.

Usage Codes: ATM, POS
Param Default: No default value

ELIMINATE-ACQ-TRK-DATA — Indicates if the interface should eliminate track data in external non-original transactions outbound from the interface to the network. Valid values are as follows:

- Y = Yes, eliminate track data.
- N = No, do not eliminate track data.

Usage Codes: ATM, POS
Param Default: N

EMV-CARD-BLOCK-SCRIPT — Specifies the hexadecimal representation of binary data that is used to disable a chip card. It includes both the Script header and the Script command. The following processes and modules use this param:

BASE24-atm Authorization process
BASE24-pos Router/Authorization module

The Authorization process and the Router/Authorization module append the Secure Messaging MAC to this data. This param is used only with the EMV add-on products for BASE24-atm and BASE24-pos.

Samples of the data to put in this parameter can be found in the ATM EMV Support Manual or POS EMV Support Manual under Issuer Scripts.

Usage Codes: ATM, EMV, POS
Param Default: No default value

EMV-PIN-UNBLOCK-SCRIPT — Specifies the hexadecimal representation of binary data that is used to reset the PIN Try Counter to the original value on a chip card. This param is also used as the template for the data required to change the PIN on a chip card. It includes both the Script header and the Script command.

The Authorization process appends the Secure Messaging MAC to this data. This param is used only with the EMV add-on product for BASE24-atm.

Samples of the data to put in this parameter can be found in the ATM EMV Support Manual or POS EMV Support Manual under Issuer Scripts.

Usage Codes: ATM, EMV
Param Default: No default value

EMV-PUT-DATA-SCRIPT — Specifies the hexadecimal representation of binary data that is used to reset the Lower Consecutive Offline Limit on a chip card. It includes both the Script header and the Script command. The following processes and modules use this param:

BASE24-atm Authorization process
BASE24-pos Router/Authorization module

The Authorization process and Router/Authorization module append the Lower Consecutive Offline Limit and Secure Messaging MAC to this data. This param is used only with the EMV add-on products for BASE24-atm and BASE24-pos.

Samples of the data to put in this parameter can be found in the ATM EMV Support Manual or POS EMV Support Manual under Issuer Scripts.

Usage Codes: ATM, EMV, POS
Param Default: No default value

ENHANCED-CRNCY-CONV — A code indicating whether enhanced currency conversion processing is performed. This parameter is checked whenever data elements P-54, S-95, or S-123 are present in the ISO-based external message for messages acquired by the co-network or BASE24. If these data elements are present in the external message, this param indicates whether the amounts in these

fields are specified in a single currency, which is represented by a value of zero, or in two currencies, which is represented by a non-zero value. The BIC ISO Interchange Interface process uses this param. Valid values are as follows:

- 0 = Do not perform enhanced currency conversion processing.
- 1 = Perform enhanced currency conversion processing for ATM transactions only.
- 2 = Perform enhanced currency conversion processing for POS transactions only.
- 3 = Perform enhanced currency conversion processing for ATM and POS transactions.

Usage Codes: ATM, EMV, POS

Param Default: 0

ENHANCED-EMV-RC-MAPPING — A code indicating whether enhanced EMV response code mapping is required. Certain BASE24-atm and BASE24-pos response codes are used to identify EMV-specific failure conditions. These response codes are mapped to generic ISO response codes, and the acquiring system often cannot identify the reason for a declined EMV transaction. This param allows new unique ISO response codes to identify specific EMV failure conditions. Valid values are as follows:

- 0 = Do not perform enhanced EMV response code mapping.
- 1 = Perform enhanced EMV response code mapping for ATM transactions only.
- 2 = Perform enhanced EMV response code mapping for POS transactions only.
- 3 = Perform enhanced EMV response code mapping for ATM and POS transactions.

The following processes use this param:

BIC ISO Interchange Interface
BASE24-atm ISO Host Interface
BASE24-pos ISO Host Interface

Usage Codes: ATM, EMV, POS

Param Default: 0

ERFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Exchange Rate File (ERF) extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for

the table. The Base Extended Memory Table Build utility uses this param. This param is used only with the Multiple Currency add-on products for BASE24-atm and BASE24-pos.

Usage Codes: ATM, BASE, POS

Param Default: 127

ERFEMT-WARM*identifier* — The symbolic name of a process to receive a warmboot command when the Exchange Rate File (ERF) extended memory table is warmbooted from the Device Control Terminal (DCT). The following processes or modules can be warmbooted:

BASE24-atm Authorization process

BASE24-pos APACS Device Handler module

BASE24-pos Standard POS Device Handler module

BASE24-pos Router/Authorization module

BASE24-pos CRT Authorization module

The Process Control Terminal Server process retrieves all ERFEMT-WARM*identifier* params when a network control operator issues a command to reinitialize the ERF extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another ERFEMT-WARM*identifier* param. For example, ERFEMT-WARM01 could contain the P1A^C10001 process and ERFEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 ERFEMT-WARM*Identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one ERFEMT-WARM*Identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples: P1A^C10001
 P1A^N*
 P1A^SPDH2
 P2A^BICI
Usage Codes: ATM, BASE, POS
Param Default: No default value

EXTR-DISK-EXTENT-SIZE-MULT — The disk extract extent size multiplier. This is an integer value that is multiplied by the primary and secondary extent size values in the Extract Configuration File (ECF) to obtain the actual size of the extents used when creating an extract disk file. For example, if this param is set to a value of 6 and the primary and secondary extent size fields on ECF screen 3 are set to a value of 9999 (pages), the Super Extract process would create a disk file with 9999×6 pages (59,994 pages) allocated for each primary and secondary extent. This param applies to the ECF primary and secondary extent sizes for both partitioned and unpartitioned files. This param is needed only when extracting extremely large files (e.g., 2 gigabytes or more) to disk and the maximum extent size value in the ECF (i.e., 9999) is insufficient. Valid values are 1 through 6.

Product Use: BASE
Param Default: 1

EXTR-DISPOSITION — A code indicating how the Super Extract process processes oversized records. The Super Extract process writes extract records in blocks. The maximum size of this block is determined by the value in the TAPE BLOCK SIZE field on screen 1 of the Extract Configuration File (ECF). Depending on the file being extracted, the size of either a single record or a record plus the extract record header from the file may exceed the maximum extract block size. When this occurs, this param determines how the Super Extract process processes the oversized record. This param can be set to one of the following values:

C = The Super Extract process writes the number of extract records necessary to extract the oversized record in its entirety. These records are identified with continuation record prefixes (CF, CL, and CR).

- N = The Super Extract process writes a single extract record identified with the usual data record prefix (DR), but truncates the data from the oversized record that does not fit in the extract block. The host must compare the block length and record length to identify an oversized extract record.
- T = The Super Extract process writes a single extract record and truncates the excess data from the oversized record as it does with the value N; however, the Super Extract process changes the prefix from DR to TR. The TR prefix identifies an oversized extract record, eliminating the need for the host to compare the block and record lengths.

Usage Codes: ATM, BASE, FHM, MAIL, POS, TB, TLR
Param Default: N

EXTRN-RQST-TIMEOUT — A code specifying the actions to be taken when a transaction request to a DPC times out. The ISO Host Interface process uses this param. Valid values are as follows:

- 0 = The ISO Host Interface process fails the transaction and returns it to the authorization process for alternate or stand-in routing. If the ISO Host Interface process receives a late response, it generates a reversal and sends it to the host.
- 1 = The ISO Host Interface process fails the transaction and returns it to the authorization process for alternate or stand-in routing and generates a reversal that it sends to the host. If the ISO Host Interface process receives a late response from the host, it drops the message.

Usage Codes: ATM, BASE, POS, TB, TLR
Read By: A symbolic name and DPC number (for example, P1A^HISO10001, P1A^HISO10002) are required in this field for each ISO Host Interface process and DPC combination for which the param is set to a value of 1. Because the READ BY field on the LNCF Param screen is limited to 16 characters, the symbolic name cannot exceed 12 characters. If it does, the param defaults to a value of 0 for the DPC.
Param Default: 0

EXTR-TAPE-BUFFERING — A code used by BASE24 systems running on operating systems of release C20 or later to indicate whether record buffering should be used when extracting records to tape drives configured for streaming mode.

Tape drives can be configured for streaming mode using SYSGEN. Prior to release C20, records written to streaming mode tape drives as a part of extract were automatically buffered. As of release C20 and later, buffering is not automatically performed in conjunction with streaming mode. If buffering is to take place, it must be specified programmatically by the Super Extract process when writing records to the tape drive.

This param allows customers who set up their tape drives for streaming mode to specify that the Super Extract process is to invoke record buffering as well. This param is designed for use with streaming mode tape drives only. ACI recommends setting this param for no record buffering when extracting to any other types of tape drives because there is no benefit provided by doing so.

Valid values are as follows:

Y = Yes, record buffering should be used.

N = No, record buffering should not be used.

The Super Extract process uses this param.

Usage Codes: BASE

Param Default: If this param is not included in the LCONF of BASE24 systems running on operating systems of release C20 or later, buffering is not used.

F-CARD-TYPE — A foreign card type used as the output file card type by the Interchange Prefix File (IPF) Refresh Plus/Visa Interface process. If the surcharging enhancement is used, a card type can be specified in this param to be used as the output file card type for issuers from outside the U.S. This param can contain up to two alphanumeric characters.

Usage Codes: BASE

Param Default: No default value

F-CHK2-CARD-TYPE — A foreign check card II card type used as the check card II output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for issuers from outside the U.S. This param can contain up to two alphanumeric characters.

Usage Codes: BASE

Param Default: No default value

F-ILNK-CARD-TYPE — A foreign Interlink card type used as the Interlink output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for Interlink issuers from outside the U.S. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

F-PLUS-CARD-TYPE — A foreign PLUS card type used as the PLUS output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for PLUS issuers from outside the U.S. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

F-VISA-CARD-TYPE — A foreign Visa card type used as the Visa output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for Visa issuers from outside the U.S. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

F-VISAPLUS-CARD-TYPE — A foreign Visa/PLUS card type used as the Visa/PLUS output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for Visa/PLUS issuers from outside the U.S. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

FIRST-VISA-TRACE-NUM — The starting value for the trace number. This param is necessary when multiple copies of the VisaNet ISO Interchange Interface process are used. When used, the value of this param must be unique for each VisaNet ISO Interchange Interface process.

Usage Codes: BASE
Param Default: No default value

FRLF-NOTIFY-INTERVAL — The number of writes made to the VisaNet ISO File Request Log File (FRLF) before calculating the percentage of file full. Each time a write is made to the FRLF, a counter is increased by one. When the counter is equal to the value specified in this param, the VisaNet ISO Interchange Interface process performs a calculation to determine how full the FRLF is. The counter is then reset to zero.

When the file reaches the percent full specified in the FRLF-NOTIFY-PERCENTAGE param, the VisaNet ISO Interchange Interface process generates an event message indicating the file is becoming full. The VisaNet ISO Interchange Interface process continues to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more since the preceding calculation, the VisaNet ISO Interchange Interface process generates another event message indicating that the file is becoming full. Valid values are 10 through 32,766.

Usage Codes: BASE
Param Default: 50

FRLF-NOTIFY-PERCENTAGE — The percentage of file full at which the VisaNet ISO Interchange Interface process generates an event message indicating that the VisaNet ISO File Request Log File (FRLF) is becoming full. The VisaNet ISO Interchange Interface process calculates the percentage of file full and continues to calculate the percentage at the interval indicated in the FRLF-NOTIFY-INTERVAL param as described in the following paragraphs. If the percentage has increased by one percent or more since the preceding calculation, the VisaNet ISO Interchange Interface process generates another event message indicating that the file is becoming full. Valid values are 10 through 99.

Usage Codes: BASE
Param Default: 80

FRWD-DCLN-ADVC — A value pertaining to the forwarding of declined advices to BASE24-atm Authorization. If this parameter is set to Y, the interface will forward declined internal 0220 ATM advices, including balance inquiries, and log them to the Interchange Log File (ILF). If this parameter is set to N, does not exist, or contains a value other than Y, the interface will default to N and not forward declined advices (external 0120 and 0220 messages mapped to internal 0220 messages).

The **COMPLETION REQUIRED TO HOST** field for this param, located on screen 2 of the Issuer Processing Code File (IPCF), should be set to a value of 4. Valid values for this parameter are as follows:

Y = Yes, forward declined internal advices and log them to the ILF.

N = No, do not forward internal declined advices.

The following processes use this param:

Banknet Interchange Interface process

EPS-Net Interchange Interface process

VisaNet Interchange Interface process

HOST-COMPLETE-TRACK2 — A code indicating whether transactions acquired from a host contain complete and unaltered Track 2 data. The EPS-Net Interchange Interface process uses this param. Valid values are as follows:

Y = Yes, transactions from a host contain complete and unaltered Track 2 data.

N = No, transactions from a host do not contain complete and unaltered Track 2 data.

Note: This param only applies to release 3.4/4.0 systems.

Usage Codes: BASE

Param Default: Y

HOST-SELECTED-ACCT — For host-acquired BASE24-atm transactions, this param indicates whether the transaction is prescreened when account numbers are already present in the 0200 request message sent to the BASE24 system. If this param is set to true, the ISO Host Interface process sets the RQST.MULT-ACCT field in the BASE24-atm Standard Internal Message (STM) to a value of 3. This value instructs the Authorization process to prescreen the transaction (i.e., perform card and PIN verification) even though accounts are already present in the request message. If this param is set to false and accounts are present in the request message, the Authorization process does not prescreen the transaction. Valid values are as follows:

True, T, or 1 = Prescreen the transaction, even if account numbers are present in the request message.

False, F, or 0 = Do not prescreen the transaction if account numbers are present in the request message.

The ISO Host Interface process uses this param. If it is not present in the LCONF or contains an incorrect value, the default value is used. If the HISO process is acting as a migration HISO bridge, the param must be set to 0.

Usage Codes: ATM, BASE, MIGR, NETW
Param Default: False

ICHG-COMPLIANCE-ACQ-DATA-LOC — A value indicating the offset into BASE24-pos Standard Internal Message (PSTM) User Data, which the Banknet Interchange Interface process and VisaNet ISO Interchange Interface process use to store the Interchange Compliance Data for acquirer traffic (i.e., outbound transactions to Banknet or VisaNet). Valid values are 0 through 185.

Note: This param is only required in a BASE24-pos release 3.4/4.0 system. It is not required in a release 5.x or above system.

Usage Codes: BASE, POS
Param Default: 0

ICHG-COMPLIANCE-ISS-DATA-LOC — A value indicating the offset into BASE24-pos Standard Internal Message (PSTM) User Data, which the Banknet Interchange Interface process uses to store the Interchange Compliance Data for issuer traffic (i.e., inbound transactions from Banknet). Valid values are 0 through 185.

Note: This param is only required in a BASE24-pos release 3.4/4.0 system. It is not required in a release 5.x or above system.

Usage Codes: BASE, POS
Param Default: 0

IDFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Institution Definition File (IDF) extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table.

Usage Codes: ATM, BASE, CORE

IDFEMT-WARM*identifier* — The symbolic name of a process to receive a warmboot command when the Institution Definition File (IDF) extended memory table is warmbooted from the Device Control Terminal (DCT). The following processes or modules can be warmbooted:

BASE24-atm Diebold 10XX/478X Device Handler process
BASE24-atm NCR 5XXX Device Handler process

The Process Control Terminal Server process retrieves all IDFEMT-WARM*identifier* params when a network control operator issues a command to reinitialize the IDF extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another IDFEMT-WARM*identifier* param. For example, IDFEMT-WARM01 could contain the P1A^C10001 process and IDFEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 IDFEMT-WARM*identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one IDFEMT-WARM*identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples:	P1A^C10001 P1A^N* P1A^SPDH2 P2A^BICI
Usage Codes:	ATM, BASE, POS
Param Default:	No default value

ILF-LOGGING-ENABLED — A code indicating whether Interchange Log File (ILF) logging is enabled. Any value other than N indicates that ILF logging is enabled. A value of N indicates the ILF logging is disabled. The following processes use this param:

BCGI Interface process
Generic Interchange Interface process

Usage Codes: BASE
Param Default: -1

ILF-NOTIFY-INTERVAL — The number of writes made to the Interchange Log File (ILF) before calculating the percentage of file full. Each time a write is made to the ILF, a counter is increased by one. When the counter is equal to the value specified in this param, the Interchange Interface process performs a calculation to determine how full the ILF is. The counter is then reset to zero.

When the file reaches the percent full specified in the ILF-NOTIFY-PERCENTAGE param, the Interchange Interface process generates an event message indicating the file is becoming full. The Interchange Interface process continues to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more since the preceding calculation, the Interchange Interface process generates another event message indicating that the file is becoming full. Valid values are 10 through 32,766. The following processes use this param:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: 50

ILF-NOTIFY-PERCENTAGE — The percentage of file full at which the Interchange Interface process generates an event message indicating that the Interchange Log File (ILF) is becoming full. The Interchange Interface process calculates the percentage of file full and continues to calculate the percentage at the interval indicated in the ILF-NOTIFY-INTERVAL param as described in the following paragraphs. If the percentage has increased by one percent or more since the preceding calculation, the Interchange Interface process generates an event message indicating that the file is becoming full.

If the calculation results in the percentage specified in the ILF-NOTIFY-PERCENTAGE param, or more, of its capacity, the Interchange Interface process generates an event message indicating the condition. Thereafter, the Interchange Interface process continues to calculate the percentage of file full at the interval indicated by the ILF-NOTIFY-INTERVAL param. When the calculated percentage of file full is less than the value of the ILF-NOTIFY-PERCENTAGE param, the process stops generating events.

Valid values are 10 through 99. The following processes use this param:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: 70 (for the Banknet, BIC ISO, LINK ISO, MDS ISO, and
 PLUS ISO Interchange Interface processes)
 80 (for the EPS-Net, Generic, and VisaNet ISO Interchange
 Interface processes)

ILF-PURGE-ATTEMPT — The number of days prior to the Interchange Log File (ILF) retention period that the VisaNet ISO Interchange Interface process attempts to find and purge ILFs. Valid values are 1 through 99.

Usage Codes: BASE
Param Default: 5

INCOMPLETE-TRACK2-TERM-TYPES — A list of terminal types, as specified in the Terminal Data File (TDF) and POS Terminal Data File (PTDF), for which incomplete Track 2 data is transmitted from the device, or for which the device or Device Handler module or process can edit the Track 2 data. The format for this param is *tt;tt;tt;tt*, where *tt* is the terminal type and must be two alphanumeric characters in length. A semicolon (;) separates each terminal type in the list. Up to 20 terminal types can be defined in this param and the list should not end with a semicolon. The EPS-Net Interchange Interface process uses this param.

Note: This param only applies to release 3.4/4.0 systems.

Usage Codes: ATM, BASE, POS

Param Default: No default value

INSTL-TXN-DATA-OFST — A flag indicating the offset in bytes of the BASE24-pos installment transaction data from the beginning of Field Identifier (FID) 'a' in an SPDH transaction message. This parameter is optional. If the parameter is not present or invalid, the Banknet interface will use the POS Data1 token to locate the installment transaction data. Valid values are 00 through 74.

Note: The contents of FID 'a' in the SPDH message are moved to character positions 23-102 in the PSTM User Data. The interface automatically adjusts its pointer to the beginning of FID 'a' before adding the offset from this parameter. The PSTM User Data can also be passed in field S-127 in a HISO message. In this case, the value of INSTL-TXN-DATA-OFST must be set to a value 22 bytes less than the offset of the installment transaction data within the PSTM User Data. The installment transaction data must occupy 6 contiguous bytes in the PSTM User Data, formatted as shown:

Bytes	Data Element	Valid Values
1-2	Installment transaction data indicator	BP
3-4	The number of months from the transaction date when the acquirer will send the first installment payment to the issuer	Two numeric digits
5-6	The total number of installment payments required for the full purchase amount	Two numeric digits

The following process uses this param:

Banknet Interchange Interface process

Usage Codes: BASE, POS

Param Default: No default value

INCR-VISA-TRACE-NUM-BY — The value by which the trace number is increased. This param is required when multiple copies of the VisaNet ISO Interchange Interface process are processing transactions. When used, the value of this param should equal the number of VisaNet ISO Interchange Interface processes that are being used.

Usage Codes: BASE

Param Default: No default value

IPCFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Issuer Processing Code File (IPCF) extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table.

Usage Codes: ATM, POS

Param Default: 127

IPCFEMT-WARM*identifier* — The symbolic name of a process to receive a warmboot command when the Issuer Processing Code File (IPCF) extended memory table is warmbooted from the Device Control Terminal (DCT). The following processes or modules can be warmbooted:

BASE24-atm Authorization process
BASE24-pos Router/Authorization module
Banknet Interchange Interface process
BIC ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

The Process Control Terminal Server process retrieves all IPCFEMT-WARM*identifier* params when a network control operator issues a command to reinitialize the IPCF extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another IPCFEMT-WARM*identifier* param. For example, IPCFEMT-WARM01 could contain the P1A^C10001 process and IPCFEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 IPCFEMT-WARM*Identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one IPCFEMT-WARM*Identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples: P1A^C10001
 P1A^N*
 P1A^SPDH2
 P2A^BICI
Usage Codes: ATM, BASE, POS
Param Default: No default value

KEK-VARIANT-USED — An indicator of whether variant 1 of the Key Exchange Key (KEK) is used for encryption and decryption of the interface's working keys. The following processes use this param:

EPS-Net Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process

Valid values for the PLUS ISO Interchange Interface process are as follows:

Y = Yes, use variant 1 (default).
N = No, do not use variant 1.

Valid values for the EPS-Net and MDS ISO Interchange Interface processes are as follows:

YES = Yes, use variant 1 (default).
NO = No, do not use variant 1.

Usage Codes: BASE
Param Default: Y (for PLUS ISO Interchange Interface processes)
 NO (for EPS-Net and MDS ISO Interchange Interface processes)

LABEL-TYPE — A code indicating the type of tape label supported by the Interchange Prefix File (IPF) and IPF3 Refresh processes. Valid values are as follows:

IBM = IBM/MVS
DOS = IBM DOS
BUR = Burroughs 5500
BLS = Burroughs Large Scale
NON = Unlabeled

Usage Codes: BASE
Param Default: No default value

LGNT-COUNTRY-ABBR — A code that identifies the country in which this logical network is located. Valid country code values are defined in the ISO 3166 standard, *Codes for the Representation of Names of Countries*. This param is used by some processes to determine the number of decimal places used for display in amount fields. The following processes and objects use this param:

Customer Service Interface object
Customer Table, Customer/Account Relation Table, Customer/Personal ID
Relation Table Server process
IMT Configuration File Server process
Interface Configuration File Server process
Internal Message Translation Interface object
Voice Response Unit Interface object

Achclear process
Archive process
Bank Advice process
Billpay Server process
Cleanup process
Remittance Generator process
Scheduled Transaction Initiator process
Table Maintenance Server process

If the param is not present in the LCONF or contains an invalid value, the processes that access the LCONF for this param and the processes that contain objects that access the LCONF for this param abend during initialization.

Usage Codes: BASE, BPAY, TB
Param Default: No default value

LGNT-CUTOVER — The logical network cutover time expressed in hh:mm format. Valid values are 00:00 through 23:59, based on a 24-hour clock. The time can be entered with or without the colon. This param is used by the following processes and objects:

Enscribe Refresh process
SQL Refresh process
Transaction Based Pricing Report Initiator process

Customer object
Customer Service Interface object
End-of-Period Process object
Internal Message Translation Interface object
Transaction object
Voice Response Unit Interface object

Bank Advice process
Billpay Server process
Remittance Generator process
Scheduled Transaction Initiator process

If the param is not present in the LCONF or contains an invalid value, the processes that access the LCONF for this param and the processes that contain objects that access the LCONF for this param abend during initialization.

Usage Codes: BASE, BPAY, TB
Param Default: No default value

LINK-START-TRACE-NUM — The initial value of the acquirer system trace audit number. The LINK ISO Interchange Interface process uses this param. Valid values are 0 through 999,999.

Usage Codes: BASE
Param Default: 0

LN-IND — A two-character hexadecimal code representing the logical network name specified in the LOGICAL-NET param for this LCONF. The value of this param is used to support the Transaction Security Services process in multiple logical network configurations. It also enables the physical partitioning of the database accessed by the Transaction Security Services process. Valid values are 0 through F.

When adding or updating a BASE24-atm or BASE24-pos Terminal Data files record, the ATD and PTD requester and server processes add the value of this param to the beginning of the terminal ID to create key locator values that are placed in hardware-encrypted key fields (if the SECURE-DEV-TYP param is set to a value of TSS). If the terminal ID for the record being added or updated has more than 14 characters, the last one or two characters are truncated when the key locator value is created. If the LN-IND param does not exist, key locators are set to the full value of the terminal ID.

TSS database conversion programs also use a runtime parameter called LN-IND to create a key locator value when converting existing BASE24 files. When they are run on a BASE24-atm Terminal Data file or BASE24-pos Terminal Data file, the two-character LN-IND value is added to the beginning of the 1–16 character terminal ID. If the terminal ID for the terminal record being converted has more than 14 characters, the last one or two characters are truncated when the key locator value is created.

When converting Key File (KEYF) or Key 6 File (KEY6) records to the TSS database, the two-character LN-IND runtime param value is added to the beginning of a 14-character key locator index value generated by the conversion program.

If you need to partition the TSS database by logical network, the value of the LN-IND LCONF param and the LN-IND runtime parameter used by the TSS database conversion programs must be set to the same value.

If you do not need to partition the TSS database, the LN-IND LCONF param should not be configured and the LN-IND runtime parameter used by the TSS database conversion programs must be set to a value of 00.

The following processes use the LN-IND LCONF param:

- BASE24-atm Terminal Data files requester and server objects
- BASE24-pos Terminal Data files requester and server objects
- BASE24-teller Terminal Data files requester and server objects
- BASE24 Merchant Host Configuration File requester and server objects

For detailed information on key locators, the Transaction Security Services process, and the TSS database, refer to the ***BASE24 Transaction Security Services Processing Guide***.

Usage Codes: ATM, POS, TLR
Param Default: No default value

LOGICAL-NET — The name of the logical network for this LCONF. The LOGICAL-NET param contains one to four alphanumeric characters identifying the valid name of the logical network. This param is used by the BASE24-billpay product to fill in the acquirer logical network in various BASE24-telebanking Standard Internal Message (BSTM) messages sent from BASE24-billpay processes to BASE24-telebanking processes.

This param is used by the following processes and objects:

- BASE24-atm Transaction Analysis utility
- BASE24-atm Authorization process
- BASE24-atm report programs
- BASE24-atm Settlement Initiator process
- BASE24-atm Transaction Context Manager process

- BASE24-billpay Bank Advice process
- BASE24-billpay Billpay Server process
- BASE24-billpay Scheduled Transaction Initiator process

- BASE24-pos Device Handler/Router/Authorization process
- BASE24-pos BNEG Refresh process
- BASE24-pos INEG Refresh process
- BASE24-pos Settlement Initiator process
- BASE24-pos Transaction Analysis utility
- BASE24-pos Stored Value Dormancy/Escheatment program

- BASE24-telebanking Issuer Reporting program

- BASE24-teller Authorization process
- BASE24-teller Device Handler process
- BASE24-teller Transaction Analysis utility

- BASE24 Configuration Manager process
- Enscribe Refresh process
- From Host Maintenance process
- Golden Database Edit File program
- Interchange report programs
- ISO Host Interface process
- ITS Transaction Log File Server process
- Logical Network Configuration File Server process
- SQL Refresh process
- Super Extract process
- Transaction Based Pricing report programs

Customer object
Customer Service Interface object
Voice Response Unit Interface object

If the param is not present in the LCONF or contains an invalid value, the processes that access the LCONF for this param and the processes that contain objects that access the LCONF for this paramabend during initialization.

Note: The BASE24 Pathway system will not initialize without this param defined in the LCONF.

Usage Codes: ATM, BASE, BPAY, FHM, POS, TB, TLR
Param Default: No default value

LOGOFF-INTERVAL — The maximum number of seconds any user in the logical network can remain inactive in the BASE24 CRT access system before being automatically logged off. This param can be overridden for a specific user by setting the LOGOFF INTERVAL field on screen 1 of the Security File (SEC).

Valid values are 00000 through 32,767. A value of 00000 locks users out of the BASE24 CRT access system.

The Security File Server process uses this param.

Usage Codes: BASE
Param Default: 1024

MAIL-HISO-GEN-TRACE-NUM — A flag that indicates whether the ISO Host Interface process is to generate a mail trace number and insert it into the headers of messages it processes or allow the host to generate and insert the trace number.

Y = Yes, generate a trace number and insert it into the message header.
N = No, do not generate a trace number and insert it into the message header.
 Allow the host to generate the trace number.

If this param is missing or invalid, the ISO Host Interface process uses a default value of Y.

Usage Codes: BASE, MAIL
Param Default: Y

MAIL-LN-CUTOVER — The time of day that the BASE24-mail logical network is cut over. All institutions in the logical network must be cut over by this time. This param can be set to any value, expressed in 24-hour time, 00:00 (12:00 a.m.) through 23:59 (11:59 p.m.). The Super Extract process uses this param.

If this param is not present in the LCONF, the Super Extract process abends during initialization.

Usage Codes: BASE, MAIL
Param Default: No default value

MAIL-SEND-RESTRICTED-BY-FIID — A code that indicates whether the ISO Host Interface process is restricted from sending mail messages to terminals owned by another FIID.

Y = Yes, the ISO Host Interface process is restricted from sending mail messages to terminals owned by another FIID.

N = No, the ISO Host Interface process is not restricted from sending mail messages to terminals owned by another FIID.

Usage Codes: BASE, MAIL
Param Default: N

MASK-POFST-PVV — A code that indicates whether the POFST/PVV field on screen 1 of the Cardholder Authorization File (CAF) should be masked. If the param is not found or is invalid, the default value is used. The Cardholder Authorization File Server uses this param.

Y = Yes, mask the POFST/PVV field on screen 1 of the CAF.

N = No, do not mask the POFST/PVV field on screen 1 of the CAF.

Usage Codes: BASE
Param Default: N

MAX-IIF-RECORDS — The maximum number of records allowed in the Institution Identification File (IIF). If this param is set to 0, the Generic Interchange Interface process calculates the number of records in the file. Valid values are 0 through 32,767.

Usage Codes: BASE
Param Default: No default value

MAX-LOGON-ATTEMPTS — The maximum consecutive number of times any user in the logical network can attempt to log on and fail before that user is locked out of BASE24. This param can be overridden for a specific user by setting the MAX LOGON ATTEMPTS field on screen 1 of the Security File (SEC).

Valid values are 00 through 99. A value of 00 indicates that users are not locked out of BASE24 no matter how many of their logon attempts fail. The Security File Server process uses this param.

Usage Codes: BASE
Param Default: 00

MAX-STF-RECORDS — The maximum number of terminals defined in the Switch Terminal File (STF) for an Interchange Interface process. The following processes use this param to determine the amount of extended memory required by the interface:

Banknet Interchange Interface process
Generic Interchange Interface process

If this param is set to a value of 0, enough extended memory for all records in the STF is allocated. Valid values are 0 through 32,767.

Usage Codes: BASE
Param Default: 0

MDS-SPPT-NON-EMV-PIN-CHANGE — A flag indicating whether the ATM allows MasterCard credit and debit cardholders to change PINS on non-chip (magnetic stripe) cards originating from the MasterCard Debit Switch. Valid values are as follows:

Y = Yes, allow PIN changes
N = No, do not allow PIN changes

The following process uses this param:

MDS ISO Interchange Interface process

Usage Codes: BASE
Param Default: N

MIGR-ATM-ADVC-DESTxx — This series of params specifies the names of the ATM migration HISO bridge processes used to handle advice transactions sent between BASE24 and BASE24-eps during migration. Each process or service name must exist in this list, differentiated by a unique two-character value in place of the xx in the param name. This param allows the ATM Authorization process to determine whether the destination of the current message is BASE24-eps so a determination can be made to require a reversal or send an advice. Valid values for the xx replacement are 00 through 50.

Usage Codes: ATM, MIGR

Param Default: None

MIGR-ATM-ENABLE — A value indicating if the ATM Authorization process performs migration-specific authorization processing. A generic param (with the process of *****) must be added with a value of Y as soon as any MIGR-HISO-ENABLE param has been added for a specific migration HISO bridge process. The authorization process can then perform migration specific authorization processing, including processing log-only migration transactions sent from BASE24-eps. If no migration HISO bridge processes are used, this param is set to N. Valid values are as follows:

Y = The BASE24 ATM Authorization process will perform migration-specific processing

N = No migration processing is being performed

Usage Codes: ATM, MIGR, NETW

Param Default: N

MIGR-ATM-HISO-DEST — The name of a migration HISO bridge process, or the service to which it belongs. This process/service name is used to send log-only transactions and advices to BASE24-eps.

Usage Codes: ATM, MIGR

Param Default: None

MIGR-ATM-PROCESSING-OPTS — Defines the ATM migration processing option to be performed. Valid values are as follows:

0 = No log-only or advices sent to BASE24-eps for journaling.

1 = Send only log-only information to BASE24-eps for journaling.

2 = Send only advices to BASE24-eps for journaling.

3 = Send both log-only and advices to BASE24-eps for journaling.

Usage Codes: ATM, MIGR
Param Default: 0

MIGR-FHM-HISO-ENABLE — This param specifies whether this HISO process performs any migration-specific FHM processing. A generic param (with the process of *****) will exist and be set to a value of 'Y' as soon as any Hot Card Status update requests from the HOST need to be forwarded to a BASE24 migration HISO bridge process to be sent on to BASE24-eps for interface processing on that system. If no migration HISO process is being used, this param should be set to a value of 'N'. Valid values are as follows.

Y = This HISO process will perform migration-specific processing
N = No migration processing is being performed

Usage Codes: ATM, MIGR, NETW, POS
Param Default: N

MIGR-HISO-ENABLE — An indicator the HISO process is acting as a migration HISO bridge. A generic param (with the process of *****) must be set to N to ensure all HISO processes configured to communicate with a HOST will not perform any migration-specific processing. A specific param (with the process name identified) must be added for each HISO process acting as a migration HISO bridge. Valid values are as follows:

Y = This HISO process configured to communicate with a HOST will perform migration-specific processing.
N = This HISO process configured to communicate with a HOST will not perform any migration-specific processing.

Usage Codes: ATM, MIGR, NETW, POS
Param Default: N

MIGR-HISO-NAME Identifier — This series of params specifies the service or symbolic name of a BASE24 interface process that has been migrated from BASE24 to BASE24-eps, and the corresponding BASE24 migration HISO bridge process name that will be used to communicate with the interface on BASE24-eps. It is used by the FHM HISO process to determine whether Hot Card Status update requests should be forwarded to interfaces on BASE24 or on BASE24-eps. The value is in the form of BASE24 Interface name/BASE24 migration HISO process name. For example: P1A^STAR/P!A^MIGRHISO1

Each MIGR-HISO-NAME param contains the name of one service or process that has migrated to BASE24-eps. When multiple interface processes or services have been migrated, this param will include an optional identifier to specify params used for the different processes or services in the same logical network. The optional identifier is usually a number but can be any unique set of characters that have not already been declared by another MIGR-HISO-NAME identifier param.

Generic params (with the process of *****) will exist and be set to the correct process names as soon as any Hot Card Status update requests from the HOST need to be forwarded to a BASE24 migration HISO bridge process to be sent on to BASE24-eps for interface processing by that system. If no migration HISO process is being used, these params do not need to exist.

A maximum of 50 params can be added.

Usage Codes: ATM, MIGR, NETW, POS
Param Default: None

MIGR-INTF-DPC-NUM — The DPC number used by the BASE24 HISO process when sending messages to BASE24-eps, and no valid DPC number is already available in the message. Valid values are in the range 0 through 9,999.

Usage Codes: ATM, MIGR, NETW, POS
Param Default: 9999

MIGR-POS-ADVC-DESTxx — This series of params specifies the names of the POS migration HISO bridge processes used to handle advice transactions sent between BASE24 and BASE24-eps during migration. Each process or service name must exist in this list, differentiated by a unique two-character value in place of the xx in the param name. This param allows the ATM Authorization process to determine whether the destination of the current message is BASE24-eps so a determination can be made to require a reversal or send an advice. Valid values for the xx replacement are 00 through 50.

Usage Codes: MIGR, POS
Param Default: None

MIGR-POS-ENABLE — A value indicating if the POS Router Authorization process performs migration-specific authorization processing. A generic param (with the process of *****) must be added with a value of Y as soon as a MIGR-HISO-ENABLE param has been added for a specific migration HISO bridge process. The POS Router authorization process can then perform

migration specific authorization processing, including processing log-only migration transactions sent from BASE24-eps. If no migration HISO bridge processes are used, this param is set to N. Valid values are as follows:

Y = The BASE24 POS Router Authorization process will perform migration-specific processing

N = No migration processing is being performed

Usage Codes: MIGR, NETW, POS

Param Default: N

MIGR-POS-HISO-DEST — The name of a migration HISO bridge process, or the service to which it belongs. This process/service name is used to send log-only transactions and advices to BASE24-eps.

Usage Codes: MIGR, POS

Param Default: None

MIGR-POS-PROCESSING-OPTS — Defines the POS migration processing option to be performed. Valid values are as follows:

0 = No log-only or advices sent to BASE24-eps for journaling.

1 = Send only log-only information to BASE24-eps for journaling.

2 = Send only advices to BASE24-eps for journaling.

3 = Send both log-only and advices to BASE24-eps for journaling.

Usage Codes: MIGR, POS

Param Default: 0

MLF-NOTIFY-INTERVAL — The number of writes made to the Maintenance Log File (MLF) before calculating the percentage of file full. Each time a write is made to the MLF, a counter is increased. When the counter is equal to the value in this param, the PLUS ISO Interchange Interface process calculates how full the MLF is. The counter is then reset to zero. When the file reaches the percent full specified in the MLF-NOTIFY-PERCENTAGE param, the PLUS ISO Interchange Interface process generates an event message indicating that the file is becoming full. The PLUS ISO Interchange Interface process continues to generate event messages indicating that the file is becoming full at the interval specified in this param. Valid values are 10 through 32,766.

Usage Codes: BASE

Param Default: 50

MLF-NOTIFY-PERCENTAGE — The percentage of used file space at which the PLUS ISO Interchange Interface process generates an event message indicating that the Maintenance Log File (MLF) is becoming full. The PLUS ISO Interchange Interface process continues to generate event messages at the interval indicated in the MLF-NOTIFY-INTERVAL param. Valid values are 10 through 99.

Usage Codes: BASE
Param Default: 70

MONAD-NOTIFY-PROCESS — The ACI Smart Chip Manager DPC number and ISO Host Interface process name, which are used to route messages from BASE24 to the ACI Smart Chip Manager product. ACI Smart Chip Manager is a card management system for multifunctional or multi-application smart cards. The ACI Smart Chip Manager application supports issuing multi-application cards and manages the lifecycles of these cards and the lifecycles of the card's applications. BASE24 can be configured as a smart card application optionally managed by ACI Smart Chip Manager; therefore, when updates are made to the BASE24 Cardholder Authorization File (CAF), the applicable updates are forwarded to the ACI Smart Chip Manager product for updating the ACI Smart Chip Manager database.

When the ACI Smart Chip Manager functionality is being used, an ISO Host Interface must be configured to communicate with the ACI Smart Chip Manager application. The ISO Host Interface process must include the BASE24-from host maintenance ISO Host Interface module.

The BASE24-from host maintenance uses the values in this params to forward applicable CAF add, update, delete, and increment messages to an ISO Host Interface process that supports BASE24-from host maintenance and applicable connections to ACI Smart Chip Manager. If a station and line are configured to ACI Smart Chip Manager, messages can be sent online. If a station or line is not configured, or if the online connection is unavailable, these messages are written to the Store-and-Forward File (SAF). The SAF can be extracted and sent to ACI Smart Chip Manager in SAF extract tape or file format.

If no lines or stations are configured, or if the online connection is unavailable to the ACI Smart Chip Manager application, the ISO Host Interface logs the CAF add, update, and delete messages to the SAF.

This optional param is formatted as “XXXXXXXXXXXXXXXXXXXX,” where “XXXX” is the DPC number and “XXXXXXXXXXXXXXXXXXXX” is the ISO Host Interface process name. BASE24 users implementing this enhancement must configure an ISO Host Interface to communicate with the ACI Smart Chip Manager application.

MULT-LN-PIN-KEY — A value containing PIN encryption key information used to reencrypt PINs on transactions passed between logical networks in a BASE24 system with multiple logical networks. This param is set at the logical network level.

In BASE24 logical networks that do not use the Transaction Security Services process, this value is 16 hexadecimal characters representing an encrypted single-length PIN encryption key.

In BASE24 logical networks using the Transaction Security Services process, this value is a 16-character hexadecimal value indicating the key locator value to a common PIN encryption key in the Interface Security Data Source (ISECD) in the Transaction Security Services (TSS) database. The encryption key can be single, double, or triple length. This param is configured in one of the following circumstances:

- When migrating to a single TSS database for all logical networks. You can delete this param when all logical networks point to the TSS database.
- When using multiple TSS databases for multiple logical networks. This param must be left in place after migration to multiple TSS databases.

If a Thales e-Security device is in use, the common PIN key must be a Zone PIN Key (ZPK). A Terminal PIN Key (TPK) cannot be used because no Thales e-Security PIN translation commands translate to TPKs.

The following processes use this param, however it must be configured with a value of all asterisks in the READ BY field on the LNCF Param screen:

BASE24-atm Authorization
BASE24-atm ISO Host Interface
BASE24-pos Device Handler/Router/Authorization
BASE24-pos ISO Host Interface

Refer to the *BASE24 Transaction Security Services Processing Guide* for more information about multiple TSS databases.

Usage Codes: ATM, POS
Param Default: No default value

NCD-DFLT-HOPR-CONTENTS — A code indicating the default hopper contents an Interchange Interface process adds to Non-Currency Dispense transactions. The following processes use this param:

PLUS ISO Interchange Interface process
MDS ISO Interchange Interface process

The value of this param should match a value in the NCD-CONTENTS table in the COBNAMES file. Valid values are defined in the NCD-CONTENTS table.

Usage Codes: BASE
Param Default: 10

NETWORK-ID — A value indicating the network the VisaNet ISO Interchange Interface process uses for transmission of messages. Valid values are as follows:

0002 = VisaNet (Default)
0003 = Interlink
0004 = Plus

Usage Codes: BASE
Param Default: 0002

NO-MANUAL-ENTRY-CARD-TYPES — A list of card types for which key entry is not permitted at a POS device. Up to 20 card types can be defined in this param. The format for this param is *ct;ct;ct;ct*, where *ct* is a valid card type. The *c* character must be an alphabetic character or a wildcard character (i.e., an asterisk), and the *t* character must be an alphanumeric character, a space, or an asterisk. If the EPS-Net Interchange Interface process finds a match between the value in the SRV field of the POS Standard Internal Message (PSTM) and one of the values listed in this param, it checks whether the transaction data was manually entered. If so, the transaction is denied. The EPS-Net Interchange Interface process uses this param.

Usage Codes: BASE, POS
Param Default: No default value

OMF-AUDIT — A code controlling the extent of record or row logging to the Online Maintenance File (OMF) by file maintenance server processes, table maintenance server processes, or other processes, or row logging to the Online Maintenance Table (OMT) by table maintenance server processes. The Security File Server process returns the value to RQMEGA each time a user logs on. RQMEGA places this value in a user context area for use by other server processes. The following processes read this param:

Security File Server process
Logical Network Configuration File Server process
Base Control Server process
Integrated Transaction Services Control Server process

Valid values are as follows:

- 0 = No OMF or OMT auditing.
- 1 = Audit record and MSG-HEADER information.
- 2 = Audit MSG-HEADER information only, do not include the record or row image.

The following processes also either read this param or use the param value after it has been read by another process:

BASE24 file maintenance server processes
BASE24 Configuration Manager process

BASE24-billpay Table Maintenance Server process
Achclear process
Archive process
Billpay Server process
Cleanup process
Scheduled Transaction Initiator process
Table Maintenance Server process

BASE24-check auth table maintenance server processes

BASE24-frequent shopper table maintenance server processes

BASE24-refunds table maintenance server processes

BASE24-telebanking table maintenance server processes

Note: The BASE24 Pathway system will not initialize without this param defined in the LCONF.

Usage Codes: ATM, BASE, BPAY, CHKA, FRSH, POS, RFND, TB, TLR
Param Default: 1

OMF-RETENTION-PERIOD — The number of days worth of Online Maintenance Files (OMFs), prior to the current business day, that are to remain on the system.

The following processes use this param:

OMF Super Extract process
Security File Server process

After the number of days indicated, the OMF is deleted from the system by the OMF Super Extract process or the Security File Server process.

Valid values used by the OMF Super Extract process are 3 through 99 with a default of 7. Valid values used by the Security File Server process are 00 through 99 with a default of 00. A value of 00 indicates that the Security File Server process does not automatically delete the OMF; the OMF must be deleted manually.

Note: The OMF is generally very large. Having a high value for the OMF-RETENTION-PERIOD param causes the retained OMFs to occupy a significant portion of disk space.

Usage Codes: ATM, BASE, BPAY, CHKA, FRSH, POS, RFND, TB, TLR
Param Default: 00

OMF-SPECIAL — A code indicating whether additional information should be written to the OMF or OMT. Additional information includes UFIR and UPFR records that have been added, modified, or deleted. It also includes the entire SEC record when screen access records have been updated using the Security File Server process. Valid values are as follows:

Y = Yes, write additional information to the OMF or OMT.
N = No, do not write additional information to the OMF or OMT.

Usage Codes: BASE, CHKA, RFND
Param Default: N

OVRD-INST-ID-FLDS — A code indicating whether the institution ID is overridden with the value from the SWI-ID field or the value from the DFLT-ACQ-ID-NUM field from the ICFE record.

When formatting a message to be sent to the interchange, the BIC ISO Interchange Interface process uses the override institution ID value for the appropriate field, based on this LCONF setting.

When formatting messages received from the interchange, the BIC ISO Interchange Interface process uses the override institution ID value for the acquiring institution ID or the receiving institution ID if the corresponding field does not have a value assigned in the internal or external message. The BIC ISO Interchange Interface process does not use the override institution ID value for the forwarding institution ID; this value is updated with a default value by the ATM Authorization process or the POS Router/Authorization module.

The BIC ISO Interchange Interface process uses this param. Valid values are as follows:

- 0 = Do not override institution ID values.
- 1 = Override acquiring institution ID only.
- 2 = Override forwarding institution ID only.
- 3 = Override acquiring and forwarding institution ID.
- 4 = Override receiving institution ID.
- 5 = Override acquiring and receiving institution ID.
- 6 = Override forwarding and receiving institution ID.
- 7 = Override acquiring, forwarding, and receiving institution ID.

Usage Codes: ATM, EMV, POS

Param Default: 0

PASSWORD-CHNG-INTERVAL — The number of days after which each user in the logical network must change passwords. Valid values are 00 through 99. A value of 00 indicates that users are not required to change their passwords. The Security File Server process and requester use this param.

Usage Codes: BASE

Param Default: 30

PASSWORD-COMPLEX — Turns on BASE24 Complex Passwords. If this param is set to the value Y, all passwords are case sensitive and other complex password params are evaluated when setting new passwords. These related params are used to set how complex passwords work. Valid values for this param are as follows:

Y = Yes, set all passwords to be case sensitive. Evaluate other complex password params.

N = No, do not set any passwords to be case sensitive. Ignore other complex password params.

Note: When this param is set to a value of Y, changes are made to the password fields in the Security File (SEC) to indicate the network is using complex passwords. These changes cannot be undone. If you believe you will turn complex passwords off after turning them on for a period of time (e.g., in a test system), you should make a backup of the SEC before setting this param to a value of Y.

Usage Codes: BASE

Param Default: N

PASSWORD-LENGTH-MIN — The minimum number of characters for all passwords. Valid values are 2 through 8. The Security File Server process and requester use this param.

Usage Codes: BASE

Param Default: 2

PASSWORD-MAX-CHNG-PER-DAY — Sets the maximum number of password changes allowed per day. If the PASSWORD-COMPLEX param is set to the value Y, this param is used to identify the maximum number of password changes allowed per day.

The value of this param must be less than or equal to the value of the PASSWORD-MAX-STORE param. If this criteria is not met, the PASSWORD-MAX-STORE param is set to the value of the PASSWORD-MAX-CHNG-PER-DAY param when the security server initializes. Valid values are 00 through 10. A value of zero indicates there is no maximum for the number of times a password can change each day.

Usage Codes: BASE

Param Default: 0

PASSWORD-MAX-STORE — Determines the number of passwords stored in the PASSWORD-HISTORY array. If the PASSWORD-COMPLEX param is set to the value Y, this param identifies the number of passwords stored in the PSWD-HIST of the SEC record. Passwords kept in the PSWD-HIST cannot be used when setting a new password.

The value of this param must be less than or equal to the value of the PASSWORD-MAX-CHNG-PER-DAY param. If this criteria is not met, the PASSWORD-MAX-STORE param is set to the value of the PASSWORD-MAX-CHNG-PER-DAY param when the security server initializes.

Valid values are 1 through 10. A value of one indicates only the current password is stored.

Usage Codes: BASE

Param Default: 1

PASSWORD-NUM-ALPHA — Sets the minimum number of alphabetic characters required in a new password. If param PASSWORD-COMPLEX is set to Y, this param sets the minimum number of alphabetic characters required in a new password. Valid values are 0 through 8. A value of zero indicates no minimum number of alphabetic characters is required in the password.

The sum of the PASSWORD-NUM-ALPHA, PASSWORD-NUM-NUMERIC, and PASSWORD-NUM-SPCL params must not exceed 8. If this criteria is not met, all three params are set to their default value (zero) when the security server initializes in order to allow processing to continue. The user must update these params with valid values that do not exceed a total of 8 characters, then restart the Security Server.

If this param is not present in the LCONF or contains an invalid value, the default value is used.

Usage Codes: BASE

Param Default: 0

PASSWORD-NUM-NUMERIC — Sets the minimum number of numeric characters required in a new password. If the PASSWORD-COMPLEX param is set to the value Y, this param identifies the minimum number of numeric characters required in a new password. Valid values are 0 through 8. A value of zero indicates no minimum number of numeric characters is required in the password.

The sum of the PASSWORD-NUM-ALPHA, PASSWORD-NUM-NUMERIC, and PASSWORD-NUM-SPCL params must not exceed 8. If this criteria is not met, all three params are set to their default value (zero) when the security server initializes in order to allow processing to continue. The user must update these params with valid values that do not exceed a total of 8 characters, then restart the Security Server.

If this param is not present in the LCONF or contains an invalid value, the default value is used.

Usage Codes: BASE

Param Default: 0

PASSWORD-NUM-SPCL — Sets the minimum number of special characters required in a new password. If param PASSWORD-COMPLEX is set to Y, this param sets the minimum number of special characters required in a new password. Valid values are 0 through 8. A value of zero indicates no minimum number of special characters is required in the password.

The sum of the PASSWORD-NUM-ALPHA, PASSWORD-NUM-NUMERIC, and PASSWORD-NUM-SPCL params must not exceed 8. If this criteria is not met, all three params are set to their default value (zero) when the security server initializes in order to allow processing to continue. The user must update these params with valid values that do not exceed a total of 8 characters, then restart the Security Server.

If this param is not present in the LCONF or contains an invalid value, the default value is used.

Usage Codes: BASE

Param Default: 0

PCI-DISPOSITION — This param instructs the SKELB library what action it should take when a Guardian error occurs on the Log Message Configuration File (LMCF) during the initialization or warmboot of an XPNET satellite process. Valid values are as follows:

A = Abend

C = Continue processing, but do not perform PCI masking

If this parameter is present and has the value "A", SKELB will cause the process to abend. If this parameter is not present or does not have the value "A", SKELB will log an event message warning that it cannot perform PCI masking or truncation, and the process will continue as normal.

Usage Codes: BASE

Param Default: C

PIT-NAM-ALGO — A flag indicating whether the BASE24-telebanking and BASE24-billpay products support a name token generation algorithm, such as Soundex. This param is used by the following processes and objects:

Customer Access object
From Host Maintenance process
Personal Information Table Server process
SQL Refresh process
Billpay Server process

If this param is set to the value Y, BASE24 processes and objects generate a family name token and a given name token for the specified Personal Information Table (PIT) row. Name tokens allow the system to match names that approximate the customer name entered by an operator or a customer service representative.

If this param is set to the value Y, operators and customer service representatives should always attempt to enter the full customer name as accurately as possible to effectively narrow the search for the configured customer information.

If this param is set to the value N, operators and customer service representatives should enter only as many characters of the customer name that they know to be correct. If they misspell the name, the system may not be able to find the configured customer information and an error message may be displayed. Valid values are as follows:

Y = Yes, the BASE24-telebanking and BASE24-billpay products support a name token generation algorithm.

N = No, the BASE24-telebanking and BASE24-billpay products do not support a name token generation algorithm.

If the param is not present in the LCONF or contains an invalid value, the processes and objects listed above use the default value.

Usage Codes: BPAY, FHM, TB

Param Default: Y

PIT-PRESENT — A flag indicating whether the Personal Information Table (PIT) is supported. The following processes and objects use this param:

Customer Access object
Billpay Server process

This param must be set to the value Y if the BASE24-billpay product is installed. Valid values are as follows:

Y = Yes, the Personal Information Table (PIT) is supported.
N = No, the Personal Information Table (PIT) is not supported.

If the param is not present in the LCONF or contains an invalid value, the processes and objects listed above use the default value.

Usage Codes: BPAY, TB
Param Default: Y

PLUS-ADMIN-NOTIFY-INTERVAL — The number of writes made to the PLUS Administrative Message file (PAM) before calculating the percentage of file full. Each time a write is made to the PAM, a counter is increased. When the counter is equal to the value in this param, the PLUS ISO Interchange Interface process calculates how full the PAM is. The counter is then reset to zero.

When the file reaches the percent full specified in the PLUS-ADMIN-NOTIFY-PERCENTAGE param, the PLUS ISO Interchange Interface process logs an event message indicating that the file is becoming full. The PLUS ISO Interchange Interface process continues to log event messages indicating that the file is becoming full at the interval specified in this param. Valid values are 10 through 32,766.

Usage Codes: BASE
Param Default: 50

PLUS-ADMIN-NOTIFY-PERCENTAGE — The percentage of used file space at which the PLUS ISO Interchange Interface process logs an event message indicating that the PLUS Administrative Message file (PAM) is becoming full.

The PLUS ISO Interchange Interface process continues to log event messages at the interval indicated in the PLUS-ADMIN-NOTIFY-INTERVAL param. Valid values are 10 through 99.

Usage Codes: BASE

Param Default: 70

PRE-VERIFIED-PIN-PAD-CHAR — Specifies the value to be repeated in a PIN block to identify the PIN as pre-verified. The default value is F, but it is possible for an actual encrypted PIN to result in a PIN block value of all Fs. If used, this value should be set to a non-hexadecimal character (i.e., a character other than 0-9 or A-F) because the use of any repeated hexadecimal character could have the same issue as the F character. If this value is set, the host must also be modified to recognize the new pre-verified PIN block character.

BASE24-pos Note: BASE24-pos transactions may or may not contain a PIN, and authorizing systems must be able to differentiate between transactions with a pre-verified PIN and transactions that do not contain a PIN (i.e., that were not entered with a PIN). Therefore, for incoming and outgoing BASE24-pos transactions, a PIN block containing this LCONF pad character is always used to indicate a PIN has been pre-verified. The absence of the P-52 (Personal Identification Number Data) data element in the external message is used to indicate the transaction did not contain a PIN (for incoming BASE24-pos messages, a space-filled P-52 data element is also acceptable to indicate the transaction did not contain a PIN).

BASE24-atm and BASE24-teller Note: BASE24-atm and BASE24-teller transactions always require a PIN. Therefore, for these product transactions, a pre-verified PIN can be accurately identified by the absence of the P-52 (Personal Identification Number Data) data element in the external message. For outgoing messages, BASE24-atm and BASE24-teller always identify a pre-verified PIN by omitting the P-52 data element. For incoming messages, the host has several options—BASE24-atm and BASE24-teller assumes a PIN has been pre-verified if the P-52 data element is omitted, contains spaces, or is filled by the pad character specified in this param.

The following processes use this param:

BIC ISO Interchange Interface process

ISO Host Interface process: Usage Codes should specify ATM, POS, or Teller

PRI-TIM-LMT — The maximum time, in hundredths of seconds, the application waits for the call to the WRITE procedure to complete. This param is used when logging to the primary EMS Collector process. Valid values are 0 through 2,147,483,647.

The following processes use this param:

Base Extended Memory Table Build utility
ITS Kernel Extended Memory Table Build utility
BASE24-telebanking Issuer Reporting program
Event object
SQL Refresh process

Usage Codes: BASE, KNL, TB
Param Default: 300

PSEUDO-3DES-CBC-MAC-TYPE — Specifies whether to use the Pseudo 3DES Cipher Block Chaining method of MACing instead of the default 3DES Cipher Block Chaining method. Valid values are as follows:

Y = Yes, use the Pseudo 3DES Cipher Block Chaining method.
N = No, use the 3DES Cipher Block Chaining method (default).

The following processes use this param:

BIC ISO Interchange Interface process
ISO Host Interface process: Usage Codes should specify ATM, POS, or Teller

PS2000-ACQ-DATA-LOC — A value indicating the offset into the PSTM user data, which the VisaNet ISO Interchange Interface process uses to store PS2000 data for acquirer traffic (i.e., outbound transactions to the VisaNet interchange). Valid values are 0 through 150. BASE I acquirers use 24 bytes of the PSTM user data. Debit acquirers use 50 bytes of the PSTM user data. This param is required for release 4.0 and above.

Usage Codes: BASE
Param Default: 0

PS2000-ISS-DATA-LOC — A value indicating the offset into the PSTM user data, which the VisaNet ISO Interchange Interface process uses to store S2000 data for issuer traffic (i.e., inbound transactions from the VisaNet interchange).

Valid values are 0 through 117. BASE I issuers use 24 bytes of the PSTM user data. Debit issuers use 83 bytes of the PSTM user data. This param is required for release 4.0 and above.

Usage Codes: BASE

Param Default: 0

RAM-MSG-MDFY — A code indicating whether incoming or outgoing messages to the Remote Application Manager (RAM) process require STX/ETX control character modification. Valid values are as follows:

0 = No, STX/ETX control character modification is not required.

1 = Yes, STX/ETX control character modification is required.

Usage Codes: BASE

Param Default: 0

RACAL-ANSI-METHOD — Specifies whether to use the ANSI X9.17 Encryption Method for key exchanges instead of the default Variant Encryption Method used by the ISO Host Interface process. The ANSI X9.17 Encryption Method can be used with a Thales (formerly Racal) Hardware security module. Valid values are as follows:

Y = Yes, use ANSI X9.17 encryption method.

N = No, use Variant encryption method.

The following processes use this param:

Banknet Interchange Interface process
BIC ISO Interchange Interface process
Generic Interchange Interface process
ISO Host Interface process
MDS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

The usage Codes should be BASE.

REF-BYPASS-PARITY-ERRORS — The maximum number of tape parity errors that can be encountered without causing the Enscribe or SQL Refresh process to abend. The Enscribe and SQL Refresh processes use this param. Valid values are as follows:

-1 = Bypass all tape parity errors.
0–32767 = Bypass the indicated number of tape parity errors.

This param can be overridden by the value the operator specifies in the startup command issued using the Refresh (REFR) screens or a network control facility.

Usage Codes: BASE, TB
Param Default: 0

REF-FUP-CPU — The CPU in which the HP NonStop File Utility Program (FUP) runs for a full-file refresh. The Enscribe Refresh process uses this param for all full-file refreshes. If two or more full-file refreshes are to run concurrently, an Enscribe Refresh process name can be specified in this param. Including an Enscribe Refresh process name enables the network to specify a different CPU for each FUP process. This param can be set to any value from 0 through 15.

Example: 01
Usage Codes: BASE
Read By: A symbolic name is required in this field if each FUP process is to run in a different CPU.
Param Default: CPU in which the Enscribe Refresh process is running

REF-IMPACT-TABLE-SIZE — The number of bytes the Enscribe Refresh process must reserve in memory to build an internal table for use during PBF partial-file refreshes with impacting. Valid values are 1 through 100,000. The Enscribe Refresh process uses this param.

Usage Codes: BASE
Param Default: 5000

REFR-INPUT-DATA-SORTED — A code that identifies whether the Enscribe Refresh process allows input data records to be unsorted. Valid values are as follows:

N = No, unsorted data is not allowed.
Y = Yes, unsorted data is allowed.

Usage Codes: BASE
Param Default: N

REFR-MAX-RECS-UNSORTED — The number of records that are passed from the Refresh process to FUP in the LOAD command. The value in this field is used to calculate the size of the scratch file used to sort the unsorted input data records before loading to the destination file. Valid values are 1 through 2,147,483,647 (the maximum size of a doubleword integer). The Enscribe Refresh process uses this param.

Usage Codes: BASE
Param Default: 10,000

REF-MONITOR-COMMAND — The number of file records or table rows to process between checking for a command from a network control operator. Each time the Enscribe Refresh process reads a record from the input file, or from a transaction log file during impacting, the Enscribe Refresh process increases a counter by one. Each time the SQL Refresh process reads a row from the input table, the SQL Refresh process increases a counter by one. When the counter is equal to the value specified in this param, the Enscribe or SQL Refresh process checks \$RECEIVE for a message from the network. The counter is reset to 0. If there are no messages waiting, the Enscribe or SQL Refresh process continues processing as normal. If a message is waiting, the Enscribe or SQL Refresh process performs processing according to the message received.

Usage Codes: BASE, TB
Param Default: 5000

REF-NOTIFY^{identifier} — The name of a process or service that the Enscribe Refresh process must notify after new files are generated during a full-file refresh. The Enscribe Refresh process uses this param for all full-file refreshes except a full-file refresh of the Switch Dispute File (SDF). The Enscribe Refresh process uses the REF-SWI-NOTIFY param for SDF full-file refreshes.

For a full-file or partial-file refresh of the No Book File (NBF), Positive Balance File (PBF), Stop Payment File (SPF), or Warning/Hold/Float File (WHFF) for BASE24-teller, the Enscribe Refresh process uses the REF-TLR-NOTIFY param instead of this param.

The Enscribe Refresh process uses this param. If broadcast messages are not used, a maximum of 150 processes can be notified. This param can contain the name of a service or the symbolic name of a process such as BASE24-atm Authorization process, a BASE24-pos Device Handler/Router/Authorization process, or a BASE24-from host maintenance process (for example, P1A^AUTH1).

Each REF-NOTIFY param contains the name of one process or service. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params or services used for different processes. The optional *identifier* is usually a number; however, it can be any unique set of characters. For example, REF-NOTIFY1 could contain the P1A^AUTH1 process and REF-NOTIFY2 could contain the P1A^AUTH2 process.

If REF-NOTIFY params are not present in the LCONF, the Enscribe Refresh process assumes no processes are to be notified after a full-file refresh.

If the REF-NOTIFY param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Enscribe Refresh process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Usage Codes: BASE
Param Default: No default value

REF-PBF-LOCKOUT-FACTOR — The number of Positive Balance File (PBF) records to be locked on disk at one time and then updated from the memory table during a partial-file refresh of the PBF. Using this param, the Enscribe Refresh process determines the amount of extended memory to allocate for this table. Valid values are 1 through 1,808.

Usage Codes: BASE
Param Default: 20

REF-PRE-ALLOCATE-EXTENTS — The number of extents to allocate prior to the start of a full-file refresh to ensure that adequate disk file space is available to complete an entire refresh of the file. The Enscribe Refresh process uses this param during full-file refreshes.

If this param is not present in the LCONF or contains an invalid value, the Enscribe Refresh process does not allocate any extents prior to the beginning of a refresh. If the Enscribe Refresh process cannot allocate the number of extents

specified in this param, the process abends during initialization. After the file is built, the Enscribe Refresh process deallocates whatever extents were not used. Valid values are 0 through 16.

Usage Codes: BASE

Param Default: 0

REF-RGCF-RETN-PRD — The number of days to retain Refresh Group Control File (RGCF) records. This number of days is the difference between the current date and time and the RGCF tape date and tape time values in the header record of the Refresh input file. After the number of days specified in this param, the Enscribe or SQL Refresh process deletes RGCF records from the file.

Valid values are as follows:

- 1 = Do not delete RGCF records from the file.
- 0 = Delete the RGCF record immediately once the refresh is complete.
- 1–3650 = Delete RGCF records from the system after this number of days.
 This range of values allows the system to retain records from one day to ten years, not regarding leap years.

Usage Codes: BASE, TB

Param Default: 7

REF-SWI-NOTIFY*identifier* — A process or service that the Enscribe Refresh process must notify after a full-file refresh of the Switch Dispute File (SDF).

The Enscribe Refresh process uses this param. If broadcast messages are not used, a maximum of 150 processes can be notified. This param can contain the name of a service or the symbolic name of an Interchange Interface process that uses the SDF.

Each REF-SWI-NOTIFY param contains the name of one service or Interchange Interface process. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services. The optional identifier is usually a number; however, it can be any unique set of characters.

If no REF-SWI-NOTIFY params are present in the LCONF, the Enscribe Refresh process does not notify any processes after a full-file refresh of the SDF.

If the REF-SWI-NOTIFY param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Enscribe Refresh process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Usage Codes: BASE
Param Default: No default value

REF-TLR-NOTIFY*identifier* — The name of a service or BASE24-teller Authorization process that the Enscribe Refresh process must notify after a full-file or partial-file refresh of the No Book File (NBF), Positive Balance File (PBF), Stop Payment File (SPF), or Warning/Hold/Float File (WHFF).

The Enscribe Refresh process uses this param. If broadcast messages are not used, a maximum of 150 BASE24-teller Authorization processes can be notified. This param can contain the name of a service or the symbolic name of a BASE24-teller Authorization process (for example, P1A^TAUTH1).

Each REF-TLR-NOTIFY param contains the name of one process or service. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services. The optional *identifier* is usually a number; however, it can be any unique set of characters. For example, REF-TLR-NOTIFY1 could contain the P1A^TAUTH1 process and REF-TLR-NOTIFY2 could contain the P1A^TAUTH2 process.

If REF-TLR-NOTIFY params are not present in the LCONF, the Enscribe Refresh process assumes no BASE24-teller processes are to be notified after a full-file or partial-file refresh of the NBF, PBF, SPF, or WHFF.

If the REF-TLR-NOTIFY param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Enscribe Refresh process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Usage Codes: BASE
Param Default: No default value

REFR-PBF-EARLY-NOTIFICATION — A flag indicating whether Refresh early notification is enabled. If this flag is set to yes, the Enscribe Refresh process notifies the Authorization processes immediately after data is loaded on to the new PBF without waiting for impacting to be completed. Valid values are as follows:

N = No, refresh early notification is disabled.

Y = Yes, refresh early notification is enabled.

Used by the Enscribe Refresh process.

Usage Codes: BASE

Param Default: No default value

REMOTE-TERMINAL-BRANCH-ID — The branch identifier used within the BASE24-atm system for remote terminals. This is an optional param used by the LINK ISO Interchange Interface process. Valid values are 4 characters containing alphanumeric characters or asterisks (*).

Usage Codes: ATM, BASE

Param Default: No default value

RESUB-CNFG — A flag indicating whether an Interchange Interface process allows resubmissions to be processed in the BASE24 environment. Valid values are as follows:

N = No, resubmissions are not processed.

Y = Yes, resubmissions are processed.

The following processes use this param:

Generic Interchange Interface process

PLUS ISO Interchange Interface process

VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

RESUB-LOG-PTLF — A flag indicating whether an Interchange Interface process logs resubmissions to the POS Transaction Log File (PTLF). The initial submittal is always logged to the PTLF. Valid values are as follows:

A = Yes, send all log only resubmittals to the PTLF.
N = No, never send a log only resubmittal to the PTLF
Y = Yes, but send only the final submittal to the PTLF

The following processes use this param:

Generic Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE, POS
Param Default: N

RESUB-MAX-DAYS-LIMIT — The maximum number of days a transaction can be resubmitted by the VisaNet ISO Interchange Interface process before it is deleted from the Resubmittal Store-and-Forward File (RSAF). Valid values are 1 through 30.

Usage Codes: BASE
Param Default: 9

RESUB-MAX-LIMIT — The maximum number of times an Interchange Interface process can resubmit a transaction before it is deleted from the Resubmittal Store-and-Forward File (RSAF). Valid values are 1 through 30. The following processes use this param:

Generic Interchange Interface process
PLUS ISO Interchange Interface process

Usage Codes: BASE
Param Default: 30

RESUB-TIME — The time of day (hh:mm) at which an Interchange Interface process starts sending resubmittal transactions to an interchange. This param is required if the BASE24 system is configured to process resubmissions. Valid values are 00:00 through 23:59. The following processes use this param:

Generic Interchange Interface process
PLUS ISO Interchange Interface process

Usage Codes: BASE
Param Default: No default value

REVERSAL-BAL-INQ

REVERSE-BAL-INQ — A code indicating whether balance inquiry transactions should be reversed if they do not complete as intended. The BIC ISO Interface process uses the REVERSAL-BAL-INQ param and the following processes use the REVERSE-BAL-INQ param:

BASE24-atm Diebold 10XX/478X Device Handler process
BASE24-atm Fujitsu 7000 Device Handler process
BASE24-atm Docutel ETS 5100/5200 Device Handler process
BASE24-atm Burroughs RT650 Device Handler process
BASE24-atm Diebold 910/911 Device Handler process
BASE24-pos Standard POS Device Handler module
Generic Interchange Interface process
ISO Host Interface process
VisaNet ISO Interchange Interface process

Valid values are as follows:

True, T, or 1 = Reversals can be generated for balance inquiries.
False, F, or 0 = Reversals cannot be generated for balance inquiries.

Note: Prior to setting this param to true, the performance impacts of this param must be considered. Reversing balance inquiries can significantly increase message traffic in the system. Also, any interchanges connected to the system must be able to accept reversals for balance inquiries. The ISO Host Interface process accepts and sends reversals for balance inquiries that have nonzero transaction amounts regardless of the setting in this parameter.

Usage Codes: ATM, BASE, POS
Param Default: False

RSAF-ISS-UNAVAIL-WAIT-TIMER — The amount of time, in hundredths of seconds, the VisaNet ISO Interchange Interface process waits before checking the Resubmittal Store-and-Forward File (RSAF) for transactions that were undeliverable to the issuer. Valid values are 0 through 8,640,000.

Note: When the timer associated with the RSAF-ISS-UNAVAIL-WAIT-TIMER param expires, the VisaNet ISO Interchange interface process checks to see if there are any transactions in the RSAF that had a last response code indicating that the issuer was unavailable. A counter in the PCT structure is maintained (increased or decreased) to keep track of any records that can be sent again. If the counter indicates that transactions are eligible for resubmission, the process opens the RSAF and sends the eligible records.

Usage Codes: BASE
Param Default: 720000 (2 hours)

RSAF-NOTIFY-INTERVAL — The number of writes made to the Resubmittal Store-and-Forward File (RSAF) before calculating the percentage of file full. Each time an Interchange Interface process writes a record to the RSAF, a counter is increased. When the counter is equal to the value in this param, a calculation is performed to determine how full the RSAF is. The counter is then reset to zero. When the file reaches the percent full specified in the RSAF-NOTIFY-PERCENTAGE param, a message is logged indicating the file is becoming full. The Interchange Interface process continues to log event messages indicating that the file is becoming full at the interval specified in this param. Valid values are 10 through 32,766.

The following processes use this param:

Generic Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: 50

RSAF-NOTIFY-PERCENTAGE — The percentage of used file space at which an Interchange Interface process logs an event message indicating that the Resubmittal Store-and-Forward File (RSAF) is becoming full. The Interchange Interface process continues to log event messages at the interval indicated in the RSAF-NOTIFY-INTERVAL param. Valid values are 10 through 99.

The following processes use this param:

Generic Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: 70

RSM-TERM-MASTER-KEY — An encrypted terminal master key that is used with Thales e-Security security devices. This key is required when one of the following processes or objects uses Thales e-Security security devices to generate message authentication code (MAC) encryption keys:

ISO Host Interface process
BASE24 Interchange (BIC) Interface process
Transaction Security object

This param is not required when only BASE24 Device Handler processes use Thales e-Security security devices to generate MAC encryption keys or when Thales e-Security security devices are not used to generate MAC encryption keys.

The ISO Host Interface process, BIC ISO Interface process, and Transaction Security object use this key in an intermediate step performed when BASE24 is responsible for generating and distributing MAC encryption keys. The key in this param does not coincide with any other keys being used by the data processing center or co-processor. For ease of maintenance, ACI recommends using one RSM-TERM-MASTER-KEY param for a network.

When this param is required, the default value of zeros must be changed. The Thales e-Security console command K can be used to obtain the encrypted key for this param. Refer to the *Host Security Module RG7000 Programmer's Manual* from Thales e-Security for information regarding the console command.

Usage Codes: BASE
Param Default: Zeros. This default must be changed if this param is required.

SAF-NOTIFY-INTERVAL — The number of writes made to the Store-and-Forward File (SAF) before calculating the percentage of file full. Each time a write is made to the SAF, a counter is increased by one. When the counter is equal to the value specified in this param, the interface process calculates how full the SAF is. The counter is then reset to zero. The following processes use this param:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
ISO Host Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

When the file reaches the percent full specified in the SAF-NOTIFY-PERCENTAGE param, the interface process generates an event message indicating that the file is becoming full. The interface process continues to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more since the preceding calculation, the interface process generates an event message indicating that the file is becoming full. Valid values are 10 through 32,766.

Usage Codes: BASE
Param Default: 50

SAF-NOTIFY-PERCENTAGE — The percentage of file full at which the interface process generates an event message indicating that the Store-and-Forward File (SAF) is becoming full. The interface process continues to calculate the percentage of file full at the interval indicated in the SAF-NOTIFY-INTERVAL param until more file space is made available. If the percentage has increased by one percent or more since the preceding calculation, the interface process generates an event message indicating that the file is becoming full. Valid values are 10 through 99. The following processes use this param:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
ISO Host Interface process
LINK ISO Interchange Interface process

MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: 70 (for the BIC ISO, LINK ISO, and PLUS ISO Interchange
 Interface processes)
 80 (for the Banknet, EPS-Net, Generic, ISO Host, MDS ISO,
 and VisaNet ISO Interchange Interface processes)

SAF-PRIOR-TO-SEND — A code indicating whether the Host Interface process places the current transaction in the Store-and-Forward File (SAF) prior to sending it to the host. The BASE24-pos ISO Host Interface process uses this param. For migration HISO bridge processes, this parameter must be set to Y. Valid values are as follows:

Y = Yes, place the current transaction in the SAF.
N = No, do not place the current transaction in the SAF.

Usage Codes: BASE, MIGR, NETW, POS
Param Default: N

SDF-WAIT-TIMER — The amount of time, in hundredths of seconds, the Generic Interchange Interface process and VisaNet ISO Interchange Interface process wait before reinitializing the Switch Dispute File (SDF). Valid values are 0 through 8,640,000.

Usage Codes: BASE
Param Default: 360000 (1 hour)

SECURE-DEV-ACCESS-TYP — Indicates what security device access mode is employed to access the Transaction Security Services process. This param is used only when the SECURE-DEV-TYP param is set to the value TSS.

This param is used by security procedures bound into the following processes:

Host Interface processes
Interchange Interface processes

BASE24-atm Authorization process
BASE24-atm Device Handler process

BASE24-pos Device Handler/Router/Authorization process

Valid values are as follows:

- 0 = Indicates the primary and secondary devices are used.
- 1 = Indicates the round-robin method is used.

Usage Codes: BASE, ATM, POS

Param Default: 0

SECURE-DEV-CONF-CMD100 — Defines the text that a BASE24 process sends to an Atalla Network Security Processor (NSP) model A10000E in a 100 command during initialization or warmboot. A 100 command enables commands that an NSP contains in disabled form. The text contained in the 100 command must be obtained directly from Atalla. The banking commands to be enabled may already exist in the NSP or may have to be obtained from Atalla and installed in the NSP. The text to be contained in the 100 command must be entered in the Text field of the LNCF Param screen in the following format:

```
<100#Text obtained from Atalla>
```

The following NSP banking commands must be enabled with a 100 command before they can be used:

- 30 = Encrypt Clear PIN, which is needed if a clear PIN is passed to the NSP for encryption.
- 37 = PIN Change Transaction, which is needed if the BASE24-atm or BASE24-telebanking PIN change transaction is offered and the NSP is used to generate the new PIN verification digits. Option 066 (verify old PIN in a separate call to the device) must be enabled with NSP command 37.
- 5E = Verify Card Verification Value, which is needed if card verification is performed and the NSP is used to verify the MasterCard card validation code (CVC) or the VISA card verification value (CVV).
- 11D = Generate MAC Key, which is needed if message authentication is performed and the NSP is used to generate a new MAC transaction key for a terminal. This command is not needed to generate a new MAC key for an interface.
- D0 = Verify Clear PIN, which is needed if a clear PIN is passed to the NSP for verification.

Note: This param is needed only if any of the banking commands listed above are used and you are not using the Transaction Security Services process. When using the Transaction Security Services process, the above banking commands are enabled in an initialization string entered on the Security Device Configuration screen.

A single SECURE-DEV-CONF-CMD100 param can be defined in the LCONF with the READ BY field on the LNCF Param screen set to asterisks (that is, the default value). The BASE24 security utilities do not send this param to non-NSP security devices.

Each 100 command received by an NSP can override the settings established by any prior 100 commands if the commands do not contain the same text. If multiple processes (BASE24 or non-BASE24) issue 100 commands to an NSP, care must be taken to ensure that all 100 commands contain the same text.

Note: Because the NSP models A8000, A8100, A9000, A9100, and A10100 do not support the 100 command, this param is not valid when these models are used. When using the A8000, A8100, A9000, A9100, or A10100, banking command and option configuration must be initialized manually outside of BASE24 using security policy commands (108 and 109) entered from the Secure Configuration Terminal (SCT). For more information on defining a security policy, refer to Atalla's *A8000 Installation, Operations, and Command Reference Guide*, *A9000 Installation, Operations, and Command Reference Guide*, *Installation and Operations Guide for A10100*, and the *Banking Command Reference Manual*.

The SECURE-DEV-CONF-CMD100 param is used by the security procedures bound into the following processes:

BASE24-atm Device Handler
BASE24-atm Authorization process

BASE24-pos Device Handler/Router/Authorization process

BASE24-teller Authorization process
BASE24-teller Device Handler processes

Host Interface processes
Interchange Interface processes

The Transaction Security object also uses this param.

Usage Codes: ATM, BASE, POS, TB, TLR
Param Default: No default value

SECURE-DEV-CONF-TXT— The configuration text sent to Atalla Network Security Processor (NSP) model A10000E in a 101 command during initialization or warmboot. A 101 command can modify three of the default configuration settings used by the NSP. The text to be contained in the 101 command must be entered in the TEXT field on the LNCF Param screen and can consist of one or more of the four-character option words described in the table below.

Note: This param is not used when implementing the Transaction Security Services process. When using the Transaction Security Services process, the above configuration text is established in a configuration string entered on the Security Device Configuration screen.

Each option word contains a three-digit option ID followed by a one-character action flag. If more than one option word is defined, the option words must be separated by commas. Each of the available option IDs can only be used once in each SECURE-DEV-CONF-TXT param.

Valid option IDs are as follows:

- 023 = Specifies whether the NSP removes carriage return and line feed characters from all response messages returned to BASE24. This option ID is required for the A10000E device. This option ID has the following valid action flag value:
 - E = Enable. Remove carriage return and line feed characters from all response messages returned to BASE24 by the NSP.
- 024 = Specifies whether the NSP identifies PIN length errors by returning a unique code in response messages to BASE24. This option ID has the following action flag values:
 - D = Disable. Return an S error response for PIN length and sanity check errors. BASE24 processes an S error response as a sanity check error.
 - E = Enable. Return an L error response for a PIN length error and return an S error response for a sanity check error. BASE24 processes an L error response as an invalid PIN and processes an S error response as a sanity check error.

- 040 = Sets the minimum valid PIN length used by the NSP when performing PIN length checks. This option ID has the following valid action flag values:
- 0 = Perform the PIN length check using a minimum PIN length of zero. This value has the effect of disabling the PIN length check because any PIN entered passes.
 - 1–9, A–C = Perform the PIN length check using this value as the minimum PIN length. A, B, and C represent lengths of 10, 11, and 12, respectively.

As an example, to remove carriage return and line feed characters from all response messages returned to BASE24, return an L response code for a PIN length error, and set a minimum PIN length of 4 characters, the following information is entered in the TEXT field on the LNCF Param screen:

023E, 024E, 0404

This param is needed only if any of these option IDs (023, 024, or 040) are used. Once a configuration value is changed using one of these option IDs, the new value remains in effect until the NSP is reset or the configuration value is changed by receiving the option ID in another 101 command. To avoid possible inconsistencies caused by one process changing a configuration value and another process expecting the default configuration value, ACI recommends the use of this param with all three option words for all BASE24 processes using NSP security modules. A single SECURE-DEV-CONF-TXT param can be defined in the LCONF with the READ BY field on the LNCF Param screen set to asterisks (that is, the default value). The BASE24 security utilities do not send this param to non-NSP security devices.

Each 101 command received by an NSP can override the settings established by any prior 101 commands if the commands do not contain the same text. If multiple processes (BASE24 or non-BASE24) issue 101 commands to an NSP, care must be taken to ensure that all 101 commands contain the same text.

Note: Because the NSP models A8000, A8100, A9000, A9100, and A10100 do not support options 024 and 040 in the 101 command, this param is not valid when these models are used. When using the A8000, A8100, A9000, A9100, or A10100, these options must be initialized manually outside of BASE24 using security policy commands (108 and 109) entered from the Secure Configuration Terminal (SCT) and the A0 and A1 options, respectively. The 023 option must be enabled using the 101 command entered outside of BASE24 as well. For more information on the 101 command and defining a security policy, refer to Atalla's

A8000 Installation, Operations, and Command Reference Guide, A9000 Installation, Operations, and Command Reference Guide, Installation and Operations Guide for A10100, and the Banking Command Reference Manual.

The SECURE-DEV-FAIL-NOTIFY param is used by the security procedures bound into the following processes:

BASE24-atm Device Handler
BASE24-atm Authorization process

BASE24-pos Device Handler/Router/Authorization process

BASE24-teller Authorization process
BASE24-teller Device Handler processes

Host Interface processes
Interchange Interface processes

The Transaction Security object also uses this param.

Usage Codes: ATM, BASE, POS, TB, TLR
Param Default: No default value

SECURE-DEV-FAIL-NOTIFY — The interval at which critical messages are logged due to the failure of a process' primary or secondary security modules. Valid values are 10 through 1,000; the default value is 20.

Note: When using the Transaction Security Services process, this param specifies the interval at which the BASE24 process attempts to reopen the Transaction Security Services process after failure of the Transaction Security Services process. For more information on how this param is used with the Transaction Security Services process, refer to the *BASE24 Transaction Security Services Processing Guide*.

If a process' primary and secondary security modules cannot be initialized during the process' startup and this param is set to the default of 20, every twentieth transaction that a process must decline because the security modules are inoperative causes a message to be logged indicating that the security modules have failed. (A critical event message is always generated immediately upon failure of both devices.)

If a process' primary security module is marked down and this param is set to the default of 20, every twentieth transaction that is directed to the primary security module causes a message to be logged even though the transactions are being handled properly by the secondary security module. Transactions routed directly to the secondary security module do not affect the primary security module's transaction counter. The SECURE-DEV-MONITOR-THRESHOLD param controls when a transaction is directed to the secondary security module instead of the primary security module.

If a process' primary and secondary security modules fail at some time after initialization, a separate failed transaction counter is maintained for each security module. A transaction that is sent to one security module and then the other increases both counters. A message is logged each time either counter reaches the value established in this param.

The SECURE-DEV-FAIL-NOTIFY param is used by security procedures bound into the following processes:

BASE24-atm Device Handler
BASE24-atm Authorization process

BASE24-pos Device Handler/Router/Authorization process

BASE24-teller Authorization process
BASE24-teller Device Handler processes

Host Interface processes
Interchange Interface processes

Usage Codes: ATM, BASE, POS, TLR
Param Default: 20

SECURE-DEV-MONITOR-THRESHOLD — The interval, expressed in the number of transactions processed by the security device defined in the SECURE-DEV1 LCONF assign, for checking the security device defined by the SECURE-DEV2 LCONF assign. Valid values are 0 through 32,000. The default value of 0 indicates that no check is performed.

Note: When using the Transaction Security Services process with primary and secondary devices, this param specifies the interval for checking the secondary Transaction Security Services process. When using the round-robin access

method, this param is ignored. For more information on how this param is used with the Transaction Security Services process, refer to the ***BASE24 Transaction Security Services Processing Guide***.

This param can be used to monitor the secondary security device or to balance the load between the primary and secondary security devices. Each process using a security device maintains its own transaction counter. This means the interval specified in the SECURE-DEV-MONITOR-THRESHOLD param must be set to the number of transactions processed by individual processes using the security device, not the total number of transactions processed by the security device. For example, if five BASE24 processes use a security device and the param is set to 1000, up to 5000 transactions (1000 by each of the five processes) can be processed by the primary security device before the secondary security device is used. Setting this param to 1 causes each of the BASE24 processes to alternate between the two security devices.

The SECURE-DEV-MONITOR-THRESHOLD param can be generic or process-specific. This param is used by the security procedures bound into the following processes:

BASE24-atm Authorization process
BASE24-atm Device Handler process

BASE24-pos Device Handler/Router/Authorization process

BASE24-teller Authorization process

Host Interface processes
Interchange Interface processes

Usage Codes: ATM, BASE, POS, TLR
Param Default: 0

SECURE-DEV-REINSTATE-TIME— The time interval, in number of minutes, at which a process should attempt to reopen a Transaction Security Services process that is marked down. This param is used with the round-robin access method. Valid values are 0 through 32,000. The default value of 0 indicates that the process should not attempt to reopen a Transaction Security Services process based on this time interval.

If this param is set to the value 0, BASE24 processes use the value of the SECURE-DEV-FAIL-NOTIFY param to determine the interval to use when attempting to reopen the failed Transaction Security Services. For more information on how this param is used with the Transaction Security Services process, refer to the ***BASE24 Transaction Security Services Processing Guide***.

This param is used by security procedures bound into the following processes:

Host Interface processes
Interchange Interface processes

BASE24-atm Authorization process
BASE24-atm Device Handler process

BASE24-pos Device Handler/Router/Authorization process:

Usage Codes: BASE, ATM, POS

SECURE-DEV-TIM-LMT — The maximum amount of time, in hundredths of a second, a BASE24 process waits for a response from the security device before the message times out. Valid values are 1 through 6,000 (for example, 6000 equals 60 seconds). This param is used by security procedures bound into the following processes:

Note: When using the Transaction Security Services process, this param specifies the maximum amount of time a BASE24 process waits for a response from the Transaction Security Services process. For more information on how this param is used with the Transaction Security Services process, refer to the ***BASE24 Transaction Security Services Processing Guide***.

BASE24-atm Device Handler
BASE24-atm Authorization process

BASE24-pos Device Handler/Router/Authorization process
BASE24-teller Authorization process
BASE24-teller Device Handler processes

Host Interface processes
Interchange Interface processes

This param is also used by the Transaction Security object.

Usage Codes: ATM, BASE, POS, TB, TLR

Param Default: 500

SECURE-DEV-TYP — Specifies whether the BASE24 security utilities in a BASE24 process communicate directly with an Atalla security device, a Thales e-Security security device, the Transaction Security Services process, or do not use a security device. Valid values are as follows:

ASM = Atalla Network Security Processor

RSM = Thales e-Security Host Security Module (same as VSM)

TSS = Transaction Security Services process

VSM = Thales e-Security Host Security Module (same as RSM)

N/A = A security module is not required

In some BASE24 logical networks it may be desirable to use more than one security device type. This is possible, since the SECURE-DEV-TYP param is assigned by process. Care must be exercised, however, in assigning different security device types to different processes, especially where the different processes communicate with each other.

For example, if a Device Handler or interface process receives a PIN encrypted under a key managed by an Atalla security device, but passes the PIN and the Atalla-encrypted PIN key to an Authorization process that is using a Thales e-Security security device for PIN verification, the PIN cannot be verified unless the Thales e-Security device is configured specifically to correctly decrypt the Atalla-encrypted PIN key.

The same care must be exercised regarding MAC keys. For example, if a Device Handler or interface process receives a MAC generated under a key managed by an Atalla security device, but attempts to verify the MAC using a Thales e-Security security device, the MAC cannot be verified unless the Thales e-Security device is configured specifically to correctly decrypt the Atalla-encrypted MAC key.

Also, the Authorization process sends information from Key Authorization File (KEYA) records to its security device so care must be taken to ensure that any encrypted data passed by the Authorization process from the KEYA to the security device has previously been encrypted by that same security device type with the same master key. When using the Transaction Security Services process, similar information is sent from the Card Verification File (CRDVD), IBM DES Verification File (IDESD), or Visa PVV Verification File (VPVVD) to the security device.

If all processes use the same type of security device or communicate with the Transaction Security Services process, a single SECURE-DEV-TYP param can be defined in the LCONF. In this case, the Process Name field on the LCONF Param screen must be set to asterisks (default value).

If different security device types are used, SECURE-DEV-TYP params must be defined in the LCONF for each type and the Process Name field on the LCONF Param screen for each type can be set to identify the processes using that type. If a majority of processes use a particular type of security device, an alternative to identifying all of its processes can be making that device type the default by placing asterisks in the Process Name field of its SECURE-DEV-TYP param. Then, only processes using a different type of security device need to be defined specifically.

If no security devices are used, a SECURE-DEV-TYP param must still be defined in the LCONF. The Process Name field on the LCONF Param screen must be set to asterisks (default value) and the field on the LCONF Param screen must be set to N/A (no security module required).

Note: For the BASE24-card product, the Plastic Card Generation Server (SVPCGEN) process attempts to read this LCONF param with a process name of SVPCGEN. If no match is found, the process attempts to find this param with a default process name of all asterisks (*****).

This param is used by security procedures bound into the following processes:

BASE24-atm Device Handler
BASE24-atm Authorization process

BASE24-card Plastic Card Generation Server (SVPCGEN) Server process

BASE24-pos Device Handler/Router/Authorization process

BASE24-teller Authorization process
BASE24-teller Device Handler processes

Host Interface processes
Interchange Interface processes

The following server processes also access this param to determine whether operators can update fields containing hardware-encrypted keys from the BASE24 CRT access system files maintenance screens:

BASE24-atm Terminal Data files server object
BASE24-pos Terminal Data files server object

When this param is set to a value of TSS and the PIN encryption type or MAC type for a record in the BASE24-atm or BASE24-pos Terminal Data files indicates that hardware security modules are used, the servers listed above move the terminal ID into all hardware encrypted key fields for the record. Thereafter, these fields can no longer be updated from the appropriate ATD and PTD files maintenance screens.

Usage Codes: ATM, BASE, CARD, POS, TLR
Read By: A symbolic name (for example, P1A^AUTH01,
 P2B^BASE02, P2A^SPDH03, SVPGEN) is required in this
 field if processes use a different security type.
Param Default: No default value

SEMF-NOTIFY*identifier* — A process or service that the Enscribe Refresh process must notify after a full-file refresh of the Scoring Engine Master File (SEMF).

The Enscribe Refresh process uses this param. If broadcast messages are not used, a maximum of 150 processes can be notified. This param can contain the name of a service or the symbolic name of a Scoring Engine Interface process or From Host Maintenance process that uses the SEMF.

Each SEMF-NOTIFY param contains the name of one process or service. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services. The optional identifier is usually a number; however, it can be any unique set of characters.

If no SEMF-NOTIFY params are present in the LCONF, the Enscribe Refresh process does not notify any processes after a full-file refresh of the SEMF.

If the SEMF-NOTIFY param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Enscribe Refresh process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Usage Codes: BASE
Param Default: No default value

SEND-ETX — A flag indicating whether an interchange interface process sends the end-of-text (ETX) control character. Valid values are as follows:

Y = Yes, send the ETX.

N = No, do not send the ETX

The following processes use this param:

BCGI Interface process

BIC ISO Interchange Interface process

Generic Interchange Interface process

ISO Host Interface process

MDS ISO Interchange Interface process

PLUS ISO Interchange Interface process

VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: Y

SEND-IMPLIED-DECIMAL — A flag that indicates whether the MDS ISO Interchange Interface process sends the implied decimal exponent. This param must be set to a value of Y if the BASE24 system is registered with MDS in the Implied Decimal Exponent Service. Valid values are as follows:.

Y = Yes, send the implied decimal point.

N = No, do not send the implied decimal point.

Usage Codes: BASE

Param Default: N

SEND-MDS-DEFAULT-ACQUIRER-ID — A flag indicating whether the MDS ISO Interchange Interface process sends the default acquirer ID from the Enhanced Interchange Configuration File (ICFE) in bit 32 when formatting an external message from a BASE24-atm transaction request. If the param is set to a value of Y, the default acquirer ID is used in all BASE24-atm requests instead of the value found in the STM acquiring institution ID. This param is optional. Valid values are as follows:

Y = Yes, send the default acquirer ID from the ICFE in all requests.

N = No, do not send the default acquirer ID in all requests.

Usage Codes: BASE
Param Default: No

SOFTWARE-PIN-VERIFICATION-ALWD — A flag indicating whether PIN verification, card verification, or PIN offset generation is allowed to be performed in software or in the clear anywhere in the BASE24 system when the SECURE-DEV-TYP param is set to a value of TSS. Valid values are as follows:

Y = Yes, PIN verification, card verification, or PIN offset generation in software is allowed.
N = No, PIN verification, card verification, or PIN offset generation in software is not allowed.

The following processes use this param:

BASE24-atm Authorization process
BASE24-pos Authorization module
BASE24-teller Authorization process

Usage Codes: ATM, POS, TLR
Param Default: N

SPAN-FLAG — A flag indicating whether an interchange interface process writes totals to the Span Clearings File. Valid values are as follows:

Y = Yes, write totals to the Span Clearings File.
N = No, do not write totals to the Span Clearings File.

The following processes use this param:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: N

STATION-TYP — A code indicating whether an Interchange Interface process uses the station names from the Enhanced Interchange Configuration File (ICFE) or the Station Name File (SNF). Valid values are as follows:

- 0 = Normal processing. The interchange interface process uses the stations from the ICFE with station 1 as the issuer station and station 2 as the acquirer station.
- 1 = Send/receive processing. The interchange interface uses the station pairs as listed in the SNF.

The following processes use this param:

BCGI Interface process
Generic Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

If this param is invalid or missing, the above processes use a default value of 0.

Usage Codes: BASE
Param Default: 0

STRFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Split Transaction Routing File extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table.

Usage Codes: ATM, BASE
Param Default: 127

STRFEMT-WARM*Identifier* — The symbolic name of a process to receive a warmboot command when the Split Transaction Routing File (STRF) extended memory table is warmbooted from the Device Control Terminal (DCT). The Process Control Terminal Server process uses this param. The Transaction Context Manager can be warmbooted.

The Device Control Terminal Server process retrieves all STRFEMT-WARM*Identifier* params when a network control operator issues a command to reinitialize the STRF extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another STRFEMT-WARM*Identifier* param. For example, STRFEMT-WARM01 could contain the P1A^C10001 process and STRFEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 STRFEMT-WARM*Identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one STRFEMT-WARM*Identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples: P1A^C10001
 P1A^N*
 P1A^SPDH2
 P2A^BICI
Usage Codes: ATM, BASE, POS
Param Default: No default value

SW-BNET-LOG-ONLY-COMPL-ADVICE — A flag indicating whether a log-only message should be sent to the BASE24-pos Router/Authorization process when a response to an automated fuel dispense completion advice is received from Banknet. Valid values are as follows:

Y = Yes, send a log-only message to the BASE24-pos Router/Authorization process.
N = No, do not send a log-only message to the BASE24-pos Router/Authorization process.

Usage Codes: BASE
Param Default: N

SW-BNET-SPPT-INSTL-TXN — A flag indicating whether the interface supports installment transactions. This parameter is optional. Valid values are as follows:

0 = Not supported.
1 = Supported by the interface in acquirer processing.
2 = Supported by the interface in issuer processing.
3 = Supported by the interface in both acquirer and issuer processing.

The following process uses this param:

Banknet Interchange Interface process

Usage Codes: BASE

Param Default: 0

SW-ETUO-RETURN-0430 — A code that indicates whether the XML Telco Interface process waits for notification of reversals from the service provider before it sends a notification to the Transaction Context Manager process to reverse funds for a mobile top-up transaction that does not complete as authorized.

If the param is set to a value of Y, the XML Telco Interface process waits for a reversal completion after sending a reversal to the service provider. This reversal completion is a notification of reversal by the service provider, indicating that the service provider has received the reversal for the mobile top-up transaction. When the XML Telco Interface process receives the notification of reversal, it sends a notification to the Transaction Context Manager process.

If the param is set to a value of N, the XML Telco Interface sends a notification to the Transaction Context Manager. The Transaction Context Manager process generates a reversal and sends it to the Authorization process or the Device Handler/Router/Authorization module.

Valid values are as follows:

Y = Yes, the XML Telco Interface process waits for the notification of reversal from the service provider.

N = No, the XML Telco Interface process does not wait for the notification of reversal from the service provider.

Usage Codes: BASE

Param Default: N

SW-ILF-FILE-OPEN — The number of days the Interchange Log File (ILF) is to remain open. After the specified number of days expires, the PLUS ISO Interchange Interface process closes the ILF. For example, if you set this param to a value of 2, today's ILF and two old ILF's will remain open.

This param should only be used if Interlink transactions are not processed by the interchange. The value of the SW-ILF-FILE-OPEN param must be equal to or less than the value of the SW-ILF-FILE-RETENTION param. Valid values are 1 through 5.

Usage Codes: BASE

Param Default: The value of the SW-ILF-FILE-RETENTION param

SW-ILF-FILE-RETENTION — The number of days worth of Interchange Log Files (ILFs), prior to the current business day's ILF, which are to remain on the system. After the specified number of days, the Interchange Interface process deletes the ILF from the system. For example, if the value in this param is 3 and the current business date is 01/06/05 (for June 5, 2001), ILFs dated 01/06/05 and 01/06/04 are on the system and open. ILFs dated 01/06/03 and 01/06/02 are on the system and closed. The ILFs dated 01/06/01 and earlier have been deleted from the system. Valid values are 3 through 99.

The following processes use this param:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE

Read By: A symbolic name (for example, P1A^BIC, P2A^BICI) is required in this field.

Param Default: 7

SW-RPT-STARTUP — The time of day (hh:mm) that an Interchange Interface process runs its report obey file. The following processes use this param:

Banknet Interchange Interface process
BCGI Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
Generic Interchange Interface process
LINK ISO Interchange Interface process

MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Valid values are 00:00 through 23:59, based on 24-hour time.

If the SW-RPT-STARTUP param is not present or contains an invalid value, the processes listed above do not run reports.

Usage Codes: BASE
Read By: A symbolic name (for example, P1A^BIC, P1A^BICI) is
 required in this field.
Param Default: No default value

SW-SPN2-USING-STA-SATELLITES — A flag indicating whether the interface will use satellite processes or standard station processing. Valid values are as follows:

Y = Yes, the interface uses station satellite processes.
N = No, the interface uses standard station processing.

The following process uses this param:

SAMA SPAN2 Interchange Interface process

Usage Codes: BASE
Param Default: N

SWI-ACQ-AVS-DATA-SUPPRS — A flag indicating whether logging address verification data for acquirer transactions to the Interchange Log File (ILF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. Valid values are as follows:

Y = Yes, suppress logging of address verification data.
N = No, do not suppress logging of address verification data.

The following processes use this param:

AEGN ISO Interchange Interface process
Alaska Option ISO Interchange Interface process
AXCI ISO Interchange Interface process
Banknet Interchange Interface process
BIC ISO Interchange Interface process

DIAS Interchange Interface process
Discover ISO Interchange Interface process
EPS-Net Interchange Interface process
FDR ISO Interchange Interface process
Generic Switch
MAC MASM Interchange Interface process
MDS ISO Interchange Interface process
Star ISO Interchange Interface process
VISA DPS Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-ACQ-CVD2-DATA-SUPPRS — A flag indicating whether logging card verification data (CVD2) for acquirer transactions to the Interchange Log File (ILF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. Valid values are as follows:

Y = Yes, suppress logging of CVD2 data.

N = No, do not suppress logging of CVD2 data.

The following processes use this param:

AEGN ISO Interchange Interface process
Alaska Option ISO Interchange Interface process
AMXI ISO Interchange Interface process
AXCI ISO Interchange Interface process
Banknet Interchange Interface process
BIC ISO Interchange Interface process
Cash Station ISO Interchange Interface process
DIAS Interchange Interface process
Discover ISO Interchange Interface process
EPS-Net Interchange Interface process
FDR ISO Interchange Interface process
Generic Switch
JCB ISO Interchange Interface process
MAC MASM Interchange Interface process
MDS ISO Interchange Interface process
Money Station Interchange Interface process
MPS Interchange Interface process
Networks ISO Interchange Interface process
NYCE ISO Interchange Interface process

PLUS ISO Interchange Interface process
PULSE ISO Interchange Interface process
SAMA SPAN2 ISO Interchange Interface process
Shazam ISO Interchange Interface process
Star ISO Interchange Interface process
VISA DPS Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-ACQ-DISCR-DATA-SUPPRS — A flag indicating whether logging discretionary data from Track 1 or Track 2 for acquirer transactions to the Interchange Log File (ILF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. Valid values are as follows:

Y = Yes, suppress logging of discretionary data.

N = No, do not suppress logging of discretionary data.

The following processes use this param:

AEGN ISO Interchange Interface process
AMXI ISO Interchange Interface process
AOI ISO Interchange Interface process
AXCI ISO Interchange Interface process
Banknet Interchange Interface process
BIC ISO Interchange Interface process
Cash Station ISO Interchange Interface process
Deluxe ISO Gateway Interchange Interface process
Discover ISO Interchange Interface process
DIAS Interchange Interface process
EPS-Net Interchange Interface process
FDR ISO Interchange Interface process
Generic Switch
JCB ISO Interchange Interface process
LINK ISO Interchange Interface process
MAC MASM Interchange Interface process
MDS ISO Interchange Interface process
Money Station Interchange Interface process
MPS Interchange Interface process
Networks ISO Interchange Interface process
NYCE ISO Interchange Interface process

PLUS ISO Interchange Interface process
PULSE ISO Interchange Interface process
SAMA SPAN2 ISO Interchange Interface process
Shazam Interchange Interface process
Star ISO Interchange Interface process
Visa DPS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: N

SWI-ENHNCD-ILF-MATCH-ACQ — A flag indicating if the acquirer processing within the interface searches up to 4 Interchange Log Files (ILFs):

current
1 day prior
2 days prior
3 days prior

when attempting a match for a CNP reversal. Valid values are as follows:

Y = Yes, search up to 4 ILFs.
N = No, only search the current and 1 day prior ILFs.

The following processes use this param:

Banknet Interchange Interface process
MDS ISO Interchange Interface process

Usage Codes: BASE
Param Default: N

SWI-ENHNCD-ILF-MATCH-ISS — A flag indicating if the issuer processing within the interface searches up to 4 Interchange Log Files (ILFs):

current
1 day prior
2 days prior
3 days prior

when attempting a match for a CNP reversal. Valid values are as follows:

Y = Yes, search up to 4 ILFs.

N = No, only search the current and 1 day prior ILFs.

The following processes use this param:

Banknet Interchange Interface process

MDS ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-ISS-AVS-DATA-SUPPRS — A flag indicating whether logging address verification data for issuer transactions to the Interchange Log File (ILF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. Valid values are as follows:

Y = Yes, suppress logging of address verification data.

N = No, do not suppress logging of address verification data.

The following processes use this param:

AEGN ISO Interchange Interface process

Alaska Option ISO Interchange Interface process

AXCI ISO Interchange Interface process

Banknet Interchange Interface process

BIC ISO Interchange Interface process

EPS-Net Interchange Interface process

FDR ISO Interchange Interface process

Generic Switch

MAC MASM Interchange Interface process

MDS ISO Interchange Interface process

Star ISO Interchange Interface process

VISA DPS Interchange Interface process

VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-ISS-CVD2-DATA-SUPPRS — A flag indicating whether logging card verification data (CVD2) for issuer transactions to the Interchange Log File (ILF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. Valid values are as follows:

Y = Yes, suppress logging of CVD2 data.

N = No, do not suppress logging of CVD2 data.

The following processes use this param:

AEGN ISO Interchange Interface process
AMXI ISO Interchange Interface process
AXCI ISO Interchange Interface process
Banknet Interchange Interface process
BIC ISO Interchange Interface process
EPS-Net Interchange Interface process
FDR ISO Interchange Interface process
Generic Switch
JCB ISO Interchange Interface process
MDS ISO Interchange Interface process
SAMA SPAN2 ISO Interchange Interface process
Star ISO Interchange Interface process
VISA DPS Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-ISS-DISCR-DATA-SUPPRS — A flag indicating whether logging discretionary data from Track 1 or Track 2 for issuer transactions to the Interchange Log File (ILF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. Valid values are as follows:

Y = Yes, suppress logging of discretionary data.

N = No, do not suppress logging of discretionary data.

The following processes use this param:

AEGN ISO Interchange Interface process
Alaska Option ISO Interchange Interface process
AMXI ISO Interchange Interface process
AXCI ISO Interchange Interface process

Banknet Interchange Interface process
BIC ISO Interchange Interface process
Cash Station ISO Interchange Interface process
Deluxe ISO Gateway Interchange Interface process
EPS-Net Interchange Interface process
FDR ISO Interchange Interface process
Generic Switch
JCB ISO Interchange Interface process
LINK ISO Interchange Interface process
MAC MASM Interchange Interface process
MDS ISO Interchange Interface process
Money Station Interchange Interface process
Networks ISO Interchange Interface process
NYCE ISO Interchange Interface process
PLUS ISO Interchange Interface process
PULSE ISO Interchange Interface process
SAMA SPAN2 ISO Interchange Interface process
Shazam Interchange Interface process
Star ISO Interchange Interface process
Switch Authorization Network Interchange Interface process
Visa DPS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-MDS-SPPT-CCA-ADVC-RVSL — A flag indicating whether the Single Message System recalculates settlement and currency conversion amounts based on a partial reversal when sending an advice. Valid values are as follows:

Y = Yes, send a full reversal followed by an advice.

N = No, send adjustment only.

The following process uses this param:

MDS ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-VISA-MAP-EXPAND-AVS-TO-BASIC — A flag indicating whether the interface maps expanded AVS result codes to the Visa suggested basic AVS result codes. Valid values are as follows:

Y = Yes, expanded to basic AVS result code mapping is performed.

N = No, only standard AVS result code processing is performed.

The following process uses this param:

VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-VISA-MVV-IN-AUTO-SUBSTAN-TKN — A flag indicating whether the interface attempts to retrieve an MVV value from the AUTO-SUBSTAN-DATA-TKN.ASGN-ID field for Visa auto-substantiation transactions. Valid values are as follows:

Y = Yes, look for MVV in the AUTO-SUBSTAN-DATA-TKN.ASGN-ID field for Visa auto-substantiation transactions.

N = No, do not look for MVV in the AUTO-SUBSTAN-DATA-TKN.ASGN-ID field for Visa auto-substantiation transactions.

The following process uses this param:

VisaNet ISO Interchange Interface process

Usage Codes: BASE

Param Default: N

SWI-WARM*identifier* — The symbolic name of an Interchange Interface process to be warmbooted. This param indicates an Interchange Interface process that receives a warmboot command from the Device Control Terminal (DCT). The Process Control Terminal Server process retrieves all SWI-WARM*identifier* params when a network control operator issues a command to reinitialize all Interchange Interface processes. A maximum of 150 processes can be warmbooted from the DCT.

Each SWI-WARM param contains the name of one Interchange Interface process. When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of

characters that has not already been declared by another SWI-WARM*Identifier* param. For example, SWI-WARM1 could contain the P1A^PISO1 process and SWI-WARM2 could contain the P1A^PISO2 process.

Usage Codes: BASE
Examples: P1A^BNET02
 P1A^MDS01
Param Default: No default value

SWITCH-COMPLETE-TRACK2 — A code indicating whether transactions acquired from an interchange other than the EPS-Net interchange contain complete and unaltered Track 2 data. The EPS-Net Interchange Interface process uses this param. Valid values are as follows:

Y = Yes, transactions from an interchange other than the EPS-Net interchange contain complete and unaltered Track 2 data.
N = No, transactions from an interchange other than the EPS-Net interchange do not contain complete and unaltered Track 2 data.

Note: This param only applies to release 3.4/4.0 systems.

Usage Codes: BASE
Param Default: Y

TAPE-FORMAT — A code indicating the type of tape format the Interchange Prefix File (IPF) Refresh Visa or Plus/Visa Interface process uses when producing an IPF refresh tape. Valid values are as follows:.

ASCII = Use the ASCII character set.
EBCDIC = Use the EBCDIC character set.

Usage Codes: BASE
Param Default: No default value

TIME-ZONE-DIFF — The number of minutes between the Interchange Interface process and the time zone of the interchange.

During warmboot processing or when the Interchange Interface process is stopped and restarted, the process compares the settlement time in the Enhanced Interchange Configuration File (ICFE), which should be set to the local time of the

interchange cutover, to the value of this param. This determines if the interchange could be a day behind. This param is required if the interchange and interface can be a day or more apart. Valid values are 0 through 1,440.

The following processes use this param:

Banknet Interchange Interface process
MDS ISO Interchange Interface process
VisaNet ISO Interchange Interface process

Usage Codes: BASE
Param Default: 0

UPDT-ILF-ON-LATE-RESP — A flag indicating whether the following processes update the Interchange Log File (ILF) when they receive a late response:

BIC ISO Interchange Interface process
LINK ISO Interchange Interface process

Valid values are as follows:

Y = Yes, update the ILF for a late response.
Other value = No, do not update the ILF for a late response.

Usage Codes: BASE
Param Default: 0 (for the BIC ISO Interchange Interface process)
 N (for the LINK ISO Interchange Interface process)

US-CARD-TYPE — A U.S. card type used as the output file card type by the Interchange Prefix File (IPF) Refresh Plus/Visa Interface process. If the surcharging enhancement is used, a card type can be specified in this param to be used as the output file card type for U.S. issuers. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

US-CHK2-CARD-TYPE — A U.S. check card II card type used as the check card II output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for U.S. issuers. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

US-ILNK-CARD-TYPE — A U.S. Interlink card type used as the Interlink output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for U.S. Interlink issuers. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

US-PLUS-CARD-TYPE — A U.S. PLUS card type used as the PLUS output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for U.S. PLUS issuers. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

US-VISA-CARD-TYPE — A U.S. Visa card type used as the Visa output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for U.S. Visa issuers. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

US-VISAPLUS-CARD-TYPE — A U.S. Visa/PLUS card type used as the Visa/PLUS output file card type by the Interchange Prefix File (IPF) Refresh Visa Interface process for U.S. Visa/PLUS issuers. This param can contain up to two alphanumeric characters.

Usage Codes: BASE
Param Default: No default value

8: BASE24-atm Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-atm product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24-atm product. Each of the following assigns should have the usage code ATM (and only the code ATM) entered in the USAGE CODES field on the LNCF Assign screen.

ATM-ADCF — The fully qualified file name of the ATM Dial-Up Command File (ADCF). The ADCF queues commands to a dial-up ATM until it initiates a connection with the BASE24 system. The following processes require this assign when the Dial-up Device Handler extension is installed:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process

Example: \B24.\$DATA.PRO1DATA.ADCF

ATM-ATD-DYN-GNRL — The fully qualified file name of the BASE24-atm Terminal Data Dynamic File—general data (ATDD1). This file contains dynamic core terminal data (i.e., data common to all types of devices that is subject to change), device information (i.e., data specific to a device type), and device-dependent data (i.e., data specific to each terminal defined). Key STM fields for the last transaction processed for a device are also stored in this file. The Diebold 10XX/478X and NCR 5XXX Device Handler processes use this assign to read and update dynamic terminal data as transactions are processed. The following processes require this assign:

Device Control Terminal Server process
Diebold 10XX/478X Device Handler process
Generic Simulator process
NCR 5XXX Device Handler process
Operator Identification File (OIF) Server process
BASE24-atm Terminal Data files Server object
Settlement Initiator process

Example: \B24.\$DATA.PRO1DATA.ATDD1

ATM-ATD-DYN-SCRATCH-PAD — The fully qualified file name of the BASE24-atm Terminal Data Dynamic File—scratch pad (ATDD2). This file contains dynamic token data for reversal processing. This assign is optional. If it is not used, data for reversal processing is obtained from last transaction data in the Transaction Log File (TLF). The following processes use this assign:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process

Example: \B24.\$DATA.PRO1DATA.ATDD2

ATM-ATD-EXTMEM-SWAPVOL — The fully qualified name of the BASE24-atm Terminal Data files extended memory swap volume. The following processes use this assign to temporarily store data when building extended memory:

BASE24-atm Terminal Data files Server object
BASE24-atm Transaction Analysis utility
Device Control Terminal Server process

If this assign is not present in the LCONF or contains an invalid value, the HP NonStop operating system assigns a swap volume location.

Example: \B24.\$DATA

ATM-ATD-STATIC-GNRL — The fully qualified file name of the BASE24-atm Terminal Data Static File—general data (ATDS1). This file contains static data, which is information that does not change during the course of transaction processing. The Diebold 10XX/478X and NCR 5XXX Device Handler processes use this assign to retrieve static terminal data, which is maintained in extended memory. The following processes require this assign:

Device Control Terminal Server process
Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process
BASE24-atm Settlement Initiator process (only with the BASE24-atm Forced Cutover module)
BASE24-atm Terminal Data files Server object

Example: \B24.\$DATA.PRO1DATA.ATDS1

ATM-DAILY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Daily Transaction Volume Report program. The naming convention for this assign is `$S.#ATDmmdd`, where *mmdd* is the month and day for which the report was run. The Transaction Based Pricing Report Initiator process uses this assign. This assign is not required. If it is not configured, the Daily Transaction Volume Report is sent to the EMS log rather than a spooler location, and a daily record is still written to the Monthly Totals Accumulation File (MTAF).

Example: `$S.ATD0101`

ATM-DAILY-REPORT-OBEYFILE — The fully qualified file name of the obey file to run the Daily Transaction Volume Report program. The naming convention for this obey file is `ATDRmmdd`, where *mmdd* is the month and day for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: `\B24.$DATA.ATDR0101`

ATM-DAILY-REPORT-PROGRAM — The fully qualified file name of the ATM Daily Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, *xx* is the number of the current release.

Example: `\B24.$BAxxTBP.ATDRPT`

ATM-DH-ATD-EXTMEM-SWAPVOL — The fully qualified name of the BASE24-atm Terminal Data files extended memory swap volume in which the following Device Handler processes temporarily store data when building extended memory for a terminal's BASE24-atm Terminal Data files records:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process

If this assign is not present in the LCONF or contains an invalid value, the HP NonStop operating system assigns a swap volume location.

Example: \B24.\$DATA

ATM-DH-CI4730 — The fully qualified file name of the configuration file for IBM 4730-series ATMs. The IBM 4730-series Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CI4730

Read By: A symbolic name (for example, P1A^I4730) is required in this field if IBM 4730 Device Handler processes do not use the same configuration files.

ATM-DH-CILOAD — The fully qualified file name of the configuration file for IBM 36XX-series ATMs. The IBM 36XX-series Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CILOAD

Read By: A symbolic name (for example, P1A^I3624) is required in this field if IBM 36XX-series Device Handler processes do not use the same configuration file.

ATM-DH-CNF910 — The fully qualified file name of the configuration file for Diebold 910 (910/911/911L) ATMs. The following Device Handler processes use this assign when downline loading terminals:

Diebold 910/911/911L
Fujitsu 910

This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFG910

Read By: A symbolic name (for example, P1A^D910) is required in this field if Diebold 910/911/911L and Fujitsu 910 Device Handler processes do not use the same configuration file.

ATM-DH-CNF912 — The fully qualified file name of the configuration file for Diebold 912 ATMs. The Diebold 912 Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFG912

Read By: A symbolic name (for example, P1A^D912) is required in this field if Diebold 912 Device Handler processes do not use the same configuration file.

ATM-DH-CNF1000 — The fully qualified file name of the configuration file for Diebold 10XX/478X ATMs. The Diebold 10XX/478X Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual BASE24-atm Terminal Data file records for the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFG1000

Read By: A symbolic name (for example, P1A^C1000) is required in this field if Diebold 10XX/478X Device Handler processes do not use the same configuration file.

ATM-DH-CNF5070 — The fully qualified file name of the configuration file for NCR 5XXX ATMs. The NCR 5XXX Configuration Server process uses this assign to access the configuration file. The NCR 5XXX Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual BASE24-atm Terminal Data file records of the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFG5070

Read By: A symbolic name (for example, P1A^N50) is required in this field if NCR 5XXX Device Handler processes do not use the same configuration file.

ATM-DH-CNF5100 — The fully qualified file name of the configuration file for Docutel 5100 ATMs. The Docutel 5100 Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFG5100

Read By: A symbolic name (for example, P1A^C51) is required in this field if Docutel 5100 Device Handler processes do not use the same configuration file.

ATM-DH-CNFFUJ — The fully qualified file name of the configuration file for Fujitsu ATMs. The Fujitsu Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFGFUJ

Read By: A symbolic name (for example, P1A^FUJ) is required in this field if Fujitsu Device Handler processes do not use the same configuration file.

ATM-DH-CNFUJ7 — The fully qualified file name of the configuration file for Fujitsu 7000 ATMs. The Fujitsu 7000 Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFGFUJ7

Read By: A symbolic name (for example, P1A^FUJ7) is required in this field if Fujitsu 7000 Device Handler processes do not use the same configuration file.

ATM-DH-FUJ7-CPLF — The fully qualified file name of the Check Proof List File (CPLF) for Fujitsu 7000 ATMs. Each Device Handler process can have a separate CPLF, or the logical network can have a single CPLF. This assign is used

with the BASE24-atm self-service banking (SSB) Device Handler Extension. The BASE24-atm self-service banking (SSB) Device Handler Extension is an add-on product.

Example: \B24.\$DATA.PRO1DATA.CPLF100A

Read By: A symbolic name (for example, P1A^FUJ7) is required in this field if using the BASE24-atm self-service banking (SSB) Device Handler Extension and the Fujitsu 7000 Device Handler processes do not use the same CPLF.

ATM-DH-HPL5100 — The fully qualified file name of the Host Program Load (HPL) file for Docutel 5100 ATMs. The Docutel 5100 Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.HPL5100

Read By: A symbolic name (for example, P1A^C51) is required in this field if Docutel 5100 Device Handler processes do not use the same HPL file.

ATM-DH-MC4730 — The fully qualified file name of the microcode file for IBM 4730-series ATMs. The IBM 4730-series Device Handler processes use this assign.

Example: \B24.\$DATA.PRO1DATA.MC4730

Read By: A symbolic name (for example, P1A^I4370) is required in this field if IBM 4370-series Device Handler processes do not use the same microcode file.

ATM-DH-MDS1000-CPLF — The fully qualified file name of the Check Proof List File (CPLF) for Diebold 10XX/478X ATMs. Each Device Handler process can have a separate CPLF, or the logical network can have a single CPLF. This assign is used with the BASE24-atm self-service banking (SSB) Device Handler Extension. The BASE24-atm self-service banking (SSB) Device Handler Extension is an add-on product.

Example: \B24.\$DATA.PRO1DATA.CPLF100A

Read By: A symbolic name (for example, P1A^C1000) is required in this field if using the BASE24-atm self-service banking (SSB) Device Handler Extension and the Diebold 10XX/478X Device Handler processes do not use the same CPLF.

ATM-DH-MP4730 — The fully qualified file name of the microcode patch file for IBM 4730-series ATMs. The IBM 4730-series Device Handler processes use this assign.

Example: \B24.\$DATA.PRO1DATA.MP4730

Read By: A symbolic name (for example, P1A^I4730) is required in this field if IBM 4370-series Device Handler processes do not use the same microcode patch file.

ATM-DH-N50-CPLF — The fully qualified file name of the Check Proof List File (CPLF) for the NCR 5XXX-series ATMs. Each Device Handler process can have a separate CPLF, or the logical network can have a single CPLF. This assign is used with the BASE24-atm self-service banking (SSB) Device Handler Extension. The BASE24-atm self-service banking (SSB) Device Handler Extension is an add-on product.

Example: \B24.\$DATA.CPLFN50

Read By: A symbolic name (for example, P1A^N50) is required in this field if using the BASE24-atm self-service banking (SSB) Device Handler Extension and the NCR 5XXX Device Handler processes do not use the same CPLF.

ATM-DH-OIF1000 — The fully qualified file name of the Operator Identification File. The Operator Identification File (OIF) Server process and Diebold 10XX/478X Device Handler processes use this assign for ATMs that support the host-controlled solenoid-activated lock feature. This feature is available with Diebold release 2.1 firmware.

Example: \B24.\$DATA.PRO1DATA.OIF1000

ATM-DH-OLI6-LOAD-FILE — The fully qualified file name of the configuration file for Olivetti 6000 ATMs. The Olivetti 6000 Device Handler processes use this assign when downline loading terminals. This value can be overridden by a corresponding value in the device-dependent information in the individual Terminal Data File (TDF) record of the ATM.

Example: \B24.\$DATA.PRO1DATA.CNFGOLI6

Read By: A symbolic name (for example, P1A^OLI6) is required in this field if Olivetti 6000 Device Handler processes do not use the same configuration file.

ATM-MONTHLY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Monthly Transaction Volume Report program. The naming convention for this location is `$$.#ATMyymm`, where *yymm* is the year and month for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: `$$.ATM0112`

ATM-MONTHLY-REPORT-OBEOF — The fully qualified file name of the obey file to run the Monthly Transaction Volume Report program. The naming convention for this obey file is `ATMRyymm`, where *yymm* is the year and month for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: `\B24.$DATA.ATMR0112`

ATM-MONTHLY-REPORT-PROGRAM — The fully qualified file name of the ATM Monthly Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, *xx* is the number of the current release.

Example: `\B24.$BAxxTBP.BAMRPT`

ATM-MTAF — The fully qualified file name of the Monthly Totals Accumulation File (MTAF). The naming convention for this file is `ATMTyymm`, where *yymm* is the year and month for which the totals in the file were accumulated. The name of the subvolume where this file resides must be eight characters in length. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \B24.\$DATA.PRO1DATA.ATMT0112
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
 ATMTyymm) by the Transaction Based Pricing Report
 Initiator process.

ATM-NIDF — The fully qualified file name of the Note ID File (NIDF). This assign is used by the Shared BNA enhancements in the BASE24-atm self-service banking (SSB) add-on product for the following processes:

Note ID File Server Process
ATM Extended Memory Table Build Utility

Example: \B24.\$DATA.PRO1DATA.NIDF

ATM-NIDFEMT — The fully qualified file name of the Note ID File (NIDF) extended memory table, which contains NIDF records. This assign is used by the Shared BNA enhancements in the BASE24-atm self-service banking (SSB) add-on product for the following processes:

ATM Extended Memory Table Build Utility
BASE24-atm NCR 5XXX Device Handler process
BASE24 atm Diebold 10XX/478X Device Handler process

Example: \B24.\$DATA.PRO1DATA.NIDFEMT

ATM-RCPT — The fully qualified file name of the Receipt File (RCPT), which contains the receipt templates used for configurable receipts. The Receipt File Server process and the following Device Handler processes use the ATM-RCPT assign:

Diebold 910/911
Diebold 912
Fujitsu
Fujitsu 7000
IBM 4730

IBM 3624 (Version 8)
 IBM 3624 (Version 7)
 Tidel

Example: \B24.\$DATA.PRO1DATA.RCPT

ATM-SETL-ATD-EXTMEM-SWAPVOL — The fully qualified name of the BASE24-atm Terminal Data files extended memory swap volume. The Settlement Initiator process uses this assign to temporarily store data when building extended memory.

If this assign is not present in the LCONF or contains an invalid value, the HP NonStop operating system assigns a swap volume location.

Example: \B24.\$DATA

ATM-SETL-MON-RPT-PROG-3-NAME — The fully qualified file name of the program that generates the Monthly Terminal Settlement Report (SETL03). The BASE24-atm Settlement Initiator process uses this assign when generating the SETL03 report. If this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process does not produce the SETL03 report.

Example: \B24.\$DATA.ATxxOBJ.RP03B24, where *xx* is the number of the current release

ATM-SETL-MON-RPT-PROG-5-NAME — The fully qualified file name of the program that generates the Logical Network Monthly Institution Approved Transaction Volume Report (STAT05). The BASE24-atm Settlement Initiator process uses this assign when generating the STAT05 report. If this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process does not produce the STAT05 report.

Example: \B24.\$DATA.ATxxOBJ.RP05B24, where *xx* is the number of the current release

ATM-SETL-RPT0-OBEY-FILE

ATM-SETL-RPT1-OBEY-FILE — The fully qualified file names of the obey files the BASE24-atm Settlement Initiator process uses to generate the two sets of BASE24-atm settlement reports. The ATM-SETL-RPT0-OBEY-FILE assign is required to execute the first set of reports at the time indicated in the ATM-SETL-RPT0-STARTUP param. The ATM-SETL-RPT1-OBEY-FILE assign is required

to execute the second set of reports at the time indicated in the ATM-SETL-RPT1-STARTUP param. If all of the BASE24-atm report programs are started at the same time, the Settlement Initiator process uses only the ATM-SETL-RPT0-OBEY-FILE assign.

If either the first or second set of reports is to be run and the corresponding assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process abends at initialization.

Example: \B24.\$DATA.PRO1DATA.R0YYMMDD

ATM-SETL-RPT0-PROG-1-NAME

ATM-SETL-RPT1-PROG-1-NAME — The fully qualified file name of the program that generates the Logical Network Clearings Statement Report (SETL01).

The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT0-PROG-1-NAME assign when generating the SETL01 report with the first set of reports. The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT1-PROG-1-NAME assign when generating the report with the second set of reports. If the BASE24-atm Settlement Initiator process starts all of the BASE24-atm report programs at the same time, it uses only the ATM-SETL-RPT0-PROG-1-NAME assign.

ACI recommends that the BASE24-atm Settlement Initiator process be configured to generate the SETL01 report with the first set of reports. If an attempt is made to generate the SETL01 report with the second set of reports, the BASE24-atm Settlement Initiator process sends additional parameters in the startup message that are not needed.

These assigns are required only if the SETL01 report must be produced. If these assigns are not present in the LCONF or contain invalid values, the BASE24-atm Settlement Initiator process does not produce the SETL01 report.

Example: \B24.\$DATA.ATxxOBJ.RP01B24, where *xx* is the number of the current release

ATM-SETL-RPT0-PROG-2-NAME

ATM-SETL-RPT1-PROG-2-NAME — The fully qualified file name of the program that generates the Logical Network Daily Terminal Settlement Report (SETL02). The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT0-PROG-2-NAME assign when generating the SETL02 report with the first set of reports. The BASE24-atm Settlement Initiator process uses the ATM-SETL-

RPT1-PROG-2-NAME assign when generating the report with the second set of reports. If the BASE24-atm Settlement Initiator process starts all of the BASE24-atm report programs at the same time, it uses only the ATM-SETL-RPT0-PROG-2-NAME assign.

These assigns are required only if the SETL02 report must be produced. If these assigns are not present in the LCONF or contain invalid values, the BASE24-atm Settlement Initiator process does not produce the SETL02 report.

Example: \B24.\$DATA.ATxxOBJ.RP02B24, where *xx* is the number of the current release

ATM-SETL-RPT0-PROG-4-NAME

ATM-SETL-RPT1-PROG-4-NAME — The fully qualified file name of the program that generates the Logical Network Daily Institution Approved Transaction Volume Report (STAT04). The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT0-PROG-4-NAME assign when generating the STAT04 report with the first set of reports. The ATM-SETL-RPT1-PROG-4-NAME assign is used when generating the report with the second set of reports. If the BASE24-atm Settlement Initiator process starts all of the BASE24-atm report programs at the same time, it uses only the ATM-SETL-RPT0-PROG-4-NAME assign.

These assigns are required only if the STAT04 report must be produced. If these assigns are not present in the LCONF or contain invalid values, the BASE24-atm Settlement Initiator process does not produce the STAT04 report.

Example: \B24.\$DATA.ATxxOBJ.RP04B24, where *xx* is the number of the current release

ATM-SETL-RPT0-PROG-6-NAME

ATM-SETL-RPT1-PROG-6-NAME — The fully qualified file name of the program that generates the Logical Network Daily Terminal Detail Transaction Log (STAT06). The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT0-PROG-6-NAME assign when generating the STAT06 report with the first set of reports. The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT1-PROG-6-NAME assign when generating the report with the second set of reports. If the BASE24-atm Settlement Initiator process starts all of the BASE24-atm report programs at the same time, it uses only the ATM-SETL-RPT0-PROG-6-NAME assign.

These assigns are required only if the STAT06 report must be produced. If these assigns are not present in the LCONF or contain invalid values, the BASE24-atm Settlement Initiator process does not produce the STAT06 report.

Example: \B24.\$DATA.ATxxOBJ.RP06B24, where *xx* is the number of the current release

ATM-SETL-RPT0-PROG-7-NAME

ATM-SETL-RPT1-PROG-7-NAME — The fully qualified file name of the program that generates the Logical Network Daily Institution Detail Transaction Log Report (STAT07). The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT0-PROG-7-NAME assign when generating the STAT07 report with the first set of reports. The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT1-PROG-7-NAME assign when generating the report with the second set of reports. If the BASE24-atm Settlement Initiator process starts all of the report programs at the same time, it uses only the ATM-SETL-RPT0-PROG-7-NAME assign.

These assigns are required only if the STAT07 report must be produced. If these assigns are not present in the LCONF or contain invalid values, the BASE24-atm Settlement Initiator process does not produce the STAT07 report.

Example: \B24.\$DATA.ATxxOBJ.RP07B24, where *xx* is the number of the current release

ATM-SETL-RPT0-PROG-8-NAME

ATM-SETL-RPT1-PROG-8-NAME — The fully qualified file name of the program that generates the Logical Network Daily Terminal Depository Report (STAT08). The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT0-PROG-8-NAME assign when generating the STAT08 report with the first set of reports. The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT1-PROG-8-NAME assign when generating the report with the second set of reports. If the BASE24-atm Settlement Initiator process starts all of the report programs at the same time, it uses only the ATM-SETL-RPT0-PROG-8-NAME assign.

These assigns are required only if the STAT08 report must be produced. If these assigns are not present in the LCONF or contain invalid values, the BASE24-atm Settlement Initiator process does not produce the STAT08 report.

Example: \B24.\$DATA.ATxxOBJ.RP08B24, where *xx* is the number of the current release

ATM-SETL-RPT3M — The fully qualified template name of the master file that contains information on terminal settlement for the current month. This file is an accumulator file where daily data is stored when the Settlement Initiator process produces daily reports. The Settlement Initiator process uses the file specified in this assign to produce the Monthly Terminal Settlement Report (SETL03-B24).

The Settlement Initiator process uses the first six characters of the file name specified in this assign to create the actual file name. It then appends two characters to the first six characters. These two characters identify the month for which the report is produced. For example, if RPT3MSTR is specified in this assign, the report file created would be RPT3MS05 for the month of May.

This assign is required if the BASE24-atm Settlement Initiator process must produce reports. If reports are to be produced and this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process abends at initialization.

Example: \B24.\$DATA.PRO1DATA.RPT3MSTR
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
 RPT3MSTR) by the BASE24-atm Settlement Initiator
 process.

ATM-SETL-RPT3T — The fully qualified template name of the totals file that contains totals information on terminal settlement for the current month. This file is an accumulator file where daily data is stored when the Settlement Initiator process produces daily reports. The Settlement Initiator process uses the file specified in this assign to produce the Monthly Terminal Settlement Report (SETL03-B24).

The Settlement Initiator process uses the first six characters of the file name specified in this assign to create the actual file name. It then appends two characters to the first six characters. These two characters identify the month for which the report is produced. For example, if RPT3TOTL is specified in this assign, the report file created would be RPT3TO05 for the month of May.

This assign is required if the BASE24-atm Settlement Initiator process must produce reports. If reports are to be produced and this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process abends at initialization.

Example: \B24.\$DATA.PRO1DATA.RPT3TOTL
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
 RPT3TOTL) by the BASE24-atm Settlement Initiator
 process.

ATM-SETL-RPT5M — The fully qualified template name of the master file that contains information on terminal settlement for the current month. This file is an accumulator file where daily data is stored when the Settlement Initiator process produces daily reports. The Settlement Initiator process uses the file specified in this assign to produce the Monthly Institution Approved Transaction Volume Report (SETL05-B24).

The Settlement Initiator process uses the first six characters of the file name specified in this assign to create the actual file name. It then appends two characters to the first six characters. These two characters identify the month for which the report is produced. For example, if RPT5MSTR is specified in this assign, the report file created would be RPT5MS05 for the month of May.

This assign is required if the BASE24-atm Settlement Initiator process must produce reports. If reports are to be produced and this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process abends at initialization.

Example: \B24.\$DATA.PRO1DATA.RPT5MSTR
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
 RPT5MSTR) by the BASE24-atm Settlement Initiator
 process.

ATM-SETL-RPT5T — The fully qualified template name for the totals file that contains totals information on terminal settlement for the current month. This file is an accumulator file where daily data is stored when the Settlement Initiator process produces daily reports. The Settlement Initiator process uses this assign to produce the Monthly Institution Approved Transaction Volume Report (SETL05-B24).

The Settlement Initiator process uses the first six characters of the file name specified in this assign to create the actual file name. It then appends two characters to the first six characters. These two characters identify the month for which the report is produced. For example, if RPT5TOTL is specified in this assign, the report file created would be RPT5TO05 for the month of May.

This assign is required if the BASE24-atm Settlement Initiator process must produce reports. If reports are to be produced and this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process abends at initialization.

Example: \B24.\$DATA.PRO1DATA.RPT5TOTL
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
 RPT5TOTL) by the BASE24-atm Settlement Initiator
 process.

ATM-TRF — The fully qualified name of the Terminal Receipt File (TRF). The following processes use this assign:

Terminal Receipt File Server process
Base Extended Memory Table Build utility

Example: \B24.\$DATA.PRO1DATA.TRF

ATM-TRFEMT — The fully qualified file name of the Terminal Receipt File (TRF) extended memory table, which contains TRF records. The following processes use this assign:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process
Base Extended Memory Table Build utility

If this assign is not present in the LCONF or contains an invalid value, the Base Extended Memory Table Build utility displays an error message indicating that the assign needs to be corrected, and the processes listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.TRFEMT

ATM-TRN-THF — The fully qualified file name of the Transaction Analysis Transaction History File (THF). The THF is a report file that contains reports produced by the BASE24-atm Transaction Analysis utility. The BASE24-atm Transaction Analysis utility is part of the BASE24 Performance Tools.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-atm Transaction Analysis utility does not initialize.

Example: \B24.\$DATA.PRO1DATA.THF

CPLF — The fully qualified file name of the Check Proof List File (CPLF). The CPLF assign is used by the IBM 473X Device Handler process.

Example: \B24.\$DATA.PRO1DATA.CPLF
Usage Codes: ATM

HSF — The fully qualified file name of the Hardware Status File (HSF). The IBM 3624 Device Handler (Version 8) processes use this file to keep track of the hardware status of 3624 terminals when the Hardware Status Error Logging (ELARG) module is in use. The Hardware Status Error Logging module is an add-

on module and must be purchased separately. Hardware faults are logged to the HSF. The BASE24-atm Settlement Initiator process creates the HSF each day. The Super Extract process uses this assign when extracting the HSF. If the HSF assign is not present in the LCONF, the Settlement Initiator process assumes the HSF is not being used.

Example: \B24.\$DATA.PRO1DATA.HSYMMDD
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
 HSYMMDD) by the BASE24-atm Settlement Initiator
 process.

RCPT — The fully qualified file name of the Receipt File (RCPT), which contains the receipt templates used for configurable receipts. The Base Extended Memory Table Build utility uses this assign to build the Receipt File (RCPT) extended memory table, which is used by the Diebold 10XX/478X and NCR 5XXX Device Handler processes.

Example: \B24.\$DATA.PRO1DATA.RCPT

RCPTTEM — The fully qualified file name of the Receipt File (RCPT) extended memory table, which contains Receipt File (RCPT) records. The following processes use this assign:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process
Base Extended Memory Table Build utility

This assign is required. If it is not present in the LCONF or contains an invalid value, the Base Extended Memory Table Build utility displays an error message indicating that the assign needs to be corrected, and the Diebold 10XX/478X and NCR 5XXX Device Handler processes do not initialize.

Example: \B24.\$DATA.PRO1DATA.RCPTTEM

REMOTE-LCONF — The location of the remote LCONF which is passed by the local Device Control Terminal (DCT) Server to its remote counterpart for supporting remotely connected terminals.

This assign is required for Dual Site support.

Example: \B24.\$DATA.PRODCNTL.L1CONF

REMOTE-PMON — The PPD of the Pathmon process on the remote system. This assign enables the local Device Control Terminal (DCT) Server to communicate with its remote counterpart to support remotely connected terminals.

This assign is required for Dual Site support.

Example: \B24.\$PPMN

SSB-BSF — The fully qualified file name of the Bin Sort File (BSF). The following BASE24-atm processes use this assign:

Bin Sort File Server process
Diebold 10XX/478X Device Handler process
Fujitsu 7000 Device Handler process
NCR 5XXX Device Handler process

The BSF contains limit sorting mechanism parameters by which the BASE24-atm Device Handler processes must sort checks.

The assign is used only with the BASE24-atm self-service banking (SSB) Enhanced Check Application. The BASE24-atm self-service banking (SSB) Enhanced Check Application is an add-on product.

Example: \B24.\$DATA.PRO1DATA.BSF

SSB-CCF — The fully qualified file name of the Corporate Check File (CCF). The CCF contains check authorization parameters based on the check issuer. The following processes use this assign:

BASE24-atm Authorization process
Corporate Check File Server process
Enscribe Refresh process
From Host Maintenance process

The assign is used only with the BASE24-atm self-service banking (SSB) Enhanced Check Application. The BASE24-atm self-service banking (SSB) Enhanced Check Application is an add-on product.

Example: \B24.\$DATA.PRO1DATA.CCF

SSB-CSF — The fully qualified file name of the Check Status File (CSF). The CSF specifies the status of registered preapproved and predeclined checks. The following processes use this assign:

BASE24-atm Authorization process
Check Status File Server process
Enscribe Refresh process
From Host Maintenance process

The assign is used only with the BASE24-atm self-service banking (SSB) Enhanced Check Application. The BASE24-atm self-service banking (SSB) Enhanced Check Application is an add-on product.

Example: \B24.\$DATA.PRO1DATA.CSF

SVRPT-ERR-LOG — The network location for event messages generated by the BASE24-atm Report Perusal Server process.

This assign identifies the Sudoterm PPD name or \$0.

Examples: \$SUDO
 \$0

TDF — The fully qualified file name of the Terminal Data File (TDF). This assign is used by the following processes:

Burroughs RT650 Device Handler process
Device Control Terminal Server process
Diebold CashSource Plus Device Handler process
Diebold 910/911 Device Handler process
Diebold 912 Device Handler process
Docutel ETS 5100/5200 Device Handler process
Fujitsu Device Handler process
Fujitsu 7000 Device Handler process
Generic Simulator process
IBM 4730 Device Handler process
IBM 3624 (Version 8) Device Handler process
IBM 3624 (Version 7) Device Handler process
Mail process
NCR “Cash” Device Handler process
Olivetti 6000 Device Handler process
Terminal Data File Server process
Tidel Device Handler process

Triton Device Handler process
BASE24-atm Terminal Data files Server object
Settlement Initiator process
BASE24-atm Transaction Analysis utility

Example: \B24.\$DATA.PRO1DATA.TDF

TLF — The fully qualified file name of the Transaction Log File (TLF). This assign is used by the following processes:

Transaction Based Pricing ATM Daily Transaction Volume Report process
Transaction Log File Server process
BASE24-atm Authorization process
BASE24-atm Settlement Initiator process
BASE24-atm Transaction Context Manager process
Enscribe Refresh process
Super Extract process
BASE24-atm Transaction Analysis utility

When using dual site processing, the Enscribe Refresh process and the Super Extract process can use process-specific TLFs.

This assign is required. If this assign is not present in the LCONF or contains an invalid value, the processes that access the LCONF for this assign abend during initialization.

Example: \B24.\$DATA.PRO1ATLF.TLYYMMDD
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
 TLYYMMDD) because BASE24 periodically creates the TLF.

Params

The following params are used exclusively by the BASE24-atm product. Each of the following params should have the usage code ATM (and only the code ATM) entered in the USAGE CODES field on the LNCF Param screen.

ATM-A4000-MASTER — The symbolic name of the BASE24-atm Authorization process (for example, P1A^AUTH01) responsible for downloading Diebold number tables (DNTs) from the Key Authorization File (KEYA) to an Atalla Network Security Processor (NSP) model A8000 or A8100 during process initialization or process warmboots. The A8000 or A8100 security device fails when more than one Authorization process attempts to load DNTs during initialization or warmboots. This param is required only when using a model A8000 or A8100 security device with the BASE24-atm product.

The BASE24-atm Authorization processes use this param.

Param Default: No default value

ATM-ACQ-DISCR-DATA-SUPPRS — A flag indicating whether logging discretionary data for acquirer transactions to the Transaction Log File (TLF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. BASE24-atm Authorization uses this param. Valid values are as follows:

Y = Yes, suppress logging of discretionary data.

N = No, do not suppress logging of discretionary data.

Param Default: N

ATM-AUTH-IDF-DATES-COMPUTE — A param specifying whether the BASE24-atm Authorization process should compute the Institution Definition File (IDF) business dates during cutover processing or if the BASE24-atm Authorization process should read the Institution Definition File (IDF) business dates from a disk. If this param is set to a value of Y, Authorization computes IDF business dates during cutover processing. If set to N, Authorization reads the IDF business dates from a disk.

Y = Yes, Authorization should compute IDF business dates during cutover.

N = No, do not compute IDF business dates during cutover, read from disk.

Param Default: N

ATM-DH-1000-AKDS-SERIAL-NUM-VRFY — A code indicating whether to verify the Encrypting PIN Pad (EPP) serial number against a list of approved numbers maintained in the Transaction Security Services (TSS) database, during the exchange of public keys between the EPP and BASE24. This verification occurs during the authentication and public key exchange sequence of Automated Key Distribution System processing. This param is used only with the Automated Key Distribution System add-on product.

The Diebold 10XX/478X Device Handler process uses this param. Valid values are as follows:

Y = Yes, verify the EPP serial number against the list in the TSS database.
 N = No, do not verify the EPP serial number against the list in the TSS database.

Param Default: N

ATM-DH-ADDENDS — A number used to display a set of screens in a secondary language. The Device Handler process adds the value of this param to the screen number of the primary language if the secondary language has been selected at the ATM.

The BASE24-atm Device Handler processes listed in the table below use this param with the corresponding default values and restrictions. The value of this param is device-dependent; for example, for Diebold 912 Device Handler processes, the param should be set to 125. Contact an ACI representative for complete information on multiple language support by a specific type of ATM.

Device Handler	Default	Restrictions
Diebold 10XX/478X	256	Should be set to 256 for the standard BASE24-atm product; however, any value equal to or greater than 256 is allowed if required for a particular configuration.
Diebold 910/911	125	Should be set to 125 for the standard BASE24-atm product; however, there is no edit check so you can use any value required for a particular configuration.
Diebold 912	125	Must be set to 125.

Device Handler	Default	Restrictions
Fujitsu 7000	0	Contains a number (an offset) used to display a set of screens in a secondary language. This offset is used with the 'P' state implementation of multiple languages.

If this param is set to an improper value, the BASE24-atm product attempts to send a non-existent screen to the device, causing an error at the device.

Read By: A symbolic name (for example, P1A^D910) is required in this field because the param value varies for different BASE24-atm Device Handler processes.

Param Default: The default value is device-dependent.

ATM-DH-AKDS-TSS-TIMER — The number of seconds the BASE24-atm Device Handler process waits for a reply from the Transaction Security Services process before aborting an authentication and public key exchange or a master key download. This param is used only with the BASE24-atm Automated Key Distribution System add-on product. Valid values are 10–600.

Read By: A symbolic name (for example, P1A^C1000) is required in this field if the param value varies among BASE24-atm Device Handler processes.

Param Default: 600

ATM-DH-AUTH-TIMER — The number of seconds the BASE24-atm Device Handler process waits, after sending a 0200 request message, for a reply from the BASE24-atm Authorization process before denying the request. Valid values are 10 through 180. The BASE24-atm Device Handler process uses this param.

Read By: A symbolic name (for example, P1A^C1000) is required in this field if the param value varies among BASE24-atm Device Handler processes.

Param Default: 45

ATM-DH-CHK-BIN-THRHLD — A value indicating the threshold of the first check bin. Check amounts that equal or exceed this value are retained in the second check bin. All others are retained in the first bin. This param is used only with the BASE24-atm self-service banking (SSB) add-on product for the following processes:

Diebold 10XX/478X Device Handler process
Fujitsu 7000 Device Handler process
NCR 5XXX Device Handler process

Valid values include any whole dollar amount from 0 through 9999999999. A value of 0 indicates that sorting is not performed, and all checks are retained in the second bin.

Note: This param is not required if the institution has installed the BASE24-atm self-service banking (SSB) Enhanced Check Application and is using the Bin Sort File (BSF).

Param Default: 0

ATM-DH-CHK-DISP-FAULT-ACT — A value controlling the action that the Diebold 10XX/478X and Fujitsu 7000 Device Handler processes take when the ATM cannot dispense the full transaction amount during a cash check transaction. This param is used with the BASE24-atm self-service banking (SSB) Enhanced Check Application.

Valid values are as follows:

0 = Cancel and reverse the cash check transaction. Return the check and do not deliver any cash to the cardholder. Disable the ATM cassette that faulted.

Note: If coins were already dispensed for the cash check transaction before it was determined that the full amount could not be dispensed, a partial reversal is performed. The completed amount of the transaction is then equal to the amount of change dispensed.

1 = Allow the cash check transaction to complete by retaining the check and dispensing the cash that is available; the BASE24 system will then generate either a full or partial reversal to reflect that the check was accepted but the full amount could not be dispensed.

Param Default: 0

ATM-DH-CONNECT-MSGS — A flag indicating whether the Olivetti 6000 Device Handler process generates event messages detailing the stations to which it is connected when it receives a 9518 text command. Valid values are as follows:

ON = Yes, event messages are generated for the 9518 command.

OFF = No, event messages are not generated for the 9518 command.

Param Default: ON

ATM-DH-CONS-MAC-ERR-LMT — The number of consecutive security message authentication code (MAC) errors that can occur before the Device Handler process downloads new MAC and PIN keys to the ATM. The actions taken by the Device Handler process vary according to Device Handler process and whether the BASE24-atm Dynamic Key Management add-on feature is being used.

- The Diebold 910/911, Fujitsu 7000, Olivetti 6000 Device Handler processes and the Diebold 10XX/478X and NCR 5XXX Device Handler processes without the Dynamic Key Management add-on feature shut down the ATM when the limit specified in this param is met.
- The Diebold 10XX/478X and NCR 5XXX Device Handler processes with the Dynamic Key Management add-on feature shut down the ATM, load new MAC and PIN keys, and attempt to reopen the ATM.
- The Tidel Device Handler process reloads the new MAC and PIN keys without shutting down the ATM.

Valid values are 0 through 32767. A value of 0 indicates that the Device Handler process does not load new keys regardless of the number of consecutive security MAC errors. The following Device Handler processes use this param:

Diebold 10XX/478X
Diebold 910/911
Fujitsu 7000
NCR 5XXX
Olivetti 6000
Tidel

Read By: A symbolic name is required in this field if the limit varies among Device Handler processes.

Param Default: 3

ATM-DH-DISCONNECT-X25-REQD — A flag indicating whether the Olivetti 6000 Device Handler process disconnects after processing a transaction from a dial-up terminal connected using the X.25 protocol. Valid values are as follows:

YES = Yes, disconnect the X.25 connection after processing the transaction.
NO = No, do not disconnect the X.25 connection after processing the transaction.

Param Default: NO

ATM-DH-DISPLAY-NATIVE-STATUS-MSG — A value indicating whether the native status message data is displayed in the event message. If this parameter does not exist or has a value other than Y, the native status message data is not displayed in the event message. This param is used by the Diebold 10XX/478X and NCR 5XXX Device Handler processes. Valid values are:

Y = Yes, display the native status message data in the event message.
N = No, do not display the native status message data in the event message.

Param Default: N

ATM-DH-DKM-KEY-CHNG-INTRVL — The maximum number of hours allowed between PIN or MAC key changes before the Device Handler process downloads new MAC and PIN keys to the ATM. This param is used with the BASE24-atm Dynamic Key Management add-on feature. Valid values are 0 through 32767. A value of 0 indicates the Device Handler process does not load new keys regardless of the length of time since the last key change. The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX
Tidel
Triton

When the time limit set by the value of this param has been reached, the Diebold 10XX/478X and NCR 5XXX Device Handler processes shut down the ATM, load new PIN and MAC keys, and attempt to reopen the ATM. The Triton Device Handler and Tidel Device Handler processes load the new PIN and MAC keys without first shutting down the ATM.

Param Default: 0

ATM-DH-DKM-MAC-ERR-LMT — The number of security MAC errors that can occur before the Device Handler process downloads new MAC and PIN keys to the ATM. This param is used with the BASE24-atm Dynamic Key Management add-on feature. Valid values are 0 through 32767. A value of 0 indicates the Device Handler process does not load new keys regardless of the number of security MAC errors that have occurred since the last key change. The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX
Tidel

When the limit set by the value of this param has been reached, the Diebold 10XX/478X and NCR 5XXX Device Handler processes shut down the ATM, load new PIN and MAC keys, and attempt to reopen the ATM. The Triton Device Handler and Tidel Device Handler processes load the new PIN and MAC keys without first shutting down the ATM.

Param Default: 0

ATM-DH-DKM-MAC-TXN-LMT — The number of security MAC generations or verifications that can occur before the Device Handler process downloads new MAC and PIN keys to the ATM. This param is used with the BASE24-atm Dynamic Key Management add-on feature. Valid values are 0 through 32767. A value of 0 indicates the Device Handler process does not load new keys regardless of the number of security MAC generations or verifications that have occurred since the last key change. The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX
Tidel
Triton

When the limit set by the value of this param has been reached, the Diebold 10XX/478X and NCR 5XXX Device Handler processes shut down the ATM, load new PIN and MAC keys, and attempt to reopen the ATM. The Triton Device Handler and Tidel Device Handler processes load the new PIN and MAC keys without first shutting down the ATM.

Param Default: 0

ATM-DH-DKM-PIN-ERR-LMT — The number of PIN verification errors that can occur before the Device Handler process downloads new MAC and PIN keys to the ATM. This param is used with the BASE24-atm Dynamic Key Management add-on feature. Valid values are 0 through 32767. A value of 0 indicates the Device Handler process does not load new keys regardless of the number of security PIN errors that have occurred since the last key change. The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX
Tidel
Triton

When the limit set by the value of this param has been reached, the Diebold 10XX/478X and NCR 5XXX Device Handler processes shut down the ATM, load new PIN and MAC keys, and attempt to reopen the ATM. The Triton Device Handler and Tidel Device Handler processes load the new PIN and MAC keys without first shutting down the ATM.

Param Default: 0

ATM-DH-DKM-PIN-TXN-LMT — The number of PIN verification transactions that can occur before the Device Handler process downloads new MAC and PIN keys. This param is used with the BASE24-atm Dynamic Key Management add-on feature. Valid values are 0 through 32767. A value of 0 indicates the Device Handler process does not load new keys regardless of the number of PIN verification transactions that have occurred since the last key change. The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX
Tidel
Triton

When the limit set by the value of this param has been reached, the Diebold 10XX/478X and NCR 5XXX Device Handler processes shut down the ATM, load new PIN and MAC keys, and attempt to reopen the ATM. The Triton Device Handler and Tidel Device Handler processes load the new PIN and MAC keys without first shutting down the ATM.

Param Default: 0

ATM-DH-DYN-TBL-RETN-PRD-DIAL-UP — The number of seconds the Device Handler process waits for the next leg of a multiple leg transaction before the dynamic data for a dial-up terminal can be removed from the dynamic data table held in extended memory. A value of 0 disables this processing. The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX

When a customer or service person performs a multiple leg transaction, the Device Handler process retains the dynamic data for the terminal in memory until all legs of the transaction are complete. For the NCR 5XXX Device Handler process, this includes the following transactions: administrative, Non-Currency Dispense, surcharging, and surcharging with interactive response notification. For the Diebold 10XX/478X Device Handler process, this includes the following transactions: Non-Currency Dispense, surcharging, and surcharging with interactive response notification. If a customer or service person cancels one of the above transactions, the terminal does not notify the Device Handler process of the cancellation and the terminal's dynamic data entry is left in extended memory.

To avoid exceeding the maximum number of entries allowed for dynamic data (specified in the ATM-DH-MAX-TERMS-IN-DYN-TBL param), the Device Handler process deletes entries from dynamic data for multiple leg transactions that have been in the dynamic data table longer than the duration specified by this param. Valid values are 0 through 32766. If this param is not configured or contains an invalid value, the default value of 60 seconds is used.

Note: A value of Y in the DIAL-UP field on Diebold 10XX/478X ATD screen 7 or on NCR 5XXX ATD screen 7 indicates a dial-up ATM.

Param Default: 60

ATM-DH-DYN-TBL-RETN-PRD-LEASE — The number of seconds the Device Handler process waits for the next leg of a multiple leg transaction before the dynamic data for a terminal connected over a leased line can be removed from the dynamic data table held in extended memory. A value of 0 disables this processing. The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX

When a customer or service person performs a multiple leg transaction, the Device Handler process retains the dynamic data for the terminal in memory until all legs of the transaction are complete. For the NCR 5XXX Device Handler process, this

includes the following transactions: administrative, Non–Currency Dispense, surcharging, and surcharging with interactive response notification. For the Diebold 10XX/478X Device Handler process, this includes the following transactions: Non–Currency Dispense, surcharging, and surcharging with interactive response notification. If a customer or service person cancels one of the above transactions, the terminal does not notify the Device Handler process of the cancellation and the terminal’s dynamic data entry is left in extended memory.

To avoid exceeding the maximum number of entries allowed for dynamic data (specified in the ATM-DH-MAX-TERMS-IN-DYN-TBL param), the Device Handler process deletes entries from dynamic data for multiple leg transactions that have been in the dynamic data table longer than the duration specified by this param. Valid values are 0 through 32766. If this param is not configured or contains an invalid value, the default value of 60 seconds is used.

Note: A value of N in the DIAL-UP field on Diebold 10XX/478X ATD screen 7 or on NCR 5XXX ATD screen 7 indicates an ATM connected over a leased line.

Param Default: 60

ATM-DH-FUJ7-CPLF-REQ — A code indicating whether the Check Proof List File (CPLF) is required for processing. This param is used only with the BASE24-atm self-service banking (SSB) add-on product.

The Fujitsu 7000 Device Handler process uses this param. Valid values are as follows:

Y = Yes, the CPLF is required.
N = No, the CPLF is not required.

If the value in this param is Y and the ATM-DH-FUJ7-CPLF assign is not present in the LCONF, the Device Handler process abends during initialization. If the value in this param is N and the ATM-DH-FUJ7-CPLF assign is not present in the LCONF, the Device Handler process supports check transactions but a CPLF is not used. If the value in this param is N and the ATM-DH-FUJ7-CPLF assign is present in the LCONF, the Device Handler process writes check transactions to the CPLF.

Param Default: Y

ATM-DH-LOG-SCND-ERR — A code indicating whether the Device Handler process raises additional event messages to tell the status of hardware components.

When an NCR 5XXX terminal experiences an error (e.g., an entry/re-entry error, orientation error, etc.) during Document Processing Module (DPM) operations and the M-status is 00 (no error) or the supply status is OK. Valid values are as follows:

Y = Yes, generate event messages for DPM errors.

N = No, do not generate event messages for DPM errors.

When using this param with the Diebold 10XX/478X Device Handler process or the NCR 5XXX Device Handler process without the DPM, this param indicates whether to raise an additional event message containing detailed information about each suspended or faulted hardware component. For the Diebold 10XX/478X Device Handler process, the event message number is 598. For the NCR 5XXX Device Handler process, the event message number is 480. Valid values are as follows:

Y = Yes, raise an additional event message containing faulted hardware information.

N = No, do not raise an additional event message.

Param Default: N

ATM-DH-MAX-IN-CORE — The maximum number of Terminal Data File (TDF) records that a Device Handler process can store in memory at one time. Thus, this param indicates the amount of extended memory each Device Handler process must reserve for TDF records and the maximum number of transactions each Device Handler process can process at one time.

The Device Handler process stores a TDF record in memory each time it receives a transaction from an ATM. The Device Handler process retains that TDF record in memory until it receives an authorization response from the Authorization process and, if required, a completion message from the ATM.

If the value in this param is too low, the Device Handler process can run out of extended memory during peak processing times and transactions are declined until more extended memory becomes available. If the value in this param is set too high, the excess extended memory is wasted.

The value in this param is an estimate of the maximum number of devices that can have transactions in progress at one time. This param can be set to any numeric value greater than zero. However, the value in this param should not be greater than the value in the ATM-DH-MAX-TDFS param.

The following BASE24-atm Device Handler processes use this param:

Burroughs 650/750
Diebold CashSource Plus
Diebold 910/911
Diebold 912
Docutel 5100
Fujitsu
Fujitsu 7000
IBM 4730
NCR “Cash”
Olivetti 6000
Tidel
Triton

Read By: A symbolic name (for example, P1A^D910) is required in this field if this number varies among BASE24-atm Device Handler processes.

Param Default: 25

ATM-DH-MAX-LOAD-CMD — The maximum number of ATM Dial-Up Command File (ADCF) LOAD commands that can be processed by the Device Handler process at one time. This param is used by the following Device Handler processes when the Dial-Up Extension is installed:

Diebold 10XX/478X
NCR 5XXX

Any integer value greater than zero is valid.

Param Default: 30

ATM-DH-MAX-QUEUED-CMD — The maximum number of LOAD commands that can be queued to a terminal at one time in the ATM Dial-Up Command File (ADCF). This param is used by the following Device Handler processes when the Dial-Up Extension is installed:

Diebold 10XX/478X
NCR 5XXX

Any integer value greater than zero is valid.

Param Default: 20

ATM-DH-MAX-TDFS — The maximum number of Terminal Data File (TDF) record keys that each BASE24-atm Device Handler process can store in memory. Thus, this param indicates the maximum number of terminals each Device Handler process can manage.

When a Device Handler process initializes or reinitializes, space is allocated in memory to build a table. This table stores the record positions of all TDF records that the Device Handler process can access. By accessing this table, the Device Handler process can quickly locate the devices to which it must send transactions.

If the value in this param is set too low, the Device Handler process may run out of space in the table and be unable to process for all the devices. If the value in this param is set too high, the excess table space is wasted. The value of this param should be equal to the total number of devices that are associated with each Device Handler process. This param can be set to any numeric value greater than zero. However, the value in this param should be greater than the value in the ATM-DH-MAX-IN-CORE param.

The following BASE24-atm Device Handler processes use this param:

Burroughs 650/750
Diebold CashSource Plus
Diebold 910/911
Diebold 912
Docutel 5100
Fujitsu
Fujitsu 7000
IBM 4730
IBM 3624 (Version 8)
IBM 3624 (Version 7)
NCR “Cash”
Olivetti 6000
Tidel
Triton

Read By: A symbolic name (for example, P1A^D910) is required in this field if this number varies among BASE24-atm Device Handler processes.

Param Default: 100

ATM-DH-MAX-TERMS — The maximum number of BASE24-atm Terminal Data files records that each of the following BASE24-atm Device Handler processes can manage:

Diebold 10XX/478X NCR 5XXX

When a Diebold 10XX/478X or NCR 5XXX Device Handler process initializes or reinitializes, space is allocated in extended memory for the BASE24-atm Terminal Data files records the Device Handler process is responsible for maintaining. By accessing this data in extended memory rather than from a disk file, the Diebold 10XX/478X and NCR 5XXX Device Handler processes can process transactions more quickly.

If the value in this param is set too low, the Diebold 10XX/478X or NCR 5XXX Device Handler process may run out of extended memory space and be unable to process for all of their assigned devices. If the value in this param is set too high, the excess extended memory space is wasted. The value of this param must be determined as described below. The total number of devices that are associated with each Device Handler process in the BASE24-atm Terminal Data Static File—general data (ATDS1) should equal this calculated value. This param can be set to any numeric value greater than zero.

The values for the ATM-DH-MAX-TERMS, ATM-DH-MAX-TERMS-IN-DYN-TBL, and ATM-DH-MAX-TERMS-IN-STATIC-TBL params must be determined due to memory management requirements. The values of the ATM-DH-MAX-TERMS-IN-DYN-TBL and the ATM-DH-MAX-TERMS-IN-STATIC-TBL params should be less than the value in the ATM-DH-MAX-TERMS param. Use the following formula to calculate the amount of extended memory (in bytes) used by each Device Handler process:

$$\begin{aligned} &8298 \\ &+ (\text{ATM-DH-MAX-TERMS value} \times 138) \\ &+ (\text{ATM-DH-MAX-TERMS-IN-DYN-TBL value} \times 8048) \\ &+ (\text{ATM-DH-MAX-TERMS-IN-STATIC-TBL value} \times 4062) \\ &= \text{Total extended memory used per Device Handler process} \end{aligned}$$

If you are also using the BASE24-atm Terminal Data Dynamic File—scratch pad (ATDD2), increase the above sum by the following:

$$(\text{ATM-DH-MAX-TERMS-IN-DYN-TBL value} \times 4062)$$

For example, if the values of the ATM-DH-MAX-TERMS, ATM-DH-MAX-TERMS-IN-DYN-TBL, and ATM-DH-MAX-TERMS-IN-STATIC-TBL params are 100, 50, and 90, respectively, the total amount of extended memory used by

each Device Handler process would be 790,078 bytes (i.e., $8298 + (100 \times 138) + (50 \times 8048) + (90 \times 4062)$). If the ATDD2 were also used, the total amount would be 993,178 bytes (i.e., $790078 + (50 \times 4062)$)

Read By: A symbolic name (for example, P1A^N50) is required in this field if this number varies among BASE24-atm Device Handler processes.

Param Default: 100

ATM-DH-MAX-TERMS-IN-CPLF-TBL — The maximum number of unique terminals that can exist at one time in the CPLF extended memory table.

Read By: A symbolic name (for example, P1A^N50) is required in this field if this number varies among BASE24-atm Device Handler processes.

Param Default: 1/5 of the value specified by the param ATM-DH-MAX-TERMS

ATM-DH-MAX-TERMS-IN-DYN-TBL — The maximum number of BASE24-atm Terminal Data Dynamic File—general data (ATDD1) and BASE24-atm Terminal Data Dynamic File—scratch pad (ATDD2) records for which the following BASE24-atm Device Handler processes can have transactions in progress at one time:

Diebold 10XX/478X
NCR 5XXX

Thus, this param indicates the amount of extended memory each Device Handler process must reserve for dynamic terminal files (ATDD1 and ATDD2) records and the maximum number of transactions each Device Handler process can process at one time.

The Diebold 10XX/478X or NCR 5XXX Device Handler process stores an ATDD1 record in memory each time it receives a transaction from an ATM. The Device Handler process retains these ATDD1 records in memory until it receives a completion message from the ATM.

If the value in this param is too low, the Device Handler process can run out of extended memory during peak processing times and transactions are declined until more extended memory becomes available. If the value in this param is set too high, the excess extended memory is wasted. The value of this param must be determined as described in the ATM-DH-MAX-TERMS param description.

The value in this param is the maximum number of devices that can have transactions in progress at one time. This param can be set to any numeric value greater than zero. However, the value in this param should not be greater than the value in the ATM-DH-MAX-TERMS param.

Read By: A symbolic name (for example, P1A^N50) is required in this field if this number varies among BASE24-atm Device Handler processes.

Param Default: The lesser of 25 or the value of the ATM-DH-MAX-TERMS param

ATM-DH-MAX-TERMS-IN-STATIC-TBL — The maximum number of Terminal Data Static File (ATDS1) records that the following BASE24-atm Device Handler process can service:

Diebold 10XX/478X
NCR 5XXX

Thus, this param indicates the amount of extended memory each Device Handler process must reserve for ATDS1 records.

The Diebold 10XX/478X or NCR 5XXX Device Handler process reads an ATDS1 record from disk and stores the record in memory the first time it receives a transaction from an ATM. The process continues to dynamically add ATDS1 records to memory until it runs out of space or the process is warmbooted. When the process runs out of space, the oldest record is deleted from memory and the new record is added. When the static data is reinitialized or the process is warmbooted, all of the ATDS1 records are deleted from memory and the process begins adding them again dynamically as transactions are processed.

If the value in this param is too low, the Device Handler process can run out of extended memory during peak processing times and be forced to delete the oldest record from memory to make room for adding a new record, thereby causing a possible degradation in transaction processing performance. If the value in this param is set too high, the excess extended memory is wasted. The value of this param must be determined as described in the ATM-DH-MAX-TERMS param description.

This param can be set to any numeric value greater than zero. However, the value in this param should not be greater than the value in the ATM-DH-MAX-TERMS param.

Read By: A symbolic name (for example, P1A^N50) is required in this field if this number varies among BASE24-atm Device Handler processes.

Param Default: 25

ATM-DH-MDS1000-CPLF-REQ — A code indicating whether the Check Proof List File (CPLF) is required for processing. This param is used only with the BASE24-atm self-service banking (SSB) add-on product.

The Diebold 10XX/478X Device Handler process uses this param. Valid values are as follows:

Y= Yes, the CPLF is required.

N= No, the CPLF is not required.

If the value in this param is Y and the ATM-DH-MDS1000-CPLF assign is not present in the LCONF, the Device Handler process abends during initialization. If the value in this param is N and the ATM-DH-MDS1000-CPLF assign is not present in the LCONF, the Diebold 10XX/478X Device Handler process supports check transactions but a CPLF is not used. If the value in this param is N and the ATM-DH-MDS1000-CPLF assign is present in the LCONF, the Diebold 10XX/478X Device Handler process writes check transactions to the CPLF.

Param Default: N

ATM-DH-N50-AKDS-SERIAL-NUM-VRFY — A code indicating whether to verify the EPP serial number against a list of approved numbers maintained in the Transaction Security Services (TSS) database. This verification occurs during the authentication and public key exchange sequence of Automated Key Distribution System processing. This param is used only with the Automated Key Distribution System add-on product.

The NCR 5XXX Device Handler process uses this param. Valid values are as follows:

Y = Yes, verify the EPP serial number against the list in the TSS database.

N = No, do not verify the EPP serial number against the list in the TSS database.

Param Default: N

ATM-DH-N50-CHK-PRNT-POS — A value that indicates the position on the reverse side of the check where the first line of information is printed when the check is retained. This param is used by the NCR 50XX/56XX SSB Device Handler Extension. Valid values are as follows:

- 0 = Print in position A.
- 1 = Print in position B.
- 2 = Print in position C.

Read By: P1A^N50SSB

Param Default: 0

ATM-DH-N50-CPLF-REQ — A value indicating whether the Check Proof List File (CPLF) is required for processing. This param is used only with the BASE24-atm self-service banking (SSB) add-on product.

The NCR 5XXX Device Handler process uses this param. If the value in this param indicates that the CPLF is required, the ATM-DH-N50-CPLF assign is also required. Valid values are as follows:

- Y = Yes, the CPLF is required.
- N = No, the CPLF is not required.

Read By: A symbolic name is required in this field if this value varies among BASE24-atm NCR 5XXX Device Handler processes.

Param Default: N

ATM-DH-N50-DPM-DFLAGS — A code indicating whether the NCR 5XXX Device Handler process checks the Document Processing Module (DPM) magnetic flux and courtesy amount verification (CAV) fields in requests. During normal processing, the NCR 5XXX Device Handler process checks both of these fields. Valid values are as follows:

- 0 = Check both the magnetic flux and CAV fields in requests. Normal processing.
- 1 = Do not check the magnetic flux field in requests.
- 2 = Do not check the CAV field in requests.
- 3 = Do not check the magnetic flux or CAV fields in requests.
- 4 = Remove null characters from DPM requests.

- 5 = Do not check the magnetic flux field and remove null characters from DPM requests.
- 6 = Do not check the CAV field and remove null characters from DPM requests.
- 7 = Do not check the magnetic flux or CAV fields and remove null characters from DPM requests.

Param Default: 0

ATM-DH-NON-VALUE-THRESHOLD — The minimum whole dollar withdrawal amount used by the following Device Handler processes to determine whether a nonvalue item is to be dispensed with the requested cash or noncurrency item:

Diebold 10XX/478X
Fujitsu 7000
NCR 5XXX

This param is only used when the DISPENSE ALGORITHM field on BASE24-pos Terminal Data files (ATD) screen 7 is set to a value other than 2 (Configurable Dispense algorithm). Valid values for this param are 5 through 2147483647.

Param Default: 5

ATM-DH-OIF1000-CHK — A value indicating whether the BASE24-atm Diebold 10XX/478X Device Handler process checks the Operator Identification File (OIF) to determine access to the ATM chest door. The BASE24-atm Diebold 10XX/478X Device Handler process uses this param for ATMs that support the host-controlled solenoid-activated lock feature. This feature is available with Diebold 2.1 firmware. Valid values are as follows:

- Y = Yes, the BASE24-atm Diebold 10XX/478X Device Handler process checks the OIF.
- N = No, the BASE24-atm Diebold 10XX/478X Device Handler process does not check the OIF.

When this param is set to the value N, the OIF is not used to control access to the ATM solenoid-locked chest door. In this case, BASE24 security is not implemented, and automatic approval is given to all chest door access requests.

Param Default: N

ATM-DH-OLI6-CMD-TIMEOUT — The number of seconds the Olivetti 6000 Device Handler process waits for a response to a command sent to a device before considering the command to have timed out. Valid values are 10–180.

Param Default: 45

ATM-DH-OLI6-KEY-CHG-TIME — The time of day the Olivetti 6000 Device Handler process performs dynamic key changes. Valid values are 00:00–23:59. If this param is not configured or is invalid, dynamic key changes do not take place.

Param Default: No default value

ATM-DH-OLI6-LOAD-MSG-LEN — The maximum length of load messages, in bytes, that the Olivetti 6000 Device Handler process can send to a terminal. Valid values are 256–3290.

Param Default: 256

ATM-DH-OLI6-LOG-CE-STATUS — A code indicating whether the Olivetti 6000 Device Handler process logs status information for A06 messages. Valid values are as follows:

- 0 = No, do not log status information for A06 messages.
- 1 = Yes, log status information for A06 messages.

If this param is not configured or is invalid, no status information is logged for A06 messages.

Param Default: 0

ATM-DH-OLI6-POLL-INTERVAL — The number of seconds the Olivetti 6000 Device Handler process waits after receiving a message from a terminal before it sends a polling message to the terminal. If the process receives another message from the terminal before the poll timer expires, the timer is reset to the value of this param.

Param Default: 300

ATM-DH-OLI6-POLL-RETRY-MAX — The maximum number of times the Olivetti 6000 Device Handler process will attempt to resend a polling message to a terminal before marking the terminal down.

Param Default: 3

ATM-DH-OLI6-RETRY-INTERVAL — The number of seconds the Olivetti 6000 Device Handler process waits after sending a polling message to a terminal before it attempts to send another polling message.

Param Default: 60

ATM-DH-OLI6-TERM-STATUS — A code indicating the type of status messages for which the Olivetti 6000 Device Handler process logs status information. Valid values are as follows:

- 0 = Do not log A05 or A0R message information.
- 1 = Log A05 message information only.
- 2 = Log A0R message information only.
- 3 = Log both A05 and A0R message information.

Param Default: 0

ATM-DH-OPT-LVL — The number of times the BASE24-atm Device Handler process writes to the BASE24-atm Terminal Data files for normal transactions. This param indicates whether the BASE24-atm Device Handler process uses one write or two writes to the BASE24-atm Terminal Data files for normal transactions. Valid values are as follows:

- 0 = Write the BASE24-atm Terminal Data files record to disk twice; once when the response is returned to the ATM and once when the completion message returns from the ATM.
- 1 = Write the BASE24-atm Terminal Data files record to disk once, when the response is returned to the ATM. The BASE24-atm Terminal Data files record will not be written to disk a second time unless the transaction is not completed as authorized.

ACI recommends setting this param to a value of 1.

The following BASE24-atm Device Handler processes use this param:

Burroughs 650/750
Diebold 10XX/478X
Diebold 910/911
Docutel 5100
Fujitsu 7000
IBM 4730
NCR 5XXX
Olivetti 6000

Read By: A symbolic name (for example, P1A^N50) is required in this field if this value varies among BASE24-atm Device Handler processes.

Param Default: 0

ATM-DH-PEAK-LEAD-TIME — The number of minutes prior to the peak transaction time that the peak transaction load group is downline loaded to a Diebold 10XX/478X, Fujitsu 7000, or NCR 5XXX terminal. The peak transaction time is defined in the INACTIVITY TIMER INFORMATION fields on the terminal-specific screen 7 of the BASE24-atm Terminal Data files (ATD). Valid values are 0 through 1440.

The following BASE24-atm Device Handler processes use this param when the BASE24-atm self-service banking (SSB) Enhanced ATM Application is installed:

Diebold 10XX/478X
Fujitsu 7000
NCR 5XXX

Param Default: 10

ATM-DH-RCPT-PHONE-NUM-FRMT — Specifies whether the phone number printed on the ATM receipt will be formatted. This param is used by the following processes:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process

Valid values are as follows:

- 0 = Do not format the phone number on the ATM receipt
- 1 = Format the phone number on the ATM receipt in the following format:
XXX-XXX-XXXX

Param Default: 0

ATM-DH-STALE-RQST-TIMEOUT — The number of seconds an incoming transaction request can remain in the BASE24-atm Device Handler process' queue before the BASE24-atm Device Handler process discards it. Valid values are 10 through 180. ACI recommends setting this param to 20. The BASE24-atm Device Handler processes use this param.

Read By: A symbolic name (for example, P1A^C1000) is required in this field if this value varies among BASE24-atm Device Handler processes.

Param Default: 45

ATM-DH-SUSPECT-RVSL-ON-IM-ALIVE — A value indicating whether the NCR 5XXX Device Handler is to generate a suspect reversal when an *I'm Alive* message is received from the ATM before the completion message from the last transaction. Setting the parameter to the value Y generates the suspect reversal. Setting the parameter to the value N does not generate the reversal. The device handler checks the last transaction status of the next transaction request to determine whether a reversal is required.

The NCR 5XXX Device Handler process uses this param. Valid values are as follows:

- Y = Yes, generate a suspect reversal.
- N = No, do not generate a suspect reversal.

Param Default: Y

ATM-DH-TERM-IN-CPLF-RETN-PRD — The maximum amount of time that a terminal and the CPLF records belonging to it are retained in the CPLF extended memory table. Valid values are as follows:

- 1-60 = Number of minutes the terminal and the CPLF records are retained

Param Default: 5

ATM-DH-TIDL-AKDS-HOST-LOAD-TIMER — The number of seconds the ATM waits for a Host RKM command message to be sent during an AKDS load before aborting the load. Valid values are as follows:

10-600 = Number of seconds the terminal waits for the Host RKM command message.

Param Default: 60

ATM-DH-TIDL-AKDS-SERIAL-NUM-VRFY — A code indicating whether to verify the EPP serial number against a list of approved numbers maintained in the Transaction Security Services (TSS) database. This verification occurs during the authentication and public key exchange sequence of Automated Key Distribution System processing. This param is used only with the Automated Key Distribution System add-on product.

The Tidel Device Handler process uses this param. Valid values are as follows:

Y = Yes, verify the EPP serial number against the list in the TSS database.

N = No, do not verify the EPP serial number against the list in the TSS database.

Param Default: N

ATM-DH-TRIT-AKDS-SERIAL-NUM-VRFY — A code indicating whether to verify the EPP serial number against a list of approved numbers maintained in the Transaction Security Services (TSS) database. This verification occurs during the authentication and public key exchange sequence of Automated Key Distribution System processing. This param is used only with the Automated Key Distribution System add-on product.

The Triton Device Handler process uses this param. Valid values are as follows:

Y = Yes, verify the EPP serial number against the list in the TSS database.

N = No, do not verify the EPP serial number against the list in the TSS database.

Param Default: N

ATM-DH-X25-MSG-SIZE — The maximum message length that can be sent over an X.25 communication network used by the NCR 5XXX and Diebold 10XX/478X Device Handler processes. The range of values is 200–500.

Param Default: 0

ATM-DH-X25-TYPE — A code indicating the type of X.25 connection used by the Olivetti 6000 Device Handler process. Valid values are as follows:

- 0 = Permanent Virtual Circuit (PVC)
- 1 = Permanent Switched Virtual Circuit (SVC)
- 2 = Switched Virtual Circuit (SVC)

Param Default: 0

ATM-DH-XCHG-RATE-NTFY — A code indicating whether to notify the consumer at an ATM of the exchange rate between the requested transaction currency and their account or terminal currency. This param is used only with the Multiple Currency Dispense add-on product. The following Device Handler processes use this param:

Diebold 10XX/478X process
NCR 5XXX process

Valid values are as follows:

- Y = Yes, the exchange rate is displayed.
- N = No, the exchange rate is not displayed.

ATM-DISCR-DATA-STM-SUPPRS — A value indicating whether discretionary data carried in the STM 0210 response should be suppressed.

For ATM authorization, it indicates whether discretionary data carried in the STM should be suppressed for transactions that are authorized by either BASE24 or a host system.

For the ATM device handlers, it indicates whether to suppress the discretionary data in the ATD and in the response STM prior to sending messages to the ATM.

For interfaces, it indicates whether or not the interface should suppress the discretionary data in the STM 0210 response messages sent to BASE24-atm.

The following processes use this param:

BASE24-atm Authorization process
BIC ISO Interface process
Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process

Valid values are as follows:

Y = Yes, suppress discretionary data in the STM.
N = No, do not suppress discretionary data in the STM

Param Default: N

ATM-DLY-RPT-STARTUP — The time of day that the Daily and Monthly Transaction Volume Report programs are run. The Transaction Based Pricing Report Initiator process uses this assign. Valid values are 00:00–23:59. This param is required.

If this param is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends during initialization.

Param Default: No default value

ATM-FCA-CUTOVER-AUDIT — A flag indicating whether the forced cutover audit function is in effect for the logical network. A value of Y indicates that when an ATM is force balanced by BASE24, the ATM prints a subtotals receipt on the audit or journal printer. A value of N indicates that no subtotals receipt is printed following force balance processing. The ATM-FCA-CUTOVER-AUDIT param is used by the following processes:

Diebold 10xx/478x Device Handler process
NCR 50XX Device Handler process
BASE24-atm Settlement Initiator process

Valid values are as follows:

Y = Yes, print the subtotals receipt on the audit or journal printer.
N = No, do not print the subtotals receipt on the audit or journal printer.

Param Default: N

ATM-FEE-INTRACTV-RESP-NTFY — A flag indicating whether surcharge interactive response notification processing (i.e., performing interactive notification sequences for acquirer or issuer fees and rebates) is being used. A value of Y indicates that this enhanced acquirer or issuer fee and rebate processing is being performed. A value of N indicates that standard product surcharging only is being performed. Valid values are as follows:

Y = Yes, use surcharge interactive response notification for surcharges.

N = No, do not use surcharge interactive response notification for surcharges.

Note: Standard product surcharging includes negative amounts for acquirer surcharges (i.e., acquirer incentives), which are available in the Surcharge Data token and displayed on BASE24-atm screens and receipts.

The following Device Handler processes use this param:

Diebold 10XX/478X
NCR 5XXX

Read By: A symbolic name is required in this field if the value varies among BASE24-atm Diebold 10XX/478X or NCR 5XXX Device Handler processes.

Param Default: N

ATM-FORWARD-INST-ID — The forwarding institution identification number. This param is used for logging purposes only. The value in this param equates to the routing and transit number representing the BASE24 system. The BASE24-atm Authorization process uses this param.

Param Default: 000000000000

ATM-GEN-AUTH-ID-RESP — A value indicating whether the BASE24-atm Authorization process generates an Authorization Response ID in the Standard Internal Message (STM) when it authorizes a transaction. The Authorization Response ID is logged to the Transaction Log File (TLF), and, therefore, can be extracted. The Authorization Response ID is generated based on the time of day, card number, and transaction amount. If the Authorization Response ID has already been provided in the STM (that is, the transaction has been authorized on a host), the BASE24-atm Authorization process does not generate a new value. Valid values are as follows:

Y = Yes, generate an Authorization Response ID in the STM.

N = No, do not generate an Authorization Response ID in the STM.

Param Default: N

ATM-I4730-RCPT-TRUNC-FRTO — A value indicating whether the IBM 473X Device Handler process performs *from* account and *to* account number truncation on all transaction receipts. If this param is set to a value of Y, the IBM 473X Device Handler process truncates all but the four least significant digits of all *from* account numbers and *to* account numbers. An asterisk character (*) is displayed for each truncated digit. For example, an account number of 1234567890123456789 is displayed as *****6789 on receipts if account numbers are truncated. Valid values are as follows:

Y = Yes, truncate all *from* account and *to* account numbers.

N = No, do not truncate any *from* account or *to* account numbers.

Param Default: N

ATM-I4730-RCPT-TRUNC-PAN — A value indicating whether the IBM 473X Device Handler process performs primary account number (PAN) truncation on all transaction receipts. If this parameter is set to the value Y, all digits except for the four least significant digits are truncated. An asterisk character (*) is displayed for each truncated digit. For example, a PAN of 1234567890123456789 would be displayed as *****6789 on receipts if PANs are truncated. Valid values are as follows:

Y = Yes, truncate all PANs.

N = No, do not truncate any PANs.

Param Default: N

ATM-ISS-DISCR-DATA-SUPPRS — A flag indicating whether logging discretionary data for issuer transactions to the Transaction Log File (TLF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. BASE24-atm Authorization uses this param. Valid values are as follows:

Y = Yes, suppress logging of discretionary data.

N = No, do not suppress logging of discretionary data.

Param Default: N

ATM-LN-CUTOVER — The time of day that the ATM logical network is cut over. All institutions in the logical network must be cut over by this time. This param can be set to any value, expressed in 24-hour time, 00:00 (12:00 a.m.) through 23:59 (11:59 p.m.). The ATM-LN-CUTOVER param is used by the following processes:

BASE24-atm Settlement Initiator process
BASE24-atm Authorization process
BASE24-atm Transaction Context Manager process
BCGI Interface process
BIC ISO Interface process
Enscribe Refresh process
EPS-Net Interchange Interface process
Generic Interchange Interface process
ISO Host Interface process
LINK ISO Interchange Interface process
MDS ISO Interchange Interface process
PLUS ISO Interchange Interface process
Super Extract process
Transaction Based Pricing Report Initiator process
VisaNet ISO Interchange Interface process

If this param is not present in the LCONF, the processes that access the LCONF for this paramabend during initialization.

Param Default: No default value

ATM-NIDFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Note ID File (NIDF) extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table. This param is used with the Shared NDC+ BNA Support enhancement within the BASE24-atm self-service banking (SSB) add-on product.

Usage Codes: ATM, BASE

Param Default: 127

ATM-NIDFEMT-WARM*Identifier* — The symbolic name of a process to receive a warmboot command when the Institution Definition File (IDF) extended memory table is warmbooted from the Device Control Terminal (DCT). The following processes or modules can be warmbooted:

BASE24-atm Diebold 10XX/478X Device Handler process
BASE24-atm NCR 5XXX Device Handler process

The Process Control Terminal Server process retrieves all IDFEMT-WARM*Identifier* params when a network control operator issues a command to reinitialize the IDF extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another IDFEMT-WARM*Identifier* param. For example, IDFEMT-WARM01 could contain the P1A^C10001 process and IDFEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 IDFEMT-WARM*Identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one IDFEMT-WARM*Identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples:	P1A^C10001 P1A^N* P1A^SPDH2 P2A^BICI
Usage Codes:	ATM, BASE, POS
Param Default:	No default value

ATM-NOTIFY-INTERVAL — The number of writes made to the Transaction Log File (TLF) before calculating the percentage of file full. Each time a write is made to the TLF, a counter is increased by one. When the counter is equal to the value specified in this param, the BASE24-atm Authorization process or BASE24-atm Settlement Initiator process calculates how full the TLF is. The counter is then reset to zero. The following processes use this param:

BASE24-atm Authorization process
BASE24-atm Settlement Initiator process
BASE24-atm Transaction Context Manager process

When the file reaches the percent full specified in the ATM-NOTIFY-PERCENTAGE param, the BASE24-atm Authorization or BASE24-atm Settlement Initiator process generates an event message indicating that the file is becoming full. The BASE24-atm Authorization or BASE24-atm Settlement Initiator process continues to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more

since the preceding calculation, the BASE24-atm Authorization or BASE24-atm Settlement Initiator process generates another event message indicating that the file is becoming full.

Valid values are 10 through 32766. The BASE24-atm Authorization and BASE24-atm Settlement Initiator processes use this param.

Param Default: 50

ATM-NOTIFY-PERCENTAGE — The percentage of file full at which the BASE24-atm Authorization or BASE24-atm Settlement Initiator process generates an event message indicating that the Transaction Log File (TLF) is becoming full. The BASE24-atm Authorization or BASE24-atm Settlement Initiator process calculates the percentage of file full and continues to calculate the percentage at the interval indicated in the ATM-NOTIFY-INTERVAL param as described in the following paragraphs. If the percentage has increased by one percent or more since the preceding calculation, the BASE24-atm or BASE24-atm Settlement Initiator process generates another event message indicating that the file is becoming full. The following processes use this param:

BASE24-atm Authorization process
BASE24-atm Settlement Initiator process
BASE24-atm Transaction Context Manager process

If the calculation results in the percentage specified in the ATM-NOTIFY-PERCENTAGE param or more, the BASE24-atm Authorization or BASE24-atm Settlement Initiator process generates an event message indicating the condition. Thereafter, the process continues to calculate the percentage of file full at the interval indicated by the ATM-NOTIFY-INTERVAL param. When the calculated percentage of file full is less than the value of the ATM-NOTIFY-PERCENTAGE param, the process stops generating events.

Valid values are 10 through 99. The BASE24-atm Authorization and BASE24-atm Settlement Initiator processes use this param.

Param Default: 70

ATM-REAR-ADMN-TRAN-PIN-ALWD — A value determining if rear administrative transaction requests that are sent to the Authorization process by the NCR 5XXX and Diebold 10XX/478X device handlers are allowed to contain PINs. This param is read by the BASE24-atm Authorization process. Valid values are as follows:

Y = Yes, rear administrative transactions are allowed to contain PINs.

N = No, rear administrative transactions are not allowed to contain PINs.

Param Default: Y

ATM-RESP-LMTS-CHK — A value determining whether daily limits are rechecked on a response when the Authorization level is online/offline and the Authorization Method is CAF or CAF/PBF. Valid values are as follows:

Y = Yes, check the limits on the response.

N = No, do not check the limits on the response.

Param Default: N

ATM-RPT-CPU — The number of the processor (CPU) in which the BASE24-atm report programs execute. The value of this param is placed in the startup command of each BASE24-atm report program started using the obey file created by the BASE24-atm Settlement Initiator process or Transaction Based Pricing Report Initiator process. Valid values are 0 through 15. The following processes use this param:

BASE24-atm Settlement Initiator

Transaction Based Pricing Report Initiator process

Param Default: If this param is not present in the LCONF, or contains an invalid value, report programs execute in the same CPU as that in which the BASE24-atm Settlement Initiator or Transaction Based Pricing Report Initiator process is running.

ATM-RPT-PRI — The priority at which the BASE24-atm report programs are executed. The value of this param is placed in the startup command of each BASE24-atm report program started using the obey file created by the BASE24-atm Settlement Initiator process or Transaction Based Pricing Report Initiator process. Valid values are 1 through 199. The following processes use this param:

BASE24-atm Settlement Initiator
Transaction Based Pricing Report Initiator process

If this param is not present in the LCONF, or contains an invalid value, the report programs attempt to execute at the same priority as the BASE24-atm Settlement Initiator or Transaction Based Pricing Report Initiator process. If this causes an error, the BASE24-atm Settlement Initiator and Transaction Based Pricing Report Initiator process attempt to run the report programs at an execution priority of 100.

Param Default: 100

ATM-SETL-ATD-LOCKED-RECS-SKIP — Identifies whether the BASE24-atm Settlement Initiator process should skip locked ATD or TDF records during cutover processing. If the record is locked, the Settlement Initiator process delays and retries reading the record until the record is unlocked and the Settlement Initiator process can access it. This param is optional.

- Y = Yes, the Settlement Initiator process skips locked ATD/TDF records and generates an event message.
N = No, the Settlement Initiator process does not skip locked ATD/TDF records during cutover processing.

Param Default: N

ATM-SETL-EXPT-RPT-FLG — A code indicating whether the BASE24-atm Settlement Initiator process must generate the exception reports for the BASE24-atm Daily Terminal Report (STAT06) and the BASE24-atm Daily Institution Report (STAT07). These reports are generated with the same report programs as those that generate the STAT06 and STAT07 reports. The BASE24-atm Settlement Initiator process uses this param. Valid values are as follows:

- Y = Yes, generate the STAT06 and STAT07 exception reports.
N = No, do not generate the STAT06 and STAT07 exception reports.

Param Default: Y

ATM-SETL-HDWRSTAT-NOTIFY*identifier* — The name of a service or the symbolic name of the IBM 3624 Device Handler process to which the BASE24-atm Settlement Initiator process sends a cutover (9502) message at logical network cutover. If broadcast messages are not used, a maximum of three processes can be notified. Upon receiving a 9502 message, the Device Handler

processes in the ATM-SETL-HDWRSTAT-NOTIFY list begin logging to the new day's Hardware Status File (HSF). The IBM 3624 Device Handler (Version 8) processes use the HSF to track the hardware status of the 3624 terminals when the Hardware Status Error Logging (ELARG) module is in use. The Hardware Status Error Logging module is an add-on module and must be purchased separately. Hardware faults are logged to the HSF.

Each ATM-SETL-HDWRSTAT-NOTIFY param contains the name of one process or service. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another ATM-SETL-HDWRSTAT-NOTIFY*identifier* param. For example, ATM-SETL-HDWRSTAT-NOTIFY1 could contain the P1A^I36241 process and ATM-SETL-HDWRSTAT-NOTIFY2 could contain the P1A^I36242 process.

The BASE24-atm Settlement Initiator process uses this param.

If this param is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process assumes that no processes are to be notified after cutover.

If the ATM-SETL-HDWRSTAT-NOTIFY*identifier* param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Settlement Initiator process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Param Default: No default value

ATM-SETL-LN-CUTOVER-LEAD-TIME — The minimum number of minutes before logical network cutover that all financial institutions should be cut over. This param can be any numeric value greater than 29. The BASE24-atm Settlement Initiator process uses this assign.

Param Default: 30

ATM-SETL-MASTER — The symbolic name of the main BASE24-atm Settlement Initiator process responsible for BASE24-atm settlement functions (for example, P1A^SETL).

If this param does not contain the name of the BASE24-atm Settlement Initiator process that reads the param, the process abends during initialization.

Param Default: No default value

ATM-SETL-MIDNIGHT-NOTIFY*identifier* — The name of a service or the symbolic name of a BASE24-atm Authorization process or a BASE24-pos Device Handler/Router/Authorization process to be notified after midnight. This param indicates a service or process that must be notified that totals have been cleared and a new customer processing date has started on a midnight-to-midnight basis. If broadcast messages are not used, a maximum of 500 processes can be notified.

Each ATM-SETL-MIDNIGHT-NOTIFY param contains the name of one service or process. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another ATM-SETL-MIDNIGHT-NOTIFY*identifier* param. For example, ATM-SETL-MIDNIGHT-NOTIFY1 could contain the P1A^AUTH1 process and ATM-SETL-MIDNIGHT-NOTIFY2 could contain the P1A^AUTH2 process.

Note: For BASE24 networks using both the BASE24-atm and BASE24-pos products and the Usage Accumulation File (UAF), this param should include all BASE24-atm Authorization processes and all BASE24-pos Device Handler/Router/Authorization processes. This ensures correct purge processing of the UAF during midnight cutover. The UAF is used by the BASE24-atm and BASE24-pos products with the Negative Authorization with Usage Accumulation method. The first settlement process to cut over after midnight performs the UAF purge processing. This process then notifies all processes that use the UAF.

The BASE24-atm Settlement Initiator process uses this param.

If this param is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process assumes that no processes are to be notified after midnight.

If the ATM-SETL-MIDNIGHT-NOTIFY*identifier* param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Settlement Initiator process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Example: P1A^AUTH1
Param Default: No default value

ATM-SETL-NOTIFY*identifier* — The name of a service or the symbolic name of a process to be notified after logical network cutover is performed. The processes to be notified are BASE24-atm Authorization processes, Host Interface processes, Interchange Interface processes, and the BASE24-atm Transaction Context Manager process. If broadcast messages are not used, a maximum of 500 processes can be notified.

Each ATM-SETL-NOTIFY param contains the name of one service or process. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another ATM-SETL-NOTIFY*identifier* param. For example, ATM-SETL-NOTIFY1 could contain the P1A^AUTH1 process and ATM-SETL-NOTIFY2 could contain the P1A^AUTH2 process.

The BASE24-atm Settlement Initiator process uses this param.

If this param is not present in the LCONF or contains an invalid value, the BASE24-atm Settlement Initiator process assumes that no processes are to be notified after settlement.

If the ATM-SETL-NOTIFY*identifier* param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Settlement Initiator process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Example: P1A^AUTH1
Param Default: No default value

ATM-SETL-RPT-FILE-RETENTION — The number of days worth of BASE24-atm report files, prior to the current business day, that are to remain on the system. After the specified time, the BASE24-atm Settlement Initiator process deletes the files from the system. For example, if the value in this param is 3 and the current business date is 02/06/05 (for June 5, 2002), the report files dated 02/

06/04, 02/06/03, and 02/06/02 are retained on the system and closed. Report files dated 02/06/01 and earlier are deleted from the system. Report files for the current business day have not yet been created.

Valid values are 3 to 99. The BASE24-atm Settlement Initiator process uses this param.

Param Default: 7

ATM-SETL-RPT0-STARTUP

ATM-SETL-RPT1-STARTUP — The BASE24-atm Settlement Initiator process uses the ATM-SETL-RPT0-STARTUP and ATM-SETL-RPT1-STARTUP params to determine when to start the first and second set of BASE24-atm report programs, respectively. For example, the ATM-SETL-RPT0-STARTUP param can be used for an initial set of reports required for balancing, and the ATM-SETL-RPT1-STARTUP param can be used for a second set of reports that are started at a later time when system processing is less active. If the BASE24-atm Settlement Initiator process starts only one set of reports, only the ATM-SETL-RPT0-STARTUP param is used. These params can be set to any value, expressed in 24-hour time, 00:00 (12:00 a.m.) through 23:59 (11:59 p.m.). The BASE24-atm Settlement Initiator process uses these params.

Note: When any non-numeric value is entered in these params, reports are not generated (ACI suggests a value of NA). This value causes a message to be logged at startup or warmboot indicating that the BASE24-atm reports will not be produced.

If a time is specified for ATM-SETL-RPT0-STARTUP but the ATM-SETL-RPT1-STARTUP param is left out or given the value NA, only one set of reports is produced. If the ATM-SETL-RPT1-STARTUP contains an invalid time, it defaults to the time given for the ATM-SETL-RPT0-STARTUP param. If the ATM-SETL-RPT0-STARTUP param is not present in the LCONF or contains an invalid value and reports are to be produced, the BASE24-atm Settlement Initiator process abends at initialization.

Param Default: No default value

ATM-SETL-TLF-EXTENTS-TO-ALLOCATE — The number of extents to allocate for the Transaction Log File (TLF). The BASE24-atm Settlement Initiator process uses this param when it creates the TLF. Valid values are 1 through 16. ACI recommends setting this param to 1.

Param Default: 16

ATM-SETL-TLF-FILE-RETENTION — The number of days worth of Transaction Log Files (TLFs) and report obey files, prior to the current business day, that are to remain on the system. After the indicated number of days, the BASE24-atm Settlement Initiator process deletes the file from the system. For example, if the value in this param is 3 and the current business date is 02/06/05 (for June 5, 2002), TLFs dated 02/06/06 and 02/06/05 are retained on the system and open. TLFs dated 02/06/04, 02/06/03, and 02/06/02 are retained on the system and closed. TLFs dated 02/06/01 and earlier are deleted from the system. Valid values are 3 through 99.

Param Default: 7

ATM-TRFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Terminal Receipt File (TRF) extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table.

Param Default: 127

ATM-TRFEMT-WARM*Identifier* — The symbolic name of a process to receive a warmboot command when the Terminal Receipt File (TRF) extended memory table is warmbooted from the Device Control Terminal (DCT). The following Device Handler processes can be warmbooted:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process

This param indicates a process that receives a warmboot command from the Device Control Terminal (DCT). The Process Control Terminal Server process retrieves all ATM-TRFEMT-WARM*Identifier* params when a network control operator issues a command to reinitialize the TRF extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another ATM-TRFEMT-WARM*Identifier* param. For example, ATM-TRFEMT-WARM01 could contain the P1A^C10001 process and ATM-TRFEMT-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 ATM-TRFEMT-WARM*Identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one ATM-TRFEMT-WARM*Identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples: P1A^C10001
 P1A^N*
 P1A^SPDH2
 P2A^BICI
Usage Codes: ATM, BASE, POS
Param Default: No default value

ATM-USE-ACCT-QUAL — A code indicating whether account qualifier matching is performed. The account qualifier token contains the account qualifier. The Authorization process compares this value from the token to the value in the QUAL field in the Cardholder Authorization File (CAF) to determine the correct account to use to process the transaction.

The QUAL field in the CAF is used to differentiate among multiple cardholder accounts with the same account type value. The QUAL field is optional, and if it is empty, the Authorization process uses the account type value to determine the correct account.

- 0 = Do not perform account qualifier matching; use the account type value for matching accounts.
- 1 = Perform account qualifier matching.

Param Default: 0

ATM-WARM*Identifier* — The symbolic name of a process to be warmbooted. Processes that can be warmbooted include BASE24-atm Authorization processes and Interchange Interface processes. This param indicates a process that receives a warmboot command from the Device Control Terminal (DCT). The Process Control Terminal Server process retrieves all ATM-WARM*Identifier* params when a network control operator issues a command to reinitialize all BASE24-atm processes. A maximum of 150 processes can be warmbooted from the DCT.

Each ATM-WARM param contains the name of one process. When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not

already been declared by another ATM-WARM*identifier* param. For example, ATM-WARM1 could contain the P1A^AUTH1 process and ATM-WARM2 could contain the P1A^AUTH2 process.

The name of the BASE24-atm Settlement Initiator process should not be included in this list.

Examples: P1A^AUTH02
 P1A^BASE01
 Param Default: No default value

CARRIER-AMTS-VT*identifier* — This param is used for definitions-based mobile top-up. It identifies the amounts supported for this mobile operator. The *identifier* is a two-digit numeric value representing the voucher type. The *identifier* is also used to associate the Operator IIN, name, mobile phone operator ID, and valid amounts for each carrier. Valid values are 00 through 08 for the Triton Device Handler process and 00 through 29 for all other Device Handler processes.

Each amount in the value must be six digits separated by semicolons. The Triton Device Handler process allows six amounts; all other Device Handler processes allow eight amounts. The example shown below represents \$30, \$50, and \$75 as valid amounts for this carrier. The following processes use this param:

Diebold 10XX/478X Device Handler process
 NCR 5XXX Device Handler process
 Triton Device Handler process

Examples: CARRIER-AMTS-VT00
 000030;000050;000075;000000;000000;000000;000000;000000
 Param Default: None

CARRIER-VT*identifier* — This param is used for definitions-based mobile top-up. It identifies the four-digit mobile phone operator ID. The value of this param matches a mobile operator with an entry in the Mobile Operator File (MOF) and enables the mobile operator to be identified for the transaction. The *identifier* is a two-digit numeric value representing the voucher type. The *identifier* is also used to associate the Operator IIN, name, mobile phone operator ID, and valid amounts for each carrier. Valid values are 00 through 08 for the Triton Device Handler process and 00 through 29 for all other Device Handler processes. The following processes use this param:

Diebold 10XX/478X Device Handler process
 NCR 5XXX Device Handler process
 Triton Device Handler process

Examples: CARRIER-VT00
 Param Default: None

MOBILE-NUM-MAX-LGTH — The maximum length allowed for the mobile phone number entered by the cardholder. Valid values are 0 through 15. The following processes use this param:

Diebold 10XX/478X Device Handler process
 NCR 5XXX Device Handler process
 Triton Device Handler process

Param Default: 11

MOBILE-NUM-MIN-LGTH — The minimum length allowed for the mobile phone number entered by the cardholder. Valid values are 0 through 15. The following processes use this param:

Diebold 10XX/478X Device Handler process
 NCR 5XXX Device Handler process
 Triton Device Handler process

Param Default: 10

MOBILE-OPERATOR-ID-VT*identifier* — This param is used for definitions-based mobile top-up. It specifies the mobile phone operator IIN (7 digits) plus the mobile operator name (20 characters) associated with the mobile phone operator. The *identifier* is a two-digit numeric value representing the voucher type. The *identifier* is also used to associate the Operator IIN, name, mobile phone operator ID, and valid amounts for each carrier.

Values must be formatted with a seven-digit operator IIN immediately followed by a mobile operator name. Valid values are 00 through 08 for the Triton Device Handler process and 00 through 29 for all other Device Handler processes. The following processes use this param:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process
Triton Device Handler process

Examples: MOBILE-OPERATOR-ID-VT00
 1200991CARRIERNAME

Param Default: None

MOBILE-PARAM-VERSION-NUM — A value used by the Triton Device Handler process to determine whether the mobile top-up information stored at the device must be replaced during a download request/response. This param value must be manually incremented when one of the following parameters are changed, otherwise the device handler will not send the updated information to the device:

CARRIER-VTidentifier
CARRIER-AMTS-VTidentifier
MOBILE-OPERATOR-ID-VTidentifier

This param is required by the BASE24-atm Triton Mobile Top-Up add on product. Valid values are 0001-9999.

Read by: A symbolic name (for example, P1A^TRITON) is required in this field.

Param Default: None

N50-NCD-CRD-EJECT-OPTION — A value indicating whether the NCR 50XX/56XX Device Handler process is to eject the card before, after, or at the same time it dispenses a noncurrency item.

A = Dispense an item before ejecting the card.

C = Eject the card before dispensing an item.

D = Dispense an item and eject the card at the same time.

Param Default: A

RCPT-EXT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Receipt File (RCPT) extended memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table.

Param Default: 127

RCPT-TEMP-WARM*Identifier* — The symbolic name of a process to receive a warmboot command when the Receipt File (RCPT) extended memory table is warmbooted from the Device Control Terminal (DCT). The following Device Handler processes can be warmbooted:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process

This param indicates a process that receives a warmboot command from the Device Control Terminal (DCT). The Process Control Terminal Server process retrieves all RCPT-TEMP-WARM*Identifier* params when a network control operator issues a command to reinitialize the RCPT extended memory table. The process sends a warmboot command to each identified process.

When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number, but can be any unique set of characters that has not already been declared by another RCPT-TEMP-WARM*Identifier* param. For example, RCPT-TEMP-WARM01 could contain the P1A^C10001 process and RCPT-TEMP-WARM02 could contain the P1A^SPDH02 process.

A maximum of 150 RCPT-TEMP-WARM*Identifier* params can be used to identify the processes to be warmbooted from the DCT. However, each param can include any combination of wildcard characters (i.e., asterisks) and alphanumeric characters, enabling one RCPT-TEMP-WARM*Identifier* param to identify several processes. For example, P1A^N* identifies all processes that start with P1A^N.

Examples:	P1A^C10001 P1A^N* P1A^SPDH2 P2A^BICI
Usage Codes:	ATM, BASE, POS
Param Default:	No default value

SPLIT-TXN-RTG-DEST — The symbolic name of the destination of the BASE24-atm Transaction Context Manager process. The BASE24-atm Transaction Context Manager process is required for split transaction routing of mobile top-up transactions. This param is required with the Mobile Top-Up add-on product and is used by the following processes:

Diebold 10XX/478X Device Handler process
NCR 5XXX Device Handler process
Triton Device Handler process.

Read By: A symbolic name is required in this field if the param value
varies among Device Handler processes.
Param Default: No default value

ACI Worldwide, Inc.

9: BASE24-billpay Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-billpay product.

BASE24-billpay assigns and params use the READ BY field on the LNCF Assign and LNCF Param screens differently than other BASE24 products. This use is described on the next page.

Time intervals defined in BASE24-billpay params can be expressed in various units. Specific identifiers are used in the param value to indicate the units in which a time interval is expressed. These identifiers are described following the process name usage discussion.

For descriptions of assigns and params used by the BASE24-billpay Billing Application, refer to the ***BASE24-billpay Billing Application Manual***.

Assign and param descriptions are provided following the above discussions. The assigns and params are listed in alphabetical order.

Process Name

For the BASE24-billpay product, the READ BY field on the LNCF Assign and LNCF Param screens can be used to associate an assign or param to one or more processes, one or more program names, or one or more server classes. The entity (that is, process, program, or server class) to which an assign or param applies, is specific to each assign and param. This entity is presented in the Process Name item of each assign and param description.

Server classes can be configured depending on whether the server process runs under XPNET or Pathway. If an assign or param is used by more than one type of BASE24-billpay process, program, or server class, the generic value BILLPAY should be used in this field.

If an assign or param is used by all copies of one type of BASE24-billpay program or server class, the generic program name or server class name should be used.

If an assign or param is used by an individual copy of a BASE24-billpay process or server class, the specific process name, symbolic process name, or server process name should be used.

Generic Program and Server Class Names

The following table shows all of the possible values for the READ BY field when an assign or param pertains to a generic program or server class, rather than a specific program, server process, or process.

When an assign or param pertains to a particular program or server process, the specific program or server process name is used. When an assign or param pertains to a particular process, the symbolic name of the process is used. When an assign or param pertains to more than one process, a value of all asterisks (*****) is used. The first column of the table shows the value placed in the Process Name field for program and server class use. The second column describes this value.

Process Name	Description
ACHCLEAR	This assign or param is used by all Achclear processes.
ARCHIVE	This assign or param is used by all Archive processes.

Process Name	Description
BANKADVICE	This assign or param is used by all Bank Advice processes.
BILLPAY	This assign or param is used by more than one program, process, or server class.
CLEANUP	This assign or param is used by all Cleanup processes.
REMITGEN	This assign or param is used by all Remittance Generator processes.
STI	This assign or param is used by all Scheduled Transaction Initiator processes.

Specific Program or Server Process Names

The following table shows examples of the possible values for the READ BY field when an assign or param pertains to a specific program or server process, rather than a generic program or server class. The exact names used depend on the naming conventions used when the system was installed and configured.

The first column of the table shows the value placed in the Process Name field for program and server process use. The second column describes this value.

Process Name	Description
ACHCLEAR n	This assign or param is used by the Achclear program that processes a specific partition of the History Table (HIST), where n specifies the number of the partition.
ACHCLVEND	This assign or param is used by the Achclear program that processes the Vendor Table (VNDR).

Process Name	Description
ARCHIVE n ARCHIVE grp	This assign or param is used by the Archive program that processes a specific partition of the History Table (HIST), where n specifies the number of the partition and grp represents an archive cleanup group from the Cleanup Configuration Table (CLPT). The first process name example applies if archiving is to be done at the system-level, while the second example applies if archiving is done at the financial institution identifier (FIID)-level.
BANKADVICE n	This assign or param is used by the Bank Advice process that processes a specific partition of the History Table (HIST), where n specifies the number of the partition.
CLEANUPDAYCNTX	Cleanup program name for daily cleanup of the Context Table.
CLEANUPDAYLOAN n	Cleanup program name for daily cleanup of the Loan Table (LOAN), where n is used to differentiate between multiple processes. Each program performs cleanup for a particular set of FIIDs.
CLEANUPDAYMISC n	Cleanup program name for daily cleanup of the Miscellaneous Request Table (MISC), where n is used to differentiate between multiple processes. Each program performs cleanup for a particular set of FIIDs.
CLEANUPDAYPST	Cleanup program name for daily cleanup of the Payment Summary Table.
CLEANUPDAYRPTA	Cleanup program name for daily cleanup of the Report Action Table (RPTA).
CLEANUPYRBKNT	Cleanup program name for yearly cleanup of the Bank Notice Table (BKNT).

Process Name	Description
CLEANUPYRCV	Cleanup program name for yearly cleanup of the Customer Vendor Table (CVND).
CLEANUPYRVND	Cleanup program name for yearly cleanup of the Vendor Table (VNDR).

Time Intervals

All BASE24-billpay params that specify a time interval as a value, can be entered in hours, minutes, seconds, milliseconds, or microseconds. The following table shows the identifiers that are accepted as part of the time interval value for a param. Time interval param values are always entered in the form of a number followed by one of these identifiers specifying the time interval unit to be used (for example, 30 M, 30 MIN, or 30 MINS). If a time interval unit identifier is not provided in the param value, the value is considered to be in seconds. The first column of the table shows the possible time interval units. The second column of the table shows the valid identifiers for each unit that can be included in the param value. A millisecond represents one-thousandth of a second and a microsecond represents one-millionth of a second.

Time Interval Unit	Valid Identifiers
Hours	H, HR, HRS, HOUR, HOURS
Minutes	M, MIN, MINS, MINUTE, MINUTES
Seconds	S, SEC, SECS, SECOND, SECONDS
Milliseconds	MS, MILLISEC, MILLISECS, MILLISECOND, MILLISECONDS
Microseconds	MICRO, MICROSEC, MICROSECS, MICROSECOND, MICROSECONDS

If a param defines a time interval, the param description indicates that the param is expressed in time interval format.

Assigns

The following assigns are used exclusively by the BASE24-billpay product. Each of the following assigns should have the usage code BPAY (and only the code BPAY) entered in the USAGE CODES field on the LNCF Assign screen.

BP-ARCHIVE — The fully qualified location of archive files created by the Archive program. The Archive program uses this assign.

This assign is also used to specify the fully qualified location of the template file for creating archive files. This template file defines the characteristics for the archive files created by the Archive program and must reside on the same system and volume as the created archive files. Archive files are created on the same system and volume as this template file.

All archive files are named in the format of ARyymmdd, where yymmdd represents the current system date. The name of the subvolume where the archive files are created is based on the value of the BP-ARCHIVE-GROUP param.

Examples:	\B24.\$DATA.PRO1ARCH.ARYYMMDD (archive file name) \B24.\$DATA.PRO1TPLT.ARCHTPLT (template file name)
Read By:	BILLPAY
Template File:	Required because archive files are created periodically by BASE24.

BP-REMIT — The fully qualified location of remittance files created by the Remittance Generator process. The Remittance Generator process uses this assign.

This assign is also used to specify the fully qualified location of the template file for creating remittance files. This template file defines the characteristics for the remittance files created by the Remittance Generator process and must reside on the same system and volume as the created remittance files. Remittance files are created on the same system and volume as this template file.

All remittance files are named in the format of *xyymmdd*, where *x* is the first character of the type of remittance placed in the file (that is, A for automated clearing house remittance or C for single- or group-item check remittance) and *yymmdd* represents the current system date.

Read By: BILLPAY

Examples: \B24.\$DATA.PRO1RMIT.XYYMMDD (remittance file name)
\B24.\$DATA.PRO1TPLT.RMTTPLT (template file name)

Template File: Required because remittance files are created periodically by BASE24.

Params

The following params are used exclusively by the BASE24-billpay product. Each of the following params should have the usage code BPAY (and only the code BPAY) entered in the USAGE CODES field on the LNCF Param screen.

BP-ACH-PAID-DAYS — The number of days to wait after the automated clearing house (ACH) payment has been successfully authorized and logged to the History Table (HIST), before the payment is flagged as PAID in the HIST. This param is used by the Achclear process. Valid values are 1 through 32767.

If this param is not present in the LCONF or contains an invalid value, the Achclear process abends during initialization.

Read By: BILLPAY
Param Default: No default value

BP-ACH-PRENOTE-DAYS — The number of days to wait after the automated clearing house (ACH) prenotification has been sent for a vendor, before prenotification is considered to be complete. The verification status of the vendor is changed from a value of P to a value of V in the Vendor Table (VNDR) after the number of days specified by this param have elapsed. This param is used by the Achclear process. Valid values are 1 through 32767.

If this param is not present in the LCONF or contains an invalid value, the Achclear process abends during initialization.

Read By: BILLPAY
Param Default: No default value

BP-ACH-PROCESS-VEND — A flag indicating whether this particular Achclear process manages the Vendor Table (VNDR) or a partition of the History Table (HIST). Valid values are as follows:

Y = Yes, this Achclear process manages the Vendor Table (VNDR).
N = No, this Achclear process does not manage the Vendor Table (VNDR); it manages a partition of the History Table (HIST) specified in the BP-HISTORY-PARTITION-NUM param.

If this param is not present in the LCONF or contains an invalid value, the Achclear process abends during initialization.

Read By: ACHCLEAR n , where n specifies a particular partition of the
 History Table (HIST)
 ACHCLVEND (Achclear process for the Vendor Table)
Param Default: No default value

BP-ACQ-CNTRY-CODE — A code that identifies the country used for the acquirer institution's country code in various BASE24-telebanking Standard Internal Message (BSTM) messages sent from BASE24-billpay processes to BASE24-telebanking processes. Valid country code values are defined in the ISO 3166 standard, *Codes for the Representation of Names of Countries*. The following processes use this param:

Bank Advice process
Billpay Server process
Scheduled Transaction Initiator process

If this param is not present in the LCONF or contains an invalid value, the Billpay Server, Scheduled Transaction Initiator, and Bank Advice processes abend during initialization.

Example: 840 (United States)
Read By: BILLPAY
Param Default: No default value

BP-ACQ-FIID — The FIID used for the acquirer FIID in various BASE24-telebanking Standard Internal Message (BSTM) messages sent from BASE24-billpay processes to BASE24-telebanking processes. It is also used to access the Bank Table. If an institution ID is not provided on the bank list inquiry transaction, the Default Acquirer FIID in this param is used. The following processes use this param:

Bank Advice process
Billpay Server process
Scheduled Transaction Initiator process

If this param is not present in the LCONF or contains an invalid value, the Billpay Server, Scheduled Transaction Initiator, and Bank Advice processesabend during initialization.

Example: BK40
Read By: BILLPAY
Param Default: No default value

BP-ARCHIVE-BY-FIID — A flag indicating whether the Archive process archives rows from the History Table (HIST) by FIID using parameters from the Cleanup Configuration Table (CLPT) or whether the Archive process archives rows from the HIST regardless of the FIID. Valid values are as follows:

Y = Yes, the Archive process archives rows from the HIST by FIID using parameters from the CLPT.
N = No, the Archive process does not archive rows from the HIST by FIID. The Archive process archives rows from the HIST without regard to the FIID.

If this param is not present in the LCONF or contains an invalid value, the Archive process abends during initialization.

Read By: ARCHIVE
Param Default: No default value

BP-ARCHIVE-BY-SYSTEM-DAYS — If the BP-ARCHIVE-BY-FIID param is set to the value N, this param specifies the number of days rows are maintained in the HIST before they are archived and deleted. If the BP-ARCHIVE-BY-FIID param is set to the value Y, this param is not required because parameters in the CLPT are used instead. This param is used by the Archive process. Valid values are 0 through 32767.

If this param is not present in the LCONF or contains an invalid value and the BP-ARCHIVE-BY-FIID param is set to the value N, the Archive process abends during initialization.

Read By: ARCHIVE
Param Default: No default value

BP-ARCHIVE-GROUP — If the BP-ARCHIVE-BY-FIID param is set to the value Y, this param specifies the archive group this Archive process will use in processing. An archive group specifies a group of rows in the CLPT. The CLPT rows indicate which FIIDs are to be archived by this process. Rows are retained in the HIST for the same number of days for all FIIDs specified in an archive group.

If this param is not present in the LCONF or contains an invalid value and the BP-ARCHIVE-BY-FIID param is set to the value Y, the Archive process abends during initialization.

For more information on archive groups and their use in the CLPT, refer to the *BASE24-billpay Tables Maintenance Manual* and the *BASE24 Remote Banking End-of-Period Processing and Reporting Manual*.

Read By: Symbolic process name
Param Default: No default value

BP-AUTHORIZER — The symbolic name of the BASE24-telebanking Integrated Authorization Server process or the name of a service to which financial authorization requests for available funds are sent from the Scheduled Transaction Initiator process. This param is used by the Scheduled Transaction Initiator process.

If this param is not present in the LCONF or contains an invalid value, the Scheduled Transaction Initiator process abends during initialization.

Example: P1A^IAS01
Read By: BILLPAY
Param Default: No default value

BP-BANK-NOTICE-EXCEPTION — An action code for which a bank notice is never required. When a transaction response indicates the action code specified by this param, the logic used to look up an action code in the Bank Notice Table (BKNT) is to be skipped. Since a notice is never required when a transaction is approved, this param should always be set to the value 000. The following processes use this param:

Billpay Server process
Scheduled Transaction Initiator process

Valid values are 000 through 999.

Read By: BILLPAY

Param Default: 000

BP-CLEANUP-GROUP — The cleanup group to be used by this Cleanup program. This group specifies the type of cleanup processing the Cleanup program is to perform and the rows that apply from the Cleanup Configuration Table (CLPT). CLPT rows identify the tables and financial institution identifiers (FIIDs) included in a particular cleanup group.

At a minimum, at least two cleanup groups must be established with one for daily cleanup and the other for yearly cleanup. Daily and yearly cleanup can be further broken down into more groups as required. For example, a cleanup group could be established for each of the following: daily cleanup of system-wide tables, daily cleanup of FIID-specific tables, annual cleanup of system-wide tables, and annual cleanup of FIID-specific tables. Alternatively, groups could be established to clean individual tables. The exact number of cleanup groups and distribution of cleanup responsibilities among Cleanup processes is determined by the performance and operations requirements of your organization. Multiple Cleanup processes can be run simultaneously, if required, with each process cleaning a different table or the same table but for different FIIDs. Each BP-CLEANUP-GROUP param is associated with a different Cleanup program.

For more information on cleanup groups and their use in the Cleanup Configuration Table (CLPT), refer to the ***BASE24-billpay Tables Maintenance Manual*** and ***BASE24 Remote Banking End-of-Period Processing and Reporting Manual***.

If this param is not present in the LCONF or contains an invalid value, the Cleanup program abends during initialization.

Examples: DAILYCONTEXT
DAILYLOAN1
DAILYMISCREQ1
DAILYPMTSUM
DAILYREPORTACTION
YEARLYBANKNOTICE
YEARLYCUSTVEND

YEARLYVEND

Read By: Cleanup program name (See the examples provided at the beginning of this section.)
Param Default: No default value

BP-CLEANUP-YEAR — The four-digit year for which the Cleanup processes that perform yearly cleanup are to delete data. This param is used by the yearly Cleanup processes.

If this param is not present in the LCONF or contains an invalid value, the yearly Cleanup processes abend during initialization.

Example: 2000
Read By: CLEANUP
Param Default: No default value

BP-EOF-WAITTIME — After processing all of the transactions for the current business day and reaching the end-of-file on the Future Table (FUTR), the Scheduled Transaction Initiator process immediately checks the table again for any more transactions for the current business day. If the process doesn't find any transactions at this time, it waits the length of time specified in this param before checking the FUTR again for any additional transactions that have been scheduled for the current business day. If the Scheduled Transaction Initiator process finds transactions to process between two end-of-file conditions, the interval specified by this param is not invoked.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the "Time Interval" discussion provided earlier in this section. Valid values are 1 second through 1 hour.

Examples: 2 MIN
 120 S
Read By: STI
Param Default: 60 (seconds)

BP-FUTURE-PARTITION-NUM — The partition of the Future Table (FUTR) processed by a specific Scheduled Transaction Initiator process. A Scheduled Transaction Initiator process selects FUTR rows from its assigned partition only. The Scheduled Transaction Initiator process uses this param. Valid values are 00 through 99.

The value of this param must be less than or equal to the value of the BP-NUM-FUTURE-PART-EXT param. The BP-NUM-FUTURE-PART-EXT param defines the maximum number of partitions that can be extracted from the FUTR.

If the BP-FUTURE-PARTITION-NUM param is not present in the LCONF or contains an invalid value, the specified Scheduled Transaction Initiator process abends during initialization.

Read By: Symbolic name of the Scheduled Transaction Initiator process (for example, P1A^STI01)

Param Default: No default value

BP-HISTORY-PARTITION-NUM — The partition of the History Table (HIST) processed by a specific Achclear, Archive, Bank Advice, or Remittance Generator process. These processes only select HIST rows from their assigned partition. The following processes use this param:

Achclear
Archive
Bank Advice
Billpay Server
Remittance Generator

Valid values are 00 through 99.

The value of this param must be less than or equal to the value of the BP-NUM-HISTORY-PART-EXT param. The BP-NUM-HISTORY-PART-EXT param defines the maximum number of partitions that can be extracted from the HIST.

If the BP-HISTORY-PARTITION-NUM param is not present in the LCONF or contains an invalid value, the specified process abends during initialization.

Read By: Program or symbolic process name (for example, P1A^BA01, ARCHIVE1, BANKADVICE1, P1A^REDORG01^CGP, P1A^RG01^CGP)

Param Default: No default value

BP-INITIAL-RETRY-LOG-INTERVAL — This param is used in conjunction with the BP-MAX-RETRY-LOG-INTERVAL param to control the frequency of retry reminder event messages when a transient system error that can be retried is encountered for a transaction. Initially, the time interval specified in this param is used between the generation of retry reminder event messages. Each time a retry

event message is generated, the current interval is doubled. Eventually, retry reminder event messages are generated according to the frequency specified in the BP-MAX-RETRY-LOG-INTERVAL param.

For example, if a retrievable transient error occurs and this param is set to 300 seconds, a retry event message is generated immediately. If the transient error is still present after 300 seconds have elapsed, another event message is generated and the retry log interval is set to 300 seconds plus 300 seconds, or 600 seconds. If the transient error is still present after 600 seconds have elapsed, the event message is generated again and the retry log interval is set to 600 seconds plus 600 seconds, or 1200 seconds. The retry log interval continues to increase in this manner until either the transient error clears or the value of the BP-MAX-RETRY-LOG-INTERVAL param is reached. This param specifies the maximum length of time between the generation of an event message for a transient error.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 1 second through 1 hour.

This param does not apply to transactions that are retried because they completed with an action code response that was configured in the Retry Table (RTRY). This param applies only when a transaction is retried due to a transient system error that can be retried, such as certain Transaction Monitoring Facility (TMF) errors or a table lock.

If this param is not present in the LCONF or contains an invalid value, the default value is used.

Examples:	4 MINS 240 S 3600 MS
Read By:	STI
Param Default:	300 (seconds)

BP-LAG-TIME — The length of time that must elapse after a transaction is written to the History Table (HIST) before it is processed by the Remittance Generator process and the Bank Advice process. This param allows time for authorized payment transactions to be reversed (for example, canceled on the customer service representative New Payment screen) before they are remitted as vendor payments and logged to the ITS Transaction Log File (ITLF). This param also specifies how much time must elapse after logical network cutover before the Remittance Generator process begins processing for the next remittance business day.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 0 through 6 hours.

Examples: 900 S
 20 M
 20 MINUTES
Read By: BILLPAY
Param Default: 15 (minutes)

BP-MASTER-VEND-ADD-ALLOWED — A flag indicating whether customer service representatives are allowed to add customer vendors for vendors that are not already configured to the Vendor Table (VNDR). This param is used by the Billpay Server process. Valid values are as follows:

Y = Yes, customer service representatives are allowed to add customer vendors for vendors not already configured to the Vendor Table (VNDR).
N = No, customer service representatives are not allowed to add customer vendors for vendors not already configured to the Vendor Table (VNDR).

When this param is set to the value Y and a customer service representative adds a customer vendor for a vendor not already configured in the VNDR, a new VNDR row is automatically created for the vendor. Default data from the default VNDR row specified by the BP-MASTER-VEND-DFLT-NUM param is applied to the new row.

Read By: BILLPAY
Param Default: N

BP-MASTER-VEND-DFLT-NUM — The vendor number for the system-wide default vendor row in the Vendor Table (VNDR). When a new vendor is added to the Vendor Table (VNDR), default data from this row is applied to the new vendor row. Some of the values in this data can be overridden by the user adding the vendor. This param is used by the Billpay Server process. Valid values are 1 through 999999999.

Read By: BILLPAY
Param Default: 1

BP-MAX-RETRY-COUNT — The maximum number of times the Scheduled Transaction Initiator process will retry a transaction due to a transient system error that can be retried, such as certain Transaction Monitoring Facility (TMF) errors or

a table lock. This param does not apply to retries due to an action code response configured in the Retry Table (RTRY). If this param is set to a value of -1, retries are attempted indefinitely. Valid values are -1 and 0 through 32767.

Read By: STI

Param Default: -1

BP-MAX-RETRY-LOG-INTERVAL — This param is used in conjunction with the BP-INITIAL-RETRY-LOG-INTERVAL param to control the frequency of retry reminder event messages when a transient system error that can be retried is encountered for a transaction. Initially, the time interval specified in the BP-INITIAL-RETRY-LOG-INTERVAL param is used between the generation of retry reminder event messages. If the transient system error persists, the retry event message interval is increased according to the value of the BP-INITIAL-RETRY-LOG-INTERVAL param until it reaches the value of the BP-MAX-RETRY-LOG-INTERVAL param. This param specifies the maximum length of time that can elapse between the generation of a retry reminder event message.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 1 through 27927262400000000 microseconds.

This param does not apply to transactions that are retried because they completed with an action code response that was configured in the Retry Table (RTRY). This param only applies when a transaction is retried due to a transient system error that can be retried, such as certain Transaction Monitoring Facility (TMF) errors or a table lock.

Examples: 1 HRS

60 M

7200 S

Read By: STI

Param Default: 3600 (seconds)

BP-NUM-FUTURE-PART-EXT — The maximum number of partitions that can be extracted from the Future Table (FUTR). The value of the BP-FUTURE-PARTITION-NUM param must be less than or equal to the value of this param. This param is used by the Scheduled Transaction Initiator process. Valid values are 00 through 99.

If this param is not present in the LCONF or contains an invalid value, the Scheduled Transaction Initiator process abends during initialization.

Read By: BILLPAY
Param Default: No default value

BP-NUM-FUTURE-PART-INS — The maximum number of partitions that can be inserted into the Future Table (FUTR). This param is used by the Billpay Server and Scheduled Transaction Initiator processes to ensure that the generated partition number does not exceed the maximum number of partitions. Valid values are 00 through 99.

If this param is not present in the LCONF or contains an invalid value, the Billpay Server and Scheduled Transaction Initiator processes abend during initialization.

Read By: BILLPAY
Param Default: No default value

BP-NUM-HISTORY-PART-EXT — The maximum number of partitions that can be extracted from the History Table (HIST). The value of the BP-HISTORY-PARTITION-NUM param must be less than or equal to the value of this param. This param is used by the Achclear, Archive, Bank Advice, and Remittance Generator processes. Valid values are 00 through 99.

If this param is not present in the LCONF or contains an invalid value, the processes listed above abend during initialization.

Read By: BILLPAY
ACHCLEAR n , where n indicates the number of a History Table (HIST) partition
Param Default: No default value

BP-NUM-HISTORY-PART-INS — The maximum number of partitions that can be inserted into the History Table (HIST). This param is used by the Billpay Server and Scheduled Transaction Initiator processes to ensure that the generated partition number does not exceed the maximum number of partitions. Valid values are 00 through 99.

If this param is not present in the LCONF or contains an invalid value, the Billpay Server and Scheduled Transaction Initiator processes abend during initialization.

Read By: BILLPAY
Param Default: No default value

BP-REDO-DATE — The date, in YYYYMMDD format, for which a Redo Remittance Generator process is to recreate vendor payment remittance. The date specified by this param must be less than the current system date. The Redo Remittance Generator process selects History Table (HIST) rows with a remittance date equal to the date specified by this param. For any Remittance Generator process with the BP-REDO-MODE param set to a value of N, this param is ignored.

If this param is not present in the LCONF or contains an invalid value, the Redo Remittance Generator process abends during initialization.

Example: 19980630
Read By: REMITGEN
Param Default: No default value

BP-REDO-MODE — A flag indicating whether a Remittance Generator process operates in redo or normal mode. If this param is set to the value Y, the process operates in redo mode and only selects History Table (HIST) rows with a remittance date equal to the value of the BP-REDO-DATE param. Otherwise, the Remittance Generator process operates in normal mode, selecting HIST rows for the current remittance date. Valid values are as follows:

Y = Yes, this Remittance Generator process operates in redo mode.
N = No, this Remittance Generator process does not operate in redo mode; it operates in normal mode.

Read By: Symbolic name of the Remittance Generator process (for example, P1A^RG01^CGP or P1A^REDORG01^CGP)
Param Default: N

BP-REMIT-TYPE — A code indicating the type of remittance generated by a Remittance Generator process operating in normal or redo mode. Each Remittance Generator process selects History Table (HIST) rows with a remittance type equal to the value of this param. The first character of the value of this param is used to name the remittance file generated (for example, *Ayyymmdd* for ACH

remittance and *Cyymdd* for check remittance, where *yymdd* is the remittance date). This param can be set to one of the following reserved values or a user-defined value:

ACH = Automated clearinghouse (ACH) remittance.

CGP = Group-item check remittance. Payments for all customers are combined on one check per vendor.

CIT = Single-item check remittance. One payment from one customer per check.

If this param is not present in the LCONF or contains an invalid value, the Remittance Generator process abends during initialization.

Read By: Symbolic name of the Remittance Generator process (for example, P1A^RG01^CGP or P1A^REDORG01^CGP)

Param Default: No default value

BP-RETRY-DELAY — The length of time to wait between retries for a transient system error that can be retried. This param is used by the Scheduled Transaction Initiator process.

This param does not apply to transactions that are retried because they completed with an action code response that was configured in the Retry Table (RTRY). This param only applies when a transaction is retried due to a transient system error that can be retried, such as certain Transaction Monitoring Facility (TMF) errors or a table lock.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 0 through 27927262400000000 microseconds.

Examples: 3600 MS
1 M
60 SEC

Read By: STI

Param Default: 30 (seconds)

BP-SERVICE-PROVIDER — The name of the service provider used to read the Service Provider Table (SVPT). The SVPT contains one row that specifies the initial value used for generating customer IDs. This value is increased by one for each subsequent customer ID generated. The Billpay Server process uses this param to generate customer IDs for new customers without preloaded data.

If this param is not present in the LCONF or contains an invalid value, the Billpay Server process abends during initialization.

Read By: BILLPAY
Param Default: No default value

BP-SLEEP-INTERVAL — The length of time the Remittance Generator and Bank Advice processes are suspended after reaching the end-of-file on the History Table (HIST) before attempting to read the table again for more transaction rows to process. If these processes fail to find any new HIST rows to process when they read the table again, the current sleep interval is doubled.

For example, if this param is set to 60 seconds, the Remittance Generator and Bank Advice processes are suspended for 60 seconds after reaching the end-of-file on the HIST. If they find no new rows to process when they read the HIST again, they would be suspended for 60 seconds plus 60 seconds, or 120 seconds. If they find no new rows the next time they read the HIST, they would be suspended for 120 seconds plus 120 seconds, or 240 seconds. The sleep interval continues to increase in this manner until either the processes find new HIST rows to process (in which case, the sleep interval is reset to the value of this param) or the value of the BP-SLEEP-INTERVAL-MAX param is reached. The BP-SLEEP-INTERVAL-MAX param specifies the maximum length of time the Remittance Generator and Bank Advice processes can be suspended.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 0 through 1 hour.

Examples: 2 MINUTES
120 SEC
7200 MILLISEC
Read By: BANKADVICE
REMITGEN
Param Default: 60 (seconds)

BP-SLEEP-INTERVAL-MAX — The maximum length of time the Remittance Generator and Bank Advice processes can be suspended before reading the History Table (HIST) again for rows to process. When these processes find a new HIST row to process, the sleep interval is reset to the value of the BP-SLEEP-INTERVAL param.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 0 through 1 hour.

Examples: 10 MINS
 1 HR
Read By: BANKADVICE
 REMITGEN
Param Default: 600 (seconds)

BP-STI-FINAL-PROCESSING — The length of time after BP-STI-WINDOW-CLOSE-TIME plus BP-STI-LAG-TIME during which the Scheduled Transaction Initiator process attempts to complete any processing for outstanding transactions that are scheduled for the current business day.

Read By: STI
Param Default: 3 (minutes)

BP-STI-LAG-TIME — The length of time after BP-STI-WINDOW-CLOSE-TIME during which the Scheduled Transaction Initiator process attempts to complete any processing for outstanding transactions prior to logical network cutover. Transactions must be at least the age of this time period to be processed by Scheduled Transaction Initiator.

Read By: STI
Param Default: 15 (minutes)

BP-STI-WINDOW-CLOSE-TIME — The time of day, in hh:mm format, that the Scheduled Transaction Initiator process will stop sending transactions scheduled to be processed for the current day. This param is used in conjunction with the BP-STI-WINDOW-OPEN-TIME param to define the daily transaction processing window for the Scheduled Transaction Initiator process. The values of these params must be set in proper relation to midnight and the value of the LGNT-CUTOVER param. Valid values are 00:00 through 23:59.

Midnight can occur before, during, or after the processing window, but logical network cutover can only occur after the processing window and midnight. Logical network cutover cannot occur before or during the processing window or before midnight. All of the valid relationships among the BP-STI-WINDOW-

CLOSE-TIME, BP-STI-WINDOW-OPEN-TIME, and LGNT-CUTOVER params and midnight are shown in the following table. Events are depicted in chronological order from left to right, with each column depicting a separate event.

Occurs First	Occurs Second	Occurs Third	Occurs Fourth
Midnight	Open window	Close window	Cutover
Open window	Midnight	Close window	Cutover
Open window	Close window	Midnight	Cutover

If the value of the BP-STI-WINDOW-OPEN-TIME param is greater than the value of the BP-STI-WINDOW-CLOSE-TIME param, the open window time is considered to be for the previous day, but after cutover. If the value of the BP-STI-WINDOW-OPEN-TIME param is greater than the value of the BP-STI-WINDOW-CLOSE-TIME param, the value of the BP-STI-WINDOW-CLOSE-TIME param cannot be less than the value of the LGNT-CUTOVER param. If it is, a configuration error message is generated.

Each of the **invalid** relationships among the BP-STI-WINDOW-CLOSE-TIME, BP-STI-WINDOW-OPEN-TIME, and LGNT-CUTOVER params and midnight are shown in the following table. Events are depicted in chronological order from left to right, with each column depicting a separate event.

Occurs First	Occurs Second	Occurs Third	Occurs Fourth
Midnight	Open window	Cutover	Close window
Midnight	Close window	Open window	Cutover

If this param is not present in the LCONF or contains an invalid value, the Scheduled Transaction Initiator process abends during initialization.

Example: 17:00
Read By: STI
Param Default: No default value

BP-STI-WINDOW-OPEN-TIME — The time of day, in hh:mm format, that the Scheduled Transaction Initiator process will start sending transactions scheduled to be processed for the current day. This param is used in conjunction with the BP-STI-WINDOW-CLOSE-TIME to define the daily transaction processing window for the Scheduled Transaction Initiator process. The values of these params must

be set in proper relation to midnight and the value of the LGNT-CUTOVER param. Valid values are 00:00 through 23:59. Refer to the BP-STI-WINDOW-CLOSE-TIME param for a discussion of valid values.

If this param is not present in the LCONF or contains an invalid value, the Scheduled Transaction Initiator process abends during initialization.

Example: 08:00
Read By: STI
Param Default: No default value

BP-TELEBANKING — The symbolic process name of the BASE24-telebanking Integrated Authorization Server process. The value of this param is used to fill in the XPNET destination in financial authorization request messages sent (using Pathsend) from a Pathway-based Billpay Server process to the XPNET process for delivery to the BASE24-telebanking Integrated Authorization Server process.

If this param is not present in the LCONF or contains an invalid value, the Pathway-based Billpay Server process abends during initialization.

Example: P1A^IAS01
Read By: BILLPAY
Param Default: No default value

BP-TELEBANKING-LOG — The symbolic process name of the BASE24-telebanking Integrated Authorization Server process. The value of this param is used to fill in the XPNET destination in messages sent from the Bank Advice process to be logged to the ITS Transaction Log File (ITLF).

Normally, this param contains the same value as the BP-TELEBANKING param; however, you could use this param to configure a separate BASE24-telebanking Integrated Authorization Server process for logging purposes only.

If this param is not present in the LCONF or contains an invalid value, the Bank Advice process abends during initialization.

Read By: BILLPAY
Example: P1A^IAS01
Param Default: No default value

BP-TMF-BATCH-DURATION-TIME — The maximum length of time a Transaction Monitoring Facility (TMF) batch can exist before it is committed.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 0 through 24 hours.

Examples: 1 MINUTE
 600 MILLISECONDS
 120 S

Read By: ACHCLEAR
 ARCHIVE
 BANKADVICE
 CLEANUP
 REMITGEN

Param Default: 60 (seconds)

BP-TMF-BATCH-SIZE — The maximum number of rows from all tables and records from all files to be included in the same Transaction Monitoring Facility (TMF) batch. If a process reaches the end-of-file on a table or file, or the time required to process a batch becomes greater than the value of the BP-TMF-BATCH-DURATION-TIME param before the size of the batch specified in this param is reached, the process will still complete the batch. Valid values are 1 through 30000.

Read By: ACHCLEAR
 ARCHIVE
 BANKADVICE
 CLEANUP
 REMITGEN

Param Default: 30

BP-TXN-TIMEOUT — The length of time the XPNET-based Billpay Server process and the Scheduled Transaction Initiator process waits for a response to an authorization request before considering the request to have timed out. This timer must be set to be longer than any timeout value set by the authorizer.

To avoid undesired timeouts, the Pathway-based Billpay Server process (for example, SERVER-BP in the Pathway Configuration File) must have a timeout value that is greater than the value of this param.

The value of this param is expressed in time interval format using any of the valid time interval unit identifiers explained under the “Time Interval” discussion provided earlier in this section. Valid values are 1 microsecond through 1 hour.

Examples: 1 MIN
 65 SECOND
 600 MILLISECS
Read By: BILLPAY
Param Default: 60 (seconds)

BP-XPNET-CTSE-PATHMON — The name of the Pathmon process that communicates with the Path Server process specified in the BP-XPNET-CTSE-SERVER-CLASS param. The Path Server process translates messages exchanged between a Pathway-based Billpay Server process and the XPNET-based Integrated Authorization Server process. The Pathmon process resides between the Pathway-based Billpay Server process and the Path Server process in this message path.

If this param is not present in the LCONF or contains an invalid value, the Pathway-based Billpay Server process abends at initialization.

Read By: BILLPAY
Example: \$P1PM
Param Default: No default value

BP-XPNET-CTSE-SERVER-CLASS — The name of the server class configured for the Path Server process. This process translates messages exchanged between a Pathway-based Billpay Server process and the XPNET-based Integrated Authorization Server process. The Path Server process resides between the Pathmon process and the XPNET process in this message path.

If this param is not present in the LCONF or contains an invalid value, the Pathway-based Billpay Server process abends at initialization.

Read By: BILLPAY
Example: SERVER-BP
Param Default: No default value

ACI Worldwide, Inc.

10: BASE24-card Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-card product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24-card product. Each of the following assigns should have the usage code CARD (and only the code CARD) entered in the USAGE CODES field on the LNCF Assign screen.

ACCOUNT-NUM-RPT — The fully qualified location of the Available Account Numbers Report. This location can be a spooler location or the name of a disk file. This report is generated when an operator initiates the account number generation function from the Card Operator Function (COF) screen. The Account Number Generation Server process uses this assign.

Example: \B24.\$\$.#ACCT

CARD-CARRIER-RPT — The fully qualified location of the Card Carrier Report. This location can be a spooler location or a disk file. This report is generated when an operator initiates a force issue or mass issue function from the Card Management Functions (CMF) screen. The Plastic Card Generation Server process uses this assign.

Example: \B24.\$\$.#CARD

CARD-PRODUCTION-RPT — The fully qualified location of the Card Production Control Report. This location can be a spooler location or a disk file. This report is generated when an operator initiates a force issue or mass issue function from the Card Management Functions (CMF) screen. The Plastic Card Generation Server process uses this assign.

Example: \B24.\$\$.#CPROD

EMBOSS-MACHINE — The fully qualified port name to which the DataCard machine is attached. This assign is only required if the output device for plastic card generation is the DataCard embossing machine. The Plastic Card Generation Server process uses this assign.

Example: \B24.\$EMOBOS

EXCEPTION-RPT — The fully qualified location of the CMS Reissue Exception Report. This location can be a spooler location or a disk file. This report is generated when an operator initiates the issue maintenance function from the Card Management Functions (CMF) screen. The Card Management Functions Server process uses this assign.

Example: \B24.\$\$.#EXP

ISSUE-MAINT-RPT — The fully qualified location of the CMS Issue Maintenance Report. This location can be a spooler location or a disk file. This report is generated when an operator initiates the issue maintenance function from the Card Management Functions (CMF) screen. The Card Management Functions Server process uses this assign.

Example: \B24.\$\$.#MAINT

ISSUE-PROJ-RPT — The fully qualified location of the CMS Reissue Projection Report. This location can be a spooler location or the name of a disk file. This report is generated when an operator initiates the issue projection function from the Card Management Functions (CMF) screen. The Card Management Functions Server process uses this assign.

Example: \B24.\$\$.#ISS

PCGEN-EXCEPTION-RPT — The fully qualified location of the PCGEN Exception Report. This location can be a spooler location or a disk file. This report is generated when an operator initiates a force issue or mass issue function from the Card Management Functions (CMF) screen. The Plastic Card Generation Server process uses this assign.

Example: \B24.\$\$.#PCGEN

PIN-MAILER-RPT — The fully qualified location of the PIN Mailer Report. This location can be a spooler location or a disk file. This report is generated when an operator initiates a force issue or mass issue function from the Card Management Functions (CMF) screen. The Plastic Card Generation Server process uses this assign.

Example: \B24.\$\$.#PIN

TAPE-DRIVE — The fully qualified name of the tape drive to which the BASE24 system is to write the card generation data. The Plastic Card Generation Server process uses this assign. This assign is only required if the output device for plastic card generation is tape.

Example: \B24.\$TAPE1

Params

The following params are used exclusively by the BASE24-card product. Each of the following params should have the usage code CARD (and only the code CARD) entered in the USAGE CODES field on the LNCF Param screen.

HRDWR-CVV-GEN — A flag indicating whether the Card Verification Value (CVV) and Card Verification Value 2 (CVV2) are generated in hardware or software. If this param is set to a value of Y, the CVV and CVV2 are generated in hardware. If this param is missing or set to any other value, the CVV and CVV2 are generated in software. The Plastic Card Generation Server (SVPCGEN) process uses this param.

Param Default: Generate the CVV and CVV2 in software.

HRDWR-PIN-GEN — A flag indicating whether the PIN and PIN mailer are generated in hardware or software. If this param is set to a value of Y, the PIN and PIN mailer are generated in hardware. If this param is missing or set to any other value, the PIN and PIN mailer are generated in software. The Plastic Card Generation Server (SVPCGEN) process uses this param.

Param Default: Generate the PIN and PIN mailer in software.

ACI Worldwide, Inc.

11: BASE24 Customer Service Assigns

The following pages document the assigns used exclusively by the BASE24 Customer Service product. The assigns are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24 Customer Service product. Each of the following assigns should have the usage code CUST (and only the code CUST) entered in the USAGE CODES field on the LNCF Assign screen.

CCIF — The fully qualified file name of the default Customer/Cardholder Information File (CCIF). The CCIF maintains information about the primary cardholder (and optionally the secondary cardholder) that is not found elsewhere in BASE24, such as the cardholder's address and telephone number. Processes use the default CCIF when an attempt to use the CCIF identified by a *CCIFIdentifier* assign is unsuccessful, where *identifier* specifies a particular refresh group configured in the Institution Definition File (IDF). The Customer Information Screens Server and Customer/Cardholder Information File Server processes use this assign.

Example: \B24.\$DATA.PRO1DATA.CCIF

CCIFIdentifier — The fully qualified file name of the CCIF for a particular refresh group. This assign includes an *identifier* used for different CCIFs in the same logical network, where *identifier* specifies a particular refresh group. Refresh groups are established by institution in the Institution Data File (IDF). One CCIF assign is established for each unique refresh group in the IDF. If a *CCIFIdentifier* assign is not found for a particular refresh group, the default CCIF specified by the CCIF assign is used instead. The *CCIFIdentifier* assign is used by the following processes:

Customer Information Screens Server process
Customer/Cardholder Information File Server process
Enscribe Refresh process

If a matching CCIF assign is found, the Enscribe Refresh process builds the new CCIF using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.CCIF (data file name)
 \B24.\$DATA.PRO1TPLT.CCIF (template file name)
Template File: Required to build the new file during full-file refreshes.

CCMF — The fully qualified file name of the default Customer/Cardholder Memo File (CCMF). The CCMF maintains miscellaneous memos about customers or cardholders. Processes use the default CCMF when an attempt to use the CCMF identified by a *CCMFIdentifier* assign is unsuccessful, where *identifier* specifies a particular refresh group configured in the Institution Definition File (IDF). The Customer Information Screens Server process and Customer/Cardholder Memo File Cleanup program use this assign.

Example: \B24.\$DATA.PRO1DATA.CCMF

CCMFIdentifier — The fully qualified file name of the CCMF for a particular refresh group. This assign includes an *identifier* used for different CCMFs in the same logical network, where *identifier* specifies a particular refresh group. Refresh groups are established by institution in the Institution Data File (IDF). One CCMF assign is established for each unique refresh group in the IDF. If a *CCMFIdentifier* assign is not found for a particular refresh group, the default CCMF specified by the CCMF assign is used instead. The *CCMFIdentifier* assign is used by the following processes:

Customer Information Screens Server process
Customer/Cardholder Memo File Cleanup program
Enscribe Refresh process

Care should be taken to ensure that multiple CCMF assigns do not contain the same physical file location. Otherwise, the Customer/Cardholder Memo File Cleanup program will attempt to process the same file multiple times.

If a matching CCMF assign is found, the Enscribe Refresh process builds the new CCMF using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.CCMF (data file name)
 \B24.\$DATA.PRO1TPLT.CCMF (template file name)
Template File: Required to build the new file during full-file refreshes.

ACI Worldwide, Inc.

12: BASE24-from host maintenance Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-from host maintenance product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24-from host maintenance product. Each of the following assigns should have the usage code FHM (and only the code FHM) entered in the USAGE CODES field on the LNCF Assign screen.

FHM-CSFC-RPT-PROG-NAME — The fully qualified location of the program that generates the BASE24-from host maintenance daily reports for the Customer/Cardholder Information File (CCIF) and Customer/Cardholder Memo File (CCMF). The main From Host Maintenance process uses this assign.

Example: \B24.\$DATA.OCxxCS.FHMCSRPT, where *xx* is the number of the current release

FHM-CUST-RPT-PROG-NAME — The fully qualified location of the program that generates the BASE24-from host maintenance daily reports for the Customer Table (CSTT) and Customer/Account Relation Table (CACT). The main From Host Maintenance process uses this assign.

Example: \B24.\$DATA.FHxxCSTT.FHMCRRPT, where *xx* is the number of the current release

FHM-RPT-CMD-FILE — The spooler location for event messages the From Host Maintenance process generates while creating reports. The From Host Maintenance process requires this assign if reports are to be created.

Example: \B24.\$\$.#FHMERR

FHM-PSNL-RPT-PROG-NAME — The fully qualified location of the program that generates the BASE24-from host maintenance daily reports for the Personal Information Table (PIT) and Customer/Personal Information Relation Table (CPIT). The main From Host Maintenance process uses this assign.

Example: \B24.\$DATA.FHxxPIT.FHMPPRPT, where *xx* is the number of the current release

FHM-RPT-OBEY-FILE — The fully qualified file name of the obey file used to produce daily From Host Maintenance reports. The main From Host Maintenance process uses this assign.

Example: \B24.\$DATA.FHMRPT.FRYYYMMDD

FHM-RPT-PROG-NAME — The fully qualified file name of the program that generates the BASE24-from host maintenance daily reports for the base files. The main From Host Maintenance process uses this assign.

Example: \B24.\$DATA.FHxxOBJ.FHMRPT, where *xx* is the number of the current release

ULF — The fully qualified file name of the Update Log File (ULF). The Super Extract process and the From Host Maintenance process use this assign.

Example: \B24.\$DATA.PRO1DATA.ULYYMMDD (data file name)
 \B24.\$DATA.PRO1TPLT.ULYYMMDD (template file name)

Template File: Required because the From Host Maintenance process periodically creates the ULF.

Params

The following params are used exclusively by the BASE24-from host maintenance product. Each of the following params should have the usage code FHM (and only the code FHM) entered in the USAGE CODES field on the LNCF Param screen.

FHM-CSFC-RPT — A code indicating whether the From Host Maintenance process is to include the BASE24 Customer Service reports when the BASE24-from host maintenance reports are generated. The From Host Maintenance process uses this param. Valid values are as follows:

Y = Yes, include the BASE24 Customer Service reports.

N = No, do not include the BASE24 Customer Service reports.

Param Default: N

FHM-CUST-RPT — A code indicating whether the From Host Maintenance process is to include the BASE24-telebanking reports for the Customer Table (CSTT) and Customer/Account Relation Table (CACT) when the BASE24-from host maintenance reports are generated. The From Host Maintenance process uses this param. Valid values are as follows:

Y = Yes, include the BASE24-telebanking customer reports.

N = No, do not include the BASE24-telebanking customer reports.

Param Default: N

FHM-ISO-FIXED-LENGTH — A code indicating whether message responses are fixed-length ISO format or standard ISO variable format messages. The From Host Maintenance process uses this param. Valid values are as follows:

Y = Yes, generate fixed-length response messages.

N = No, do not generate fixed-length response messages.

Param Default: N

FHM-LN-CUTOVER — The time of day that the entire logical network is cut over. All institutions in the logical network must be cut over by this time. This param can be set to any value, expressed in 24-hour time, 00:00 (12:00 a.m.) through 23:59 (11:59 p.m.). The From Host Maintenance process uses this param

to determine when the logical network cuts over and to determine the time of day to begin logging records to a new ULF. The Super Extract process reads this param when extracting the Store-and-Forward File (SAF).

If this param is not present in the LCONF or contains an invalid value, the From Host Maintenance process accessing the LCONF for this param abends during initialization.

FHM-MASTER — The symbolic name of the From Host Maintenance process that creates BASE24-from host maintenance reports. If more than one From Host Maintenance process exists, only the process specified in this param can create from host maintenance reports. The From Host Maintenance process uses this param.

If this param is not present in the LCONF or contains an invalid value, the From Host Maintenance process accessing the LCONF for this param abends during initialization.

Example: P1A^FHM1

FHM-MAX-NUM-FILE-ENTRIES — A value that specifies the maximum number of entries allowed in the file table. The file table is built from the Institution definition File (IDF) and contains all Financial Institution Identifiers (FIIDs), their products, and file names. The file table is used by the From Host Maintenance process. The range of valid values is 0 through 2340.

Param Default: 320

FHM-PSNL-RPT — A code indicating whether the From Host Maintenance process is to include the BASE24-telebanking reports for the Personal Information Table (PIT) and Customer/Personal ID Relation Table (CPIT) when the BASE24-from host maintenance reports are generated. The From Host Maintenance process uses this param. Valid values are as follows:

Y = Yes, include the BASE24-telebanking personal information reports.

N = No, do not include the BASE24-telebanking personal information reports.

Param Default: N

FHM-REL-IND — Indicates whether the current (6.0) or previous (5.x) release of BASE24-from host maintenance message is being used. Valid values are as follows:

- 01 = Current release (6.0)
- 02 = Previous release (5.x)

The From Host Maintenance process uses this param.

Note: The BASE24-from host maintenance product uses the same release for all message formats.

Param Default: 02

FHM-RPT — A code indicating whether the From Host Maintenance process is to include reports for the base files. Valid values are as follows:

- Y = Yes, include base reports.
- N = No, do not include base reports.

The From Host Maintenance process uses this param.

Param Default: N

FHM-RPT-CPU — The number of the processor (CPU) in which the From Host Maintenance process executes the BASE24-from host maintenance report programs. The value of this param is placed in the startup command of each BASE24-from host maintenance report program started using the obey file created by the From Host Maintenance process. The From Host Maintenance process uses this param. Valid values are 0 through 15.

If this param is not present in the LCONF or contains an invalid value, report programs execute in the same CPU as that in which the From Host Maintenance process is running.

Param Default: The CPU where the From Host Maintenance process is currently running

FHM-RPT-FILE-RETENTION — The number of days worth of BASE24-from host maintenance report files and report obey files, prior to the current business day, that are to remain on the system. After the specified number of days, the From Host Maintenance process deletes the files from the system. For example, if

the value in this param is 3 and the current business date is 01/06/05 (for June 5, 2001), files dated 01/06/04, 01/06/03 and 01/06/02 are retained on the system and closed. Files dated 01/06/01 and earlier have been deleted from the system. Files for the current business day have yet to be created.

The From Host Maintenance process uses this param. Valid values are 3 through 99.

Param Default: 7

FHM-RPT-PRI — The priority at which the BASE24-from host maintenance report programs are executed. The value of this param is placed in the startup command of each BASE24-from host maintenance report program started using the obey file created by the From Host Maintenance process. This param can be set to any numeric value from 1 through 199. The From Host Maintenance process uses this param.

If this param is not present in the LCONF or contains an invalid value, the report programs are executed at the same priority as the From Host Maintenance process. If this causes an error, the report programs attempt to run at an execution priority of 100.

Param Default: Same priority as the From Host Maintenance process, or 100

FHM-RPT-STARTUP — The time of day used by the From Host Maintenance process to determine when the BASE24-from host maintenance report programs are started. This param can be set to any value, expressed in 24-hour time, 00:00 (12:00 a.m.) through 23:59 (11:59 p.m.). The From Host Maintenance process uses this param.

If this param is not present in the LCONF or contains an invalid value, the From Host Maintenance process executes all report programs at logical network cutover (the time specified in the FHM-LN-CUTOVER param).

Param Default: FHM-LN-CUTOVER param value

FHM-SLAVE-NOTIFY*identifier* — The symbolic name of a secondary From Host Maintenance process to which the main From Host Maintenance process must send a 9502 message at cutover. The main From Host Maintenance process uses this param when multiple From Host Maintenance processes are configured in a single logical network. A maximum of 16 processes can be notified.

Each FHM-SLAVE-NOTIFY param contains the name of one process. When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another FHM-SLAVE-NOTIFY param.

If this param is not present in the LCONF or contains an invalid value, the main From Host Maintenance process does not notify any secondary From Host Maintenance processes.

FHM-ULF-AUDIT — A code indicating what information the From Host Maintenance process logs to records in the Update Log File (ULF). The From Host Maintenance process uses this param. Valid values are as follows:

- 0 = Do not audit the ULF record or log MSG-HEADER information.
- 1 = Audit the ULF record and log MSG-HEADER information.
- 2 = Log MSG-HEADER information; do not audit the ULF record.

Param Default: 1

FHM-ULF-FILE-RETENTION — The number of days worth of Update Log Files (ULFs), prior to the current business day, that are to remain on the system. After the specified time, the From Host Maintenance process deletes the old files from the system. Valid values are 3 through 99.

Param Default: 7

FHM-ULF-NOTIFY-INTERVAL — The number of writes made to the Update Log File (ULF) before calculating the percentage of file full. Each time a write is made to the ULF, a counter is increased by one. When the counter is equal to the value specified in this param, the From Host Maintenance process calculates how full the ULF is. The counter is then reset to zero.

When the file reaches the percent full specified in the FHM-ULF-NOTIFY-PERCENTAGE param, the From Host Maintenance process generates an event message indicating that the file is becoming full. The From Host Maintenance process continues to generate event messages indicating that the file is becoming full at the interval specified in this param. Valid values are 10 through 32766. The From Host Maintenance process uses this param.

Param Default: 50

FHM-ULF-NOTIFY-PERCENTAGE — The percentage of file full at which the From Host Maintenance process generates an event message indicating that the Update Log File (ULF) is becoming full. The From Host Maintenance process continues to generate event messages at the interval indicated in the FHM-ULF-NOTIFY-INTERVAL param. Valid values are 10 through 99. The From Host Maintenance process uses this param.

Param Default: 70

FHM-ULF-REJECTS — A code indicating the extent to which the From Host Maintenance process logs rejected record updates to the Update Log File (ULF). Valid values are as follows:

Y = Yes, log all rejected updates.

N = No, do not log rejected updates.

The From Host Maintenance process uses this param.

Param Default: N

ACI Worldwide, Inc.

13: BASE24-inventory Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-inventory product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24-inventory product.

INV-EXP-STOCK-CLEANUP-REP-LOC — The fully qualified file name of the report location for the BASE24-inventory Housekeeping expired stock cleanup task. This assign is used and required by BASE24-inventory Housekeeping.

Example: \B24.\$S.#INVEXP

INV-GROUP-STOCK-DELETE-REP-LOC — The fully qualified file name of the report location for the BASE24-inventory Housekeeping group stock delete task. This assign is used and required by BASE24-inventory Housekeeping.

Example: \B24.\$S.#INVGRP

INV-REFR-REP — The fully qualified file name of the BASE24-inventory Refresh report location. This assign is required for the product functionality.

Example: \B24.\$S.#INVREFR

INV-SOLD-STOCK-CLEANUP-REP-LOC — The fully qualified file name of the report location for BASE24-inventory Housekeeping sold stock cleanup task. This assign is used and required by BASE24-inventory Housekeeping.

Example: \B24.\$S.#INVSOLD

NRIF — The fully-qualified name of the BASE24-inventory Refresh Input Format (NRIF). This assign is used by the BASE24-inventory Refresh and is required for the product functionality.

Example: \B24.\$DATA.PRO1DATA.NRIF

NSCF — The fully qualified field name of the BASE24-inventory Stock Configuration File (NSCF). This assign is used by the BASE24-inventory Stock Manager, Refresh, Housekeeping, and Settlement Initiator and is required for this enhancement.

Example: \B24.\$DATA.PRO1DATA.NSCF

NTLF — The fully qualified file name of the BASE24-inventory Transaction Log File (NTLF). This assign is used by the BASE24-inventory Stock Manager and Settlement Initiator and is required for this enhancement.

Example: \B24.\$DATA.PRO1DATA.NTYMMDD
Template: Required (example: \B24.\$DATA.PRO1TPLT.
 NTYYMMDD)

Params

The following params are used exclusively by the BASE24-inventory product.

INV-LN-CUTOVER — The BASE24-inventory logical network cutover time in HHMM format. This param is used by the BASE24-inventory Settlement Initiator process. It is a required param. Valid values are 00:00 to 23:59.

Param Default: No default value

INV-LNET-CUTOVER-SERVICE — The service name of the processes requiring a logical network cutover message from the BASE24-inventory Settlement Initiator process. This param is used by the BASE24-inventory Settlement Initiator process. It is a required param.

Param Default: No default value

INV-SETL-ATM-CUT-SERVICE — The service name of the BASE24-atm processes requiring a logical network cutover message from the BASE24-inventory Settlement Initiator process. This param is used by the BASE24-inventory Settlement Initiator process. It is an optional param.

Param Default: No default value

INV-SETL-LN-CUTOVER-LEAD-TIME — The minimum number of minutes that all BASE24-inventory Stock Manager processes must be cutover before BASE24-inventory logical network cutover occurs. This param is used by the BASE24-inventory Settlement Initiator process. Valid values are 0–1440.

Param Default: 30

INV-SETL-NTLF-EXT-TO-ALLOCATE — The number of extents BASE24-inventory Settlement Initiator allocates when creating new BASE24-inventory Transaction Log Files (NTLF). This param is used by the BASE24-inventory Settlement Initiator process. Valid values are 1–16.

Param Default: 16

INV-SETL-NTLF-FILE-RETENTION — The number of days the BASE24-inventory Transaction Log Files (NTLF) are retained to disk. This param is used by the BASE24-inventory Settlement Initiator process. Valid values are 3–99.

Param Default: 7

INV-SETL-POS-CUT-SERVICE — The service name of the BASE24-pos processes requiring a logical network cutover message from the BASE24-inventory Settlement Initiator process. This param is used by the BASE24-inventory Settlement process. It is an optional param.

Param Default: No default value

INV-SMGR-STOCK-TYPE — The stock type a specific BASE24-inventory Stock Manager process controls. This param is used by BASE24-inventory Stock Manager processes. It is a required param and must be defined as process-specific for the Stock Manager process controlling the stock type.

Param Default: No default value

ACI Worldwide, Inc.

14: BASE24-mail Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-mail product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24-mail product. Each of the following assigns should have the usage code MAIL (and only the code MAIL) entered in the USAGE CODES field on the LNCF Assign screen.

HMBF — The fully qualified file name of the BASE24-mail Host Mail Box File (HMBF). The HMBF contains one record for each mail message to a host that is being stored for later delivery. The Mail process and Super Extract process use this assign. This assign is required only for logical networks that have BASE24-mail installed.

Example: \B24.\$DATA.PRO1DATA.HMBF

HMTF — The fully qualified file name of the Host Message Text File (HMTF). The HMTF contains a record for each mail message to a host. The Mail process and Super Extract process use this assign. This assign is required only for logical networks that have BASE24-mail installed.

Example: \B24.\$DATA.PRO1DATA.HMTF

LOG — The fully qualified name of the log location for the Mail process. This assign is used only in logical networks that have BASE24-mail installed.

Example: \B24.\$SUDO

MBAF — The fully qualified file name of the Mail Box Address File (MBAF). The Mail Box Address File Server and Mail processes use this assign. This assign is required only for logical networks that have BASE24-mail installed.

Example: \B24.\$DATA.PRO1DATA.MBAF

MBF — The fully qualified file name of the Mail Box File (MBF). The Mail process and Super Extract process use this assign. This assign is required only for logical networks that have BASE24-mail installed.

Example: \B24.\$DATA.PRO1DATA.MBF

MTF — The fully qualified file name of the Mail Box Message File (MTF). The Mail process and Super Extract process use this assign. This assign is required only for logical networks that have BASE24-mail installed.

Example: \B24.\$DATA.PRO1DATA.MTF

Params

The following params are used exclusively by the BASE24-mail product. Each of the following params should have the usage code MAIL (and only the code MAIL) entered in the USAGE CODES field on the LNCF Param screen.

EMS-BCST-RESTRICT-BY-TYPE — A code indicating whether the Mail process restricts broadcast lists by location type. Valid values are as follows:

Y = Yes, terminal broadcasts, location type 2, cannot use broadcast lists.

N = No, terminal broadcasts, location type 2, can use broadcast lists.

Param Default: N

EMS-BROADCAST-ID-LMT — The maximum number of records the Mail process allows in the broadcast ID table. Valid values are 1–32765.

Param Default: 100

EMS-BROADCAST-MBR-LMT — The maximum number of records the Mail process allows in the broadcast member table. Valid values are 1–32765.

Param Default: 5000

EMS-DPC-STATUS — A code indicating whether mail DPC status is available to the Mail process. Valid values are as follows:

UP = Yes, mail DPC status is available.

DOWN = No, mail DPC status is not available.

Param Default: DOWN

EMS-FIID-RESTRICTED — A flag indicating whether mail users are restricted to sending messages to a single FIID. The Mail process uses this param. Valid values are as follows:

Y = Yes, mail is restricted to a single FIID.

N = No, mail is not restricted to a single FIID.

Param Default: Y

EMS-FILE-FULL-PCT-WARN — The percentage of file full at which the Mail process generates an event message indicating that its tables are becoming full. Valid values are 10 through 99.

Param Default: 80

EMS-LOGICAL-NET — The name of the logical network in which the Mail process runs. This param is required.

Param Default: No default value

EMS-PROD-BYTE-MAP — The product indicator byte map indicating the products (i.e., BASE24-pos) supported by the BASE24-mail product. The Mail Box Address File (MBAF) Server process uses this param. The product byte map consists of 16 alphanumeric characters, with each character representing a different product. A value of 1 in one or more of the 16 positions indicates that the product associated with that position in the byte map is supported. The BASE24-pos product is represented by the third character in the byte map.

EMS-PSTU-ACTIVE-LMT-FIID — The maximum number of active pass-through messages the Mail process allows in the FIID queue. Valid values are 1–32767.

Param Default: 10

EMS-PSTU-ACTIVE-LMT-TERM — The maximum number of active pass-through messages the Mail process allows in the terminal queue. Valid values are 1–32767.

Param Default: 10

EMS-PSTU-QUEUE-DEPTH — The maximum number of pass-through messages that can be queued to the Mail process. Valid values are 1–32767.

Param Default: 1000

EMS-PSTU-WAIT-INTERVAL — The length of time, in minutes, a pass-through message can remain in the queue before it is considered to be expired. Valid values are 1–32767.

Param Default: 5

EMS-SEND-METHOD-FIID — A flag indicating whether the Mail process sends BASE24-mail Host Mail Box File (HMBF) records directly to their destination or places them in the Pass-through queue first. Valid values are as follows:

Y = Yes, send HMBF records directly to their destination.

N = No, do not send HMBF records directly to their destination.

Param Default: Y

EMS-SEND-METHOD-TERM — A code indicating how the Mail process sends terminal messages. Valid values are as follows:

0 = Do not automatically send terminal messages.

1 = Send terminal messages only if the Device Handler module is not busy.

2 = Automatically send terminal messages.

Param Default: 0

EMS-TERMINAL-LMT — The maximum number of terminals allowed in the network. The Mail process and the POS Terminal Data File (PTDF) module for the BASE24-mail product use this param. Valid values are 1–32767.

Param Default: 1000

15: BASE24-pos Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-pos product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24-pos product. Each of the following assigns should have the usage code POS (and only the code POS) entered in the USAGE CODES field on the LNCF Assign screen.

BP-ADMN — The fully qualified file name of the Administrative Card File (ADMN). The Administrative Card File Server process and the BASE24-pos Device Handler/Router/Authorization process use this assign. The BASE24-pos Router module reads the assign during initialization.

This assign is required only if administrative transactions are supported.

Example: \B24.\$DATA.PRO1DATA.ADMN

BP-ANEG — The fully qualified file name of the National Negative File (ANEG) for American Express. This assign is required only if the BASE24-pos product checks the ANEG prior to routing transactions to the American Express Interchange. This assign is used by the following processes:

National Negative Card File (NNF) Server process
BASE24-pos Device Handler/Router/Authorization process

The BASE24-pos Router module reads this assign during initialization.

Example: \B24.\$DATA.PRO1DATA.ANEG

BP-AST — The fully qualified file name of the Authorization Selection Table File (AST). The BASE24-pos Router module reads the assign during initialization. The Authorization Selection Table File (AST) Server process and the BASE24-pos Device Handler/Router/Authorization process use this assign.

This assign is required. If this assign is not present in the LCONF or contains an invalid value, the BASE24-pos Device Handler/Router/Authorization process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.AST

BP-BNEG — The fully qualified file name of the BNEG for Visa. This assign is required only if the BASE24-pos product checks the BNEG prior to routing transactions to the Visa Interchange. This assign is used by the following processes:

National Negative Card File (NNF) Server process
Base National Negative File (BNEG) Refresh process
BASE24-pos Device Handler/Router/Authorization process

The BASE24-pos Router module reads this assign during initialization. The Base National Negative File (BNEG) Refresh process uses the file attributes of the template file indicated in the assign to create a new BNEG during a full-file refresh of the file.

Example: \B24.\$DATA.PRO1DATA.BNEG (data file name)
 \B24.\$DATA.PRO1TPLT.BNEG (template file name)
Template File: Required to build the BNEG during full-file refreshes.

BP-BNR — The fully qualified file name of the Base National Range File (BNR) for Visa. The BP-BNR assign is required only if BASE24-pos checks the BNR prior to routing transactions to the Visa Interchange. The BASE24-pos Device Handler/Router/Authorization process and the BNEG Refresh process use this assign.

The BASE24-pos Router module attempts to read this assign during initialization. The BNEG Refresh process uses the file attributes of the template file indicated in the assign to create a new BNR during a full-file refresh of the file.

Example: \B24.\$DATA.PRO1DATA.BNR (data file name)
 \B24.\$DATA.PRO1TPLT.BNR (template file name)
Template File: Required to build the BNR during full-file refreshes.

BP-CAPF — The fully qualified file name of the Card Authorization Parameters File (CAPF). This assign is required only for logical networks that have institutions using the Parametric Authorization method. The Card Authorization Parameters File Server process and the BASE24-pos Device Handler/Router/Authorization process use this assign. The BASE24-pos Router module reads the assign during initialization.

Example: \B24.\$DATA.PRO1DATA.CAPF

BP-CRUF — The fully qualified file name of the CRT Authorization Retailer Usage File (CRUF). This assign is used only if CRT Authorization is installed in the BASE24-pos system and is required only if BASE24-pos CRT Authorization performs merchandise return accumulation and limit checking.

The BASE24-pos Device Handler/Router/Authorization process and the CRT Authorization Retailer Usage File (CRUF) Server process use this assign.

Example: \B24.\$DATA.PRO1DATA.CRUF

BP-CSEC — The fully qualified name of the CRT Authorization Security File (CSEC). This assign is used only if CRT Authorization is installed in the BASE24-pos system and is required only if the CRT operators perform functions from the Online Transaction screen and the POS Referral File (PRF) screen.

The BASE24-pos CRT Authorization Device Handler module uses this assign.

Example: \B24.\$DATA.PRO1DATA.CSEC

BP-INEG — The fully qualified file name of the INAS National Negative File (INEG) for MasterCard. This assign is required only if the BASE24-pos product checks the INEG prior to routing transactions to the MasterCard Interchange. This assign is used by the following processes:

National Negative Card File (NNF) Server process
INAS National Negative File (INEG) Refresh process
BASE24-pos Device Handler/Router/Authorization process

The BASE24-pos Router module reads this assign during initialization. The INAS National Negative File (INEG) Refresh process uses the file attributes of the template file indicated in the assign to create a new INEG during a full-file refresh of the file.

Example: \B24.\$DATA.PRO1DATA.INEG (data file name)
 \B24.\$DATA.PRO1TPLT.INEG (template file name)
Template File: Required to build the INEG during full-file refreshes.

BP-INR — The fully qualified file name of the INAS National Range File (INR) for MasterCard. The BP-INR assign is required only if BASE24-pos checks the INR prior to routing transactions to the MasterCard Interchange. The INEG Refresh process and the BASE24-pos Device/Router/Authorization process use this assign.

The BASE24-pos Router module attempts to read the assign during initialization. The INEG Refresh process uses the file attributes of the template file indicated in the assign to create a new INR during full-file refreshes of the national range file.

Example: \B24.\$DATA.PRO1DATA.INR (data file name)
 \B24.\$DATA.PRO1TPLT.INR (template file name)
Template File: Required to build the INR during full-file refreshes.

BP-RPTR — The spooler location to which to send refresh reports for the Base National Negative File (BNEG) and INAS National Negative File (INEG). This assign is required only if the BASE24-pos product uses national negative files or national range files. The Base National Negative File (BNEG) Refresh process and the INAS National Negative File (INEG) Refresh process use this assign when refreshing a national negative file.

Example: \B24.\$S.#NEGREF

BP-RTBL — The fully qualified file name of the Routing Table File (RTBL) used for the BASE24-pos product. The Routing Table File (RTBL) Server process and the BASE24-pos Device Handler/Router/Authorization process use this assign. The BASE24-pos Router module reads this assign during initialization.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-pos Device Handler/Router/Authorization process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.RTBL

CRT-ADMN-AQF — The fully qualified file name of the Administrative Queue File (AQF). This assign is required for logical networks that have BASE24-pos CRT Administration Device Handler/Router/Authorization processes. The BASE24-pos CRT Device Handler/Router/Authorization process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-pos CRT Device Handler/Router/Authorization process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.AQF

CRT-AUTH-CHF — The fully qualified file name of the Card History File (CHF). This assign is required for logical networks that have BASE24-pos CRT Authorization Device Handler/Router/Authorization processes. The Enscribe Refresh process uses the file attributes of the template file indicated in this assign to create a new CHF during a full-file refresh of the file.

Example: \B24.\$DATA.PRO1DATA.CHF (data file name)
 \B24.\$DATA.PRO1TPLT.CHF (template file name)
Template File: Required to build the CHF during full-file refreshes.

CRT-AUTH-PRF — The fully qualified file name of the POS Referral File (PRF). This assign is required only for logical networks that have BASE24-pos CRT Authorization/Administration Device Handler/Router/Authorization processes. This assign is used by the following processes:

BASE24-pos Main Settlement process
BASE24-pos Device Handler/Router/Authorization process
POS Referral File Server process

If this assign is not present in the LCONF or contains an invalid value, the BASE24-pos Authorization module does not write transactions that receive referral response codes to the PRF, and the BASE24-pos CRT Authorization module is unable to retrieve the transactions from the PRF to perform its processing.

Example: \B24.\$DATA.PRO1DATA.FFYMMDD

CRT-AUTH-TQF — The fully qualified file name of the Terminal Queue File (TQF). This assign is required only for logical networks that have BASE24-pos CRT Device Handler/Router/Authorization processes.

Example: \B24.\$DATA.PRO1DATA.TQF

CRT-AUTH-TQFT — The fully qualified file name of the TQF Token File (TQFT) used to contain token data. This assign is used in logical networks with BASE24-pos CRT Authorization Device Handler/Router/Authorization processes that use the TQFT as the token retrieval option.

This assign is required only when the CRT-AUTH-TKN-RETRV-OPT param is set to a value of 1 and the TQFT is used to store tokens.

Example: \B24.\$DATA.PRO1DATA.TQFT

KEYD — The fully qualified file name of the Derivation Key File (KEYD). The BASE24-pos Device Handler/Router/Authorization process uses this assign for the BASE24-pos Standard POS Device Handler module when ACI standard POS terminals use derived unique key per transaction (DUKPT) security for PINs.

Example: \B24.\$DATA.PRO1DATA.KEYD

POS-ALTKEY-SCRATCH-FILE — The fully qualified file name of the alternate key scratch file. The Main Settlement process uses this assign to create the obey files that start the BASE24-pos report programs.

Example: \B24.\$DATA.PRO1DATA.FILE

POS-CARD-OBEYFILE — The fully qualified file name of the obey file for BASE24-pos reports. The Main Settlement process uses this assign. This assign is required if the Main Settlement process is to produce BASE24-pos reports. If this assign is not present in the LCONF or contains an invalid value, BASE24-pos reports are not produced.

Example: \B24.\$DATA.PRO1DATA.RCYMMDD

POS-CART — The fully qualified file name of the Check Authorization Routing Table File (CART) used by the BASE24-pos Device Handler/Router/Authorization process when processing check guarantee or check verification transactions and by the Check Authorization Routing Table File (CART) Server process. This assign is required if check guarantee or check verification transactions are to be routed or authorized by BASE24-pos. If this assign is not configured, check guarantee and check verification transactions to be routed to the host or an interchange for authorization, or authorized by BASE24-pos, are denied.

Example: \B24.\$DATA.PRO1DATA.CART

POS-DAILY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Daily Transaction Volume Report program. The naming convention for this assign is \$S.#PSD*mmdd*, where *mmdd* is the month and day for which the report was run. The Transaction Based Pricing Report Initiator process uses this assign. This assign is not required. If it is not configured, the Daily Transaction Volume Report is sent to the EMS log rather than a spooler location, and a daily record is still written to the Monthly Totals Accumulation File (MTAF).

Example: \$S.PSD0101

POS-DAILY-REPORT-OBEYFILE — The fully qualified file name of the obey file to run the Daily Transaction Volume Report program. The naming convention for this obey file is `PSDR $mmdd$` , where $mmdd$ is the month and day for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \B24.\$DATA.PSDR0101

POS-DAILY-REPORT-PROGRAM — The fully qualified file name of the POS Daily Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, xx is the number of the current release.

Example: \B24.\$BA xx TBP.PSDRPT

POS-DH-PTD-EXTMEM-SWAPVOL — The fully qualified name of the BASE24-pos Terminal Data files extended memory swap volume used by the following BASE24-pos Device Handler modules to temporarily store data when building extended memory for the BASE24-pos Terminal Data files:

Standard POS Device Handler (SPDH)
Hypercom Device Handler (HPDH)

If this assign is not present in the LCONF or contains an invalid value, the HP NonStop operating system assigns a swap volume location.

Example: \B24.\$DATA

POS-EAF — The fully qualified file name of the E-Commerce Authentication File (EAF). The BASE24-pos Device Handler/Router/Authorization and Settlement Initiator processes use this assign for secure Internet validation processing.

This assign is required only when the POS-EAF-PREV assign is present.

Example: \B24.\$DATA.PRO1DATA.EAF

POS-EAF-PREV — The fully qualified file name of the previous E-Commerce Authentication File (EAF). The BASE24-pos Device Handler/Router/Authorization and Settlement Initiator processes use this assign for secure Internet validation processing.

This assign is required only when the POS-EAF assign is present.

Example: \B24.\$DATA.PRO1DATA.EAFPREV

POS-HPDH-HPCF — The fully qualified file name of the Hypercom Configuration File (HPCF) used by the BASE24-pos Hypercom Device Handler module. This assign is required for all logical networks that have Hypercom T4, T5, and T6 devices. The Hypercom Configuration File (HPCF) Server process and the BASE24-pos Hypercom Device Handler (HPDH) module use this assign. The HPDH module reads this assign during initialization.

Example: \B24.\$DATA.PRO1DATA.HPCF

POS-HPDH-HPTC — The fully qualified file name of the Hypercom T7 Configuration File (HPTC) used by the BASE24-pos Hypercom Device Handler (HPDH) module. This assign is required for all logical networks that have Hypercom T7 devices. The Hypercom T7 Configuration File (HPTC) Server process and the BASE24-pos Hypercom Device Handler (HPDH) module use this assign. The HPDH module reads this assign during initialization.

Example: \B24.\$DATA.PRO1DATA.HPTC

POS-MONTHLY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Monthly Transaction Volume Report program. The naming convention for this location is \$\$.#PSMyymm, where *yymm* is the year and month for which the report was run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \$\$PSM0112

POS-MONTHLY-REPORT-OBEYFILE — The fully qualified file name of the obey file to run the Monthly Transaction Volume Report program. The naming convention for this obey file is `PSMRyymm`, where *yymm* is the year and month for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: `\B24.$DATA.PSMR0112`

POS-MONTHLY-REPORT-PROGRAM — The fully qualified file name of the POS Monthly Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, *xx* is the number of the current release.

Example: `\B24.$BAxxTBP.BAMRPT`

POS-MTAF — The fully qualified file name of the Monthly Totals Accumulation File (MTAF). The naming convention for this file is `PSMTyymm`, where *yymm* is the year and month for which the totals in the file were accumulated. The name of the subvolume where this file resides must be eight characters in length. The Transaction Based Pricing Report Initiator, POS Daily Transaction Volume Report, and Monthly Transaction Volume Report processes use this assign.

If this assign is not present in the LCONF or contains an invalid value, the processes listed above abend.

Example: `\B24.$DATA.PRO1DATA.PSMT0112`

Template File: Required (for example, `\B24.$DATA.PRO1TPLT.PSMTyymm`) by the Transaction Based Pricing Report Initiator process.

POS-PIRF — The fully qualified file name of the POS Institution Reporting File (PIRF). The PIRF contains information used to generate the periodic institution summary report. The BASE24-pos report programs use this assign. This assign is required for the Daily Network Settlement Report (B24PS01) or if periodic reports are to be produced.

Example: \B24.\$DATA.PRO1DATA.PIRF

POS-PRDF — The fully qualified file name of the POS Retailer Definition File (PRDF). The PRDF contains information on each retailer participating in the BASE24-pos system. This assign is required and used by the following processes:

POS Retailer Definition File (PRDF) Server process
Enscribe Refresh process
Super Extract process
BASE24-pos report programs
BASE24-pos Device Handler/Router/Authorization process
BASE24-pos Secondary Settlement processes

The BASE24-pos Router module reads this assign during initialization. This assign is required for BASE24-pos report programs that generate daily or periodic retailer reports.

Example: \B24.\$DATA.PRO1DATA.PRDF

POS-PRRF — The fully qualified file name of the POS Retailer Reporting File (PRRF). The BASE24-pos report programs use this assign to access the PRRF and obtain reporting information to generate reports.

This assign is required for BASE24-pos report programs that generate daily or periodic retailer reports.

Example: \B24.\$DATA.PRO1DATA.PRRF

POS-PTD-DYN-GNRL — The fully qualified file name of the BASE24-pos Terminal Data Dynamic File—general data (PTDD1). This file contains dynamic core terminal data (i.e., data common to all types of devices that is subject to change), device information (i.e., data specific to a device type), and device-dependent data (i.e., data specific to each terminal defined). Key PSTM fields for the last transaction processed for a device are also stored in this file. The Standard

POS Device Handler and Hypercom Device Handler modules use this assign to read and update dynamic terminal data as transactions are processed. The following processes and modules use this assign:

BASE24-pos Device Handler/Router/Authorization process
BASE24-pos Terminal Data files Server object
Generic Simulator process
Hypercom Device Handler module
Secondary Settlement process
Standard POS Device Handler module

Example: \B24.\$DATA.PRO1DATA.PTDD1

POS-PTD-DYN-SCRATCH-PAD — The fully qualified file name of the BASE24-pos Terminal Data Dynamic File—scratch pad (PTDD2). This file contains dynamic token data for reversal processing. This assign is optional. If this assign is used, the Standard POS Device Handler and Hypercom Device Handler modules store and retrieve token data from the PTDD2. If this assign is not used, data for reversal processing is obtained from last transaction data in the POS Transaction Log File (PTLF). The following processes and modules use this assign:

BASE24-pos Device Handler/Router/Authorization process
Hypercom Device Handler module
Standard POS Device Handler module

Example: \B24.\$DATA.PRO1DATA.PTDD2

POS-PTD-EXTMEM-SWAPVOL — The fully qualified name of the BASE24-pos Terminal Data files extended memory swap volume. The following processes use this assign to temporarily store data when building extended memory:

BASE24-pos Terminal Data files Server object
BASE24-pos Transaction Analysis utility

If this assign is not present in the LCONF or contains an invalid value, the HP NonStop operating system assigns a swap volume location.

Example: \B24.\$DATA

POS-PTD-STATIC-GNRL — The fully qualified file name of the BASE24-pos Terminal Data Static File—general data (PTDS1). This file contains static data, which is information that does not change during the course of transaction processing. The Standard POS Device Handler and Hypercom Device Handler modules use this assign to retrieve static terminal data, which is maintained in extended memory. The following processes and modules use this assign:

BASE24-pos Device Handler/Router/Authorization process
BASE24-pos Terminal Data files Server object
Hypercom Device Handler module
Standard POS Device Handler module

Example: \B24.\$DATA.PRO1DATA.PTDS1

POS-PTDF — The fully qualified file name of the BASE24-pos Terminal Data File (PTDF). This assign is used by the following processes:

Generic Simulator process
BASE24-pos Terminal Data files Server object
BASE24-pos Secondary Settlement process
Mail Box Address File Server process (if BASE24-mail is installed)
Mail process (if BASE24-mail is installed)
BASE24-pos Transaction Analysis utility
BASE24-pos Device Handler/Router/Authorization process, except for those containing a Standard POS Device Handler or Hypercom Device Handler module

The BASE24-pos Device Handler modules read this assign during initialization. The Secondary Settlement process uses this assign to access the PTDF and obtain cutover information.

Example: \B24.\$DATA.PRO1DATA.PTDF

POS-PTLF — The fully qualified file name of the BASE24-pos Transaction Log File (PTLF). This assign is used by the following processes:

Customer Service Transaction Perusal Server process
Main and Secondary Settlement processes
POS Daily Transaction Volume Report process
POS Transaction Log File (PTLF) Server process
Encube Refresh process
Super Extract process
BASE24-pos report programs
BASE24-pos Main and Secondary Settlement processes

BASE24-pos Transaction Analysis utility

BASE24-pos Device Handler/Router/Authorization process (The BASE24-pos Router module reads the assign during initialization.)

When using dual site processing, the Enscribe Refresh process and the Super Extract process can use process-specific PTLFs.

This assign is required.

Example: \B24.\$DATA.PRO1PTLF.POYYMMDD (data file name)
 \B24.\$DATA.PRO1TPLT.POYYMMDD (template file name)
Template File: Required because BASE24 creates PTLFs periodically.

POS-RPT-2 — The spooler location to which to send the Daily Retailer Summary Report (B24POS11) and the Daily Retailer Activity Report (B24POS12). The BASE24-pos report program that generates these two reports uses this assign.

The default spooler location for this assign is specified in the PRINT LOCATION field on screen 5 of the POS Retailer Definition File (PRDF). If this field is not configured or is invalid, a default location of \$S.#RETL is used.

Example: \B24.\$S.#RPT2
Assign Default: Print location from PRDF or \$S.#RETL.

POS-RPT-21 — The spooler location to which to send the Periodic Institution Summary Report (B24POS21). The BASE24-pos report program that generates the B24POS21 report uses this assign.

Assign Default: \$S.#RPT21

POS-RPT-22 — The spooler location to which to send the Periodic Retailer Summary Report (B24POS22). The BASE24-pos report program (SVPS22) that generates the B24POS22 report uses this assign.

Assign Default: \$S.#RPT22

POS-RPT-2R — The spooler location to which to send the Daily Retailer Exception Detail Report (B24POS12-EXPT). The BASE24-pos report program that generates the Daily Retailer Activity Report (B24POS12), the Daily Retailer Summary Report (B24POS11), and the Daily Retailer Exception Report (B24POS12-EXPT) use this assign.

Assign Default: \$S.#EXPT12

POS-RPT-30 — The spooler location to which to send the Network Referral Statistical Report (B24POS30). The BASE24-pos report program that generates the B24POS30 report uses this assign.

Assign Default: \$S.#RPT30

POS-RPT-35 — The spooler location to which to send the Daily Retailer Reconciliation Report (B24POS35). The BASE24-pos report program that generates the B24POS35 report uses this assign.

Assign Default: \$S.#RPT35

POS-RPT-ERR-FILE — The spooler location to which report error messages generated by the BASE24-pos report programs are sent. This assign is required for all BASE24-pos logical networks. The BASE24-pos report programs and the Main Settlement process use this assign.

Example: \B24.\$S.#POSERR

POS-SETL-PTD-EXTMEM-SWAPVOL — The fully qualified name of the BASE24-pos Terminal Data files extended memory swap volume. The Secondary Settlement processes use this assign to temporarily store data in extended memory.

If this assign is not present in the LCONF or contains an invalid value, the HP NonStop operating system assigns a swap volume location.

Example: \B24.\$DATA

POS-SETL-RPT-1 — The spooler location for the Daily Network Settlement Report (B24POS01). The BASE24-pos report program that generates the B24POS01 report uses the POS-SETL-RPT1 assign.

Assign Default: \$S.#ISR

POS-SETL-RPT-1R — The spooler location to which to send the Daily Cardholder Exception Detail Report (B24POS02-EXPT). The BASE24-pos report program that generates the Daily Cardholder Activity Report (B24POS02) and the Daily Cardholder Exception Detail Report (B24POS02-EXPT) uses this assign.

Assign Default: \$S.#EXPT2

POS-SETL-RPT-PROG-1-NAME — The fully qualified file name of the program that generates the Daily Network Settlement Report (B24POS01), the Daily Cardholder Activity Report (B24POS02), and the Daily Cardholder Exception Detail Report (B24POS02-EXPT). The Main Settlement process uses this assign to create the obey file that generates these BASE24-pos reports.

This assign is required only if the B24POS01, B24POS02, and B24POS02-EXPT reports are to be produced. If this assign is not present in the LCONF or contains an invalid value, these reports are not generated.

Example: \B24.\$DATA.PSxxOBJ.B24PS1, where xx is the number of the current release

POS-SETL-RPT-PROG-2-NAME — The fully qualified file name of the program that generates the Daily Retailer Summary Report (B24POS11), the Daily Retailer Activity Report (B24POS12), and the Daily Retailer Exception Detail Report (B24POS12-EXPT). The Main Settlement process uses this assign to create the obey file that generates these BASE24-pos reports.

This assign is required only if the B24POS11, B24POS12, and B24POS12-EXPT reports are to be produced. If this assign is not present in the LCONF or contains an invalid value, these reports are not generated.

Example: \B24.\$DATA.PSxxOBJ.B24PS2, where xx is the number of the current release

POS-SETL-RPT-PROG-4-NAME — The fully qualified file name of the program that generates the Daily Clerk Totals Report (B24POS04). The Main Settlement process uses this assign to create the obey file that generates this BASE24-pos report.

This assign is required only if the B24POS04 report is to be produced. If this assign is not present in the LCONF or contains an invalid value, this report is not generated.

Example: \B24.\$DATA.PSxxOBJ.B24PS4, where xx is the number of the current release

POS-SETL-RPT-PROG-5-NAME — The fully qualified file name of the program that generates the Daily Disputed Transaction Report (B24POS05). The Main Settlement process uses this assign to create the obey file that generates this BASE24-pos report.

This assign is required only if the B24POS05 report is to be produced. If this assign is not present in the LCONF or contains an invalid value, this report is not generated.

Example: \B24.\$DATA.PSxxOBJ.B24PS5, where xx is the number of the current release

POS-SETL-RPT-PROG-30-NAME — The fully qualified file name of the program that generates the Network Referral Statistical Report (B24POS30) for CRT Authorization. The Main Settlement process uses the POS-SETL-RPT-PROG-30-NAME assign to create the obey file that generates this BASE24-pos report.

The assign is required only if the B24POS30 report is to be produced. If this assign is not present in the LCONF or contains an invalid value, this report is not generated.

Example: \B24.\$DATA.BPxxOBJ.B24RP30, where xx is the number of the current release

POS-SETL-RPT-PROG-35-NAME — The fully qualified file name of the program that generates the Daily Retailer Reconciliation Report (B24POS35). The Main Settlement process uses this assign to create the obey file that generates this BASE24-pos report.

This assign is required only if the B24POS35 report is to be produced. If this assign is not present in the LCONF or contains an invalid value, this report is not generated.

Example: \B24.\$DATA.PSxxOBJ.B24PS35, where xx is the number of the current release

POS-SPDH-ACNF — The fully qualified file name of the ACI Standard Configuration File (ACNF). This file is required for all logical networks that have the BASE24 Standard POS Device Handler (SPDH) module. The ACI Standard Device Configuration File (ACNF) Server process and the SPDH module use this assign.

Example: \B24.\$DATA.PRO1DATA.ACNF

POS-SPDH-ARSP — The fully qualified file name of the ACI Standard Device Response File (ARSP). This file is required for all logical networks that have the BASE24 Standard POS Device Handler (SPDH) module. The ACI Standard Device Response File (ARSP) Server process and the BASE24-pos Device Handler/Router/Authorization process use this assign.

Example: \B24.\$DATA.PRO1DATA.ARSP

POS-SV-CPF-EXTMEM-SWAPVOL — The fully qualified name of the swap volume in which the BASE24-pos Stored Value Dormancy/Escheatment program temporarily stores data from the CPF when building extended memory.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-pos Stored Value Dormancy/Escheatment program uses the volume in which it resides.

Example: \B24.\$\$SWAP

POS-SV-DORMANCY-RPT — The spooler location to which to send the Dormancy report. The BASE24-pos Stored Value Dormancy/Escheatment program uses this assign.

Default: \$S.#DORMRPT

POS-SV-ESCHEATMENT-RPT — The spooler location to which to send the Escheatment report. The BASE24-pos Stored Value Dormancy/Escheatment program uses this assign.

Default: \$S.#ESCHRPT

POS-SV-IDF-EXTMEM-SWAPVOL — The fully qualified name of the swap volume in which the BASE24-pos Stored Value Dormancy/Escheatment program temporarily stores data from the IDF when building extended memory.

If this assign is not present in the LCONF or contains an invalid value, the Stored Value Dormancy/Escheatment program uses the volume in which it resides.

Example: \B24.\$SWAP

POS-SV-PTLF-EXTMEM-SWAPVOL — The fully qualified name of the swap volume in which the BASE24-pos Stored Value Dormancy/Escheatment program temporarily stores data from the PTLF when building extended memory.

If this assign is not present in the LCONF or contains an invalid value, the Stored Value Dormancy/Escheatment program uses the volume in which it resides.

Example: \B24.\$SWAP

POS-SV-RETAIL-EXTMEM-SWAPVOL — The fully qualified name of the swap volume in which the BASE24-pos Stored Value Dormancy/Escheatment program temporarily stores data from the PRDF when building extended memory.

If this assign is not present in the LCONF or contains an invalid value, the Stored Value Dormancy/Escheatment program uses the volume in which it resides.

Example: \B24.\$SWAP

POS-SV-SVDF-EXTMEM-SWAPVOL — The fully qualified name of the swap volume in which the BASE24-pos Stored Value Dormancy/Escheatment program temporarily stores data from the SVDF when building extended memory.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-pos Stored Value Dormancy/Escheatment program uses the volume in which it resides.

Example: \B24.\$SWAP

POS-SVDF — The fully qualified file name of the BASE24-pos Stored Value Dormancy File (SVDF). The SVDF contains dormancy configuration parameters. This assign is used by the following processes:

POS Stored Value Dormancy File (SVDF) server process
BASE24-pos Stored Value Dormancy/Escheatment program

This assign is required.

Example: \B24.\$DATA.PRO1DATA.SVDF

POS-SVHF — The fully qualified file name of the Stored Value History File (SVHF). Transactions using a stored value card are logged to this file when the BASE24-pos Stored Value add-on product is installed. If transactions are routed to an interchange for authorization, logging to this file is optional. The following processes use this assign:

BASE24-pos Device Handler/Router/Authorization process (The BASE24-pos Router module reads the assign during initialization.)
BASE24-pos Stored Value Dormancy/Escheatment program
History File Cleanup module (HFCLUP)
Net Position Report program.

Example: \B24.\$DATA.PRO1DATA.SVHF

POS-TRN-THF — The fully qualified file name of the Transaction Analysis Transaction History File (THF). The THF is a report file that contains reports produced by the BASE24-pos Transaction Analysis utility. The BASE24-pos Transaction Analysis utility is part of the BASE24 Performance Tools.

This assign is required when running the BASE24 Performance Tools.

Example: \B24.\$DATA.PRO1DATA.THF

RCDF — The fully qualified file name of the Response Code Description File (RCDF). The RCDF defines ISO and BASE24 Response code descriptions. Values in this file override BASE24 response code descriptions in the ACI Standard Response File (ARSP). The following modules and processes use this assign:

Response Code Description File Server process
Base Extended Memory Table Build utility
BASE24-pos Standard POS Device Handler module

Example: \B24.\$DATA.PRO1DATA.RCDF

RCDFEMT — The fully qualified file name of the Response Code Description File (RCDF) extended memory table, which contains RCDF records. The following modules and processes use this assign:

Base Extended Memory Table Build Utility
BASE24-pos Standard POS Device Handler module

Example: \B24.\$DATA.PRO1DATA.RCDFEMT

Params

The following params are used exclusively by the BASE24-pos product. Each of the following params should have the usage code POS (and only the code POS) entered in the USAGE CODES field on the LNCF Param screen.

ADJ-ADVICE-RC — A code used by the ISO Host Interface process to specify for outgoing BASE24-pos 0220 adjustment messages whether the transaction response code or reversal code is to be included in the P-39 (Response Code) data element of the external message. Typically, only a response code or reversal code (one or the other) is present and meaningful for a transaction. For example, in a normal response message, the response code is present and meaningful, and in an approved adjustment/reversal request/advice, the reversal code is present and meaningful. However, in the case of declined adjustment advices, both a reversal code (the reason for the adjustment) and a response code (the reason for the decline) are present in the PSTM. Since declined adjustments are supported by BASE24-pos and can be sent to a host, hosts are provided the option of including the response code or reversal code in the P-39 external message data element for 0220 adjustment messages. Valid values are as follows:

- 1 = Reversal code. Default.
- 2 = Reversal code for approved advices, response code for declined advices
- 3 = Response code

CRT-ADMN-APPRV-CDE-LGTH — A code specifying the approval code length that the BASE24-pos CRT Device Handler/Router/Authorization process generates for administrative transactions. Only CRT Administration Device Handler modules use this param. Valid values are 2 through 6.

Param Default: 6

CRT-ADMN-MAX-AQFS — The maximum number of Administrative Queue File (AQF) records that the BASE24-pos CRT Device Handler/Router/Authorization process can store in memory at one time. Only CRT Administrative Device Handler modules use this param. Valid values include any numeric value greater than zero.

Param Default: 75

CRT-AUTH-APPRV-CDE-LGTH — A code specifying the approval code length that the BASE24-pos CRT Device Handler/Router/Authorization process generates when authorizing a transaction. Only CRT Authorization Device Handler modules use this param. Valid values are 2 through 6.

Param Default: 6

CRT-AUTH-MAX-CRUF — The maximum number of CRT Authorization Retailer Usage File (CRUF) records that a BASE24-pos CRT Device Handler/Router/Authorization process can store in memory at one time. Only CRT Authorization Device Handler modules use this param. Valid values include any numeric value greater than zero.

Param Default: 75

CRT-AUTH-MAX-TQFS — The maximum number of Transaction Queue File (TQF) records that the BASE24-pos CRT Authorization Device Handler module can store in memory at one time. Only CRT Authorization Device Handler modules use this param. Valid values include any numeric value greater than zero.

Param Default: 75

CRT-AUTH-MAX-TQFTS — The maximum number of TQF Token File (TQFT) records the BASE24-pos CRT Authorization Device Handler module can store in memory at one time. Only the CRT Authorization Device Handler modules use this param. Valid values include any numeric value greater than zero.

Param Default: 75

CRT-AUTH-RESP-TIMEOUT — The number of seconds that the BASE24-pos CRT Administration or CRT Authorization Device Handler module waits for an authorization response to a transaction request message before sending an unable to process response message. Valid values include any numeric value greater than zero. The BASE24-pos Device Handler/Router/Authorization process uses this param. The BASE24-pos CRT Administration and CRT Authorization Device Handler modules read this param.

Read By: A symbolic name (for example, P1A^CRT01) is required in this field if this value varies among BASE24-pos Device Handler/Router/Authorization processes.

Param Default: 30

CRT-AUTH-TKN-RETRV-OPT — A code indicating where tokens from approved responses are stored. The tokens are appended to reversal messages, if necessary. The BASE24-pos CRT Authorization Device Handler module uses this param. Valid values are as follows:

- 0 = No token data is stored on responses or added to reversals.
- 1 = Token data is stored in and retrieved from the TQF or TQFT. If the TQFT is not being used (i.e., the CRT-AUTH-TQFT assign is not present or is invalid), the token data is stored in and retrieved from the TQF.
- 2 = Token data is stored in and retrieved from the PTLF record associated with this transaction.

Param Default: 1

ENHNC-PRE-AUTH-COMP-TIME — The amount of time, in minutes, the terminal has to send a preauthorization hold completion transaction to the acquirer for enhanced preauthorization hold processing. This param is used by the Device Handler/Router/Authorization process. Valid values are 0 through 32767.

Param Default: 120

ENHNC-PRE-AUTH-HLD-STORE-TIME — The amount of time that the enhanced preauthorization hold transaction is stored on the Usage Accumulation File (UAF) or Cardholder Authorization File (CAF).

The first position of this param identifies the hold increment. Valid values for this position are as follows:

- 0 = Minutes
- 1 = Hours
- 2 = Days

The second and third positions of this param indicate the units of time specified in the first position. Valid values are 00 through 99.

The BASE24-pos Device Handler/Router/Authorization processes use this param.

Param Default: No default value

FREQ-SHOP-QUEUE — The symbolic name of the service where all messages routed to the BASE24-frequent shopper product are sent. The BASE24-pos Device Handler/Router/Authorization process uses this param when the BASE24-frequent shopper product is used in conjunction with the BASE24-pos product.

Example: FSAUTH
Param Default: No default value

POS-A4000-MASTER — The symbolic name of the BASE24-pos Device Handler/Router/Authorization process (for example, P1A^RTAU01) responsible for downloading Diebold number tables (DNTs) from the Key Authorization File (KEYA) to an Atalla Network Security Processor (NSP) model A8000 or A8100 during process initialization and process warmboots. The A8000 and A8100 security devices fail when more than one Authorization module attempts to load DNTs during initialization or warmboots. This param is required only when using a model A8000 or A8100 security device with the BASE24-pos product.

The BASE24-pos Device Handler/Router/Authorization processes use this param.

Param Default: No default value

POS-ACQ-AVS-DATA-SUPPRS — A flag indicating whether logging address verification data for acquirer transactions to the POS Transaction Log File (PTLF) should be suppressed. The BASE24-pos Router/Authorization module uses this param. Valid values are as follows:

Y = Yes, suppress logging of address verification data.
N = No, do not suppress logging of address verification data.

Param Default: N

POS-ACQ-CVD2-DATA-SUPPRS — A flag indicating whether logging card verification data for acquirer transactions to the POS Transaction Log File (PTLF) should be suppressed. The BASE24-pos Router/Authorization module uses this param. Valid values are as follows:

Y = Yes, suppress logging of card verification data.
N = No, do not suppress logging of card verification data.

Param Default: N

POS-ACQ-DISCR-DATA-SUPPRS — A flag indicating whether logging discretionary data for acquirer transactions to the POS Transaction Log File (PTLF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. The BASE24-pos Router/Authorization module uses this param. Valid values are as follows:

Y = Yes, suppress logging of discretionary data.

N = No, do not suppress logging of discretionary data.

Param Default: N

POS-APDH-AUTH-DUP-TIMEOUT — The number of seconds the APACS 30/40 Device Handler module adds to the current time to determine whether a transaction with the same message number, dial indicator, card number, and transaction amount as the previously authorized transaction is in a duplicate time window. The current time plus the value of this param is compared to the transaction time.

An authorization request is classified as a duplicate message if it meets the criteria described above and is within the same time window as the previously received authorization message, by adding the value of this param to the transaction time.

Param Default: 10

POS-APDH-CONFIRM-FLAG — A flag indicating whether confirmation messages are required from APACS 30/40 terminals. If this param is set to Y, the APACS 30/40 Device Handler module sets the CONFIRMATION-REQUEST field in the response message to the device to a value of 1. Valid values are as follows:

Y = Yes, confirmation messages are required.

N = No, confirmation messages are not required.

Param Default: N

POS-APDH-CONFIRM-TIMEOUT — The number of seconds the APACS 30/40 Device Handler module waits for a confirmation message from the device before it times out. The APACS 30/40 Device Handler module uses this param. Valid values are 0 through 999999999.

Param Default: 15

POS-APDH-DISCONNECT-ON-ERROR — A flag indicating whether the APACS 30/40 Device Handler module disconnects the station when the module encounters an error while attempting to process a request from an APACS 30/40 terminal. Valid values are as follows:

Y = Yes, disconnect the station when an error is encountered.

N = No, do not disconnect the station when an error is encountered.

If this param is set to any value other than N, it is treated like the value Y.

Param Default: Y

POS-APDH-EXTEND-RESP-TIMEOUT — The number of seconds to which the transaction response timer is reset for card prefixes identified in the POS-APDH-HOLD-MESSAGE-PREFIX param. Valid values are 0 through 999999999.

Param Default: 120

POS-APDH-HOLD-MESSAGE-PREFIX — A list of card prefixes for which the card issuers may want to use human intervention in an extended authorization scenario. The APACS 30/40 Device Handler module generates a hold message, sends it to the terminal, and resets the transaction response timer based on the value of the POS-APDH-EXTEND-RESP-TIMEOUT param for prefixes identified in this list. Up to 20 card prefixes can be defined, with each value separated by a semicolon (;).

Param Default: No default value

POS-APDH-LOG-APACS-DATA — A flag indicating whether additional APACS data is logged to the POS Transaction Log File (PTLF). If this param is set to a value of Y, the Confirmation Code, Balance Code, and Descriptive Data fields in the APACS 40 request message are appended to the user data in the POS Standard Internal Message (PSTM) for subsequent logging to the PTLF. The APACS 30/40 Device Handler module uses this param.

Y = Yes, log additional APACS data to the PTLF.

N = No, do not log additional APACS data to the PTLF.

Param Default: N

POS-APDH-POST-FLOOR-LIMIT — The post-floor limit, in whole currency units, to be sent to an APACS 30/40 terminal in cardholder response messages when the POS-APDH-USE-POST-FL-LIMIT param is set to a value of Y. Transactions with amounts less than or equal to this value will be authorized offline regardless of system availability. This param is used by the APACS 30/40 Device Handler module. Valid values are 0 through 999999999.

Param Default: 20

POS-APDH-PRE-FLOOR-LIMIT — The pre-floor limit, in whole currency units, to be sent to an APACS 30/40 terminal in cardholder response messages when the POS-APDH-USE-PRE-FL-LIMIT param is set to a value of Y. Transactions with amounts less than or equal to this value will be authorized offline regardless of system availability. This param is used by the APACS 30/40 Device Handler module. Valid values are 0 through 999999999.

Param Default: 10

POS-APDH-REFERRAL-PREFIX — A list of card prefixes for which the APACS 30/40 Device Handler module returns referral codes sent by card issuers to the terminal in addition to the Call Card Issuer Message. Up to 20 card prefixes can be defined, with each value separated by a semicolon (;).

Param Default: No default value

POS-APDH-STALE-REQ-TIMEOUT — The number of seconds an incoming transaction request can remain in the APACS 30/40 Device Handler module's queue before being discarded. This param is used by the APACS 30/40 Device Handler module. Valid values for this param are 10 through 180.

Param Default: 45

POS-APDH-USE-POST-FL-LIMIT — A flag indicating whether the value in the POS-APDH-POST-FLOOR-LIMIT param is returned to an APACS 30/40 terminal in cardholder response messages. This param is used by the APACS 30/40 Device Handler module. Valid values are as follows:

Y = Yes, include the post-floor limit in response messages.

N = No, do not include the post-floor limit in response messages.

Param Default: Y

POS-APDH-USE-PRE-FL-LIMIT — A flag indicating whether the value in the POS-APDH-PRE-FLOOR-LIMIT param is returned to an APACS 30/40 terminal in cardholder response messages. This param is used by the APACS 30/40 Device Handler module. Valid values are as follows:

Y= Yes, include the pre-floor limit in response messages.

N= No, do not include the pre-floor limit in response messages.

Param Default: Y

POS-AST-RECSIZE — The average size of a record, in bytes, in the Authorization Selection Table File (AST). During Device Handler/Router/Authorization initialization, this param is used to calculate the amount of extended memory required to hold all of the AST records. This param should be used if any AST records contain more than one service entry and are, therefore, longer than 348 bytes. Valid values are 348 through 1888.

To minimize the amount of extended memory required, this value should estimate the average length of the AST records used by the BASE24-pos Device Handler/Router/Authorization process.

Param Default: 348

POS-B24-TO-POS-ACCT-SUPPRS — Specifies whether the account type in the BASE24-pos Standard Internal Message (PSTM) should be suppressed when the PSTM is mapped to the external message. The BIC ISO Interface process suppresses the account type from the PSTM by using an account type of zeroes in the external message. Valid values are as follows:

Y= Suppress

N= Do not suppress (default)

POS-CAFPBF-RET-PERIOD — The number of days for which expired records are retained in the Cardholder Authorization File (CAF) and Positive Balance File (PBF) when the CAF/PBF Cleanup process (CAFPBF) is run. This param is required when the BASE24-pos Stored Value add-on product is installed.

The CAF/PBF Cleanup process uses this param. Valid values are 1 through 32767.

The CAF/PBF Cleanup process (CAFPBF) deletes records from the CAF and PBF when the following criteria are met:

- The CAF record is expired and the expiration date no longer falls within the retention period specified by this param.
- The card type for the CAF record is set to a value of SN or SR for stored value cards.
- The PBF balance for the account is 0 or the PBF fails with an end of file error.
- The expiration date for the account record in the CAF is not equal to 0000. A value of 0000 indicates that the stored value card does not expire.

Param Default: No default value

POS-CART-RECSIZE — The average size of a record, in bytes, in the Check Authorization Routing Table File (CART). The CART is used for check guarantee/verification transaction processing. The BASE24-pos Device Handler/Router/Authorization process uses this param only if processing check guarantee/verification transactions. Valid values are 86 through 1048. A value of 86 indicates one routing table entry per CART record.

Param Default: 86

POS-CHECK-LIMITS-FLAG — A flag indicating whether the Institution Definition File (IDF) prescreening limits are checked prior to checking merchandise refund limits. If this param is set to Y, the IDF prescreening limits will be checked to determine if the refund limits should be checked before going to the host. If this param is set to N, invalid, or missing, the IDF prescreening limits will not be checked and the refund limits will always be used to determine refund approval. Valid values are as follows:

Y = Yes, check the IDF prescreening limits prior to checking refund limits.

N = No, do not check IDF prescreening limits prior to checking refund limits.

Param Default: N

POS-CHRGBCK-NO-RESP-ORIG — Indicates whether the BASE24-pos Router module sends a response message to the transaction originator when it receives a card issuer reversal request (0402) message. This param is optional. If the value of this param is the same as the value of the TRAN.ORIG field of the

BASE24-pos Standard Internal Message (PSTM), the Router module does not send a response to the transaction originator. The BASE24-pos Device Handler/Router/Authorization process uses this param.

Param Default: No default value

POS-DH-AUTH-RESP-TIMEOUT — The number of seconds that the APACS 30/40 Device Handler module waits for an authorization response to a transaction request message before sending an unable to process response message to the device. Valid values include any numeric value greater than zero. The BASE24-pos Device Handler/Router/Authorization process uses this param. The APACS 30/40 Device Handler module reads this param.

The BASE24 Standard POS Device Handler (SPDH) module and the Hypercom POS Device Handler (HPDH) module do not use this param. The SPDH module determines the number of seconds it waits for an authorization response based on a setting in the ACI Standard Device Configuration File (ACNF). The HPDH module determines the number of seconds it waits for an authorization response based on the value of the POS-HPDH-AUTH-RESP-TIMEOUT param.

Read By: A symbolic name (for example, P1A^APACS01) is required in this field if this value varies among BASE24-pos Device Handler/Router/Authorization processes.

Param Default: 30

POS-DH-CONS-MAC-ERR-LMT — The number of consecutive security message authentication code (MAC) errors that can occur before the Device Handler module takes corrective action. Only the Merchant Host Interface (MHI) module, Standard POS Device Handler (SPDH) module, and Hypercom T7 Device Handler module are capable of taking corrective actions. After the number of consecutive security MAC errors specified in this param is reached, the Hypercom T7 Device Handler module indicates that a downline load is needed in the next message to the device. The MHI module generates a new MAC key and sends it in the next message to the device. When configured for MAC generation with DUKPT, the SPDH module generates an event message. When configured for MAC generation without DUKPT, the SPDH module generates a new MAC communications key and sends it in the next message to the device.

Valid values are 0 through 32000. A value of 0 indicates that Device Handler modules do not take any corrective actions regardless of the number of consecutive security MAC errors.

Read By: A symbolic name is required in this field if this value varies among Device Handler modules.

Param Default: 3

POS-DH-CUTOVER-LEAD-TIME — The number of minutes prior to the end of the retailer cutover window that the Device Handler module can start cutting over terminals whose cutover option is set to “DH Network Forced Cutover.” Valid values are any numeric value from 0 through the number of minutes from the start of the retailer window to the end of the retailer window. The Router module of the Device Handler/Router/Authorization process uses this param to determine when to notify the Device Handler module to cut over the terminals.

Param Default: 30

POS-DH-DUKPT-UPDATE-METHOD — A code indicating whether the Standard POS Device Handler (SPDH) module can automatically update the DATA ENCRYPTION TYPE field or the PIN ENCRYPTION TYPE field on BASE24-pos Terminal Data files (PTD) screen 7.

The DATA ENCRYPTION TYPE field can be updated to a value of 05 (full message encryption - DUKPT) or 06 (configurable message encryption - DUKUPT) when the Key Serial Number and Descriptor field (SubFID T of FID 6) is received in a message for the first time and a Derivation Key File (KEYD) record exists for the SPDH terminal. If the DATA ENCRYPTION TYPE field was set to 04 (configurable message encryption), then the module updates the field to 06 (configurable message encryption - DUKPT). Otherwise, if the DATA ENCRYPTION TYPE field was set to 00 (no encryption) or 03 (full message encryption), the module updates the field to 05 (full message encryption - DUKPT).

The PIN ENCRYPTION TYPE field can be updated to a value of 07 (DUKPT) when the Key Serial Number and Descriptor field (SubFID T of FID 6) is received in a message for the first time and a Derivation Key File (KEYD) record exists for the SPDH terminal.

Valid values are as follows:

Y= Yes, automatically update the PIN encryption or the data encryption method in the BASE24-pos Terminal Data files.

N= No, do not automatically update the PIN encryption or the data encryption method in the BASE24-pos Terminal Data files.

Param Default: N

POS-DH-ISO-RESP-CDE-FRMT — Controls which International Organization for Standardization (ISO) response code format is used in FID X of the POS standard message. The Standard POS Device Handler (SPDH) module uses this param. Valid values are as follows:

87 = Two-digit value based on the ISO 8583-1987 standard

93 = Three-digit value based on the ISO 8583-1993 standard

Param Default: 93

POS-DH-KEYD-READ-FROM-DISK — A code indicating whether the Standard POS Device Handler (SPDH) module reads the Derivation Key File (KEYD) from disk or from memory. Valid values are as follows:

Y= Yes, read the KEYD from disk.

N= No, do not read the KEYD from disk. The file is read from extended memory. The KEYD is loaded into extended memory during initialization.

Param Default: N

POS-DH-KSN-ANSI-STD-OPT — Controls the action taken by the Standard POS Device Handler (SPDH) module if the terminal follows the ANSI standard for KSN calculations. If this parameter is set, then the ANSI standard for validating the KSN value is used. If the parameter is missing or turned off, the SPDH code validates the KSN value as it has in the past.

Valid values are as follows:

Y = Use the ANSI standard for KSN calculations

N = Use the current standard for KSN calculations

Param Default: N

POS-DH-KSN-APPRV-OPT — Controls the action taken by the Standard POS Device Handler (SPDH) module if the static data received in the Key Serial Number (KSN) and Descriptor field (FID 6, subFID T) of a request message does not match the KSN static data maintained in PTD device dependent data. Valid values are as follows:

- 1 = Deny the transaction
- 2 = Approve the transaction but do not update the PTD key serial number (KSN)
- 3 = Approve the transaction and update the PTD key serial number (KSN)

Param Default: 3

POS-DH-KSN-CNTR-APPRV-OPT — Controls the action taken by the Standard POS Device Handler (SPDH) module if the difference in the transaction counter between two transactions from the same terminal exceeds the limit set in the POS-DH-KSN-MAX-DIFFERENCE param. The previous transaction counter is maintained in PTD device dependent data, and the current transaction counter is carried in the Key Serial Number (KSN) and Descriptor field (FID 6, subFID T) of the request message. Valid values are as follows:

- 1 = Deny the transaction
- 2 = Approve the transaction but do not update the PTD key serial number (KSN)
- 3 = Approve the transaction and update the PTD key serial number (KSN)

Param Default: 3

POS-DH-KSN-DESCR — The default key serial number (KSN) descriptor required by the Thales e-Security security device to perform a translate command when unique keys are derived per transaction at the terminal to encrypt the PIN block. The default KSN descriptor is a three-byte numeric value that contains the sum of the individual digits of the KSN minus the counter. For example, a KSN that is 16 bytes in length would have a KSN descriptor whose individual digits when added together would equal 11 (i.e., 16, the actual length of the KSN – the transaction counter). The KSN descriptor for a 16-byte KSN would then be 803 ($8 + 0 + 3 = 11$). The Standard POS Device Handler (SPDH) module uses this param.

Param Default: 644

POS-DH-KSN-MAX-DIFFERENCE — Indicates the largest allowable difference in the transaction counter between two transactions from the same terminal. The previous transaction counter is maintained in PTD device dependent data, and the current transaction counter is carried in the Key Serial Number

(KSN) and Descriptor field (FID 6, subFID T) of the request message. Valid values are 0 through 4096, where 0 indicates that no difference checking is performed. The Standard POS Device Handler module uses this param.

Param Default: 4096

POS-DH-KSN-SAVE-OPT — Controls the action taken by the Standard POS Device Handler (SPDH) module if an out-of-sequence transaction occurs and disrupts Key Serial Number (KSN) counter incrementing. In an out-of-sequence transaction, the KSN is not restored on the following transaction (because the terminal corrects the sequence number and resends the transaction), causing a duplicate KSN to be generated. Valid values for this param are as follows:

Y = Yes, save the previous transaction's KSN and restore it.

N = No, do not save the previous transaction's KSN and do not restore it.

Param Default: N

POS-DH-LMT-EXCEED-DISP — A code indicating the action taken by the Device Handler module when the return or adjustment limits are exceeded for a transaction. The following Device Handler modules use this param:

APACS 30/40 Device Handler module
Merchant Host Interface module
Standard POS Device Handler module

Valid values are as follows:

0 = Continue processing.

1 = Deny the transaction.

2 = Refer the transaction.

Param Default: 0

POS-DH-MAC-ADMIN-WITH-KEY — Indicates the action taken in applying the Message Authentication Code (MAC) on administrative transactions. When formatting a response message pertaining to an administrative transaction and Message Authentication Coding is configured, the param will determine if a MAC should automatically be placed in the message, even if the ACI Standard

Configuration File does not have a MAC configured for the message. This will occur if the param is set to Y and a key is configured to be sent in response. Valid values are as follows.

Y = Yes, automatically place a MAC on administrative transactions.

N = No, do not automatically place a MAC on administrative transactions.

POS-DH-MAX-CNFGS — The maximum number of configuration records the BASE24-pos Device Handler module can store in memory at one time. Valid values include any numeric value greater than zero. The BASE24 Standard POS Device Handler (SPDH) and Merchant Host Interface (MHI) modules use this param.

This param does not pertain to Hypercom POS Device Handler (HPDH) modules. The maximum number of configuration records the HPDH module can store in memory at one time is configured using the POS-HPDH-MAX-HPCFS param.

Read By: A symbolic name (for example, P2A^SPDH, P1A^MHI) is required in this field if this value varies among BASE24-pos Device Handler/Router/Authorization or Merchant Host Interface processes.

Param Default: 10

POS-DH-MAX-IN-CORE — The maximum number of POS Terminal Data File (PTDF) records that a Merchant Host Interface (MHI) module can store in memory at one time. Thus, this param indicates the amount of extended memory each Merchant Host Interface module must reserve for PTDF records and the maximum number of transactions each Merchant Host Interface module can process at one time.

The Merchant Host Interface module stores a PTDF record in memory each time it receives a transaction from a device. The Merchant Host Interface module retains that PTDF record in memory until it receives an authorization response from the Authorization module and, if required, a completion message from the device.

If the value in this param is too low, the Merchant Host Interface module can run out of extended memory during peak processing times and transactions are declined until more extended memory becomes available. If the value in this param is set too high, the excess extended memory is wasted.

The value in this param is an estimate of the maximum number of devices that can have transactions in progress at one time. Valid values include any numeric value greater than zero. However, the value in this param should not be greater than the value in the POS-DH-MAX-TDFS param.

The BASE24-pos Merchant Host Interface process uses this param.

Read By: A symbolic name (for example, P2A^MHI02) is required in this field if this value varies among Merchant Host Interface processes.

Param Default: 25

POS-DH-MAX-TDFS — The maximum number of POS Terminal Data File (PTDF) record keys that each Device Handler module can store in memory. Thus, this param indicates the maximum number of terminals each Device Handler module can service.

When a Device Handler module initializes or reinitializes, space is allocated in memory to build a table. This table stores the record positions of all PTDF records that the Device Handler module can access. By accessing this table, the Device Handler module can quickly locate the devices to which it must send transactions.

If the value in this param is set too low, the Device Handler module may run out of space in the table and be unable to process for all the devices. If the value in this param is set too high, the excess table space is wasted. The value of this param should be equal to the total number of devices that are associated with each Device Handler module. Valid values include any numeric value greater than zero. However, the value in this param should be greater than the value in the POS-DH-MAX-IN-CORE param.

The BASE24-pos Device Handler/Router/Authorization process uses this param when the following Device Handler modules are bound in:

APACS 30/40 Device Handler module
Merchant Host Interface module

This param does not pertain to Standard POS Device Handler or Hypercom POS Device Handler modules. The maximum number of BASE24-pos Terminal Data files records that SPDH and HPDH modules can store in memory at one time is configured using the POS-DH-MAX-TERMS param.

The BASE24-pos Device Handler/Router/Authorization process uses this param.

Read By: A symbolic name (for example, P1A^APACS02) is required in this field if this value varies among BASE24-pos Device Handler/Router/Authorization or Merchant Host Interface processes.

Param Default: 25 (for the Merchant Host Interface module)
75 (for the APACS 30/40 Device Handler module)

POS-DH-MAX-TERMS — The maximum number of BASE24-pos Terminal Data files records that each BASE24-pos Standard POS Device Handler (SPDH) or Hypercom Device Handler (HPDH) module can hold in extended memory at one time. Thus, this param indicates the maximum number of terminals each SPDH or HPDH module can service.

When an SPDH or HPDH module initializes or reinitializes, space is allocated in extended memory for the BASE24-pos Terminal Data files records the module maintains. By accessing this data in extended memory rather than from a disk file, these modules can process transactions more quickly.

If the value in this param is set too low, the SPDH or HPDH module can run out of extended memory space and be unable to process for all of their assigned devices. If the value in this param is set too high, the excess extended memory space is wasted. The value of this param should be equal to the total number of devices that are associated with each Device Handler module. This param can be set to any numeric value greater than zero. However, the value in this param should be greater than the values in the POS-DH-MAX-TERMS-IN-DYN-TBL and the POS-DH-MAX-TERMS-IN-STATIC-TBL params. The BASE24-pos Device Handler/Router/Authorization process uses this param.

Read By: A symbolic name is required in this field if the number of POS devices associated with an SPDH or HPDH module varies among BASE24-pos Device Handler/Router/Authorization processes.

Param Default: 50

POS-DH-MAX-TERMS-IN-DYN-TBL — The maximum number of BASE24-pos Terminal Data Dynamic File—general data (PTDD1) records that a BASE24-pos Standard POS Device Handler (SPDH) or Hypercom Device Handler (HPDH) module can store in extended memory at one time. Thus, this param indicates the amount of extended memory each Device Handler module must reserve for PTDD1 records and the maximum number of transactions each Device Handler module can process at one time.

The SPDH or HPDH module stores a PTDD1 record in memory each time it receives a transaction from a POS device. The Device Handler module retains these PTDD1 records in memory until it receives an authorization response from the Authorization module and, if required, a completion message from the POS device.

If the value in this param is too low, the Device Handler module can run out of extended memory during peak processing times and transactions are declined until more extended memory becomes available. If the value in this param is set too high, the excess extended memory is wasted.

The value in this param is an estimate of the maximum number of devices that can have transactions in progress at one time. This param can be set to any numeric value greater than zero. However, the value in this param should not be greater than the value in the POS-DH-MAX-TERMS param. The BASE24-pos Device Handler/Router/Authorization process uses this param.

Read By: A symbolic name (for example, P1A^SPDH02, P1A^HPDH02) is required in this field if this number varies among BASE24-pos Device Handler/Router/Authorization processes.

Param Default: 25

POS-DH-MAX-TERMS-IN-STATIC-TBL — The maximum number of BASE24-pos Terminal Data Static File—general data (PTDS1) records that a BASE24-pos Standard POS Device Handler (SPDH) or Hypercom Device Handler (HPDH) module can store in extended memory at one time. Thus, this param indicates the amount of extended memory each Device Handler module must reserve for PTDS1 records.

The SPDH or HPDH module stores a PTDS1 record in memory the first time it receives a transaction from the POS device. The module continues to dynamically add PTDS1 records to memory until it runs out of space or the process is warmbooted. When the module runs out of space, the oldest record is deleted from memory and the new record is added. When the static data is reinitialized or the process is warmbooted, all of the PTDS1 records are deleted from memory and the module begins adding them again dynamically as transactions are processed.

If the value in this param is too low, the Device Handler module can run out of extended memory during peak processing times and be forced to access terminal data from disk until more extended memory becomes available, causing a possible degradation in transaction processing performance. If the value in this param is set too high, the excess extended memory is wasted.

This param can be set to any numeric value greater than zero. However, the value in this param should not be greater than the value in the POS-DH-MAX-TERMS param. The BASE24-pos Device Handler/Router/Authorization process uses this param. If this param is not configured, the default value is used.

Read By: A symbolic name (for example, P1A^SPDH02, P1A^HPDH02) is required in this field if this number varies among BASE24-pos Device Handler/Router/Authorization processes.

Param Default: 25

POS-DH-PTD-NFTY-PCNT — Specifies the percentage of extended memory table full at which the BASE24-pos Standard POS Device Handler (SPDH) or Hypercom Device Handler (HPDH) generates an event message. The device handler monitors the size of the BASE24-pos Terminal Data (PTD) table. If the current percentage full value of the table meets or exceeds the value of this LCONF parameter, the device handler logs an event message warning of the condition. Each time the current percentage full value of the table increases or decreases by 1% and still remains at or above the specified value, an event message is logged. Valid values for this param are 0 though 99. The default value is 0 (turned off/do not monitor). The recommended value is 90 percent.

Param Default: 0

POS-DH-PTD-NFTY-PCNT-DYN — Specifies the percentage of extended memory table full at which the BASE24-pos Standard POS Device Handler (SPDH) or Hypercom Device Handler (HPDH) generates an event message. The device handler monitors the size of the BASE24-pos Terminal Data Dynamic (PTDD1) table. If the current percentage full value of the table meets or exceeds the value of this LCONF parameter, the device handler logs an event message warning of the condition. Each time the current percentage full value of the table increases or decreases by 1% and still remains at or above the specified value, an event message is logged. Valid values for this param are 0 though 99. The default value is 0 (turned off/do not monitor). The recommended value is 90 percent.

Param Default: 0

POS-DH-PTD-STATIC-REPL — A value indicating whether the PTD static record should be replaced in extended memory of the Standard POS Device Handler (SPDH) module if it is found that the static record has been updated via AFT since it was added to extended memory. Valid values for this param are as follows:

Y = Yes, replace the PTD static record in extended memory.
N = No, do not replace the PTD static record in extended memory.

Param Default: N

POS-DH-SEQNUM-RESET-OPT — Controls the action taken by the Standard POS Device Handler (SPDH) module upon each customer transaction to ensure each overall sequence number at a specific SPDH is unique. The SPDH will reset any of the three components of the sequence number field, including the shift number, batch number, or sequence number. Adding this param requires a selection of one of the following valid values and a warmboot of the SPDH. Valid values are as follows:

0 = Reset shift, batch, and sequence numbers
1 = Reset shift and sequence numbers, but not batch number
2 = Reset batch and sequence numbers, but not shift number
3 = Reset sequence number, but not shift or batch numbers
9 = Do not reset any values

Param Default: 0

POS-DISCR-DATA-PSTM-SUPPRS — A value indicating whether discretionary data carried in the PSTM 0210 response should be suppressed.

For POS authorization, it indicates whether discretionary data carried in the PSTM should be suppressed for transactions that are authorized by either BASE24 or a host system.

For the SPDH device handler, it indicates whether to suppress the discretionary data in the PTD and in the response PSTM prior to sending the message to the device.

For interfaces, it indicates whether or not the interface should suppress the discretionary data in the PSTM 0210 response messages sent to BASE24-pos.

The following processes use this param:

BASE24-pos Router/Authorization process
BASE24-pos Standard POS Device Handler process
BIC ISO Interface process

Valid values are as follows:

Y = Yes, suppress discretionary data in the PSTM.
N = No, do not suppress discretionary data in the PSTM.

Param Default: N

POS-DLY-RPT-STARTUP — The time of day that the Daily and Monthly Transaction Volume Report programs are run. The Transaction Based Pricing Report Initiator process uses this param. Valid values are 00:00–23:59. This param is required.

If this param is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends during initialization.

Param Default: No default value

POS-EAF-NOTIFY-INTERVAL — The number of writes made to the E-Commerce Authentication File (EAF) before calculating the percentage of file full. Each time a write is made to the EAF, a counter is increased by one. When the counter is equal to the value specified in this param, the Router module calculates how full the EAF is. The counter is then reset to zero. Valid values are 5–32766. The BASE24-pos Device Handler/Router/Authorization process uses this param.

Param Default: 5

POS-EAF-NOTIFY-PERCENTAGE — The percentage of file full at which the Router module of the BASE24-pos Device Handler/Router/Authorization process generates an event message indicating that the EAF is becoming full. The Router module calculates the percentage of file full and continues to calculate the percentage at the interval indicated in the POS-EAF-NOTIFY-INTERVAL param as described in the paragraphs below until more space is made available. If the percentage has increased by one percent or more since the preceding calculation, the Router module generates an event message indicating that the file is becoming full.

Each time the BASE24-pos Authorization module writes the number of EAF records specified in the POS-EAF-NOTIFY-INTERVAL param, the Router module checks the EAF to determine how full the file is. Since the EAF is a key-sequenced file, the percentage reflects the size of the file based on the end of file (EOF). This does not take into consideration unused EAF space.

If the calculation results in the percentage specified in the POS-EAF-NOTIFY-PERCENTAGE param, or more, of its capacity, the Router module generates an event message indicating the condition. Thereafter, the Router module calculates the percentage of file full each time the number of records specified in the POS-EAF-NOTIFY-INTERVAL param is written to the EAF and as long as the transaction log file calculation results in the percentage specified in the POS-EAF-NOTIFY-PERCENTAGE param, or above, of its capacity.

Valid values are 10 through 99. The BASE24-pos Device Handler/Router/Authorization process uses this param.

Param Default: 70

POS-ELEC-FOLLOW-UP-OPT — A flag indicating how electronic follow-up transactions received through the Visa Interchange are tabulated for the Transaction Based Pricing POS Daily Transaction Volume Report. If this param is set to a value of Y, the report program checks the POS Transaction Log File (PTLF). If the Visa Switch token exists for the transaction and the Stand In Processing Code (STIP) field is set to a value of 9101, the transaction is considered to be an electronic follow-up transaction. Otherwise, a draft capture flag value of 3 is the only indicator of an electronic follow-up transaction. Valid values are as follows:

Y = Yes, check the Visa Switch token and STIP field for electronic follow-up transactions.

N = No, do not check the Visa Switch token and STIP field for electronic follow-up transactions.

Param Default: Y

POS-EXPT-RPT-FLG — A code indicating whether the BASE24-pos report programs produce the Daily Cardholder Exception Detail Report (B24POS02-EXPT) and the Daily Retailer Exception Detail Report (B24POS12-EXPT). The BASE24-pos report programs use this param. Valid values are as follows:

Y = Yes, generate the exception reports.

N = No, do not generate the exception reports.

Param Default: Y

POS-FORWARD-INST-ID — The value that the BASE24-pos Router module places in the FRWD-INST-ID-NUM field of the BASE24-pos Standard Internal Message (PSTM). The value in this param is the routing and transit number representing BASE24. This param can be set to any 11-digit numeric value, including zeros (for example, 12345678901). The BASE24-pos Device Handler/Router/Authorization process uses this param.

Param Default: 00000000000

POS-FUEL-PREAUTHS — A flag indicating how preauthorization and completion transactions are tabulated for the Transaction Based Pricing POS Daily Transaction Volume Report. For 0210 messages, the report program checks the transaction amount for a value of 1 or less in the local currency. If this condition is met and the POS-FUEL-PREAUTHS param is set to a value of Y, the preauthorization transaction is counted as a preauthorization completion and the 0220 completion message is processed normally. Otherwise, the preauthorization transaction is not counted as a preauthorization completion. Valid values are as follows:

Y = Yes, count the preauthorization transaction as a preauthorization completion when it meets the specified criteria.

N = No, do not count the preauthorization transaction as a preauthorization completion even if it meets the specified criteria.

Param Default: Y

POS-HPDH-AUTH-RESP-TIMEOUT — The number of seconds that the BASE24-pos Hypercom Device Handler (HPDH) module waits for a response from the Authorization module. When the HPDH module sends a request to the Authorization module, it also sets a timer for the number of seconds specified in this param. If the timer expires before the HPDH module receives a response from the Authorization module, the HPDH module declines the request.

The HPDH module uses this param. The value in this param should be less than the shortest terminal timeout.

Param Default: 30

POS-HPDH-LOG-TERM-STATS — A code indicating whether to log Hypercom terminal statistics to the PTLF. Valid values are as follows:

Y = Yes, log Hypercom terminal statistics to the PTLF.

N = No, do not log Hypercom terminal statistics to the PTLF.

Param Default: N

POS-HPDH-MAX-HPCFS — The maximum number of Hypercom Configuration File (HPCF) records the BASE24-pos Hypercom Device Handler (HPDH) module can store in memory at one time. If this param is not included in the LCONF or is set to an invalid value, the HPDH module generates an error message and uses the default value listed below.

The HPDH module uses this param when Hypercom T4, T5, or T6 devices are configured in the logical network. This param can be set to any numeric value greater than zero.

Param Default: 10

POS-HPDH-MAX-HPTCS — The maximum number of Hypercom T7 Configuration File (HPTC) records the BASE24-pos Hypercom Device Handler (HPDH) module can store in memory at one time. If this param is not included in the LCONF or is set to an invalid value, the HPDH module generates an error message and uses the default value listed below.

The HPDH module uses this param when Hypercom T7 devices are configured in the logical network. Valid values include any numeric value greater than zero.

Param Default: 10

POS-HPDH-NAC-ID*identifier* — A Hypercom Network Access Controller (NAC) ID and its corresponding station name in the XPNET system. The *identifier* specifies the NAC ID. The station name is set in the param text. One param exists for each NAC ID and its corresponding station. Information contained in these params is used to build an internal table containing NAC IDs and their corresponding station names. BASE24 references the NAC ID and station table during message processing to determine the NAC source and destination associated with the message. Only those stations that are used are

required to be in this param. Valid values for NAC IDs are 00 through FF (for example, POS-HPDH-NAC-ID99, POS-HPDH-NAC-ID1C, POS-HPDH-NAC-IDDE). This range allows up to 256 NAC stations.

Example: Station name of S1ANAC01 for the POS-HPDH-NAC-ID01 param

POS-HPDH-NMS-ID*identifier* — A Hypercom Network Management System (NMS) ID and its corresponding station name in the XPNET system. The *identifier* specifies the NMS ID. The station name is set in the param text. One param exists for each NMS ID and its corresponding station. Information contained in these params is used to build an internal table containing the NMS IDs and their corresponding station names. BASE24 references the NMS ID and station table when processing messages to or from an NMS to determine the NMS source and destination associated with the message. Only those stations that are used are required to be in this param. Valid values for NMS IDs are 0 through F (for example, POS-HPDH-NMS-ID3, POS-HPDH-NMS-IDA, POS-HPDH-NMS-IDC). This range allows up to 16 NMS stations.

Example: Station name of S1ANMS1 for the POS-HPDH-NMS-ID1 param

POS-HPDH-OLDMSG-TIMEOUT — The number of seconds a message is allowed to remain in the BASE24-pos Hypercom Device Handler queue. Messages that have been in the queue longer than the duration of time indicated in this param are dropped. The value in this param plus the value in the POS-HPDH-AUTH-RESP-TIMEOUT param should be less than the shortest terminal timeout. A value of zero indicates that no messages will be dropped. The BASE24-pos Hypercom Device Handler (HPDH) module uses this param.

Param Default: 0

POS-IPDH-FREQ-SHOP-TIMEOUT — The number of seconds the BASE24-pos Device Handler/Router/Authorization process will wait for a response from the BASE24-frequent shopper product before it sends a frequent shopper unavailable response back to the POS terminal. The BASE24-pos Device Handler/Router/Authorization process uses this param when the BASE24-frequent shopper product is used in conjunction with the BASE24-pos product. Valid values are 0 through 600 seconds.

Param Default: 60

POS-ISS-AVS-BLANK-ZIP-CDE-ALWD — A code allowing a blank ZIP code to be sent in transaction and verified by the BASE24-pos Device Handler/Router/Authorization process. Valid values are:

Y = Permits blank zip code

N = Does not permit blank zip code (default)

Param Default: N

POS-ISS-AVS-DATA-SUPPRS — A flag indicating whether logging address verification data for issuer transactions to the POS Transaction Log File (PTLF) should be suppressed. The Track 1 and Track 2 discretionary data fields are changed to zeros to preserve track length. The BASE24-pos Router/Authorization module uses this param. Valid values are as follows:

Y = Yes, suppress logging of address verification data.

N = No, do not suppress logging of address verification data.

Param Default: N

POS-ISS-CVD2-DATA-SUPPRS — A flag indicating whether logging card verification data for issuer transactions to the POS Transaction Log File (PTLF) should be suppressed. The BASE24-pos Router/Authorization module uses this param. Valid values are as follows:

Y = Yes, suppress logging of card verification data.

N = No, do not suppress logging of card verification data.

Param Default: N

POS-ISS-DISCR-DATA-SUPPRS — A flag indicating whether logging discretionary data for issuer transactions to the POS Transaction Log File (PTLF) should be suppressed. The BASE24-pos Router/Authorization module uses this param. Valid values are as follows:

Y = Yes, suppress logging of discretionary data.

N = No, do not suppress logging of discretionary data.

Param Default: N

POS-LN-CUTOVER — The time of day that the POS logical network is to cut over. All institutions in the logical network must be cut over by this time. This param can be any value, expressed in 24-hour time, 00:00 (12:00 a.m.) through 23:59 (11:59 p.m.). This param is required and is used by the following processes or modules:

BASE24-pos Main and Secondary Settlement processes
 BASE24-pos Device Handler/Router/Authorization process
 BASE24-pos CRT Authorization Device Handler process

ISO Host Interface process
 Banknet Interchange Interface process
 BIC ISO Interchange Interface process
 Generic Interchange Interface process
 MDS ISO Interchange Interface process
 PLUS ISO Interchange Interface process
 VisaNet ISO Interchange Interface process
 EPS-Net Interchange Interface process
 Enscribe Refresh process
 Transaction Based Pricing Report Initiator process
 Super Extract process

The Host Interface, Interchange Interface, and Main and Secondary Settlement processes use this param to cut over to a new business day. The BASE24-pos Router module uses this param to derive the current processing date. The Super Extract process reads this param during an extract of the Store-and-Forward File (SAF).

If the param is not present in the LCONF or contains an invalid value, the processes that access the LCONF for this param abend during initialization.

Param Default: No default value

POS-LOG-MAC-ERR — A code indicating whether message authentication code (MAC) verification errors are logged to the POS Transaction Log File (PTLF). The BASE24 Standard POS Device Handler module uses this param. Valid values are as follows:

Y = Yes, log MAC verification errors to the PTLF.
 N = No, do not log MAC verification errors to the PTLF

Param Default: N

POS-MHI-MAX-REQUESTS — The maximum number of POS Standard Internal Message (PSTM) records the Merchant Host Interface (MHI) Device Handler module can store in memory at one time. The value of this param should be an estimate of the maximum number of transactions in progress at one time. Valid values include any numeric value greater than zero. The param value is used only in host control mode.

In host control mode, PSTMs are stored in a table in memory while transactions are in progress. A PSTM record is retained in memory each time a transaction is received from a device until an authorization response is received. Also, a PSTM record is stored in memory while waiting for a completion message from the device.

The BASE24-pos Merchant Host Interface (MHI) Device Handler module uses this param.

Process Name: A symbolic name is required in this field if this value varies among Device Handler/Router/Authorization processes (for example, P2A^MHI).

Param Default: 50

POS-NCR-0500-RESP-TIMEOUT — The number of seconds the NCR/NDP Device Handler module waits for a reconciliation response from the NCR device to a reconciliation request message initiated by the BASE24 system before aborting the reconciliation processing.

Param Default: 30

POS-NCR-0800-RESP-TIMEOUT — The number of seconds the NCR/NDP Device Handler module waits for a network management response from the NCR device to a network management request message initiated by the BASE24 system. The two supported network management timers are: Key Load—Working Key and Key Status.

Param Default: 30

POS-NCR-AUTH-RESP-TIMEOUT — The number of seconds the NCR/NDP Device Handler module waits for an authorization response to a transaction request message before sending an unable to process response to the device. This param should be a value less than the shortest terminal timeout.

Param Default: 30

POS-NCR-MAX-IN-CORE — The maximum number of POS Terminal Data File (PTDF) records that can be stored in memory by the NCR/NDP Device Handler module at one time. The value in this param should be equal to an estimate of the number of devices that can have transactions in progress at one time.

Param Default: 10

POS-NCR-MAX-TDFS — The maximum number of POS Terminal Data File (PTDF) records to be handled by one NCR/NDP process. For example, if 100 terminals are connected to an NCR/NDP Device Handler process, this param should be 100. On the other hand, if generic queuing is being used and 1000 terminals can be processed, this param should be set to 1000.

Param Default: 20

POS-NCR-OLDMSG-TIMEOUT — The number of seconds an NCR/NDP terminal request message is allowed to remain in the NCR/NDP Device Handler queue. Messages that have been in the queue longer than the duration of time indicated in this param are dropped. A value of zero indicates that no messages are dropped.

Param Default: 0

POS-NOTIFY-INTERVAL — The number of writes made to the POS Transaction Log File (PTLF) before calculating the percentage of file full. Each time a write is made to the PTLF, a counter is increased by one. When the counter is equal to the value specified in this param, the Device Handler/Router/Authorization process and Secondary Settlement process calculates how full the PTLF is. The counter is then reset to zero.

When the file reaches the percent full specified in the POS-NOTIFY-PERCENTAGE param, the Device Handler/Router/Authorization process and Secondary Settlement process generates an event message indicating the file is becoming full and continues to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more since the preceding calculation, the Device Handler/Router/Authorization process and Secondary Settlement process generates another event message indicating that the file is becoming full.

Valid values are 10 through 32766. The Secondary Settlement process and the BASE24-pos Device Handler/Router/Authorization process use this param.

Param Default: 50

POS-NOTIFY-PERCENTAGE — The percentage of file full at which the BASE24-pos Device Handler/Router/Authorization process or Secondary Settlement process generates an event message indicating that the POS Transaction Log File (PTLF) is becoming full. The Device Handler/Router/Authorization process or Secondary Settlement process calculates the percentage of file full and continues to calculate the percentage at the interval indicated in the POS-NOTIFY-INTERVAL param as described in the following paragraphs until more file space is made available. If the percentage has increased by one percent or more since the preceding calculation, the Device Handler/Router/Authorization or Secondary Settlement process generates another event message indicating that the file is becoming full.

If the calculation results in the percentage specified in the POS-NOTIFY-PERCENTAGE param or more, the Device Handler/Router/Authorization or Secondary Settlement process generates an event message indicating the condition. The processes continue to calculate the percentage of file full at the interval indicated by the POS-NOTIFY-INTERVAL param. When the calculated percentage of file full is less than the value of the POS-NOTIFY-PERCENTAGE param, the processes stop generating events.

Valid values are 10 through 99. The BASE24-pos Device Handler/Router/Authorization and Secondary Settlement processes use this param.

Param Default: 70

POS-PASSTHRU-ACQ-SEQ-NUM-CHK — A flag indicating whether the acquirer sets sequence numbers during message sequencing. The BASE24-pos Device Handler/Router/Authorization process uses this param. Valid values are as follows:

ON = The acquirer determines the sequence number

OFF = The acceptor sequence number resets the acquirer sequence number

Param Default: OFF

POS-PASSTHRU-PROCESS-TYPE — A code that indicates whether a POS device is an acceptor or an acquirer of pass-through transactions. The BASE24-pos Device Handler/Router/Authorization process uses this param. Valid values are as follows:

- ACC = Acceptor. Transactions are accepted from the acquirer BASE24-pos system, authorized, and returned to the acquirer.
- ACQ = Acquirer. Transactions are acquired from POS devices attached to the ACI Standard POS Device Handler (SPDH) process and passed to the acceptor BASE24-pos system for authorization.
- NON = Pass-through functionality is turned off.

Param Default: ACQ

POS-PRDF-RECSIZE — The average size of a record, in bytes, in the POS Retailer Definition File (PRDF). The PRDF is used in validating POS transactions and defining authorization and routing parameters. The BASE24-pos Main Settlement process uses the value of this param to calculate the amount of disk space required to build the alternate keys for the PRDF. Valid values are 616 to 4062.

Param Default: 616

POS-PREF-NOTIFY^{identifier} — The symbolic name of a process or service the BNEG or INEG Refresh process must notify after new files are generated during a full-file refresh of a national negative file. If broadcast messages are not used, a maximum of 60 processes can be notified.

Each POS-PREF-NOTIFY param contains the name of one process or service. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services. The optional *identifier* is usually a number; however, it can be any unique set of characters that has not already been declared by another POS-PREF-NOTIFY^{identifier} param. For example, POS-PREF-NOTIFY1 could contain the P1A^V1DRA01 process and POS-PREF-NOTIFY2 could contain the P1A^V1DRA02 process.

The BNEG or INEG Refresh process uses the POS-PREF-NOTIFY param after a full-file refresh.

If no POS-PREF-NOTIFY*identifier* params are present, the BNEG or INEG Refresh process assumes no BASE24-pos Device Handler/Router/Authorization processes are notified after a full-file refresh of a national negative file (BNEG or INEG).

If the POS-PREF-NOTIFY param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Enscribe Refresh process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Example: P1A^V1DRA01
Param Default: No default value

POS-PRF-RECSIZE — The average size of a record, in bytes, in the POS Referral File (PRF). The PRF is used to override authorization responses online for referrals, based on cardholder information displayed on a screen. The PRF is used by the BASE24-pos CRT Authorization add-on product. The BASE24-pos Main Settlement process uses the value of this param to calculate the amount of disk space required to build the alternate keys for the PRF. Valid values are 1100 to 4062.

Param Default: 1350

POS-PTLF-RECSIZE — The average size of a record, in bytes, in the POS Transaction Log File (PTLF). The BASE24-pos Main Settlement process uses the value of this param to calculate the amount of disk space required to build the alternate keys for the PTLF. Valid values are 988–4048 (for a format 2 PTLF) or 988–4072 (for a format 1 PTLF).

Param Default: 1150

POS-RESP-LMTS-CHK — A value determining whether daily limits are rechecked on a response when the Authorization level is online/offline and the Authorization Method is CAF or CAF/PBF. Valid values are as follows:

Y = Yes, check the limits on the response.
N = No, do not check the limits on the response.

Param Default: N

POS-RETRY-TIMER — The number of seconds the BASE24 Standard POS Device Handler (SPDH) module waits to resend a failed response to a terminal. A failed response is a response message from the SPDH module that could not be delivered to a terminal due to a communications problem. The response is resent up to two more times at the time interval specified in this param. Valid values include any numeric value greater than zero. The SPDH module uses this param only when processing with the X.21 protocol.

If this param is not present in the LCONF or is set to a value less than zero, the param defaults to zero. In this case, the SPDH module resends failed messages immediately.

Param Default: 0

POS-RPT-CPU — The number of the processor (CPU) in which the BASE24-pos Transaction Based Pricing report programs execute. The value of this param is placed in the startup command of each BASE24-pos report program started using the obey file created by the Transaction Based Pricing Report Initiator process. Valid values are 0 through 15. The Transaction Based Pricing Report Initiator processes use this param.

Param Default: If this param is not present in the LCONF, or contains an invalid value, report programs run in the same CPU as that in which the Transaction Based Pricing Report Initiator process is running.

POS-RPT-PRI — The priority at which the BASE24-pos Transaction Based Pricing report programs are executed. The value of this param is placed in the startup command of each BASE24-pos report program started using the obey file created by the Transaction Based Pricing Report Initiator process. Valid values are 1 through 199. The Transaction Based Pricing Report Initiator processes use this param.

Param Default: If this param is not present in the LCONF, or contains an invalid value, the report programs attempt to execute at the same priority as the Transaction Based Pricing Report Initiator process. If this causes an error, the Transaction Based Pricing Report Initiator process attempt to run the report programs at an execution priority of 100.

POS-RTAU-ALGO-CHECK — A code indicating whether the Router module must perform an algorithm check on a transaction's primary account number (PAN). If the Router module must perform an algorithm check, this param also indicates whether the Router module must perform the check before or after accessing the SPROUTE File. Valid values are as follows:

- 0 = Do not perform an algorithm check.
- 1 = Perform an algorithm check before accessing the SPROUTE File.
- 2 = Access the SPROUTE File before checking the algorithm.

The Router module of the BASE24-pos Device Handler/Router/Authorization process uses this param.

Param Default: 1

POS-RTAU-AST-ROUTE — A code indicating how the BASE24-pos Router module handles a transaction received from a host or a BASE24-pos device when a Card Prefix File (CPF) record is available for the card issuer, but a valid AST record cannot be located with the Financial Institution Identifier (FIID) from the CPF record. A valid Authorization Selection Table File (AST) record contains an authorization table entry that matches the service and issuer codes received with the transaction. Valid values are as follows:

- 0 = Normal routing
- 1 = Enhanced routing

When normal routing is specified and a CPF record is found for a transaction received from a host or a POS device, the Router module uses only the FIID from the CPF record when searching for a valid AST record. If a valid AST record is not found, further attempts to locate a valid AST record are not made.

When enhanced routing is specified and a CPF record is found for a transaction received from a host or a POS device, the Router module makes a second attempt to locate a valid AST record in those situations where a valid AST record is not found with the FIID from the CPF record. The Router module uses either the terminal FIID from the BASE24-pos Standard Internal Message (PSTM) or the FIID from the POS Retailer Definition File (PRDF) if the terminal FIID is not in the PSTM.

When a transaction is received from an interchange and a CPF record exists, the Router module always makes the second attempt to locate an AST record as described above, regardless of this param setting.

When no CPF record exists, the Router module checks the AST once using either the terminal FIID from the PSTM or the FIID from the PRDF if the terminal FIID is not in the PSTM, regardless of this param setting or the transaction source.

The Router module of the BASE24-pos Device Handler/Router/Authorization process uses this param.

Param Default: 0

POS-RTAU-IDF-DATES-COMPUTE — A param specifying whether the BASE24-pos Router module should compute the Institution Definition File (IDF) business dates during cutover processing or if the BASE24-pos Router module should read the Institution Definition File (IDF) business dates from a disk. If this param is set to a value of Y, Authorization computes IDF business dates during cutover processing. If set to N, Authorization reads the IDF business dates from a disk.

Y = Yes, Authorization should compute IDF business dates during cutover.
N = No, do not compute IDF business dates during cutover, read from disk.

Param Default: N

POS-RTAU-MAX-RDFS — The maximum number of POS Retailer Definition File (PRDF) records the Router module can store in memory at one time. The Router module allocates memory for a table of PRDF records. Valid values are 1 through 32767. The Router module of the BASE24-pos Device Handler/Router/Authorization process uses this param.

Param Default: 75

POS-RVSL-ROUTE — A code indicating whether the BASE24-pos Router module uses normal or enhanced routing when sending reversal transactions to Interchange Interface processes acting as transaction authorizers (issuers). With enhanced routing, the Router module saves the symbolic name of the authorizer when the original transaction response is sent to an Interchange Interface process. The module then sends a subsequent reversal transaction to the symbolic name saved from the original transaction response. This ensures that the reversal transaction is sent to the same Interchange Interface process that received the

original transaction response. Enhanced reversal routing is recommended only when online authorization (authorization type 0 or authorization level 1 is used). Valid values are as follows:

- 0 = Use normal reversal routing logic.
- 1 = Use enhanced reversal routing logic as described above.

Param Default: 0

POS-SETL-ALIVE-TIMEOUT — The time interval, in minutes, at which the Senior Secondary Settlement process verifies that the Main Settlement process is open and running. Valid values are 10 through 120. The Senior Secondary Settlement process uses this param.

Param Default: 120

POS-SETL-EAF-NOTIFY*identifier* — The name of a service or the symbolic name of a BASE24-pos Device Handler/Router/Authorization process or Router/Authorization module that the main Settlement process must notify at EAF cutover.

If the POS-SETL-EAF-NOTIFY*identifier* param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Settlement Initiator process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Param Default: No default value

POS-SETL-EAF-RETENTION-PERIOD — The number of days the current E-Commerce Authentication File (EAF) and the previous EAF should be retained before the BASE24-pos settlement process deletes the previous EAF, renames the current EAF, and creates a new EAF. Note that the EAF is not a daily file; it is based on the value of this param. For example, if this param is set to a value of 7, the EAF contains seven days of information.

Param Default: 150

POS-SETL-FI-CUTOVER-LEAD-TIME — The minimum number of minutes before financial institution cutover that all retailers must be cut over. This param is used if a retailer's cutover time is not set properly in its POS Retailer Definition

File (PRDF) record. If a record contains a retailer cutover time that is less than the minimum number of minutes specified by this param, then the Secondary Settlement process resets the retailer cutover time to be this number of minutes prior to financial institution cutover.

The Secondary Settlement processes use this param. Valid values are 0 through 1440.

Param Default: 30

POS-SETL-LN-CUTOVER-LEAD-TIME — The minimum number of minutes before POS logical network cutover that all institutions must be cut over. This param is used if an institution's cutover time is not set properly in its Institution Definition File (IDF) record. If an IDF record contains an institution cutover time that is less than the minimum number of minutes specified by this param, the Main Settlement process resets the institution cutover time to be this number of minutes prior to logical network cutover.

The Main Settlement process, Secondary Settlement processes, and CRT Administration Device Handler process use this param. Valid values are 0–1440.

Param Default: 30

POS-SETL-MASTER — The symbolic name of the Main Settlement process. The Main Settlement process is responsible for settlement functions. Other settlement processes in the BASE24-pos system include Secondary Settlement processes. Only the main process, identified in this param, can perform institution and logical network cutover and generate reports. All BASE24-pos Settlement processes read this param. If the param value is the symbolic name of the process reading the param, the process initializes as the Main Settlement process. Otherwise, the process initializes as a Secondary Settlement process.

If this param contains an invalid process name, the Main Settlement process cannot initialize correctly and, instead, runs as a Secondary Settlement process. In that case, no Main Settlement process is actually defined within the system and settlement and cutover actions cannot be performed. When the Main Settlement process initializes correctly, the event message “*process-name* is Main” is generated.

The BASE24-pos Main and Secondary Settlement processes use this param.

Example: P1A^POSETL

Param Default: No default value

POS-SETL-MIDNIGHT-NOTIFY*identifier* — The name of a service or the symbolic name of a BASE24-pos Device Handler/Router/Authorization process or a BASE24-atm Authorization process that the Main Settlement process must notify at midnight. The Main Settlement process must notify this service or process if the institution clears the UAF or resets the customer business date in the Cardholder Authorization File (CAF) at midnight. This param is used by the Main Settlement process and the BASE24-pos Transaction Context Manager process. If broadcast messages are not used, a maximum of 500 processes can be notified.

Each POS-SETL-MIDNIGHT-NOTIFY param contains the name of one process or service. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another POS-SETL-MIDNIGHT-NOTIFY*identifier* param. For example, the POS-SETL-MIDNIGHT-NOTIFY1 param could contain the P1A^AUTH1 process and the POS-SETL-MIDNIGHT-NOTIFY2 param could contain the P1A^AUTH2 process.

Note: For BASE24 networks using both the BASE24-pos and BASE24-atm products and the Usage Accumulation File (UAF), this param should include all BASE24-pos Device Handler/Router/Authorization processes and all BASE24-atm Authorization processes. This ensures correct purge processing of the UAF during midnight cutover. The UAF is used by the BASE24-atm and BASE24-pos products with the Negative Authorization with Usage Accumulation method. The first settlement process to cut over after midnight performs the UAF purge processing. This process then needs to notify all processes that use the UAF.

If no POS-SETL-MIDNIGHT-NOTIFY*identifier* params are present in the LCONF or they contain invalid values, the Main Settlement process assumes that no processes are notified at midnight cutover.

If the POS-SETL-MIDNIGHT-NOTIFY*identifier* param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Settlement Initiator process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Example: P1A^VDRA01
Param Default: No default value

POS-SETL-NOTIFY*identifier* — The name of a service or the symbolic name of a BASE24-pos Device Handler/Router/Authorization or Interchange Interface process that the Main Settlement process must notify at the time specified in the POS-LN-CUTOVER param. The Main Settlement process uses this param. If broadcast messages are not used, a maximum of 500 processes can be notified.

Note: This param is required when the ACI Commerce Gateway product is used with the BASE24-pos product. When this param is configured to notify the ISO Host Interface process, the Main Settlement process sends a 9502 cutover command to the specified process. When the ISO Host Interface process receives this command, it updates a global posting date value that it uses when the posting date is not included in a transaction. Because the ACI Commerce Gateway product does not send the posting date in messages sent to the ISO Host Interface process, this param is necessary to properly cut over the posting date.

Each POS-SETL-NOTIFY param contains the name of one process or service. When multiple processes or services must be notified, this param can include an optional *identifier* to specify params used for different processes or services in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another POS-SETL-NOTIFY*identifier* param. For example, the POS-SETL-NOTIFY1 param could contain the P1A^VDRA01 process and the POS-SETL-NOTIFY2 param could contain the P1A^VDRA02 process.

If no POS-SETL-NOTIFY*identifier* params are present in the LCONF or they contain invalid values, the Main Settlement process assumes that no processes are notified at the time specified in the POS-LN-CUTOVER param.

If the POS-SETL-NOTIFY*identifier* param contains the name of a service, the BROADCAST-NOTIFY param must exist and contain a valid value for the Settlement Initiator process to send broadcast messages to service providers.

When broadcast notification is not in use, this param contains an individual process to be notified instead of a service.

Example: P1A^VDRA01
Param Default: No default value

POS-SETL-PTLF-EXTENTS — The number of extents the Main Settlement process must reserve, or allocate, when creating new POS Transaction Log Files (PTLFs). Valid values are 1 through 16. ACI recommends setting this param to a value of 1. The Main Settlement process uses this param.

Param Default: 16

POS-SETL-PTLF-FILE-RETENTION — The number of days worth of POS Transaction Log Files (PTLFs) prior to the current business day which are to remain on the system. After the specified number of days, the Main Settlement process deletes the outdated PTLF from the system. For example, if the value in this param is 3 and the current business date is 01/06/05 (for June 5, 2001), PTLFs dated 01/06/06 (for June 6, 2001) and 01/06/05 (for June 5, 2001) are retained on the system and open. PTLFs dated 01/06/04 (for June 4, 2001), 01/06/03 (for June 3, 2001), and 01/06/02 (for June 2, 2001) are retained on the system and closed. PTLFs dated 01/06/01 (for June 1, 2001) and earlier are deleted from the system.

Valid values are 2 through 32767. The Main Settlement process uses this param.

Param Default: 7

POS-SETL-REPORTS — The time of day at which the Main Settlement process starts the BASE24-pos report programs. Valid values are as follows:

- 2 = Do not create a report obey file or start the BASE24-pos report programs. Reports will not be produced.
- 1 = Create a report obey file but do not start the BASE24-pos report programs. Reports must be run manually.
- 0–2359 = Create a report obey file and start the BASE24-pos report programs at the time specified. The time set must be greater than the time set in the POS-LN-CUTOVER param.

When a time is specified in this param, the time can be any value, expressed in 24-hour time, from 00:00 (12:00 a.m.) to 23:59 (11:59 p.m.). The time set must be greater than the time set in the POS-LN-CUTOVER param. If the hour to start the BASE24-pos report program is greater than 23:00 (11:00 p.m.), an event message is generated indicating that the report timer has been reset for an hour after logical network cutover.

If the param is not present in the LCONF, the report obey file is created but the report timer is not set. If a value other than a valid value is entered in this param, an event message is displayed indicating that a report timer has been set to expire one hour after logical network cutover.

Param Default: Create a report obey file with a timer set to expire one hour after logical network cutover

POS-SETL-RPT-CPU — The number of the processor (CPU) in which the BASE24-pos report programs execute. Valid values are 00 through 99. The value in this param is placed in the startup command of each BASE24-pos report program started using the obey file created by the Main Settlement process. The Main Settlement process uses this param.

If the param is not present in the LCONF or contains an invalid value, the Main Settlement process executes the report programs in the CPU in which the Main Settlement process is running.

Param Default: CPU in which the Main Settlement process is running

POS-SETL-RPT-FILE-RETENTION — The number of days worth of BASE24-pos report obey files, prior to the current business day, that are to remain on the system. After the specified number of days, the Main Settlement process deletes the outdated obey files from the system. For example, if the value in this param is 3 and the current business date is 01/06/05 (for June 5, 2001), the report obey files dated 01/06/04, 01/06/03, and 01/06/02 are retained on the system. Report obey files dated 01/06/01 and earlier are deleted from the system. Report obey files for the current business day have not yet been created.

Valid values are 2 through 32767. The Main Settlement process uses this param.

Param Default: 7

POS-SETL-RPT-PRI — The priority at which the Main Settlement process executes the BASE24-pos report programs. Valid values are 1 through 199. The value in this param is placed in the startup command of each BASE24-pos report program started using the obey file created by the Main Settlement process. The Main Settlement process uses this param.

Param Default: 100

POS-SETL-SENIOR-SLAVE — The symbolic name of the Secondary Settlement process responsible for periodically verifying that the Main Settlement process is still open and running. All Secondary Settlement processes read this param at initialization to identify which Secondary Settlement process is the Senior Secondary Settlement process. Only one Secondary Settlement process name can be specified in this param.

If this param does not contain a valid symbolic name of a Secondary Settlement process, no Secondary Settlement process verifies that the Main Settlement process is open and running.

Param Default: No default value

POS-SETL-TERM-CUTOVER-DELAY-TIME — The minimum number of minutes after logical network cutover that terminals whose posting date is one day ahead of the BASE24 posting date must wait before cutting over to a new date. The value in this param is subtracted from the logical network cutover time to obtain the time at which terminals can begin cutover. Secondary Settlement processes use this param. Valid values are 5 through 1440.

Param Default: 5

POS-SETL-THRESHOLD — The number of times the Main Settlement process attempts to send a startup message to a Secondary Settlement process before entering a wait state. The Main Settlement process enters the wait state after this number of attempts when the Secondary Settlement process fails to reply. Valid values are 1 through 5. The Main Settlement process uses this param.

Param Default: 5

POS-SETL-TRACE — A code indicating whether the Main and Secondary Settlement processes log trace messages indicating processing activity.

Trace messages are generated when the terminal, retailer, and network cut over; when process messages are passed between the Main and Secondary Settlement processes; when any files are purged; when 0500 messages are sent to the host; when terminals are forced balanced; and when an operator sends a RESYNC command from the network control facility. Valid values are as follows:

- 0 = Do not log terminal, retailer, and network messages.
- 1 = Log terminal, retailer, and network messages.

Note: This param should be set to a value of 1 only in a test environment. Logging terminal, retailer, and network cutover messages in a production environment can negatively impact performance.

The Main and Secondary Settlement processes use this param.

Param Default: 0

POS-SETL-WAIT-INTERVAL — The number of minutes the Main Settlement process remains in a wait state before sending another startup message to a Secondary Settlement process that failed to reply to earlier startup messages. Valid values are 2 through 15. The Main Settlement process uses this param.

Param Default: 15

POS-SLAVE-KEY*identifier* — The range of retailer IDs for which this Secondary Settlement process is responsible. The *identifier* is the symbolic name of the Secondary Settlement process. The param text contains the low-key retailer ID and the high-key retailer ID separated by a / symbol. For example, a POS-SLAVE-KEYP1A^SETL1 param with text set to 00001/00010 indicates that the P1A^SETL1 process is responsible for retailers 00001 through 00010. Each retailer ID can consist of up to 19 alphanumeric characters. The ranges of retailer IDs cannot overlap. For example, if one Secondary Settlement process is responsible for the range 00001/00010 and another Secondary Settlement process is responsible for the range 00009/00020, the POS-SLAVE-KEY*identifier* params for these Secondary Settlement processes are invalid because both params include retailer IDs 00009 and 00010.

When only one Secondary Settlement process is configured in the BASE24-pos logical network, this param can contain the identifier for that process and up to 19 asterisks for each high/low key (for example, */*).

The Main Settlement process reads this param to obtain and verify the retailer ID ranges. It does not read the symbolic name of each Secondary Settlement process. Each Secondary Settlement process reads this param for its symbolic name and its retailer ID range.

If the POS-SLAVE-KEY*Identifier* param does not contain the name of a Secondary Settlement process and a valid range of retailer IDs, the Main Settlement process assumes there are no Secondary Settlement processes configured in the BASE24-pos logical network (that is, the logical network is an issuer-only network).

Param Default: No default value

POS-SPLIT-TXN-RTG-DEST — Specifies the destination of the Transaction Context Manager (TCM). The TCM is required for split transaction routing used with the SPDH Device Handler Mobile Top-Up Extension. The Mobile Top-Up Extension accommodates the possibility of multiple authorization destinations. The SPDH Device Handler module routes transactions with a mobile top-up transaction subtype to the TCM destination specified in this parameter.

Param Default: No default value

POS-SV-PTLF-LOGGING — A flag indicating whether Stored Value transactions are logged to the PTLF.

If this param is set to the value Y, each transaction the Dormancy process logs to the Stored Value History File (SVHF) is also logged to the PTLF. These transactions are logged as a purchase transaction with a transaction subtype of C003, Dormancy Transaction.

If this param is set to the value Y, each transaction the Escheatment process logs to the Stored Value History File (SVHF) is also logged to the PTLF. These transactions are logged as a balance inquiry transaction, with a transaction subtype of C004, Escheatment Transaction.

Valid values are as follows:

Y = Yes, log Stored Value transactions to the PTLF.

N = No, do not log Stored Value transactions to the PTLF.

Param Default: N

POS-SV-RETAILER-ID — Specifies the POS retailer identification number. This param is used by the Dormancy or Escheatment process when logging transactions to the PTLF.

Param Default: DORMANCY-RETAILER

POS-SV-TERMINAL-ID — Specifies the POS terminal identification number. This param is used by the Dormancy or Escheatment process when logging transactions to the PTLF.

Param Default: DORMANCY-TERM

POS-SVHF-ICHG-AUTH-LOG — A flag indicating whether the Router/Authorization module logs stored value transactions authorized by an interchange to the Stored Value History File (SVHF). This param is optional when the BASE24-pos Stored Value add-on product is installed. The BASE24-pos Device Handler/Router/Authorization process uses this param. Valid values are as follows:

Y = Yes, log transactions authorized by an interchange to the SVHF.
N = No, do not log transactions authorized by an interchange to the SVHF.

Param Default: Y

POS-SVHF-NOTIFY-INTERVAL — The number of writes made to the Stored Value History File (SVHF) before calculating the percentage of file full. Each time a write is made to the SVHF, a counter is increased by one. When the counter is equal to the value specified in this param, the process calculates how full the SVHF is. The counter is then reset to zero.

When the file reaches the percent full specified in the POS-SVHF-NOTIFY-PERCENTAGE param, the process generates an event message indicating the file is becoming full. The process continues to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more since the preceding calculation, the process generates another event message indicating that the file is becoming full.

Valid values are 5 through 32766. The following processes use this param:

BASE24-pos Device Handler/Router/Authorization process
BASE24-pos Stored Value Dormancy/Escheatment program

Param Default: 5

POS-SVHF-NOTIFY-PERCENTAGE — The percentage of file full at which the process generates an event message indicating that the Stored Value History File (SVHF) is becoming full. The process calculates the percentage of file full and continues to calculate the percentage at the interval indicated in the POS-

SVHF-NOTIFY-INTERVAL param as described in the following paragraphs. If the percentage has increased by one percent or more since the preceding calculation, the process generates another event message indicating that the file is becoming full.

If the calculation results in the percentage specified in the POS-SVHF-NOTIFY-PERCENTAGE param or more, the process generates an event message indicating the condition. The process continue to calculate the percentage of file full at the interval indicated by the POS-SVHF-NOTIFY-INTERVAL param. When the calculated percentage of file full is less than the value of the POS-SVHF-NOTIFY-PERCENTAGE param, the process stop generating events.

Valid values are 10 through 99. The following processes use this param:

BASE24-pos Device Handler/Router/Authorization process
BASE24-pos Stored Value Dormancy/Escheatment program

Param Default: 70

POS-SVHF-RET-PERIOD — The number of days worth of history data to retain in the Stored Value History File (SVHF) when the History File Cleanup module (HFCLUP) is run. This param is required when the BASE24-pos Stored Value add-on product is installed and the SVHF is used. The History File Cleanup module (HFCLUP) and Net Position Report program use this param. Valid values are 1 through 32767.

Param Default: No default value

POS-WARM*identifier* — The symbolic name of a process to be warmbooted. Processes that can be notified include BASE24-pos Device Handler/Router/Authorization processes and Interchange Interface processes. A maximum of 150 processes can be warmbooted. The names of the Main and Secondary Settlement processes should not be included in this list.

Each POS-WARM param contains the name of one process. When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that have not already been declared by another POS-WARM*identifier* param. For example, the POS-WARM1 param can specify the P1A^AUTH1 process and the POS-WARM2 param can specify the P1A^AUTH2 process.

This param is used by the Process Control Terminal Server process.

Examples: P1A^AUTH02
 P1A^BASE01

Param Default: No default value

RCDFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Response Code Definition File (RCDF) external memory table. This param is used to set the amount of memory allocated by the Base Extended Memory Table Build utility for the table.

Param Default: 127

16: BASE24-telebanking Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-telebanking product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Note: Full-file refresh of HP NonStop SQL tables without system downtime is not currently supported. Therefore, full-file refresh of SQL tables is only recommended at system installation.

Assigns

The following assigns are used exclusively by the BASE24-telebanking product. Each of the following assigns should have the usage code TB (and only the code TB) entered in the USAGE CODES field on the LNCF Assign screen.

ADRT — The fully qualified file name of the Address Table File (ADRT). The Address Table File Server process and ITS Kernel Extended Memory Table Build utility use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Address Table File Server process displays an error message indicating that the assign needs to be corrected, and the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops.

Example: \B24.\$DATA.PRO1DATA.ADRT

CACT-PARTxx — The fully qualified table location for a partition of the Customer/Account Relation Table (CACT), where *xx* is the partition number. Each partition must be placed on a different HP NonStop system volume. The SQL Refresh process uses this assign.

This assign is required for either a full-file refresh of the entire CACT or for a full-file refresh of a single CACT partition. The value of *xx* in the assign name corresponds to the partition number included in the refresh table header or refresh message. Valid values for *xx* are 00–99.

If the CACT is not partitioned or if it is partitioned and the full table is being refreshed, the SQL Refresh process uses the CACT-PART00 assign. A partition number value of 00 is used to represent the primary partition of a partitioned table or non-partitioned tables. If any other partition is being refreshed, the value of *xx* in the assign name must equal the refresh partition number included in the refresh table header or refresh message. Unlike Enscribe files, SQL tables are partitioned by table name rather than partition number. The CACT-PARTxx assign allows you to equate the refresh file header partition number to a partitioned table name.

Examples: CACT-PART00: \B24.\$DATA.PRO1DATA.CACT
 CACT-PART01: \B24.\$DATA2.PRO1DATA.CACT
 CACT-PART02: \B24.\$DATA1.PRO1DATA.CACT

CPIT-PARTxx — The fully qualified table location for a partition of the Customer/Personal Information Relation Table (CPIT), where *xx* is the partition number. The SQL Refresh process uses this assign.

This assign is required for either a full-file refresh of the entire CPIT or for a full-file refresh of a single CPIT partition. The value of *xx* in the assign name corresponds to the partition number included in the refresh table header or refresh message. Valid values for *xx* are 00–99.

If the CPIT is not partitioned or if it is partitioned and the full table is being refreshed, the SQL Refresh process uses the CPIT-PART00 assign. A partition number value of 00 is used to represent the primary partition of a partitioned table or non-partitioned tables. If any other partition is being refreshed, the value of *xx* in the assign name must equal the refresh partition number included in the refresh table header or refresh message. Unlike Enscribe files, SQL tables are partitioned by table name rather than partition number. The CPIT-PARTxx assign allows you to equate the refresh file header partition number to a partitioned table name.

Examples: CPIT-PART00: \B24.\$DATA22.PRO1DATA.CPIT
CPIT-PART01: \B24.\$DATA.PRO1DATA.CPIT
CPIT-PART02: \B24.\$DATA5.PRO1DATA.CPIT

CSTT-PARTxx — The fully qualified table location for a partition of the Customer Table (CSTT), where *xx* is the partition number. The SQL Refresh process uses this assign.

This assign is required for either a full-file refresh of the entire CSTT or for a full-file refresh of a single CSTT partition. The value of *xx* in the assign name corresponds to the partition number included in the refresh table header or refresh message. Valid values for *xx* are 00–99.

If the CSTT is not partitioned or if it is partitioned and the full table is being refreshed, the SQL Refresh process uses the CSTT-PART00 assign. A partition number value of 00 is used to represent the primary partition of a partitioned table or non-partitioned tables. If any other partition is being refreshed, the value of *xx* in the assign name must equal the refresh partition number included in the refresh

table header or refresh message. Unlike Enscribe files, SQL tables are partitioned by table name rather than partition number. The CSTT-PARTxx assign allows you to equate the refresh file header partition number to a partitioned table name.

Examples: CSTT-PART00: \B24.\$DATA.PRO1DATA.CSTT
 CSTT-PART01: \B24.\$DATA1.PRO1DATA.CSTT
 CSTT-PART02: \B24.\$DATA2.PRO1DATA.CSTT

CUSTEMT — The fully qualified file name of the Customer extended memory table, which contains Customer Allowed Transaction Table (CATT) rows. The ITS Kernel Extended Memory Table Build utility and the Customer Access object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility displays an error message indicating that the assign needs to be corrected, and the processes that contain the Customer Access object do not initialize.

Example: \B24.\$DATA.PRO1DATA.CUSTEMT

ELF — The fully qualified file name of the Exception Log File (ELF). The following objects use this assign:

Interface Manager object
Interface Master Services object
End-of-Period Process object

This assign is required for the Interface Manager and Interface Master Services objects. If this assign is not present in the LCONF or contains an invalid value, processes containing these objects do not initialize.

This assign is optional for the End-of-Period Process object. If this assign is not present in the LCONF or contains an invalid value, the End-of-Period process does not perform ELF processing.

Examples: \B24.\$DATA.PRO1DATA.ELFMMDD (data file name)
 \B24.\$DATA.PRO1TPLT.ELFMMDD (template file name)
Template File: Required because BASE24 periodically creates the ELF.

FCF — The fully qualified file name of the File Control File (FCF). The following processes and objects use this assign:

File Control File Server process
Enscribe Refresh process
Transaction History object

If this assign is not present in the LCONF or contains an invalid value, the processes listed above and the processes that contain the object listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.FCF

IAS-symbolic-name — The fully qualified PPD name of each Integrated Authorization Server process configured in the Network Environment File (NEF). The Integrated Authorization Server processes use this assign. The name of the assign, *IAS-symbolic-name*, is the actual symbolic name of the Integrated Authorization Server process (e.g., P1A^IAS01, P1A^IAS02, P1A^IAS03) associated with the PPD name defined in this assign.

If this assign is not present in the LCONF or contains an invalid value, Integrated Authorization Server processes do not initialize.

Example: \B24.\$P1I1

IFCF — The fully qualified file name of the ITS Interface Configuration File (IFCF). The Interface Configuration File Server process, ITS Kernel Extended Memory Table Build utility, and BASE24 Remote Banking Transaction Analysis utility use this assign.

If this assign is not present in the LCONF or contains an invalid value, the processes listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.IFCF

IMP-symbolic-name — The fully qualified PPD name of the Interface Master process (IMP). The Interface Manager object uses this assign. The name of the assign, *IMP-symbolic-name*, is the actual symbolic name of the Interface Master process (e.g., P1A^IMP).

If this assign is not present in the LCONF or contains an invalid value, processes containing the Interface Manager object do not initialize.

Example: \B24.\$P1I5

IMTEMT — The fully qualified file name of the Internal Message Translation File (IMTF) extended memory table. The ITS Kernel Extended Memory Table Build utility and the Internal Message Translation Interface object use this assign.

If this assign is not present in the LCONF, the ITS Kernel Extended Memory Table Build utility and the processes that contain the Internal Message Translation Interface object do not initialize.

Example: \B24.\$DATA.PRO1DATA.IMTEMT

IMTF — The fully qualified file name of the Internal Message Translation File (IMTF). The Internal Message Translation File Server process and ITS Kernel Extended Memory Table Build utility use this assign.

If this assign is not present in the LCONF or contains an invalid value, the processes listed above do not initialize.

Example: \B24.\$DATA.PRO1DATA.IMTF

INTFEMT — The fully qualified name of the Interface extended memory table. The following process and objects use this assign:

ITS Kernel Extended Memory Table Build utility
Interface Manager object
Interface Master Services object
Transaction Security object

This assign is required for the ITS Kernel Extended Memory Table Build utility, Interface Manager object, and Interface Master Services object. If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and processes that contain the objects listed do not initialize.

This assign is optional for the Transaction Security object. If this assign is not present in the LCONF or contains an invalid value and the Transaction Security object receives a request that requires the Interface extended memory table, the Transaction Security object declines the request.

Example: \B24.\$DATA.PRO1DATA.INTFEMT

IPRF — The fully qualified name of the Institution Periodic Reporting File (IPRF). The BASE24-telebanking Issuer Reporting program stores daily report information in the IPRF, then uses the information to generate monthly reports (reports 5 and 6).

The IPRF is a key-sequenced file that is sized based on the number of institutions performing monthly reporting, the number of processing codes supported by the institutions, and the value in the PERIODIC FILE RETENTION field on Institution Definition File (IDF) screen 42 for each of the institutions.

This assign is optional for the BASE24-telebanking Issuer Reporting program. If this assign is missing or invalid, periodic reporting is not supported.

Example: \B24.\$DATA.PRO1DATA.IPRF

IRCF — The fully qualified name of the Institution Routing Configuration File (IRCF). The Institution Routing Configuration File Server process and the ITS Kernel Extended Memory Table Build utility use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Institution Routing Configuration File Server process displays an error message indicating that the assign needs to be corrected, and the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops.

Example: \B24.\$DATA.PRO1DATA.IRCF

IRTEEMT — The fully qualified file name of the Institution Routing extended memory table. The ITS Kernel Extended Memory Table Build utility and Router object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and processes that contain the Router object do not initialize.

Example: \B24.\$DATA.PRO1DATA.IRTEEMT

ISECENT-SWAPVOL — The fully qualified name of the swap volume in which the Transaction Security object temporarily stores data when building extended memory tables.

If this assign is not present in the LCONF or contains an invalid value, the default volume is used and an error message is generated indicating that the ISECENT-SWAPVOL assign is invalid.

Example: \B24.\$SWAP

ISF — The fully qualified name of the Interface Security File (ISF). The Interface Security File Server process and the Transaction Security object use this assign.

This assign is required for the Interface Security File Server process. If this assign is not present in the LCONF or contains an invalid value, the Interface Security File Server process does not initialize.

This assign is optional for the Transaction Security object. If this assign is not present in the LCONF or contains an invalid value, the Transaction Security object declines a request that uses the ISF.

Example: \B24.\$DATA.PRO1DATA.ISF

IST — The fully qualified name of the Interface Station Table (IST). The Interface Configuration Server process and the ITS Kernel Extended Memory Table Build utility use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Interface Configuration Server process displays an error message indicating that the assign needs to be corrected, and the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops.

Example: \B24.\$DATA.PRO1DATA.IST

KEYAEMT — The fully qualified file name of the Key Authorization File (KEYA) extended memory table. The ITS Kernel Extended Memory Table Build utility and the Authorization Security Access object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and the processes that contain the Authorization Security Access object do not initialize.

Example: \B24.\$DATA.PRO1DATA.KEYAEMT

LCF — The fully qualified file name of the Log Configuration File (LCF). This assign is used by the following:

Address Table File Server process
Log Configuration File Server process
ITS Kernel Extended Memory Table Build utility
Super Extract process
Enscribe Refresh process
BASE24 Remote Banking Transaction Analysis utility
Remote Banking Daily Transaction Volume Report program
Telebanking Issuer Reporting program

If this assign is not present in the LCONF or contains an invalid value, the Address Table File Server process displays an error message indicating that the assign needs to be corrected, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and the remaining processes listed do not initialize.

Example: \B24.\$DATA.PRO1DATA.LCF

PBFEMT-SWAPVOL — The fully qualified name of the volume in which Positive Balance File (PBF) extended memory tables are built. The Account Access object uses this object.

If this assign is not present in the LCONF or contains an invalid value, processes that use the Account Access object do not initialize.

Example: \B24.\$DATA

PCDF — The fully qualified file name of the Processing Code Definition File (PCDF). This assign is used by the following:

Processing Code Definition File Server process
ITS Kernel Extended Memory Table Build utility
BASE24-telebanking Issuer Reporting program

If this assign is not present in the LCONF or contains an invalid value, the Processing Code Definition File Server process displays an error message indicating that the assign needs to be corrected, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and the BASE24-telebanking Issuer Reporting program does not initialize.

Example: \B24.\$DATA.PRO1DATA.PCDF

PIT-PARTxx — The fully qualified table location for a partition of the Personal Information Table (PIT), where *xx* is the partition number. The SQL Refresh process uses this assign.

This assign is required for either a full-file refresh of the entire PIT or for a full-file refresh of a single PIT partition. The value of *xx* in the assign name corresponds to the partition number included in the refresh table header or refresh message. Valid values for *xx* are 00–99.

If the PIT is not partitioned or if it is partitioned and the full table is being refreshed, the SQL Refresh process uses the PIT-PART00 assign. A partition number value of 00 is used to represent the primary partition of a partitioned table or non-partitioned tables. If any other partition is being refreshed, the value of *xx* in the assign name must equal the refresh partition number included in the refresh table header or refresh message. Unlike Enscribe files, SQL tables are partitioned by table name rather than partition number. The PIT-PART*xx* assign allows you to equate the refresh file header partition number to a partitioned table name.

Examples: PIT-PART00: \B24.\$DATA1.PRO1DATA.PIT
 PIT-PART01: \B24.\$DATA5.PRO1DATA.PIT
 PIT-PART02: \B24.\$DATA.PRO1DATA.PIT

RB-TRN-THF — The fully qualified file name of the Transaction Analysis Transaction History File (THF). The THF is a report file that contains reports produced by the BASE24 Remote Banking Transaction Analysis utility. The BASE24 Remote Banking Transaction Analysis utility is part of the BASE24 Performance Tools.

The RB-TRN-THF assign is required when running the BASE24 Performance Tools.

Example: \B24.\$DATA.PRO1DATA.THF

REF-RPT-SQL — The spooler location to which the SQL Refresh process sends the refresh reports for refreshes of all SQL tables. The SQL Refresh process uses this assign.

Example: \B24.\$\$.#REFSQL

REF-SOURCEDICT — The fully qualified volume and subvolume location of the source record dictionary used in full-file refreshes. This assign is used by the SQL Refresh process in the LOAD statement. For full-file refreshes, the LOAD function works like an Enscribe file to SQL table load. Therefore, Enscribe dictionaries have been created for each of the SQL tables that allow full-file refreshes. These dictionaries reside on the OCxxRFDI subvolume, where xx is the number of the current release.

This assign is used in conjunction with the CACT-SOURCEREC, CPIT-SOURCEREC, CSTT-SOURCEREC, and PIT-SOURCEREC params. These params indicate the actual DDL records to be used on the OCxxRFDI subvolume.

Example: \B24.\$DATA.OCxxRFDI

SECURE-DEVICE n — The fully qualified name of the security device or interface module used with the security device.

For the Atalla A8000 or A8100 security device, this assign specifies the HP NonStop SYSGEN utility or DSC name of the primary security device. For Atalla A9000, A9100, A10000E, and A10100 security devices, this assign specifies the name given to the A9000, A9100, A10000E, or A10100 interface module used with the primary security device. The device name or interface module name must be compatible with the HP NonStop Expand product.

For Thales e-Security security devices other than the RG7100 security device using Transmission Control Protocol/Internet Protocol (TCP/IP) or the RG7300 security device using synchronous data-link control (SDLC), this assign specifies the SYSGEN utility or DSC name of the primary security device. For an RG7100 device using TCP/IP, this assign specifies the process name given to the Remote Application Manager process (for example, \$RAM). For an RG7300 device using SDLC, this assign specifies the process name given to the HSM Interface process (for example, \$HIP).

The device name or interface module name must be compatible with the HP NonStop Expand product.

The Transaction Security object uses this assign. Each security module used by a Transaction Security object requires its own SECURE-DEVICE assign.

When the Transaction Security object requires the services of a security module, it uses the next available security module. The *n* in the assign name identifies the order in which the Transaction Security object accesses the security modules. For example, the Transaction Security object accesses the security module identified by the SECURE-DEVICE1 assign before it accesses the security module identified by the SECURE-DEVICE2 assign.

The SECURE-DEVICE-COUNT param identifies the number of security modules being used. For example, if the SECURE-DEVICE-COUNT param is set to 5, the Transaction Security object accesses the security module identified by the SECURE-DEVICE5 assign, then starts over with the security module identified by the SECURE-DEVICE1 assign.

Examples: \B24.\$SECDVA (for an Atalla A8000 security device, this assign specifies the HP NonStop SYSGEN device name)

 \B24.\$BOX1 (for an Atalla A9000, A10000E, and A10100 security devices, this assign specifies the PPD name of the Boxcar interface module)

 \B24.\$RAM (for a Thales e-Security RG7100 device using TCP/IP, this assign specifies the process name given to the Remote Application Manager process)

User Field: Required for Atalla Network Security Processors (NSPs). For the A8000 or A8100 NSP, the User Field field can be set to a value of A4 or NSP. For the A9000 or A9100 NSP, the User Field must be set to a value of A4. For all other NSP security devices, the User Field must be set to NSP.

 The value in the User Field identifies the Atalla security device being used and the security functions available. For a detailed description of how these values are used, refer to the ***BASE24 Transaction Security Manual***.

SVCSREMT-SWAPVOL — The fully qualified name of the swap volume in which the Customer Service Representative Server process stores information when mapping a Pathway-formatted message into an internal transaction data (ITD) message and vice versa.

If this assign is not present in the LCONF or contains an invalid value, the Customer Service Representative Server process uses the volume in which it resides.

Example: \B24.\$DATA

SVTLFEMT-SWAPVOL — The fully qualified name of the swap volume in which the Log File Perusal Server process stores information before displaying it.

If this assign is not present in the LCONF or contains an invalid value, the Log File Perusal Server process uses the volume in which it resides.

Example: \B24.\$DATA

TB-DAILY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Daily Transaction Volume Report program. The naming convention for this assign is `$$.#RBDmmdd`, where *mmdd* is the month and day for which the report was run. The Transaction Based Pricing Report Initiator process uses this assign. This assign is not required. If it is not configured, the Daily Transaction Volume Report is sent to the EMS log rather than a spooler location, and a daily record is still written to the Remote Banking Accumulation File (RBAF).

Example: \$\$RBD0101

TB-DAILY-REPORT-OBEYFILE — The fully qualified file name of the obey file to run the Daily Transaction Volume Report program. The naming convention for this obey file is `RBDRmmdd`, where *mmdd* is the month and day for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \B24.\$DATA.RBDR0101

TB-DAILY-REPORT-PROGRAM — The fully qualified file name of the Remote Banking Daily Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, *xx* is the number of the current release.

Example: \B24.\$BA_{xx}TBP.RBDRPT

TB-MONTHLY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Monthly Transaction Volume Report program. The naming convention for this location is \$S.#RBM_{yy}*ymm*, where *ymm* is the year and month for which the report was run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \$S.RBM0112

TB-MONTHLY-REPORT-OBEYFILE — The fully qualified file name of the obey file to run the Monthly Transaction Volume Report program. The naming convention for this obey file is RBMR_{yy}*ymm*, where *ymm* is the year and month for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \B24.\$DATA.RBMR0112

TB-MONTHLY-REPORT-PROGRAM — The fully qualified file name of the Remote Banking Monthly Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, *xx* is the number of the current release.

Example: \B24.\$BA_{xx}TBP.RBMRPTLO

TB-RBAF — The fully qualified file name of the Remote Banking Accumulation File (RBAF). The naming convention for this file is RBMT_{yy}*ymm*, where *ymm* is the year and month for which the totals in the file were accumulated. The name of the subvolume where this file resides must be eight characters in length. The

Transaction Based Pricing Report Initiator process, Remote Banking Daily Transaction Volume Report program, and Remote Banking Monthly Transaction Volume Report program use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process and the report programs listed above abend.

Example: \B24.\$DATA.PRO1DATA.RBMT0112
Template File: Required (for example, \B24.\$DATA.PRO1TPLT.RBMTyymm) by the Transaction Based Pricing Report Initiator process.

TB-RPT-ISS-FS-DIST — The fully qualified name of the volume for the scratch file used by the HP NonStop FastSort utility distributor-collector process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present, the HP NonStop FastSort utility distributor-collector process creates a scratch file on \$SYSTEM.

Example: \B24.\$DATA

TB-RPT-ISS-FS-DIST-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the distributor-collector process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility distributor-collector process runs the SORTPROG process named \$SYSTEM.SYSnn.SORTPROG, where *nn* is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTDIST

TB-RPT-ISS-FS-DIST-SWAP — The fully qualified file name of the temporary swap file used by the HP NonStop FastSort utility distributor-collector process for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-DIST assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-DIST assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPDIST

TB-RPT-ISS-FS-SS1 — The fully qualified name of the volume for the scratch file used by the first HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program logs a message to its report error file and stops.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS1-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the first Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility first Subsort process runs the SORTPROG process named \$SYSTEM.SYSnn.SORTPROG, where *nn* is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS1

TB-RPT-ISS-FS-SS1-SWAP — The fully qualified file name of the temporary swap file used by the first Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS1 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS1 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS1

TB-RPT-ISS-FS-SS2 — The fully qualified name of the volume for the scratch file used by the second HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program logs a message to its report error file and stops.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS2-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the second Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility second Subsort process runs the SORTPROG process named \$SYSTEM.SYS nn .SORTPROG, where nn is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS2

TB-RPT-ISS-FS-SS2-SWAP — The fully qualified file name of the temporary swap file used by the second Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS2 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS2 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS2

TB-RPT-ISS-FS-SS3 — The fully qualified name of the volume for the scratch file used by the third HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program does not perform the subsort associated with this scratch file. Assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS8 control how many Subsort processes the HP NonStop FastSort utility uses. Subsort processes 1 and 2 are required and Subsort processes 3 through 8 are

optional. For example, if assigns TB-RPT-ISS-FS-SS1 and TB-RPT-ISS-FS-SS2 exist, the HP NonStop FastSort utility uses two Subsort processes. If assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS3 exist, the HP NonStop FastSort utility uses three Subsort processes.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS3-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the third Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility third Subsort process runs the SORTPROG process named \$SYSTEM.SYS*nn*.SORTPROG, where *nn* is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS3

TB-RPT-ISS-FS-SS3-SWAP — The fully qualified file name of the temporary swap file used by the third Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS3 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS3 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS3

TB-RPT-ISS-FS-SS4 — The fully qualified name of the volume for the scratch file used by the fourth HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program does not perform the subsort associated with this scratch file. Assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS8 control how many Subsort processes the HP NonStop FastSort utility uses.

Subsort processes 1 and 2 are required and Subsort processes 3 through 8 are optional. For example, if assigns TB-RPT-ISS-FS-SS1 and TB-RPT-ISS-FS-SS2 exist, the HP NonStop FastSort utility uses two Subsort processes. If assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS4 exist, the HP NonStop FastSort utility uses four Subsort processes.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS4-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the fourth Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility fourth Subsort process runs the SORTPROG process named \$SYSTEM.SYS nn .SORTPROG, where nn is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS4

TB-RPT-ISS-FS-SS4-SWAP — The fully qualified file name of the temporary swap file used by the fourth Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS4 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS4 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS4

TB-RPT-ISS-FS-SS5 — The fully qualified name of the volume for the scratch file used by the fifth HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program does not perform the subsort associated with this scratch file. Assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS8 control how many Subsort processes the HP NonStop FastSort utility uses. Subsort processes 1 and 2 are required and Subsort processes 3 through 8 are optional. For example, if assigns TB-RPT-ISS-FS-SS1 and TB-RPT-ISS-FS-SS2

exist, the HP NonStop FastSort utility uses two Subsort processes. If assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS5 exist, the HP NonStop FastSort utility uses five Subsort processes.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS5-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the fifth Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility fifth Subsort process runs the SORTPROG process named \$SYSTEM.SYS nn .SORTPROG, where nn is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS5

TB-RPT-ISS-FS-SS5-SWAP — The fully qualified file name of the temporary swap file used by the fifth Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS5 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS5 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS5

TB-RPT-ISS-FS-SS6 — The fully qualified name of the volume for the scratch file used by the sixth HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program does not perform the subsort associated with this scratch file. Assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS8 control how many Subsort processes the HP NonStop FastSort utility uses.

Subsort processes 1 and 2 are required and Subsort processes 3 through 8 are optional. For example, if assigns TB-RPT-ISS-FS-SS1 and TB-RPT-ISS-FS-SS2 exist, the HP NonStop FastSort utility uses two Subsort processes. If assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS6 exist, the HP NonStop FastSort utility uses six Subsort processes.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS6-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the sixth Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility sixth Subsort process runs the SORTPROG process named \$SYSTEM.SYS nn .SORTPROG, where nn is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS6

TB-RPT-ISS-FS-SS6-SWAP — The fully qualified file name of the temporary swap file used by the sixth Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS6 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS6 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS6

TB-RPT-ISS-FS-SS7 — The fully qualified name of the volume for the scratch file used by the seventh HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program does not perform the subsort associated with this scratch file. Assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS8 control how many Subsort processes the HP NonStop FastSort utility uses.

Subsort processes 1 and 2 are required and Subsort processes 3 through 8 are optional. For example, if assigns TB-RPT-ISS-FS-SS1 and TB-RPT-ISS-FS-SS2 exist, the HP NonStop FastSort utility uses two Subsort processes. If assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS7 exist, the HP NonStop FastSort utility uses seven Subsort processes.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS7-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the seventh Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility seventh Subsort process runs the SORTPROG process named \$SYSTEM.SYS nn .SORTPROG, where nn is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS7

TB-RPT-ISS-FS-SS7-SWAP — The fully qualified file name of the temporary swap file used by the seventh Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS7 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS7 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS7

TB-RPT-ISS-FS-SS8 — The fully qualified name of the volume for the scratch file used by the eighth HP NonStop FastSort utility Subsort process to sort data for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program does not perform the subsort associated with this scratch file. Assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS8 control how many Subsort processes the HP NonStop FastSort utility uses.

Subsort processes 1 and 2 are required and Subsort processes 3 through 8 are optional. For example, if assigns TB-RPT-ISS-FS-SS1 and TB-RPT-ISS-FS-SS2 exist, the HP NonStop FastSort utility uses two Subsort processes. If assigns TB-RPT-ISS-FS-SS1 through TB-RPT-ISS-FS-SS8 exist, the HP NonStop FastSort utility uses eight Subsort processes.

Example: \B24.\$DATA

TB-RPT-ISS-FS-SS8-SORTPROG — The fully qualified file name of the SORTPROG process used by the HP NonStop FastSort utility to sort data from the eighth Subsort process for the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility eighth Subsort process runs the SORTPROG process named \$SYSTEM.SYS nn .SORTPROG, where nn is the system image version.

Example: \B24.\$DATA.PRO1DATA.SORTSS8

TB-RPT-ISS-FS-SS8-SWAP — The fully qualified file name of the temporary swap file used by the eighth Subsort process of the HP NonStop FastSort utility for extended memory management. The HP NonStop FastSort utility creates the output file that is used to generate BASE24-telebanking issuer reports.

If this assign is not present in the LCONF or contains an invalid value, the FastSort utility creates a temporary swap file. The FastSort utility places the swap file in the volume specified in the TB-RPT-ISS-FS-SS8 assign if that volume is on the local system or on \$SYSTEM if the volume specified in the TB-RPT-ISS-FS-SS8 assign is not on the local system.

Example: \B24.\$DATA.PRO1DATA.SWAPSS8

TB-RPT-ISS-NAME — The fully qualified file name of the BASE24-telebanking Issuer Reporting program. The End-of Period Processing object uses this assign to start the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the End-of Period Processing object does not start the BASE24-telebanking Issuer Reporting program.

Example: \B24.\$DATA.PRO1DATA.TBRPT1

TB-RPT-ISS-OBEY-FILE — The fully qualified file name of the obey file used by the End-of-Period Process object to start the BASE24-telebanking Issuer Reporting program.

If this assign is not present in the LCONF or contains an invalid value, the End-of-Period Processing object does not start the BASE24-telebanking Issuer Reporting program.

Example: \B24.\$DATA.PRO1DATA.TBRMMDD

TB-RPT-ISS-OUT-FILE — The spooler location for the Statistics and Errors Report generated by the BASE24-telebanking Issuer Reporting program. If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program uses the default spooler location. The End-of-Period Process object uses this assign.

Assign Default: \$S.#TB1RPT

TB-RPT-ISS-SORTFILE — The fully qualified file name of the HP NonStop FastSort utility output file that is used to generate BASE24-telebanking issuer reports. The BASE24-telebanking Issuer Reporting program purges this output file after it generates the reports.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program logs a message to its report error file and stops.

Examples: \B24.\$DATA.PRO1DATA.SORTFILE (output file name)
 \B24.\$DATA.PRO1TPLT.SORTFILE (template file name)

Template File: A template file is optional. The HP NonStop FastSort utility uses the template file or calculates the sort output file size if no template file exists.

TB-RPT-ISS-SWAPFILE — The fully qualified file name of the swap file used by the BASE24-telebanking Issuer Reporting program for extended memory management during report generation. The swap file must be located on the same HP NonStop node as the HP NonStop FastSort utility.

If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program logs a message to its report error file and stops.

Examples: \B24.\$DATA.PRO1DATA.SWAPFILE (data file name)
 \B24.\$DATA.PRO1TPLT.SWAPFILE (template file name)

Template File: A template file is optional. The BASE24-telebanking Issuer Reporting program uses the template file to create the swap file or calculates the swap file size if no template file exists.

TB-RPT-ISS-TB01-LOC — The spooler location for the Daily Customer Activity Detail Report, report TB01. If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program uses the default spooler location.

Assign Default: \$\$.#TB01

TB-RPT-ISS-TB02-LOC — The spooler location for the Daily Customer Activity Summary Report, report TB02. If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program uses the default spooler location.

Assign Default: \$\$.#TB02

TB-RPT-ISS-TB03-LOC — The spooler location for the Daily Financial Activity Detail Report, report TB03. If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program uses the default spooler location.

Assign Default: \$\$.#TB03

TB-RPT-ISS-TB04-LOC — The spooler location for the Daily Financial Activity Summary Report, report TB04. If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program uses the default spooler location.

Assign Default: \$\$.#TB04

TB-RPT-ISS-TB05-LOC — The spooler location for the Monthly Customer Activity Summary Report, report TB05. If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program uses the default spooler location.

Assign Default: \$S.#TB05

TB-RPT-ISS-TB06-LOC — The spooler location for the Monthly Financial Activity Summary Report, report TB06. If this assign is not present in the LCONF or contains an invalid value, the BASE24-telebanking Issuer Reporting program uses the default spooler location.

Assign Default: \$S.#TB06

THCF — The fully qualified file name of the Transaction History Configuration File (THCF). The following processes use this assign:

Transaction History Configuration File Server process
ITS Kernel Extended Memory Table Build utility
Enscribe Refresh process

If this assign is not present in the LCONF or contains an invalid value, the Transaction History Configuration File Server process displays an error message indicating that the assign needs to be corrected, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and the Enscribe Refresh process does not initialize.

Example: \B24.\$DATA.PRO1DATA.THCF

THF-group — The fully qualified file name of the Transaction History File (THF). The name of this assign, including the *group* variable, must match a value in the ASSIGN field on Transaction History Configuration File (THCF) screen 1. The Enscribe Refresh process and the Transaction History object use this assign.

Examples: \B24.\$DATA.PRO1DATA.THF (data file name)
 \B24.\$DATA.PRO1TPLT.THF (template file name)

Note: Because the Enscribe Refresh process appends a version indicator to the THF file name, the file portion of the file name (THF in these examples) cannot exceed seven characters in length.

Template File: Required to build the new file during full-file refreshes.

THFEMT — The fully qualified name of the Transaction History File (THF) extended memory table. The ITS Kernel Extended Memory Table Build utility and the Transaction History object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and the processes that contain the Transaction History object do not initialize.

Example: \B24.\$DATA.PRO1DATA.THFEMT

TLF-DEFAULT — The fully qualified file name of the default ITS Transaction Log File (ITLF). Processes, programs, and objects use the default ITLF when an attempt to use the ITLF identified by a *TLF-group* assign is unsuccessful. This assign is used by the following:

BASE24-telebanking Issuer Reporting program
BASE24 Remote Banking Transaction Analysis utility
Transaction Based Pricing Remote Banking Daily Transaction Volume Report
Transaction object

The default ITLF permits processing to continue when the ITLF identified by the *TLF-group* assign is unavailable. However, the default ITLF cannot be perused, cannot be used for extracts, and cannot be read when it is necessary to process a reversal. Using the same data and template file names for the TLF-DEFAULT and *TLF-group* assigns causes all transactions to be logged to the ITLF that can be perused, used for extracts, and read for reversals. Transactions are declined when that ITLF is full or otherwise unavailable.

If this assign is not present in the LCONF or contains an invalid value, the processes listed above and the processes that contain the objects listed above do not initialize. The BASE24-telebanking Issuer Reporting program does not initialize only if this assign and the *TLF-group* assign both are missing or contain invalid values.

Examples: \B24.\$DATA1.PRO1DATA.TLYYMMDD (data file name)
 \B24.\$DATA1.PRO1TPLT.TLYYMMDD (template file name)
Template File: Required because BASE24 periodically creates the ITLF.

TLF-group — The fully qualified file name of the ITS Transaction Log File (ITLF). The name of this assign, including the *group* variable, must match the value in the ASSIGN field on Log Configuration File (LCF) screen 1. This assign is used by the following:

Log File Perusal Server process
 Customer Service Transaction Perusal Server process
 Enscribe Refresh process
 Super Extract process
 BASE24-telebanking Issuer Reporting program
 End-of-Period Process object
 Transaction object

If this assign is not present in the LCONF or contains an invalid value, the processes listed above and the processes that contain the objects listed aboveabend during initialization. The BASE24-telebanking Issuer Reporting program does not initialize only if this assign and the TLF-DEFAULT assign both are missing or contain invalid values.

Note: There should be only one TLF-group assign because all ITS objects must use a common logging destination.

Examples: \B24.\$DATA.PRO1DATA.TLFMMDD (data file name)
 \B24.\$DATA.PRO1TPLT.TLFMMDD (template file name)
 Template File: Required because BASE24 periodically creates the ITLF.

TLFEMT — The fully qualified name of the Transaction Log File (TLF) extended memory table. The TLFEMT assign is used by the following processes:

ITS Kernel Extended Memory Table Build utility
 End-of-Period Process object
 Transaction object

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility and the processes that contain the Transaction object do not initialize.

Example: \B24.\$DATA.PRO1DATA.TLFEMT

Params

The following params are used exclusively by the BASE24-telebanking product. Each of the following params should have the usage code TB (and only the code TB) entered in the USAGE CODES field on the LNCF Param screen.

CACT-PRI-PARTONLY — A flag indicating whether all partitions of the Customer/Account Relation Table (CACT) or only the primary partition of the CACT are refreshed during a full-file refresh. This param is used by the SQL Refresh process.

If this param is set to a value of Y and the partition number of the CACT is 00, a full-file refresh of only the primary partition is performed. If this param is set to a value of N and the partition number of the CACT is 00, a full-file refresh of all partitions in the table is performed.

If the partition number of the CACT to be refreshed is greater than 00, a full-file refresh of only the specified partition is performed, regardless of the value of this param. Valid values are as follows:

- Y = Yes, a full-file refresh is restricted to the primary partition if the partition number is 00.
- N = No, a full-file refresh is not restricted to the primary partition if the partition number is 00.

Param Default: N

CACT-SOURCEREC — The record name within the Data Definition Language (DDL) dictionary for the CACT-LOAD definition. This param is used by the SQL Refresh process in conjunction with the REF-SOURCEDICT assign to obtain the correct DDL record when performing a full-file refresh of the CACT.

Param Default: CACT-LOAD

CPIT-PRI-PARTONLY — A flag indicating whether all partitions of the Customer/Personal Information Relation Table (CPIT) or only the primary partition of the CPIT are refreshed during a full-file refresh. This param is used by the SQL Refresh process.

If this param is set to a value of Y and the partition number of the CPIT is 00, a full-file refresh of only the primary partition is performed. If this param is set to a value of N and the partition number of the CPIT is 00, a full-file refresh of all partitions in the table is performed.

If the partition number of the CPIT to be refreshed is greater than 00, a full-file refresh of only the specified partition is performed, regardless of the value of this param. Valid values are as follows:

- Y = Yes, a full-file refresh is restricted to the primary partition if the partition number is 00.
- N = No, a full-file refresh is not restricted to the primary partition if the partition number is 00.

Param Default: N

CPIT-SOURCEREC — The record name within the Data Definition Language (DDL) dictionary for the CPIT-LOAD definition. This param is used by the SQL Refresh process in conjunction with the REF-SOURCEDICT assign to obtain the correct DDL record when performing a full-file refresh of the CPIT.

Param Default: CPIT-LOAD

CSTT-PRI-PARTONLY — A flag indicating whether all partitions of the Customer Table (CSTT) or only the primary partition of the CSTT are refreshed during a full-file refresh. This param is used by the SQL Refresh process.

If this param is set to a value of Y and the partition number of the CSTT is 00, a full-file refresh of only the primary partition is performed. If this param is set to a value of N and the partition number of the CSTT is 00, a full-file refresh of all partitions in the table is performed.

If the partition number of the CSTT to be refreshed is greater than 00, a full-file refresh of only the specified partition is performed, regardless of the value of this param. Valid values are as follows:

- Y = Yes, a full-file refresh is restricted to the primary partition if the partition number is 00.
- N = No, a full-file refresh is not restricted to the primary partition if the partition number is 00.

Param Default: N

CSTT-SOURCEREC — The record name within the Data Definition Language (DDL) dictionary for the CSTT-LOAD definition. This param is used by the SQL Refresh process in conjunction with the REF-SOURCEDICT assign to obtain the correct DDL record when performing a full-file refresh of the CSTT.

Param Default: CSTT-LOAD

CUSTENT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Customer extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Param Default: 127

ELF-FILE-RETENTION — The number of days that an Exception Log File (ELF) is kept before being purged by the End-of-Period Process object. Valid values are 0 through 32767.

Param Default: 7

IMP-TIME-LIMIT — The maximum length of time, in hundredths of seconds, that the Interface Manager object waits for a response from the Interface Master process (IMP). Valid values are 0 through 2147483647.

Param Default: 500

IMTEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Internal Message Translation File (IMTF) extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Param Default: 127

INTFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Interface extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Param Default: 127

IRTEEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the institution routing extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Param Default: 127

KEYAEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Key Authorization File (KEYA) extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Param Default: 127

LGNT-CUTOVER-LEAD-TIME — The time that the End-of-Period Process object creates new log files, expressed as a number of minutes before the time specified in the LGNT-CUTOVER param. Valid values are 0 through 32767.

Param Default: 15

PIT-PRI-PARTONLY — A flag indicating whether all partitions of the Personal Information Table (PIT) or only the primary partition of the PIT are refreshed during a full-file refresh. This param is used by the SQL Refresh process.

If this param is set to a value of Y and the partition number of the PIT is 00, a full-file refresh of only the primary partition is performed. If this param is set to a value of N and the partition number of the PIT is 00, a full-file refresh of all partitions in the table is performed.

If the partition number of the PIT to be refreshed is greater than 00, a full-file refresh of only the specified partition is performed, regardless of the value of this param. Valid values are as follows:

Y = Yes, a full-file refresh is restricted to the primary partition if the partition number is 00.

N = No, a full-file refresh is not restricted to the primary partition if the partition number is 00.

Param Default: N

PIT-SOURCEREC — The record name within the Data Definition Language (DDL) dictionary for the PIT-LOAD definition. This param is used by the SQL Refresh process in conjunction with the REF-SOURCEDICT assign to obtain the correct DDL record when performing a full-file refresh of the Personal Information Table (PIT).

Param Default: PIT-LOAD

REF-INPUT-BLK-DSK — Specifies the size of block segments on the disk used as input for refreshes. The SQL Refresh process uses this param.

Param Default: 57344

REF-INPUT-BLK-TAPE — Specifies the size of block segments on the tape used as input for refreshes. The SQL Refresh process uses this param.

Param Default: 32000

REF-SQLCI-CPU — The CPU in which the NonStop SQL/MP conversational interface (SQLCI) process runs for a full-file refresh of an SQL table. The SQL Refresh process uses this param for all full-file refreshes of SQL tables. Valid values are 00 through 15.

Example: 01

Read By: A symbolic name is required in this field if each SQLCI process runs in a different CPU.

Param Default: CPU in which the SQL Refresh process is running

REF-SQLCI-DELAY — The number of seconds to delay before the SQL Refresh process attempts to stop the NonStop SQL/MP conversational interface (SQLCI) process. This delay allows the SQLCI process to stop on its own before being stopped by the SQL Refresh process.

Param Default: 1

SECURE-DEVICE-COUNT — The number of security devices configured in this logical network. The value of this param should match the number of SECURE-DEVICE n assigns in this LCONF. The Transaction Security object uses this param. Valid values are 1 through 32767.

Param Default: 5

SECURE-DEVICE-TYPE — A code identifying the type of security module specified in the SECURE-DEVICE n assigns. Valid values are as follows:

NSP = Atalla Network Security Processor
 N/A = A security module is not required
 RSM = Thales e-Security Host Security Module

The Transaction Security object uses this param.

Param Default: N/A

TB-DLY-RPT-STARTUP — The time of day that the Daily and Monthly Transaction Volume Report programs are run. The Transaction Based Pricing Report Initiator process uses this assign. Valid values are 00:00–23:59. This param is required.

If this param is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends during initialization.

Param Default: No default value

TB-RPT-CPU — The number of the processor (CPU) in which the BASE24 Remote Banking Transaction Based Pricing report programs execute. The value of this param is placed in the startup command of each BASE24 Remote Banking report program started using the obey file created by the Transaction Based Pricing Report Initiator process. Valid values are 0 through 15. The Transaction Based Pricing Report Initiator processes use this param.

Param Default: If this param is not present in the LCONF, or contains an invalid value, report programs execute in the same CPU as that in which the Transaction Based Pricing Report Initiator process is running.

TB-RPT-ISS-CPU — The CPU in which the BASE24-telebanking Issuer Reporting program executes. The End-of-Period Process object places the value of this param in the startup command of each obey file it creates for the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

Param Default: 00

TB-RPT-ISS-FILE-RETENTION — The number of days worth of BASE24-telebanking issuer reporting obey files, prior to the current business day, that are to remain on the system. After the specified number of days, the End-of-Period Process object deletes the outdated obey files from the system. For example, if the value in this param is 3 and the current business date is 01/06/05 (for June 5, 2001), the report obey files dated 01/06/04, 01/06/03, and 01/06/02 are retained on the system and closed. Report obey files dated 01/06/01 and earlier have been deleted from the system. Report obey files for the current business day have not yet been created.

Valid values are 2 through 32767. The End-of-Period Process object uses this param.

Param Default: 7

TB-RPT-ISS-FS-DIST-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the distributor-collector process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: No default value

TB-RPT-ISS-FS-DIST-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the distributor-collector process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-DIST-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the distributor-collector process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-DIST-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility distributor-collector process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS1-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the first Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS1-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the first Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS1-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the first Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS1-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility first Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS2-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the second Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS2-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the second Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS2-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the second Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS2-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility second Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS3-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the third Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS3-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the third Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS3-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the third Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS3-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility third Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS4-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the fourth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS4-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the fourth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS4-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the fourth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS4-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility fourth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS5-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the fifth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS5-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the fifth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS5-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the fifth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS5-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility fifth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS6-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the sixth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS6-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the sixth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS6-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the sixth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS6-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility sixth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the

BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS7-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the seventh Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS7-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the seventh Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS7-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the seventh Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS7-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility seventh Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-FS-SS8-CPU — The number of the CPU used by the SORTPROG process of the HP NonStop FastSort utility to sort data for the eighth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 00 through 15.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility selects the CPU that the SORTPROG process uses.

Param Default: CPU in which the SORTPROG process is running

TB-RPT-ISS-FS-SS8-MEM — The maximum number of data pages that can be used by the HP NonStop FastSort utility SORTPROG process that sorts data for the eighth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000.

This param should be set to a value of 64 or allowed to default to a value of 64.

Param Default: 64

TB-RPT-ISS-FS-SS8-PRI — The priority assigned to the HP NonStop FastSort utility SORTPROG process that sorts data for the eighth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility uses the default process priority for the operating system.

Param Default: Default process priority for the operating system

TB-RPT-ISS-FS-SS8-SEG — The size, in pages, of the extended memory segment used by the HP NonStop FastSort utility eighth Subsort process. The HP NonStop FastSort utility sorts the data contained on reports generated by the BASE24-telebanking Issuer Reporting program. Valid values are 64 through 8000; however, the extended memory segment cannot exceed 90 percent of the memory a CPU has that is not required by the operating system.

If this param is not present in the LCONF or contains an invalid value, the HP NonStop FastSort utility determines the size of the extended memory segment it uses.

Param Default: No default value

TB-RPT-ISS-PRI — The priority at which the BASE24-telebanking Issuer Reporting program is executed. The End-of-Period Process object places the value of this param in the startup command of each obey file it creates for the BASE24-telebanking Issuer Reporting program. Valid values are 1 through 199.

Param Default: 100

TB-RPT-ISS-RUN — A flag indicating whether the End-of-Period Process object must start the BASE24-telebanking Issuer Reporting program automatically. Valid values are as follows:

Y = Yes, start the BASE24-telebanking Issuer Reporting program automatically.

N = No, do not start the BASE24-telebanking Issuer Reporting program automatically.

Param Default: N

TB-RPT-ISS-SUP-TXN-CAT-TTLS — A flag indicating whether the BASE24-telebanking Issuer Reporting program suppresses totals on reports each time the transaction category changes.

Reports can include three levels of totals: processing code, transaction category, and institution. A transaction category includes all processing codes with the same transaction type. The value of this param controls whether the transaction category totals are printed. The processing code and institution totals are always printed. Valid values are as follows:

Y = Yes, suppress totals when the transaction category changes.

N = No, do not suppress totals when the transaction category changes.

Param Default: N

TB-RPT-ISS-TIM — The time at which the End-of-Period Process object is supposed to start the BASE24-telebanking Issuer Reporting program. This param can be set to any value based on a 24-hour clock (0000 to 2359).

Param Default: The time specified in LGNT-CUTOVER assign plus 30 minutes

TB-RPT-PRI — The priority at which the BASE24 Remote Banking Transaction Based Pricing report programs are executed. The value of this param is placed in the startup command of each BASE24 Remote Banking report program started using the obey file created by the Transaction Based Pricing Report Initiator process. Valid values are 1 through 199. The Transaction Based Pricing Report Initiator processes use this param.

Param Default: If this param is not present in the LCONF, or contains an invalid value, the report programs attempt to execute at the same priority as the Transaction Based Pricing Report Initiator process. If this causes an error, the Transaction Based Pricing Report Initiator process attempt to run the report programs at an execution priority of 100.

THFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the transaction history file extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Param Default: 127

TLF-EXTENTS — The number of extents that the End-of-Period Process object allocates when it creates a new ITS Transaction Log File (ITLF). Valid values are 1 through 16.

Param Default: 5

TLF-FILE-RETENTION — The number of days that an ITS Transaction Log File (ITLF) is kept before being purged by the End-of-Period Process object. Valid values are 3 through 99.

Param Default: 7

TLFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the transaction log file extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Param Default: 127

TSEC-OBJ-MASTER — The symbolic process name of the process containing the Transaction Security object that is responsible for performing the following initialization steps:

- Downloading the Diebold number table (DNT) to the hardware security modules used by the process.
- Sending the command text defined in the SECURE-DEV-CONF-CMD100 param to the hardware security modules used by the process.
- Sending the command text defined in the SECURE-DEV-CONF-TXT param to the hardware security modules used by the process.

These initialization steps need to be performed only once. Without this param, unnecessary processing is performed because each Transaction Security object repeats these initialization steps.

Example: P1A^IAS01

Param Default: Current Transaction Security object identification

ACI Worldwide, Inc.

17: BASE24-teller Assigns and Params

The following pages document the assigns and params used exclusively by the BASE24-teller product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by the BASE24-teller product. Each of the following assigns should have the usage code TLR (and only the code TLR) entered in the USAGE CODES field on the LNCF Assign screen.

NBF*identifier* — The fully qualified file name of the No Book File (NBF). This assign can include an optional *identifier* to specify assigns used for different NBFs in the same logical network.

The NBF assign is used by the Enscribe Refresh process to retrieve the name of the template file during full-file refreshes.

The Enscribe Refresh process first reads the Institution Definition File (IDF) for the fully qualified file name of the NBF used by all institutions in the refresh group. The Enscribe Refresh process then reads the LCONF to find an NBF assign that has a matching file name in the LOCATION/ID field. If no matching NBF assign is found, the Enscribe Refresh process abends during initialization.

If a matching NBF assign is found, the Enscribe Refresh process builds the new NBF using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.NBF (data file name)
 \B24.\$DATA.PRO1TPLT.NBF (template file name)
Template File: Required to build the NBF during full-file refreshes.

TLR-DAILY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Daily Transaction Volume Report program. The naming convention for this assign is \$S.#TRD*mmdd*, where *mmdd* is the month and day for which the report was run. The Transaction Based Pricing Report Initiator process uses this assign. This assign is not required. If it is not configured, the Daily Transaction Volume Report is sent to the EMS log rather than a spooler location, and a daily record is still written to the Monthly Totals Accumulation File (MTAF).

Example: \$S.TRD0101

TLR-DAILY-REPORT-OBEYFILE — The fully qualified file name of the obey file to run the Daily Transaction Volume Report program. The naming convention for this obey file is TRDR*mmdd*, where *mmdd* is the month and day for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \B24.\$DATA.TRDR0101

TLR-DAILY-REPORT-PROGRAM — The fully qualified file name of the Teller Daily Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, *xx* is the number of the current release.

Example: \B24.\$BA*xx*TBP.TRDRPT

TLR-DCT-LOG — The network location for event messages generated by the Device Control Terminal (DCT) server process for the BASE24-teller product.

This assign identifies the Sudoterm PPD name or \$0.

Examples: \B24.\$PLGR.#P1DCT
 \$SUDO
 \$0

TLR-MONTHLY-REPORT-DESTINATION — The fully qualified name of the spooler location for the report produced by the Monthly Transaction Volume Report program. The naming convention for this location is \$S.#TRM*yymm*, where *yymm* is the year and month for which the report was run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \$S.TRM0112

TLR-MONTHLY-REPORT-OBEYFILE — The fully qualified file name of the obey file to run the Monthly Transaction Volume Report program. The naming convention for this obey file is TRMR $yymm$, where $yymm$ is the year and month for which the report is to be run. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \B24.\$DATA.TRMR0112

TLR-MONTHLY-REPORT-PROGRAM — The fully qualified file name of the Teller Monthly Transaction Volume Report program object file. The Transaction Based Pricing Report Initiator process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends. In the following example, xx is the number of the current release.

Example: \B24.\$BA xx TBP.BAMRPT

TLR-MTAF — The fully qualified file name of the Monthly Totals Accumulation File (MTAF). The naming convention for this file is TRMT $yymm$, where $yymm$ is the year and month for which the totals in the file were accumulated. The name of the subvolume where this file resides must be eight characters in length. The Transaction Based Pricing Report Initiator process, BASE24-teller Daily Transaction Volume Report program, and the Monthly Transaction Volume Report program use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends.

Example: \B24.\$DATA.PRO1DATA.TRMT0112

Template File: Required (for example, \B24.\$DATA.PRO1TPLT.
TRMT $yymm$) by the Transaction Based Pricing Report
Initiator process.

TLR-ORF — The fully qualified file name of the Override Response File (ORF). The TLR-ORF assign is used by the following processes:

Override Response File (ORF) Server process
BASE24-teller Authorization process
BASE24-teller Device Handler processes (required)

Example: \B24.\$DATA.PRO1DATA.ORF

TLR-RPT-CRD-ACTIVITY — The spooler location to which to send the Daily Institution Cardholder Activity Report (STAT07-B24). The BASE24-teller report program that produces the Daily Institution Cardholder Activity Report (STAT07-B24) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Daily Institution Cardholder Activity Report (STAT07-B24) is sent to the default spooler location.

Assign Default: \$S.#CARPT

TLR-RPT-DLY-DETAIL — The spooler location to which to send the Daily Detail Report (report 01). The BASE24-teller report program that produces the Daily Detail Report (report 01) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Daily Detail Report (report 01) is sent to the default spooler location.

Assign Default: \$S.#REPORT1

TLR-RPT-DLY-TIM — The spooler location to which to send the Daily Summary by Teller ID and Time Block Report (report 04). The BASE24-teller report program that produces the Daily Summary by Teller ID and Time Block Report (report 04) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Daily Summary by Teller ID and Time Block Report (report 04) is sent to the default spooler location.

Assign Default: \$S.#REPORT4

TLR-RPT-DLY-TLR — The spooler location to which to send the Daily Summary by Teller ID Report (report 03). The BASE24-teller report program that produces the Daily Summary by Teller ID Report (report 03) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Daily Summary by Teller ID Report (report 03) is sent to the default spooler location.

Assign Default: \$S.#REPORT3

TLR-RPT-DLY-TYP — The spooler location to which to send the Daily Summary by Type Report (report 02). The BASE24-teller report program that produces the Daily Summary by Type Report (report 02) uses this assign. If this assign is not included in the LCONF or contains an invalid value, the Daily Summary by Type Report (report 02) is sent to the default spooler location.

Assign Default: \$S.#REPORT2

TLR-RPT-NTWK-CLEARINGS — The spooler location to which to send the Daily Network Clearings Statement Report (SETL01-B24). The BASE24-teller report program that produces the Daily Network Clearings Statement Report (SETL01-B24) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Daily Network Clearings Statement Report (SETL01-B24) is sent to the default spooler location.

Assign Default: \$S.#NTWK

TLR-RPT-PERIODIC-TIM — The spooler location to which to send the Periodic Summary by Time Block Report (report 14). The BASE24-teller report program that produces the Periodic Summary by Time Block Report (report 14) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Periodic Summary by Time Block Report (report 14) is sent to the default spooler location.

Assign Default: \$S.#REPRT14

TLR-RPT-PERIODIC-TLR — The spooler location to which to send the Periodic Summary by Teller ID Report (report 13). The BASE24-teller report program that produces the Periodic Summary by Teller ID Report (report 13) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Periodic Summary by Teller ID Report (report 13) is sent to the default spooler location.

Assign Default: \$S.#REPRT13

TLR-RPT-PERIODIC-TYP — The spooler location to which to send the Periodic Summary by Type Report (report 12). The BASE24-teller report program that produces the Periodic Summary by Type Report (report 12) uses this assign. If this assign is not present in the LCONF or contains an invalid value, the Periodic Summary by Type Report (report 12) is sent to the default spooler location.

Assign Default: \$S.#REPRT12

TLR-RTTB — The fully qualified file name of the Report Transaction by Time Block File (RTTB). The BASE24-teller report programs use this assign to generate periodic reports.

Example: \B24.\$DATA.PRO1DATA.RTTB

TLR-RTTF — The fully qualified file name of the Report Transaction by Type File (RTTF). The BASE24-teller report programs use this assign to generate periodic reports.

Example: \B24.\$DATA.PRO1DATA.RTTF

TLR-TRN-THF — The fully qualified file name of the Transaction Analysis Transaction History File (THF). The THF is a report file that contains reports produced by the BASE24-teller Transaction Analysis utility. The BASE24-teller Transaction Analysis utility is part of the BASE24 Performance Tools.

The TLR-TRN-THF assign is required when running the BASE24 Performance Tools.

Example: \B24.\$DATA.PRO1DATA.THF

TLR-TTDF — The fully qualified file name of the Teller Terminal Data File (TTDF). The following processes use this assign:

TTDF Server process
BASE24-teller DCT Server process
BASE24-teller Device Handler process (required)
BASE24-teller Transaction Analysis utility

Example: \B24.\$DATA.PRO1DATA.TTDF

TLR-TTF — The fully qualified file name of the Teller Transaction File (TTF). The following processes use this assign:

Teller Transaction File Server process
Teller Transaction Log File Server process
BASE24-teller Cardholder Activity Report Server process
BASE24-teller Authorization process
BASE24-teller Device Handler process (required)

BASE24-teller reports
Super Extract process
Teller Transaction File Extract process

Example: \B24.\$DATA.PRO1DATA.TTF

TLR-TTLF — The fully qualified file name of the Teller Transaction Log File (TTLF). The following processes use this assign:

Teller Transaction Log File Server process
BASE24-teller Transaction Analysis utility
BASE24-teller Device Handler process (required)
BASE24-teller Authorization processes
Transaction Based Pricing Daily Transaction Volume Report program
BASE24-teller Settlement process
BASE24-teller report server processes
Super Extract process
Enscribe Refresh process

Examples: \B24.\$DATA.PRO1DATA.TRYMMDD (data file name)
 \B24.\$DATA.PRO1TPLT.TRYMMDD (template file name)

Template File: Required because the TTLF is created periodically by
 BASE24.

TLR-WHFF*identifier* — The fully qualified name of the Warning/Hold/Float File (WHFF). This assign includes an optional *identifier* to specify assigns used for different WHFFs in the same logical network.

The TLR-WHFF assign is used by the Enscribe Refresh process to retrieve the name of the template file during full-file refreshes.

The Enscribe Refresh process first reads the Institution Definition File (IDF) for the fully qualified file name of the WHFF used by all institutions in the refresh group. The Enscribe Refresh process then reads the LCONF to find a TLR-WHFF assign that has a matching file name in the LOCATION/ID field. If no matching TLR-WHFF assign is found, the Enscribe Refresh process abends during initialization.

If a matching TLR-WHFF assign is found, the Enscribe Refresh process builds the new TLR-WHFF using the template file indicated in the assign. If the file attributes of the template file are unacceptable, the Enscribe Refresh process abends during initialization.

Example: \B24.\$DATA.PRO1DATA.WHFF (data file name)
 \B24.\$DATA.PRO1TPLT.WHFF (template file name)
Template File: Required to build the WHFF during full-file refreshes.

Params

The following params are used exclusively by the BASE24-teller product. Each of the following params should have the usage code TLR (and only the code TLR) entered in the USAGE CODES field on the LNCF Param screen.

TLR-DH-AUTH-TIMER — The maximum amount of time, in seconds, that BASE24-teller Device Handler processes wait for an authorization response from BASE24-teller Authorization processes before canceling a transaction (for example, 180 equals 3 minutes). Valid values are 10 through 180. The BASE24-teller Device Handler processes use this param.

Param Default: 45

TLR-DH-MAX-TERMS — The maximum number of Teller Terminal Data File (TTDF) records that can be associated with a BASE24-teller Device Handler process. The Device Handler process uses this value to determine the amount of extended memory it must reserve for TTDF records. This param can be set to any numeric value greater than zero.

The TLR-DH-MAX-TERMS param can include an optional *identifier* to specify params used for different BASE24-teller Device Handler processes in the same logical network. The BASE24-teller Device Handler processes (for example, P1A^TRDH1) use this param.

Read By: A symbolic name (for example, P1A^TRDH2) is required in this field if this value varies among BASE24-teller Device Handler processes.

Param Default: 150

TLR-DH-NATIVE-MSG — An indicator of whether the native message token is carried in the BASE24-teller Internal Message (TSTM) to facilitate account processing. Valid values are as follows:

Y = Yes, the native message token is carried in the TSTM.

N = No, the native message token is not carried in the TSTM.

The BASE24-teller Device Handler process, if designed to do so, uses the TLR-DH-NATIVE-MSG param.

Param Default: N

TLR-DH-ORF-RESP — A value that indicates which response code descriptions the BASE24-teller Device Handler process is to use. Valid values are as follows:

- 0 = Use response code descriptions from the DHTBLS.
- 1 = Use response code descriptions from the Override Response File (ORF).
- 2 = Use response code descriptions from the institution's ORF.

Param Default: 1

TLR-DH-STALE-RQST-TIMEOUT — The number of seconds an incoming transaction request can remain in the Device Handler's queue before being discarded by the BASE24-teller Device Handler process. Valid values for this param are 10 through 180.

Param Default: 45

TLR-DLY-RPT-STARTUP — The time of day that the Daily and Monthly Transaction Volume Report programs are run. The Transaction Based Pricing Report Initiator process uses this assign. Valid values are 00:00–23:59. This param is required.

If this param is not present in the LCONF or contains an invalid value, the Transaction Based Pricing Report Initiator process abends during initialization.

Param Default: No default value

TLR-LN-CUTOVER — The time of day that the BASE24-teller logical network is to cut over. All institutions in the logical network must be cut over by this time. This param can be any value expressed in 24-hour time, 00:00 (12:00 a.m.) through 23:59 (11:59 p.m.). The TLR-LN-CUTOVER param is used by the following processes:

- ISO Host Interface process
- Enscribe Refresh process
- Super Extract process
- Transaction Based Pricing Report Initiator process
- BASE24-teller Device Handler process
- BASE24-teller Settlement process

If the param is not present or contains an invalid value, the process that accesses the LCONF abends during initialization.

Param Default: No default value

TLR-MAX-NBF-REC-CNT — The number of No Book File (NBF) records that cause an update to be declined, if exceeded. Valid values include any numeric value greater than 4. The BASE24-teller Authorization process uses this param.

Param Default: 10

TLR-PROCESS-CRD-PIN — A code indicating whether the BASE24-teller Authorization process requires the Card Prefix File (CPF) or the Key Authorization File (KEYA) to process cards or PINs. Valid values are as follows:

- C = Card processing is performed but PIN processing and card verification are not; CPF is required.
- B = Card and PIN processing or card verification is performed; CPF and KEYA are required.
- N = No card or PIN processing is performed; neither CPF or KEYA are required.

Param Default: N

TLR-RPT-CPU — The number of the processor (CPU) in which the BASE24-teller Transaction Based Pricing report programs execute. The value of this param is placed in the startup command of each BASE24-teller report program started using the obey file created by the Transaction Based Pricing Report Initiator process. Valid values are 0 through 15. The Transaction Based Pricing Report Initiator processes use this param.

Param Default: If this param is not present in the LCONF, or contains an invalid value, report programs execute in the same CPU as that in which the Transaction Based Pricing Report Initiator process is running.

TLR-RPT-FILE-RETENTION — The number of days worth of records, prior to the current business date, to retain in the Report Transaction by Time Block File (RTTB) and Report Transaction by Type File (RTTF). The Daily Report server process uses this param. Valid values are 3 through 9999.

Param Default: 7

TLR-RPT-PRI — The priority at which the BASE24-teller Transaction Based Pricing report programs are executed. The value of this param is placed in the startup command of each BASE24-teller report program started using the obey file created by the Transaction Based Pricing Report Initiator process. Valid values are 1 through 199. The Transaction Based Pricing Report Initiator processes use this param.

Param Default: If this param is not present in the LCONF, or contains an invalid value, the report programs attempt to execute at the same priority as the Transaction Based Pricing Report Initiator process. If this causes an error, the Transaction Based Pricing Report Initiator process attempt to run the report programs at an execution priority of 100.

TLR-RPT-PRNT-TKN-ERR — An indicator of whether non-critical token errors are printed to reports. The Daily Report server process uses this param. Valid values are as follows:

Y = Yes, print non-critical token error messages.

N = No, do not print non-critical token error messages.

Param Default: Y

TLR-SETL-MASTER — The symbolic name of the BASE24-teller Settlement Initiator process that is responsible for BASE24-teller settlement functions. If more than one BASE24-teller Settlement Initiator process exists, only the main process, identified in this param, can perform settlement.

If this param does not contain the name of the BASE24-teller Settlement Initiator process that reads the param, the process abends during initialization.

Example: P1A^TSETL

Param Default: No default value

TLR-SETL-NOTIFY*identifier* — The symbolic name of a process to be notified after cutover is performed. The processes to be notified are BASE24-teller Device Handler processes, BASE24-teller Authorization processes, and Host Interface processes. A maximum of 500 processes can be notified.

Each TLR-SETL-NOTIFY param contains the name of one process. When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The

optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another TLR-SETL-NOTIFY*identifier* param. For example, the TLR-SETL-NOTIFY1 param could contain the P1A^TAUTH1 process and the TLR-SETL-NOTIFY2 param could contain the P1A^TAUTH2 process.

If the BASE24-teller Settlement Initiator process does not find a valid value for this param when it accesses the LCONF, the BASE24-teller Settlement Initiator process assumes that no processes are notified after settlement.

Example: P1A^TAUTH1
Param Default: No default value

TLR-SETL-TTLF-FILE-RETENTION — The number of days worth of Teller Transaction Log Files (TTLFs), prior to the current business date, which are to remain on the system. After the indicated number of days, the BASE24-teller Settlement Initiator process deletes the outdated file from the system. For example, if the value in this param is 3 and the current business date is 01/06/05 (for June 5, 2001), TTLFs dated 01/06/05 through 01/06/12 are retained on the system and open. TTLFs dated 01/06/04, 01/06/03, and 01/06/02 are retained on the system and closed. TTLFs dated 01/06/01 and earlier have been deleted from the system. Valid values are 2 through 99.

Param Default: 3

TLR-TTLF-NOTIFY-INTERVAL — The number of writes made to the Teller Transaction Log File (TTLF) before calculating the percentage of file full. Each time a write is made to the TTLF, a counter is increased. When the counter is equal to the value specified in this param, a calculation is performed to determine how full the TTLF is. The counter is then reset to zero.

When the file reaches the percent full specified in the TLR-TLF-NOTIFY-PERCENT param, a message is logged by BASE24-teller Device Handler processes or the Authorization process indicating that the file is becoming full. BASE24-teller Device Handler processes and the Authorization process continue to calculate the percentage of file full at the interval specified in this param. If the percentage has increased by one percent or more since the preceding calculation, BASE24-teller Device Handler processes or the Authorization process log a message that the file is becoming full.

Valid values are 10 through 32766. BASE24-teller Device Handler processes and the Authorization process use this param.

Param Default: 50

TLR-TTLF-NOTIFY-PERCENT — The percentage of file full at which BASE24-teller Device Handler processes and the Authorization process generates an event message indicating that the Teller Transaction Log File (TTLF) is becoming full. BASE24-teller Device Handler processes and the Authorization process calculate the percentage of file full and continues to calculate the percentage at the interval specified in the TLR-TLF-NOTIFY-INTERVAL param as described in the following paragraphs. If the percentage has increased by one percent or more since the preceding calculation, BASE24-teller Device Handler processes and the Authorization process log a message that the file is becoming full.

If the calculation results in the percentage specified in the TLR-TTLF-NOTIFY-PERCENT param, or more, of its capacity, the BASE24-teller Device Handler process or Authorization process generates an event message indicating the condition. Thereafter, the process continues to calculate the percentage of file full at the interval indicated by the TLR-TTLF-NOTIFY-INTERVAL param. When the calculated percentage of file full is less than the value of the TLR-TTLF-NOTIFY-PERCENT param, the processes stop generating events.

Valid values are 10 through 99. BASE24-teller Device Handler processes and the Authorization process use this param.

Param Default: 70

TLR-TTLFX-NOTIFY *identifier* — The symbolic name of a process that needs to be notified that the Positive Balance File (PBF), No Book File (NBF), Stop Payment File (SPF), and Warning/Hold/Float File (WHFF) are not current after an extract of the Teller Transaction Log File (TTLF) has occurred.

Each TLR-TTLFX-NOTIFY param contains the name of one process. When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the logical network. The optional *identifier* is usually a number that can be set to any numeric value from 1 through 60. For example, the TLR-TTLFX-NOTIFY1 param could contain the P1A^TAUTH1 process and TLR-TTLFX-NOTIFY2 param could contain the P1A^TAUTH2 process.

The Super Extract process uses this param.

Param Default: No default value

TLR-WARM*identifier* — The symbolic name of a process to be warmbooted. Processes that can be notified include the BASE24-teller Authorization process, Host Interface process, and BASE24-teller Device Handler process. A maximum of 150 processes can be warmbooted.

Each TLR-WARM param contains the name of one process. When multiple processes must be notified, this param can include an optional *identifier* to specify params used for different processes in the same logical network. The optional *identifier* is usually a number but can be any unique set of characters that has not already been declared by another TLR-WARM*identifier* param. For example, the TLR-WARM1 param could contain the P1A^TAUTH1 process and the TLR-WARM2 param could contain the P1A^TAUTH2 process.

The name of the BASE24-teller Settlement Initiator process should not be included in this list.

The Process Control Terminal (DCT) server process uses this param for the BASE24-teller product.

Example: P1A^TAUTH02

Param Default: No default value

TLR-WRITE-HLDS-DEP-FLOATS — A flag indicating whether to write a record to the Warning/Hold/Float File (WHFF) when processing a hold or deposit float on a Positive Balance File (PBF) record. Valid values are as follows:

0 = No, holds and deposit floats are not written to the WHFF.

1 = Yes, holds and deposit floats are written to the WHFF.

The BASE24-teller Authorization process and Super Extract process use this param.

Param Default: 1

18: Object-Oriented Application Assigns and Params

The following pages document the assigns and params used exclusively by the object-oriented applications, such as the BASE24-telebanking product. The assigns are listed first, followed by the params. The assigns and params are listed in alphabetical order.

Assigns

The following assigns are used exclusively by object-oriented application processes and objects. The following table shows you all of the usage codes that apply to object-oriented applications. Each of the following assigns should have one or more of these usage codes entered in the USAGE CODES field on the LNCF Assign screen.

Usage Code	Description
CORE	BASE24 ITS Core objects
KNL	BASE24 ITS Kernel and Integrated Endpoint (IEP) objects
TB	BASE24-telebanking

AORF — The fully qualified file name of the Assign/Object Relationship File (AORF). The Assign/Object Relationship File Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Assign/Object Relationship File Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.AORF
Usage Codes: KNL, TB

APRF — The fully qualified file name of the Assign/Process Type Relationship File (APRF). The Assign/Process Type Relationship File Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Assign/Process Type Relationship File Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.APRF
Usage Codes: KNL, TB

ASGN — The fully qualified file name of the Assign File (ASGN). The Assign File Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Assign File Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.ASGN
Usage Codes: KNL, TB

CTXEMT-SWAPVOL — The fully qualified name of the swap volume in which the Context Manager object stores data for the Context extended memory table.

If this assign is not present in the LCONF or contains an invalid value, the Integrated Endpoint process will use the volume where the executing program object is running as the swap volume.

Example: \B24.\$DATA
Usage Codes: KNL, TB

DEST — The fully qualified file name of the Destination File (DEST). The ITS Kernel Extended Memory Table Build utility and the Destination File Server process use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Destination File Server process displays an error message indicating that the assign needs to be corrected, and the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops.

Example: \B24.\$DATA.PRO1DATA.DEST
Usage Codes: KNL, TB

DESTEMT — The fully qualified file name of the Destination extended memory table. The ITS Kernel Extended Memory Table Build utility and the Destination object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility and the Integrated Endpoint process are unable to open or create the Destination extended memory table and stop.

Example: \B24.\$DATA.PRO1DATA.DESTEMT
Usage Codes: KNL, TB

EMT — The fully qualified file name of the Extended Memory Table File (EMT). The Extended Memory Table File Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Extended Memory Table File Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.EMT
Usage Codes: KNL, TB

EORF — The fully qualified file name of the Extended Memory Table/Object Relationship File (EORF). The Extended Memory Table/Object Relationship File Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Extended Memory Table/Object Relationship File Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.EORF
Usage Codes: KNL, TB

EPRF — The fully qualified file name of the Extended Memory Table/Process Type Relationship File (EPRF). The Extended Memory Table/Process Type Relationship File Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Extended Memory Table/Process Type Relationship File Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.EPRF
Usage Codes: KNL, TB

ESEMT — The fully qualified file name of the Event Suppression extended memory table. The ITS Kernel Extended Memory Table Build utility, Event object, and Log Permission object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the appropriate process or object logs an error message indicating that the assign needs to be corrected. The ESEMT will not be built and event suppression will not be performed until the ESEMT assign is valid.

Example: \B24.\$DATA.PRO1DATA.ESEMT
Usage Codes: KNL, TB

ESF — The fully qualified file name of the Event Suppression File (ESF). The Event Suppression File Server process and ITS Kernel Extended Memory Table Build utility use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Event Suppression File Server process and ITS Kernel Extended Memory Table Build utility log an error message indicating that this assign is invalid.

Example: \B24.\$DATA.PRO1DATA.ESF
Usage Codes: KNL, TB

ISCF-server class — The fully qualified name of the Integrated Server Control File (ISCF). The server class to which the ISCF applies is included in the assign name. Each server class must have a separate ISCF assign. The Integrated Server Control File Server process, Process Control object, and Enscribe Refresh process use this assign.

The name of this assign, including the *server class* variable, must match the value in the CONTROL FILE ASSIGN field on Server Class Type File (SCT) screen 1.

If this assign is not present in the LCONF or contains an invalid value, the Integrated Server Control File Server process and Enscribe Refresh process display an error message indicating that the assign needs to be corrected, and the processes that contain the Process Control object do not initialize.

Examples: \B24.\$DATA.PRO1DATA.ISCFIEP (data file name)
 \B24.\$DATA.PRO1TPLT.ISCF (template file name)
 Note: Because the Process Control object appends a version indicator to the ISCF file name, the file portion of the file name (ISCFIEP and ISCF in these examples) cannot exceed seven characters in length.

Usage Codes: KNL, TB
Template File: Required to build the new file when the existing file is full.

LPF — The fully qualified file name of the Log Permission Process Partition File (LPF). The Log Permission Process Partition File Server process and the Event object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Log Permission Process Partition File Server process displays an error message indicating that the assign needs to be corrected, and processes that contain the Event object log an error message indicating that the LPF assign is invalid and do not perform network-level event suppression.

Example: \B24.\$DATA.PRO1DATA.LPF
Usage Codes: KNL, TB

LPP-process — The fully qualified PPD name of a Log Permission process, where *process* is the symbolic name of the Log Permission process to which this assign applies. The Event object uses this assign. The last character of the *process* variable in the assign name should match the last character of the PPD name it defines.

Each LPP must have its own LPP assign defined by the LPF.

Example: \B24.\$LPP1 is the PPD name for the LPP-P1A^LPP1 assign.
Usage Codes: KNL, TB

OBJ — The fully qualified name of the Object File (OBJ). This assign is used by the following:

Object File Server process
ITS Kernel Extended Memory Table Build utility
Enscribe Refresh process
Process Control object

If this assign is not present in the LCONF or contains an invalid value, the Object File Server process displays an error message indicating that the assign needs to be corrected, the ITS Kernel Extended Memory Table Build utility logs an error message to its report file and stops, and the Enscribe Refresh process and processes that use the Process Control object do not initialize.

Example: \B24.\$DATA.PRO1DATA.OBJ
Usage Codes: KNL, TB

PATHMON-NAM — The fully qualified name of the PATHMON process. This assign is used by the ITS Kernel Extended Memory Table Build utility.

Examples: \B24.\$PPMN
Usage Codes: KNL

PCTLEMT-SWAPVOL — The fully qualified name of the swap volume in which the Process Control object stores the process set and server class set involved in processing Integrated Server Control File (ISCF) Write requests. The Process Control object uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the default volume is used and the Process Control object generates an error message.

Example: \B24.\$SWAP
Usage Codes: KNL, TB

PORF — The fully qualified name of the Process/Object Relationship File (PORF). This assign is used by the following:

Process/Object Relationship File Server process
Enscribe Refresh process
Process Control object

If this assign is not present in the LCONF or contains an invalid value, the Process/Object Relationship File Server process displays an error message indicating that the assign needs to be corrected, and the Enscribe Refresh process and processes that contain the Process Control object do not initialize.

Example: \B24.\$DATA.PRO1DATA.PORF
Usage Codes: KNL, TB

PRO — The fully qualified file name of the Process File (PRO). The Process File Server process and the Process Control object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the Process File Server process and the processes that contain the Process Control object log an error message indicating that this assign is invalid. Process-related control functions will not work properly until this assign is corrected.

Example: \B24.\$DATA.PRO1DATA.PRO
Usage Codes: KNL, TB

PTF — The fully qualified file name of the Process Type File (PTF). The Process Type File Server process uses this assign.

If this assign is not present in the LCONF or contains an invalid value, the Process Type File Server process displays an error message indicating that the assign needs to be corrected.

Example: \B24.\$DATA.PRO1DATA.PTF
Usage Codes: KNL, TB

SCM — The fully qualified file name of the Source Class Map File (SCM). The Source Class Map File Server process and the ITS Kernel Extended Memory Table Build utility use this assign. The ITS Kernel Extended Memory Table Build utility requires this assign to build the Source Class Map extended memory table.

If this assign is not present in the LCONF or contains an invalid value, the Source Class Map File Server process and the ITS Kernel Extended Memory Table Build utility log an error message indicating that this assign is invalid. In addition, the Source Class Map extended memory table cannot be built until this assign is corrected.

Example: \B24.\$DATA.PRO1DATA.SCM
Usage Codes: KNL, TB

SCMEMT — The fully qualified name of the Source Class Map extended memory table. The ITS Kernel Extended Memory Table Build utility and Class object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility and the processes that contain the Class object log an error message indicating that this assign is invalid.

Example: \B24.\$DATA.PRO1DATA.SCMEMT
Usage Codes: KNL, TB

SCT — The fully qualified file name of the Server Class Type File (SCT). This assign is used by the following:

Server Class Type File Server process
Enscribe Refresh process
Process Control object

If this assign is not present in the LCONF or contains an invalid value, the processes listed above and the processes that contain the Process Control object log an error message indicating that this assign is invalid.

Example: \B24.\$DATA.PRO1DATA.SCT
Usage Codes: KNL, TB

SPRF — The fully qualified file name of the Server Class/Process Relationship File (SPRF). This assign is used by the following:

Enscribe Refresh process
Server Class/Process Relationship File Server process
Process Control object

If this assign is not present in the LCONF or contains an invalid value, the processes listed above and the processes that contain the Process Control object log an error message indicating that this assign is invalid.

Example: \B24.\$DATA.PRO1DATA.SPRF
Usage Codes: KNL, TB

SSMENT — The fully qualified name of the Source Symbolic Map extended memory table. The ITS Kernel Extended Memory Table Build utility and the XPNET Interface object use this assign.

If this assign is not present in the LCONF or contains an invalid value, the ITS Kernel Extended Memory Table Build utility and the processes that contain the XPNET Interface object log an error message indicating that this assign is invalid. Processes with the XPNET Interface object will not be able to perform source class retrieval processing until this assign is corrected.

Example: \B24.\$DATA.PRO1DATA.SSMEMT
Usage Codes: KNL, TB

TRCENT-SWAPVOL — The fully qualified name of the swap volume in which the Trace object stores trace information before writing it to disk.

If this assign is not present in the LCONF or contains an invalid value, processes that contain the Trace object do not initialize.

Example: \B24.\$DATA
Usage Codes: KNL, TB

Params

The following params are used exclusively by object-oriented application processes and objects. The following table shows you all of the product use codes that apply to object-oriented applications. Each of the following params should have one or more of these use codes entered in the Product Use field on the LNCF Param screen.

Product Use Code	Description
CORE	BASE24 ITS Core objects
KNL	BASE24 ITS Kernel and Integrated Endpoint (IEP) objects
TB	BASE24-telebanking

CPFEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Card Prefix File (CPF) extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table. The ITS Kernel Extended Memory Table Build utility uses this param.

Usage Codes: KNL
Param Default: 127

CTX-SECND-ALLOC — The number of blocks of additional memory an Endpoint Class Handler object requests for context storage when the primary allotment of memory blocks is not sufficient. The Endpoint Class Handler object requests additional memory in multiples of the amount specified in this param. Valid values are 0 through 32767.

The READ BY field on the LNCF Param screen contains the type of endpoint to which the param applies. Valid values are as follows:

GENE = Generic endpoint
VRU = Interactive voice response (IVR) system
***** = Default record for all endpoints

Usage Codes: KNL, TB
Read By: Type of endpoint to which this param applies
Param Default: 2

CTXEMT-CONTEXT-PAGES — The total number of pages (4096 bytes per page) of memory needed to store context during peak transaction processing for all Endpoint Class Handler objects in the Integrated Endpoint process.

The Context Manager object uses this param.

Usage Codes: KNL, TB

Param Default: 0

DESTENT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Destination File (DEST) extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Usage Codes: KNL, TB

Param Default: 127

ESEMT-MAX-TBL-SIZE — The maximum size (in megabytes) of the event suppression extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Usage Codes: KNL, TB

Param Default: 127

IEP-SYM-NAM — The symbolic name of an Integrated Endpoint process simulator. This param enables a test network user to specify a simulator name as an Integrated Endpoint process symbolic name. If the param is found, the ITS Kernel Extended Memory Table Build utility updates the Station Table entry for the IEP symbolic name in the Interface extended memory table with the param value. If the param is not found, a report message is written to inform the user that an invalid Station Table entry exists.

Usage Codes: KNL, TB

Param Default: No default value

LPP-TIME-LIMIT — The length of time, in hundredths of seconds, that the Event object waits for a response from the Log Permission process when processing network-level event suppression requests. Valid values are 50 through 500.

Usage Codes: KNL, TB
Param Default: 100 (1 second)

MAX-LPP-PROCESSES — The maximum number of Log Permission processes that can be configured in a logical network. Valid values are 0 through 32,767.

The Event object uses this param.

Usage Codes: KNL, TB
Param Default: 2

NETLIST-CPU — The CPU in which the Netlist utility is to run. Valid values are 0 through 15.

The ITS Kernel Extended Memory Table Build utility uses this param.

Usage Codes: KNL, TB
Param Default: 0

NETLIST-PRI — The execution priority at which the Netlist utility is to run. Valid values are 1 through 199.

The ITS Kernel Extended Memory Table Build utility uses this param.

Product Use: KNL, TB
Param Default: 100

NOM-PERCENT-THRESHOLD — The percentage at which network overload is detected for an Integrated Server process or queue.

If this param is set to a nonzero value and the value of the Network Overload Management Percent field in the header of a network message received from the XPNET process is equal to or exceeds the value of this param, the XPNET Interface object sets this field to a value of 101. This value indicates that the process or queue is currently overloaded.

If this param is set to a value of 0, network overload management processing is not performed and the XPNET Interface object sets the Network Overload Management Percent field in the header to a value of 0.

Valid values for this param are 0 through 100.

Usage Codes: KNL, TB

Param Default: 50

PCTLEMT-SEGSIZE — The number of pages in a segment of the Process Control memory table. A page is equal to 2048 bytes. Valid values are 0 through 32767.

All processes that contain the Process Control object use this param.

Usage Codes: KNL, TB

Param Default: 512

PROCESS-EVENT-TABLE-SIZE — The maximum number of entries permitted in the Process Event Table (PET). The Event object uses the Process Event Table to hold entries for process level event suppression. The Event object also uses the Process Event Table to reduce the number of times it must call the Log Permission process to perform logical network event suppression.

Usage Codes: KNL, TB

Param Default: 32

QED — Queue evaluation delay. The length of time, in hundredths of seconds, the XPNET Interface object waits before reevaluating the queue for its process once queuing reaches an overload condition. Valid values are 1000 through 6000.

Usage Codes: KNL, TB

Param Default: 1000 (10 seconds)

ROUTE-OBJECT-ID — The identifier of the object to which the Internal Message Translation Interface object routes transactions received from a procedural entity. The Internal Message Translation Interface object uses this param. If this param is missing or invalid, it defaults to the identifier of the Router object.

Usage Codes: CORE, TB
Param Default: 1020 (Router object ID)

SCMENT-MAX-TBL-SIZE — The maximum size (in megabytes) of the Source Class Map File extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Usage Codes: KNL, TB
Param Default: 127

SSMENT-MAX-TBL-SIZE — The maximum size (in megabytes) of the source symbolic map extended memory table. This param is used to set the amount of memory allocated by the ITS Kernel Extended Memory Table Build utility for the table.

Usage Codes: KNL, TB
Param Default: 127

Index

A

Accessing the LCONF, [1-8](#)
ACI Commerce Gateway product, LCONF param used, [15-60](#)
Adding a param, [5-8](#)
Adding an assign, [4-8](#)
Application Configuration Table (ACT), [1-3](#)
ASSIGN NAME field description, [4-4](#)
Assigns
 adding, [4-8](#)
 deleting, [4-9](#)
 for Enscribe files, [1-2](#)
 for hardware, [1-2](#)
 for SQL tables, [1-2](#)
 updating, [4-7](#)
 updating filenames in, [4-7](#)

B

BASE24 Virtual Menu, [2-3](#)
Broadcast notification, [7-49](#)

C

CHANGE SUBVOL NAME field description, [6-4](#)
CHANGE SYSTEM NAME field description, [6-3](#)
CHANGE VOLUME NAME field description, [6-4](#)
COMMENTS field description, [4-5](#), [5-5](#)

D

Defines for SQL tables, [1-2](#)
Deleting a param, [5-8](#)
Deleting an assign, [4-9](#)
Displaying the assign, param, or edit screen, [3-6](#)
Displaying the LNCf Assign screen, [4-6](#)
Displaying the LNCf Edit screen, [6-5](#)
Displaying the LNCf Param screen, [5-6](#)

E

ENTER DESIRED USAGE CODES field description, [3-4](#)
Exiting from the LNCf Assign screen, [4-9](#)

Exiting from the LNCf Edit screen, [6-6](#)
Exiting from the LNCf Param screen, [5-9](#)

F

File access, BASE24 Virtual Menu, [2-3](#)
FILE-NAME field description, [3-3](#)
Function keys, standard, [2-4](#)

H

Help screens, [2-5](#)

I

ITEM TYPE field description, [3-4](#)

L

LCONF assigns and params
 LCONF assign definition, [1-2](#)
 LCONF param definition, [1-2](#)
LCONF File specifications
 file creation, [1-4](#)
 file security, [1-4](#)
LCONFLD program, [1-5](#)
LCONFLDR command file, [1-5](#)
LNCf Assign screen
 field descriptions, [4-3](#)
 function keys, [4-2](#)
 procedures, [4-6](#)
 screen illustration, [4-3](#)
LNCf Edit screen
 field descriptions, [6-3](#)
 function keys, [6-2](#)
 procedures, [6-5](#)
 screen illustration, [6-3](#)
LNCf Param screen
 field descriptions, [5-3](#)
 function keys, [5-2](#)
 procedures, [5-6](#)
 screen illustration, [5-3](#)
LNCf Printing screen
 field descriptions, [3-3](#)
 function keys, [3-2](#)
 procedures, [3-6](#)
 screen illustration, [3-3](#)

LNCF Requester process, [2-1](#)
LNCF Server process, [2-1](#)
LNCFTBLS file, [3-4](#)
LOCATION/ID field description, [4-4](#)

P

PARAM NAME field description, [5-4](#)
Params
 adding, [5-8](#)
 deleting, [5-8](#)
 for BASE24 retail products, [1-3](#)
 for BASE24-check auth, [1-3](#)
 for BASE24-frequent shopper, [1-3](#)
 for BASE24-refunds, [1-3](#)
 searching for, [5-6](#)
 updating, [5-7](#)
Pseudo process names, [1-9](#)

R

READ BY field description, [4-3](#), [5-3](#)
Reading a specific assign, [4-6](#)
Reading a specific param, [5-6](#)
Reading forward through multiple assigns, [4-7](#)
Reading forward through multiple params, [5-7](#)
REPORT LOCATION field description, [3-4](#)
Reports
 assign report, [3-9](#)
 param report, [3-12](#)

S

Searching for a param, [5-6](#)
Searching for an assign, [4-6](#)
Sending a param to a spooler location, [5-9](#)
Sending an assign to a spooler location, [4-9](#)
Sending reports to a spooler location, [3-6](#)

T

TEMPLATE FILE field description, [4-4](#)
TEXT field description, [5-4](#)
TO field description, [6-3](#), [6-4](#)

U

Updating a param, [5-7](#)
Updating an assign, [4-7](#)
Updating system, volume, or subvolume names, [6-5](#)
USAGE CODES field description, [4-5](#), [5-4](#)
Usage codes, adding, [3-4](#)
USER FIELD field description, [4-5](#)

Index by Assign Name

A

ADRT, [16-2](#)
ALT-COLL, [7-2](#)
AORF, [18-2](#)
APCF, [7-2](#)
APCFEMT, [7-3](#)
APRF, [18-2](#)
ARF, [7-3](#)
ASGN, [18-2](#)
ATM-ADCF, [8-2](#)
ATM-ATD-DYN-GNRL, [8-2](#)
ATM-ATD-DYN-SCRATCH-PAD, [8-3](#)
ATM-ATD-EXTMEM-SWAPVOL, [8-3](#)
ATM-ATD-STATIC-GNRL, [8-3](#)
ATM-DAILY-REPORT-DESTINATION, [8-4](#)
ATM-DAILY-REPORT-OBEYFILE, [8-4](#)
ATM-DAILY-REPORT-PROGRAM, [8-4](#)
ATM-DH-ATD-EXTMEM-SWAPVOL, [8-4](#)
ATM-DH-CI4730, [8-5](#)
ATM-DH-CILOAD, [8-5](#)
ATM-DH-CNF1000, [8-6](#)
ATM-DH-CNF5070, [8-6](#)
ATM-DH-CNF5100, [8-7](#)
ATM-DH-CNF910, [8-5](#)
ATM-DH-CNF912, [8-6](#)
ATM-DH-CNFFUJ, [8-7](#)
ATM-DH-CNFUJ7, [8-7](#)
ATM-DH-FUJ7-CPLF, [8-7](#)
ATM-DH-HPL5100, [8-8](#)
ATM-DH-MC4730, [8-8](#)
ATM-DH-MDS1000-CPLF, [8-8](#)
ATM-DH-MP4730, [8-9](#)
ATM-DH-N50-CPLF, [8-9](#)
ATM-DH-OIF1000, [8-9](#)
ATM-DH-OLI6-LOAD-FILE, [8-9](#)
ATM-DLY-RPT-STARTUP, [8-49](#)
ATM-MONTHLY-REPORT-DESTINATION, [8-10](#)
ATM-MONTHLY-REPORT-OBEYFILE, [8-10](#)
ATM-MONTHLY-REPORT-PROGRAM, [8-10](#)

ATM-MTAF, [8-10](#)
ATM-NIDF, [8-11](#)
ATM-NIDFEMT, [8-11](#)
ATM-RCPT, [8-11](#)
ATM-SETL-ATD-EXTMEM-SWAPVOL, [8-12](#)
ATM-SETL-MON-RPT-PROG-3-NAME, [8-12](#)
ATM-SETL-MON-RPT-PROG-5-NAME, [8-12](#)
ATM-SETL-RPT0-OBEY-FILE, [8-12](#)
ATM-SETL-RPT0-PROG-1-NAME, [8-13](#)
ATM-SETL-RPT0-PROG-2-NAME, [8-13](#)
ATM-SETL-RPT0-PROG-4-NAME, [8-14](#)
ATM-SETL-RPT0-PROG-6-NAME, [8-14](#)
ATM-SETL-RPT0-PROG-7-NAME, [8-15](#)
ATM-SETL-RPT0-PROG-8-NAME, [8-15](#)
ATM-SETL-RPT1-OBEY-FILE, [8-12](#)
ATM-SETL-RPT1-PROG-1-NAME, [8-13](#)
ATM-SETL-RPT1-PROG-2-NAME, [8-13](#)
ATM-SETL-RPT1-PROG-4-NAME, [8-14](#)
ATM-SETL-RPT1-PROG-6-NAME, [8-14](#)
ATM-SETL-RPT1-PROG-7-NAME, [8-15](#)
ATM-SETL-RPT1-PROG-8-NAME, [8-15](#)
ATM-SETL-RPT3M, [8-16](#)
ATM-SETL-RPT3T, [8-16](#)
ATM-SETL-RPT5M, [8-17](#)
ATM-SETL-RPT5T, [8-17](#)
ATM-TRF, [8-19](#)
ATM-TRFEMT, [8-19](#)
ATM-TRN-THF, [8-19](#)
ATT, [7-3](#)

B

BNIIF, [7-4](#)
BNRLF, [7-4](#)
BP-ADMN, [15-2](#)
BP-ANEG, [15-2](#)
BP-ARCHIVE, [9-7](#)
BP-AST, [15-2](#)
BP-BNEG, [15-3](#)
BP-BNR, [15-3](#)

BP-CAPF, [15-3](#)
 BP-CRUF, [15-4](#)
 BP-CSEC, [15-4](#)
 BP-INEG, [15-4](#)
 BP-INR, [15-4](#)
 BP-REMIT, [9-7](#)
 BP-RPTR, [15-5](#)
 BP-RTBL, [15-5](#)
 BRIDGE-NAME, [7-4](#)

C

CACT-PART, [16-2](#)
 CAF*Identifier*, [7-5](#)
 CCIF, [11-2](#)
 CCIF*Identifier*, [11-2](#)
 CCMF, [11-3](#)
 CCMF*Identifier*, [11-3](#)
 CPCONF, [7-5](#)
 CPF, [7-5](#)
 CPFEMT, [7-6](#)
 CPIT-PART, [16-3](#)
 CPLF, [8-19](#)
 CRT-ADMN-AQF, [15-5](#)
 CRT-AUTH-CHF, [15-6](#)
 CRT-AUTH-TQF, [15-6](#)
 CRT-AUTH-TQFT, [15-6](#)
 CSTT-PART, [16-3](#)
 CTXEMT-SWAPVOL, [18-3](#)
 CUSTEMT, [16-4](#)

D

DCC-CRNCY-RATE-SOURCE, [7-57](#)
 DCCD, [7-6](#)
 DCCDEMT, [7-7](#)
 DCT-LOG, [7-7](#)
 DEST, [18-3](#)
 DESTEMT, [18-3](#)

E

ECF, [7-7](#)
 ELF, [16-4](#)
 EMF, [7-7](#)
 EMF5, [7-8](#)
 EMT, [18-4](#)
 EMT-SWAPVOL, [7-8](#)
 EORF, [18-4](#)
 EPRF, [18-4](#)

ERF, [7-8](#)
 ERFEMT, [7-9](#)
 ERIIF, [7-9](#)
 ESEMT, [18-4](#)
 ESF, [18-5](#)

F

FCF, [16-5](#)
 FHM-CSFC-RPT-PROG-NAME, [12-2](#)
 FHM-CUST-RPT-PROG-NAME, [12-2](#)
 FHM-PSNL-RPT-PROG-NAME, [12-2](#)
 FHM-RPT-CMD-FILE, [12-2](#)
 FHM-RPT-OBEY-FILE, [12-3](#)
 FHM-RPT-PROG-NAME, [12-3](#)
 FRLF, [7-9](#)
 FUP-FILE-NAME, [7-10](#)
 FUP-OUTFILE-NAME, [7-10](#)

G

GENSIM-SIMCMDS, [7-10](#)

H

HCF, [7-10](#)
 HMBF, [14-2](#)
 HMTF, [14-2](#)
 HSF, [8-19](#)

I

IAS-symbolic-name, [16-5](#)
 ICF, [7-10](#)
 ICFE, [7-11](#)
 IDF, [7-11](#)
 IDFEMT, [7-13](#)
 IFCF, [16-5](#)
 ILF, [7-13](#)
IMP-symbolic-name, [16-5](#)
 IMTEMT, [16-6](#)
 IMTF, [16-6](#)
 INTFEMT, [16-6](#)
 INV-EXP-STOCK-CLEANUP-REP-LOC, [13-2](#)
 INV-GROUP-STOCK-DELETE-REP-LOC, [13-2](#)
 INV-REFR-REP, [13-2](#)
 INV-SOLD-STOCK-CLEANUP-REP-LOC, [13-2](#)
 IPCF, [7-14](#)
 IPCFEMT, [7-14](#)
 IPRF, [16-7](#)
 IRCF, [16-7](#)

IRTEEMT, [16-7](#)
ISCF-*server class*, [18-5](#)
ISECEMT-SWAPVOL, [16-8](#)
ISF, [16-8](#)
IST, [16-8](#)
ITF, [7-15](#)

K

KEY5, [7-15](#)
KEY6, [7-15](#)
KEYA, [7-16](#)
KEYAEMT, [16-8](#)
KEYD, [15-7](#)
KEYF, [7-16](#)
KEYI, [7-17](#)

L

LCF, [16-9](#)
LCONF-RPT-LOC, [7-17](#)
LMCF, [7-18](#)
LOG, [14-2](#)
LPF, [18-6](#)
LPP-*process*, [18-6](#)

M

MBAF, [14-2](#)
MBF, [14-2](#)
MOF, [7-18](#)
MTF, [14-3](#)

N

NBF, [17-2](#)
NCSP, [7-18](#)
NCSS, [7-18](#)
NEG*identifier*, [7-18](#)
NETLIST-PROG, [7-19](#)
NRIF, [13-2](#)
NSCF, [13-2](#)
NTLF, [13-3](#)

O

OBJ, [18-6](#)
OMF, [7-19](#)

P

PAM, [7-20](#)

PATHMON-NAM, [18-7](#)
PBFEMT-SWAPVOL, [16-9](#)
PBF*identifier*, [7-20](#)
PCDF, [16-9](#)
PCTLEMT-SWAPVOL, [18-7](#)
PCT-LOG, [7-21](#)
PDF, [7-21](#)
PISO-ISF, [7-21](#)
PISO-MLF, [7-22](#)
PIT-PART, [16-10](#)
PLUS-PPF, [7-22](#)
PORF, [18-7](#)
POS-ALTKEY-SCRATCH-FILE, [15-7](#)
POS-CARD-OBEYFILE, [15-7](#)
POS-CART, [15-7](#)
POS-DAILY-REPORT-DESTINATION, [15-7](#)
POS-DAILY-REPORT-OBEYFILE, [15-8](#)
POS-DAILY-REPORT-PROGRAM, [15-8](#)
POS-DH-PTD-EXTMEM-SWAPVOL, [15-8](#)
POS-DLY-RPT-STARTUP, [15-42](#)
POS-EAF, [15-8](#)
POS-EAF-PREV, [15-9](#)
POS-HPDH-HPCF, [15-9](#)
POS-HPDH-HPTC, [15-9](#)
POS-MONTHLY-REPORT-DESTINATION, [15-9](#)
POS-MONTHLY-REPORT-OBEYFILE, [15-10](#)
POS-MONTHLY-REPORT-PROGRAM, [15-10](#)
POS-MTAF, [15-10](#)
POS-PIRF, [15-11](#)
POS-PRDF, [15-11](#)
POS-PRRF, [15-11](#)
POS-PTD-DYN-GNRL, [15-11](#)
POS-PTD-DYN-SCRATCH-PAD, [15-12](#)
POS-PTD-EXTMEM-SWAPVOL, [15-12](#)
POS-PTDF, [15-13](#)
POS-PTD-STATIC-GNRL, [15-13](#)
POS-PTLF, [15-13](#)
POS-RPT-2, [15-14](#)
POS-RPT-21, [15-14](#)
POS-RPT-22, [15-14](#)
POS-RPT-2R, [15-15](#)
POS-RPT-30, [15-15](#)
POS-RPT-35, [15-15](#)
POS-RPT-CPU, [15-54](#)
POS-RPT-ERR-FILE, [15-15](#)
POS-SETL-PTD-EXTMEM-SWAPVOL, [15-15](#)
POS-SETL-RPT-1, [15-15](#)
POS-SETL-RPT-1R, [15-16](#)

POS-SETL-RPT-PROG-1-NAME, [15-16](#)
POS-SETL-RPT-PROG-2-NAME, [15-16](#)
POS-SETL-RPT-PROG-30-NAME, [15-17](#)
POS-SETL-RPT-PROG-35-NAME, [15-17](#)
POS-SETL-RPT-PROG-4-NAME, [15-16](#)
POS-SETL-RPT-PROG-5-NAME, [15-17](#)
POS-SPDH-ACNF, [15-18](#)
POS-SPDH-ARSP, [15-18](#)
POS-SV-CPF-EXTMEM-SWAPVOL, [15-18](#)
POS-SVDF, [15-20](#)
POS-SV-DORMANCY-REPORT, [15-18](#)
POS-SV-ESCHEATMENT-RPT, [15-19](#)
POS-SVHF, [15-20](#)
POS-SV-IDF-EXTMEM-SWAPVOL, [15-19](#)
POS-SV-PTLF-EXTMEM-SWAPVOL, [15-19](#)
POS-SV-RETAIL-EXTMEM-SWAPVOL, [15-19](#)
POS-SV-SVDF-EXTMEM-SWAPVOL, [15-19](#)
POS-TRN-THF, [15-20](#)
PRI-COLL, [7-22](#)
PRM-PTBL, [7-23](#)
PRO, [18-7](#)
PTF, [18-8](#)

R

RAM-CNFG, [7-23](#)
RB-TRN-THF, [16-10](#)
RCDF, [15-20](#)
RCDFEMT, [15-21](#)
RCPT, [8-20](#)
RCPTMT, [8-20](#)
REF-RPT-SQL, [16-11](#)
REF-SOURCEDICT, [16-11](#)
REMOTE-LCONF, [8-20](#)
REMOTE-PMON, [8-21](#)
RGCF, [7-23](#)
RPT, [7-23](#)
RPT-ERROR-FILE, [7-24](#)
RPTR, [7-25](#)
RSAF, [7-25](#)

S

SAF, [7-25](#)
SCM, [18-8](#)
SCMEMT, [18-8](#)
SCT, [18-8](#)
SDF, [7-26](#)
SEC, [7-26](#)

SECURE-DEV1, [7-27](#)
SECURE-DEV2, [7-29](#)
SECURE-DEVICEn, [16-11](#)
SECURE-DEV-xx, [7-32](#)
SEMF, [7-33](#)
SNF, [7-33](#)
SPANCTL, [7-34](#)
SPFIdentifier, [7-34](#)
SPRF, [18-9](#)
SSB-BSF, [8-21](#)
SSB-CCF, [8-21](#)
SSB-CSF, [8-22](#)
SSMEMT, [18-9](#)
STF, [7-35](#)
STRF, [7-35](#)
STRFEMT, [7-35](#)
SURF, [7-36](#)
SVCSREMT-SWAPVOL, [16-12](#)
SVRPT-ERR-LOG, [8-22](#)
SVTLFEMT-SWAPVOL, [16-13](#)
SWCH-IIF, [7-37](#)
SW-RPT01-PROG-NAME, [7-36](#)
SW-RPT09-PROG-NAME, [7-37](#)
SW-RPT-OBEY-FILE, [7-36](#)

T

TB-DAILY-REPORT-DESTINATION, [16-13](#)
TB-DAILY-REPORT-OBEYFILE, [16-13](#)
TB-DAILY-REPORT-PROGRAM, [16-13](#)
TB-DLY-RPT-STARTUP, [16-34](#)
TB-MONTHLY-REPORT-DESTINATION, [16-14](#)
TB-MONTHLY-REPORT-OBEYFILE, [16-14](#)
TB-MONTHLY-REPORT-PROGRAM, [16-14](#)
TB-RBAF, [16-14](#)
TB-RPT-CPU, [16-34](#)
TB-RPT-ISS-FS-DIST, [16-15](#)
TB-RPT-ISS-FS-DIST-SORTPROG, [16-15](#)
TB-RPT-ISS-FS-DIST-SWAP, [16-15](#)
TB-RPT-ISS-FS-SS1, [16-16](#)
TB-RPT-ISS-FS-SS1-SORTPROG, [16-16](#)
TB-RPT-ISS-FS-SS1-SWAP, [16-16](#)
TB-RPT-ISS-FS-SS2, [16-17](#)
TB-RPT-ISS-FS-SS2-SORTPROG, [16-17](#)
TB-RPT-ISS-FS-SS2-SWAP, [16-17](#)
TB-RPT-ISS-FS-SS3, [16-17](#)
TB-RPT-ISS-FS-SS3-SORTPROG, [16-18](#)
TB-RPT-ISS-FS-SS3-SWAP, [16-18](#)
TB-RPT-ISS-FS-SS4, [16-18](#)

TB-RPT-ISS-FS-SS4-SORTPROG, [16-19](#)
TB-RPT-ISS-FS-SS4-SWAP, [16-19](#)
TB-RPT-ISS-FS-SS5, [16-19](#)
TB-RPT-ISS-FS-SS5-SORTPROG, [16-20](#)
TB-RPT-ISS-FS-SS5-SWAP, [16-20](#)
TB-RPT-ISS-FS-SS6, [16-20](#)
TB-RPT-ISS-FS-SS6-SORTPROG, [16-21](#)
TB-RPT-ISS-FS-SS6-SWAP, [16-21](#)
TB-RPT-ISS-FS-SS7, [16-21](#)
TB-RPT-ISS-FS-SS7-SORTPROG, [16-22](#)
TB-RPT-ISS-FS-SS7-SWAP, [16-22](#)
TB-RPT-ISS-FS-SS8, [16-22](#)
TB-RPT-ISS-FS-SS8-SORTPROG, [16-23](#)
TB-RPT-ISS-FS-SS8-SWAP, [16-23](#)
TB-RPT-ISS-NAME, [16-23](#)
TB-RPT-ISS-OBEY-FILE, [16-24](#)
TB-RPT-ISS-OUT-FILE, [16-24](#)
TB-RPT-ISS-SORTFILE, [16-24](#)
TB-RPT-ISS-SWAPFILE, [16-24](#)
TB-RPT-ISS-TB01-LOC, [16-25](#)
TB-RPT-ISS-TB02-LOC, [16-25](#)
TB-RPT-ISS-TB03-LOC, [16-25](#)
TB-RPT-ISS-TB04-LOC, [16-25](#)
TB-RPT-ISS-TB05-LOC, [16-26](#)
TB-RPT-ISS-TB06-LOC, [16-26](#)
TCF, [7-38](#)
TDF, [8-22](#)
THCF, [16-26](#)
THFEMT, [16-27](#)
THF-group, [16-26](#)
TKN, [7-38](#)
TLF, [8-23](#)
TLF-DEFAULT, [16-27](#)
TLFEMT, [16-28](#)
TLF-group, [16-28](#)
TLR-DAILY-REPORT-DESTINATION, [17-2](#)
TLR-DAILY-REPORT-OBEYFILE, [17-3](#)
TLR-DAILY-REPORT-PROGRAM, [17-3](#)
TLR-DCT-LOG, [17-3](#)
TLR-DLY-RPT-STARTUP, [17-11](#)
TLR-MONTHLY-REPORT-DESTINATION, [17-3](#)
TLR-MONTHLY-REPORT-OBEYFILE, [17-4](#)
TLR-MONTHLY-REPORT-PROGRAM, [17-4](#)
TLR-MTAF, [17-4](#)
TLR-ORF, [17-5](#)
TLR-RPT-CPU, [17-12](#)
TLR-RPT-CRD-ACTIVITY, [17-5](#)
TLR-RPT-DLY-DETAIL, [17-5](#)

TLR-RPT-DLY-TIM, [17-5](#)
TLR-RPT-DLY-TLR, [17-5](#)
TLR-RPT-DLY-TYP, [17-6](#)
TLR-RPT-NTWK-CLEARINGS, [17-6](#)
TLR-RPT-PERIODIC-TIM, [17-6](#)
TLR-RPT-PERIODIC-TLR, [17-6](#)
TLR-RPT-PERIODIC-TYP, [17-6](#)
TLR-RTTB, [17-7](#)
TLR-RTTF, [17-7](#)
TLR-TRN-THF, [17-7](#)
TLR-TTDF, [17-7](#)
TLR-TTF, [17-7](#)
TLR-TTLF, [17-8](#)
TLR-WHFF, [17-8](#)
TRCEMT-SWAPVOL, [18-9](#)
TSRF, [7-39](#)

U

UFIR, [7-39](#)
ULF, [12-3](#)
UPFR, [7-39](#)

V

VISA-ISF, [7-39](#)

ACI Worldwide, Inc.

Index by Param Name

A

ACCOUNT-NUM-RPT, [10-2](#)
ACCT-NUM-TYP, [7-41](#)
ADDL-DATA-SEND, [7-42](#)
ADJ-ADVICE-RC, [15-22](#)
AFT-PAN-DIGITS, [7-42](#)
ALT-TIM-LMT, [7-43](#)
APCFEMT-MAX-TBL-SIZE, [7-43](#)
APCFEMT-WARM*Identifier*, [7-43](#)
ATM-A4000-MASTER, [8-24](#)
ATM-ACQ-DISCR-DATA-SUPPRS, [8-24](#)
ATM-AUTH-IDF-DATES-COMPUTE, [8-24](#)
ATM-BALANCE-OPTION, [7-44](#)
ATM-DH-1000-AKDS-SERIAL-NUM-VRFY, [8-25](#)
ATM-DH-ADDENDS, [8-25](#)
ATM-DH-AKDS-TSS-TIMER, [8-26](#)
ATM-DH-AUTH-TIMER, [8-26](#)
ATM-DH-CHK-BIN-THRHL, [8-27](#)
ATM-DH-CHK-DISP-FAULT-ACT, [8-27](#)
ATM-DH-CONNECT-MSGS, [8-28](#)
ATM-DH-CONS-MAC-ERR-LMT, [8-28](#)
ATM-DH-DISCONNECT-X25-REQD, [8-29](#)
ATM-DH-DISPLAY-NATIVE-STATUS-MSG, [8-29](#)
ATM-DH-DKM-KEY-CHNG-INTRVL, [8-29](#)
ATM-DH-DKM-MAC-ERR-LMT, [8-30](#)
ATM-DH-DKM-MAC-TXN-LMT, [8-30](#)
ATM-DH-DKM-PIN-ERR-LMT, [8-31](#)
ATM-DH-DKM-PIN-TXN-LMT, [8-31](#)
ATM-DH-DYN-TBL-RETN-PRD-DIAL-UP, [8-32](#)
ATM-DH-DYN-TBL-RETN-PRD-LEASE, [8-32](#)
ATM-DH-FUJ7-CPLF-REQ, [8-33](#)
ATM-DH-LOG-SCND-ERR, [8-33](#)
ATM-DH-MAX-IN-CORE, [8-34](#)
ATM-DH-MAX-LOAD-CMD, [8-35](#)
ATM-DH-MAX-QUEUED-CMD, [8-35](#)
ATM-DH-MAX-TDFS, [8-36](#)
ATM-DH-MAX-TERMS, [8-36](#)
ATM-DH-MAX-TERMS-IN-CPLF-TBL, [8-38](#)
ATM-DH-MAX-TERMS-IN-DYN-TBL, [8-38](#)
ATM-DH-MAX-TERMS-IN-STATIC-TBL, [8-39](#)
ATM-DH-MDS1000-CPLF-REQ, [8-40](#)
ATM-DH-N50-AKDS-SERIAL-NUM-VRFY, [8-40](#)
ATM-DH-N50-CHK-PRNT-POS, [8-41](#)
ATM-DH-N50-CPLF-REQ, [8-41](#)
ATM-DH-N50-DPM-DFLAGS, [8-41](#)
ATM-DH-NON-VALUE-THRESHOLD, [8-42](#)
ATM-DH-OIF1000-CHK, [8-42](#)
ATM-DH-OLI6-CMD-TIMEOUT, [8-43](#)
ATM-DH-OLI6-KEY-CHG-TIME, [8-43](#)
ATM-DH-OLI6-LOAD-MSG-LEN, [8-43](#)
ATM-DH-OLI6-LOG-CE-STATUS, [8-43](#)
ATM-DH-OLI6-POLL-INTERVAL, [8-43](#)
ATM-DH-OLI6-POLL-RETRY-MAX, [8-44](#)
ATM-DH-OLI6-RETRY-INTERVAL, [8-44](#)
ATM-DH-OLI6-TERM-STATUS, [8-44](#)
ATM-DH-OPT-LVL, [8-44](#)
ATM-DH-PEAK-LEAD-TIME, [8-45](#)
ATM-DH-RCPT-PHONE-NUM-FRMT, [8-45](#)
ATM-DH-STALE-RQST-TIMEOUT, [8-46](#)
ATM-DH-SUSPECT-RVSL-ON-IM-ALIVE, [8-46](#)
ATM-DH-TERM-IN-CPLF-RETN-PRD, [8-46](#)
ATM-DH-TIDL-AKDS-HOST-LOAD-TIMER, [8-47](#)
ATM-DH-TIDL-AKDS-SERIAL-NUM-VRFY, [8-47](#)
ATM-DH-X25-MSG-SIZE, [8-48](#)
ATM-DH-X25-TYPE, [8-48](#)
ATM-DH-XCHG-RATE-NTFY, [8-48](#)
ATM-DISCR-DATA-STM-SUPPRS, [8-48](#)
ATM-FCA-CUTOVER-AUDIT, [8-49](#)
ATM-FEE-INTRACTV-RESP-NTFY, [8-50](#)
ATM-FORWARD-INST-ID, [8-50](#)
ATM-GEN-AUTH-ID-RESP, [8-50](#)
ATM-I4730-RCPT-TRUNC-FRTO, [8-51](#)
ATM-I4730-RCPT-TRUNC-PAN, [8-51](#)
ATM-ISS-DISCR-DATA-SUPPRS, [8-51](#)
ATM-LN-CUTOVER, [8-52](#)
ATM-NIDFEMT-MAX-TBL-SIZE, [8-52](#)
ATM-NIDFEMT-WARM*Identifier*, [8-52](#)
ATM-NOTIFY-INTERVAL, [8-53](#)

ATM-NOTIFY-PERCENTAGE, [8-54](#)
ATM-REAR-ADMN-TRAN-PIN-ALWD, [8-55](#)
ATM-RESP-LMTS-CHK, [8-55](#)
ATM-RPT-CPU, [8-55](#)
ATM-RPT-PRI, [8-55](#)
ATM-SETL-ATD-LOCKED-RECS-SKIP, [8-56](#)
ATM-SETL-EXPT-RPT-FLG, [8-56](#)
ATM-SETL-HDWRSTAT-NOTIFY, [8-56](#)
ATM-SETL-LN-CUTOVER-LEAD-TIME, [8-57](#)
ATM-SETL-MASTER, [8-57](#)
ATM-SETL-MIDNIGHT-NOTIFY*Identifier*, [8-58](#)
ATM-SETL-NOTIFY*Identifier*, [8-59](#)
ATM-SETL-RPT0-STARTUP, [8-60](#)
ATM-SETL-RPT1-STARTUP, [8-60](#)
ATM-SETL-RPT-FILE-RETENTION, [8-59](#)
ATM-SETL-TLF-EXTENTS-TO-ALLOCATE, [8-60](#)
ATM-SETL-TLF-FILE-RETENTION, [8-61](#)
ATM-TRFEMT-MAX-TBL-SIZE, [8-61](#)
ATM-TRFEMT-WARM*Identifier*, [8-61](#)
ATM-USE-ACCT-QUAL, [8-62](#)
ATM-WARM*Identifier*, [8-62](#)

B

BAL-ENQ-SUPPORT, [7-45](#)
BASE24-REL, [7-45](#)
BASE24-TAPE-LBL-PROC-USED, [7-46](#)
BASE-CURRENCY-CODE, [7-45](#)
BNRLF-NOTIFY-INTERVAL, [7-46](#)
BNRLF-NOTIFY-PERCENTAGE, [7-47](#)
BP-ACH-PAID-DAYS, [9-9](#)
BP-ACH-PRENOTE-DAYS, [9-9](#)
BP-ACH-PROCESS-VEND, [9-9](#)
BP-ACQ-CNTRY-CODE, [9-10](#)
BP-ACQ-FIID, [9-10](#)
BP-ARCHIVE-BY-FIID, [9-11](#)
BP-ARCHIVE-BY-SYSTEM-DAYS, [9-11](#)
BP-ARCHIVE-GROUP, [9-12](#)
BP-AUTHORIZER, [9-12](#)
BP-BANK-NOTICE-EXCEPTION, [9-12](#)
BP-CLEANUP-GROUP, [9-13](#)
BP-CLEANUP-YEAR, [9-14](#)
BP-DATE-FORMAT, [7-47](#)
BP-EOF-WAITTIME, [9-14](#)
BP-FUTURE-PARTITION-NUM, [9-14](#)
BP-HISTORY-PARTITION-NUM, [9-15](#)
BP-INITIAL-RETRY-LOG-INTERVAL, [9-15](#)
BP-LAG-TIME, [9-16](#)
BP-MASTER-VEND-ADD-ALLOWED, [9-17](#)

BP-MASTER-VEND-DFLT-NUM, [9-17](#)
BP-MAX-RETRY-COUNT, [9-17](#)
BP-MAX-RETRY-LOG-INTERVAL, [9-18](#)
BP-NUM-FUTURE-PART-EXT, [9-18](#)
BP-NUM-FUTURE-PART-INS, [9-19](#)
BP-NUM-HISTORY-PART-EXT, [9-19](#)
BP-NUM-HISTORY-PART-INS, [9-19](#)
BP-REDO-DATE, [9-20](#)
BP-REDO-MODE, [9-20](#)
BP-REMIT-TYPE, [9-20](#)
BP-RETRY-DELAY, [9-21](#)
BP-SERVICE-PROVIDER, [9-21](#)
BP-SLEEP-INTERVAL, [9-22](#)
BP-SLEEP-INTERVAL-MAX, [9-22](#)
BP-STI-FINAL-PROCESSING, [9-23](#)
BP-STI-LAG-TIME, [9-23](#)
BP-STI-WINDOW-CLOSE-TIME, [9-23](#)
BP-STI-WINDOW-OPEN-TIME, [9-24](#)
BP-TELEBANKING, [9-25](#)
BP-TELEBANKING-LOG, [9-25](#)
BP-TMF-BATCH-DURATION-TIME, [9-26](#)
BP-TMF-BATCH-SIZE, [9-26](#)
BP-TXN-TIMEOUT, [9-26](#)
BP-XPNET-CTSE-PATHMON, [9-27](#)
BP-XPNET-CTSE-SERVER-CLASS, [9-27](#)
BRIDGE-WAIT-TIME, [7-48](#)
BROADCAST-DELAY, [7-48](#)
BROADCAST-NOTIFY, [7-49](#)

C

CACT-PRESENT, [7-50](#)
CACT-PRI-PARTONLY, [16-29](#)
CACT-SOURCEREC, [16-29](#)
CAF-SCND-CRD-PROMOTE, [7-50](#)
CARD-CARRIER-RPT, [10-2](#)
CARD-PRODUCTION-RPT, [10-2](#)
CARRIER-AMTS-VT*Identifier*, [8-63](#)
CARRIER-VT*Identifier*, [8-63](#)
CASH-WDL-AUTH-PROD, [7-51](#)
CHK-RTG-GRP, [7-51](#)
CICS-ID-OFFSET, [7-51](#)
CONSOLE-PRT, [7-51](#)
COUNTER-UPDATE-INTERVAL, [7-52](#)
CPFEMT-MAX-TBL-SIZE, [18-10](#)
CPF-REC-SIZE, [7-52](#)
CPIT-PRESENT, [7-53](#)
CPIT-PRI-PARTONLY, [16-29](#)
CPIT-SOURCEREC, [16-30](#)

CPS-ATM, 7-54
CRT-ADMIN-APPRV-CDE-LGTH, 15-22
CRT-ADMN-MAX-AQFS, 15-22
CRT-AUTH-APPRV-CDE-LGTH, 15-23
CRT-AUTH-MAX-CRUFs, 15-23
CRT-AUTH-MAX-TQFS, 15-23
CRT-AUTH-MAX-TQFTS, 15-23
CRT-AUTH-RESP-TIMEOUT, 15-23
CRT-AUTH-TKN-RETRV-OPT, 15-24
CSTT-PRI-PARTONLY, 16-30
CSTT-SOURCEREC, 16-31
CTXEMT-CONTEXT-PAGES, 18-11
CTX-SECND-ALLOC, 18-10
CURRENCY-CODE, 7-54
CURRENCY-CONVERSION-ACQ, 7-55
CURRENCY-CONVERSION-ISS, 7-55
CUSTEMT-MAX-TBL-SIZE, 16-31
CVV-ON-BASE24, 7-55

D

DATE-DISPLAY-FORMAT, 7-56
DATE-DISPLAY-TYPE, 7-56
DCCDEMT-MAX-TBL-SIZE, 7-57
DCCDEMT-WARM*Identifier*, 7-58
DEBIT-CARD-TYPES, 7-58
DEFAULT-ISSUER-FEE, 7-59
DEFAULT-MEMBER-NUMBER, 7-59
DESTEMT-MAX-TBL-SIZE, 18-11
DES-TRIPLE-SINGLE, 7-59
DSCV-VER-IND, 7-60
DUAL-SITE-DISPLAY, 7-60
DUAL-SITE-MODE, 7-61

E

ELF-FILE-RETENTION, 16-31
ELIMINATE-ACQ-TRK-DATA, 7-61
EMBOSS-MACHINE, 10-2
EMS-BCST-RESTRICT-BY-TYPE, 14-4
EMS-BROADCAST-ID-LMT, 14-4
EMS-BROADCAST-MBR-LMT, 14-4
EMS-DPC-STATUS, 14-4
EMS-FIID-RESTRICTED, 14-4
EMS-FILE-FULL-PCT-WARN, 14-5
EMS-LOGICAL-NET, 14-5
EMS-PROD-BYTE-MAP, 14-5
EMS-PSTU-ACTIVE-LMT-FIID, 14-5
EMS-PSTU-ACTIVE-LMT-TERM, 14-5

EMS-PSTU-QUEUE-DEPTH, 14-5
EMS-PSTU-WAIT-INTERVAL, 14-6
EMS-SEND-METHOD-FIID, 14-6
EMS-SEND-METHOD-TERM, 14-6
EMS-TERMINAL-LMT, 14-6
EMV-CARD-BLOCK-SCRIPT, 7-61
EMV-PIN-UNBLOCK-SCRIPT, 7-62
EMV-PUT-DATA-SCRIPT, 7-62
ENHANCED-CRNCY-CONV, 7-62
ENHANCED-EMV-RC-MAPPING, 7-63
ENHNC-PRE-AUTH-COMP-TIME, 15-24
ENHNC-PRE-AUTH-HLD-STORE-TIME, 15-24
ERFEMT-MAX-TBL-SIZE, 7-63
ERFEMT-WARM*Identifier*, 7-64
ESEM-T-MAX-TBL-SIZE, 18-11
EXCEPTION-RPT, 10-3
EXTR-DISK-EXTENT-SIZE-MULT, 7-65
EXTR-DISPOSITION, 7-65
EXTRN-RQST-TIMEOUT, 7-66
EXTR-TAPE-BUFFERING, 7-66

F

F-CARD-TYPE, 7-67
F-CHK2-CARD-TYPE, 7-67
FHM-CSFC-RPT, 12-4
FHM-CUST-RPT, 12-4
FHM-ISO-FIXED-LENGTH, 12-4
FHM-LN-CUTOVER, 12-4
FHM-MASTER, 12-5
FHM-MAX-NUM-FILE-ENTRIES, 12-5
FHM-PSNL-RPT, 12-5
FHM-REL-IND, 12-6
FHM-RPT, 12-6
FHM-RPT-CPU, 12-6
FHM-RPT-FILE-RETENTION, 12-6
FHM-RPT-PRI, 12-7
FHM-RPT-STARTUP, 12-7
FHM-SLAVE-NOTIFY, 12-7
FHM-ULF-AUDIT, 12-8
FHM-ULF-FILE-RETENTION, 12-8
FHM-ULF-NOTIFY-INTERVAL, 12-8
FHM-ULF-NOTIFY-PERCENTAGE, 12-9
FHM-ULF-REJECTS, 12-9
F-ILNK-CARD-TYPE, 7-68
FIRST-VISA-TRACE-NUM, 7-68
F-PLUS-CARD-TYPE, 7-68
FREQ-SHOP-QUEUE, 15-25
FRLF-NOTIFY-INTERVAL, 7-69

FRLF-NOTIFY-PERCENTAGE, [7-69](#)
FRWD-DCLN-ADVC, [7-69](#)
F-VISA-CARD-TYPE, [7-68](#)
F-VISAPLUS-CARD-TYPE, [7-68](#)

H

HOST-COMPLETE-TRACK2, [7-70](#)
HOST-SELECTED-ACCT, [7-70](#)
HRDWR-CVV-GEN, [10-5](#)
HRDWR-PIN-GEN, [10-5](#)

I

ICHG-COMPLIANCE-ACQ-DATA-LOC, [7-71](#)
ICHG-COMPLIANCE-ISS-DATA-LOC, [7-71](#)
IDFEMT-MAX-TBL-SIZE, [7-71](#)
IDFEMT-WARM*Identifier*, [7-72](#)
IEP-SYM-NAM, [18-11](#)
ILF-LOGGING-ENABLED, [7-72](#)
ILF-NOTIFY-INTERVAL, [7-73](#)
ILF-NOTIFY-PERCENTAGE, [7-73](#)
ILF-PURGE-ATTEMPT, [7-74](#)
IMP-TIME-LIMIT, [16-31](#)
IMTEMT-MAX-TBL-SIZE, [16-31](#)
INCOMPLETE-TRACK2-TERM-TYPES, [7-74](#)
INCR-VISA-TRACE-NUM-BY, [7-76](#)
INSTL-TXN-DATA-OFST, [7-75](#)
INTFEMT-MAX-TBL-SIZE, [16-31](#)
INV-LN-CUTOVER, [13-4](#)
INV-LNET-CUTOVER-SERVICE, [13-4](#)
INV-SETL-ATM-CUT-SERVICE, [13-4](#)
INV-SETL-LN-CUTOVER-LEAD-TIME, [13-4](#)
INV-SETL-NTLF-EXT-TO-ALLOCATE, [13-4](#)
INV-SETL-NTLF-FILE-RETENTION, [13-5](#)
INV-SETL-POS-CUT-SERVICE, [13-5](#)
INV-SMGR-STOCK-TYPE, [13-5](#)
IPCFEMT-MAX-TBL-SIZE, [7-76](#)
IPCFEMT-WARM*Identifier*, [7-76](#)
IRTEEMT-MAX-TBL-SIZE, [16-32](#)
ISSUE-MAINT-RPT, [10-3](#)
ISSUE-PROJ-RPT, [10-3](#)

K

KEK-VARIANT-USED, [7-77](#)
KEYAEMT-MAX-TBL-SIZE, [16-32](#)

L

LABEL-TYPE, [7-78](#)

LGNT-COUNTRY-ABBR, [7-78](#)
LGNT-CUTOVER, [7-79](#)
LGNT-CUTOVER-LEAD-TIME, [16-32](#)
LINK-START-TRACE-NUM, [7-79](#)
LN-IND, [7-79](#)
LOGICAL-NET, [7-81](#)
LOGOFF-INTERVAL, [7-82](#)
LPP-TIME-LIMIT, [18-12](#)

M

MAIL-HISO-GEN-TRACE-NUM, [7-82](#)
MAIL-LN-CUTOVER, [7-83](#)
MAIL-SEND-RESTRICTED-BY-FIID, [7-83](#)
MASK-POFST-PVV, [7-83](#)
MAX-IIF-RECORDS, [7-83](#)
MAX-LOGON-ATTEMPTS, [7-84](#)
MAX-LPP-PROCESSES, [18-12](#)
MAX-STF-RECORDS, [7-84](#)
MDS-SPPT-NON-EMV-PIN-CHANGE, [7-84](#)
MIGR-ATM-ADVC-DESTxx, [7-85](#)
MIGR-ATM-ENABLE, [7-85](#)
MIGR-ATM-HISO-DEST, [7-85](#)
MIGR-ATM-PROCESSING-OPTS, [7-85](#)
MIGR-FHM-HISO-ENABLE, [7-86](#)
MIGR-HISO-ENABLE, [7-86](#)
MIGR-HISO-NAME *Identifier*, [7-86](#)
MIGR-INTF-DPC-NUM, [7-87](#)
MIGR-POS-ADVC-DESTxx, [7-87](#)
MIGR-POS-ENABLE, [7-87](#)
MIGR-POS-HISO-DEST, [7-88](#)
MIGR-POS-PROCESSING-OPTS, [7-88](#)
MLF-NOTIFY-INTERVAL, [7-88](#)
MLF-NOTIFY-PERCENTAGE, [7-89](#)
MOBILE-NUM-MAX-LGTH, [8-64](#)
MOBILE-NUM-MIN-LGTH, [8-64](#)
MOBILE-OPERATOR-ID-VT*Identifier*, [8-64](#)
MONAD-NOTIFY-PROCESS, [7-89](#)
MULT-LN-PIN-KEY, [7-90](#)

N

N50-NCD-CRD-EJECT-OPTION, [8-65](#)
NCD-DFLT-HOPR-CONTENTS, [7-91](#)
NETLIST-CPU, [18-12](#)
NETLIST-PRI, [18-12](#)
NETWORK-ID, [7-91](#)
NO-MANUAL-ENTRY-CARD-TYPES, [7-91](#)
NOM-PERCENT-THRESHOLD, [18-12](#)

O

OMF-AUDIT, [7-92](#)
 OMF-RETENTION-PERIOD, [7-93](#)
 OMF-SPECIAL, [7-93](#)
 OVRRD-INST-ID-FIELDS, [7-94](#)

P

PASSWORD-CHNG-INTERVAL, [7-94](#)
 PASSWORD-COMPLEX, [7-95](#)
 PASSWORD-LENGTH-MIN, [7-95](#)
 PASSWORD-MAX-CHNG-PER-DAY, [7-95](#)
 PASSWORD-MAX-STORE, [7-96](#)
 PASSWORD-NUM-ALPHA, [7-96](#)
 PASSWORD-NUM-NUMERIC, [7-96](#)
 PASSWORD-NUM-SPECIAL, [7-97](#)
 PCGEN-EXCEPTION-RPT, [10-3](#)
 PCI-DISPOSITION, [7-97](#)
 PCTLEMT-SEGSIZE, [18-13](#)
 PIN-MAILER-RPT, [10-3](#)
 PIT-NAM-ALGO, [7-98](#)
 PIT-PRESENT, [7-99](#)
 PIT-PRI-PARTONLY, [16-32](#)
 PIT-SOURCEREC, [16-33](#)
 PLUS-ADMIN-NOTIFY-INTERVAL, [7-99](#)
 PLUS-ADMIN-NOTIFY-PERCENTAGE, [7-99](#)
 POS-A4000-MASTER, [15-25](#)
 POS-ACQ-AVS-DATA-SUPPRS, [15-25](#)
 POS-ACQ-CVD2-DATA-SUPPRS, [15-25](#)
 POS-ACQ-DISC-DATA-SUPPRS, [15-26](#)
 POS-APDH-AUTH-DUP-TIMEOUT, [15-26](#)
 POS-APDH-CONFIRM-FLAG, [15-26](#)
 POS-APDH-CONFIRM-TIMEOUT, [15-26](#)
 POS-APDH-DISCONNECT-ON-ERROR, [15-27](#)
 POS-APDH-EXTEND-RESP-TIMEOUT, [15-27](#)
 POS-APDH-HOLD-MESSAGE-PREFIX, [15-27](#)
 POS-APDH-LOG-APACS-DATA, [15-27](#)
 POS-APDH-POST-FLOOR-LIMIT, [15-28](#)
 POS-APDH-PRE-FLOOR-LIMIT, [15-28](#)
 POS-APDH-REFERRAL-PREFIX, [15-28](#)
 POS-APDH-STALE-REQ-TIMEOUT, [15-28](#)
 POS-APDH-USE-POST-FL-LIMIT, [15-28](#)
 POS-APDH-USE-PRE-FL-LIMIT, [15-29](#)
 POS-AST-RECSIZE, [15-29](#)
 POS-B24-TO-POS-ACCT-SUPPRS, [15-29](#)
 POS-CAFPBF-RET-PERIOD, [15-29](#)
 POS-CART-RECSIZE, [15-30](#)
 POS-CHECK-LIMITS-FLAG, [15-30](#)
 POS-CHRGBCK-NO-RESP-ORIG, [15-30](#)
 POS-DH-AUTH-RESP-TIMEOUT, [15-31](#)
 POS-DH-CONS-MAC-ERR-LMT, [15-31](#)
 POS-DH-CUTOVER-LEAD-TIME, [15-32](#)
 POS-DH-DUKPT-UPDATE-METHOD, [15-32](#)
 POS-DH-ISO-RESP-CDE-FRMT, [15-33](#)
 POS-DH-KEYD-READ-FROM-DISK, [15-33](#)
 POS-DH-KSN-ANSI-STD-OPT, [15-33](#)
 POS-DH-KSN-APPRV-OPT, [15-34](#)
 POS-DH-KSN-CNTR-APPRV-OPT, [15-34](#)
 POS-DH-KSN-DESCR, [15-34](#)
 POS-DH-KSN-MAX-DIFFERENCE, [15-34](#)
 POS-DH-KSN-SAVE-OPT, [15-35](#)
 POS-DH-LMT-EXCEED-DISP, [15-35](#)
 POS-DH-MAC-ADMIN-WITH-KEY, [15-35](#)
 POS-DH-MAX-CNFGS, [15-36](#)
 POS-DH-MAX-IN-CORE, [15-36](#)
 POS-DH-MAX-TDFS, [15-37](#)
 POS-DH-MAX-TERMS, [15-38](#)
 POS-DH-MAX-TERMS-IN-DYN-TBL, [15-38](#)
 POS-DH-MAX-TERMS-IN-STATIC-TBL, [15-39](#)
 POS-DH-PTD-NFTY-PCNT, [15-40](#)
 POS-DH-PTD-NFTY-PCNT-DYN, [15-40](#)
 POS-DH-PTD-STATIC-REPL, [15-41](#)
 POS-DH-SEQNUM-RESET-OPT, [15-41](#)
 POS-DISCR-DATA-STM-SUPPRS, [15-41](#)
 POS-EAF-NOTIFY-INTERVAL, [15-42](#)
 POS-EAF-NOTIFY-PERCENTAGE, [15-42](#)
 POS-ELEC-FOLLOW-UP-OPT, [15-43](#)
 POS-EXPT-RPT-FLG, [15-43](#)
 POS-FORWARD-INST-ID, [15-44](#)
 POS-FUEL-PREAUTHS, [15-44](#)
 POS-HPDH-AUTH-RESP-TIMEOUT, [15-44](#)
 POS-HPDH-LOG-TERM-STATS, [15-45](#)
 POS-HPDH-MAX-HPCFS, [15-45](#)
 POS-HPDH-MAX-HPTCS, [15-45](#)
 POS-HPDH-NAC-ID*entifier*, [15-45](#)
 POS-HPDH-NMS-ID*entifier*, [15-46](#)
 POS-HPDH-OLDMSG-TIMEOUT, [15-46](#)
 POS-IPDH-FREQ-SHOP-TIMEOUT, [15-46](#)
 POS-ISS-AVS-BLANK-ZIP-CDE-ALWD, [15-47](#)
 POS-ISS-AVS-DATA-SUPPRS, [15-47](#)
 POS-ISS-CVD2-DATA-SUPPRS, [15-47](#)
 POS-ISS-DISCR-DATA-SUPPRS, [15-47](#)
 POS-LN-CUTOVER, [15-48](#)
 POS-LOG-MAC-ERR, [15-48](#)
 POS-MHI-MAX-REQUESTS, [15-49](#)
 POS-NCR-0500-RESP-TIMEOUT, [15-49](#)

POS-NCR-0800-RESP-TIMEOUT, [15-49](#)
POS-NCR-AUTH-RESP-TIMEOUT, [15-49](#)
POS-NCR-MAX-IN-CORE, [15-50](#)
POS-NCR-MAX-TDFS, [15-50](#)
POS-NCR-OLDMSG-TIMEOUT, [15-50](#)
POS-NOTIFY-INTERVAL, [15-50](#)
POS-NOTIFY-PERCENTAGE, [15-51](#)
POS-PASSTHRU-ACQ-SEQ-NUM-CHK, [15-51](#)
POS-PASSTHRU-PROCESS-TYPE, [15-52](#)
POS-PRDF-RECSIZE, [15-52](#)
POS-PREF-NOTIFY, [15-52](#)
POS-PRF-RECSIZE, [15-53](#)
POS-PTLF-RECSIZE, [15-53](#)
POS-RESP-LMTS-CHK, [15-53](#)
POS-RETRY-TIMER, [15-54](#)
POS-RPT-PRI, [15-54](#)
POS-RTAU-ALGO-CHECK, [15-55](#)
POS-RTAU-AST-ROUTE, [15-55](#)
POS-RTAU-IDF-DATES-COMPUTE, [15-56](#)
POS-RTAU-MAX-RDFS, [15-56](#)
POS-RVSL-ROUTE, [15-56](#)
POS-SETL-ALIVE-TIMEOUT, [15-57](#)
POS-SETL-EAF-NOTIFY*identifier*, [15-57](#)
POS-SETL-EAF-RETENTION-PERIOD, [15-57](#)
POS-SETL-FI-CUTOVER-LEAD-TIME, [15-57](#)
POS-SETL-LN-CUTOVER-LEAD-TIME, [15-58](#)
POS-SETL-MASTER, [15-58](#)
POS-SETL-MIDNIGHT-NOTIFY*identifier*, [15-59](#)
POS-SETL-NOTIFY*identifier*, [15-60](#)
POS-SETL-PTLF-EXTENTS, [15-61](#)
POS-SETL-PTLF-FILE-RETENTION, [15-61](#)
POS-SETL-REPORTS, [15-61](#)
POS-SETL-RPT-CPU, [15-62](#)
POS-SETL-RPT-FILE-RETENTION, [15-62](#)
POS-SETL-RPT-PRI, [15-62](#)
POS-SETL-SENIOR-SLAVE, [15-63](#)
POS-SETL-TERM-CUTOVER-DELAY-TIME, [15-63](#)
POS-SETL-THRESHOLD, [15-63](#)
POS-SETL-TRACE, [15-63](#)
POS-SETL-WAIT-INTERVAL, [15-64](#)
POS-SLAVE-KEY*identifier*, [15-64](#)
POS-SPLIT-TXN-RTG-DEST, [15-65](#)
POS-SVHF-ICHG-AUTH-LOG, [15-66](#)
POS-SVHF-NOTIFY-INTERVAL, [15-66](#)
POS-SVHF-NOTIFY-PERCENTAGE, [15-66](#)
POS-SVHF-RET-PERIOD, [15-67](#)
POS-SV-PTLF-LOGGING, [15-65](#)
POS-SV-RETAILER-ID, [15-65](#)

POS-SV-TERMINAL-ID, [15-66](#)
POS-WARM*identifier*, [15-67](#)
PRE-VERIFIED-PIN-PAD-CHAR, [7-100](#)
PRI-TIM-LMT, [7-101](#)
PROCESS-EVENT-TABLE-SIZE, [18-13](#)
PS2000-ACQ-DATA-LOC, [7-101](#)
PS2000-ISS-DATA-LOC, [7-101](#)
PSEUDO-3DES-CBC-MAC-TYPE, [7-101](#)

Q

QED, [18-13](#)

R

RACAL-ANSI-METHOD, [7-102](#)
RAM-MSG-MDFY, [7-102](#)
RCDFEMT-MAX-TBL-SIZE, [15-68](#)
RCPTMT-MAX-TBL-SIZE, [8-65](#)
RCPTMT-WARM*identifier*, [8-66](#)
REF-BYPASS-PARITY-ERRORS, [7-103](#)
REF-FUP-CPU, [7-103](#)
REF-IMPACT-TABLE-SIZE, [7-103](#)
REF-INPUT-BLK-DSK, [16-33](#)
REF-INPUT-BLK-TAPE, [16-33](#)
REF-MONITOR-COMMAND, [7-104](#)
REF-NOTIFY*identifier*, [7-104](#)
REF-PBF-LOCKOUT-FACTOR, [7-105](#)
REF-PRE-ALLOCATE-EXTENTS, [7-105](#)
REF-RGCF-RETN-PRD, [7-106](#)
REFR-INPUT-DATA-SORTED, [7-103](#)
REFR-MAX-RECS-UNSORTED, [7-104](#)
REFR-PBF-EARLY-NOTIFICATION, [7-108](#)
REF-SQLCI-CPU, [16-33](#)
REF-SQLCI-DELAY, [16-33](#)
REF-SWI-NOTIFY*identifier*, [7-106](#)
REF-TLR-NOTIFY*identifier*, [7-107](#)
REMOTE-TERMINAL-BRANCH-ID, [7-108](#)
RESUB-CNFG, [7-108](#)
RESUB-LOG-PTLF, [7-109](#)
RESUB-MAX-DAYS-LIMIT, [7-109](#)
RESUB-MAX-LIMIT, [7-109](#)
RESUB-TIME, [7-109](#)
REVERSAL-BAL-INQ, [7-110](#)
REVERSE-BAL-INQ, [7-110](#)
ROUTE-OBJECT-ID, [18-14](#)

[RSAF-ISS-UNAVAIL-WAIT-TIMER, 7-110](#)
[RSAF-NOTIFY-INTERVAL, 7-111](#)
[RSAF-NOTIFY-PERCENTAGE, 7-111](#)
[RSM-TERM-MASTER-KEY, 7-112](#)

S

[SAF-NOTIFY-INTERVAL, 7-112](#)
[SAF-NOTIFY-PERCENTAGE, 7-113](#)
[SAF-PRIOR-TO-SEND, 7-114](#)
[SCMEMT-MAX-TBL-SIZE, 18-14](#)
[SDF-WAIT-TIMER, 7-114](#)
[SECURE-DEV-ACCESS-TYP, 7-114](#)
[SECURE-DEV-CONF-CMD100, 7-115](#)
[SECURE-DEV-CONF-TXT, 7-117](#)
[SECURE-DEV-FAIL-NOTIFY, 7-119](#)
[SECURE-DEVICE-COUNT, 16-33](#)
[SECURE-DEVICE-TYPE, 16-34](#)
[SECURE-DEV-MONITOR-THRESHOLD, 7-120](#)
[SECURE-DEV-REINSTATE-TIME, 7-121](#)
[SECURE-DEV-TIM-LMT, 7-122](#)
[SECURE-DEV-TYP, 7-123](#)
[SEMF-NOTIFY*identifier*, 7-125](#)
[SEND-ETX, 7-126](#)
[SEND-IMPLIED-DECIMAL, 7-126](#)
[SEND-MDS-DEFAULT-ACQUIRER-ID, 7-126](#)
[SOFTWARE-PIN-VERIFICATION-ALWD, 7-127](#)
[SPAN-FLAG, 7-127](#)
[SPLIT-TXN-RTG-DEST, 8-66](#)
[SSMEMT-MAX-TBL-SIZE, 18-14](#)
[STATION-TYP, 7-128](#)
[STRFEMT-MAX-TBL-SIZE, 7-128](#)
[STRFEMT-WARM*identifier*, 7-128](#)
[SW-BNET-LOG-ONLY-COMPL-ADVICE, 7-129](#)
[SW-BNET-SPPT-INSTL-TXN, 7-129](#)
[SW-ETUO-RETURN-0430, 7-130](#)
[SWI-ACQ-AVS-DATA-SUPPRS, 7-132](#)
[SWI-ACQ-CVD2-DATA-SUPPRS, 7-133](#)
[SWI-ACQ-DISCR-DATA-SUPPRS, 7-134](#)
[SWI-ENHNCD-ILF-MATCH-ACQ, 7-135](#)
[SWI-ENHNCD-ILF-MATCH-ISS, 7-135](#)
[SWI-ISS-AVS-DATA-SUPPRS, 7-136](#)
[SWI-ISS-CVD2-DATA-SUPPRS, 7-137](#)
[SWI-ISS-DISCR-DATA-SUPPRS, 7-137](#)
[SW-ILF-FILE-OPEN, 7-130](#)
[SW-ILF-FILE-RETENTION, 7-131](#)
[SWI-MDS-SPPT-CCA-ADVC-RVSL, 7-138](#)
[SWITCH-COMPLETE-TRACK2, 7-140](#)
[SWI-VISA-MAP-EXPAND-AVS-TO-BASIC, 7-139](#)

[SWI-VISA-MVV-IN-AUTO-SUBSTAN-TKN, 7-139](#)
[SWI-WARM*identifier*, 7-139](#)
[SW-RPT-STARTUP, 7-131](#)
[SW-SPN2-USING-STA-SATELLITES, 7-132](#)

T

[TAPE-DRIVE, 10-4](#)
[TAPE-FORMAT, 7-140](#)
[TB-RPT-ISS-CPU, 16-34](#)
[TB-RPT-ISS-FILE-RETENTION, 16-35](#)
[TB-RPT-ISS-FS-DIST-CPU, 16-35](#)
[TB-RPT-ISS-FS-DIST-MEM, 16-35](#)
[TB-RPT-ISS-FS-DIST-PRI, 16-35](#)
[TB-RPT-ISS-FS-DIST-SEG, 16-36](#)
[TB-RPT-ISS-FS-SS1-CPU, 16-36](#)
[TB-RPT-ISS-FS-SS1-MEM, 16-36](#)
[TB-RPT-ISS-FS-SS1-PRI, 16-37](#)
[TB-RPT-ISS-FS-SS1-SEG, 16-37](#)
[TB-RPT-ISS-FS-SS2-CPU, 16-37](#)
[TB-RPT-ISS-FS-SS2-MEM, 16-37](#)
[TB-RPT-ISS-FS-SS2-PRI, 16-38](#)
[TB-RPT-ISS-FS-SS2-SEG, 16-38](#)
[TB-RPT-ISS-FS-SS3-CPU, 16-38](#)
[TB-RPT-ISS-FS-SS3-MEM, 16-39](#)
[TB-RPT-ISS-FS-SS3-PRI, 16-39](#)
[TB-RPT-ISS-FS-SS3-SEG, 16-39](#)
[TB-RPT-ISS-FS-SS4-CPU, 16-39](#)
[TB-RPT-ISS-FS-SS4-MEM, 16-40](#)
[TB-RPT-ISS-FS-SS4-PRI, 16-40](#)
[TB-RPT-ISS-FS-SS4-SEG, 16-40](#)
[TB-RPT-ISS-FS-SS5-CPU, 16-41](#)
[TB-RPT-ISS-FS-SS5-MEM, 16-41](#)
[TB-RPT-ISS-FS-SS5-PRI, 16-41](#)
[TB-RPT-ISS-FS-SS5-SEG, 16-41](#)
[TB-RPT-ISS-FS-SS6-CPU, 16-42](#)
[TB-RPT-ISS-FS-SS6-MEM, 16-42](#)
[TB-RPT-ISS-FS-SS6-PRI, 16-42](#)
[TB-RPT-ISS-FS-SS6-SEG, 16-42](#)
[TB-RPT-ISS-FS-SS7-CPU, 16-43](#)
[TB-RPT-ISS-FS-SS7-MEM, 16-43](#)
[TB-RPT-ISS-FS-SS7-PRI, 16-43](#)
[TB-RPT-ISS-FS-SS7-SEG, 16-44](#)
[TB-RPT-ISS-FS-SS8-CPU, 16-44](#)
[TB-RPT-ISS-FS-SS8-MEM, 16-44](#)
[TB-RPT-ISS-FS-SS8-PRI, 16-44](#)
[TB-RPT-ISS-FS-SS8-SEG, 16-45](#)
[TB-RPT-ISS-PRI, 16-45](#)
[TB-RPT-ISS-RUN, 16-45](#)

TB-RPT-ISS-SUP-TXN-CAT-TTLS, [16-45](#)
TB-RPT-ISS-TIM, [16-46](#)
TB-RPT-PRI, [16-46](#)
THFEMT-MAX-TBL-SIZE, [16-46](#)
TIME-ZONE-DIFF, [7-140](#)
TLF-EXTENTS, [16-47](#)
TLF-FILE-RETENTION, [16-47](#)
TLR-DH-AUTH-TIMER, [17-10](#)
TLR-DH-MAX-TERMS, [17-10](#)
TLR-DH-NATIVE-MSG, [17-10](#)
TLR-DH-ORF-RESP, [17-11](#)
TLR-DH-STALE-RQST-TIMEOUT, [17-11](#)
TLR-LN-CUTOVER, [17-11](#)
TLR-MAX-NBF-REC-CNT, [17-12](#)
TLR-PROCESS-CRD-PIN, [17-12](#)
TLR-RPT-FILE-RETENTION, [17-12](#)
TLR-RPT-PRI, [17-13](#)
TLR-RPT-PRNT-TKN-ERR, [17-13](#)
TLR-SETL-MASTER, [17-13](#)
TLR-SETL-NOTIFY, [17-13](#)
TLR-SETL-TTLF-FILE-RETENTION, [17-14](#)
TLR-TTLF-NOTIFY-INTERVAL, [17-14](#)
TLR-TTLF-NOTIFY-PERCENT, [17-15](#)
TLR-TTLFX-NOTIFY, [17-15](#)
TLR-WARM*Identifier*, [17-16](#)
TLR-WRITE-HLDS-DEP-FLOATS, [17-16](#)
TSEC-OBJ-MASTER, [16-47](#)

U

UPDT-ILF-ON-LATE-RESP, [7-141](#)
US-CARD-TYPE, [7-141](#)
US-CHK2-CARD-TYPE, [7-142](#)
US-ILNK-CARD-TYPE, [7-142](#)
US-PLUS-CARD-TYPE, [7-142](#)
US-VISA-CARD-TYPE, [7-142](#)
US-VISAPLUS-CARD-TYPE, [7-142](#)