



Data source reference manual

BASE24-eps[®]

© 2011 by ACI Worldwide, Inc. All rights reserved.

All information contained in this documentation, as well as the software described in it, is confidential and proprietary to ACI Worldwide, Inc., or one of its subsidiaries, is subject to a license agreement, and may be used or copied only in accordance with the terms of such license. Except as permitted by such license, no part of this documentation may be reproduced, stored in a retrieval system, or transmitted in any form or by electronic, mechanical, recording, or any other means, without the prior written permission of ACI Worldwide, Inc., or one of its subsidiaries. ACI, ACI Worldwide, and the ACI product names used in this documentation are trademarks or registered trademarks of ACI Worldwide, Inc., or one of its subsidiaries.

Other companies' trademarks, service marks, or registered trademarks and service marks are trademarks, service marks, or registered trademarks and service marks of their respective companies.

Contents

About data source documentation.....	13
What's new.....	14
Derived types.....	15
List of Assigns.....	17
Data source list.....	106
ABI_Interface (1.0) (abifd).....	106
ABI_Key (1.0) (abikd).....	107
ACCEL_Interface (1.0) (acifd).....	108
Account_Routing (1.0) (actrtd).....	108
Acct_Status_Extrn_to_Intrn (1.0) (aseid).....	109
Acct_Status_Intrn_to_Extrn (1.0) (asied).....	109
Acquirer_Instrument_Type_Rel (1.0) (aintrd).....	110
Acquirer_Issuer_Relation (1.0) (aird).....	110
Acquirer_Route_Profile (1.0) (artpd).....	111
Acquirer_Txn_Allowed (1.0) (acqtxd).....	111
ActFunc (1.0) (uactfn).....	112
Action_Code_Extrn_to_Intrn (2.0) (aceid).....	112
Action_Code_Intrn_to_Extrn (2.0) (acied).....	113
Active_Script_Statistics (1.0) (actssd).....	113
ActSess (1.0) (uactse).....	114
ACTSESS2 (1.0) (uacts2).....	114
Admin_Card (1.0) (admcd).....	115
AEGN_Interface (1.0) (aeifd).....	117
AMEX_CAPN_Interface (1.0) (acpnfd).....	117
APACS_Configuration (2.0) (apacsd).....	118
APCF (1.0) (apcf).....	118
APPLCNFG (2.0) (appld).....	120
APPLDSRC (1.0) (apsrcd).....	120
AS2805_Config (1.0) (as28d).....	120
AS2805_Interface (1.0) (as28ifd).....	121
ATDCNFG (3.0) (atdcnd).....	121
ATMCNFG (1.0) (atmcnd).....	124
ATMLOG (1.0) (atlgd).....	125
ATM_CONF (1.0) (atmcnf).....	126
ATM_CONSUMER_MEDIA (2.0) (atmmcd).....	127
ATM_DD1 (3.0) (atmdd1).....	127
ATM_DD2 (1.0) (atmdd2).....	138
ATM_DIAL_UP_CMD (1.0) (atmdcd).....	139
ATM_DKM (1.0) (atdkmd).....	139
ATM_DS1 (4.0) (atmds1).....	140
ATM_EMV (1.0) (atmemd).....	144

ATM_FAST_CASH (1.0) (atmfcd).....	145
ATM_FLOW_CNTL (1.0) (atmmfd).....	146
ATM_HOPR (1.0) (atmhpdp).....	147
ATM_IFXDATA (1.0) (atmifx).....	156
ATM_INACT (1.0) (atmind).....	157
ATM_MAC (1.0) (atmmcd).....	158
ATM_MBYTE_XLATE (1.0) (atmxds).....	158
ATM_OPER (1.0) (atmopdp).....	159
ATM_OP_CDE (2.0) (atmopc).....	159
ATM_PEAK_LOAD (1.0) (atmpkd).....	160
ATM_PREV_TTL (3.0) (atmprv).....	164
ATM_PRFL (3.0) (atmprd).....	171
ATM_RECEIPT (1.0) (atmrcd).....	174
ATM_REQ_RCPT (1.0) (atmqrd).....	175
ATM_RQUID (1.0) (ifxrqd).....	176
ATM_SSB_BIN (1.0) (ssbbnd).....	176
ATM_SSB_BNA (1.0) (ssbbna).....	177
ATM_SSB_CPL (1.0) (ssbcpl).....	177
ATM_STATE_SCRN (2.0) (atmssd).....	178
ATM_STMNT_DATA (1.0) (atmstd).....	181
ATM_STMNT_PRNT (1.0) (atmpsdp).....	181
ATM_SUR (1.0) (atmchdp).....	182
ATM_TC_Proc_Code (1.0) (attpdp).....	183
AudDtlPK (1.0) (uadupk).....	183
AuditDtl (1.0) (uadutl).....	183
AuditTbl (1.0) (uadutb).....	184
Audit_Store_and_Forward (1.0) (asafdp).....	184
Audit_Store_and_Forward_Config (1.0) (asafcd).....	185
Authorization_Script (1.0) (athscdp).....	186
B24EPS_Ignt_map (1.0) (b24lmd).....	187
B24_filetyp_map (1.0) (b24ftdp).....	187
B53_Institution (1.0) (b53ind).....	188
Banknet_Configuration (5.0) (bnetcd).....	188
Banknet_Group_Timers (2.0) (bngtd).....	189
Banknet_Institution_Id (3.0) (bniid).....	189
Banknet_Institution_Id2 (1.0) (bni2dp).....	191
Banknet_Merchant_Program (1.0) (bntmpdp).....	192
BASE24_KEYF (1.0) (keyfd).....	192
Batch_Auth_Config (1.0) (bacdp).....	198
Batch_Auth_Posn (1.0) (bapdp).....	199
BEPS_Instrm_Prtyp (1.0) (beipdp).....	199
BIC_Interface (1.0) (biifdp).....	199
BLZ_Map (1.0) (blzmpdp).....	200
BNFT_Interface (1.0) (bnifdp).....	201
BNTng_Header (1.0) (bnthdp).....	201

BNTng_Init_Data (1.0) (bntid).....	203
BPDATA (1.0) (bpdatd).....	203
CACNFSAF (1.0) (cacsaf).....	204
CACNTX (1.0) (cacntx).....	204
Card (5.0) (crdd).....	205
Cardnet_ID_Code (1.0) (crdnicd).....	212
Cardnet_Interface (1.0) (crdnifd).....	212
Cardnet_Interface_Terminal (1.0) (crdnitd).....	213
Card_Account (3.0) (crdad).....	213
CARD_ACCOUNT_MBYTE (1.0) (crdamd).....	224
Card_Block (1.0) (crdbd).....	228
Card_Impacts (3.0) (crdimd).....	228
Card_Verification (1.0) (crdvd).....	229
Channel_Instrm_Type_Relation (2.0) (citrd).....	230
Channel_Instrument_Type_Rel (1.0) (cintrd).....	230
Channel_Public_Key_Security (3.0) (chnpkd).....	231
Channel_Security (6.0) (csecd).....	232
Channel_Security_Future (1.0) (csecfd).....	242
Chan_Profile_Instrm_Typ_Relation (2.0) (cpitrd).....	244
Check_Status (1.0) (chkstd).....	245
Check_Type (1.0) (cktypd).....	245
Chip_Authentication (1.0) (cad).....	246
Circuit_Interface (1.0) (crctfd).....	247
CMPTPRFL (1.0) (cmptd).....	248
Compiler_Message (2.0) (msgd).....	248
Context (1.0) (ctxd).....	249
Context_Configuration (1.0) (ctxcd).....	249
Context_USEC (1.0) (ucntxt).....	250
Contingency_Interface (1.0) (ctgyd).....	250
Credit_Debit_Master_File (1.0) (cdmfd).....	251
CTVRSFAF (3.0) (cosaftd).....	252
CUP_Institution (1.0) (cupind).....	262
CUP_Interface (1.0) (cupifd).....	263
Currency_Conversion_Rate (1.0) (ccrd).....	263
dal_tbl (1.0) (daltbl).....	264
DATASRC (1.0) (dtsrctd).....	264
Derivation_Key (2.0) (drvkd).....	265
DIAS_Interface (1.0) (diasfd).....	265
Diebold_Number_Table (1.0) (dntd).....	266
Discover_Institution (1.0) (dscvnd).....	275
Discover_Interface (1.0) (dscvfd).....	275
DS_OLTP_Relation (1.0) (doltpd).....	275
Dual_PIN_Verification (1.0) (dpvnd).....	276
Dynamic_Card_Verification (1.0) (dcrdvd).....	277
EFunds_Institution (1.0) (efiid).....	277

EFunds_Interface (3.0) (efifd).....	278
EMVPRFL (1.0) (emvprd).....	278
EMV_Card_Vrfn_Results_Status (1.0) (cvrd).....	279
EMV_Iss_Auth_Dta (1.0) (eiadd).....	280
EMV_Reason_Online_Code_Status (1.0) (rocd).....	280
EMV_Script_Context (1.0) (escd).....	281
EMV_Security (5.0) (emvsd).....	281
EMV_Terminal_Vrfn_Results_Status (1.0) (tvrdr).....	289
Environment (1.0) (envmtd).....	289
EPP_Serial_Number (1.0) (epnumd).....	290
EPSNET_Inst (1.0) (epiifd).....	290
EPSNET_Interface (1.0) (epsnfd).....	291
Equens_Instrm_Typ_Extrn (1.0) (eqnied).....	292
Equens_Instrm_Typ_Intrn (1.0) (eqniid).....	293
Equens_Interface (1.0) (eqnifd).....	293
ERSB_Interface (1.0) (ersbifd).....	294
ESAPDT (3.0) (eapdtd).....	294
ESATDD1 (3.0) (eatd1d).....	301
ESATDD2 (2.0) (eatd2d).....	315
ESATDL (1.0) (eatdld).....	316
ESATDS1 (2.0) (eats1d).....	316
Euro_Opted_Currency (1.0) (eocd).....	318
Event (1.0) (eventd).....	319
EVENTLOG (1.0) (evtld).....	322
Event_Document (1.0) (evdocd).....	323
EVNTLOG (1.0) (evtlog).....	323
Exception_Log (2.0) (exlogd).....	324
EXCPT (1.0) (EXCPT).....	324
Exported_Operator_Documentation (1.0) (opdocd).....	325
EXTRCNCT (1.0) (extcnd).....	327
FCSHPRFL (1.0) (fcschd).....	328
Fees (1.0) (feed).....	330
Fields (1.0) (ufield).....	330
Fifth_Third_Intf (1.0) (ftifd).....	331
file_part_catalog (1.0) (fpctgd).....	331
file_part_fields (1.0) (fpfldd).....	332
file_part_list (1.0) (fplstd).....	332
File_Update_Route (1.0) (furd).....	332
Filters (2.0) (ufltrs).....	333
FIS_Interface (1.0) (fisifd).....	334
FldVals (1.0) (ufldvl).....	334
FLTXROLE (1.0) (uflxrl).....	334
FIXFldVI (1.0) (uflixfl).....	335
FPID_History (1.0) (fpidd).....	335
FPS_Batch_Config (1.0) (fpbcd).....	336

FPS_Batch_Control (1.0) (fpbtcd).....	336
FPS_Cutover (1.0) (fpsctd).....	337
FPS_Member (2.0) (fpsmd).....	338
FPS_Payment_Pri_Group (2.0) (fppgd).....	340
FPS_Payment_Submission (1.0) (fpsubd).....	341
FPS_Payment_Typ (1.0) (fpptd).....	343
FPS_Queue (1.0) (fpsqd).....	343
FPS_Queue_Assign (1.0) (fpqad).....	344
FPS_Queue_Profile (1.0) (fpqpd).....	344
Functs (1.0) (ufncts).....	345
Futr_Key (1.0) (futrkd).....	346
GICC_Acq_SGN (1.0) (giccasd).....	346
GICC_Channel (1.0) (giccd).....	347
GICC_Interface (1.0) (giccifd).....	349
GICC_Iss_SGN (1.0) (giccisd).....	349
GISO_ACQ_MSG_HND (1.0) (gamhndd).....	350
GISO_CRD_ACPT_RT (1.0) (gcrdrtd).....	350
GISO_Interface (1.0) (gisoifd).....	351
GISO_IN_MSG_DEF (1.0) (gimdefd).....	351
GISO_ISS_MSG_HND (1.0) (gimhndd).....	352
GISO_OUT_MSG_DEF (1.0) (gomdefd).....	353
HISO87_Interface (9.0) (hi87d).....	353
HISO87_Proc_Txn (1.0) (hi8ptd).....	356
HISO93_Interface (2.0) (hi93d).....	356
Holiday (1.0) (hldyd).....	357
Host_Public_Key_Security (1.0) (hspkd).....	357
Host_Public_Key_Security_Primary (1.0) (hspkpd).....	358
Host_Public_Key_Security_Second (1.0) (hspksd).....	359
HPDH_Configuration (1.0) (hpdhd).....	360
HPDH_NAC_Term (1.0) (hnacd).....	360
HPDH_NMS_Term (1.0) (hnmsd).....	361
HPRPRFL (2.0) (hprpfd).....	361
HSMCNFG (1.0) (hsmcnf).....	371
IBM_Context (1.0) (ictxd).....	372
IBM_DES (1.0) (idesd).....	373
Identikey (1.0) (idntd).....	374
IDF (1.0) (idf).....	374
IFXDATA (3.0) (ifxdtd).....	389
IFX_Host_Action_Code_Int_Ext (1.0) (ifxacd).....	390
IFX_Host_Interface (1.0) (ifxhid).....	391
Ind_Sort_Code_Directory (1.0) (iscdd).....	391
Ind_Sort_Code_Directory_Input (1.0) (iscdid).....	392
Institution (6.0) (instd).....	393
Instrm_Status_Extrn_to_Intrn (1.0) (iseid).....	397
Instrm_Status_Intrn_to_Extrn (1.0) (isied).....	397

Instrm_Typ_Extrn_to_Intrn (1.0) (iteid).....	397
Instrm_Typ_Intrn_to_Extrn (1.0) (itied).....	398
INSTRUMENT_TYPE (1.0) (itypd).....	399
Instrum_Typ_Interchange_Rel (2.0) (itird).....	399
Interac_Admin (1.0) (intramd).....	400
Interac_ATM_IIN (1.0) (intraid).....	400
Interac_Base (1.0) (intrbad).....	401
Interac_Entry_Point (1.0) (intrepd).....	403
Interac_Interface (1.0) (intrifd).....	404
Interac_POS_IIN (1.0) (intrpid).....	405
Interchange_Prefix (3.0) (ipfxd).....	406
Interchange_Security (5.0) (isecd).....	406
Interchange_Security_Future (1.0) (isecfd).....	419
Interface (5.0) (intfd).....	422
Interface_FPS (2.0) (fpsid).....	425
Interface_Manager (8.0) (ifmgrd).....	426
Interface_SAF (3.0) (ifsafd).....	435
Interface_Station (2.0) (ifstad).....	437
Interface_Terminal (2.0) (iftrmd).....	438
Interface_WPS (2.0) (fpswd).....	438
ISO_Field (1.0) (isofd).....	439
ISO_FLD_DEFN (1.0) (fdefnd).....	440
ISO_Message (1.0) (isomd).....	440
ISO_PROC_CODE (1.0) (pceid).....	442
Issuer_Profile_Map (1.0) (ipmd).....	442
Issuer_Route_Profile (1.0) (irtpd).....	443
Issuer_Txn_Allowed (1.0) (isstxd).....	443
ITMRPRFL (1.0) (imtrd).....	444
JCB_Institution (1.0) (jcbind).....	445
JCB_Interface (1.0) (jcifd).....	445
Journal (2.0) (jrnld).....	446
Journal_Continuation (2.0) (jrnlcd).....	447
Journal_Data_Suppression (1.0) (jdtsd).....	448
Journal_Key_Seq (2.0) (jrnld).....	448
Journal_Key_Seq2 (4.0) (jrnld).....	450
Journal_Profile_Group (1.0) (jpgd).....	452
Journal_Profile_Group_Assign (2.0) (jpgad).....	452
Journal_Query_Config (4.0) (jqcd).....	453
Journal_Query_Config_Output (1.0) (jqcod).....	455
Journal_Query_Output_Assign (1.0) (jqoad).....	456
Journal_Query_Output_Map (1.0) (jqomd).....	457
Journal_Query_Position_Info (2.0) (jqpid).....	457
Key_Map (1.0) (kymapd).....	458
Key_Token (1.0) (ktd).....	458
LCONF (1.0) (lconf).....	459

Limits (1.0) (lmtd).....	460
Linked_Currency (1.0) (lnkcd).....	461
LIS5_Interface (1.0) (li5ifd).....	461
LISTENER (1.0) (lstnd).....	462
LTMRPFL (1.0) (ltmrd).....	463
MACPRFL (1.0) (macd).....	464
MDS_BIN_File_Updt (1.0) (mdsbin).....	464
MDS_Brand_Rel (1.0) (mdsbid).....	465
MDS_Institution (1.0) (mdsiid).....	465
MDS_Interface (1.0) (mdsifd).....	465
Merchant (5.0) (mrchd).....	466
Merchant_Channel_Profile (3.0) (mcpd).....	469
Merchant_Delivery_Channel (6.0) (mrchcd).....	472
Merchant_Delivery_Channel_Profil (3.0) (mdcpd).....	486
Merchant_Master_File (1.0) (mmfd).....	490
Merch_Instr_Typ_Relation (2.0) (mitrd).....	492
MSGCNTX (1.0) (msgctx).....	493
NCR_PIN_Verification (1.0) (ncrd).....	493
Netwk_Brand_Instrm_Reln (1.0) (ipfnd).....	494
NYCE_BIN_File_Updt (1.0) (nybin).....	494
NYCE_Institution (1.0) (nyind).....	495
NYCE_Interface (1.0) (nyifd).....	495
OLTP_Warmboot (1.0) (ooltpd).....	495
OPERID (1.0) (OIF).....	496
OPTRCPT (1.0) (OR).....	496
Password (2.0) (upswd).....	497
PBAL_Impacts (3.0) (pblimd).....	497
PermDetl (1.0) (uprmdt).....	498
PermGrp (1.0) (uprmgr).....	498
Perms (1.0) (uperms).....	498
PermType (1.0) (uprmt).....	498
Perusal_Script (1.0) (perscd).....	499
PmGpXPrm (1.0) (upmgpx).....	499
PMX (1.0) (pmxd).....	500
Positive_Balance (2.0) (pbald).....	500
POS_TC_Proc_Code (1.0) (pstpd).....	504
Prefix (8.0) (prfxd).....	505
Prefix_Block (1.0) (pfxbd).....	515
Presto_Interface (1.0) (prifd).....	516
Pre_Auth_Hold (3.0) (preaud).....	516
PRICE_Interface (1.0) (prceifd).....	534
PRM_Interface (3.0) (prmid).....	535
PROCESS (2.0) (procd).....	535
Proc_Code_ATM_TC (1.0) (atptd).....	536
PROC_CODE_ISO (1.0) (pcied).....	536

Proc_Code_POS_TC (1.0) (psptd).....	537
PswdGrp (1.0) (upswdg).....	537
PswdHist (3.0) (upswdh).....	538
Pulse_Institution (1.0) (pinstd).....	538
Pulse_Interface (2.0) (pulifd).....	539
Pulse_Switch_Date (1.0) (pswid).....	539
RCPTRQRD (1.0) (rcptrd).....	539
Real_Time_Feed_Config (2.0) (rtfcd).....	540
Reason_Online_Code_Description (1.0) (rocdd).....	541
RECEIPT (1.0) (rcptd).....	541
Referral (1.0) (rfrld).....	542
Roles (2.0) (uroles).....	542
RoIXPmGp (1.0) (urolxp).....	543
Route (2.0) (routed).....	543
RQUID (2.0) (rquid).....	550
RVSLSAF (1.0) (RS).....	551
Script (2.0) (scrptd).....	551
Script_Configuration (2.0) (scptcd).....	552
Script_Source (2.0) (scsrcd).....	553
SecGrp (1.0) (usecgp).....	553
Security_Device_Config (2.0) (secdcd).....	554
SIS_ASYNC_DEST_MAP (2.0) (admf).....	555
SMX (1.0) (smxd).....	556
SPAN2_Interface (3.0) (spifd).....	556
SPAN2_Interface_Terminal (1.0) (sptmd).....	557
SPDH_act_cde_descr (1.0) (spiad).....	558
SPDH_Configuration (3.0) (spicd).....	558
SPDH_ISO_Response_Code (1.0) (sprcd).....	559
SPDH_ISO_Response_Text (1.0) (sprtd).....	560
SPDH_Message (2.0) (spimd).....	560
SPDH_opt_resp_data (1.0) (spiod).....	563
SPDH_txn_cde_descr (1.0) (spitd).....	563
SrchFld (1.0) (usrchf).....	564
SRCHPRFL (1.0) (srchd).....	564
SrchXAdt (1.0) (usrchx).....	565
Star_BIN_File_Updt (1.0) (strbin).....	565
Star_Institution (2.0) (sinstd).....	565
Star_Interface (5.0) (strifd).....	566
STAR_Network_Rel (1.0) (strnid).....	566
Star_NE_BIN_File_Updt (1.0) (stnbin).....	567
Star_NE_Network_Rel (1.0) (stnnid).....	567
STMPPRFL (1.0) (stmpd).....	567
STMTDATA (1.0) (stmttd).....	568
Stop_Payment (1.0) (stppyd).....	569
Store_and_Forward (2.0) (safd).....	570

Stream (1.0) (strmd).....	571
Stream132 (1.0) (strm2d).....	571
Stream_Binary (1.0) (strmbd).....	571
Surcharge (2.0) (surchd).....	571
Surcharge_Country_Code (1.0) (succd).....	572
SVS_Interface (1.0) (svsifd).....	573
SVS_Mrch_Num (1.0) (svsmnd).....	573
System_Algorithm_Config (1.0) (sacd).....	574
System_Prefix (2.0) (sprfxd).....	574
TaskFlds (1.0) (utskfl).....	575
TaskFnCs (1.0) (utskfn).....	576
Tasks (1.0) (utasks).....	576
TBP_Daily (2.0) (tbpdd).....	576
TERM_LN_FIID_MAP (1.0) (tlnfid).....	576
Ticket (1.0) (utickt).....	577
TMX (1.0) (tmxd).....	577
Token_Config (1.0) (tknd).....	577
Token_Id_List (2.0) (tknid).....	578
Totals (1.0) (ttld).....	578
Totals_Configuration (1.0) (ttlcd).....	578
Totals_Entry (1.0) (ttled).....	579
Totals_Entry2 (1.0) (ttle2d).....	579
Totals_Tag_Documentation (1.0) (ttltd).....	580
Trace (1.0) (trcd).....	580
Trace_Config (1.0) (trccfd).....	581
Trace_Filter (1.0) (trcfd).....	581
Transport_Key (1.0) (trnsd).....	582
UAE_Interface (1.0) (uaeifd).....	583
Usage (2.0) (usgd).....	583
Users (3.0) (uusers).....	602
User_Perusal_Prfl_Relation (1.0) (upprd).....	602
USRAULOG (1.0) (ualogd).....	603
UsrStat (1.0) (uusrst).....	604
USRXFILT (1.0) (uusrxf).....	604
UsrXRole (1.0) (uusrxr).....	604
VERSIONS (1.0) (versd).....	604
Visa_BIN_File_Updt (1.0) (visbin).....	605
Visa_Brand_Rel (1.0) (vsbid).....	605
Visa_DPS_Institution (1.0) (vdiid).....	605
Visa_DPS_Interface (2.0) (vdifd).....	606
Visa_Institution (2.0) (vsiid).....	606
Visa_Interface (4.0) (visifd).....	607
Visa_PVV (1.0) (vpvvd).....	608
WEBAPPOPTS (1.0) (wboptd).....	611
WEBAPPS (1.0) (webapd).....	611

WEBUSROPTS (1.0) (wbusrd).....611

ZKA_KGK (1.0) (zkgkd).....612

List of data elements.....613

About data source documentation

This document contains information about the BASE24-eps data sources. The information is extracted directly from metamn files for components and is presented alphabetically by data source name.

Audience

This manual is intended for use as a reference source for BASE24-eps configuration managers.

Prerequisites

Readers must be familiar with the BASE24-eps environment and meta database.

What's new

This topic provides an overview of recent changes made to data source documentation.

Release 1.0 Version 11.1 major changes

BASE24-eps data source documentation has been updated to reflect changes made for 11.1. Also, changes include:

- The BASE24-eps Data Source Reference Manual is now an online manual to improve the presentation and access to data source information.
- Assign information is now provided.
- Previous versions of the documentation did not include due to error those data source table names that had the text "OLTP" in the name. This error has been corrected.
- Previous versions of the documentation also did not include, by design, OLTP names. These are now included beginning with this version.

Derived types

Some data elements in data sources are derived from base types. The following table provides versions, base types, and descriptions derived data element types.

Derived type	Version	Base type	Description
acct_num	1.0	bt_stringf(28)	Account Number.
amt	1.0	bt_int64s	Accumulator/Limit Amount.
b24_key	1.0	bt_binaryf(8)	
chan_id	1.0	bt_stringf(16)	Channel Identifier definition.
chk_digits	1.0	bt_stringf(6)	The check digits used by the security tools for check digit validation.
cnt	1.0	bt_int16s	Count.
cnt_lrg	1.0	bt_int32s	Count for large numbers.
comments	1.0	bt_stringf(50)	Free text element to contain comments.
crncy_cde	1.0	bt_int16s	Currency Code
data_src	1.0	bt_stringf(32)	The data source.
email_addr	1.0	bt_stringf(50)	Email address.
evt_rec_typ	1.0	bt_stringf(2)	The record type for the event document can be PC - probable cause, AT - action taken, RM - remedy, SS - sub-system name, TK - token information.
hld_amt	1.0	bt_int64s	The amount associated with a pre-auth hold.
hld_exp_ts	1.0	bt_int64s	The expiration date/time of the associated pre-auth hold.
hld_id	1.0	bt_stringf(20)	The transaction identifier associated with a pre-auth hold. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_typ	1.0	bt_stringf(2)	The type of hold associated with a pre-auth hold. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
instrm_typ	1.0	bt_stringf(2)	One or two character codes which are used to identify card types. The same codes must be used for a particular card type in all of the files. Reserved codes are to be used only as defined, and include: AD = Administrative AX = American Express credit BD = Business deposit C* = Private label credit (includes C, C0-C9, CA, and CC-CZ) CB = Carte Blanche credit D = Demonstration DC = Diners Club credit DS = Discover (Sears) credit M = MasterCard credit MD = MasterCard debit MM = MasterCard dual P* = Proprietary debit (includes P, P0-P9, and PA-PZ) SC = Special, Check SP = Special purpose ST = Super teller V = VISA credit VD = VISA debit VV = VISA dual User-defined Codes: The user can add any one- or two- character code not included in the reserved code list above, according to the following guidelines: - The first character must be alphabetic (A, B, D-O, and Q-Z). - The second character can be A-Z, 0-9, or a blank.
inst_id	1.0	bt_stringf(20)	Institution Identifier.

Derived type	Version	Base type	Description
keyx_hdr	1.0	bt_stringf(8)	The key header field required for a key in the Atalla Key Block (AKB) format.
keyx_kam	1.0	bt_stringf(16)	The MAC of the key header and key data of a key in the Atalla Key Block (AKB) format.
keyx_trpl	1.0	bt_binaryf(48)	The Key encrypted under the hardware security device. If the key is a single-length or double-length key, the field is left-justified and space filled.
key_idx	1.0	bt_int16s	Current key index. Indicates if key1 or key2 is the current key.
lgnt	1.0	bt_stringf(4)	Logical network
nam	1.0	bt_stringf(16)	Name field. For example a script name.
pan	1.0	bt_stringf(28)	Cardholders Account Number
phn_num	1.0	bt_stringf(20)	Phone number.
prfl_def	1.0	bt_stringf(16)	Transaction Profile definition.
prfx_range	1.0	bt_int64s	The fields that contain the low and high prefix ranges.
proc_cde	1.0	bt_stringf(6)	This 6 character code that describes transaction type and the account types involved.
req	1.0	bt_stringf(1)	Required field
timestamp	1.0	bt_int64s	Timestamp (from IFMG)
timr_id	1.0	bt_binaryf(34)	Timer tag, identifier of timer
timr_lmt	1.0	bt_int16s	Timer limit, maximum amount of time to use (from IFMG)
tim_hhmm	1.0	bt_stringf(4)	The time in hours and minutes.
trk_ofst	1.0	bt_int16s	Track offsets.
ts	1.0	bt_int64s	Time Stamp. A value consisting of the number of Microseconds elapsed since Jan 1, 1970.
txn_cde	1.0	bt_stringf(2)	This is the transaction code, which is part of the processing code.
typ	1.0	bt_stringf(2)	This is a basic type element for 2 characters.
usr_prfl	1.0	bt_stringf(16)	User Profile.
vvk	1.0	bt_stringf(6)	The verification value of the generated key used to identify key synchronization errors.
yyymmddhhmmss	1.0	bt_stringf(12)	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
yyyymmddhhmm	1.0	bt_stringf(12)	The date/time format yyyymmddhhmm.
yyyymmdd	1.0	bt_stringf(8)	The date format yyyymmdd.
yyyymm	1.0	bt_stringf(6)	The date format yyyymm.

List of Assigns

This topic provides a list of assigns for data source tables, versions, and physical file names.

ABI_INTERFACE

Table name: ABI_Interface

Version: 1

Phys. file: abifd

ABI_INTERFACE_OLTP

Table name: ABI_Interface_OLTP

Version: 1

Phys. file: abifod

ABI_KEY

Table name: ABI_Key

Version: 1

Phys. file: abikd

ABI_KEY_OLTP

Table name: ABI_Key_OLTP

Version: 1

Phys. file: abikod

ACCEL_INTERFACE

Table name: ACCEL_Interface

Version: 1

Phys. file: acifd

ACCEL_INTERFACE_OLTP

Table name: ACCEL_Interface_OLTP

Version: 1

Phys. file: acifod

ACCOUNT_ROUTING

Table name: Account_Routing

Version: 1

Phys. file: actrtd

ACCOUNT_ROUTING_OLTP

Table name: Account_Routing_OLTP

Version: 1

Phys. file: actrtod

ACCT_STAT_EXT_INT

Table name: Acct_Status_Extrn_to_Intrn

Version: 1

Phys. file: aseid

ACCT_STAT_INT_EXT

Table name: Acct_Status_Intrn_to_Extrn

Version: 1

Phys. file: asied

ACQUIRER_ISSUER_RELATION_OLTP

Table name: Acquirer_Issuer_Relation_OLTP

Version: 1

Phys. file: airod

ACQUIRER_TXN_ALLOWED_OLTP

Table name: Acquirer_Txn_Allowed_OLTP

Version: 1

Phys. file: aqtxod

ACQ_INSTRM_TYP_REL

Table name: Acquirer_Instrument_Type_Rel

Version: 1

Phys. file: aintrd

ACQ_INSTRM_TYP_REL_OLTP

Table name: Acquirer_Instrum_Type_Rel_OLTP

Version: 1

Phys. file: aintod

ACQ_ISS_RELATION

Table name: Acquirer_Issuer_Relation

Version: 1

Phys. file: aird

ACQ_RTE_PROFILE

Table name: Acquirer_Route_Profile

Version: 1

Phys. file: artpd

ACQ_TXN_ALLOWED

Table name: Acquirer_Txn_Allowed

Version: 1

Phys. file: acqtxd

ACTFUNC

Table name: ActFunc

Version: 1

Phys. file: uactfn

ACTION_CODE_EXTRN_TO_INTRN_OLTP

Table name: Action_Code_Extrn_to_Intrn_OLTP

Version: 1

Phys. file: aceiod

ACTION_CODE_INTRN_TO_EXTRN_OLTP

Table name: Action_Code_Intrn_to_Extrn_OLTP

Version: 1

Phys. file: acieod

ACTSESS

Table name: ActSess

Version: 1

Phys. file: uactse

ACTSESS2

Table name: ACTSESS2

Version: 1

Phys. file: uacts2

ACTV_SCRIPT_STAT

Table name: Active_Script_Statistics

Version: 1

Phys. file: actssd

ACT_CDE_EXT_INT

Table name: Action_Code_Extrn_to_Intrn

Version: 2

Phys. file: aceid

ACT_CDE_INT_EXT

Table name: Action_Code_Intrn_to_Extrn

Version: 2

Phys. file: acied

ADMIN_CARD

Table name: Admin_Card

Version: 1

Phys. file: admcd

AEGN_INTERFACE

Table name: AEGN_Interface

Version: 1

Phys. file: aeifd

AEGN_INTERFACE_OLTP

Table name: AEGN_Interface_OLTP

Version: 1

Phys. file: aeifod

AKDS_CAPACITY_REPORT

Table name: Stream132

Version: 1

Phys. file: akdscap

AMEX_CAPN_INTF

Table name: AMEX_CAPN_Interface

Version: 1

Phys. file: acpnfd

AMEX_CAPN_INTF_OLTP

Table name: AMEX_CAPN_Interface_OLTP

Version: 1

Phys. file: acpnfo

APACS_CONFIG

Table name: APACS_Configuration

Version: 2

Phys. file: apacsd

APACS_CONFIG_OLTP

Table name: APACS_Configuration_OLTP

Version: 2

Phys. file: apacod

APCF

Table name: APCF

Version: 1

Phys. file: apcf

APPLCNFG

Table name: APPLCNFG

Version: 2

Phys. file: appld

APPLDSRC

Table name: APPLDSRC

Version: 1

Phys. file: apsrcd

AS2805_CONFIG

Table name: AS2805_Config

Version: 1
Phys. file: as28d

AS2805_CONFIG_OLTP

Table name: AS2805_Config_OLTP
Version: 1
Phys. file: as28od

AS2805_INTERFACE

Table name: AS2805_Interface
Version: 1
Phys. file: as28ifd

AS2805_INTERFACE_OLTP

Table name: AS2805_Interface_OLTP
Version: 1
Phys. file: as28ifo

ATDCNFG

Table name: ATDCNFG
Version: 3
Phys. file: atdcnd

ATMCNFG

Table name: ATMCNFG
Version: 1
Phys. file: atmcnd

ATMLOG

Table name: ATMLOG
Version: 1
Phys. file: atlgd

ATM_CONF

Table name: ATM_CONF
Version: 1
Phys. file: atmcnf

ATM_CONSUMER_MEDIA

Table name: ATM_CONSUMER_MEDIA
Version: 2
Phys. file: atmmed

ATM_CONSUMER_MEDIA_OLTP

Table name: ATM_CONSUMER_MEDIA_OLTP
Version: 2
Phys. file: atmmeo

List of Assigns

ATM_DD1

Table name: ATM_DD1

Version: 3

Phys. file: atmdd1

ATM_DD2

Table name: ATM_DD2

Version: 1

Phys. file: atmdd2

ATM_DIAL_UP_CMD

Table name: ATM_DIAL_UP_CMD

Version: 1

Phys. file: atmdcd

ATM_DKM

Table name: ATM_DKM

Version: 1

Phys. file: atdkmd

ATM_DKM_OLTP

Table name: ATM_DKM_OLTP

Version: 1

Phys. file: atdkmod

ATM_DS1

Table name: ATM_DS1

Version: 4

Phys. file: atmds1

ATM_DS1_OLTP

Table name: ATM_DS1_OLTP

Version: 4

Phys. file: atmos1

ATM_EMV

Table name: ATM_EMV

Version: 1

Phys. file: atmemd

ATM_EMV_OLTP

Table name: ATM_EMV_OLTP

Version: 1

Phys. file: atmemo

ATM_FAST_CASH

Table name: ATM_FAST_CASH

Version: 1

Phys. file: atmfcf

ATM_FAST_CASH_OLTP

Table name: ATM_FAST_CASH_OLTP

Version: 1

Phys. file: atmfd

ATM_FLOW_CNTL

Table name: ATM_FLOW_CNTL

Version: 1

Phys. file: atmmfd

ATM_FLOW_CNTL_OLTP

Table name: ATM_FLOW_CNTL_OLTP

Version: 1

Phys. file: atmmod

ATM_HOPR

Table name: ATM_HOPR

Version: 1

Phys. file: atmhpd

ATM_HOPR_OLTP

Table name: ATM_HOPR_OLTP

Version: 1

Phys. file: atmhd

ATM_IFXDATA

Table name: ATM_IFXDATA

Version: 1

Phys. file: atmifx

ATM_INACT

Table name: ATM_INACT

Version: 1

Phys. file: atmind

ATM_INACT_OLTP

Table name: ATM_INACT_OLTP

Version: 1

Phys. file: atmiod

ATM_INFO_RPT

Table name: Stream132

Version: 1

Phys. file: atinf

ATM_MAC

Table name: ATM_MAC

Version: 1

Phys. file: atmmcd

ATM_MAC_OLTP

Table name: ATM_MAC_OLTP

Version: 1

Phys. file: atmmco

ATM_MBYTE_XLATE

Table name: ATM_MBYTE_XLATE

Version: 1

Phys. file: atmxdx

ATM_MBYTE_XLATE_OLTP

Table name: ATM_MBYTE_XLATE_OLTP

Version: 1

Phys. file: atmxdx

ATM_OPER

Table name: ATM_OPER

Version: 1

Phys. file: atmopd

ATM_OPER_OLTP

Table name: ATM_OPER_OLTP

Version: 1

Phys. file: atmood

ATM_OP_CDE

Table name: ATM_OP_CDE

Version: 2

Phys. file: atmopc

ATM_OP_CDE_OLTP

Table name: ATM_OP_CDE_OLTP

Version: 2

Phys. file: atmopo

ATM_PEAK_LOAD

Table name: ATM_PEAK_LOAD

Version: 1

Phys. file: atmpkd

ATM_PEAK_LOAD_OLTP

Table name: ATM_PEAK_LOAD_OLTP

Version: 1
Phys. file: atmpko

ATM_PREV_TTL

Table name: ATM_PREV_TTL
Version: 3
Phys. file: atmprv

ATM_PRFL

Table name: ATM_PRFL
Version: 3
Phys. file: atmprd

ATM_PRFL_OLTP

Table name: ATM_PRFL_OLTP
Version: 3
Phys. file: atmpro

ATM_RECEIPT

Table name: ATM_RECEIPT
Version: 1
Phys. file: atmrcd

ATM_RECEIPT_OLTP

Table name: ATM_RECEIPT_OLTP
Version: 1
Phys. file: atmrod

ATM_REQ_RCPT

Table name: ATM_REQ_RCPT
Version: 1
Phys. file: atmqrđ

ATM_REQ_RCPT_OLTP

Table name: ATM_REQ_RCPT_OLTP
Version: 1
Phys. file: atmqod

ATM_RQUID

Table name: ATM_RQUID
Version: 1
Phys. file: ifxrqd

ATM_SSB_BIN

Table name: ATM_SSB_BIN
Version: 1
Phys. file: ssbbnd

ATM_SSB_BIN_OLTP

Table name: ATM_SSB_BIN_OLTP

Version: 1

Phys. file: ssbbod

ATM_SSB_BNA

Table name: ATM_SSB_BNA

Version: 1

Phys. file: ssbbna

ATM_SSB_CPL

Table name: ATM_SSB_CPL

Version: 1

Phys. file: ssbcpl

ATM_STATE_SCRN

Table name: ATM_STATE_SCRN

Version: 2

Phys. file: atmssd

ATM_STATE_SCRN_OLTP

Table name: ATM_STATE_SCRN_OLTP

Version: 2

Phys. file: atmssso

ATM_STMNT_DATA

Table name: ATM_STMNT_DATA

Version: 1

Phys. file: atmstd

ATM_STMNT_PRNT

Table name: ATM_STMNT_PRNT

Version: 1

Phys. file: atmpsds

ATM_STMNT_PRNT_OLTP

Table name: ATM_STMNT_PRNT_OLTP

Version: 1

Phys. file: atmpod

ATM_SUR

Table name: ATM_SUR

Version: 1

Phys. file: atmchd

ATM_SUR_OLTP

Table name: ATM_SUR_OLTP

Version: 1

Phys. file: atmcod

ATM_TC_PROC_CODE

Table name: ATM_TC_Proc_Code

Version: 1

Phys. file: attpd

ATM_TRAN_CODE_PROC_CODE_OLTP

Table name: ATM_Tran_Code_Proc_Code_OLTP

Version: 1

Phys. file: attpod

AUDDTLPK

Table name: AudDtlPK

Version: 1

Phys. file: uaudpk

AUDITDTL

Table name: AuditDtl

Version: 1

Phys. file: uaudtl

AUDITTBL

Table name: AuditTbl

Version: 1

Phys. file: uaudtb

AUDIT_SAF_CONFIG

Table name: Audit_Store_and_Forward_Config

Version: 1

Phys. file: asafcd

AUDIT_STORE_AND_FORWARD

Table name: Audit_Store_and_Forward

Version: 1

Phys. file: asafd

AUDIT_STORE_AND_FORWARD_OUTSTND

Table name: Audit_Store_and_Forward

Version: 1

Phys. file: asafod

AUTHORIZATION_SCRIPT_OLTP

Table name: Authorization_Script_OLTP

Version: 1

Phys. file: athsod

AUTH_SCRIPT

Table name: Authorization_Script

Version: 1

Phys. file: athscd

B24EPS_LGNT_MAP

Table name: B24EPS_lgnt_map

Version: 1

Phys. file: b24lmd

B24EPS_LGNT_MAP_OLTP

Table name: B24EPS_lgnt_map_OLTP

Version: 1

Phys. file: b24lmo

B24_FILETYP_MAP

Table name: B24_filetyp_map

Version: 1

Phys. file: b24ftd

B24_FILETYP_MAP_OLTP

Table name: B24_filetyp_map_OLTP

Version: 1

Phys. file: b24fto

B53_INSTITUTION

Table name: B53_Institution

Version: 1

Phys. file: b53ind

B53_INSTITUTION_OLTP

Table name: B53_Institution_OLTP

Version: 1

Phys. file: b53nod

BANKNET_CONFIG

Table name: Banknet_Configuration

Version: 5

Phys. file: bnetcd

BANKNET_CONFIG_OLTP

Table name: Banknet_Configuration_OLTP

Version: 5

Phys. file: bnetod

BANKNET_GROUP_TIMERS

Table name: Banknet_Group_Timers

Version: 2

Phys. file: bngtd

BANKNET_INST_ID

Table name: Banknet_Institution_Id

Version: 3

Phys. file: bniid

BANKNET_INST_ID2

Table name: Banknet_Institution_Id2

Version: 1

Phys. file: bni2d

BANKNET_INST_ID2_OLTP

Table name: Banknet_Institution_Id2_OLTP

Version: 1

Phys. file: bni2od

BANKNET_INST_ID_OLTP

Table name: Banknet_Institution_Id_OLTP

Version: 3

Phys. file: bniiid

BANKNET_MERCHANT_PROGRAM_OLTP

Table name: Banknet_Merchant_Program_OLTP

Version: 1

Phys. file: bntmod

BANKNET_MRCH_PGM

Table name: Banknet_Merchant_Program

Version: 1

Phys. file: bntmpd

BASE24_KEYF

Table name: BASE24_KEYF

Version: 1

Phys. file: keyfd

BATCH_AUTH_CNFG

Table name: Batch_Auth_Config

Version: 1

Phys. file: bacd

BATCH_AUTH_CONFIG_OLTP

Table name: Batch_Auth_Config_OLTP

Version: 1

Phys. file: bacod

BATCH_AUTH_POSN

Table name: Batch_Auth_Posn

Version: 1

Phys. file: bapd

BEPS_INSTRM_PRTY

Table name: BEPS_Instrm_Prty

Version: 1

Phys. file: beipd

BEPS_INSTRM_PRTY_OLTP

Table name: BEPS_Instrm_Prty_OLTP

Version: 1

Phys. file: beipod

BIC_INTERFACE

Table name: BIC_Interface

Version: 1

Phys. file: biifd

BIC_INTERFACE_OLTP

Table name: BIC_Interface_OLTP

Version: 1

Phys. file: biifod

BLZ_MAP

Table name: BLZ_Map

Version: 1

Phys. file: blzmpd

BLZ_MAP2_OLTP

Table name: BLZ_Map2_OLTP

Version: 1

Phys. file: blzm2od

BLZ_MAP_OLTP

Table name: BLZ_Map_OLTP

Version: 1

Phys. file: blzmpod

BNFT_INTERFACE

Table name: BNFT_Interface

Version: 1

Phys. file: bnifd

BNFT_INTERFACE_OLTP

Table name: BNFT_Interface_OLTP

Version: 1
Phys. file: bnifod

BNTNG_HEADER

Table name: BNTng_Header
Version: 1
Phys. file: bnth2d

BNTNG_HEADER_OLTP

Table name: BNTng_Header_OLTP
Version: 1
Phys. file: bnth2od

BNTNG_INIT_DATA

Table name: BNTng_Init_Data
Version: 1
Phys. file: bntid

BPDATA

Table name: BPDATA
Version: 1
Phys. file: bpdatd

CACNFSAF

Table name: CACNFSAF
Version: 1
Phys. file: cacsaf

CACNTX

Table name: CACNTX
Version: 1
Phys. file: cacntx

CARD

Table name: file_part_catalog
Version: 1
Phys. file: crdcat

CARDNET_ID_CODE

Table name: Cardnet_ID_Code
Version: 1
Phys. file: crdnicd

CARDNET_ID_CODE_OLTP

Table name: Cardnet_ID_Code_OLTP
Version: 1
Phys. file: crdnico

CARDNET_INTERFACE_OLTP

Table name: Cardnet_Interface_OLTP

Version: 1

Phys. file: crdnifo

CARDNET_INTERFACE_TERMINAL_OLTP

Table name: Cardnet_Interface_Terminal_OLTP

Version: 1

Phys. file: crdnito

CARDNET_INTF

Table name: Cardnet_Interface

Version: 1

Phys. file: crdnifd

CARDNET_TERMINAL

Table name: Cardnet_Interface_Terminal

Version: 1

Phys. file: crdnitd

CARD_01A

Table name: Card

Version: 5

Phys. file: crd01a

CARD_01B

Table name: Card

Version: 5

Phys. file: crd01b

CARD_ACCOUNT

Table name: file_part_catalog

Version: 1

Phys. file: caccat

CARD_ACCTM_01A

Table name: CARD_ACCOUNT_MBYTE

Version: 1

Phys. file: cdm01a

CARD_ACCTM_01B

Table name: CARD_ACCOUNT_MBYTE

Version: 1

Phys. file: cdm01b

CARD_ACCT_01A

Table name: Card_Account

Version: 3
Phys. file: cda01a

CARD_ACCT_01B

Table name: Card_Account
Version: 3
Phys. file: cda01b

CARD_ACCT_MBYTE

Table name: file_part_catalog
Version: 1
Phys. file: caccam

CARD_BLOCK

Table name: Card_Block
Version: 1
Phys. file: crdbd

CARD_BLOCK_OLTP

Table name: Card_Block_OLTP
Version: 1
Phys. file: crdbod

CARD_IMPACTS

Table name: Card_Impacts
Version: 3
Phys. file: crdimd

CARD_VERIFICATION_OLTP

Table name: Card_Verification_OLTP
Version: 2
Phys. file: crdvod

CARD_VRFCTN

Table name: Card_Verification
Version: 1
Phys. file: crdvd

CHANNEL_SECURITY

Table name: Channel_Security
Version: 6
Phys. file: csecd

CHAN_IM_TYP_RLN

Table name: Channel_Instrm_Type_Relation
Version: 2
Phys. file: citrd

CHAN_INSTRM_TYP_REL

Table name: Channel_Instrument_Type_Rel

Version: 1

Phys. file: cintrd

CHAN_INSTRM_TYP_REL_OLTP

Table name: Channel_Instrum_Type_Rel_OLTP

Version: 1

Phys. file: cintod

CHAN_PIM_TYP_RLN

Table name: Chan_Profile_Instrm_Typ_Relation

Version: 2

Phys. file: cpitrd

CHAN_PKEY_SEC

Table name: Channel_Public_Key_Security

Version: 3

Phys. file: chnpkd

CHAN_PROFILE_INSTRM_TYP_REL_OLTP

Table name: Chan_Profile_Instrm_Typ_Rel_OLTP

Version: 2

Phys. file: cpitod

CHAN_SEC_FUTURE

Table name: Channel_Security_Future

Version: 1

Phys. file: csecfd

CHECK_STATUS

Table name: file_part_catalog

Version: 1

Phys. file: ckscat

CHECK_TYPE

Table name: Check_Type

Version: 1

Phys. file: cktypd

CHECK_TYPE_OLTP

Table name: Check_Type_OLTP

Version: 1

Phys. file: cktypod

CHIP_AUTHENTICATION

Table name: Chip_Authentication

Version: 1
Phys. file: cad

CHIP_AUTHENTICATION_OLTP

Table name: Chip_Authentication_OLTP
Version: 1
Phys. file: caod

CHK_STAT_01A

Table name: Check_Status
Version: 1
Phys. file: cks01a

CHK_STAT_01B

Table name: Check_Status
Version: 1
Phys. file: cks01b

CIRCUIT_INTF

Table name: Circuit_Interface
Version: 1
Phys. file: crctfd

CIRCUIT_INTF_OLTP

Table name: Circuit_Interface_OLTP
Version: 1
Phys. file: crctfo

CMPTPRFL

Table name: CMPTPRFL
Version: 1
Phys. file: cmptd

CNTGCY_INTERFACE

Table name: Contingency_Interface
Version: 1
Phys. file: ctgyd

COMPILER_MESSAGE

Table name: Compiler_Message
Version: 2
Phys. file: cmsgd

CONTEXT

Table name: Context_USEC
Version: 1
Phys. file: ucntxt

CONTEXT_CONFIG

Table name: Context_Configuration

Version: 1

Phys. file: ctxcd

CONTEXT_CONFIGURATION_OLTP

Table name: Context_Configuration_OLTP

Version: 1

Phys. file: ctxcod

CONTINGENCY_INTERFACE_OLTP

Table name: Contingency_Interface_OLTP

Version: 1

Phys. file: ctgyod

CREDIT_DEBIT_MASTER

Table name: Credit_Debit_Master_File

Version: 1

Phys. file: cdmfd

CREDIT_DEBIT_MASTER_OLTP

Table name: Credit_Debit_Master_File_OLTP

Version: 1

Phys. file: cdmfod

CRNCY_CONV_RATE

Table name: Currency_Conversion_Rate

Version: 1

Phys. file: ccrd

CTVRSAF

Table name: CTVRSAF

Version: 3

Phys. file: cosafd

CUP_INSTITUTION

Table name: CUP_Institution

Version: 1

Phys. file: cupind

CUP_INSTITUTION_OLTP

Table name: CUP_Institution_OLTP

Version: 1

Phys. file: cupino

CUP_INTERFACE

Table name: CUP_Interface

Version: 1

Phys. file: cupifd

CUP_INTERFACE_OLTP

Table name: CUP_Interface_OLTP

Version: 1

Phys. file: cupifo

CURRENCY_CONVERSION_RATE_OLTP

Table name: Currency_Conversion_Rate_OLTP

Version: 1

Phys. file: ccrod

CXD

Table name: Context

Version: 1

Phys. file: ctxd

CXD_ABI

Table name: Context

Version: 1

Phys. file: cxabid

CXD_ACCEL

Table name: Context

Version: 1

Phys. file: cxacd

CXD_AEGN

Table name: Context

Version: 1

Phys. file: cxaed

CXD_AMEX_CAPN

Table name: Context

Version: 1

Phys. file: cxacpnd

CXD_AS2805

Table name: Context

Version: 1

Phys. file: cxas28d

CXD_ATM

Table name: Context

Version: 1

Phys. file: cxatmd

CXD_B53

Table name: Context
Version: 1
Phys. file: cxb53d

CXD_BANKNET

Table name: Context
Version: 1
Phys. file: cxbnetd

CXD_BIC

Table name: Context
Version: 1
Phys. file: cxbid

CXD_BNFT

Table name: Context
Version: 1
Phys. file: cxbnftd

CXD_CIRCUIT

Table name: Context
Version: 1
Phys. file: cxcrctd

CXD_CONTINGENCY

Table name: Context
Version: 1
Phys. file: cxctgyd

CXD_CSC

Table name: Context
Version: 1
Phys. file: cxcsd

CXD_CUP

Table name: Context
Version: 1
Phys. file: cxcupd

CXD_DIAS

Table name: Context
Version: 1
Phys. file: cxdiasd

CXD_DISCOVER

Table name: Context

Version: 1
Phys. file: cxdscvd

CXD_EFUNDS

Table name: Context
Version: 1
Phys. file: cxefnd

CXD_EPSNET

Table name: Context
Version: 1
Phys. file: cxepd

CXD_EQUENS

Table name: Context
Version: 1
Phys. file: cxeqnsd

CXD_ERSB

Table name: Context
Version: 1
Phys. file: cxersbd

CXD_FIFTH_THIRD

Table name: Context
Version: 1
Phys. file: cxftd

CXD_FIS

Table name: Context
Version: 1
Phys. file: cxfisd

CXD_FPSI

Table name: Context
Version: 1
Phys. file: cxpid

CXD_FPSW

Table name: Context
Version: 1
Phys. file: cxpwd

CXD_GICC

Table name: Context
Version: 1
Phys. file: cxgiccd

CXD_GISO

Table name: Context

Version: 1

Phys. file: cxgisod

CXD_HISO

Table name: Context

Version: 1

Phys. file: cxhisd

CXD_IFX_HOST_INTF

Table name: Context

Version: 1

Phys. file: cxifxhd

CXD_INTERAC

Table name: Context

Version: 1

Phys. file: cxintrd

CXD_ISO93

Table name: Context

Version: 1

Phys. file: cxiso93d

CXD_JCB

Table name: Context

Version: 1

Phys. file: cxjcd

CXD_LIS5

Table name: Context

Version: 1

Phys. file: cxlis5d

CXD_MDS

Table name: Context

Version: 1

Phys. file: cxmds

CXD_NYCE

Table name: Context

Version: 1

Phys. file: cxnyd

CXD_PRESTO

Table name: Context

Version: 1
Phys. file: cxprd

CXD_PRICE

Table name: Context
Version: 1
Phys. file: cxprcd

CXD_PRM

Table name: Context
Version: 1
Phys. file: cxprmd

CXD_PULSE

Table name: Context
Version: 1
Phys. file: cxpulsd

CXD_SPAN2

Table name: Context
Version: 1
Phys. file: cxspd

CXD_STAR

Table name: Context
Version: 1
Phys. file: cxstrd

CXD_SVS

Table name: Context
Version: 1
Phys. file: cxsvsd

CXD_UAE

Table name: Context
Version: 1
Phys. file: cxuaed

CXD_VISA

Table name: Context
Version: 1
Phys. file: cxvisad

CXD_VISA_DPS

Table name: Context
Version: 1
Phys. file: cxvdps

DALSLCT

Table name: Stream132

Version: 1

Phys. file: dalslct

DAL_TBL

Table name: dal_tbl

Version: 1

Phys. file: daltbl

DATASRC

Table name: DATASRC

Version: 1

Phys. file: dtsrct

DB2CONV_REPORT

Table name: Stream132

Version: 1

Phys. file: dbcnvrpt

DERIVATION_KEY

Table name: Derivation_Key

Version: 2

Phys. file: drvkd

DERIVATION_KEY_OLTP

Table name: Derivation_Key_OLTP

Version: 2

Phys. file: drvkod

DIAS_INTERFACE

Table name: DIAS_Interface

Version: 1

Phys. file: diasfd

DIEBOLD_NUMBER_TABLE_OLTP

Table name: Diebold_Number_Table_OLTP

Version: 1

Phys. file: dntod

DIEBOLD_NUM_TBL

Table name: Diebold_Number_Table

Version: 1

Phys. file: dntd

DISCOVER_INST

Table name: Discover_Institution

Version: 1
Phys. file: dscvnd

DISCOVER_INST_OLTP

Table name: Discover_Institution_OLTP
Version: 1
Phys. file: dscvno

DISCOVER_INTF

Table name: Discover_Interface
Version: 1
Phys. file: dscvfd

DISCOVER_INTF_OLTP

Table name: Discover_Interface_OLTP
Version: 1
Phys. file: dscvfo

DS_OLTP_RELATION

Table name: DS_OLTP_Relation
Version: 1
Phys. file: doltpd

DUAL_PIN_VERIFICATION_OLTP

Table name: Dual_PIN_Verification_OLTP
Version: 1
Phys. file: dpvnod

DUAL_PIN_VRFCTN

Table name: Dual_PIN_Verification
Version: 1
Phys. file: dpvnd

DYNAMIC_CARD_VERIFICATION_OLTP

Table name: Dynamic_Card_Verification_OLTP
Version: 1
Phys. file: dcrdod

DYN_CARD_VRFCTN

Table name: Dynamic_Card_Verification
Version: 1
Phys. file: dcrdvd

EFUNDS_INST

Table name: EFunds_Institution
Version: 1
Phys. file: efiid

EFUNDS_INST_OLTP

Table name: EFunds_Institution_OLTP

Version: 1

Phys. file: efio

EFUNDS_INTERFACE

Table name: EFunds_Interface

Version: 3

Phys. file: efifd

EFUNDS_INTERFACE_OLTP

Table name: EFunds_Interface_OLTP

Version: 3

Phys. file: efiod

EMVPRFL

Table name: EMVPRFL

Version: 1

Phys. file: emvprd

EMV_CARD_VRFN_RSLTS_OLTP

Table name: EMV_Card_Vrfn_Results_OLTP

Version: 1

Phys. file: cvrod

EMV_CARD_VRFN_RSLTS_ORDER_OLTP

Table name: EMV_Card_Vrfn_Results_Order_OLTP

Version: 1

Phys. file: cvrood

EMV_CRD_VRF_RSLT

Table name: EMV_Card_Vrfn_Results_Status

Version: 1

Phys. file: cvrd

EMV_ISS_AUTH_DTA

Table name: EMV_Iss_Auth_Dta

Version: 1

Phys. file: eiadd

EMV_ISS_AUTH_DTA_OLTP

Table name: EMV_Iss_Auth_Dta_OLTP

Version: 1

Phys. file: eiadod

EMV_RSN_ONL_CDE

Table name: EMV_Reason_Online_Code_Status

Version: 1
Phys. file: rocd

EMV_RSN_ONL_CDE_OLTP

Table name: EMV_Reason_Online_Code_OLTP
Version: 1
Phys. file: rocod

EMV_SCRIPT_CONTEXT

Table name: EMV_Script_Context
Version: 1
Phys. file: escd

EMV_SECURITY

Table name: EMV_Security
Version: 5
Phys. file: emvsd

EMV_SECURITY_OLTP

Table name: EMV_Security_OLTP
Version: 6
Phys. file: emvsod

EMV_TERM_VRFN_RSLTS_OLTP

Table name: EMV_Term_Vrfn_Results_OLTP
Version: 1
Phys. file: tvrod

EMV_TERM_VRFN_RSLTS_ORDER_OLTP

Table name: EMV_Term_Vrfn_Results_Order_OLTP
Version: 1
Phys. file: tvrood

EMV_TRM_VRF_RSLT

Table name: EMV_Terminal_Vrfn_Results_Status
Version: 1
Phys. file: tvrd

ENVIRONMENT

Table name: Environment
Version: 1
Phys. file: envmtd

EPP_SERIAL_NUM

Table name: EPP_Serial_Number
Version: 1
Phys. file: epnumd

EPSNET_INST

Table name: EPSNET_Inst

Version: 1

Phys. file: epiifd

EPSNET_INSTITUTION_OLTP

Table name: EPSNET_Institution_OLTP

Version: 1

Phys. file: epiiod

EPSNET_INTERFACE

Table name: EPSNET_Interface

Version: 1

Phys. file: epsnfd

EPSNET_INTERFACE_OLTP

Table name: EPSNET_Interface_OLTP

Version: 1

Phys. file: epsnod

EQUENS_INTERFACE

Table name: Equens_Interface

Version: 1

Phys. file: eqnifd

EQUENS_INTERFACE_OLTP

Table name: Equens_Interface_OLTP

Version: 1

Phys. file: eqnifo

EQUENS_IT_EXT

Table name: Equens_Instrm_Typ_Extrn

Version: 1

Phys. file: eqnied

EQUENS_IT_EXT_OLTP

Table name: Equens_Instrm_Typ_Extrn_OLTP

Version: 1

Phys. file: eqnieo

EQUENS_IT_INT

Table name: Equens_Instrm_Typ_Intrn

Version: 1

Phys. file: eqniid

EQUENS_IT_INT_OLTP

Table name: Equens_Instrm_Typ_Intrn_OLTP

Version: 1
Phys. file: eqniio

ERSB_INTERFACE

Table name: ERSB_Interface
Version: 1
Phys. file: ersbifd

ERSB_INTERFACE_OLTP

Table name: ERSB_Interface_OLTP
Version: 1
Phys. file: ersbifo

ESADCF

Table name: ESAPDT
Version: 1
Phys. file: eadcfd

ESAPDT

Table name: ESAPDT
Version: 3
Phys. file: eapdtd

ESATDD1

Table name: ESATDD1
Version: 3
Phys. file: eatd1d

ESATDD2

Table name: ESATDD2
Version: 2
Phys. file: eatd2d

ESATDL

Table name: ESATDL
Version: 1
Phys. file: eatdld

ESATDS1

Table name: ESATDS1
Version: 2
Phys. file: eats1d

EURO_OPTED_CRNCY

Table name: Euro_Opted_Currency
Version: 1
Phys. file: eocd

EURO_OPTED_CURRENCY_OLTP

Table name: Euro_Opted_Currency_OLTP

Version: 1

Phys. file: eocod

EVENT

Table name: Event

Version: 1

Phys. file: eventd

EVENTLOG

Table name: EVENTLOG

Version: 1

Phys. file: evtld

EVENT_DOCUMENT

Table name: Event_Document

Version: 1

Phys. file: evdocd

EVENT_OLTP

Table name: Event_OLTP

Version: 1

Phys. file: evtod

EVNTLOG

Table name: EVNTLOG

Version: 1

Phys. file: evtlog

EVT_REPORT

Table name: Stream132

Version: 1

Phys. file: strmd

EXCEPTION_LOG

Table name: Exception_Log

Version: 2

Phys. file: exlogd

EXCPT

Table name: EXCPT

Version: 1

Phys. file: IBMQREP_EXCEPTIONS

EXPORTD_OPER_DOC

Table name: Exported_Operator_Documentation

Version: 1
Phys. file: opdocd

EXTRCNCT

Table name: EXTRCNCT
Version: 1
Phys. file: extcnd

FCSHPRFL

Table name: FCSHPRFL
Version: 1
Phys. file: fcschd

FEES

Table name: Fees
Version: 1
Phys. file: feed

FEES_OLTP

Table name: Fees_OLTP
Version: 1
Phys. file: feeod

FIELDS

Table name: Fields
Version: 1
Phys. file: ufield

FIFTH_THIRD_INTF

Table name: Fifth_Third_Intf
Version: 1
Phys. file: ftifd

FIFTH_THIRD_INTF_OLTP

Table name: Fifth_Third_Intf_OLTP
Version: 1
Phys. file: ftifod

FILE_PART_FIELDS

Table name: file_part_fields
Version: 1
Phys. file: fpfldd

FILE_PART_FIELDS_OLTP

Table name: file_part_fields_OLTP
Version: 1
Phys. file: fpflod

FILE_PART_LIST

Table name: file_part_list

Version: 1

Phys. file: fplstd

FILE_PART_LIST_OLTP

Table name: file_part_list_OLTP

Version: 1

Phys. file: fplsod

FILE_UPDATE_ROUTE

Table name: File_Update_Route

Version: 1

Phys. file: furd

FILE_UPDATE_ROUTE_OLTP

Table name: File_Update_Route_OLTP

Version: 1

Phys. file: furod

FILTERS

Table name: Filters

Version: 2

Phys. file: ufltrs

FIS_INTERFACE

Table name: FIS_Interface

Version: 1

Phys. file: fisifd

FIS_INTERFACE_OLTP

Table name: FIS_Interface_OLTP

Version: 1

Phys. file: fisiod

FLDVALS

Table name: FldVals

Version: 1

Phys. file: ufldvl

FLTXROLE

Table name: FLTXROLE

Version: 1

Phys. file: uflxrl

FLXFLDVL

Table name: FIXFldVI

Version: 1
Phys. file: uflxf1

FPID_HISTORY1

Table name: FPID_History
Version: 1
Phys. file: fpid1d

FPID_HISTORY2

Table name: FPID_History
Version: 1
Phys. file: fpid2d

FPID_HISTORY3

Table name: FPID_History
Version: 1
Phys. file: fpid3d

FPID_HISTORY4

Table name: FPID_History
Version: 1
Phys. file: fpid4d

FPID_HISTORY5

Table name: FPID_History
Version: 1
Phys. file: fpid5d

FPID_HISTORY6

Table name: FPID_History
Version: 1
Phys. file: fpid6d

FPID_HISTORY7

Table name: FPID_History
Version: 1
Phys. file: fpid7d

FPS_BATCH_CNTL

Table name: FPS_Batch_Control
Version: 1
Phys. file: fpbtcd

FPS_BATCH_CONFIG

Table name: FPS_Batch_Config
Version: 1
Phys. file: fpbcd

FPS_BATCH_CONFIG_OLTP

Table name: FPS_Batch_Config_OLTP

Version: 1

Phys. file: fpbcod

FPS_CUTOVER

Table name: FPS_Cutover

Version: 1

Phys. file: fpsctd

FPS_MEMBER

Table name: FPS_Member

Version: 2

Phys. file: fpsmd

FPS_MEMBER_OLTP

Table name: FPS_Member_OLTP

Version: 2

Phys. file: fpsmod

FPS_PAYMENT_PRI_GROUP_OLTP

Table name: FPS_Payment_Pri_Group_OLTP

Version: 2

Phys. file: fppgod

FPS_PAYMENT_TYP_OLTP

Table name: FPS_Payment_Typ_OLTP

Version: 1

Phys. file: fpptod

FPS_PMNT_PRI_GRP

Table name: FPS_Payment_Pri_Group

Version: 2

Phys. file: fppgd

FPS_PMNT_SUB

Table name: FPS_Payment_Submission

Version: 1

Phys. file: fpsubd

FPS_PMNT_TYP

Table name: FPS_Payment_Typ

Version: 1

Phys. file: fpptd

FPS_QUEUE

Table name: FPS_Queue

Version: 1
Phys. file: fpsqd

FPS_QUEUE_AS

Table name: FPS_Queue_Assign
Version: 1
Phys. file: fpqad

FPS_QUEUE_ASSIGN_OLTP

Table name: FPS_Queue_Assign_OLTP
Version: 1
Phys. file: fpqaod

FPS_QUEUE_MANAGER_OLTP

Table name: FPS_Queue_Manager_OLTP
Version: 1
Phys. file: fpqmod

FPS_QUEUE_PF

Table name: FPS_Queue_Profile
Version: 1
Phys. file: fpqpd

FPS_QUEUE_PROFILE_OLTP

Table name: FPS_Queue_Profile_OLTP
Version: 1
Phys. file: fpqpod

FUNCTS

Table name: Functs
Version: 1
Phys. file: ufncts

FUTR_KEY

Table name: Futr_Key
Version: 1
Phys. file: futrkd

GICC_ACQ_SGN

Table name: GICC_Acq_SGN
Version: 1
Phys. file: giccasd

GICC_CHAN

Table name: GICC_Channel
Version: 1
Phys. file: giccd

GICC_INTERFACE

Table name: GICC_Interface

Version: 1

Phys. file: giccifd

GICC_INTERFACE_OLTP

Table name: GICC_Interface_OLTP

Version: 1

Phys. file: giccifo

GICC_ISS_SGN

Table name: GICC_Iss_SGN

Version: 1

Phys. file: giccisd

GISO_ACQ_MSG_HND

Table name: GISO_ACQ_MSG_HND

Version: 1

Phys. file: gamhndd

GISO_ACQ_MSG_HND_OLTP

Table name: GISO_ACQ_MSG_HND_OLTP

Version: 1

Phys. file: gamhndo

GISO_CRD_ACPT_RT

Table name: GISO_CRD_ACPT_RT

Version: 1

Phys. file: gcrdrtd

GISO_CRD_ACPT_RT_OLTP

Table name: GISO_CRD_ACPT_RT_OLTP

Version: 1

Phys. file: gcrdrto

GISO_INTERFACE

Table name: GISO_Interface

Version: 1

Phys. file: gisoifd

GISO_INTERFACE_OLTP

Table name: GISO_Interface_OLTP

Version: 1

Phys. file: gisoifo

GISO_IN_MSG_DEF

Table name: GISO_IN_MSG_DEF

Version: 1

Phys. file: gimdefd

GISO_IN_MSG_DEF_OLTP

Table name: GISO_IN_MSG_DEF_OLTP

Version: 1

Phys. file: gimdefo

GISO_ISS_MSG_HND

Table name: GISO_ISS_MSG_HND

Version: 1

Phys. file: gimhndd

GISO_ISS_MSG_HND_OLTP

Table name: GISO_ISS_MSG_HND_OLTP

Version: 1

Phys. file: gimhndo

GISO_OUT_MSG_DEF

Table name: GISO_OUT_MSG_DEF

Version: 1

Phys. file: gomdefd

GISO_OUT_MSG_DEF_OLTP

Table name: GISO_OUT_MSG_DEF_OLTP

Version: 1

Phys. file: gomdefo

HISO87_INTERFACE

Table name: HISO87_Interface

Version: 9

Phys. file: hi87d

HISO87_INTERFACE_OLTP

Table name: HISO87_Interface_OLTP

Version: 9

Phys. file: hi87od

HISO87_PROC_TXN

Table name: HISO87_Proc_Txn

Version: 1

Phys. file: hi8ptd

HISO87_PROC_TXN_OLTP

Table name: HISO87_Proc_Txn_OLTP

Version: 1

Phys. file: hi8pto

HISO93_INTERFACE

Table name: HISO93_Interface

Version: 2

Phys. file: hi93d

HISO93_INTERFACE_OLTP

Table name: HISO93_Interface_OLTP

Version: 2

Phys. file: hi93od

HOLIDAY

Table name: Holiday

Version: 1

Phys. file: hldyd

HOLIDAY_OLTP

Table name: Holiday_OLTP

Version: 1

Phys. file: hldyod

HOST_PKEY_PRI

Table name: Host_Public_Key_Security_Primary

Version: 1

Phys. file: hspkpd

HOST_PKEY_SCND

Table name: Host_Public_Key_Security_Second

Version: 1

Phys. file: hspksd

HOST_PUBLIC_KEY

Table name: Host_Public_Key_Security

Version: 1

Phys. file: hspkd

HPDH_CONFIG

Table name: HPDH_Configuration

Version: 1

Phys. file: hpdhd

HPDH_CONFIG_OLTP

Table name: HPDH_Configuration_OLTP

Version: 1

Phys. file: hpdhod

HPDH_NAC_TERM

Table name: HPDH_NAC_Term

Version: 1
Phys. file: hnacd

HPDH_NAC_TERM_OLTP

Table name: HPDH_NAC_Term_OLTP
Version: 1
Phys. file: hnacod

HPDH_NMS_TERM

Table name: HPDH_NMS_Term
Version: 1
Phys. file: hnmsd

HPDH_NMS_TERM_OLTP

Table name: HPDH_NMS_Term_OLTP
Version: 1
Phys. file: hnmsod

HPKDRPT

Table name: Stream132
Version: 1
Phys. file: hpkdrpt

HPRPRFL

Table name: HPRPRFL
Version: 2
Phys. file: hprpfd

HSMCNFG

Table name: HSMCNFG
Version: 1
Phys. file: hsmcnf

IBM_DES

Table name: IBM_DES
Version: 1
Phys. file: idesd

IBM_DES_OLTP

Table name: IBM_DES_OLTP
Version: 2
Phys. file: idesod

ICHG_PREFIX

Table name: Interchange_Prefix
Version: 3
Phys. file: ipfxd

ICHG_SECURITY

Table name: Interchange_Security

Version: 5

Phys. file: isecd

ICHG_SEC_FUTURE

Table name: Interchange_Security_Future

Version: 1

Phys. file: isecfd

IDENTIKEY

Table name: Identikey

Version: 1

Phys. file: idntd

IDENTIKEY_OLTP

Table name: Identikey_OLTP

Version: 1

Phys. file: idntod

IDF

Table name: IDF

Version: 1

Phys. file: idf

IFXDATA

Table name: IFXDATA

Version: 3

Phys. file: ifxdtd

IFX_HOST_ACT_CDE

Table name: IFX_Host_Action_Code_Int_Ext

Version: 1

Phys. file: ifxacd

IFX_HOST_ACT_CDE_OLTP

Table name: IFX_Host_Action_Cod_Int_Ext_OLTP

Version: 1

Phys. file: ifxaod

IFX_HOST_INTF

Table name: IFX_Host_Interface

Version: 1

Phys. file: ifxhid

IFX_HOST_INTF_OLTP

Table name: IFX_Host_Interface_OLTP

Version: 1
Phys. file: ifxhod

IM_STAT_EXT_INT

Table name: Instrm_Status_Extrn_to_Intrn
Version: 1
Phys. file: iseid

IM_STAT_INT_EXT

Table name: Instrm_Status_Intrn_to_Extrn
Version: 1
Phys. file: isied

IM_TYP_EXT_INT

Table name: Instrm_Typ_Extrn_to_Intrn
Version: 1
Phys. file: iteid

IM_TYP_EXT_INT_OLTP

Table name: Instrm_Typ_Extrn_to_Intrn_OLTP
Version: 1
Phys. file: iteiod

IM_TYP_ICHG_RLN

Table name: Instrum_Typ_Interchange_Rel
Version: 2
Phys. file: itird

IM_TYP_INT_EXT

Table name: Instrm_Typ_Intrn_to_Extrn
Version: 1
Phys. file: itied

IM_TYP_INT_EXT_OLTP

Table name: Instrm_Typ_Intrn_to_Extrn_OLTP
Version: 1
Phys. file: itieod

INBOUND_STATION_OLTP

Table name: Inbound_Station_OLTP
Version: 1
Phys. file: istaod

IND_SORT_CDE_DIR

Table name: Ind_Sort_Code_Directory
Version: 1
Phys. file: iscd

IND_SORT_CDE_INP

Table name: Ind_Sort_Code_Directory_Input

Version: 1

Phys. file: iscdid

IND_SORT_CODE_BIC_OLTP

Table name: Ind_Sort_Code_Bic_OLTP

Version: 1

Phys. file: isbiod

IND_SORT_CODE_DIRECTORY_OLTP

Table name: Ind_Sort_Code_Directory_OLTP

Version: 1

Phys. file: iscdod

INSTITUTION

Table name: Institution

Version: 6

Phys. file: instd

INSTITUTION_ID_OLTP

Table name: Institution_ID_OLTP

Version: 1

Phys. file: inidod

INSTITUTION_OLTP

Table name: Institution_OLTP

Version: 5

Phys. file: instod

INSTRUMENT_TYPE

Table name: INSTRUMENT_TYPE

Version: 1

Phys. file: itypd

INSTRUM_TYP_INTERCHANGE_REL_OLTP

Table name: Instrum_Typ_Interchange_Rel_OLTP

Version: 2

Phys. file: itirod

INTERAC_ADMIN

Table name: Interac_Admin

Version: 1

Phys. file: intramd

INTERAC_ATM_IIN

Table name: Interac_ATM_IIN

Version: 1

Phys. file: inraid

INTERAC_ATM_IIN_OLTP

Table name: Interac_ATM_IIN_OLTP

Version: 1

Phys. file: intraio

INTERAC_BASE

Table name: Interac_Base

Version: 1

Phys. file: intrbad

INTERAC_BASE_OLTP

Table name: Interac_Base_OLTP

Version: 1

Phys. file: intrbao

INTERAC_EP

Table name: Interac_Entry_Point

Version: 1

Phys. file: EPCF

INTERAC_INTF

Table name: Interac_Interface

Version: 1

Phys. file: intrifd

INTERAC_INTF_OLTP

Table name: Interac_Interface_OLTP

Version: 1

Phys. file: intrifo

INTERAC_POS_IIN

Table name: Interac_POS_IIN

Version: 1

Phys. file: intrpid

INTERAC_POS_IIN_OLTP

Table name: Interac_POS_IIN_OLTP

Version: 1

Phys. file: intrpio

INTERCHANGE_PREFIX_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipfxod

INTERCHANGE_SECURITY_OLTP

Table name: Interchange_Security_OLTP

Version: 5

Phys. file: isecod

INTERFACE

Table name: Interface

Version: 5

Phys. file: intfd

INTERFACE_ACQUIRER_OLTP

Table name: Interface_Acquirer_OLTP

Version: 3

Phys. file: ifacod

INTERFACE_FPS

Table name: Interface_FPS

Version: 2

Phys. file: fpsid

INTERFACE_FPS_OLTP

Table name: Interface_FPS_OLTP

Version: 2

Phys. file: fpsiod

INTERFACE_ISSUER_OLTP

Table name: Interface_Issuer_OLTP

Version: 2

Phys. file: ifisod

INTERFACE_MGR

Table name: Interface_Manager

Version: 8

Phys. file: ifmgrd

INTERFACE_OLTP

Table name: Interface_OLTP

Version: 4

Phys. file: intfod

INTERFACE_SAF

Table name: Interface_SAF

Version: 3

Phys. file: ifsafd

INTERFACE_SAF_OLTP

Table name: Interface_SAF_OLTP

Version: 1
Phys. file: isafod

INTERFACE_STA

Table name: Interface_Station
Version: 2
Phys. file: ifstad

INTERFACE_TERM

Table name: Interface_Terminal
Version: 2
Phys. file: iftrmd

INTERFACE_TERMINAL_OLTP

Table name: Interface_Terminal_OLTP
Version: 2
Phys. file: iftmod

INTERFACE_WPS

Table name: Interface_WPS
Version: 2
Phys. file: fpswd

INTERFACE_WPS_OLTP

Table name: Interface_WPS_OLTP
Version: 2
Phys. file: fpswod

IPF_INPUT1

Table name: Stream
Version: 1
Phys. file: ipin1

IPF_INPUT_ACCEL

Table name: Stream
Version: 1
Phys. file: ipaci

IPF_INPUT_AFFN

Table name: Stream
Version: 1
Phys. file: ipafi

IPF_INPUT_BEPS

Table name: Stream
Version: 1
Phys. file: ipbei

IPF_INPUT_CU24

Table name: Stream

Version: 1

Phys. file: ipcui

IPF_INPUT_MDS

Table name: Stream

Version: 1

Phys. file: ipmdi

IPF_INPUT_NYCE

Table name: Stream

Version: 1

Phys. file: ipnyi

IPF_INPUT_PULSE

Table name: Stream

Version: 1

Phys. file: ippui

IPF_INPUT_STAR

Table name: Stream

Version: 1

Phys. file: ipsti

IPF_INPUT_STAR_NE

Table name: Stream

Version: 1

Phys. file: ipsni

IPF_INPUT_VDPS

Table name: Stream

Version: 1

Phys. file: ipvdi

IPF_REPORT1

Table name: Stream132

Version: 1

Phys. file: iprp1

IPF_REPORT_ACCEL

Table name: Stream132

Version: 1

Phys. file: ipacr

IPF_REPORT_AFFN

Table name: Stream132

Version: 1
Phys. file: ipafr

IPF_REPORT_BEPS

Table name: Stream132
Version: 1
Phys. file: ipber

IPF_REPORT_CU24

Table name: Stream132
Version: 1
Phys. file: ipcur

IPF_REPORT_MDS

Table name: Stream132
Version: 1
Phys. file: ipmdr

IPF_REPORT_NYCE

Table name: Stream132
Version: 1
Phys. file: ipnyr

IPF_REPORT_PULSE

Table name: Stream132
Version: 1
Phys. file: ippur

IPF_REPORT_STAR

Table name: Stream132
Version: 1
Phys. file: ipstr

IPF_REPORT_STAR_NE

Table name: Stream132
Version: 1
Phys. file: ipsnr

IPF_REPORT_VDPS

Table name: Stream132
Version: 1
Phys. file: ipvdr

IPRFX_ACCEL

Table name: Interchange_Prefix
Version: 3
Phys. file: ipacd

IPRFX_ACCEL_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipacod

IPRFX_AFFN

Table name: Interchange_Prefix

Version: 3

Phys. file: ipafd

IPRFX_AFFN_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipafod

IPRFX_BEPS

Table name: Interchange_Prefix

Version: 3

Phys. file: ipbepsd

IPRFX_BEPS_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipbepso

IPRFX_CU24

Table name: Interchange_Prefix

Version: 3

Phys. file: ipcud

IPRFX_CU24_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipcuod

IPRFX_ISO93

Table name: Interchange_Prefix

Version: 3

Phys. file: ipf93d

IPRFX_ISO93_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ip93od

IPRFX_JEAN

Table name: Interchange_Prefix

Version: 3
Phys. file: ipjed

IPRFX_JEAN_OLTP

Table name: Interchange_Prefix_OLTP
Version: 3
Phys. file: ipjeod

IPRFX_LINK

Table name: Interchange_Prefix
Version: 3
Phys. file: iplis5d

IPRFX_LINK_OLTP

Table name: Interchange_Prefix_OLTP
Version: 3
Phys. file: iplis5o

IPRFX_MDS

Table name: Interchange_Prefix
Version: 3
Phys. file: ipfxmd

IPRFX_MDS_OLTP

Table name: Interchange_Prefix_OLTP
Version: 3
Phys. file: ipfmod

IPRFX_NYCE

Table name: Interchange_Prefix
Version: 3
Phys. file: ipnyd

IPRFX_NYCE_OLTP

Table name: Interchange_Prefix_OLTP
Version: 3
Phys. file: ipnyod

IPRFX_PULSE

Table name: Interchange_Prefix
Version: 3
Phys. file: ippud

IPRFX_PULSE_OLTP

Table name: Interchange_Prefix_OLTP
Version: 3
Phys. file: ippuod

IPRFX_STAR

Table name: Interchange_Prefix

Version: 3

Phys. file: ipstd

IPRFX_STAR_NE

Table name: Interchange_Prefix

Version: 3

Phys. file: ipsnd

IPRFX_STAR_NE_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipsnod

IPRFX_STAR_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipstod

IPRFX_VDPS

Table name: Interchange_Prefix

Version: 3

Phys. file: ipvdd

IPRFX_VDPS_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipvdod

IPRFX_VISA

Table name: Interchange_Prefix

Version: 3

Phys. file: ipfxvd

IPRFX_VISA_OLTP

Table name: Interchange_Prefix_OLTP

Version: 3

Phys. file: ipfvod

ISO_FIELD

Table name: ISO_Field

Version: 1

Phys. file: isofd

ISO_FIELD_OLTP

Table name: ISO_Field_OLTP

Version: 1
Phys. file: isofod

ISO_FLD_DEFN

Table name: ISO_FLD_DEFN
Version: 1
Phys. file: fdefnd

ISO_FLD_DEFN_OLTP

Table name: ISO_FLD_DEFN_OLTP
Version: 1
Phys. file: fdefno

ISO_MESSAGE

Table name: ISO_Message
Version: 1
Phys. file: isomd

ISO_MESSAGE_OLTP

Table name: ISO_Message_OLTP
Version: 1
Phys. file: isomod

ISO_PROC_CODE

Table name: ISO_PROC_CODE
Version: 1
Phys. file: pceid

ISO_PROC_CODE_OLTP

Table name: ISO_PROC_CODE_OLTP
Version: 1
Phys. file: pceiod

ISSUER_PROFILE_MAP_OLTP

Table name: Issuer_Profile_Map_OLTP
Version: 1
Phys. file: ipmod

ISSUER_TXN_ALLOWED_OLTP

Table name: Issuer_Txn_Allowed_OLTP
Version: 1
Phys. file: istxod

ISS_PROFILE_MAP

Table name: Issuer_Profile_Map
Version: 1
Phys. file: ipmd

ISS_ROUTE_PRFL

Table name: Issuer_Route_Profile

Version: 1

Phys. file: irtpd

ISS_TXN_ALLOWED

Table name: Issuer_Txn_Allowed

Version: 1

Phys. file: isstxd

ITMRPRFL

Table name: ITMRPRFL

Version: 1

Phys. file: imtrd

JCB_INSTITUTION

Table name: JCB_Institution

Version: 1

Phys. file: jcbind

JCB_INSTITUTION_OLTP

Table name: JCB_Institution_OLTP

Version: 1

Phys. file: jcbino

JCB_INTERFACE

Table name: JCB_Interface

Version: 1

Phys. file: jcifd

JCB_INTERFACE_OLTP

Table name: JCB_Interface_OLTP

Version: 1

Phys. file: jcifod

JLF_BNK1_A40_1

Table name: Journal

Version: 2

Phys. file: a1jr40

JLF_BNK1_A40_2

Table name: Journal

Version: 2

Phys. file: a2jr40

JLF_BNK1_A40_3

Table name: Journal

Version: 2
Phys. file: a3jr40

JLF_BNK1_A40_4

Table name: Journal
Version: 2
Phys. file: a4jr40

JLF_BNK1_A40_5

Table name: Journal
Version: 2
Phys. file: a5jr40

JLF_BNK1_A99_1

Table name: Journal
Version: 2
Phys. file: a1jr99

JLF_BNK1_A99_2

Table name: Journal
Version: 2
Phys. file: a2jr99

JLF_BNK1_A99_3

Table name: Journal
Version: 2
Phys. file: a3jr99

JLF_BNK1_A99_4

Table name: Journal
Version: 2
Phys. file: a4jr99

JLF_BNK1_A99_5

Table name: Journal
Version: 2
Phys. file: a5jr99

JLF_BNK1_P40_1

Table name: Journal
Version: 2
Phys. file: p1jr40

JLF_BNK1_P40_2

Table name: Journal
Version: 2
Phys. file: p2jr40

List of Assigns

JLF_BNK1_P40_3

Table name: Journal

Version: 2

Phys. file: p3jr40

JLF_BNK1_P40_4

Table name: Journal

Version: 2

Phys. file: p4jr40

JLF_BNK1_P40_5

Table name: Journal

Version: 2

Phys. file: p5jr40

JLF_BNK1_P99_1

Table name: Journal

Version: 2

Phys. file: p1jr99

JLF_BNK1_P99_2

Table name: Journal

Version: 2

Phys. file: p2jr99

JLF_BNK1_P99_3

Table name: Journal

Version: 2

Phys. file: p3jr99

JLF_BNK1_P99_4

Table name: Journal

Version: 2

Phys. file: p4jr99

JLF_BNK1_P99_5

Table name: Journal

Version: 2

Phys. file: p5jr99

JOURNAL_CONTINUATION_1

Table name: Journal_Continuation

Version: 2

Phys. file: jrnlc1

JOURNAL_CONTINUATION_2

Table name: Journal_Continuation

Version: 2
Phys. file: jrnlc2

JOURNAL_CONTINUATION_3

Table name: Journal_Continuation
Version: 2
Phys. file: jrnlc3

JOURNAL_CONTINUATION_4

Table name: Journal_Continuation
Version: 2
Phys. file: jrnlc4

JOURNAL_DATA_SUPPRESSION_OLTP

Table name: Journal_Data_Suppression_OLTP
Version: 1
Phys. file: jdtsod

JOURNAL_PRFL_GROUP_ASSIGN_OLTP

Table name: Journal_Prfl_Group_Assign_OLTP
Version: 2
Phys. file: jpgaod

JOURNAL_PROFILE_GROUP_OLTP

Table name: Journal_Profile_Group_OLTP
Version: 1
Phys. file: jpgod

JOURNAL_QUERY_POSITION_INFO

Table name: Journal_Query_Position_Info
Version: 2
Phys. file: jqpid

JOURNAL_TEMPLATE

Table name: Journal
Version: 2
Phys. file: tjrn1

JQRY_ASGN_PTLFX_OUT1

Table name: PMX
Version: 1
Phys. file: px1

JQRY_ASGN_PTLFX_OUT2

Table name: PMX
Version: 1
Phys. file: px2

JQRY_ASGN_PTLFX_OUT3

Table name: PMX

Version: 1

Phys. file: px3

JQRY_ASGN_PTLFX_RPT

Table name: Stream132

Version: 1

Phys. file: rptptlfx

JQRY_ASGN_SWITLFX_1

Table name: SMX

Version: 1

Phys. file: sx1

JQRY_ASGN_SWITLFX_2

Table name: SMX

Version: 1

Phys. file: sx2

JQRY_ASGN_SWITLFX_3

Table name: SMX

Version: 1

Phys. file: sx3

JQRY_ASGN_SWITLFX_OUT1

Table name: SMX

Version: 1

Phys. file: JQRY_ASGN_SWITLFX_1

JQRY_ASGN_SWITLFX_OUT2

Table name: SMX

Version: 1

Phys. file: JQRY_ASGN_SWITLFX_2

JQRY_ASGN_SWITLFX_OUT3

Table name: SMX

Version: 1

Phys. file: JQRY_ASGN_SWITLFX_3

JQRY_ASGN_SWITLFX_RPT

Table name: Stream132

Version: 1

Phys. file: rptswix

JQRY_ASGN_TLFX_OUT1

Table name: TMX

Version: 1
Phys. file: tx1

JQRY_ASGN_TLFX_OUT2

Table name: TMX
Version: 1
Phys. file: tx2

JQRY_ASGN_TLFX_OUT3

Table name: TMX
Version: 1
Phys. file: tx3

JQRY_ASGN_TLFX_RPT

Table name: Stream132
Version: 1
Phys. file: rpttlfx

JQRY_RECON_EXTR_OUT1

Table name: Stream132
Version: 1
Phys. file: reconx1

JQRY_RECON_EXTR_OUT2

Table name: Stream132
Version: 1
Phys. file: reconx2

JQRY_RECON_EXTR_OUT3

Table name: Stream132
Version: 1
Phys. file: reconx3

JQRY_RECON_EXTR_RPT

Table name: Stream132
Version: 1
Phys. file: rptreconx

JRNL_DATA_SUPPRS

Table name: Journal_Data_Suppression
Version: 1
Phys. file: jdtsd

JRNL_PF_GRP

Table name: Journal_Profile_Group
Version: 1
Phys. file: jpgd

JRNL_PF_GRP_ASGN

Table name: Journal_Profile_Group_Assign

Version: 2

Phys. file: jpgad

JRNL_QRY_CNFG

Table name: Journal_Query_Config

Version: 4

Phys. file: jqcd

JRNL_QRY_CNF_OUT

Table name: Journal_Query_Config_Output

Version: 1

Phys. file: jqcod

JRNL_QRY_OUT_ASN

Table name: Journal_Query_Output_Assign

Version: 1

Phys. file: jqoad

JRNL_QRY_OUT_MAP

Table name: Journal_Query_Output_Map

Version: 1

Phys. file: jqomd

JRNL_TPLT

Table name: Journal

Version: 2

Phys. file: jrnld

KEY_CONVERSION_REPORT

Table name: Stream132

Version: 1

Phys. file: keyconv

KEY_MAP

Table name: Key_Map

Version: 1

Phys. file: kymapd

KEY_TOKEN

Table name: Key_Token

Version: 1

Phys. file: ktd

LCONF

Table name: LCONF

Version: 1
Phys. file: lconf

LIMITS

Table name: Limits
Version: 1
Phys. file: lmttd

LIMITS_OLTP

Table name: Limits_OLTP
Version: 1
Phys. file: lmtod

LINKED_CURRENCY

Table name: Linked_Currency
Version: 1
Phys. file: lnkcd

LINKED_CURRENCY_OLTP

Table name: Linked_Currency_OLTP
Version: 1
Phys. file: lnkcod

LIS5_INTERFACE

Table name: LIS5_Interface
Version: 1
Phys. file: li5ifd

LIS5_INTERFACE_OLTP

Table name: LIS5_Interface_OLTP
Version: 1
Phys. file: li5iod

LISTENER

Table name: LISTENER
Version: 1
Phys. file: lstnd

LTMRPFL

Table name: LTMRPFL
Version: 1
Phys. file: ltmrd

MACPFL

Table name: MACPFL
Version: 1
Phys. file: macd

MDS_BIN_FILE

Table name: MDS_BIN_File_Updt

Version: 1

Phys. file: mdsbin

MDS_BRAND_INSTRM_REL

Table name: MDS_Brand_Rel

Version: 1

Phys. file: mdsbid

MDS_BRAND_INSTRM_REL_OLTP

Table name: MDS_Brand_Rel_OLTP

Version: 1

Phys. file: mdsbod

MDS_INSTITUTION

Table name: MDS_Institution

Version: 1

Phys. file: mdsiid

MDS_INSTITUTION_OLTP

Table name: MDS_Institution_OLTP

Version: 1

Phys. file: mdsiio

MDS_INTERFACE

Table name: MDS_Interface

Version: 1

Phys. file: mdsifd

MDS_INTERFACE_OLTP

Table name: MDS_Interface_OLTP

Version: 1

Phys. file: mdsiod

MERCHANT

Table name: Merchant

Version: 5

Phys. file: mrchd

MERCHANT_DELIVERY_CHAN_PRFL_OLTP

Table name: Merchant_Delivery_Chan_Prfl_OLTP

Version: 3

Phys. file: mdcpod

MERCHANT_MASTER

Table name: Merchant_Master_File

Version: 1

Phys. file: mmfd

MERCHANT_MASTER_OLTP

Table name: Merchant_Master_File_OLTP

Version: 1

Phys. file: mmfd

MERCHANT_OLTP

Table name: Merchant_OLTP

Version: 3

Phys. file: mrchod

MERCH_INSTR_TYPE_RELATION_OLTP

Table name: Merch_Instr_Type_Relation_OLTP

Version: 2

Phys. file: mitrod

MRCH_CHAN_PRFL

Table name: Merchant_Channel_Profile

Version: 3

Phys. file: mcpd

MRCH_CHAN_PRFL_OLTP

Table name: Merchant_Channel_Profile_OLTP

Version: 3

Phys. file: mcpod

MRCH_DLVR_CHAN

Table name: Merchant_Delivery_Channel

Version: 6

Phys. file: mrchcd

MRCH_DLVR_CHAN_P

Table name: Merchant_Delivery_Channel_Profil

Version: 3

Phys. file: mdcpd

MRCH_IM_TYP_RLN

Table name: Merch_Instr_Typ_Relation

Version: 2

Phys. file: mitrd

MSGCNTX

Table name: MSGCNTX

Version: 1

Phys. file: msgctx

MTRCRC

Table name: Stream

Version: 1

Phys. file: mtrcrc

NCR_PIN_VERIFICATION_OLTP

Table name: NCR_PIN_Verification_OLTP

Version: 1

Phys. file: ncrod

NCR_PIN_VRFY

Table name: NCR_PIN_Verification

Version: 1

Phys. file: ncrd

NET_BRND_IM_RELN

Table name: Netwk_Brand_Instrm_ReIn

Version: 1

Phys. file: ipfnd

NET_BRND_IM_RELN_OLTP

Table name: Netwk_Brand_Instrm_ReIn_OLTP

Version: 1

Phys. file: ipfnod

NYCE_BIN_FILE

Table name: NYCE_BIN_File_Updt

Version: 1

Phys. file: nybin

NYCE_INSTITUTION

Table name: NYCE_Institution

Version: 1

Phys. file: nyind

NYCE_INSTITUTION_OLTP

Table name: NYCE_Institution_OLTP

Version: 1

Phys. file: nyinod

NYCE_INTERFACE

Table name: NYCE_Interface

Version: 1

Phys. file: nyifd

NYCE_INTERFACE_OLTP

Table name: NYCE_Interface_OLTP

Version: 1

Phys. file: nyifod

OLTP_WARMBOOT

Table name: OLTP_Warmboot

Version: 1

Phys. file: ooltpd

OPERID

Table name: OPERID

Version: 1

Phys. file: OIF

OPTRCPT

Table name: OPTRCPT

Version: 1

Phys. file: OR

OUTBOUND_STATION_OLTP

Table name: Outbound_Station_OLTP

Version: 1

Phys. file: ostaod

PASSWORD

Table name: Password

Version: 2

Phys. file: upswd

PBAL_01A

Table name: Positive_Balance

Version: 2

Phys. file: pbl01a

PBAL_01B

Table name: Positive_Balance

Version: 2

Phys. file: pbl01b

PBAL_IMPACTS

Table name: PBAL_Impacts

Version: 3

Phys. file: pblimd

PERMDETL

Table name: PermDetl

Version: 1

Phys. file: uprmdt

PERMGRP

Table name: PermGrp

Version: 1

Phys. file: uprmgr

PERMS

Table name: Perms

Version: 1

Phys. file: uperms

PERMTYPE

Table name: PermType

Version: 1

Phys. file: uprmty

PERUSAL_SCRIPT

Table name: Perusal_Script

Version: 1

Phys. file: perscd

PERUSAL_SCRIPT_OLTP

Table name: Perusal_Script_OLTP

Version: 1

Phys. file: persod

PMGPXPRM

Table name: PmGpXPrm

Version: 1

Phys. file: upmgpx

POSITIVE_BALANCE

Table name: file_part_catalog

Version: 1

Phys. file: pblcat

POS_TC_PROC_CODE

Table name: POS_TC_Proc_Code

Version: 1

Phys. file: pstpd

POS_TRAN_CODE_PROC_CODE_OLTP

Table name: POS_Tran_Code_Proc_Code_OLTP

Version: 1

Phys. file: pstpod

PREFIX

Table name: Prefix

Version: 8
Phys. file: prfxd

PREFIX_BLOCK

Table name: Prefix_Block
Version: 1
Phys. file: pfxbd

PREFIX_BLOCK_OLTP

Table name: Prefix_Block_OLTP
Version: 1
Phys. file: pfxbod

PREFIX_OLTP

Table name: Prefix_OLTP
Version: 8
Phys. file: prfxod

PRESTO_INTERFACE

Table name: Presto_Interface
Version: 1
Phys. file: prifd

PRESTO_INTERFACE_OLTP

Table name: Presto_Interface_OLTP
Version: 1
Phys. file: prifod

PRE_AUTH_HOLD

Table name: Pre_Auth_Hold
Version: 3
Phys. file: preaud

PRICE_INTERFACE

Table name: PRICE_Interface
Version: 1
Phys. file: prceifd

PRICE_INTERFACE_OLTP

Table name: PRICE_Interface_OLTP
Version: 1
Phys. file: prceifo

PRM_INTERFACE

Table name: PRM_Interface
Version: 3
Phys. file: prmid

PRM_INTERFACE_OLTP

Table name: PRM_Interface_OLTP

Version: 3

Phys. file: prmioid

PROCESS

Table name: PROCESS

Version: 2

Phys. file: procd

PROC_CODE_ATM_TC

Table name: Proc_Code_ATM_TC

Version: 1

Phys. file: atptd

PROC_CODE_ATM_TRAN_CODE_OLTP

Table name: Proc_Code_ATM_Trans_Code_OLTP

Version: 1

Phys. file: atptod

PROC_CODE_ISO

Table name: PROC_CODE_ISO

Version: 1

Phys. file: pcied

PROC_CODE_ISO_OLTP

Table name: PROC_CODE_ISO_OLTP

Version: 1

Phys. file: pcieod

PROC_CODE_POS_TC

Table name: Proc_Code_POS_TC

Version: 1

Phys. file: psptd

PROC_CODE_POS_TRAN_CODE_OLTP

Table name: Proc_Code_POS_Trans_Code_OLTP

Version: 1

Phys. file: psptod

PSWDGRP

Table name: PswdGrp

Version: 1

Phys. file: upswdg

PSWDHIST

Table name: PswdHist

Version: 3

Phys. file: upswdh

PUBLIC_KEY_CONV_RPT

Table name: Stream132

Version: 1

Phys. file: pubkey

PULSE_INSTITUTION

Table name: Pulse_Institution

Version: 1

Phys. file: pinstd

PULSE_INSTITUTION_OLTP

Table name: Pulse_Institution_OLTP

Version: 1

Phys. file: pinsod

PULSE_INTERFACE

Table name: Pulse_Interface

Version: 2

Phys. file: pulifd

PULSE_INTERFACE_OLTP

Table name: Pulse_Interface_OLTP

Version: 2

Phys. file: puliod

PULSE_SWITCH_DATE

Table name: Pulse_Switch_Date

Version: 1

Phys. file: pswid

RCPTRQRD

Table name: RCPTRQRD

Version: 1

Phys. file: rcptrd

REAL_TIME_FEED_CONFIG

Table name: Real_Time_Feed_Config

Version: 2

Phys. file: rtfcd

REAL_TIME_FEED_CONFIG_OLTP

Table name: Real_Time_Feed_Config_OLTP

Version: 2

Phys. file: rtfcod

RECEIPT

Table name: RECEIPT

Version: 1

Phys. file: rcptd

REFERRAL

Table name: Referral

Version: 1

Phys. file: rfrld

REFERRAL_OLTP

Table name: Referral_OLTP

Version: 1

Phys. file: rfrlod

REFRESH_INPUT1

Table name: Stream

Version: 1

Phys. file: refr1

REFRESH_INPUT2

Table name: Stream

Version: 1

Phys. file: refr2

REFRESH_REPORT

Table name: Stream132

Version: 1

Phys. file: prfrpt

ROLES

Table name: Roles

Version: 2

Phys. file: uroles

ROLXPMGP

Table name: RolXPmGp

Version: 1

Phys. file: urolxp

ROUTE

Table name: Route

Version: 2

Phys. file: routed

ROUTE_OLTP

Table name: Route_OLTP

Version: 2
Phys. file: routod

RQUID

Table name: RQUID
Version: 2
Phys. file: rquid

RSN_ONL_CDE_DSC

Table name: Reason_Online_Code_Description
Version: 1
Phys. file: rocdd

RVSLSAF

Table name: RVSLSAF
Version: 1
Phys. file: RS

SAF_ABI

Table name: Store_and_Forward
Version: 2
Phys. file: sfabid

SAF_ACCEL

Table name: Store_and_Forward
Version: 2
Phys. file: sfacd

SAF_AEGN

Table name: Store_and_Forward
Version: 2
Phys. file: sfaed

SAF_AMEX_CAPN

Table name: Store_and_Forward
Version: 2
Phys. file: sfacpnd

SAF_AS2805

Table name: Store_and_Forward
Version: 2
Phys. file: sfas28d

SAF_B53

Table name: Store_and_Forward
Version: 2
Phys. file: sfb53d

SAF_BANKNET

Table name: Store_and_Forward

Version: 2

Phys. file: bntsfid

SAF_BIC

Table name: Store_and_Forward

Version: 2

Phys. file: sfbid

SAF_BNFT

Table name: Store_and_Forward

Version: 2

Phys. file: sfbnftd

SAF_CIRCUIT

Table name: Store_and_Forward

Version: 2

Phys. file: sfcrcd

SAF_CONTINGENCY

Table name: Store_and_Forward

Version: 2

Phys. file: sfctgyd

SAF_CSC

Table name: Store_and_Forward

Version: 2

Phys. file: sfcscd

SAF_CUP

Table name: Store_and_Forward

Version: 2

Phys. file: sfcupd

SAF_DIAS

Table name: Store_and_Forward

Version: 2

Phys. file: sfdiasd

SAF_DISCOVER

Table name: Store_and_Forward

Version: 2

Phys. file: sfdscvd

SAF_EFUNDS

Table name: Store_and_Forward

Version: 2
Phys. file: sfefnd

SAF_EPSNET

Table name: Store_and_Forward
Version: 2
Phys. file: sfepnd

SAF_EQUENS

Table name: Store_and_Forward
Version: 2
Phys. file: sfeqnsd

SAF_ERSB

Table name: Store_and_Forward
Version: 2
Phys. file: sfersbd

SAF_FIFTH_THIRD

Table name: Store_and_Forward
Version: 2
Phys. file: sfttd

SAF_FIS

Table name: Store_and_Forward
Version: 2
Phys. file: fissfd

SAF_FPSI

Table name: Store_and_Forward
Version: 2
Phys. file: sfpid

SAF_FPSW

Table name: Store_and_Forward
Version: 2
Phys. file: sfpwd

SAF_GICC

Table name: Store_and_Forward
Version: 2
Phys. file: sfgiccd

SAF_GISO

Table name: Store_and_Forward
Version: 2
Phys. file: sfgisod

SAF_HISO

Table name: Store_and_Forward

Version: 2

Phys. file: sfhisd

SAF_IFX_HOST_INTF

Table name: Store_and_Forward

Version: 2

Phys. file: sfifxhd

SAF_INTERAC

Table name: Store_and_Forward

Version: 2

Phys. file: sfintrd

SAF_INTF_EXTRA1

Table name: Store_and_Forward

Version: 2

Phys. file: sfex1d

SAF_INTF_EXTRA2

Table name: Store_and_Forward

Version: 2

Phys. file: sfex2d

SAF_INTF_EXTRA3

Table name: Store_and_Forward

Version: 2

Phys. file: sfex3d

SAF_INTF_EXTRA4

Table name: Store_and_Forward

Version: 2

Phys. file: sfex4d

SAF_ISO93

Table name: Store_and_Forward

Version: 2

Phys. file: iso93sfd

SAF_JCB

Table name: Store_and_Forward

Version: 2

Phys. file: sfjcd

SAF_LIS5

Table name: Store_and_Forward

Version: 2
Phys. file: sflis5d

SAF_MANAGER_OLTP

Table name: SAF_Manager_OLTP
Version: 3
Phys. file: safmod

SAF_MDS

Table name: Store_and_Forward
Version: 2
Phys. file: mdssfd

SAF_NYCE

Table name: Store_and_Forward
Version: 2
Phys. file: sfnyd

SAF_PRESTO

Table name: Store_and_Forward
Version: 2
Phys. file: sfprd

SAF_PRICE

Table name: Store_and_Forward
Version: 2
Phys. file: sfprcd

SAF_PRM_CDNRT

Table name: Store_and_Forward
Version: 2
Phys. file: sfcndd

SAF_PRM_CDRT

Table name: Store_and_Forward
Version: 2
Phys. file: sfcdrd

SAF_PRM_ENTNRT

Table name: Store_and_Forward
Version: 2
Phys. file: sfentnd

SAF_PRM_ENTRT

Table name: Store_and_Forward
Version: 2
Phys. file: sfentrd

SAF_PRM_MIFNRT

Table name: Store_and_Forward

Version: 2

Phys. file: sfmfrnd

SAF_PRM_MIFRT

Table name: Store_and_Forward

Version: 2

Phys. file: sfmfrd

SAF_PULSE

Table name: Store_and_Forward

Version: 2

Phys. file: sfpulsd

SAF_RTFATM

Table name: Store_and_Forward

Version: 2

Phys. file: sfrtad

SAF_RTFPOS

Table name: Store_and_Forward

Version: 2

Phys. file: sfrtpd

SAF_SPAN2

Table name: Store_and_Forward

Version: 2

Phys. file: sfspd

SAF_STAR

Table name: Store_and_Forward

Version: 2

Phys. file: strsfid

SAF_SVS

Table name: Store_and_Forward

Version: 2

Phys. file: svssfd

SAF_UAE

Table name: Store_and_Forward

Version: 2

Phys. file: sfuaed

SAF_VISA

Table name: Store_and_Forward

Version: 2
Phys. file: vissfd

SAF_VISA_DPS

Table name: Store_and_Forward
Version: 2
Phys. file: sfvdps

SCRIPT

Table name: Script
Version: 2
Phys. file: scrptd

SCRIPT_CNFG

Table name: Script_Configuration
Version: 2
Phys. file: scptcd

SCRIPT_OLTP

Table name: Script_OLTP
Version: 1
Phys. file: scptod

SCRIPT_SOURCE

Table name: Script_Source
Version: 2
Phys. file: scsrcl

SECGRP

Table name: SecGrp
Version: 1
Phys. file: usecgp

SEC_DEV_CONFIG

Table name: Security_Device_Config
Version: 2
Phys. file: seccl

SFRF_INPUT1

Table name: Stream_Binary
Version: 1
Phys. file: sfrp1

SFRF_REPORT1

Table name: Stream132
Version: 1
Phys. file: sfrpt1

SIADMF

Table name: SIS_ASYNC_DEST_MAP

Version: 2

Phys. file: admf

SPAN2_INTERFACE

Table name: SPAN2_Interface

Version: 3

Phys. file: spifd

SPAN2_INTERFACE_OLTP

Table name: SPAN2_Interface_OLTP

Version: 2

Phys. file: spifod

SPAN2_INTERFACE_TERMINAL

Table name: SPAN2_Interface_Terminal

Version: 1

Phys. file: sptmd

SPAN2_INTERFACE_TERMINAL_OLTP

Table name: SPAN2_Interface_Terminal_OLTP

Version: 1

Phys. file: sptmod

SPDH_ACT_CDE_DESCR_OLTP

Table name: SPDH_act_cde_descr_OLTP

Version: 1

Phys. file: spiaod

SPDH_ACT_CDE_DSC

Table name: SPDH_act_cde_descr

Version: 1

Phys. file: spiad

SPDH_CONFIG

Table name: SPDH_Configuration

Version: 3

Phys. file: spicd

SPDH_CONFIG_OLTP

Table name: SPDH_Configuration_OLTP

Version: 3

Phys. file: spicod

SPDH_ISO_RESP_CDE_OLTP

Table name: SPDH_ISO_Response_Code_OLTP

Version: 1

Phys. file: sprcod

SPDH_ISO_RESP_TXT_OLTP

Table name: SPDH_ISO_Response_Text_OLTP

Version: 1

Phys. file: sprtod

SPDH_ISO_RSP_CDE

Table name: SPDH_ISO_Response_Code

Version: 1

Phys. file: sprcd

SPDH_ISO_RSP_TXT

Table name: SPDH_ISO_Response_Text

Version: 1

Phys. file: sprtd

SPDH_MESSAGE

Table name: SPDH_Message

Version: 2

Phys. file: spimd

SPDH_MESSAGE_OLTP

Table name: SPDH_Message_OLTP

Version: 2

Phys. file: spimod

SPDH_OPT_DATA

Table name: SPDH_opt_resp_data

Version: 1

Phys. file: spiod

SPDH_OPT_RESP_DATA_OLTP

Table name: SPDH_opt_resp_data_OLTP

Version: 1

Phys. file: spiood

SPDH_TXN_CDE_DESCR_OLTP

Table name: SPDH_txn_cde_descr_OLTP

Version: 1

Phys. file: spitod

SPDH_TXN_CDE_DSC

Table name: SPDH_txn_cde_descr

Version: 1

Phys. file: spitd

SRCHFLD

Table name: SrchFld
Version: 1
Phys. file: usrchf

SRCHPRFL

Table name: SRCHPRFL
Version: 1
Phys. file: srchd

SRCHXADT

Table name: SrchXAdt
Version: 1
Phys. file: usrchx

STAR_INSTITUTION

Table name: Star_Institution
Version: 2
Phys. file: sinstd

STAR_INSTITUTION_OLTP

Table name: Star_Institution_OLTP
Version: 2
Phys. file: sinsod

STAR_INTERFACE

Table name: Star_Interface
Version: 5
Phys. file: strifd

STAR_INTERFACE_OLTP

Table name: Star_Interface_OLTP
Version: 5
Phys. file: striod

STAR_NE_BIN_FILE

Table name: Star_NE_BIN_File_Updt
Version: 1
Phys. file: stnbin

STAR_NE_NETWORK_REL

Table name: Star_NE_Network_Rel
Version: 1
Phys. file: stnnid

STAR_NE_NETWORK_REL_OLTP

Table name: Star_NE_Network_Rel_OLTP

Version: 1
Phys. file: stnnod

STMPPRFL

Table name: STMPPRFL
Version: 1
Phys. file: stmpd

STMTDATA

Table name: STMTDATA
Version: 1
Phys. file: stmtd

STOP_PAYMENT

Table name: file_part_catalog
Version: 1
Phys. file: stpcat

STOP_PMNT_01A

Table name: Stop_Payment
Version: 1
Phys. file: stp01a

STOP_PMNT_01B

Table name: Stop_Payment
Version: 1
Phys. file: stp01b

STREAM

Table name: Stream
Version: 1
Phys. file: rptsrc

STRST

Table name: Stream
Version: 1
Phys. file: strst

SURCHARGE

Table name: Surcharge
Version: 2
Phys. file: surchd

SURCHARGE_COUNTRY_CODE

Table name: Surcharge_Country_Code
Version: 1
Phys. file: succd

SURCHARGE_COUNTRY_CODE_OLTP

Table name: Surcharge_Country_Code_OLTP

Version: 1

Phys. file: succod

SURCHARGE_OLTP

Table name: Surcharge_OLTP

Version: 2

Phys. file: surcod

SVS_INTERFACE

Table name: SVS_Interface

Version: 1

Phys. file: svdif

SVS_INTERFACE_OLTP

Table name: SVS_Interface_OLTP

Version: 1

Phys. file: svsiid

SVS_MRCH_NUM

Table name: SVS_Mrch_Num

Version: 1

Phys. file: svsmnd

SVS_MRCH_NUM_OLTP

Table name: SVS_Mrch_Num_OLTP

Version: 1

Phys. file: svsmid

SYSTEM_ALGORITHM_CONFIG_OLTP

Table name: System_Algorithm_Config_OLTP

Version: 1

Phys. file: sacod

SYSTEM_PREFIX

Table name: System_Prefix

Version: 2

Phys. file: sprfxd

SYSTEM_PREFIX_OLTP

Table name: System_Prefix_OLTP

Version: 2

Phys. file: spfxod

SYS_ALGO_CONFIG

Table name: System_Algorithm_Config

Version: 1
Phys. file: sacd

TASKFLDS

Table name: TaskFlds
Version: 1
Phys. file: utskfl

TASKFNCS

Table name: TaskFnCS
Version: 1
Phys. file: utskfn

TASKS

Table name: Tasks
Version: 1
Phys. file: utasks

TBP_DAILY

Table name: TBP_Daily
Version: 2
Phys. file: tbpdd

TBP_REPORT

Table name: Stream132
Version: 1
Phys. file: tbprpt

TERM_LN_FIID_MAP

Table name: TERM_LN_FIID_MAP
Version: 1
Phys. file: tlnfid

TERM_LN_FIID_MAP_OLTP

Table name: TERM_LN_FIID_MAP_OLTP
Version: 1
Phys. file: tlnfod

TICKET

Table name: Ticket
Version: 1
Phys. file: utickt

TOKEN_CONFIG

Table name: Token_Config
Version: 1
Phys. file: tknd

TOKEN_CONFIG_OLTP

Table name: Token_Config_OLTP

Version: 1

Phys. file: tknod

TOKEN_ID_LIST

Table name: Token_Id_List

Version: 2

Phys. file: tknid

TOTALS

Table name: Totals

Version: 1

Phys. file: ttld

TOTALS_CONFIGURATION

Table name: Totals_Configuration

Version: 1

Phys. file: ttlcd

TOTALS_CONFIGURATION_OLTP

Table name: Totals_Configuration_OLTP

Version: 1

Phys. file: ttlcod

TOTALS_ENTRY

Table name: Totals_Entry

Version: 1

Phys. file: ttled

TOTALS_ENTRY2

Table name: Totals_Entry2

Version: 1

Phys. file: ttle2d

TOTALS_MANAGER_CNFG_OLTP

Table name: Totals_Manager_Cnfg_OLTP

Version: 1

Phys. file: ttlmod

TOTALS_TAG_DOCUMENTATION

Table name: Totals_Tag_Documentation

Version: 1

Phys. file: ttld

TRACE

Table name: Trace

Version: 1
Phys. file: trcd

TRACE2

Table name: Trace
Version: 1
Phys. file: trc2d

TRACE_CONFIG

Table name: Trace_Config
Version: 1
Phys. file: trccfd

TRACE_FILTER

Table name: Trace_Filter
Version: 1
Phys. file: trcfd

TRANSPORT_KEY

Table name: Transport_Key
Version: 1
Phys. file: trnsd

TRANSPORT_KEY_OLTP

Table name: Transport_Key_OLTP
Version: 1
Phys. file: trnsod

TRC

Table name: Stream132
Version: 1
Phys. file: trc

UAE_INTERFACE

Table name: UAE_Interface
Version: 1
Phys. file: uaeifd

UICTGY_JAVA_SAF

Table name: Audit_Store_and_Forward
Version: 1
Phys. file: ujsafd

UICTGY_JAVA_SAF_OUTSD

Table name: Audit_Store_and_Forward
Version: 1
Phys. file: ujsfod

UICTGY_SAF

Table name: Audit_Store_and_Forward

Version: 1

Phys. file: usaofd

UICTGY_SAF_CNFG

Table name: Audit_Store_and_Forward_Config

Version: 1

Phys. file: usafcd

UICTGY_SAF_OUTSD

Table name: Audit_Store_and_Forward

Version: 1

Phys. file: usafod

USAGE

Table name: Usage

Version: 2

Phys. file: usgd

USERS

Table name: Users

Version: 3

Phys. file: uusers

USER_PERUSAL_PRFL_RELATION_OLTP

Table name: User_Perusal_Prfl_Relation_OLTP

Version: 1

Phys. file: upprod

USER_PRSL_PF_RLN

Table name: User_Perusal_Prfl_Relation

Version: 1

Phys. file: upprd

USRAULOG

Table name: USRAULOG

Version: 1

Phys. file: ualogd

USRSTAT

Table name: UsrStat

Version: 1

Phys. file: uusrst

USRXFILT

Table name: USRXFILT

Version: 1
Phys. file: uusrxf

USRXROLE

Table name: UsrXRole
Version: 1
Phys. file: uusrxr

VERSIONS

Table name: VERSIONS
Version: 1
Phys. file: versd

VERSION_RPT

Table name: Stream
Version: 1
Phys. file: strmd

VISA_BIN_FILE

Table name: Visa_BIN_File_Updt
Version: 1
Phys. file: visbin

VISA_BRAND_INSTRM_REL

Table name: Visa_Brand_Rel
Version: 1
Phys. file: vsbid

VISA_BRAND_INSTRM_REL_OLTP

Table name: Visa_Brand_Rel_OLTP
Version: 1
Phys. file: vsbiod

VISA_DPS_INSTITUTION

Table name: Visa_DPS_Institution
Version: 1
Phys. file: vdiid

VISA_DPS_INSTITUTION_OLTP

Table name: Visa_DPS_Institution_OLTP
Version: 1
Phys. file: vdiiid

VISA_DPS_INTERFACE

Table name: Visa_DPS_Interface
Version: 2
Phys. file: vdifd

VISA_DPS_INTERFACE_OLTP

Table name: Visa_DPS_Interface_OLTP

Version: 2

Phys. file: vdifod

VISA_INST

Table name: Visa_Institution

Version: 2

Phys. file: vsiid

VISA_INST_OLTP

Table name: Visa_Institution_OLTP

Version: 2

Phys. file: vsiiid

VISA_INTERFACE

Table name: Visa_Interface

Version: 4

Phys. file: visifd

VISA_INTERFACE_OLTP

Table name: Visa_Interface_OLTP

Version: 4

Phys. file: visiod

VISA_IPF_REPORT

Table name: Stream132

Version: 1

Phys. file: visipf

VISA_PVV

Table name: Visa_PVV

Version: 1

Phys. file: vpvvd

VISA_PVV_OLTP

Table name: Visa_PVV_OLTP

Version: 2

Phys. file: vpvvod

WEBAPPOPTS

Table name: WEBAPPOPTS

Version: 1

Phys. file: wboptd

WEBAPPS

Table name: WEBAPPS

Version: 1

Phys. file: webapd

WEBUSROPTS

Table name: WEBUSROPTS

Version: 1

Phys. file: wbusrd

ZKA_KGK

Table name: ZKA_KGK

Version: 1

Phys. file: zkgkd

Data source list

This section provides an alphabetical listing of all data sources.

For each data source, the following information is provided:

- Data source name as the main heading with the latest version number of the data source and the short name being provided in parenthesis
- Info as to whether the data source is audited and supports versioning
- Data source description
- Element (field) name, type, and description (if available)

Note: Key fields are indicated by * after the element name.

ABI_Interface (1.0) (abifd)

ABI Interface Configuration.

[Audited] [Supports versioning]

OLTP: ABI_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
atm_ssb [bt_flag]	Specifies whether to send fields (25, 28, 93, 94, 53) to SSB. Values are (0 - Will not send, 1 - Will send).
hndlr_repeat_msg [bt_flag]	Specifies whether to send repeat advices 1221, 1421 and 1521. Values are (0 - Will not send, 1 - Will send).
abi_setl_dat [bt_flag]	Specifies whether to send the settlement date in field 15 in 1210 and 1430 messages. Values are (0 - Will not send, 1 - Will send).
abi_e100_gc [bt_flag]	Specifies whether to handle the B100 Euro messages (msg type = E100) according to the B100 protocol and the 1100/1420 "Grandi Clienti" according to the ISO Grandi Clienti protocol recognized by Function Code field 24 ("181" or "182" values). Values are (0 – Will not send, 1 – Will send).
pos_send_1220 [bt_flag]	Specifies whether to send 1220 messages. Values are (0 - Will not send, 1 - Will send).
pos_send_moto_1220 [bt_flag]	Specifies whether to send 1220 messages for mail order telephone order transactions. Values are (0 - Will not send, 1 - Will send).
dbi_field_44 [bt_flag]	Specifies whether to send response message text in field 44. Values are (0 - Will not send, 1 - Will send).

Element (type)	Description
abi_cc_rrn [bt_flag]	Specifies whether to use the full sequence number in field 37 retrieval reference number for all credit transactions. Values are (0 - Will not use full, 1 - Will use full).
abi_orig_crncy [bt_flag]	Specifies whether to allow use of original currency. The original currency is stored in bu_tde_amt_b24_orig. The cardholder billing currency is stored in the transaction amount TDE. Values are (0 - Will not allow, 1 - Will allow).
abi_abl_srvc [bt_flag]	Specifies whether to process additional service transactions (first and second byte of the processing code field: "14" , "37" , "46","56" and/or third and fourth byte of the processing code field: "60" ,"61" , "62" , "63" , "64" e "99". Values are (0 – Will not process, 1 – Will process).
pos_fl2_type [bt_flag]	Specifies whether to use floor limit 2. Values are (0 - Will not use, 1 - Will use).
pos_dest_circuit_inst_id [bt_stringf(11)]	Identifies the destination institutuion id in field 93. If it is set to "TOKEN", use the issuer id.
pos_tran_orig_inst_id [bt_stringf(11)]	Identifies the originator institutuion id in field 94.
atm_rcv_inst_id [bt_stringf(11)]	Identifies the receiving institutuion id in field 100.
pos_rcv_inst_id [bt_stringf(11)]	Identifies the receiving institutuion id in field 100.
atm_abi_frwd_inst_id [bt_stringf(11)]	A value assigned by ABI to identify the forwarding institutuion id in field 33.
abi_multi_key [bt_stringf(1)]	Identifies the key choice. Values are (0 – indicates use standard keys for interface, 1 – indicates use institution in field P-33 to locate keys, 2 – indicates use institution in field S-94 to locate keys).
pos_dflt_rtlr [bt_stringf(1)]	Values are (N - use the Retailer code (card acceptor id) from the field 42 of the incoming message, Y - use the default Retailer code)
pos_rcncl_hour [bt_int16s]	Specifies the reconciliation cutover time hour.
pos_rcncl_min [bt_int16s]	Specifies the reconciliation cutover time minute.
pos_restart_1520_tim [bt_int16s]	Specifies the reconciliation restart delay (minutes) before attempting to send a new reconciliation message, when the received response code is 503 -Totals not Available.
abi_bin_prestitempo [bt_stringf(8)]	The interface compares the starting characters of the PAN of the transaction with the characters set in the param (max length 8). If they match and the field 42 field is long 7 bytes the interface add the prefix "010" to the field 42 to set the retailer-id (card acceptor id).

ABI_Key (1.0) (abikd)

ABI Key Configuration.

[Audited] [Supports versioning]

OLTP: ABI_Key_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
abi_mac_key [bt_stringf(8)]	Identifies the key used to generate a MAC using the ABI software encryption module. ABI defines the key as 8 decimal digits.

ACCEL_Interface (1.0) (acifd)

ACCEL Interface Table.

[Audited] [Supports versioning]

OLTP: ACCEL_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
accel_netwk_id [bt_stringf(6)]	Accel Network Identifier.
dest_id_cde [bt_stringf(11)]	A code identifying the destination institution or its agent. This code is used when sending a Network Management request to an interface.

Account_Routing (1.0) (actrtd)

The Account Routing data source provides routing information to supplement the account information entered at a terminal or ATM so that the account can be located.

[Audited] [Supports versioning]

OLTP: Account_Routing_OLTP

Element (type)	Description
acct_typ* [bt_stringf(2)]	The account type for which the routing information applies.
acct_lgth* [bt_int16s]	The length of the account number for which the routing information in this record applies. Valid values: 1 - 28.
rttn* [bt_stringf(11)]	The routing and transit number of the check issuing institution or check-issuer identification number. This value is derived from the check MICR data. Values are right-justified and zero-filled, containing only numeric characters.
fm_ts [ts 1.0]	File Maintenance Timestamp. Timestamp of last update to the data source record.

Element (type)	Description
insrt_pos [bt_int16s]	The position within the account number where one or more characters may be inserted in order to create a unique account number. Valid values: 0 - 28.
insrt_lgth [bt_int16s]	The number of characters that may be inserted into the account number in order to make it unique. Valid Values: 0 - 27.
insrt_val [bt_stringf(18)]	The numeric characters that may be inserted into the account number to make it unique. Values are left-justified and space-filled.
inst_id_num [bt_stringf(11)]	The institution's transit/routing number or issuer identification number unique to the institution. Values are right-justified and zero-filled, containing only numeric characters.

Acct_Status_Extrn_to_Intrn (1.0) (aseid)

Account external status value to internal status value mapping.

[Audited] [Supports versioning]

Element (type)	Description
acct_stat_prfl*[bt_stringf(16)]	Account Status profile. Used as part of the primary key to read the Account Status External to Internal data source.
acct_stat_extrn*[bt_stringf(2)]	External value of the account status.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acct_stat_extrn_descr [bt_stringf(48)]	Text description of the external account status.
acct_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.

Acct_Status_Intrn_to_Extrn (1.0) (asied)

Account internal status value to external status value mapping.

[Audited] [Supports versioning]

Element (type)	Description
acct_stat_prfl*[bt_stringf(16)]	Account Status profile. Used as part of the primary key to read the Account Status External to Internal data source.
acct_stat*[bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
acct_stat_extrn_descr [bt_stringf(48)]	Text description of the external account status.
acct_stat_extrn [bt_stringf(2)]	External value of the account status.

Acquirer_Instrument_Type_Rel (1.0) (aintrd)

The Acquirer Instrument Type Relationship is used by the Merchant Host Extension to allow certain profiles to be configured at the Instrument Type by Merchant or group of Merchants.

[Audited] [Supports versioning]

Element (type)	Description
acq_instrm_typ_rel_prfl* [bt_stringf(16)]	Acquirer Instrument Type Relationship Profile.
[]	
instrm_typ* [bt_stringf(2)]	Instrument Type.
[]	
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
[]	
acq_txn_prfl [bt_stringf(16)]	Acquirer Transaction Profile.
[]	
acq_lmt_prfl [bt_stringf(16)]	Acquirer Limits Profile.
[]	

Acquirer_Issuer_Relation (1.0) (aird)

The Acquirer Issuer Relation table contains one record for each issuer route profile, acquirer route profile, and transaction code (i.e., the first two characters of a processing code) combination in the system. Through configuration of AIR records, a relationship between an acquirer and an issuer is defined by specifying an allowed transaction code. The key to the AIRD is Issuer Route Profile, Acquirer Route Profile, and Transaction Code. The Issuer Route Profile and Acquirer Route Profile may be wildcarded with asterisks. This table defines a set of transactions that is valid for every Issuer/Acquirer Route Profile combination. The route code is used as a key to the Route Table.

[Audited] [Supports versioning]

OLTP: Acquirer_Issuer_Relation_OLTP

Element (type)	Description
iss_rte_prfl* [prfl_def 1.0]	The route profile of the issuer whose customer initiated the transaction. The issuer route profile is defined where ever the issuer is determine and allows one or more issuers to share routing and authorization configurations. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.

Element (type)	Description
acq_rte_prfl*[prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
txn_cde*[bt_stringf(2)]	The transaction code, which is the first 2 bytes of the processing code. The default value is zeroes.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rte_cde [bt_stringf(16)]	The route code is used to group processing codes for routing and authorization purposes. This field is left justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.

Acquirer_Route_Profile (1.0) (artpd)

The Acquirer Route Profile table contains the description associated with each acquirer route profile defined in the system.

[Audited] [Supports versioning]

Element (type)	Description
acq_rte_prfl*[prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
bus_descr [bt_stringf(32)]	This is the business description for Issuer and Acquirer Route Profiles.

Acquirer_Txn_Allowed (1.0) (acqtxd)

The Acquirer Transaction Allowed table contains one row for each acquirer transaction profile, message category code and processing code in the system that are allowed. This table defines the set of transactions that are valid for an acquirer.

[Audited] [Supports versioning]

OLTP: Acquirer_Txn_Allowed_OLTP

Element (type)	Description
acq_txn_prfl*[prfl_def 1.0]	The transaction profile for the acquirer who acquired the transaction. The acquirer transaction profile allows one or more acquirers to share processing code definitions and transactions allowed information. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
msg_cat* [bt_stringf(1)]	The message category relative to the message type identifier. It is the second byte of the message type identifier (e.g. the message category for a 1200 message type is 2). Valid values are: 1 - Authorization; 2 - Financial; 3 - File Maintenance; 5 - Settlement; 6 - Administrative; 8 - Network Management.
proc_cde* [proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
txn_alwd [bt_stringf(1)]	This field defines whether the transaction is allowed by the acquirer. Valid values are: 0 - Disallowed entirely, 2 - Allowed within the state, 3 - Allowed nationally, 4 = Allowed internationally. Default value is 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
min_oper_lvl [bt_int16s]	This field defines the minimum operator level needed to execute the transaction. The valid values are from 0 to 9. Default value is 0.
admin_crd_req [bt_stringf(1)]	This field indicates whether an admin card is required to perform the transaction. Valid values are: Y - Yes, N - No. Default value is N.

ActFunc (1.0) (uactfn)

Activity Functions table

[Audited] [Supports versioning]

Element (type)	Description
AFID* [bt_int32s]	
ActivityType [bt_stringf(50)]	

Action_Code_Extrn_to_Intrn (2.0) (aceid)

The Action Code External to Internal Table contains one record for every external action code defined for the action code profile. All external action codes for the message profile must be the same number of bytes.

[Audited] [Supports versioning]

OLTP: Action_Code_Extrn_to_Intrn_OLTP

Element (type)	Description
act_cde_prfl* [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
act_cde_extrn* [bt_stringf(3)]	The external action code which is used to map to an internal action code or is the result of a mapping from an internal action code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Must be 1 to 3 characters in length.

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
act_cde_extrn_descr [bt_stringf(48)]	Contains a text description of the external action code value.
act_cde [bt_int16s]	The internal action code which is used to map to an external action code or is the result of a mapping from an external action code. Valid values are 000 - 999.
act_cde_extrn_descr_mbyte [bt_binaryl(96)]	Contains a multi-byte text description of the external action code value.

Action_Code_Intrn_to_Extrn (2.0) (acied)

The Action Code External to Internal Table contains one record for every external action code defined for the action code profile. All external action codes for the message profile must be the same number of bytes.

[Audited] [Supports versioning]

OLTP: Action_Code_Intrn_to_Extrn_OLTP

Element (type)	Description
act_cde_prfl*[prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
act_cde*[bt_int16s]	The internal action code which is used to map to an external action code or is the result of a mapping from an external action code. Valid values are 000 - 999.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
act_cde_extrn [bt_stringf(3)]	The external action code which is used to map to an internal action code or is the result of a mapping from an internal action code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Must be 1 to 3 characters in length.
act_cde_extrn_descr [bt_stringf(48)]	Contains a text description of the external action code value.
act_cde_extrn_descr_mbyte [bt_binaryl(96)]	Contains a multi-byte text description of the external action code value.

Active_Script_Statistics (1.0) (actssd)

The Active Script Statistics Table contains one record for each authorizer and message type which is being monitored. The records contain the counts for the script and whether the script is enabled or not. Once the number of transactions processed with the script exceeds the minimum transaction count, the percentage of approvals, denials and referrals are compared to their corresponding threshold limits to determine whether the script should continue to be used or not. If not, the script is disabled. This table is updated during online processing for scripts configured to be monitored. This table should not be audited.

[Not Audited] [Supports versioning]

Element (type)	Description
auth_nam* [bt_stringf(16)]	The name of the authorizer. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_typ* [bt_stringf(4)]	The message type of the transaction.
script_txn_cnt [bt_int32s]	The number of transactions processed with this script. Default value is 0.
script_apprv_cnt [bt_int32s]	The number of transactions approved with this script. Default value is 0.
script_deny_cnt [bt_int32s]	The number of transactions denied with this script. Default value is 0.
script_refer_cnt [bt_int32s]	The number of transactions referred with this script. Default value is 0.
script_enabled_flg [bt_flag]	Flag indicating whether the execution of a high level authorization script is enabled or disabled. Values are: 1 - script enabled, 0 - script disabled. Default value is 1.

ActSess (1.0) (uactse)

Active Session Table

[Audited] [Supports versioning]

Element (type)	Description
UserID* [bt_stringf(16)]	
SessionNum* [bt_int16s]	
WorkstationID [bt_stringf(50)]	
SessionExpireTS [ts 1.0]	
SessionTimeout [bt_int32s]	
CreateTS [ts 1.0]	

ACTSESS2 (1.0) (uacts2)

Active Sessions2 Table

[Audited] [Supports versioning]

Element (type)	Description
UserID* [bt_stringf(64)]	
SessionTkn* [bt_stringf(32)]	
WorkstationID [bt_stringf(50)]	
SessionExpireTS [ts 1.0]	
SessionTimeout [bt_int32s]	

Element (type)	Description
CreateTS [ts 1.0]	
LastUpdtTm [ts 1.0]	

Admin_Card (1.0) (admcd)

Admin Card Data Source. The table contains an entry for each Administrative Card used by a merchant and defines the transactions that the are allowed to be performed by the card.

[Audited] [Supports versioning]

Element (type)	Description
crd_num*[pan 1.0]	The Primary Account Number.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mrch_id [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
clerk_nam [bt_stringf(25)]	The name of the clerk
lst_used_dat [yyymmdd 1.0]	The date, in yyymmdd format, that this entry was last used.
lst_reset_dat [yyymmdd 1.0]	The date, in yyymmdd format, that the number of bad PIN tries for this entry was last reset.
bad_pin_try [bt_int16s DELTA]	The number of times the administrative cardholder has entered an incorrect PIN.
pvv [bt_stringf(12)]	The PIN Verification Value for the card.
pvki [bt_char]	This value is used for Visa PVV PIN Verification Method and indicates which key pair to use.
txn_alwd_01 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_02 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_03 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_04 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_05 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_06 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_07 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_08 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_09 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_10 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_11 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_12 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_13 [txn_cde 1.0]	Transaction that this card is allowed to perform

[illegible]

Element (type)	Description
txn_alwd_49 [txn_cde 1.0]	Transaction that this card is allowed to perform
txn_alwd_50 [txn_cde 1.0]	Transaction that this card is allowed to perform

AEGN_Interface (1.0) (aeifd)

AEGN Interface Table.

[Audited] [Supports versioning]

OLTP: AEGN_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
stnd_in_auth_parm [bt_stringf(2)]	Stand-in Authorization Parameter.

AMEX_CAPN_Interface (1.0) (acpnfd)

The AMEX CAPN Interface Table.

[Audited] [Supports versioning]

OLTP: AMEX_CAPN_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
auth_msg_rsn_cde [bt_stringf(4)]	A code identifying the message reason in field 25 for 1100 authorization messages. The code is provided during certification and used to indicate the message is certified.
rvsl_msg_rsn_cde [bt_stringf(4)]	A code identifying the message reason in field 25 for 1420 reversal messages. The code is provided during certification and used to indicate the message is certified.
nmm_msg_rsn_cde [bt_stringf(4)]	A code identifying the message reason in field 25 for 1804 network management messages. The code is provided during certification and used to indicate the message is certified.

APACS_Configuration (2.0) (apacsd)

Configuration data for the APACS device handler.

[Audited] [Supports versioning]

OLTP: APACS_Configuration_OLTP

Element (type)	Description
chan_prfl*[prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
confirm_auth_flg [bt_flag]	A flag indicating whether to authorisation transaction confirmations are required. Valid values are: 0 – not required, 1 – required. Default value is 0.
confirm_fncl_flg [bt_flag]	A flag indicating whether to financial transaction confirmations are required. Valid values are: 0 – not required, 1 – required. Default value is 0.
confirm_rcncl_flg [bt_flag]	A flag indicating whether to reconciliation confirmations are required. Valid values are: 0 – not required, 1 – required. Default value is 0.
apacs_hld_flg [bt_flag]	Indicates whether hold messages are used for APACS devices. Valid values are 0 - not used, 1 - used. Default is 0.
apacs_hld_timr [bt_int16s]	Time limit in seconds before issuing the first hold message if used for APACS devices. Valid values are 1 - 9999. Default is 30.
apacs_hld_intrvl [bt_int16s]	Time limit in seconds between hold messages if used for APACS devices. Valid values are 1 - 9999. Default is 120.
flr_lmt_trig_onl_auth_flg [bt_flag]	A flag indicating whether to send floor limit triggering online auth amount to the channel. Valid values are: 0 – do not send, 1 – send. Default value is 0.
flr_lmt_trig_onl_auth_amt [bt_int64s]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents) that can be authorised by the channel without attempting to perform online authorisation.
flr_lmt_onl_auth_fail_flg [bt_flag]	A flag indicating whether to send floor limit online auth fail amount to the channel. Valid values are: 0 – do not send, 1 – send. Default value is 0.
flr_lmt_onl_auth_fail_amt [bt_int64s]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents) that can be authorised by the channel following a failed online authorisation attempt.

APCF (1.0) (apcf)

BASE24 Classic - Acquirer Processing Code File.

[Not Audited] [Does not support versioning]

Element (type)	Description
AqurTrnsPrflTx*[bt_stringf(16)]	BASE24 Classic element - The acquirer transaction profile field is part of the key to the APCF. Each acquirer transaction profile defines a set of transactions supported by an acquirer (i.e., institution, retailer, or terminal). This allows one or more acquirers to share processing code definitions and transactions allowed information.
MssgCtgrCd*[bt_stringf(1)]	BASE24 Classic element - Indicates the message category relative to the processing code. It is the second byte of the message type from the internal message (e.g., the message category for a 0200 message type is 2). This is a required field.
TrnsCodeTx*[bt_stringf(2)]	BASE24 Classic Element - Indicates the processing code for which this definition applies. The default value is zeroes.
Accn1TypeTx*[bt_stringf(2)]	BASE24 Classic Element - Indicates the processing code for which this definition applies. The default value is zeroes.
Accn2TypeTx*[bt_stringf(2)]	BASE24 Classic Element - Indicates the processing code for which this definition applies. The default value is zeroes.
UserFild1Tx*[bt_stringf(1)]	BASE24 Classic Element - This field ensures word alignment. This field must be a space.
LastAfmTsLong [bt_int64s]	BASE24 Classic Element - Julian timestamp (date/time) of the last AFM function performed to the data record.
LastAfmUpdtType [bt_int16s]	BASE24 Classic Element - Record maintenance function: 0 - Add 1 - Image before modify 2 - Image after modify 3 - Purge
UserIdGropNmbrShort [bt_int16s]	BASE24 Classic Element - An indicator that identifies the last file maintenance action on this record. This includes the user who performed the update, the time at which it was done, and the type of update.
UserIdUserNmbrInt [bt_int32s]	BASE24 Classic Element - The user number of the operator that performed the last file maintenance application. This value is taken from the information given when the operator last logged on to BASE24.
LastAfmTermNameTx [bt_stringf(24)]	BASE24 Classic Element - This field contains the terminal ID where the record maintenance occurred. Used only by Pathway servers. Non-Pathway servers default TERM-NAM field to blanks.
TrnsAlwdTx [bt_stringf(1)]	BASE24 Classic Element - Indicates whether the transaction is allowed by the acquirer. The default value is 0 (disallowed entirely). Valid values are: 0 = Disallowed entirely 1 or 5 = Allowed within the county 2 or 6 = Allowed within the state 3 or 7 = Allowed nationally 4 or 8 = Allowed internationally
LogAuthDestRespTx [bt_stringf(1)]	BASE24 Classic Element - A field indicating whether responses for transactions sent to the AUTH-DEST are to be logged by BASE24. This is for use by BASE24 Classic ONLY when transactions are APCF routed by Classic endpoints. Valid values are: Y = Yes, Log Response N = No, Do Not Log Response Default value is N.
AuthDestTx [bt_stringf(16)]	BASE24 Classic Element - The name of the authorization destination to which transactions from the acquiring endpoint are to be sent. This is for use by BASE24 Classic. The destination specified in this field cannot be the process name of a BASE24-atm authorization process or a BASE24-pos Router/Authorization process.
DscrTagTx [bt_stringf(30)]	BASE24 Classic Element - A tag that can be associated with a long or short description that exists in the PDF (Processing Code Description File). Since the

Element (type)**Description**

PDF is an optional file, the user may also choose to use this field as the only description for a processing code.

APPLCNFG (2.0) (appld)

The application configuration table is used by all applications built on the Java Server Framework. It is used for storing application configuration information as defined by each application. The configuration entries can be stored as a global entry for all applications or the entry can be configured to only be used by a single process.

[Audited] [Supports versioning]

Element (type)**Description**

CnfgPropIDTx* [bt_stringf(100)]

The name of a configuration property from the Application Configuration (APPLCNFG) table.

PrcsID* [bt_stringf(16)]

A unique ID assigned to a process in the Process table (PROCESS).

CnfgPropValTx [bt_stringf(255)]

The value of a configuration property from the Application Configuration (APPLCNFG) table.

DscrTx [bt_stringf(255)]

This element is used to record descriptive text for entries in the Application Configuration table (APPLCNFG), External Connection table (EXTNCNCT) and the Listener table (LISTENER).

LastUpdtTm [ts 1.0]

The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

RowAccess [bt_char]

EntryTemplate [bt_stringf(255)]

ValidationTemplate [bt_stringf(50)]

APPLDSRC (1.0) (apsrccd)

This table is used for application specific data source relationship configuration.

[Audited] [Supports versioning]

Element (type)**Description**

ApplID* [bt_stringf(16)]

DataSrcNamTx* [bt_stringf(16)]

AS2805_Config (1.0) (as28d)

AS2805 Config Table.

[Audited] [Supports versioning]

OLTP: AS2805_Config_OLTP

Element (type)	Description
chan_prfl*[prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces)
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the datasource record by GUI client application
key_mgmt [bt_stringf(1)]	The AS28DH supports a number of key management schemes "0" - None "1" - AS2805 6.2 "2" - AS2805 6.4 (default)
roll_kek2 [bt_flag]	A code indicating whether the terminal will roll *KEK2 if term proof fails on current and previous *KEK1. For AS2805 6.4 environment only 0 - No, do not roll KEK2 (default) 1 - Yes, roll KEK2

AS2805_Interface (1.0) (as28ifd)

AS2805 Interface Table.

[Audited] [Supports versioning]

OLTP: AS2805_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rcv_inst_id [bt_stringf(11)]	This the Receiving Institution ID associated with the Interface.
setl_typ [bt_int16s]	This field indicates the settlement type (role) of the Interface. (0 - Co-network, 1 - Master, 2-Secondary).
setl_inst_id [bt_stringf(11)]	This the Settlement Institution ID associated with the Interface.

ATDCNFG (3.0) (atdcnd)

ATM DH Configuration Table. The data here is static data that may be specified at the ATM profile level.

[Audited] [Supports versioning]

Element (type)	Description
CnfgPrflTx*[bt_stringf(16)]	The configuration profile ID of an ATM terminal. The value is stored on the ES ATDS1 table and is used to link the terminal to the ES ATM Configuration Profile (ATDCNFG) table entry for the terminal.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
MltpAcctSlctCd [bt_stringf(1)]	Indicates whether or not the ATM terminal can support multiple account selection. The data is configured on the ES ATD Configuration Profile table (ATDCNFG). The ES device handler process will place this value in the transaction request. Standard multiple account selection performs an account look-up, retrieving account numbers (and when available, account descriptions). Static multiple account selection is performed from static generic account menus at the terminal (example, MAC MAS). Valid values are: 0 = Not configured 1 = Terminal supports standard multiple account select 2 = Terminal supports static multiple account select The default value is 0.
MltpAcctMxNum [bt_int32s]	This defines the maximum number of accounts that can be returned in an OAR transaction response. The number of accounts returned will vary by ATM type.
MltpAcctAcqCapCd [bt_stringf(1)]	This field contains the Open Account Relationship (OAR) acquirer capability. This field controls how the issuer will return OAR account information. Valid values are 0 - Send both from and to accounts (when applicable). 1 - One side at a time (only send from or to in one send from issuer).
DfltDpstBinTx [bt_stringf(1)]	The depository bin to use to retain the check. This element is only used if Self-Service Banking (SSB) is enabled in the ATM system.
CustBlncPrsnCd [bt_stringf(1)]	A control flag indicating the type of balance should be displayed. The flag is recorded on the ES ATM Configuration Profile (ATDCNFG) table and is managed through the ES UI. Possible values are Both ledger and available balance = 0 Ledger balance only = 1 Available Balance only = 2
CustBlncLctnCd [bt_stringf(1)]	A control flag indicating the location where the customer balance should be displayed. The flag is recorded on the ES ATM Configuration PProfile (ATDCNFG) table and is managed through the ES UI. Possible values are Both screen and receipt = 0 On the screen only = 1 On the receipt only = 2 On the receipt with screen backup = 3
MltpTrnsPrRcptCd [bt_stringf(1)]	Indicates whether or not the ATM terminal can support multiple transaction per receipt. The data is configured on the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = No 1 = Yes The default value is 0.
MxLnsPrRcptNum [bt_int32s]	The maximum number of printed lines on a receipt. The data is configured in the ES ATD Configuration Profile table (ATDCNFG).
OptnRcptTypCd [bt_stringf(1)]	A code which indicates how cardholder-selected optional receipt processing should work. Terminal State and Screen download configuration determines specifics of the implementation (prompting once per session or on individual transactions). Note - when this feature is enabled, receipts are always printed on transactions involving a partial dispense. Valid values are: 0 = Not configured (always use static configuration settings in the database). 1 = Use static configuration settings in the database if the printer is operable. The cardholder is given an option to cancel if the printer is inoperable and printing is configured for the transaction. 2 = The cardholder controls receipt choice on all approved transactions. If the transaction is denied, use static configuration settings in the database. 3 = The cardholder controls receipt choice on all approved and denied transactions. The default value is 0.
AvlbpstTypCd [bt_stringf(1)]	The available depository types configured at an ATM. Possible types are Standard = 0 Commercial = 1 Both standard and commercial = 2 This data is stored in the configuration profile table and is used during deposit type transactions.
LclPinVrfyTypCd [bt_stringf(1)]	A code, configured on the ES ATD Configuration Profile table (ATDCNFG), indicating when the ATM device can perform PIN verification at the ATM, without the involvement of the authorization system. The ATM device must have PIN verification capability to perform local PIN verification, and the ATM configuration file must be configured for local PIN verification. The value in this field is used as input to a fraud prevention

Element (type)	Description
	check for financial and administrative transactions whose PIN has been verified locally by the terminal. Valid values are: 0 = Not configured 1 = Allow on-us local verification 2 = Allow any local verification (on-us / not-on-us)
WthdAmntTypCd [bt_stringf(1)]	Currently unused.
NcdRtTrnsNmbrTx [bt_stringf(11)]	The routing ID used for non-currency dispense transactions. The data is configured on the ES ATDS1 table and is sent to the authorization process with transaction requests which are non-currency transactions.
NcdClsOnMsdsCd [bt_stringf(1)]	A flag indicating whether the ATM should be closed if a misdispense occurs when dispensing non-currency items. The data is configured on the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Not configured 1 = Close the ATM The default value is 0.
NcdNValFrChckCd [bt_stringf(1)]	A flag determining if non-value items may be dispensed when a transaction is for a checking account type. The data is configured on the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Not allowed 1 = Allowed The default value is 0.
NcdNValFrSvngCd [bt_stringf(1)]	A flag determining if non-value items may be dispensed when a transaction is for a savings account type. The data is configured on the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Not allowed 1 = Allowed The default value is 0.
LrgMsgMxSzNum [bt_int32s]	A value indicating the maximum size of a message for an ATM. The default is 600 bytes. To support large messages this field should be set to 2032 bytes. The data is stored on the ATM Configuration Profile table (ATMPRFL).
NcdNValFrCrdtCd [bt_stringf(1)]	A flag determining if non-value items may be dispensed when a transaction is for a credit account type. The data is configured on the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Not allowed 1 = Allowed The default value is 0.
DialUpFlrActnCd [bt_stringf(1)]	A flag indicating the disposition of transactions involving Message Failures processing transaction Function Commands under the Dial-up ASYNC protocol. The element is stored on the ES ATM Configuration Profile table (ATDCNFG). Possible values are 0 - Do not reverse when no terminal ACK has been received. 1 - Reverse when no terminal ACK has been received.
InstRtTrnsNmbrTx [bt_stringf(11)]	The institution routing ID used for routing transactions in the authorization system. The element is stored on the ES ATDS1 table.
AltrRtTrnsNmbrTx [bt_stringf(11)]	The alternate routing number for an ATM. The alternate number is used if the transaction can not be routed using the primary routing number. This element is used only on the Configuration Profile table.
TermPrtcCd [bt_stringf(1)]	Indicates which line protocol is being used for communications with this terminal. Valid values are: A = ASYNC P = X25 PVC X = X25 SVC S = SNA T = TCP/IP The default value is T. The data is configured on the ES ATD Configuration Profile table (ATDCNFG).
TermSbPrtcCd [bt_stringf(1)]	Indicates which messaging protocol is being used for communications with this terminal. Valid values are: D = Dial-Up connection P = Permanent connection The default value is P. The data is configured on the ES ATD Configuration Profile table (ATDCNFG).
TermCrncCd [crncy_cde 1.0]	A code indicating the type of currency used to represent the terminals amount fields. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981

Element (type)	Description
	to determine the proper code. Example: 840 (The U.S. currency code). The data is configured on the ES ATDD1 table.
TermMgmtExCnctIdTx [bt_stringf(16)]	The external connection ID for terminal management for the ATM. This is the message destination for messages outbound from the ES ATM device handler to the ATM device. It is required because in a large terminal population, the terminals may be spread across multiple ICE-XS processes, for example.
MsgDataEncrSprtCd [bt_stringf(1)]	The type of Message Data encryption and verification that is supported by the ATM device. The data is stored in the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Not configured 1 = Software Message Authentication 3 = Hardware Message Authentication The default value is 0.
MsgDataEncrTypCd [bt_stringf(1)]	The character set that the data to be encrypted or verified is in. The data is configured in the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = ASCII 1 = EBCDIC The default value is 0.
MsgDataEncrMthdCd [bt_stringf(1)]	This field determines what type of calculation will be done on the fields in the message. The data is stored in the ES ATD Configuration Profile table (ATDCNFG). For Selective Field Data Encryption, the fields included in the data string to be encrypted are configured via the Device Handler configuration file IFXCryptoMetadata.xml. Valid values are: 0 = Full Message Encryption 1 = Selective Field Message Encryption. The default value is 1.
KeyHierIndCd [bt_stringf(1)]	This field determines number of key hierarchy levels. With two levels a terminal master key and working keys exist, i.e. PIN, MAC, and MSG (message encryption). Key hierarchy level 3 introduces key exchange keys (one for each of the working keys) between terminal master key and working keys. Valid values are: 2 = 2 level key 3 = 3 level key. The default value is 2.
CryptoMetaPrflTx [bt_stringf(16)]	Profile name used as key into file IFXCryptoMetadata.xml (with a corresponding profile name XML element).
DkmAuthentKeyCnt [bt_stringf(1)]	The number of keys being authenticated during AKDS mutual authentication. The data is stored in the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 1 = One key is used for encryption and verification 2 = Two separate keys are used for encryption and verification. The default value is 2.
DkmCertAuthSprtCd [bt_stringf(1)]	Indication whether certificate authority is supported for certificate rollover. The data is configured in the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = ATM does not support certificate rollover via certificate authority 1 = Certificate rollover via certificate authority supported. The default value is 0.
EncrDevTypCd [bt_stringf(1)]	Indication which type of encryption device the ATM is using for AKDS. Valid values are: 0 - AKDS not configured, 1 - AKDS enabled/NCR signature, 2 - AKDS enabled/Diebold certificates, 3 - AKDS enabled/Wincor-Nixdorf signature. Default is 0.
KySgnrTx [bt_stringf(16)]	Name of Host Public Key owner. (TSS will use a default value of HOST if this field is spaces)

ATMCNFG (1.0) (atmcnd)

ATM DH Configuration Table. This data is generated from an ATM configuration file. The configuration data is separated into separate rows for easy access. The data in this table is down loaded to the ATM devices when a load is requested.

[Not Audited] [Supports versioning]

Element (type)	Description
LoadPrflTx* [bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it. The data is configured on the ES ATDS1 table. The data is also used as a key to the ES ATM Configuration table (ATMCNFG) to retrieve load data during the ATM load process.
RecTypeCd* [bt_stringf(1)]	The record type of a load data entry in the ATM Configuration table (ATMCNFG). Valid values are: 1 = Configuration Parameters 2 = States 3 = Screens 4 = FITs 5 = Supervisor Data 6 = Config ID number
GroupldTx* [bt_stringf(4)]	The ATM Load Group ID. The data is stored on the ES ATDS1 table and replicated for the ES User Interface, on the ES ATDD1 table. The base group has a value of 0000.
RecNumTx* [bt_stringf(3)]	The specific load items record number (e.g., 000 for a screen record would be screen number 0). The data is stored in the ATM Configuration table (ATMCNFG). The value is managed by the Configuration Loader process.
LangBankldTx* [bt_stringf(3)]	An ES ATM device handler element. The ID of the language bank within the ATM where the character set for the language is defined. This ID is must correspond to the correct language bank in the ATM of the screens may be illegible.
LoadDataBn [bt_binaryv(4030)]	The ATM load context, stored in the ATM Configuration table (ATMCNFG). When an ATM device is being loaded, the ES device handler saves the load context, where the device is in the load process, in this column. The data is managed by the ES device handler.

ATMLOG (1.0) (atlgd)

The ATM native message log table. This table is optionally used by the ES ATM device handlers to log the native messages sent from or to the ATM devices. Requests, responses and statuses are saved. The data is in its native format.

[Not Audited] [Supports versioning]

Element (type)	Description
TermldTx* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
InsrtTs* [bt_int64s]	The date and time an row was inserted into the table. This data is used to retrieve the records in the order they were written.
MsgDrctTx* [bt_stringf(1)]	A BASE24-es Device Handler message audit log element. The element defines the direction of the message being logged. Values are I (inbound) and O (outbound).
MsgFailTx* [bt_stringf(1)]	A BASE24-es Device Handler message audit log element. The element identifies whether the message being logged is a failed message or not (value 1 = failed).
MsgPartNum* [bt_int32s]	BASE24-es Device Handler Message Audit Lof element. This element specifies the sequential part number for messages that are too long to fit into one row. Numbering begins at 1.

Element (type)	Description
MsgPrclsID [bt_stringf(16)]	A BASE24-es Device Handler Message Audit Log element. The unique ID assigned to the process.
InsrtTmTx [bt_stringf(24)]	The row insert time as represented as a string. This field is obtained from a java.sql.Timestamp and is pre-formatted in the form yyyy-mm-dd hh:mm:ss.mmm. For example, 2004-07-15 09:12:26.468.
MsgDataBn [bt_binaryv(3988)]	A BASE24-es Device Handler element. The message saved in the ATM Audit Log table, in its native format.

ATM_CONF (1.0) (atmcnf)

ATM DH Load Configuration Table. This data is generated from an ATM configuration file. The configuration data is separated into separate rows for easy access. The data in this table is down loaded to the ATM devices when a load is requested.

[Audited] [Supports versioning]

Element (type)	Description
load_prfl*[bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it. The data is configured on the ATM_DS1 table. The data is also used as a key to the ATM Configuration table (ATM_CONF) to retrieve load data during the ATM load process.
rec_typ_cde*[bt_stringf(1)]	The record type of a load data entry in the ATM Configuration table (ATM_CONF). Valid values are: 1 = Screens 2 = States 3 = Configuration Parameters 4 = FITs 5 = Supervisory Data 6 = Configuration Identifier
load_group_id*[bt_stringf(4)]	The ATM Load Group ID. The data is stored on the ATM_DS1 table and replicated for the ES User Interface, on the ATM_DD1 table. The base group has a value of 0000.
rec_load_num*[bt_stringf(3)]	The specific load items record number (e.g., 000 for a screen record would be screen number 0). The data is stored in the ATM Configuration table (ATM_CONF). The value is managed by the Configuration Loader process.
lang_bank_id*[bt_stringf(3)]	An ES ATM device handler element. The ID of the language bank within the ATM where the character set for the language is defined. This ID is must correspond to the correct language bank in the ATM of the screens may be illegible.
load_tkn_repl [bt_flag]	This field indicates whether token replacement processing should be invoked for this ATM load record. This applies to states, FITS and screen load images. If enabled token replacement processing will be invoked to modify the load image contained in this record. The default value is false, not enabled.
load_data_bin [bt_binaryv(4030)]	The ATM load context, stored in the ATM Configuration table (ATM_CONF). When an ATM device is being loaded, the ATM device handler saves the load context, where the device is in the load process, in this column. The data is managed by the ATM device handler.

ATM_CONSUMER_MEDIA (2.0) (atmmed)

This data source contains configurable media elements that are used to build configurable data in ATM responses. For example: Non-Currency Dispense and Open Account Relationship processing.

[Audited] [Supports versioning]

OLTP: ATM_CONSUMER_MEDIA_OLTP

Element (type)	Description
term_typ* [bt_stringf(2)]	A code indicating the type of terminal. The data is configured on the ATM_DS1 table. Valid values are 01 - NCR 5xxx 02 - Diebold 10xx 03 - Wincor NDC 04 - Wincor DDC 05 - Triton 06 - Tidel
load_prfl* [bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it. The data is configured on the ATM_DS1 table. The data is also used as a key to the ATM Configuration table (ATM_CONF) to retrieve load data during the ATM load process.
media_lang_id* [bt_stringf(5)]	The ID of the language bank within the ATM where the character set for the language is defined. This ID must correspond to the correct language bank in the ATM of the screens may be illegible. This field has 2 uses: Map native language identifier from the ATM to an ISO-639 value. Used to determine data for screens based on ISO-639 value found in the Language TDE.
atm_media_text_key* [bt_stringf(40)]	This field contains a portion of the key used to find ATM Consumer Media Configuration data. This data is used to build configurable media data such as: Non-Currency Dispense, Open Account Relationship processing and receipt data.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
atm_media_text [bt_binaryv(80)]	This field contains the configurable data that is formatted in an ATM response message. This data is used to build configurable ATM displays for processing such as: Non-Currency Dispense and Open Account Relationship processing. Note for proper media vertical alignment, spaces will be retained in this field as entered by the user on the screen.

ATM_DD1 (3.0) (atmdd1)

ATM Dynamic Data Table 1. The data in this table includes hopper amounts and transaction counts and amounts. The data in this table is updated per transaction to adjust the counts and amounts.

[Audited] [Supports versioning]

Element (type)	Description
term_id* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
post_dat [yyyyymmdd 1.0]	The current settlement date.

Element (type)	Description
atm_seq_num [bt_int32s]	The last transaction sequence number. If the terminal supports the generation of such a number, this number comes from the terminal. Otherwise, it is generated by the ATM device handler for the terminal. The data is stored on the ATM_DD1 table.
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
hpr1_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr1_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr1_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr1_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr1_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr1_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr2_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr2_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr2_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr2_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr2_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.

Element (type)	Description
hpr2_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr3_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr3_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr3_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr3_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr3_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr3_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr4_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr4_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr4_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr4_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr4_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr4_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).

Element (type)	Description
hpr5_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr5_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr5_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr5_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr5_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr5_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr6_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr6_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr6_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr6_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr6_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr6_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr7_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The

Element (type)	Description
	value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr7_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr7_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr7_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr7_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr7_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr8_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr8_amt_incr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr8_amt_decr [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr8_amt_out [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr8_amt_end [amt 1.0 DELTA]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr8_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
envl_deposit_cnt [bt_int32s DELTA]	The total number of unverified deposit envelopes received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.

Element (type)	Description
envl_deposit_amt [bt_int64s DELTA]	The total value of envelope deposits into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
cash_deposit_cnt [bt_int32s DELTA]	The total number of cash deposits received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
cash_deposit_amt [bt_int64s DELTA]	The total value of cash deposited into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
cmrcl_deposit_cnt [bt_int32s DELTA]	The total number of commercial deposits (e.g., from Securomatic devices) received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
cmrcl_deposit_amt [bt_int64s DELTA]	The total value of commercial deposits into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
payments_cnt [bt_int32s DELTA]	The total number of payment envelopes received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
payments_amt [bt_int64s DELTA]	The total value of payment transactions performed at an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
msgs_to_fiid_cnt [bt_int32s DELTA]	The total number of messages to the financial institution received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
checks_cnt [bt_int32s DELTA]	The total number of checks received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
checks_amt [bt_int64s DELTA]	The total value of the checks deposited into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
log_only_cnt [bt_int32s DELTA]	The total number of log only transactions completed since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
cards_retain_cnt [bt_int32s DELTA]	The total number of consumer cards retained by the ATM since the terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
term_debits [bt_int64s DELTA]	The unverified amount of terminal debits since the terminal was last balanced. The amount in this field consists of debits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit

Element (type)	Description
term_credits [bt_int64s DELTA]	transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us and not-on-us payment-enclosed transactions On-us and not-on-us transfers On-us and not-on-us payments between accounts The value in this field is stored in the ATM_DD1 table and is managed by the ATM device handler. The total amount of terminal credits since the terminal was last balanced. The amount in this field consists of credits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us withdrawals On-us and not-on-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the TERM-CR amount. On-us and not-on-us transfers On-us and not-on-us payments between accounts On-us and not-on-us non-currency dispense transactions The value in this field is stored on the ATM_DD1 table and is managed by the ATM device handler.
on_us_debits [bt_int64s DELTA]	The total amount of on-us debits since the ATM terminal was last balanced. The amount in this field consists of debits from the customers point of view. Transaction amounts are added to the balance in this field for: On-us withdrawals On-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the ON-US-DB amount. On-us transfers On-us payments between accounts On-us non-currency dispense transactions The value in this field is managed by the ATM device handler. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed.
on_us_credits [bt_int64s DELTA]	The total amount of on-us credits since the ATM terminal was last balanced. The amount in this field consists of credits from the customers point of view. Transaction amounts are added to the balance in this field for On-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us payment enclosed transactions On-us transfers On-us payments between accounts The value in this field is managed by the ATM device handler. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed.
ssb_chk_suprt_ind [bt_stringf(1)]	A code indicating whether the ATM terminal supports the SSB Check Application features. The data is stored in the ATM_DD1 table and the value is managed by the ATM device handler. Valid values are: 0 = Not configured 1 = Yes - supports the SSB Check Application The default value is 0.
ssb1_check_cnt [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb1_check_amt [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb1_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb2_check_cnt [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.

Element (type)	Description
ssb2_check_amt [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb2_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb3_check_cnt [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb3_check_amt [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb3_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb4_check_cnt [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb4_check_amt [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb4_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
balance_ind [bt_stringf(1)]	An element that indicates how an ATM terminal was last balanced. The data is stored on the ATM_DD1 table and is used only for information purposes. Possible values are Balanced at the terminal = 0 Balanced at the ES UI = 1 Force balanced by the system = 9
cutover_pending [bt_stringf(1)]	A control flag indicating cutover is pending for the ATM. The flag is recorded on the ATM_DD1 table and is managed by the device handler.
atmflw_seq_cntl [bt_int32s]	This data element contains the number of a logical document within the Flow Control Configuration. The logical document contains all of the records of the latest service versions when the logical document was created.
new_post_dat [bt_stringf(8)]	The terminal owners posting date (YYYYMMDD) used while the terminal is waiting to cut over. The data is stored on the ATM_DD1 table. The value in this field is managed by the ATM device handler. It is set by the End of Period process and reset by the ATM Device Handler.
last_settle_tm [ts 1.0]	The date and time an ATM was last balanced using an administrative balancing function. The data is stored on the ATM_DD1 table and is managed by the ATM device handler.
user_txt_area [bt_stringf(70)]	This field is for informational only data. It is configured on the ATM_DD1 table.

Element (type)	Description
dkm_pin_txn_cnt [bt_int32s DELTA]	The number of transactions requiring PIN verification since the last PIN key change. The element is stored on the ATM_DD1 table and is controlled by the device handler.
dkm_pin_err_cnt [bt_int32s DELTA]	The number of transactions with a PIN verification error since the last PIN key change. The element is stored on the ATM_DD1 table and is controlled by the device handler.
dkm_mac_txn_cnt [bt_int32s DELTA]	The number of transactions requiring MAC verification since the last MAC key change. The element is stored on the ATM_DD1 table and is controlled by the device handler.
dkm_mac_err_cnt [bt_int32s DELTA]	The number of transactions with a MAC verification error since the last MAC key change. The element is stored on the ATM_DD1 table and is controlled by the device handler.
dkm_key_chng_tm [ts 1.0]	The Julian timestamp of the last key change executed with the ATM. The element is stored on the ATM_DD1 table and is controlled by the device handler.
emv_scrpt_crd_blk [bt_stringf(1)]	This field contains a copy of the issuers script processing flags for EMV. The element is stored in the ATM_DD1 table and is managed by the ATM device handler.
emv_scrpt_put_data [bt_stringf(1)]	This field contains a copy of the issuers script processing flags for EMV. The element is stored in the ATM_DD1 table and is managed by the ATM device handler.
online_ind [bt_stringf(1)]	An indicator of whether the ATM is on-line (i.e., communicating to the data processing center). The data is stored on the ATM_DD1 table. The value in this field is controlled by the ATM device handler. Valid values are: 0 = Off-line 1 = On-line 2 = Undetermined The default value is 2. Note that on some platform and messaging middleware combinations, the on-line status cannot be known until a message is actually received by the ATM device handler.
open_ind [bt_stringf(1)]	An indicator of whether the ATM is open. An ATM is open only if an Open command response has been received by the ATM device handler. The data is stored on the ATM_DD1 table. The value in this field is controlled by the ATM device handler. Valid values are: 0 = Closed 1 = Open The default value is 0.
device_seq_num [bt_stringf(9)]	The sequence number of the device. This value is received in the native messages from the device. For native devices this is the Logical Unit Number (LUNO). The element is stored on the ATM_DD1 table and is managed by the ATM device handler.
msg_coord_num [bt_stringf(1)]	Transaction message coordination number extracted from the transaction request. This element is stored on the ATM_DD1 table and is managed by the ATM device handler.
cntl_intertxn_tout [bt_int32s DELTA]	A control counter indicating the number of consecutive intertransaction timeouts that have occurred. The counter is recorded on the ATM_DD1 table and is managed by the device handler. If too many consecutive timeouts occur, an event is generated by the ES ATM device handler.
cntl_txn_stat [bt_stringf(1)]	A control flag indicating the current transaction status. The flag is recorded on the ATM_DD1 table and is managed by the device handler. The ATM Device Handler is expecting completion of one of the following: 0 - Expect Transaction, 1 - Expect Authorization, 2 - Expect Financial, 3 - Expect Non-Financial.
cntl_load_stat [bt_stringf(1)]	A control flag indicating whether or not the terminal is involved in a load. The flag is recorded on the ATM_DD1 table and is managed by the device handler. Values are 0 - Load not in progress, 1 - Load in progress.
cntl_bal_ind [bt_stringf(1)]	A control flag indicating balancing is required for the terminal. The flag is recorded on the ATM_DD1 table and is managed by the device handler.

Element (type)	Description
cntl_rear_bal_ind [bt_stringf(1)]	A control flag indicating whether or not rear balancing is in progress at the ATM. The flag is recorded on the ATM_DD1 table and is managed by the device handler.
cntl_suprvsr_ind [bt_stringf(1)]	A control flag indicating the whether or not the ATM has had the supervisor switch set. The flag is recorded on the ATM_DD1 table and is managed by the device handler.
cntl_opt_rcpt_stat [bt_stringf(1)]	A control flag indicating whether or not the receipt printer is operable or inoperable and whether the corresponding load has been sent to the ATM. The flag is recorded on the ATM_DD1 table and is managed by the device handler. Valid values are as follows: 0 - Operable load group loaded to the ATM, 1 - Operable load group loading to the ATM, 2 - Inoperable load group loaded to the ATM, 3 - Inoperable load group loading to the ATM.
cntl_part_rvrsl [bt_stringf(1)]	A control flag indicating whether or not a partial reversal is pending at the ATM. The flag is recorded on the ATM_DD1 table and is managed by the device handler.
cntl_rcpt_pg_cnt [bt_int32s]	A control value indicating the number of pages the receipt will require. The value is recorded on the ATM_DD1 table and is managed by the device handler.
cntl_rcpt_ln_cnt [bt_int32s]	A control value indicating the number of lines to be printed on a receipt. The value is recorded on the ATM_DD1 table and is managed by the device handler.
hardware_array [bt_stringf(40)]	The hardware presence array for an ATM. The data is stored in the ATM_DD1 table and is managed by the ATM device handler. The hardware array bytes correspond to hardware sub units in the ATM. Note that only the hardware sub units directly effecting transaction processing are recorded on the ATM_DD1. While other sub units may be present in by the device, their existence is not recorded. Possible values for each byte are Configured (1) or Not Configured (0).
fitness_array [bt_stringf(40)]	The hardware Fitness Array for an ATM. The data is stored in the ATM_DD1 table and is managed by the ATM device handler. The fitness array bytes correspond to hardware sub units in the ATM. Note that only the hardware sub units directly effecting transaction processing are recorded on the ATM_DD1. While other sub units may be reported on by the device, their status is not recorded. However, should they fail, an event will be logged. Not all ATM devices have all possible sub units. For example, the coin dispenser may not be present on many ATM devices. The Hardware Array indicates which of the devices is present on the ATM.
supply_array [bt_stringf(40)]	The supply data array for an ATM. The data is stored in the ATM_DD1 table and is managed by the ATM device handler. The supply data array bytes correspond to various sub devices which require consumable supplies, for within the ATM for example, the receipt printer. Possible values for each byte are Unchanged (0), Good (1), Low (2), Out (3)and Overfill(4).
sensor_array [bt_stringf(40)]	The sensor data array for an ATM. The data is stored in the ATM_DD1 table and is managed by the ATM device handler. The sensor data array bytes correspond to various sensors within the ATM for example, the vibration sensor. Possible values for each byte are 0 = No Sensor, 1 = Active/Good State, 2 = Inactive.
inactivity_timer [bt_int64s]	This field contains a unique id of the last inactivity timer started. It is used to avoid conflicts when a cancel message is sent (by an ATM device handler process) at about the same time as the expired inactivity timer message (sent by the timer process). The value in this field is stored in the ATM_DD1 table and is managed by the ATM device handler.

Element (type)	Description
load_group_id [bt_stringf(4)]	The ATM Load Group ID. The data is stored on the ATM_DS1 table and replicated for the ES User Interface, on the ATM_DD1 table. The base group has a value of 0000.
load_config_id [bt_stringf(4)]	This field contains the four digit configuration ID (0000 through 9999) associated with the terminals downloaded configuration file. The data is stored on the ATM_DD1 table and is managed by the ATM device handler.
software_rls [bt_stringf(10)]	The software release number retrieved from an ATM terminal. The data is stored in the ATM_DD1 table and is available for display purposes. The ATM provides the value. The ATM device handler simply records it in the ATM_DD1.
software_id [bt_stringf(20)]	The software identifier specifies the software being used on an NCR device for smartcard processing. This data is managed by the ATM device handler and is stored on ATM_DD1.
model_num [bt_stringf(10)]	The model number of an ATM. The data is stored in the ATM_DD1 table and is managed by the ATM device handler. The data is retrieved from the ATM using a configuration information retrieve request when a full load is performed on the ATM.
lst_txn_stat_enab [bt_char]	This code, stored on the ATM_DD1 table, indicates whether the ATM device will send the last transaction status information on the next request. Possible values are 0 - Last transaction status is not enabled. 1 - Last transaction status is enabled. The default value, set in the user interface is 0 (last transaction status is not enabled). The element is managed by the ATM device handler.
sur_amt_lmt_ind [bt_stringf(1)]	A flag indicating the status of the Surcharge Amount Limit. The value is configured in the ATM_DD1 Configuration table. This flag is set to the value of 3 when the UI modifies the Surcharge Amount Limit and Non-Interactive Surcharging is configured in Surcharge Type. Valid values are: 0 = Not configured 1 = Download complete 2 = Download in progress 3 = Download pending The default value is 0.
interact_cond_stat [bt_stringf(20)]	This data element contains the service seed for the next service to be completed, when processing an interactive transaction. Once the ATM responds to the previous message, this field is used as the seed into flow control to continue processing the current interactive transaction.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dual_site_ind [bt_char]	Indicates if the record/transaction originated on the Local System or the Remote System. Valid values: space or L - Local (default). R - Remote.
onl_key_pan [pan 1.0]	The primary account number for use in online queries.
onl_key_amt [bt_int64s]	The amount used for online queries. This is the amount originally requested.
onl_key_seq_num [bt_stringf(12)]	The sequence number used for online queries.
onl_key_discrim [bt_stringf(4)]	The discriminant used for online queries.
last_txn_captr_dat [bt_stringf(8)]	The capture date in YYYYMMDD of the last transaction the ATM processed.
last_txn_cur_cde [bt_int16s]	This field contains the currency code of the last transaction processed by the ATM.
last_txn_proc_cde [bt_stringf(6)]	This field contains the processing code of the last transaction that was processed by the ATM.

Element (type)	Description
last_txn_iss_inst_id [inst_id 1.0]	The issuer institution identifier uniquely identifying the issuing institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). This field is used by the device handler to find the original transaction on a reversal.
master_key_loaded [bt_flag]	This field indicates whether the Master Key has been loaded to an ATM. The default value for this field is false. This field is managed by the ATM device handler and is set to true when the Master Key has been successfully loaded to the ATM.
term_bna_rjct_notes_cnt [bt_int32s DELTA]	The total number of notes rejected (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
term_bna_vault_notes_cnt [bt_int32s DELTA]	The total number of notes vaulted (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
term_bna_escr_notes_cnt [bt_int32s DELTA]	The total number of notes escrowed (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
term_bna_rtrn_notes_cnt [bt_int32s DELTA]	The total number of notes returned (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
atm_peak_load_prfl [bt_stringf(16)]	This field contains the peak load profile used by the ATM. This profile is stored on the ATM_DD1 data source. This profile is optional and should only be filled for ATMs utilizing peak load (Transaction Time Windows) processing.
term_ind_array [bt_stringf(50)]	Contains a series of indicators and flags that the ATM C++ device handler uses during the processing of a transaction. This information is stored on the ATM_DD1 data source and is managed by the ATM device handler.
dkm_cnsc_mac_err_cnt [bt_int32s DELTA]	The number of consecutive transactions with a MAC verification error since the last MAC key change. The element is stored on the ATM_DD1 table and is controlled by the device handler.
prvt_use_array [bt_stringf(500)]	Contains an buffer in which Tag/Length/Value (TLV) entries are stored. The usage of this field is device dependent, meaning the valid tags within this buffer are defined by each device handler.
dial_up_queue_cnt [bt_int32s DELTA]	The total number of commands in the ATM Dial-Up Command table (ADC) for this terminal.
cntl_sur_amt_lmt [bt_int64s]	The current surcharge amount limit that has been downloaded to the terminal.

ATM_DD2 (1.0) (atmdd2)

ATM Dynamic Data Table 2. This table contains several scratch pad areas for recording terminal and transaction context while awaiting a response from the ATM device.

[Audited] [Supports versioning]

Element (type)	Description
term_id* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
atmdd2_rec_typ* [bt_stringf(1)]	This field identifies the type of information that is saved in the ATM_DD2 data source. Valid values for this field are L - Load data and T - Transaction data. This field is managed by the ATM device handler.
rec_num* [bt_stringf(3)]	This field is used to make a primary key unique when multiple rows exist for the other fields in the primary key. rec_num begins with value 1 except for the Card Account table which begins with value 0.
num_atmdd2_recs [bt_stringf(3)]	This field contains the total number of records that were written to the ATM_DD2 data source for a single transaction.
cmmn_tran_data [bt_binaryl(4025)]	Transaction context storage area in ATM_DD2. This element is managed by the ES ATM device handler.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

ATM_DIAL_UP_CMD (1.0) (atmdcd)

This data source contains data to support Dial Up load processing. This data source will contain a record for every load command to be processed by the ATM.

[Audited] [Supports versioning]

Element (type)	Description
term_id* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
exec_pri* [bt_stringf(1)]	This data element contains the priority of the command. Valid values are: "0" - critical, "1" - high, "2" - medium, "3" - low, " " - suspend (default, "2").
tran_ent_ts* [ts 1.0]	The transaction entry time.
cmd_err_cnt [bt_int32s]	This data element contains the number of resend attempts.
cmd_stat [bt_stringf(1)]	This data element contains the status of the command. Valid values are: "1" - inactive new, "2" - active, "3" - inactive resend.
cmd_val [bt_stringv(500)]	This data element contains the Dial Up load command.

ATM_DKM (1.0) (atdkmd)

ATM Dynamic Key Management Table 1. This table contains the DKM limits related to the DKM counters from ATM_DD1.

[Audited] [Supports versioning]

OLTP: ATM_DKM_OLTP

Element (type)	Description
dkm_prfl*[prfl_def 1.0]	The Dynamic Key Management (DKM) profile identifies the DKM processing values to be used for the specified ATM. The DKM profile is defined in ATM_DS1.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dkm_cnsc_mac_err_lmt [bt_int32s]	The number of consecutive MAC errors that can occur before the device handler downloads a new MAC and PIN key to the ATM. A value of 0 indicates that the device handler does not reload keys regardless the number of consecutive MAC errors.
dkm_key_chng_tm_intrvl [bt_int32s]	This data element specifies the maximum time allowed between key changes before the device handler downloads a new MAC and PIN key to the ATM. The value is in hours. A value of 0 indicates that the device handler does not reload keys regardless of the length of time since the last key change.
dkm_mac_err_lmt [bt_int32s]	The number of MAC errors that can occur before the device handler downloads a new MAC and PIN key to the ATM. A value of 0 indicates that device handler does not reload keys regardless of the number of MAC errors.
dkm_mac_txn_lmt [bt_int32s]	The number of MAC generations or verifications that can occur before the device handler downloads a new MAC and PIN key to the ATM. A value of 0 indicates that the device handler does not reload keys regardless the number of MAC generations or verifications.
dkm_pin_err_lmt [bt_int32s]	The number of PIN verification errors that can occur before the device handler downloads a new MAC and PIN key to the ATM. A value of 0 indicates that the device handler does not reload keys regardless of the number of PIN verification errors.
dkm_pin_txn_lmt [bt_int32s]	The number of PIN verifications that can occur before the device handler downloads a new MAC and PIN key to the ATM. A value of 0 indicates that the device handler does not reload keys regardless of the number of PIN verifications performed.

ATM_DS1 (4.0) (atmds1)

ATM Static Data Table 1. The static, basic data associated with an ATM terminal. When adding a new ATM, using existing profiles, this is the only data that need be added.

[Audited] [Supports versioning]

OLTP: ATM_DS1_OLTP

Element (type)	Description
term_id*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
term_typ [bt_stringf(2)]	A code indicating the type of terminal. The data is configured on the ATM_DS1 table. Valid values are 01 - NCR 5xxx 02 - Diebold 10xx 03 - Wincor NDC 04 - Wincor DDC 05 - Triton 06 - Tidel

Element (type)	Description
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acq_tran_prfl [bt_stringf(16)]	The Acquirer Transaction Profile ID for an ATM terminal. The profile is used for authorization purposes.
acq_rte_prfl [prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
term_ownr [bt_stringf(22)]	The name of the financial institution owning the terminal. The data is configured on the ATM_DS1 table.
term_adrs [bt_stringf(25)]	A unique address which identifies the location of the terminal. This field is used as print information on the ATM customer receipt. The data is configured on the ATM_DS1 table.
term_city [bt_stringf(13)]	The name of the city where the terminal is located. The data is configured on the ATM_DS1 table.
term_state [bt_stringf(3)]	The state, province, or political subdivision where the terminal is located. The entry in this field is used to validate sharing transactions. In the United States, this field contains the ANSI standard state code as specified in States and Outlying Areas of the United States, FIPS PUB 5-1. Codes for other countries must be agreed upon by all sharing institutions. The data is configured in the ATM_DS1 table.
term_cnty [bt_stringf(3)]	The county where the terminal is located. The entry in this field is used to validate sharing transactions. For the United States, this field contains the ANSI standard county code specified in Counties and County Equivalents of the States of the United States, FIPS PUB 6-1. Codes for other countries must be agreed upon by all sharing institutions. The data is configured on the ATM_DS1 table.
term_cntr [bt_stringf(3)]	The country where the terminal is located. The entry in this field is used to validate sharing transactions. Valid values are listed in the ISO Codes For the Representation of Names of Countries, 3166-1981. The data is configured on the ATM_DS1 table.
term_branch [bt_stringf(4)]	The Branch ID for the branch in which the terminal is located. The data is configured in the ATM Static Data source ATM_DS1.
term_region [bt_stringf(4)]	The Region ID for the region in which the terminal is located. The data is configured in the ATM Static Data source ATM_DS1.
postal_cde [bt_stringf(10)]	The postal code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
load_prfl [bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it. The data is configured on the ATM_DS1 table. The data is also used as a key to the ATM Configuration table (ATM_CONF) to retrieve load data during the ATM load process.
act_cde_prfl [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field

Element (type)	Description
	is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
hpr_prfl [bt_stringf(16)]	The hopper configuration profile ID associated with an ATM. The hopper profile ID is stored in the ATM_DS1 table and is used to link the ATM to its hopper configuration defined in the Hopper Configuration table (ATM_HOPR).
cnfg_prfl [bt_stringf(16)]	The configuration profile ID of an ATM terminal. The value is stored on the ATM_DS1 table and is used to link the terminal to the ATM Configuration Profile (ATM_PRFL) table entry for the terminal.
rcpt_prfl [bt_stringf(16)]	The profile ID used to link an ATM terminal to the Receipt configuration table. The data is configured on the ATM_DS1 table.
atm_prev_ttl_flg [bt_flag]	This indicator controls whether this ATM stores the current ATM totals into the Previous Day ATM Total Data Source. The ATMs previous day totals can be viewed from a read-only user interface.
atm_tm_ofst [bt_int32s]	The time difference (plus or minus in minutes) between this ATM terminal and the host systems processor location. The value in this field is added to the time to calculate the local time. The data is configured on the ATM_DS1 table.
rcpt_rqrd_prfl [bt_stringf(16)]	This field, configured on the ATM_DS1 table, contains the profile ID used to look up the receipt required information from the required receipt table ATM_RQ_RCPT.
term_inact_prfl [prfl_def 1.0]	The terminal inactivity profile identifies the inactivity values to be used for the specified ATM.
dep_bin_prfl [prfl_def 1.0]	The deposit BIN profile identifies the BIN files location to be used for the specified ATM for self service banking.
atm_emv_prfl [prfl_def 1.0]	The EMV profile identifies the EMV processing values to be used for the specified ATM.
atm_mac_prfl [prfl_def 1.0]	The Message Authentication Code (MAC) profile identifies the MAC processing values to be used for the specified ATM.
fast_cash_prfl [prfl_def 1.0]	The fast cash profile identifies the fast cash setup to be used for the specified ATM.
atm_sur_prfl [prfl_def 1.0]	The ATM surcharge profile identifies the surcharge setup to be used for the specified ATM. This field identifies the terminal surcharge group of which this terminal is a member and is passed to the authorization system where it is used for surcharge calculations.
stmnt_prnt_prfl [prfl_def 1.0]	The statment print profile identifies the statement print parameter setting to be used for the specified ATM.
ctx_prfl [bt_stringf(16)]	The context profile of the client attempting to store or retrieve context. This field is left-justified, upper case (containing any combination of alpha-numeric and special characters, but without any embedded spaces).
optnl_rcpt_ld_grp [bt_stringf(4)]	Printer operable load group for optional receipts. The data is configured on the ATM Static data table ATM_DS1.
optnl_rcpt_inop_gp [bt_stringf(4)]	Printer inoperable load group for optional receipts. This element is stored on the ATM static configuration table ATM_DS1.
atm_char_set [bt_stringf(1)]	This field defines the character set that is used by the ATM device. Default value is ASCII. Valid values are the following: 0 = ASCII 1 = AT&T EBCDIC 2 = HP EBCDIC 3 = IBM EBCDIC 4 = NCR EBCDIC 5 = DIEBOLD EBCDIC

Element (type)	Description
last_txn_stat_capable [bt_flag]	This field indicates the ATMs capability to support last transaction status processing. Valid values are: 0 - ATM does not support last transaction status, 1 - ATM does support last transaction status processing. Default value is 0.
pk_host_nam [bt_stringf(16)]	Name of Host Public Key owner. Set to Host.
epp_vrfy_flg [bt_stringf(1)]	This flag control whether the serial number of the Electronic PIN Pad (EPP) should be validated when performing an automatic public key load to an ATM device.
emv_capable [bt_flag]	This field indicates whether an ATM has EMV capabilities. This field is used by the ATM device handler to determine whether EMV configuration should be loaded to the ATM during a load sequence. Default value is false, no EMV capabilities.
load_group_area [bt_stringf(100)]	The ATM Load Group area defines up to 25, 4 digit load group identifiers to be loaded to an ATM. The array of load group identifiers are stored on the ATM_DS1 table. The base/default group has a value of 0000.
akds_cap_ind [bt_int32s]	This field indicates the AKDS capability of the ATMs Electronic PIN Pad (EPP). Valid values are: 0 - No AKDS Capability (default), 1 - Certificate, 2 - Signature.
atm_co_owned [bt_stringf(1)]	Indicates co-ownership of the ATM. Valid values are: 0 - Unknown (default), 1 - Co-owned ATM, 9 - Not Co-owned ATM.
atm_social_deprivation [bt_stringf(1)]	Indicates the socio-economic area where the ATM is located. Reference UK Link LIS5 interface mandate / UK Community Development Finance Initiatives (CDFIs). Valid values are 0 - Unknown (default), 1 - Located in an area of social deprivation, 9 - Not located in an area of social deprivation.
dkm_prfl [prfl_def 1.0]	The Dynamic Key Management profile identifies the DKM processing values to be used for the specified ATM. Used also as a key for ATM_DKM table.
forced_cutover_aud_ind [bt_flag]	This field indicates forced cutover audit indicator Default value is false
sur_amt_ld_grp [bt_stringf(4)]	Non-interactive surcharge load group. This field will be used to store the non-interactive surcharge load group for terminals configured with a non-interactive surcharge profile. The field should be blank filled if the terminal is not configured for non-interactive surcharging.
retrv_term_cnt_ind [bt_stringf(1)]	Indicates whether this terminal should get counts from the terminal before balancing and cutover of the terminal. Valid values are 0 - Do not get the counts, 1 - Get the counts, but do not stop cutover/balancing if terminal is offline, 2 - Get the counts, do not cutover/balance if the counts can't be retrieved.
term_descr [bt_stringf(40)]	Description used to identify the terminal. The data is configured on the ATM_DS1 table.
term_descr_mbyte [bt_binaryl(80)]	Multi-byte terminal description, used to identify the terminal. The data is configured on the ATM_DS1 table.
term_ownr_mbyte [bt_binaryl(44)]	Multi-byte name of the financial institution owning the terminal. The data is configured on the ATM_DS1 table.
term_adrs_mbyte [bt_binaryl(50)]	Multi-byte address which identifies the location of the terminal. This field is used as print information on the ATM customer receipt. The data is configured on the ATM_DS1 table.
term_city_mbyte [bt_binaryl(26)]	Multi-byte name of the city where the terminal is located. The data is configured on the ATM_DS1 table.

Element (type)	Description
term_state_mbyte [bt_binary(6)]	Multi-byte state, province, or political subdivision where the terminal is located. The data is configured in the ATM_DS1 table.
term_cnty_mbyte [bt_binary(6)]	Multi-byte county where the terminal is located. The data is configured on the ATM_DS1 table.
term_cntr_mbyte [bt_binary(6)]	Multi-byte country where the terminal is located. The data is configured on the ATM_DS1 table.
term_branch_mbyte [bt_binary(8)]	Multi-byte Branch ID for the branch in which the terminal is located. The data is configured in the ATM Static Data source ATM_DS1.
term_region_mbyte [bt_binary(8)]	Multi-byte Region ID for the region in which the terminal is located. The data is configured in the ATM Static Data source ATM_DS1.
postal_cde_mbyte [bt_binary(20)]	Multi-byte postal code.
epp_mfg [bt_stringf(2)]	The manufacturer of the EPP hardware. Valid values: 00 - Unknown, 01 - Wincor Nixdorf, 02 - NCR, 03 - Diebold, 04 - Fujitsu, 05 - De La Rue, 06 - Triton, 07 - Olivetti, 08 - Tidel.
home_site_ind [bt_char]	Indicates the home site of the device associated with the data record (i.e., which site is primary connection site) Valid values: Alpha-numeric character. The default value will be the Environment parameter named HOME_SITE_ID. If the parameter does not exist, the default will be a space.

ATM_EMV (1.0) (atmemd)

This data source contains the configuration related to ATM EMV processing.

[Audited] [Supports versioning]

OLTP: ATM_EMV_OLTP

Element (type)	Description
atm_emv_prfl*[prfl_def 1.0]	The EMV profile identifies the EMV processing values to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
emv_term_crd_cap [bt_binaryf(1)]	EMV Terminal Capabilities. Indicates the card data input capabilities of the terminal, as shown below. This field contains binary data. Byte 1 (Card Data Input Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 Reserved for future use 5 Reserved for future use 6 IC with contacts 7 Magnetic stripe 8 Manual key entry
emv_term_script [bt_binaryf(1)]	EMV Terminal Capabilities. Indicates the security capabilities of the terminal, as shown below. This field contains binary data. Byte 3 (Security Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 Combined DDA/CA generation 5 Reserved for future use 6 Card capture 7 Dynamic data authentication 8 Static data authentication
emv_term_cvm [bt_binaryf(1)]	EMV Terminal Capabilities. Indicates the CVM capabilities of the terminal, as shown below. This field contains binary data. Byte 2 (CVM Capability) EMV Bit Position

Element (type)	Description
	Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 No CVM Required 5 Enciphered PIN for offline verification 6 Signature (paper) 7 Enciphered PIN for online verification 8 Plaintext PIN for ICC verification

ATM_FAST_CASH (1.0) (atmfcd)

This data source contains the ATM configuration for fast cash withdrawal processing. This data source is accessed via the fast cash profile configured on the ATM profile configuration (ATM_PRFL).

[Audited] [Supports versioning]

OLTP: ATM_FAST_CASH_OLTP

Element (type)	Description
fast_cash_prfl*[prfl_def 1.0]	The fast cash profile identifies the fast cash setup to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
fast_cash_amt_1 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration Profile table (ATM_FAST_CASH).
fast_cash_amt_2 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration Profile table (ATM_FAST_CASH).
fast_cash_amt_3 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_amt_4 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_amt_5 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_amt_6 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_amt_7 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration table (ATM_FAST_CASH).

Element (type)	Description
fast_cash_amt_8 [amt 1.0]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_1 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_2 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_3 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_4 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_5 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_6 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_7 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).
fast_cash_cur_8 [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ATM Configuration table (ATM_FAST_CASH).

ATM_FLOW_CNTL (1.0) (atmmfd)

This data source controls the steps that are processed for a transaction acquired from a BASE24-es ATM device handler. A list of services will be defined for each transaction type. The order of the steps may be modified to suite the customers processing requirements.

[Audited] [Supports versioning]

OLTP: ATM_FLOW_CNTL_OLTP

Element (type)	Description
atmflw_seq_cntl*[bt_int32s]	This data element contains the number of a logical document within the Flow Control Configuration. The logical document contains all of the records of the latest service versions when the logical document was created.
atmflw_svc*[bt_stringf(40)]	This data element defines the service provided by the IS process. The service must match the name of an ATM registered service within the "IS".
atmflw_cond_stat*[bt_stringf(20)]	This data element contains the condition status of the ATM service that was just completed by the ATM Flow Control Manager. The first service initiated for a transaction, this data element contains spaces.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
atmflw_svc_cnt [bt_int16s]	This data element contains the number of services defined in the ATM service buffer. This data element is maintained via the user interface processing.
atmflw_svc_buf [bt_stringv(3920)]	This data element contains a list of services to be performed for the specified transaction type. This also defines the services to be added to a transaction based on the previous service performed and that services completion status. The services contained in this buffer must match the name of an ATM registered service within the "IS".

ATM_HOPR (1.0) (atmhpdp)

This data source contains the ATM Hopper Profile Configuration. This data is accessed via the hopper profile configured on the ATM Static Data (ATM_DS1).

[Audited] [Supports versioning]

OLTP: ATM_HOPR_OLTP

Element (type)	Description
hpr_prfl*[bt_stringf(16)]	The hopper configuration profile ID associated with an ATM. The hopper profile ID is stored in the ATM_DS1 table and is used to link the ATM to its hopper configuration defined in the Hopper Configuration table (ATM_HOPR).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dispense_algorithm [bt_int16s]	A code describing the dispense algorithm used for an ATM terminal. The data is stored on the ATM Configuration Properties table ATM_HOPR. ACI Worldwide supplies the following dispense algorithms: 0 - Least Number of Bills 1 - Threshold 2 - Configurable Dispense
hpr1_contents [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.

Element (type)	Description
hpr1_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr1_stnd_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr1_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr1_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E. All other device types use the space character.
hpr1_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr1_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr1_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 99999999.
hpr1_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.
hpr1_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr1_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr2_contents [bt_stringf(2)]	AA code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and

Element (type)	Description
	when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
hpr2_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr2_std_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr2_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr2_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
hpr2_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr2_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr2_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 99999999.
hpr2_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.
hpr2_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr2_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr3_contents [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information

Element (type)	Description
	on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
hpr3_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr3_std_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr3_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr3_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
hpr3_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr3_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr3_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 99999999.
hpr3_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.
hpr3_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr3_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.

Element (type)	Description
hpr4_contents [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
hpr4_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr4_std_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr4_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr4_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
hpr4_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr4_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr4_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 99999999.
hpr4_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.
hpr4_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr4_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense

Element (type)	Description
	Amount field for the specified hopper. Valid values are 0 through 999999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr5_contents [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
hpr5_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr5_stnd_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr5_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr5_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
hpr5_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr5_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr5_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 999999999.
hpr5_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.
hpr5_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 999999999. This field is only used if the Configurable Dispense Algorithm is selected.

Element (type)	Description
hpr5_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr6_contents [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
hpr6_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr6_stnd_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr6_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr6_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E. All other device types use the space character.
hpr6_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr6_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr6_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 99999999.
hpr6_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.
hpr6_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense

Element (type)	Description
	amount, bills from the hopper are used. Valid values are 0 through 999999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr6_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 999999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr7_contents [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
hpr7_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr7_std_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr7_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr7_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
hpr7_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr7_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr7_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 999999999.
hpr7_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.

Element (type)	Description
hpr7_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr7_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr8_contents [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table ATM_HOPR table. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
hpr8_unit_val [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr8_stnd_beg_amt [amt 1.0]	The standard amount of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table ATM_HOPR.
hpr8_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr8_cassette_map [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
hpr8_mcur_disp_ord [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table ATM_HOPR.
hpr8_threshold [amt 1.0]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ATM Hopper Configuration Profile table ATM_HOPR.
hpr8_nval_thrshld [amt 1.0]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one non-value item is dispensed from the non-value hopper. Valid values are 1 through 99999999.

Element (type)	Description
hpr8_max_bills [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The value is configured on the ATM Hopper Profile configuration table ATM_HOPR.
hpr8_strt_disp_amt [amt 1.0]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
hpr8_stop_disp_amt [amt 1.0]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
atm_max_bills [bt_int32s]	This data elements defines the maximum number of bills/coupons that can be dispensed by an ATM device. This describes the physical limitations of the ATMs bill dispenser.
atm_max_coins [bt_int32s]	This data elements defines the maximum number of coins that can be dispensed by an ATM device. This describes the physical limitations of the ATMs coin dispenser.

ATM_IFXDATA (1.0) (atmifx)

The IFX ATM specific data associated with the ES IFX device handler. This table is managed by the device handler. It is viewable read-only through the UI.

[Audited] [Supports versioning]

Element (type)	Description
term_id*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
mac_sec_obj_id [bt_stringf(36)]	The object ID for the Message Authentication Key. This value is set by the ES IFX device handler prior to sending down the key to the IFX ATM.
pin_sec_obj_id [bt_stringf(36)]	The object ID for the PIN Encryption Key. This value is set by the ES IFX device handler prior to sending down the key to the IFX ATM.
mstr_sec_obj_id [bt_stringf(36)]	The object ID for the Master Key. This value is set by the ES IFX device handler prior to sending down the key to the IFX ATM.
term_obj_id [bt_stringf(36)]	The object ID for the terminal object. This value is set by the ES IFX device handler when a response to a Terminal Object Add message (TermObjAddRq) is received. This is NOT the terminal ID. It is the Id of an object added into the ATM software.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

ATM_INACT (1.0) (atmind)

This data source contains configuration data for ATM channel inactivity processing. This data is accessed through the inactivity profile located on the ATM Configuration Profile (ATM_PRFL).

[Audited] [Supports versioning]

OLTP: ATM_INACT_OLTP

Element (type)	Description
term_inact_prfl*[prfl_def 1.0]	The terminal inactivity profile identifies the inactivity values to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
inact_tmouts_alwd [bt_int32s]	This data element tracks the number of consecutive timeouts that occur within a transaction. Once this consecutive threshold is reached a log event is generated and the counter is reset back to 0. This threshold controls when an event will be generated indicating that an ATM is exceeding the normal number of consecutive timeouts. This data element applies to all time periods (peak and non-peak). This data is configured on the ATM Inactivity Profile Table (ATM_INACT).
inact_wrkd_strt_pk [bt_stringf(4)]	The start of the workday intertransaction peak period represented as HHMM. This time defines the start of the period when the workday peak intertransaction time is used.
inact_wrkd_end_pk [bt_stringf(4)]	The end of the workday intertransaction peak period represented as HHMM. This time defines the end of the period when the workday peak intertransaction time is used.
inact_wrkd_peak [bt_int32s]	The time interval, in seconds, for workday, peak transaction periods, which the ATM device handler will use for intertransaction timers. If no transaction is received for this duration, an event is logged. This data is configured on the ATM Inactivity Profile Table (ATM_INACT).
inact_wknd_strt_pk [bt_stringf(4)]	The start of the weekend intertransaction peak period represented as HHMM. This time defines the start of the period when the weekend peak intertransaction time is used.
inact_wkend_end_pk [bt_stringf(4)]	The end of the weekend intertransaction peak period represented as HHMM. This time defines the end of the period when the weekend peak intertransaction time is used.
inact_wknd_peak [bt_int32s]	The time interval, in seconds, for weekend, peak transaction periods, which the ATM device handler will use for intertransaction timers. If no transaction is received for this duration, an event is logged. This data is configured on the ATM Inactivity Profile Table (ATM_INACT).
inact_non_peak [bt_int32s]	The time interval, in seconds, for non-peak transaction periods, which the ATM device handler will use for intertransaction timers. If no transaction is received for this duration, an event is logged. This data is configured on the ATM Inactivity Profile table (ATM_INACT).

ATM_MAC (1.0) (atmmcd)

This data source contains the configuration related to ATM Message Authentication Code (MAC) processing.

[Audited] [Supports versioning]

OLTP: ATM_MAC_OLTP

Element (type)	Description
atm_mac_prfl*[prfl_def 1.0]	The Message Authentication Code (MAC) profile identifies the MAC processing values to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mac_data_typ [bt_stringf(1)]	The character set that the data to be authenticated is in. The data is configured in the ATM Device Security table (ATM_MAC). Valid values are: 0 = ASCII 1 = AT&T EBCDIC 2 = HP EBCDIC 3 = IBM EBCDIC 4 = NCR EBCDIC 5 = DIEBOLD EBCDIC The default value is 0.
mac_sol_stat [bt_stringf(1)]	A code indicating whether Solicited Status Messages will have a MAC code authenticated. The data is stored on the ATM Device Security table (ATM_MAC). Valid values are: 0 = Not configured 1 = Authenticate Solicited Status Messages The default value is 0.
mac_auth_method [bt_stringf(1)]	This field determines what type of calculation will be done on the fields in the message. The data is stored in the ATM Device Security table (ATM_MAC). For Selective Field MACing, the fields included in the data string to be authenticated are configured via the Field Selection Tables in the Device Handler. Valid values are: 0 = Full Message Authentication 1 = Selective Field Message Authentication The default value is 0.

ATM_MBYTE_XLATE (1.0) (atmxds)

This data source contains the configuration used to translate multi-byte character data into an ATM control characters that can be transmitted to the ATM.

[Audited] [Supports versioning]

OLTP: ATM_MBYTE_XLATE_OLTP

Element (type)	Description
term_typ*[bt_stringf(2)]	A code indicating the type of terminal. Valid values are 01 - NCR 5xxx 02 - Diebold 10xx 03 - Wincor NDC 04 - Wincor DDC 05 - Triton 06 - Tidel
load_prfl*[bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it.
media_typ*[bt_stringf(2)]	Defines the type of media that is being used. Valid values are: "00" - receipt, "01" - screen.
media_lang_id*[bt_stringf(5)]	The ID of the language bank within the ATM where the character set for the language is defined. This ID must correspond to the correct language bank in the ATM of the screens may be illegible. This field has 2 uses: Map native language identifier from the ATM to an ISO-639 value. Used to

Element (type)	Description
	determine data for screens based on ISO-639 value found in the Language TDE.
multi_byte_chars*[bt_binaryf(6)]	This field contains the Hex string representation of the multi-byte character.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
atm_char_set_bytes [bt_binaryf(2)]	Equivalent of multi-byte character in ATM coordinates character set.
char_set_designator [bt_binaryf(6)]	Complete associated escape sequence for the ATM coordinate character.
multi_byte_xlate_descr [bt_stringf(80)]	Multi-byte character translation description.

ATM_OPER (1.0) (atmopd)

The Operator ID data source is used to verify a bank agent has access to the cash vault while rear balancing a Diebold ATM.

[Audited] [Supports versioning]

OLTP: ATM_OPER_OLTP

Element (type)	Description
oper_grp_id*[bt_stringf(2)]	The Operator Group ID for the Operator ID File. This field may be any two characters.
oper_id*[bt_int32s]	The Operator ID. The data is configured on the Diebold ATM Operator ID table ATM_OPER. The table is accessed by the ATM device handler only during administrative transactions for Diebold ATM devices.
term_id*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
oper_cash_access [bt_char]	A flag indicating whether or not the operator has access to the cash vault. If the value is Y, access is allowed. Otherwise access is not allowed.

ATM_OP_CDE (2.0) (atmopc)

This table contains mapping information to determine the appropriate processing code and transaction setup that needs to be performed by the ATM device handler based on the Op Code buffer received in the message from the ATM.

[Audited] [Supports versioning]

OLTP: ATM_OP_CDE_OLTP

Element (type)	Description
term_typ*[bt_stringf(2)]	A code indicating the type of terminal. The data is configured on the ATM_DS1 table. Valid values are 01 - NCR 5xxx 02 - Diebold 10xx 03 - Wincor NDC 04 - Wincor DDC 05 - Triton 06 - Tidel
op_cde_buf*[bt_stringf(8)]	This field contains up to 8 bytes of the Op Code buffer received in the message from the ATM device. It is used to determine the appropriate processing code and setup processing that needs to be performed.
load_prfl*[bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it. The data is configured on the ATM_DS1 table. The data is also used as a key to the ATM Configuration table (ATM_CONF) to retrieve load data during the ATM load process.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
proc_cde [proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
atmopcd_task_cnt [bt_int16s]	This data element contains the number of tasks defined in the ATM Op Code Task buffer. This data element is maintained by the user interface.
atmopcd_task_buf [bt_stringv(3900)]	This field contains the setup tasks to be performed for this transaction type. This field is organized into value pairs of 60 bytes, which are defined as follows: Task, length 40; parameter, length 20 (The parameter can be used to stored additional data that needs to be passed to the setup task for processing). This field will contain a maximum of 65 task/parameter pairs.

ATM_PEAK_LOAD (1.0) (atmpkd)

The peak load (Transaction Time Windows) configuration profile determines transitions between peak and standard load groups at the ATM using the holidays for the specified institution. The profile controls the types of transactions performed at the terminal during specific times of the day and days of the week, allowing restriction of time-consuming transactions to off-peak time periods. This data source is used by the ATM Batch Manager and the ATM C++ device handlers to manage these load groups.

[Audited] [Supports versioning]

OLTP: ATM_PEAK_LOAD_OLTP

Element (type)	Description
atm_peak_load_prfl*[bt_stringf(16)]	This field contains the peak load profile used by the ATM. This profile is stored on the ATM_DD1 data source. This profile is optional and should only be filled for ATMs utilizing peak load (Transaction Time Windows) processing.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
hol_stnd_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.

Element (type)	Description
hol_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for holidays.
hol_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for holidays, ending a peak period.
hol_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for holidays.
hol_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for holidays.
hol_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for holidays, ending a peak period.
hol_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for holidays.
sun_stnd_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.
sun_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for specified day of the week.
sun_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
sun_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
sun_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for a specified day of the week.
sun_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
sun_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
mon_stnd_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.
mon_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for specified day of the week.

Element (type)	Description
mon_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
mon_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
mon_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for a specified day of the week.
mon_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
mon_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
tues_std_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.
tues_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for specified day of the week.
tues_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
tues_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
tues_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for a specified day of the week.
tues_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
tues_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
wed_std_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.
wed_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for specified day of the week.
wed_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.

Element (type)	Description
wed_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
wed_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for a specified day of the week.
wed_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
wed_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
thurs_stnd_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.
thurs_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for specified day of the week.
thurs_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
thurs_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
thurs_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for a specified day of the week.
thurs_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
thurs_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
fri_stnd_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.
fri_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for specified day of the week.
fri_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
fri_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.

Element (type)	Description
fri_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for a specified day of the week.
fri_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
fri_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
sat_stnd_load_grps [bt_stringf(20)]	Contains 1 or more load groups (a maximum of 5) to be loaded to the ATM during non-peak timeframes. The load groups are loaded based on the timeframes specified in the ATM Peak Load Profile.
sat_peak1_strt_tm [bt_stringf(4)]	Contains the first peak load start time. This is used by the ATM device handler to determine when to load the first peak load group(s) to the ATM for specified day of the week.
sat_peak1_end_tm [bt_stringf(4)]	Contains the first peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
sat_peak1_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the first peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.
sat_peak2_strt_tm [bt_stringf(4)]	Contains the second peak load start time. This is used by the ATM device handler to determine when to load the second peak load group(s) to the ATM for a specified day of the week.
sat_peak2_end_tm [bt_stringf(4)]	Contains the second peak load end time. This is used by the ATM device handler to determine when to load the standard load group(s) to the ATM for a specified day of the week, ending a peak period.
sat_peak2_load_grps [bt_stringf(20)]	Contains the peak load groups that are loaded to the ATM during the second peak period. This field holds up to 5, 4 digit load group identifiers used for a specified day of the week.

ATM_PREV_TTL (3.0) (atmprv)

ATM DH Previous Days Totals Table. The data in this table includes hopper amounts and transaction counts and amounts. The table is updated at ATM terminal cutover time if previous days totals are configured in the application configuration.

[Audited] [Supports versioning]

Element (type)	Description
term_id*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
post_dat [yyyyymmdd 1.0]	The current settlement date.

Element (type)	Description
hpr1_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr1_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr1_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr1_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr1_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr1_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr2_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr2_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr2_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr2_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr2_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr2_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr3_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.

Element (type)	Description
hpr3_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr3_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr3_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr3_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr3_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr4_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr4_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr4_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr4_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr4_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr4_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr5_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr5_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.

Element (type)	Description
hpr5_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr5_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr5_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr5_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr6_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr6_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr6_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr6_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr6_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr6_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr7_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr7_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr7_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.

Element (type)	Description
hpr7_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr7_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr7_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
hpr8_amt_beg [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr8_amt_incr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr8_amt_decr [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr8_amt_out [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ATM_DD1 table. This value is maintained by the ATM device handler.
hpr8_amt_end [amt 1.0]	The amount of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ATM_DD1 table. This value is managed by the ATM device handler.
hpr8_cur_cde [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
envl_deposit_cnt [bt_int32s]	The total number of unverified deposit envelopes received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
envl_deposit_amt [bt_int64s]	The total value of envelope deposits into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
cash_deposit_cnt [bt_int32s]	The total number of cash deposits received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
cash_deposit_amt [bt_int64s]	The total value of cash deposited into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
cmrcl_deposit_cnt [bt_int32s]	The total number of commercial deposits (e.g., from Securomatic devices) received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored

Element (type)	Description
	on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
cmrcl_deposit_amt [bt_int64s]	The total value of commercial deposits into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
payments_cnt [bt_int32s]	The total number of payment envelopes received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
payments_amt [bt_int64s]	The total value of payment transactions performed at an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
msgs_to_fiid_cnt [bt_int32s]	The total number of messages to the financial institution received since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
checks_cnt [bt_int32s]	The total number of checks received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
checks_amt [bt_int64s]	The total value of the checks deposited into an ATM, during a business day. The amount is recorded on the ATM_DD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
log_only_cnt [bt_int32s]	The total number of log only transactions completed since the ATM terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
cards_retain_cnt [bt_int32s]	The total number of consumer cards retained by the ATM since the terminal was last balanced. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed. The value in this field is managed by the ATM device handler.
term_debits [bt_int64s]	The unverified amount of terminal debits since the terminal was last balanced. The amount in this field consists of debits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us and not-on-us payment-enclosed transactions On-us and not-on-us transfers On-us and not-on-us payments between accounts The value in this field is stored in the ATM_DD1 table and is managed by the ATM device handler.
term_credits [bt_int64s]	The total amount of terminal credits since the terminal was last balanced. The amount in this field consists of credits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us withdrawals On-us and not-on-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the TERM-CR amount. On-us and not-on-us transfers On-us and not-on-us payments between accounts On-us and not-on-us non-currency dispense transactions The value in this field is stored on the ATM_DD1 table and is managed by the ATM device handler.
on_us_debits [bt_int64s]	The total amount of on-us debits since the ATM terminal was last balanced. The amount in this field consists of debits from the customers point of view. Transaction amounts

Element (type)	Description
	are added to the balance in this field for: On-us withdrawals On-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the ON-US-DB amount. On-us transfers On-us payments between accounts On-us non-currency dispense transactions The value in this field is managed by the ATM device handler. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed.
on_us_credits [bt_int64s]	The total amount of on-us credits since the ATM terminal was last balanced. The amount in this field consists of credits from the customers point of view. Transaction amounts are added to the balance in this field for On-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us payment enclosed transactions On-us transfers On-us payments between accounts The value in this field is managed by the ATM device handler. The data is stored on the ATM_DD1 table when an administrative balancing transaction is performed.
term_currency [crncy_cde 1.0]	A code indicating the type of currency used to represent the terminals amount fields. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code). The data is configured on the ATM_PRFL table.
ssb1_check_cnt [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb1_check_amt [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb1_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb2_check_cnt [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb2_check_amt [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb2_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb3_check_cnt [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb3_check_amt [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb3_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for

Element (type)	Description
	Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb4_check_cnt [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb4_check_amt [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
ssb4_dep_seq_num [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ATM_DD1 table. The value is managed by the ATM device handler.
last_settle_tm [ts 1.0]	The date and time an ATM was last balanced using an administrative balancing function. The data is stored on the ATM_DD1 table and is managed by the ATM device handler.
user_txt_area [bt_stringf(70)]	This field is for informational only data. It is configured on the ATM_DD1 table.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
term_bna_rjct_notes_cnt [bt_int32s]	The total number of notes rejected (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
term_bna_vault_notes_cnt [bt_int32s]	The total number of notes vaulted (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
term_bna_escr_notes_cnt [bt_int32s]	The total number of notes escrowed (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
term_bna_rtrn_notes_cnt [bt_int32s]	The total number of notes returned (as last reported by the ATM terminal). The data is stored on the ATM_DD1 table. Used in administrative balancing transactions. The value in this field is managed by the ATM device handler.
prvt_use_array [bt_stringf(500)]	Contains an buffer in which Tag/Length/Value (TLV) entries are stored. The usage of this field is device dependent, meaning the valid tags within this buffer are defined by each device handler.

ATM_PRFL (3.0) (atmprd)

ATM Device Handler Configuration Profile Table. The data here is static data that may be specified at an ATM profile level.

[Audited] [Supports versioning]

OLTP: ATM_PRFL_OLTP

Element (type)	Description
cnfg_prfl*[bt_stringf(16)]	The configuration profile ID of an ATM terminal. The value is stored on the ATM_DS1 table and is used to link the terminal to the ATM Configuration Profile (ATM_PRFL) table entry for the terminal.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
atm_oar_ind [bt_stringf(1)]	Indicates whether or not the ATM terminal can support Open Account Relationship selection. The data is configured on the ATM Configuration Profile table ATM_PRFL. The ATM device handler process will place this value in the transaction request. Standard OAR look-up, retrieving account numbers (and when available, account descriptions). Valid values are: 0 = Not configured 1 = Terminal supports Open Account Relationship processing. The default value is 0.
oar_max_accts [bt_int32s]	This defines the maximum number of accounts that can be returned in an OAR transaction response. The number of accounts returned will vary by ATM type.
oar_acq_cap [bt_stringf(1)]	This field contains the Open Account Relationship (OAR) acquirer capability. This field controls how the issuer will return OAR account information. Valid values are 0 - Send both from and to accounts (when applicable). 1 - One side at a time (only send from or to in one send from issuer).
sharing_group [bt_stringf(24)]	The ATM sharing group defined for an ATM terminal. The data is configured in the ATM Configuration Profile table ATM_PRFL. It is passed to the authorization system where it is used to determine if the transaction is allowed.
dflt_dpst_bin [bt_stringf(1)]	The depository bin to use to retain the check. This element is only used if Self-Service Banking (SSB) is enabled in the ATM system.
cust_bal_presented [bt_stringf(1)]	A control flag indicating the type of balance should be displayed. The flag is recorded on the ATM Configuration Profile ATM_PRFL table and is managed through the ES UI. Possible values are Both ledger and available balance = 0 Ledger balance only = 1 Available Balance only = 2
cust_bal_loc [bt_stringf(1)]	A control flag indicating the location where the customer balance should be displayed. The flag is recorded on the ATM Configuration Profile ATM_PRFL table and is managed through the ES UI. Possible values are Both screen and receipt = 0 On the screen only = 1 On the receipt only = 2
mult_tran_per_rcpt [bt_stringf(1)]	Indicates whether or not the ATM terminal can support multiple transaction per receipt. The data is configured on the ATM Configuration Profile table ATM_PRFL. Valid values are: 0 = No 1 = Yes The default value is 0.
max_lines_per_rcpt [bt_int32s]	The maximum number of printed lines on a receipt. The data is configured in the ATM Configuration Profile table ATM_PRFL.
optional_rcpt_typ [bt_stringf(1)]	A code which indicates how cardholder-selected optional receipt processing should work. Terminal State and Screen download configuration determines specifics of the implementation (prompting once per session or on individual transactions). Note - when this feature is enabled, receipts are always printed on transactions involving a partial dispense. Valid values are: 0 = Not configured (always use static configuration settings in the database). 1 = Use static configuration settings in the database if the printer is operable. The cardholder is given an option to cancel if the printer is inoperable and printing is configured for the transaction. 2 = The cardholder controls receipt choice on all approved transactions. If the transaction is denied, use static configuration settings in the database. 3 = The cardholder controls receipt choice on all approved and denied transactions. The default value is 0.

Element (type)	Description
avail_dep_typ [bt_stringf(1)]	The available depository types configured at an ATM. Possible types are Standard = 0 Commercial = 1 Both standard and commercial = 2 This data is stored in the configuration profile table and is used during deposit type transactions.
local_pin_vrfy_typ [bt_stringf(1)]	A code, configured on the ATM Configuration Profile table ATM_PRFL, indicating when the ATM device can perform PIN verification at the ATM, without the involvement of the authorization system. The ATM device must have PIN verification capability to perform local PIN verification, and the ATM configuration file must be configured for local PIN verification. The value in this field is used as input to a fraud prevention check for financial and administrative transactions whose PIN has been verified locally by the terminal. Valid values are: 0 = Not configured 1 = Allow on-us local verification 2 = Allow any local verification (on-us / not-on-us)
wdl_amt_typ [bt_flag]	This field indicates whether the amount contains a decimal or is represented as a whole amount. Valid values are: 0 - Whole Amount no decimal, 1 - Amount includes a decimal.
ncd_route_num [bt_stringf(11)]	The routing ID used for non-currency dispense transactions. The data is configured on the ATM_DS1 table and is sent to the authorization process with transaction requests which are non-currency transactions.
ncd_close_on_msds [bt_stringf(1)]	A flag indicating whether the ATM should be closed if a misdispense occurs when dispensing non-currency items. The data is configured on the ATM Configuration Profile table ATM_PRFL. Valid values are: 0 = Not configured 1 = Close the ATM The default value is 0.
ncd_non_val_checking [bt_stringf(1)]	A flag determining if non-value items may be dispensed when a transaction is for a checking account type. The data is configured on the ATM Configuration Profile table ATM_PRFL. Valid values are: 0 = Not allowed 1 = Allowed The default value is 0.
ncd_non_val_savings [bt_stringf(1)]	A flag determining if non-value items may be dispensed when a transaction is for a savings account type. The data is configured on the ATM Configuration Profile table ATM_PRFL. Valid values are: 0 = Not allowed 1 = Allowed The default value is 0.
ncd_non_val_credit [bt_stringf(1)]	A flag determining if non-value items may be dispensed when a transaction is for a credit account type. The data is configured on the ATM Configuration Profile table ATM_PRFL. Valid values are: 0 = Not allowed 1 = Allowed The default value is 0.
lrg_msg_max_size [bt_int32s]	A value indicating the maximum size of a message for an ATM. The default is 600 bytes. To support large messages this field should be set to 2032 bytes. The data is stored on the ATM Configuration Profile table ATM_PRFL.
dial_up_fail_act [bt_stringf(1)]	A flag indicating the disposition of transactions involving Message Failures processing transaction Function Commands under the Dial-up ASYNC protocol. The element is stored on the ATM Configuration Profile table ATM_PRFL. Possible values are 0 - Do not reverse when no terminal ACK has been received. 1 - Reverse immediately when no terminal ACK has been received. 2 - Reverse on the next transaction when no terminal ACK has been received.
adm_n_phone_num [bt_stringf(20)]	The Administrative Contact phone number for an ATM. The element may be used to record a phone number for the person(s) responsible for administrating the terminal. The data is recorded on the ATM Configuration Profile table ATM_PRFL.
inst_route_num [bt_stringf(11)]	The institution routing ID used for routing transactions in the authorization system. The element is stored on the ATM_DS1 table.
alt_route_num [bt_stringf(11)]	The alternate routing number for an ATM. The alternate number is used if the transaction can not be routed using the primary routing number. This element is used only on the ATM Configuration Profile table (ATMRPFL).

Element (type)	Description
term_protocol [bt_stringf(1)]	Indicates which line protocol is being used for communications with this terminal. Valid values are: A = ASYNC P = X25 PVC X = X25 SVC S = SNA T = TCP/IP The default value is T. The data is configured on the ATM Configuration Profile table ATM_PRFL.
term_sub_protocol [bt_stringf(1)]	Indicates which messaging protocol is being used for communications with this terminal. Valid values are: D = Dial-Up connection P = Permanent connection The default value is P. The data is configured on the ATM Configuration Profile table (ATM_PRFL).
term_loc_ind [bt_stringf(1)]	The Terminal Location Indicator indicates the location of the terminal. Valid values are: 0 = On premises of card acceptor facility 1 = Off premises of card acceptor facility (remote location). The default value is 0. The data is configured on the ATM Configuration Profile table ATM_PRFL.
term_currency [crncy_cde 1.0]	A code indicating the type of currency used to represent the terminals amount fields. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code). The data is configured on the ATM_PRFL table.
term_mgt_ext_conn [bt_stringf(16)]	The external connection ID for terminal management for the ATM. This is the message destination for messages outbound from the ATM device handler to the ATM device. It is required because in a large terminal population, the terminals may be spread across multiple ICE-XS processes, for example.
wrkday_strt_pk_id [bt_stringf(4)]	This element has been deprecated and should not be used.
wrkday_end_pk_id [bt_stringf(4)]	This element has been deprecated and should not be used.
wkend_strt_pk_id [bt_stringf(4)]	This element has been deprecated and should not be used.
wkend_end_pk_id [bt_stringf(4)]	This element has been deprecated and should not be used.
disp_algo_fail_act [bt_stringf(1)]	A flag indicating the disposition of transactions denied from the dispense algorithm. The element is stored on the ATM Configuration Profile table ATM_PRFL. Possible values are 0 - Device Handler will deny the current transaction and prompt for another transaction (default). 1 - Device Handler will redirect to a new transaction specifying the recommended cash amount.
dial_up_call_mgmt [bt_stringf(1)]	A flag indicating whether the middleware or Device Handler controls the call disconnect under the Dial-up protocol. The element is stored on the ATM Configuration Profile table ATM_PRFL. Possible values are "0" - middleware auto disconnect, "1" - middleware auto disconnect with override, "2" - Device Handler control of the call disconnect).

ATM_RECEIPT (1.0) (atmrctd)

The ATM Receipt Template Table. The table contains the templates for all receipts generated by the ATM devices.

[Audited] [Supports versioning]

OLTP: ATM_RECEIPT_OLTP

Element (type)	Description
rcpt_prfl*[bt_stringf(16)]	The profile ID used to link an ATM terminal to the Receipt configuration table. The data is configured on the ATM_DS1 table.
rcpt_lang*[bt_stringf(5)]	This field indicates the Language Code indicator associated with a receipt template. The data is configured in the Receipt table (ATM_RECEIPT). Valid values are defined by the ISO-639 Language Code standard.
rcpt_typ*[bt_stringf(4)]	The receipt type field indicates the type of receipt, based on the transaction type (e.g., Administrative, Financial, Deposit, etc.). The value is configured on the Receipt table (ATM_RECEIPT). It is used to look up receipt templates for transaction receipts. Valid values are HDR, BODY and TRLR.
rcpt_sub_typ*[bt_stringf(2)]	The receipt type field indicates the type of receipt, based on the transaction code (e.g., 10, 20, 21, 30, etc.). The value is configured on the Receipt table (ATM_RECEIPT). It is used along with the rcpt_typ to look up receipt templates for transaction receipts. Valid values are defined in the ES UI. Only valid values may be selected in the UI.
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
rcpt_from_acct_typ*[bt_stringf(2)]	A code defining the From account type for the key to the Receipt table (ATM_RECEIPT). A wild card character (**) may be used as well as a specific account type.
rcpt_to_acct_typ*[bt_stringf(2)]	A code defining the To account type for the key to the Receipt table (ATM_RECEIPT). A wild card character (**) may be used as well as a specific account type.
rcpt_prnt_typ*[bt_stringf(1)]	The Receipt Printer Type element defining the type of printer on which a receipt is to be printed. The data is configured as a key element on the Receipt table (ATM_RECEIPT). This field may contain a wildcard character when used on the Receipt table. Valid values are: * = Wildcard (Consumer/Journal) 1 = Consumer Printer 2 = Journal Printer 3 = Digital Audio Signal (DAS) 4 = Depository Printer 5 = Generic Printer
rcpt_prnt_sub_typ*[bt_stringf(1)]	The Receipt Printer Subtype element defines the type of printing technology used by a printer. The data is configured as a key element on the Receipt table (ATM_RECEIPT). This field may contain a wildcard character when used on the Receipt table. Valid values are: * = All (wildcard) 1 = Standard 2 = Thermal
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rcpt_tmpl_data [bt_binaryv(3000)]	The receipt template data stored in the Receipt Template table (ATM_RECEIPT). The data defines the format of a transaction receipt. This data is stored in Tag, Length, Value (TLV) format. The length is stored as a binary value.

ATM_REQ_RCPT (1.0) (atmqrd)

This is the ATM Required Receipt data source. For any given Receipt Profile and Acquirer Transaction Code, this table defines whether or not a receipt is required. The flags are broken down by Receipt printer and Journal printer. Additionally, the requirement is defined for approved and declined transactions.

[Audited] [Supports versioning]

OLTP: ATM_REQ_RCPT_OLTP

Element (type)	Description
rcpt_prfl*[bt_stringf(16)]	The profile ID used to link an ATM terminal to the Receipt configuration table. The data is configured on the ATM_DS1 table.
rcpt_acq_txn_cde*[bt_stringf(6)]	The Acquirer Transaction Code used as a part of the key to the Receipt Required (ATM_REQ_RCPT) table.
rcpt_txn_aprv_ind [bt_int16s]	An indicator, configured on the Receipt configuration table (ATM_REQ_RCPT), that determines whether a consumer receipt must be printed at the ATM for approved transactions. Possible values are 0 - Printing not required, 1 - Printing required, 2 - Optional.
rcpt_txn_deny_ind [bt_int16s]	An indicator, configured on the Receipt configuration table (ATM_REQ_RCPT), that determines whether a consumer receipt must be printed at the ATM for denied transactions. Possible values are 0 - Printing not required, 1 - Printing required, 2 - Optional.
jrnل_txn_aprv_ind [bt_int16s]	An indicator, configured on the Receipt configuration table (ATM_REQ_RCPT), that determines whether a journal receipt must be printed at the ATM for approved transactions. Possible values are 0 - Printing not required, 1 - Printing required, 2 - Optional.
jrnل_txn_deny_ind [bt_int16s]	An indicator, configured on the Receipt configuration table (ATM_REQ_RCPT), that determines whether a journal receipt must be printed at the ATM for denied transactions. Possible values are 0 - Printing not required, 1 - Printing required, 2 - Optional.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

ATM_RQUID (1.0) (ifxrqd)

The table is used by the ES IFX device handler and is managed solely by the device handler - it is NOT viewable through the UI. The RqUID (IFX document ReQuest Unique Identifier) is used for duplicate checking.

[Audited] [Supports versioning]

Element (type)	Description
rquid_id*[bt_stringf(36)]	The Request Unique Identifier (RqUID) from the service wrapper of an IFX document.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rquid_user_data [bt_stringf(50)]	This field is for informational only data. It is configured on the ATM_RQUID table.

ATM_SSB_BIN (1.0) (ssbbnd)

This data source defines the terminal check sorting mechanism based on the check issuer and the check amount. A record will exist for each unique sorting mechanism within a particular institution.

[Audited] [Supports versioning]

OLTP: ATM_SSB_BIN_OLTP

Element (type)	Description
dep_bin_prfl* [prfl_def 1.0]	The deposit BIN profile identifies the BIN files location to be used for the specified ATM for self service banking.
inst_id_num* [bt_stringf(11)]	The institutions transit/routing number or issuer identification number unique to the institution. This field is left justified (containing only numeric characters).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
thrld_chk_amt [bt_int64s]	The threshold check amount is the amount to which the check amount is compared to determine the check depository bin. If the check amount is less than the threshold check amount, the below-threshold check depository bin is used, otherwise the threshold check depository bin is used. Default value is 0.
thrld_chk_amt_cur_cde [crncy_cde 1.0]	The currency represented in the threshold check amount. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
blw_thrld_chk_dep_bin [bt_stringf(1)]	This data element identifies the depository BIN when below the threshold.
thrld_chk_dep_bin [bt_stringf(1)]	This data element identifies the self-service banking threshold depository BIN.

ATM_SSB_BNA (1.0) (ssbbna)

This data source contains a record for every ATM. The ATM device handler manages this file, populating it with BNA Notes Definition Status Message Data. This data is used in determining the context of BNA Transaction Request data and Status Message data.

[Audited] [Supports versioning]

Element (type)	Description
term_id* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
rec_typ [bt_stringf(2)]	A code indicating the type of terminal. The data is configured on the ATM_SSB_BNA table. Valid values are 01 - NCR 5xxx
bna_stat_data [bt_binaryv(1900)]	This data element contains the Bunch Note Acceptor notes definition data.

ATM_SSB_CPL (1.0) (ssbcpl)

This data source contains data to support Check Proof processing in self-service banking. This data source will contain a record for every check processed by the ATM. This file can be printed out at the ATM via an administrative transaction and if used by the financial institution during check settlement processing.

[Audited] [Supports versioning]

Element (type)	Description
term_id* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
depository_bin* [bt_stringf(1)]	This data element contains the depository bin value, used in self-service banking.
dep_bin_seq_num* [bt_int32s]	The terminal depository bin sequence number from the check bin. This field contains a bin sequence number from the ATM_DD1 table, value ranging from 0001 to 9999. The value is managed by the ATM device handler.
chk_micr_data* [bt_stringf(70)]	This data element contains the MICR data for self-service bank processing of checks.
tran_ent_ts [ts 1.0]	The transaction entry time.
chk_amt [bt_int64s]	The value of the check for the transaction.
chk_amt_cur_cde [crncy_cde 1.0]	The currency code associated with the check.
chk_stat [bt_stringf(1)]	This data element contains the status of a check that is processed in a self-service banking environment. Valid values are: 0 - Status ok, 1 - Unapproved abnormal check retain.

ATM_STATE_SCRN (2.0) (atmssd)

This table contains data to determine and set the next ATM state and screen information in a response to the ATM based upon the terminal type, action code and satisfying the specified conditions. This table is used when building an ATM response message.

[Audited] [Supports versioning]

OLTP: ATM_STATE_SCRN_OLTP

Element (type)	Description
term_typ* [bt_stringf(2)]	A code indicating the type of terminal. The data is configured on the ATM_DS1 table. Valid values are 01 - NCR 5xxx 02 - Diebold 10xx 03 - Wincor NDC 04 - Wincor DDC 05 - Triton 06 - Tidel
load_prfl* [bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it. The data is configured on the ATM_DS1 table. The data is also used as a key to the ATM Configuration table (ATM_CONF) to retrieve load data during the ATM load process.
atm_act_cde* [bt_stringf(4)]	This field contains the internal action code value used by the ATM device handler for internal processing.
state_scrn_seq_num* [bt_int16s]	This field identifies a sequence to be followed when determining the next state and screen for a given terminal type and action code. For a given terminal type and action code the ATM DH starts with sequence 0 and continues (incrementing by 1) until a record is found where all of the specified conditions in the condition list are satisfied.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
act_cde_descr [bt_stringf(80)]	This field describes the action code that is contained on this record. It describes the action that resulted in the ATM devices next state and screen.
cond_descr [bt_stringf(80)]	This field contains a description of the next state and screen that has been chosen in device handler processing. This data is used to help understand the condition (state/screen) that is being set.
state_scrn_cond [bt_stringf(400)]	This field specifies the conditions that must be met to use the state and screen information configured in this record. This field contains 10, 40 character conditions. Configuration of one or more conditions is optional.
state_num [bt_stringf(3)]	This field specifies the next ATM device state to be set based on the terminal type, action code and conditions.
suppress_rcpt [bt_flag]	This field specifies whether receipt printing should be suppressed based on the terminal type, action code and conditions. The default is false (not suppressed).
card_capture [bt_flag]	This field specifies whether the card should be captured based on the terminal type, action code and conditions. The default is false (do not capture the card).
media_act [bt_int16s]	This field identifies they type of media action that needs to be taken for a depository transaction. Valid values are: 0 - No media action required (default), 1 - Return media to the cardholder, 2 - Retain media in the ATM vault.
state_scrn1_func_id [bt_stringf(1)]	This field identifies the function identifier that is to be sent to the ATM. This identifier instructs the ATM to perform a function. Function identifiers for NCR devices are all the same value for up to 7 entries, while Diebold function identifiers are different across the 7 entries.
state_scrn1_scrn_num [bt_stringf(3)]	This field defines the screen information to be displayed at the ATM for the specified function identifier.
state_scrn1_task [bt_stringf(40)]	This field identifies the setup task that needs to be performed for the specified function identifier.
state_scrn2_func_id [bt_stringf(1)]	This field identifies the function identifier that is to be sent to the ATM. This identifier instructs the ATM to perform a function. Function identifiers for NCR devices are all the same value for up to 7 entries, while Diebold function identifiers are different across the 7 entries.
state_scrn2_scrn_num [bt_stringf(3)]	This field defines the screen information to be displayed at the ATM for the specified function identifier.
state_scrn2_task [bt_stringf(40)]	This field identifies the setup task that needs to be performed for the specified function identifier.
state_scrn3_func_id [bt_stringf(1)]	This field identifies the function identifier that is to be sent to the ATM. This identifier instructs the ATM to perform a function. Function identifiers for NCR devices are all the same value for up to 7 entries, while Diebold function identifiers are different across the 7 entries.
state_scrn3_scrn_num [bt_stringf(3)]	This field defines the screen information to be displayed at the ATM for the specified function identifier.
state_scrn3_task [bt_stringf(40)]	This field identifies the setup task that needs to be performed for the specified function identifier.
state_scrn4_func_id [bt_stringf(1)]	This field identifies the function identifier that is to be sent to the ATM. This identifier instructs the ATM to perform a function. Function identifiers for NCR devices are all the same value for up to 7 entries, while Diebold function identifiers are different across the 7 entries.

Element (type)	Description
state_scrn4_scrn_num [bt_stringf(3)]	This field defines the screen information to be displayed at the ATM for the specified function identifier.
state_scrn4_task [bt_stringf(40)]	This field identifies the setup task that needs to be performed for the specified function identifier.
state_scrn5_func_id [bt_stringf(1)]	This field identifies the function identifier that is to be sent to the ATM. This identifier instructs the ATM to perform a function. Function identifiers for NCR devices are all the same value for up to 7 entries, while Diebold function identifiers are different across the 7 entries.
state_scrn5_scrn_num [bt_stringf(3)]	This field defines the screen information to be displayed at the ATM for the specified function identifier.
state_scrn5_task [bt_stringf(40)]	This field identifies the setup task that needs to be performed for the specified function identifier.
state_scrn6_func_id [bt_stringf(1)]	This field identifies the function identifier that is to be sent to the ATM. This identifier instructs the ATM to perform a function. Function identifiers for NCR devices are all the same value for up to 7 entries, while Diebold function identifiers are different across the 7 entries.
state_scrn6_scrn_num [bt_stringf(3)]	This field defines the screen information to be displayed at the ATM for the specified function identifier.
state_scrn6_task [bt_stringf(40)]	This field identifies the setup task that needs to be performed for the specified function identifier.
state_scrn7_func_id [bt_stringf(1)]	This field identifies the function identifier that is to be sent to the ATM. This identifier instructs the ATM to perform a function. Function identifiers for NCR devices are all the same value for up to 7 entries, while Diebold function identifiers are different across the 7 entries.
state_scrn7_scrn_num [bt_stringf(3)]	This field defines the screen information to be displayed at the ATM for the specified function identifier.
state_scrn7_task [bt_stringf(40)]	This field identifies the setup task that needs to be performed for the specified function identifier.
state_scrn_act_array [bt_stringf(25)]	This array holds action indicators used to determine which actions and data should be included in the response for this state and screen. Each element of this array controls a specific action/data in the response. The values of each array element are 0 - Do not perform action, 1 - Perform action. Array elements currently defined are as follows: 0 - Include Audio Response data 1 - Include Dispense Count data
state_scrn_task_buf [bt_stringf(1800)]	This buffer contains the setup-field tasks to be performed for function data formatting (as a virtual controller). This buffer is organized into value pairs of 60 bytes, which are defined as follows: Task, length 40; parameter, length 20 (The parameter can be used to store additional data that needs to be passed to the setup-field task for processing). This buffer will contain a maximum of 30 task/parameter pairs.

ATM_STMNT_DATA (1.0) (atmstd)

ES device handler table. This table is used to temporarily store statement data to be printed in a statement print transaction. This table is only used in statement print transactions.

[Audited] [Supports versioning]

Element (type)	Description
term_id* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ATM_DS1 table and is used to link the ATM terminal to the ATM_DD1 and ATM_DD2 tables.
atm_seq_num* [bt_int32s]	The last transaction sequence number. If the terminal supports the generation of such a number, this number comes from the terminal. Otherwise, it is generated by the ATM device handler for the terminal. The data is stored on the ATM_DD1 table.
stmnt_seq_num* [bt_int32s]	The statement sequence number used to chunk the statement for storage in this table. Since the data is too long to store in one row, the data is spread across multiple rows. Each row has a unique statement sequence number. The values range from 0 to n, where n is the largest possible value that may be stored using the specified data type. The data is stored on the Statement Data table (ATM_STMNT_DATA) and is managed by the ATM device handler.
stmnt_txn_tm [ts 1.0]	The transaction date and time stored with statement data in the Statement Data table (ATM_STMNT_DATA). This field is used to detect old statement data so that it can be deleted by a cleanup process. The data is managed by the ATM device handler.
stmnt_data [bt_stringv(4000)]	A chunk of statement data, stored in the Statement Data table (ATM_STMNT_DATA). The data is managed by the ATM device handler.

ATM_STMNT_PRNT (1.0) (atmps)

This data source contains the ATM Statement Print Profile configuration. This configuration is used when formatting the statement print data.

[Audited] [Supports versioning]

OLTP: ATM_STMNT_PRNT_OLTP

Element (type)	Description
stmnt_prnt_prfl* [prfl_def 1.0]	The statment print profile identifies the statement print parameter setting to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
stmnt_lns_per_pg [bt_int32s]	The values in the following fields are used by the ATM device handler process for statement print transactions. The value is configured in the ATM Profile table ATM_PRFL. The number of lines on statements printed at the terminal. Valid values are 24 through 88. The default value is 60.
stmnt_lns_per_inch [bt_int32s]	The number of lines per inch on statements printed at the terminal. The value is configured in the ATM Statement Print Profile table (ATM_STMNT_PRNT). The value in this field is sent to the statement printer by the ATM device handler process for each

Element (type)	Description
	statement print transaction. Valid values are: 6 = 6 lines per inch 8 = 8 lines per inch The default value is 6.
stmnt_left_mrgn [bt_int32s]	A code used by the ATM device handler to set the left margin for statements printed at the terminal. The value is configured on the ATM Statement Print profile table (ATM_STMNT_PRNT). The value in this field is sent to the statement printer for each statement print transaction. This number must be at least four less than the number specified in the Right Margin field. Valid values are 000 through 128. The default value is 000.
stmnt_right_mrgn [bt_int32s]	A code used by the ATM device handler to set the right margin for statements printed at the terminal. The value is configured in the ATM Statement Print Profile table (ATM_STMNT_PRNT). The value is sent to the statement printer for each statement print transaction. This number must be at least four greater than the number specified in the Left Margin field. Valid values are 004 through 132. The default value is 080.
stmnt_format [bt_stringf(1)]	Indicates to the host whether the ATM device handler process supports the data compression message format. The data is configured on the ATM Statement Print Profile table (ATM_STMNT_PRNT). Valid values are: 0 = Columnar format (data compression is not supported). 1 = BASE24-atm data compression format (data compression is supported). The default value is 0.

ATM_SUR (1.0) (atmchd)

This data source contains the ATM Surcharge configuration. The data is accessed via the surcharge profile configured on the ATM_DS1 table.

[Audited] [Supports versioning]

OLTP: ATM_SUR_OLTP

Element (type)	Description
atm_sur_prfl*[prfl_def 1.0]	The ATM surcharge profile identifies the surcharge setup to be used for the specified ATM. This field identifies the terminal surcharge group of which this terminal is a member and is passed to the authorization system where it is used for surcharge calculations.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
sur_amt_lmt [amt 1.0]	This field is used to store the maximum surcharge amount displayed to a cardholder in Non-Interactive Surcharging transactions. The value is configured on the ATM_SUR Configuration table. This value is downloaded to the terminal as part of the screen configuration. Loading is managed by the Surcharge Amount Limit Indicator. The default value is 0.
sur_amt_lmt_curr [crncy_cde 1.0]	This field contains the currency code associated with the maximum surcharge amount displayed to a cardholder in Non-Interactive Surcharging transactions.
sur_method [bt_stringf(1)]	This field is used for surcharging. This field specifies the terminals surcharging method. Valid values are: 0 = Not configured 1 = Interactive Request (pre-authorization notification) 2 = Interactive Request (post-authorization notification) 3 = Non-Interactive, user has accepted up to max. surcharge The default value is 0. The data is configured on the ATM_SUR Configuration table.

ATM_TC_Proc_Code (1.0) (attpd)

The ATM Transaction Code to Processing Code table contains an entry for every BASE24 ATM transaction code which may be received. The ATM transaction code is mapped to a corresponding processing code.

[Audited] [Supports versioning]

Element (type)	Description
proc_cde_prfl* [bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
atm_txn_cde* [bt_stringf(6)]	The transaction code used to describe the effect of a transaction on the customer account and the accounts affected. It is composed of the transaction code, the from account type and the to account type.
txn_subtyp* [bt_stringf(4)]	An optional value that can be used with an existing BASE24 Classic transaction code to define a new transaction type. Any four characters are permitted. Default value is spaces (not applicable).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
proc_cde [proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.

AudDtlPK (1.0) (uaudpk)

Audit Detail Primary Key table

[Audited] [Supports versioning]

Element (type)	Description
ActivityTS* [ts 1.0]	
ActivityID* [bt_int32s]	
TableName* [bt_stringf(30)]	
Seq* [bt_int32s]	
PrimaryKey [bt_stringv(850)]	

AuditDtl (1.0) (uaudtl)

Audit Detail table

[Audited] [Supports versioning]

Element (type)	Description
ActivityTS*[ts 1.0]	
ActivityID*[bt_int32s]	
TableName*[bt_stringf(30)]	
ColumnName*[bt_stringf(50)]	
Seq*[bt_int32s]	
AfterValue [bt_stringf(1000)]	
BeforeValue [bt_stringv(1000)]	

AuditTbl (1.0) (uaudtb)

Audit table

[Audited] [Supports versioning]

Element (type)	Description
ActivityTS*[ts 1.0]	
ActivityID*[bt_int32s]	
AFID [bt_int32s]	
UserID [bt_stringf(16)]	
SessionNum [bt_int16s]	
WorkstationID [bt_stringf(50)]	
ErrorData [bt_stringf(80)]	
ContextID [bt_int32s]	

Audit_Store_and_Forward (1.0) (asafd)

The Audit Store and Forward (SAF) table contains all the records which are stored to be forwarded to the EAE at a later time.

[Not Audited] [Supports versioning]

Element (type)	Description
fm_ts_aud_saf*[bt_stringf(24)]	The timestamp of when the Audit Store and Forward (SAF) record was initially added. This timestamp is in the form yyyy-mm-dd hh:mm:ss.hhh
session_num*[bt_stringf(2)]	The session number retrieved from the Ticket XML Element.
saf_seq_num*[bt_int16s]	The sequence number identifying SAF records for SAF messages that do not fit in a single SAF record. The first SAF record in a sequence has a sequence number of 0.

Element (type)	Description
saf_send_cnt [bt_int16s]	The counter indicating the number of times this specific Store and Forward (SAF) message has been sent. Once the SAF send count exceeds the maximum SAF retry count, the record is deleted and no longer sent.
saf_cont_flg [bt_flag]	This flag indicates more SAF records must be read to build the entire SAF message. Valid values are: False - message is complete. True - read more records to build complete message.
saf_msg [bt_binaryv(3900)]	This is the contents of the Store and Forward (SAF) message which is used to send a message to an interface. This may be a fully built message ready to be sent or a partially built message needing additional formatting before sending. The specific interface defines the layout of this field.

Audit_Store_and_Forward_Config (1.0) (asafcd)

This table contains SAF Configuration information for Auditing UI functions. It contains SAF limits and timeout values. There should only be one record in this table.

[Not Audited] [Supports versioning]

Element (type)	Description
cmpnt_id*[bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
saf_cnt [cnt_lrg 1.0]	The number of Store and Forward (SAF) records add to the SAF data source waiting to be sent.
max_saf_outstnd_lmt [bt_int16s]	The maximum number of Store and Forward (SAF) records that can be outstanding at a time. Valid values are 1 - 9999. Default value is 1. This field is no longer used in Interface Manager Table.
saf_outstnd_cnt [bt_int16s]	The number of Store and Forward (SAF) records outstanding that have been sent and are waiting for a response. This field is no longer used in Interface Station Table.
saf_pend_timr_flg [bt_flag]	A flag indicating whether a Store and Forward (SAF) timer is pending. Valid values are: 0 - No SAF timer is pending, 1 - A SAF timer is pending. The default value is 0.
saf_timr_lmt [timr_lmt 1.0]	Store and Forward (SAF) Timer Limit, indicates the number of seconds to wait for a response after transmitting a SAF record. Valid values are: 1 - 9999, 60=Default. This field is no longer used in Interface Manager Table.
max_saf_retries_lmt [bt_int16s]	The maximum number of times a Store and Forward (SAF) record will be resent before the record is deleted. Valid values are 0 to 999. A value of 0 indicates an infinite number of tries. Default value is 3. This field is no longer used in Interface Manager Table.
saf_status [bt_flag]	A flag indicating whether Store and Forward (SAF) processing is enabled(true) or disabled(false). Default value is enabled.

Element (type)	Description
saf_delay_timr_lmt [timr_lmt 1.0]	Store and Forward (SAF) Timer Limit, indicates the number of seconds to wait to check whether records exist in the SAF waiting to be sent. Valid values are: 1 - 9999, 300=Default. This field is no longer used in Interface Manager Table.
ui_aud_sta_nam [bt_stringf(16)]	The symbolic name of the station which sends UI Audit Logging requests to the Enterprise Auditing Environment (EAE) and receives UI Audit Logging responses from the EAE. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Authorization_Script (1.0) (athscd)

The Authorization Script Table contains one record for each Authorization Script defined in the Script Configuration data source. It defines whether the script is enabled or not and whether to monitor the script to ensure thresholds are met for the script.

[Audited] [Supports versioning]

OLTP: Authorization_Script_OLTP

Element (type)	Description
auth_nam*[bt_stringf(16)]	The name of the authorizer. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_typ*[bt_stringf(4)]	The message type of the transaction.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
script_nam [nam 1.0]	The name of an executable script. This field is left-justified, upper case (containing any combination of alphanumeric and special character, but without any embedded spaces).
script_enabled_flg [bt_flag]	Flag indicating whether the execution of a high level authorization script is enabled or disabled. Values are: 1 - script enabled, 0 - script disabled. Default value is 1.
monitor_script_flg [bt_flag]	Flag indicating whether the script is monitored to meet or exceed established thresholds for approvals, denials and referrals. Valid values are: 1 - monitor script, 0 - Do not monitor script. Default value is 1.
apprv_thrhd_lmt [bt_int16s]	The threshold limit for approved transactions. It is expressed as a percentage of the total transactions approved as a result of a high level authorization script. If the percentage of the transactions approved by the script falls below this percentage, the script is disabled from further execution.
deny_thrhd_lmt [bt_int16s]	The threshold limit for denied transactions. It is expressed as a percentage of the total transactions denied as a result of a high level authorization script. If the percentage of the transactions denied by the script rises above this percentage, the script is disabled from further execution.
refer_thrhd_lmt [bt_int16s]	The threshold limit for referred transactions. It is expressed as a percentage of the total transactions referred as a result of a high level authorization script. If the percentage of the transactions referred by the script rises above this percentage, the script is disabled from further execution.
min_script_txn_cnt [bt_int32s]	The minimum number of transactions to process with this script before evaluating whether the threshold limits for the script are met or not. The script can not be

Element (type)	Description
	disabled due to threshold limits until the minimum transaction count has been reached.

B24EPS_Ignt_map (1.0) (b24lmd)

The BASE24_EPS Interface BASE24 Logical Network Mapping. It will be created that will be used by the ISO87 interface to map the BASE24-eps Interface Name to the appropriate BASE24 Logical Network ID value.

[Audited] [Supports versioning]

OLTP: B24EPS_Ignt_map_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
term_lgnt [bt_stringf(4)]	Identifies the Logical Network in Base24 associated with the terminal for an acquired transaction, which will used to map the interface name to the appropriate BASE24 Logical Network ID. The value in this field must be alphanumeric with a minimum length of 4 bytes. Unused positions must be padded to the right with spaces. Wildcarding (all asterisk) is allow.

B24_filetyp_map (1.0) (b24ftd)

The B24_filetyp_map. It will be used by the ISO87 interface to map the BASE24 Service (or Process) Name to the BASE24-eps File Name used for sending FHM Hot Card Updates out to an interchange.

[Audited] [Supports versioning]

OLTP: B24_filetyp_map_OLTP

Element (type)	Description
srvc_nam* [bt_stringf(16)]	The BASE24 Service or Process Name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
file_typ [bt_stringf(2)]	The type of file update to be routed using this record. For a list of file update types. Valid Values are: Card Table "01" Positive Balance "02" Negative File Update "04" Visa Stop Payment "05" Visa Card Recovery Bulletin "06" Banknet File Update "07" EPS-Net File Update "08" Equiens File Update "09" Remove Merchant Authorization "10" JCB Negative File Update "12" AEGN Negative File Update "13" NYCE Negative File Update "14" Fifth Third File Update "15" Shazam Negative File Update "16" NETS Negative File Update "17" Presto Negative File Update "18" Accel/Exchange Negative File Update "19" MDS Dispute Processing "20" COOP Negative File Update "21" MDS File Update "22" E-RSB File Update "23" PRICE File Update "24" Span2 Dispute File Update "25" Check Status "26" Stop Payment "27" Visa SMS

Element (type)	Description
	Exception Processing "28" Pulse Negative File Update "45" Visa DPS 0382 File Update Message "46" STAR 0382 File Update Message "47" Elan Host File Update "48" EFD eFunds Host File Update "49" Interac Administrative Messages "50" FDR File Update "91"

B53_Institution (1.0) (b53ind)

B53 Institution Table.

[Audited] [Supports versioning]

OLTP: B53_Institution_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
inst_acronym [bt_stringf(4)]	The Institution Acronym.

Banknet_Configuration (5.0) (bnetcd)

The Banknet Configuration Table contains a record with additional configuration required for each Banknet Interface.

[Audited] [Supports versioning]

OLTP: Banknet_Configuration_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mci_id [bt_stringf(6)]	The MCI identification number for the institution.
nmm_timr_lmt [timr_lmt 1.0]	The number of seconds to wait for a response after transmitting a Network Management Request, including but not limited to Signon, Logon or Echo-Test, to the Host or Interchange. Valid values are: 1 - 9999. Default value is 30.
xnmm_timr_lmt [timr_lmt 1.0]	The number of seconds to wait before sending a network management message after a station is marked down or a network management request has timed out. Valid values are: 1 - 9999. Default is 60 seconds.

Element (type)	Description
inf_pro_flg [bt_flag]	A flag that indicates whether the Interface is a MasterCard Intermediate Network Facility (INF) Processor.
netwk_asgn_tcc [bt_flag]	Specifies whether the external network will assign the transaction category code (0 – Will not assign, 1 – Will assign).
mci_mult_ind [bt_flag]	This is a boolean flag to indicate if multiple customer IDs need to be configured.
ukdm_sppt_ind [bt_flag]	This is a boolean flag to indicate the acquirer supports U.K. Domestic Maestro transactions.

Banknet_Group_Timers (2.0) (bngtd)

The Banknet Group Timers Table contains a record for each logon sent to keep track of duplicate MCI ids and to handle logon timeouts and responses.

[Audited] [Supports versioning]

Element (type)	Description
mci_id*[bt_stringf(6)]	The MCI identification number for the institution.
logon_timr_typ*[bt_int16s]	Logon Timer Type, indicates the type of timer started. Valid values are: 1 = NMM Logon, 2 = XNMM Logon.
seq_num*[bt_int64s]	The sequence number identifying the last transaction performed in the current batch. The value is incremented by one for each occurrence of transaction within a current batch. On close batch transaction processing, the value is reset to zero and accumulation begins within the new batch when the first transaction occurs. This is system protected element.
timr_id [timr_id 1.0]	Timer Identifier, indicates the value passed back from a timer start request.
timer_exp_ts [ts 1.0]	The timestamp of when the timer has expired.
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inbnd_sta_nam [bt_stringf(16)]	The symbolic name of the inbound station which receives messages from an interface. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Banknet_Institution_Id (3.0) (bniid)

The Banknet Institution Identification Table contains an entry for every institution identifier defined in the system which is mapped to an MCI identification number.

[Audited] [Supports versioning]

OLTP: Banknet_Institution_Id_OLTP

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mci_id [bt_stringf(6)]	The MCI identification number for the institution.
security_cde [bt_stringf(5)]	The security code required for online requests.
trffc_typ [bt_char]	The traffic type. Valid values are: A - Acquirer traffic only, I - Issuer traffic only, B - (default) both acquirer and issuer.
avs_logon_typ [bt_char]	The AVS logon type associated with a mci_id. Valid values are: 0 - not supported, 1 - issuer receives complete address data and provides AVS, 2 - issuer receives condensed address data and provides AVS, 3 - issuer receives complete address data and Banknet provides AVS, 4 - issuer receives condensed address data and Banknet provides AVS, 5 - Banknet provides AVS and issuer does not see AVS data.
mci_id_1 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_1 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_1 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_2 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_2 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_2 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_3 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_3 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_3 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_4 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_4 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_4 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_5 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_5 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_5 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_6 [bt_stringf(6)]	The MCI identification number for the institution.

Element (type)	Description
mci_criteria_typ_6 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_6 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.

Banknet_Institution_Id2 (1.0) (bni2d)

The Banknet Institution Identification Table contains an entry for every institution identifier defined in the system which is mapped to an MCI identification number.

[Audited] [Supports versioning]

OLTP: Banknet_Institution_Id2_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mci_id [bt_stringf(6)]	The MCI identification number for the institution.
security_cde [bt_stringf(5)]	The security code required for online requests.
trffc_typ [bt_char]	The traffic type. Valid values are: A - Acquirer traffic only, I - Issuer traffic only, B - (default) both acquirer and issuer.
avs_logon_typ [bt_char]	The AVS logon type associated with a mci_id. Valid values are: 0 - not supported, 1 - issuer receives complete address data and provides AVS, 2 - issuer receives condensed address data and provides AVS, 3 - issuer receives complete address data and Banknet provides AVS, 4 - issuer receives condensed address data and Banknet provides AVS, 5 - Banknet provides AVS and issuer does not see AVS data.
mci_id_1 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_1 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_1 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_2 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_2 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_2 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_3 [bt_stringf(6)]	The MCI identification number for the institution.

Element (type)	Description
mci_criteria_typ_3 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_3 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_4 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_4 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_4 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_5 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_5 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_5 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.
mci_id_6 [bt_stringf(6)]	The MCI identification number for the institution.
mci_criteria_typ_6 [bt_stringf(1)]	The criteria type for the MCI identification number for the institution. 1 - The transaction currency code determines the MCI to use. 2 - The transaction card type determines the MCI to use.
mci_criteria_val_6 [bt_stringf(3)]	The criteria value for the MCI identification number for the institution.

Banknet_Merchant_Program (1.0) (bntmpd)

The Banknet Merchant Program Table contains a record for each merchant program a merchant may belong to which maps to the MasterCard Promotion Code.

[Audited] [Supports versioning]

OLTP: Banknet_Merchant_Program_OLTP

Element (type)	Description
mrch_pgm*[bt_stringf(1)]	The merchant program in which the merchant participates for this instrument type. The meaning is defined by the network associated with this instrument type. Valid values are 0-9, A-Z and a space. Default value is a space.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mrch_pgm_cde [bt_stringf(6)]	The merchant program code supported by the interface. Default value is spaces.

BASE24_KEYF (1.0) (keyfd)

The DDL layout of the BASE24 KEYF. This is used by the KEYF UI server and is used when BASE24 customers are using TSS.

[Not Audited] [Does not support versioning]

Element (type)	Description
b24_rec_typ* [bt_char]	The record type indicator for this KEYF record. The value in this field must be set to 1 to indicate an Interface record.
b24_fiid* [bt_stringf(4)]	The FIID of the interchange to which this record information applies. The FIID present in this field must have a corresponding record in the Interchange Configuration File (ICF).
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
user_fld1* [bt_stringf(1)]	One byte user field (temporary filler).
b24_fm_ts_1 [bt_int16s]	Part 1 of the Last-FM timestamp
b24_fm_ts_2 [bt_int16s]	Part 2 of the Last-FM timestamp
b24_fm_ts_3 [bt_int16s]	Part 3 of the Last-FM timestamp
b24_fm_user_grp [bt_int16s]	The group number of the operator that performed the last file maintenance application. This value is taken from the information given when the operator last logged on to BASE24.
b24_fm_user_num [bt_int32s]	The user number of the operator that performed the last file maintenance application. This value is taken from the information given when the operator last logged on to BASE24.
b24_fm_updt_typ [bt_char]	The type of file maintenance that was last applied to the record.
b24_fm_sta_num [bt_stringf(4)]	Not used.
b24_fm_user_fld [bt_char]	Not used.
b24_mac_typ [bt_char]	A code indicating the type of message authentication to be used between a DPC or an interchange and the BASE24 Interface process.
b24_ext_encrypt_typ [bt_char]	A code indicating the type of PIN management used by the DPC or interchange. This field affects management of PINs for messages sent to the DPC or interchange by the BASE24 Interface process.
b24_int_encrypt_typ [bt_char]	A code indicating the type of PIN management used by BASE24. This field affects the management of PINs for messages inbound to the BASE24 Interface process from the DPC or interchange.
b24_pin_blk [bt_char]	Specifies the PIN block format used by the DPC or interchange.
b24_ansi_pan [bt_char]	The PAN digits used by the DPC or interchange when the value in the PIN-BLK field is equal to 1. The value in this field specifies which PAN digits are used in the formation of the PIN block that is transmitted in the external message.
pin_pad_char [bt_char]	PIN Pad character used to pad the PIN block. Valid values are 0 - 9, A - F. Default is F.
b24_interm_key_clear [b24_key 1.0]	The clear version of the intermediate key.
b24_interm_key_encrypt [b24_key 1.0]	The encrypted version of the intermediate key.
b24_out_pin_key_1 [b24_key 1.0]	A key used for the encryption of PINs in transactions sent to the DPC or interchange. This PIN key is designated as key number 1.

Element (type)	Description
b24_out_pin_key_2 [b24_key 1.0]	A key used for the encryption of PINs in transactions sent to the DPC or interchange. This PIN key is designated as key number 2.
b24_out_pin_cur_idx [bt_char]	A code indicating which outbound PIN encryption key is to be used by the BASE24 Interface process.
b24_user_fld4 [bt_stringf(7)]	Not used.
b24_out_pin_key_cntr_1 [bt_int64s]	A sequential counter assigned to the Outbound PIN Key 1. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_out_pin_key_cntr_2 [bt_int64s]	A sequential counter assigned to the Outbound PIN Key 2. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_out_pin_key_cntr [bt_int32s]	A sequential counter identifying the key that is currently being used.
b24_out_pin_vvk_1 [bt_binaryf(3)]	Check digits for outbound PIN key 1.
b24_out_pin_vvk_2 [bt_binaryf(3)]	Check digits for outbound PIN key 2.
b24_out_mac_key_1 [b24_key 1.0]	A key used for the creation of MACs in transactions sent to the DPC or interchange. This MAC key is designated as key number 1.
b24_out_mac_key_2 [b24_key 1.0]	A key used for the creation of MACs in transactions sent to the DPC or interchange. This MAC key is designated as key number 2.
b24_out_mac_cur_idx [bt_char]	A code indicating which outbound MAC key is to be used by the BASE24 Interface process.
b24_user_fld5 [bt_stringf(7)]	Not used.
b24_out_mac_key_cntr_1 [bt_int64s]	A sequential counter assigned to the Outbound MAC Key 1. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_out_mac_key_cntr_2 [bt_int64s]	A sequential counter assigned to the Outbound MAC Key 2. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_out_mac_key_cntr [bt_int32s]	A sequential counter identifying the key that is currently being used.
b24_out_mac_vvk_1 [bt_binaryf(3)]	Check digits for outbound MAC key 1.
b24_out_mac_vvk_2 [bt_binaryf(3)]	Check digits for outbound MAC key 2.
b24_in_pin_key_1 [b24_key 1.0]	A key used for the encryption of PINs in transactions received from the DPC or interchange. This PIN key is designated as key number 1.
b24_in_pin_key_2 [b24_key 1.0]	A key used for the encryption of PINs in transactions received from the DPC or interchange. This PIN key is designated as key number 2.
b24_in_pin_cur_idx [bt_char]	A code indicating which inbound PIN encryption key is to be used by the BASE24 Interface process.
b24_user_fld6 [bt_stringf(7)]	Not used.
b24_in_pin_key_cntr_1 [bt_int64s]	A sequential counter assigned to the Inbound PIN Key 1. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_in_pin_key_cntr_2 [bt_int64s]	A sequential counter assigned to the Inbound PIN Key 2. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_in_pin_key_cntr [bt_int32s]	A sequential counter identifying the key that is currently being used.
b24_in_pin_vvk_1 [bt_binaryf(3)]	Check digits for inbound PIN key 1.
b24_in_pin_vvk_2 [bt_binaryf(3)]	Check digits for inbound PIN key 2.

Element (type)	Description
b24_in_mac_key_1 [b24_key 1.0]	A key used for the creation of MACs in transactions received from the DPC or interchange. This MAC key is designated as key number 1.
b24_in_mac_key_2 [b24_key 1.0]	A key used for the creation of MACs in transactions received from the DPC or interchange. This MAC key is designated as key number 2.
b24_in_mac_cur_indx [bt_char]	A code indicating which inbound MAC key is to be used by the BASE24 Interface process.
b24_user_fld7 [bt_stringf(7)]	Not used.
b24_in_mac_key_cntr_1 [bt_int64s]	A sequential counter assigned to the Inbound MAC Key 1. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_in_mac_key_cntr_2 [bt_int64s]	A sequential counter assigned to the Inbound MAC Key 2. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_in_mac_key_cntr [bt_int32s]	A sequential counter identifying the key that is currently being used.
b24_in_mac_vvk_1 [bt_binaryf(3)]	Check digits for inbound MAC key 1.
b24_in_mac_vvk_2 [bt_binaryf(3)]	Check digits for inbound MAC key 2.
b24_exchng_key [b24_key 1.0]	The key under which PIN or MAC keys are to be encrypted if PIN or MAC keys are automatically exchanged between BASE24 and an interchange. This key must be manually exchanged between BASE24 and the interchange, and must be the security module encrypted form of the key.
b24_last_txn_ts_1 [bt_int16s]	Part 1 of the last transaction timestamp.
b24_last_txn_ts_2 [bt_int16s]	Part 2 of the last transaction timestamp.
b24_last_txn_ts_3 [bt_int16s]	Part 3 of the last transaction timestamp.
b24_last_txn_id [bt_int16s]	Last transaction non-stop id.
b24_last_txn_pro_num [bt_int16s]	Last transaction process number.
old_key_timr_lmt [bt_int32s]	This field specifies the timer used for clearing old/previous KAM(s), KDT(s) and KPT(s). This field is displayed as seconds but written to disk as hundredths of seconds. Allowed values in seconds: 0 - 99999. Default is 30.
b24_kek_seq_num_out [bt_int64s]	The value in this field represents the next message id number that should be used when a Key Exchange is sent to the network.
b24_kek_seq_num_in [bt_int64s]	The value in this field represents the next message id number that should be used when a Key Exchange is received from the network.
b24_out_kme_cur_indx [bt_char]	A code indicating which outbound KME encryption key is to be used by the BASE24 Interface process, KME key number 1 or KME key number 2. Valid values are 1 and 2.
b24_user_fld8a [bt_stringf(1)]	Not used.
b24_out_kme_key_cntr_1 [bt_int64s]	A sequential counter assigned to the Outbound KME Key 1. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_out_kme_key_cntr_2 [bt_int64s]	A sequential counter assigned to the Outbound KME Key 2. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_in_kme_cur_indx [bt_char]	A code indicating which inbound KME encryption key is to be used by the BASE24 Interface process, KME key number 1 or KME key number 2. Valid values are 1 and 2.

Element (type)	Description
b24_user_fld8b [bt_stringf(1)]	Not used.
b24_in_kme_key_cntr_1 [bt_int64s]	A sequential counter assigned to the Inbound KME Key 1. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_in_kme_key_cntr_2 [bt_int64s]	A sequential counter assigned to the Inbound KME Key 2. Values range from 0 through HEX FFFFFFFFFFFFFFFF.
b24_full_encrypt [bt_stringf(1)]	Identifies the level of MSG encryption. Valid values: 0 = No MSG encryption (default). 1 = Full MSG encryption. 2 = Encryption on specified fields. This option is not currently supported.
b24_encrypt_typ_msg [bt_stringf(1)]	A code indicating the type of MSG encryption used by the DPC or interchange. This field affects the encryption of data for messages sent to the DPC or interchange by the BASE24 Interface process. Valid values are: 0 = No MSG encryption (default). 1 = Security module MSG management.
b24_msg_vvk [bt_binaryf(3)]	The check digits for the MSG Key. The value in this field is entered as four hexadecimal characters from the KEYF screen, but is stored in binary form. It is used by the ASMCOM and RSMCOM security tools for check digit validation and by some interfaces.
b24_user_fld8c [bt_stringf(1)]	Not used.
b24_in_msg_key_cntr [bt_int32s]	A sequential counter identifying the inbound MSG key that is currently being used. Values range from 0 through hex FFFFFFFFFFFFFFFF.
b24_out_msg_key_cntr [bt_int32s]	A sequential counter identifying the outbound MSG key that is currently being used. Values range from 0 through hex FFFFFFFFFFFFFFFF.
b24_msg_key_timr_lmt [bt_int32s]	The time limit, in minutes, associated with Dynamic Key Management MSG Key exchange. Valid values range from 0 to 32767. If a time limit is configured, a minimum value of five minutes is required.
b24_msg_key_txn_lmt [bt_int32s]	The maximum number of transactions allowed between Dynamic Key Management MSG Key exchanges. Valid values range from 0 to 9,999. If a transaction limit is configured, a minimum of 50 transactions must be entered.
b24_msg_err_lmt [bt_int16s]	The maximum number of MSG encryption errors allowed by this Interface. Once this limit is reached, the Interface generates or requests a new key. If this field contains the value 0, the number of MSG encryption errors is not checked. Valid values are from 0 to 9999. If an error limit is configured, a minimum of 5 errors is required.
b24_msg_cnsc_err_lmt [bt_int16s]	The maximum number of consecutive MSG encryption/decryption errors allowed by the Interface. Once this limit is reached, the Interface generates or requests a new key. If this field contains the value 0, the number of consecutive MSG encryption/decryption errors is not checked. Valid values are from 0 to 9999. If a consecutive error limit is configured, a minimum of 5 errors is required.
b24_user_fld9a [bt_stringf(99)]	Not used.
b24_rcv_id [bt_stringf(16)]	Identifies the receiver of the Cryptographic Service Message for Dynamic Key Exchange messages.
b24_org_id [bt_stringf(16)]	Identifies the originator of the Cryptographic Service Message for Dynamic Key Exchange messages.

Element (type)	Description
b24_notarize_flg [bt_char]	A flag indicating whether key notarization is supported.
b24_mac_data_typ [bt_char]	A code indicating the character set of the data to be authenticated. This is the format that the data is in prior to performing the MAC calculation.
b24_full_msg_mac [bt_char]	This field indicates if the full message or selected fields will be included in the MAC calculation.
b24_user_fld10 [bt_stringf(1)]	Not used.
inbnd_kpt_variant [bt_char]	Encryption variant of the PIN key.
inbnd_kam_variant [bt_char]	Encryption variant of the MAC key.
b24_key_proc_typ [bt_stringf(1)]	A code indentifying the type of dynamic key management processing this interface can perform.
b24_num_keys [bt_stringf(1)]	The number of keys supported by this interface.
b24_key_lgth [bt_stringf(1)]	The length (single or double)of keys supported by this interface.
kpt_timr_lmt [bt_int32s]	PIN Key Timer Limit indicates the amount of time in minutes to use the current PIN Key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of seconds.
kam_timr_lmt [bt_int32s]	MAC Key Timer Limit indicates the amount of time in minutes to use the current MAC key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of seconds.
max_kpt_txn_cnt [bt_int32s]	The number of PIN Key transactions that are allowed before requesting a new key. Valid values are 0 to 99999 (9,999 for KEYF). 0 indicates no transaction count limit is used. Default value is 0.
b24_pin_err_lmt [bt_int16s]	The maximum number of PIN translation errors allowed by this Interface. If this field contains the value 0, the number of PIN translation errors is not checked. Valid values are from 0 to 9999. If an error limit is configured, a minimum of 5 errors is required.
max_kpt_cnsc_err_cnt [bt_int16s]	The number of consecutive PIN key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no consecutive error count limit is used. If this field contains the value 0, the number of PIN translation errors is not checked. If an error limit is configured, a minimum of 5 errors is required.
max_kam_txn_cnt [bt_int32s]	The number of MAC generations/verifications that are allowed before requesting a new key. Valid values are 0 to 99999 (9,999 for KEYF). 0 indicates no transaction count limit is used. Default value is 0.
b24_mac_err_lmt [bt_int16s]	The maximum number of MAC errors allowed by this Interface. Valid values are 0 to 9999. 0 indicates no consecutive error count limit is used. If this field contains the value 0, the number of MAC errors is not checked. If an error limit is configured, a minimum of 5 errors is required.
max_kam_cnsc_err_cnt [bt_int16s]	The number of consecutive MAC key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no consecutive error count limit is used. Default value is 0. For the KEYF, if an error limit is configured, a minimum of 5 errors is required.
b24_kmac_sync_err_lmt [bt_int16s]	The maximum number of KMAC sync errors allowed by this Interface.

Element (type)	Description
b24_mac_exchng_key [b24_key 1.0]	The key under which MAC keys are to be encrypted if MAC keys are automatically exchanged between BASE24 and an interchange.
b24_mac_exchng_key_extnd [b24_key 1.0]	The key under which MAC keys are to be encrypted if MAC keys are automatically exchanged.
b24_mac_exchng_key_vvk [bt_binaryf(3)]	Check digits for the MAC exchange key.
b24_exchng_key_vvk [bt_binaryf(3)]	Check digits for the PIN exchange key.
b24_exchng_key_extnd [b24_key 1.0]	The key under which PIN or MAC keys are to be encrypted if PIN or MAC keys are automatically exchanged between BASE24 and an interchange. This key must be manually exchanged between BASE24 and the interchange, and must be the security module encrypted form of the key.
b24_interm_key_vvk [bt_binaryf(3)]	Check digits for the intermediate key.
b24_user_fld11 [bt_stringf(1)]	Not used.

Batch_Auth_Config (1.0) (bacd)

The Batch Auth Configuration data source is a new data source containing configuration options for the Batch Auth process.

[Audited] [Supports versioning]

OLTP: Batch_Auth_Config_OLTP

Element (type)	Description
btch_auth_nam*[bt_stringf(16)]	The symbolic name of the Batch Auth Process. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces)
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
btch_delay_timr_lmt [bt_int16s]	Delay Timer Limit, indicates the number of seconds to wait to check whether records exist in the Batch Auth list waiting to be sent. Valid values are: 1 - 9999, 180=Default
btch_max_outstnd_lmt [bt_int16s]	The maximum number of Batch Auth records that can be outstanding at a time. Valid values are 1 - 9999. Default value is 1
btch_timr_lmt [bt_int16s]	Timer Limit, indicates the number of seconds to wait for a response after transmitting a Batch Auth record. Valid values are: 1 - 9999, 60=Default
btch_max_retries [bt_int16s]	The maximum number of times a Batch Auth record will be resent before the record is deleted. Valid values are 0 to 999. Default value is 3
posn_updt_intrvl [bt_int16s]	The number of records to process before updating the disk record with the position information. Valid values are 0 to 999. Default value is 100. A value of 0 indicates to never update position information.
posn_info_retn [bt_int16s]	The number of days Batch Auth Position Information will be keep. Valid values are 1- 99. Default value is 7. This field is not used if Position Update Interval is zero.

Element (type)	Description
posn_info_cleanup_tim [bt_stringf(4)]	The time of day in HHMM that expired position information will be cleaned up. Valid values are 00:00 - 23:59. Default is 08:00. This field is not used if Position Update Interval is zero.

Batch_Auth_Posn (1.0) (bapd)

The Batch Auth Position data source contains position information for each batch. This data source is updated periodically based on the posn_updt_intrvl specified in the Batch Auth Configuration data source. This allows a batch to be restarted without sending a lot of extra duplicate records.

[Audited] [Supports versioning]

Element (type)	Description
btch_auth_ctx_key*[bt_stringf(80)]	Batch Key
fm_ts [ts 1.0]	The timestamp the record was inserted/updated
lst_data_rec_num [bt_stringf(8)]	The last data record number processed by the Batch Auth process for this batch

BEPS_Instrm_Prty (1.0) (beipd)

Banknet IPF Instrument Type Priority Table.

[Audited] [Supports versioning]

OLTP: BEPS_Instrm_Prty_OLTP

Element (type)	Description
instrm_typ*[instrm_typ 1.0]	A code identifying the instrument type.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_prty [bt_int16s]	The instrument type priority (lower value means higher priority).

BIC_Interface (1.0) (biifd)

BIC Interface Table.

[Audited] [Supports versioning]

OLTP: BIC_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
setl_typ [bt_int16s]	This field indicates the settlement type (role) of the Interface. (0 - Co-network, 1 - Master, 2-Secondary).
encrypt_typ [bt_int16s]	Indicates the PIN encryption type used. (0 - No Pin Encryption, 1 - Security device PIN, Management).
mac_sppt_typ [bt_int16s]	Indicates the MAC support level in the BIC Interface (0 - No MAC Support, 1 - Hardware MAC Support).
setl_inst_id [bt_stringf(11)]	This the Settlement Institution ID associated with the Interface.
acq_stand_in_for_conetwork [bt_flag]	BASE24-eps can stand-in for the co-network when acting as acquirer (forwarding requests to co-network).
iss_stand_in_for_conetwork [bt_flag]	Co-network can stand-in for BASE24-eps when BASE24-eps is acting as an issuer (receiving request from co-network)
acq_ovrrd_inst_id_flg [bt_flag]	This is a boolean flag to indicate if BIC Institution ID should be used to override the Acquirer Institution ID.
frwd_ovrrd_inst_id_flg [bt_flag]	This is a boolean flag to indicate if the Forwarding Institution ID should be over-ridden.
acq_frwd_ovrrd_inst_id [bt_stringf(11)]	This the Institution ID to be used when overriding the Acquirer Institution ID or Forwarding Institution Id.
rcv_ovrrd_inst_id_flg [bt_flag]	This is a boolean flag to indicate if the Receiving Institution ID should be overridden.
rcv_ovrrd_inst_id [bt_stringf(11)]	This the Institution ID to be used when overriding the Receiving Institution ID.
inbnd_u_kam_cntr [bt_int32s]	Inbound Message Authentication transport counter.
inbnd_u_kpt_cntr [bt_int32s]	Inbound PIN transport counter.
outbnd_u_kam_cntr [bt_int32s]	Outbound Message Authentication transport counter.
outbnd_u_kpt_cntr [bt_int32s]	Outbound PIN transport counter.

BLZ_Map (1.0) (blzmpd)

The German BLZ Mapping data source maintains the records used to map the Long BLZs to the Short BLZs when building the PAN or prefix based on German Track 3 data.

[Audited] [Supports versioning]

OLTP: BLZ_Map_OLTP

Element (type)	Description
brch_cde* [bt_stringf(3)]	The Track 2 Branch Code. (Prikey)
short_blz* [bt_stringf(5)]	The short Bankleitzahl (BLZ). (Prikey) BLZ is the German bank route code (or sort code).

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Timestamp. Timestamp of last update to the data source record.
long_blz [bt_stringf(8)]	The long Bankleitzahl (BLZ). (Altkey) BLZ is the German bank route code (or sort code). When received on transactions, Track 3 will contain a long, 8-digit BLZ that must be mapped to a short, 5-digit BLZ (prefaced by a 3-digit branch code) for processing within BASE24-eps (used as the "prefix" value).

BNFT_Interface (1.0) (bnifd)

Benefit Interface Table.

[Audited] [Supports versioning]

OLTP: BNFT_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rcv_id_cde [bt_stringf(11)]	A code identifying the receiving institution.
acq_id_cde [bt_stringf(11)]	A code identifying the acquiring institution.
setl_typ [bt_int16s]	This field indicates the settlement type (role) of the Interface. (0 - Co-network, 1 - Master, 2-Secondary).
orig_id [bt_stringf(16)]	Identifies the originator of the Cryptographic Service Message for Dynamic Key Exchange messages. The value in this field must be alphanumeric with a minimum length of 4 bytes. Unused positions must be padded to the right with spaces.
rcv_id [bt_stringf(16)]	Identifies the receiver of the Cryptographic Service Message for Dynamic Key Exchange messages. The value in this field must be alphanumeric with a minimum length of 4 bytes. Unused positions must be padded to the right with spaces.
inbnd_u_kam_cntr [bt_int32s]	Inbound Message Authentication transport counter.
inbnd_u_kpt_cntr [bt_int32s]	Inbound PIN transport counter.
outbnd_u_kam_cntr [bt_int32s]	Outbound Message Authentication transport counter.
outbnd_u_kpt_cntr [bt_int32s]	Outbound PIN transport counter.

BNtNg_Header (1.0) (bnthd)

Record of Changes: Date Version Person ----- 15FEB2008 1.0.00 F. Cuc Initial release. Symptom: None. Problem: None. Fix: None. Reference: WO #061007-01 31MAR2008 1.0.01 D.Kinney Phase 1 Enablement. Symptom: None. Problem: None. Fix: Implement all security functions supported by both BASE24-eps and IBM

CryptoExpress2/ICSF. New Key Token data source. Reference: WO #031110-06 Task 71358 04DEC2008 1.0.02 J.Samson Thales AS2805 Enhancements Symptom: None. Problem: None. Fix: Created version 4.0 of the Channel Security table and version 2.0 of the Interchange Security table and the Interchange Security OLTP for the Thales AS2805 Enhancement. Version 2.0 of the Interchange Security table also contains new elements for the FPS Enhanced KEK Processing enhancement. Created Version 2.0 of the Derivation Key table and the Derivation Key OLTP for the DUKPT Encryption Enhancement. Reference: WO #040628-15 (Thales AS2805) WO #070807-02 (DUKPT Data Encryption) WO #080924-01 (Enhanced KEK Processing) Task 84781, CR 2273 21JAN2009 1.0.03 J.Samson Canadian Security Enhancements Symptom: None. Problem: None. Fix: Added inbnd_old_data_tmr to version 4.0 of the Channel Security table. Reference: WO #080722-04 (Canadian Security) Task 86060, CR 2495 29JAN2009 1.0.04 J.Samson Thales AS2805 Enhancements Symptom: None. Problem: None. Fix: Added input_key_typ to version 2.0 of the Interchange Security and Interchange Security OLTP tables. Increased SIS_TBL_MAX_ROW_LGTH to 2324 for the Interchange_Security_OLTP. Reference: WO #040628-15 (Thales AS2805) Task 86337, CR 2569 Task 86417, CR 2588 24MAR2009 1.0.05 A.Florea German Security Enhancements Symptom: None. Problem: None. Fix: Added data sources: - dual_pin_Verification (with OLTP) - ZKA_KGK (with OLTP) - EMV_Iss_Auth_Dta (with OLTP) Updated data sources: - Channel_Security - Interchange_Security (with OLTP) Reference: WO #080513-04 06MAY2009 1.0.06 J. Samson Symptom: None. Problem: None. Fix: Added element drv_id to CSEC, ISEC and ISEC_OLTP. Removed the ZKA_KGK_OLTP. Reference: WO #080513-04 22SEP2009 1.0.07 J. Samson Symptom: None. Problem: None. Fix: Added explicit DEFAULT clause for the key_table_num element in the CSEC and ISEC. Reference: WO #080513-04 11MAY2010 1.0.08 A. Florea Symptom: None. Problem: None. Fix: Updates in the scope of 2/3 level key hierarchy Added data sources: - CHANNEL_SECURITY_FUTURE - INTERCHANGE_SECURITY_FUTURE Updated data sources: - INTERCHANGE_SECURITY (with OLTP) - CHANNEL_SECURITY Reference: WO #040618-03 06OCT2010 1.0.09 A. Florea Symptom: None. Problem: None. Fix: Updates in the scope of 2/3 level key hierarchy Enable old KEK timer, remove old level 1 keys Updated data sources: - INTERCHANGE_SECURITY (with OLTP) - CHANNEL_SECURITY Reference: WO #040618-03 29OCT2010 1.0.10 A. Florea Symptom: Future keys tables cannot be created on z/OS DB2. Problem: Column names too long (limit is 30 chars). Fix: Updates: - INTERCHANGE_SECURITY_FUTURE - CHANNEL_SECURITY_FUTURE Reference: Case #01100969 04NOV2010 1.0.11 A. Florea Symptom: Future keys usage must be controlled via a column in current keys datasource. Problem: Need to control future keys usage via GUI. Fix: Updates: - INTERCHANGE_SECURITY (with OLTP) - CHANNEL_SECURITY Reference: WO #040618-03 CR #9783 10JAN2011 1.0.12 A. Florea Symptom: Metadata version mismatch Problem: Table version not incremented when adding futr_keys_usg column. Fix: Updates: - INTERCHANGE_SECURITY (with OLTP) - CHANNEL_SECURITY Reference: CR #10763 14JAN2011 1.0.13 R. Dirlea Symptom: None. Problem: None. Fix: Updates in the scope of CEDICAM enhancements. - Interchange_Security (with OLTP) (new version): added two new fields (multi_flg and series_enabled_flg) and updated the comments (description) for the pin_blk_typ, kam_typ and kkt_am_variant fields to reflect all possible values. - BNTng_Header (with OLTP) (update): changed the type of the bntng_hdr_key field from keyx_hdr (8 bytes) to bt_stringf(64). - Channel_Security (update): updated the comments(description) for the pin_blk_typ, kam_typ and kkt_am_variant fields. Reference: WO #040618-03, Task #107774, CR #9098 10MAR2011 1.0.14 R. Dirlea Symptom: Load of BNTng_Header_OLTP failed on a 11.1 Unix update. Problem: BNTng_Header data source (with OLTP) changed (primary key was updated), but the version number remained at 1. Fix: Changed the physical name of the table for the ASSIGN, so that set-up does not try to recreate the same physical file. (e.g., PHYSICAL_FILE_NAM bnth2d/bnth2od). Reference: Salesforce case #01119537, Task #113465, CR #11820. 16MAR2011 1.0.15 J. Samson Symptom: Default values contain quotation marks. Problem: Default values should not be enclosed in quotes. Fix: Changed the multi_flg and series_enabled_flg default values from "N" to N in the Interchange_Security table. Reference: Task #113800, CR #11947. This table is used to hold the additional key header information required by the BNTng HSM.

[Audited] [Supports versioning]

OLTP: BNTng_Header_OLTP

Element (type)	Description
bntng_hdr_key*[bt_stringf(64)]	BNTng Header data source key field. Used to link to header field(s) in other security data sources.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
bntng_key_id_typ [bt_stringf(2)]	Exchanged key identifier type.
bntng_decrypt_key_id [bt_stringf(38)]	Decryption Key Identifier. Identifies the key identifier for the key used to decrypt BNTng encrypted keys.
bntng_exch_key_id [bt_stringf(38)]	Identifier of the exchanged key.
bntng_key_usage [bt_stringf(4)]	Identifies the key usage authorizations for the exchanged key.
bntng_encrypt_mthd [bt_stringf(2)]	Key encryption method. Valid values are: 02 = DES ECB (Single or Double length keys) 04 = DES CBC (Double Length keys) 05 = DES ECB (Double Length keys with additional data)

BNTng_Init_Data (1.0) (bntid)

This table is used to hold initialization data for the BNTng HSM.

[Audited] [Supports versioning]

Element (type)	Description
dev_nam* [bt_stringf(32)]	The assign name of the hardware security device.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
bntng_init_data_id* [bt_stringf(16)]	User defined Initialization Data Identifier.
bntng_init_data [bt_stringf(4000)]	Initialization data for the BNTng HSM.

BPDATA (1.0) (bpdtd)

This table contains Bill Payment data records for the Java ATM Device Handler (IFX).

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
BillPay_Row* [bt_int32s]	The payee data for a single ATM could span multiple rows. This field indicates the placement of this row in the complete data set for this ATM.
BillPay_FullFlag [bt_int32s]	Indicates if the data record for this row is full.
BillPay_Data [bt_stringv(3780)]	The Bill Payment data records for this row. Multiple records are concatenated together. Individual data records are of a fixed length.

CACNFSAF (1.0) (cacsaf)

The CACNFSAF table (Certificate Authority Confirmation SAF). Confirmations to the Certificate Authority are required to keep the Encryption Certificates consistent between the CA database and the ATM (EPP).

[Audited] [Supports versioning]

Element (type)	Description
InsrtTs* [bt_int64s]	The date and time an row was inserted into the table. This data is used to retrieve the records in the order they were written.
ExtrCnctID [bt_stringf(50)]	Used to uniquely identify an external connection in the External Connection table (EXTRCNCT).
AttmptCnt [bt_int32s]	The number of times a row in the Reversal SAF has been retried. After a configurable number of retries, the row is deleted without being sent.
MsgFrmtTx [bt_stringf(4)]	A code identifying the format of the message stored in the Reversal SAF.
MsgIdTx [bt_stringf(150)]	Holds a unique id of the message sent asynchronously for which context is held. The value in this field is stored in tables CACNTX table and is managed by the ES device handler.
KeyOwnrIdTx [bt_stringf(16)]	This field contains a unique id of the owner of the key being handled (e.g. terminal id).
KeyOwnrTypTx [bt_stringf(2)]	This field contains the key owner type of the key being handled (e.g. device type).
CertTypTx [bt_stringf(1)]	A code indicating the type of the certificate requested/confirmed. Valid values are 0 (Certificate type verification key) and 1 (Certificate type encryption key).
CACMsgBn [bt_binaryl(3500)]	The message saved in the Certificate Authority Confirmation SAF table. Reduced size (reference MsgBn, 3926) to allow standard record length of 4062 (allowed by NSK Enscribe for KeySequenced files).

CACNTX (1.0) (cacntx)

The Certificate Authority Context Table for Certificate Authority rollover messages in flight.

[Audited] [Supports versioning]

Element (type)	Description
MsgIdTx* [bt_stringf(150)]	Holds a unique id of the message sent asynchronously for which context is held. The value in this field is stored in tables CACNTX table and is managed by the ES device handler.
ExpTm [bt_int64s]	The timestamp a context entry expires. The value in this field is stored in the CACNTX table and is managed by the ES device handler.
KeyOwnrIdTx [bt_stringf(16)]	This field contains a unique id of the owner of the key being handled (e.g. terminal id).
KeyOwnrTypTx [bt_stringf(2)]	This field contains the key owner type of the key being handled (e.g. device type).

Element (type)	Description
CertTypTx [bt_stringf(1)]	A code indicating the type of the certificate requested/confirmed. Valid values are 0 (Certificate type verification key) and 1 (Certificate type encryption key).
CADDataArea [bt_binaryl(1024)]	Holds the context for asynchronous messages sent to the certificate authority while in flight. The value in this field is stored in the CACNTX table and is managed by the ES device handler.

Card (5.0) (crdd)

The Card Table. Contains one record for each card in the network that will be used for transaction authorization purposes.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pan* [bt_stringf(28)]	Primary Account Number
crd_seq_num* [bt_stringf(3)]	The card sequence number used to identify an individual member when several members have the same card number.
avs_chk [bt_stringf(1)]	Indicates if Address Verification should be performed. Valid values are: 0 (No), 1 (Yes). Default is 0 (No).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
refr_ts [yymmddhhmmss 1.0]	Refresh Time Stamp. Timestamp of the refresh that created this record.
refr_id [bt_stringf(32)]	An indicator of the refresh that created this record. This field is informational only.
cust_id [bt_stringf(28)]	Customer id that is associated with a payment instrument type. The customer id value will be the same for each instrument type owned by an individual.
instrm_typ [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.
instrm_stat [bt_stringf(2)]	The status (e.g., lost, stolen, open, etc.) of the instrument type. Values are user-defined.
instrm_stat_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the instrument status was changed.
pvv [bt_stringf(12)]	The PIN Verification Value for the card.
pin_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the PIN was changed.

Element (type)	Description
eff_dat [yyyyymmdd 1.0]	The date an instrument type becomes effective.
exp_dat [yyyyymm 1.0]	The expiration date of an instrument.
eff_dat_scnd [yyyyymmdd 1.0]	The date a secondary instrument type becomes effective.
exp_dat_scnd [yyyyymm 1.0]	The expiration date of a secondary instrument.
instrm_stat_scnd [bt_stringf(2)]	The status (e.g., lost, stolen, open, etc.) of the instrument type. Values are user-defined.
instrm_stat_scnd_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the secondary instrument status was changed.
lmt_prfl [prfl_def 1.0]	The limit profile. Used as the key to the Limit Table.
lmt_usg_1_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_1_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_1_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_1_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_1_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_2_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_2_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_2_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_2_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_2_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the

Element (type)	Description
	length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_3_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_3_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_3_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_3_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_3_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_4_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_4_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_4_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_4_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_4_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option

Element (type)	Description
	is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_5_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_5_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_5_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_5_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_5_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_6_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_6_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_6_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_6_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_6_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.

Element (type)	Description
acct_num_ttl [bt_int16s]	The total number of accounts associated with an instrument type.
acct_num_1 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_1_typ [typ 1.0]	The account type of an account number.
acct_num_1_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_1_descr [bt_stringf(10)]	The description of the account.
acct_num_2 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_2_typ [typ 1.0]	The account type of an account number.
acct_num_2_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_2_descr [bt_stringf(10)]	The description of the account.
acct_num_3 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_3_typ [typ 1.0]	The account type of an account number.
acct_num_3_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_3_descr [bt_stringf(10)]	The description of the account.
acct_num_4 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_4_typ [typ 1.0]	The account type of an account number.
acct_num_4_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_4_descr [bt_stringf(10)]	The description of the account.
acct_num_5 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_5_typ [typ 1.0]	The account type of an account number.
acct_num_5_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_5_descr [bt_stringf(10)]	The description of the account.
acct_num_6 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_6_typ [typ 1.0]	The account type of an account number.
acct_num_6_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.

Element (type)	Description
acct_num_6_descr [bt_stringf(10)]	The description of the account.
acct_num_7 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_7_typ [typ 1.0]	The account type of an account number.
acct_num_7_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_7_descr [bt_stringf(10)]	The description of the account.
acct_num_8 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_8_typ [typ 1.0]	The account type of an account number.
acct_num_8_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_8_descr [bt_stringf(10)]	The description of the account.
acct_num_9 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_9_typ [typ 1.0]	The account type of an account number.
acct_num_9_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_9_descr [bt_stringf(10)]	The description of the account.
acct_num_10 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_10_typ [typ 1.0]	The account type of an account number.
acct_num_10_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_10_descr [bt_stringf(10)]	The description of the account.
addr_1 [bt_stringf(25)]	The address line 1. Where only one line of address is supported, this address will be used and addr_2 will be ignored. This field is left-justified (containing any combination of alphanumeric and special characters).
addr_2 [bt_stringf(25)]	The address line 2. This field is left-justified (containing any combination of alphanumeric and special characters).
postal_cde [bt_stringf(10)]	The postal code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
dflt_pri_acct_typ [bt_stringf(2)]	Specifies the default account type to be used to determine the default account.
csm_buf_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the CSM Buffer was changed.
csm_buf [bt_binaryv(1000)]	This variable length field is available to allow customer specific data.

Element (type)	Description
dep_typ [bt_int16s]	Depository Type is a flag identifying the preferred depository type when a deposit is made to distinguish between business deposits and normal deposits. Valid values are: 0 – use standard. 1 – use commercial
lmt_usg_1_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_2_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_3_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_4_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_5_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_6_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
atc_reset [bt_int16s]	A flag indicating whether the primary ATC value should be set to the secondary ATC value. Valid values are: 0 – Do not reset the primary the primary ATC value (default). 1 – Reset the primary ATC value.
atc_reset_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the ATC Reset flag was changed.
exp_dat_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the Primary Expiration Date was changed.
eff_dat_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the Primary Effective Date was changed.
chk_base_flg [bt_int16s]	A flag used to indicate whether check transactions involving checks not defined in the Check Status data source should be included in the Total Cash Advance/Withdrawal usages and checked against the Total Cash Advance/Withdrawal limits. Valid values are: 0 = No, do not include in Total Cash Advance/Withdrawal usages. 1 = Yes, include in Total Cash Advance/Withdrawal usages. 2 = Use Prefix value
chk_stat_chk_base_flg [bt_int16s]	A flag used to indicate whether check transactions involving checks defined in the Check Status data source should be included in the Total Cash Advance/Withdrawal usages and checked against the Total Cash Advance/Withdrawal limits. Valid values are: 0 = No, do not include in Total Cash Advance/Withdrawal usages. 1 = Yes, include in Total Cash Advance/Withdrawal usages. 2 = Use Prefix value

Cardnet_ID_Code (1.0) (crdnicd)

The Cardnet ID Code Table.

[Audited] [Supports versioning]

OLTP: Cardnet_ID_Code_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces)
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
cardnet_id_cde [bt_stringf(11)]	Cardnet ID Code.

Cardnet_Interface (1.0) (crdnifd)

The Cardnet Interface Table.

[Audited] [Supports versioning]

OLTP: Cardnet_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces)
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
send_cntr_id [bt_stringf(11)]	Sending Center ID.
test_mde_flg [bt_flag DEFAULT 0]	Test Mode Flag.
mrch_contract_co_cde [bt_stringf(11)]	Merchant Contract Company Code.
acq_cat [bt_stringf(2)]	Acquirer Category.
mrch_co_cde [bt_stringf(11)]	Merchant Company Code.
mrch_term_num [bt_stringf(8)]	Merchant Terminal Number.
mrch_num [bt_stringf(15)]	Merchant Number.
auth_cntr_id [bt_stringf(11)]	Authorizing Center ID.

Cardnet_Interface_Terminal (1.0) (crdnitd)

The Cardnet Interface Terminal Table.

[Audited] [Supports versioning]

OLTP: Cardnet_Interface_Terminal_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acq_inst_id*[inst_id 1.0]	Acquirer ID.
intf_term_id*[bt_stringf(16)]	Terminal ID.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mrch_term_num [bt_stringf(8)]	Merchant Terminal Number.
mrch_num [bt_stringf(15)]	Merchant Number.

Card_Account (3.0) (crdad)

The Card Account Table. Contains information for account numbers belonging to the specified card. This table is used if there are more than 10 accounts associated with the specified Card. The Card row contains data for up to 10 accounts.

[Audited] [Supports versioning]

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pan*[bt_stringf(28)]	Primary Account Number
crd_seq_num*[bt_stringf(3)]	The card sequence number used to identify an individual member when several members have the same card number.
rec_num*[bt_stringf(3)]	This field is used to make a primary key unique when multiple rows exist for the other fields in the primary key. rec_num begins with value 1 except for the Card Account table which begins with value 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acct_num_1 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_1_typ [typ 1.0]	The account type of an account number.

Element (type)	Description
acct_num_1_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_1_descr [bt_stringf(10)]	The description of the account.
acct_num_2 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_2_typ [typ 1.0]	The account type of an account number.
acct_num_2_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_2_descr [bt_stringf(10)]	The description of the account.
acct_num_3 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_3_typ [typ 1.0]	The account type of an account number.
acct_num_3_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_3_descr [bt_stringf(10)]	The description of the account.
acct_num_4 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_4_typ [typ 1.0]	The account type of an account number.
acct_num_4_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_4_descr [bt_stringf(10)]	The description of the account.
acct_num_5 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_5_typ [typ 1.0]	The account type of an account number.
acct_num_5_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_5_descr [bt_stringf(10)]	The description of the account.
acct_num_6 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_6_typ [typ 1.0]	The account type of an account number.
acct_num_6_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_6_descr [bt_stringf(10)]	The description of the account.
acct_num_7 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_7_typ [typ 1.0]	The account type of an account number.
acct_num_7_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_7_descr [bt_stringf(10)]	The description of the account.

Element (type)	Description
acct_num_8 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_8_typ [typ 1.0]	The account type of an account number.
acct_num_8_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_8_descr [bt_stringf(10)]	The description of the account.
acct_num_9 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_9_typ [typ 1.0]	The account type of an account number.
acct_num_9_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_9_descr [bt_stringf(10)]	The description of the account.
acct_num_10 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_10_typ [typ 1.0]	The account type of an account number.
acct_num_10_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_10_descr [bt_stringf(10)]	The description of the account.
acct_num_11 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_11_typ [typ 1.0]	The account type of an account number.
acct_num_11_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_11_descr [bt_stringf(10)]	The description of the account.
acct_num_12 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_12_typ [typ 1.0]	The account type of an account number.
acct_num_12_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_12_descr [bt_stringf(10)]	The description of the account.
acct_num_13 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_13_typ [typ 1.0]	The account type of an account number.
acct_num_13_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_13_descr [bt_stringf(10)]	The description of the account.
acct_num_14 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_14_typ [typ 1.0]	The account type of an account number.

Element (type)	Description
acct_num_14_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_14_descr [bt_stringf(10)]	The description of the account.
acct_num_15 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_15_typ [typ 1.0]	The account type of an account number.
acct_num_15_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_15_descr [bt_stringf(10)]	The description of the account.
acct_num_16 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_16_typ [typ 1.0]	The account type of an account number.
acct_num_16_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_16_descr [bt_stringf(10)]	The description of the account.
acct_num_17 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_17_typ [typ 1.0]	The account type of an account number.
acct_num_17_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_17_descr [bt_stringf(10)]	The description of the account.
acct_num_18 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_18_typ [typ 1.0]	The account type of an account number.
acct_num_18_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_18_descr [bt_stringf(10)]	The description of the account.
acct_num_19 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_19_typ [typ 1.0]	The account type of an account number.
acct_num_19_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_19_descr [bt_stringf(10)]	The description of the account.
acct_num_20 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_20_typ [typ 1.0]	The account type of an account number.
acct_num_20_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_20_descr [bt_stringf(10)]	The description of the account.

Element (type)	Description
acct_num_21 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_21_typ [typ 1.0]	The account type of an account number.
acct_num_21_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_21_descr [bt_stringf(10)]	The description of the account.
acct_num_22 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_22_typ [typ 1.0]	The account type of an account number.
acct_num_22_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_22_descr [bt_stringf(10)]	The description of the account.
acct_num_23 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_23_typ [typ 1.0]	The account type of an account number.
acct_num_23_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_23_descr [bt_stringf(10)]	The description of the account.
acct_num_24 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_24_typ [typ 1.0]	The account type of an account number.
acct_num_24_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_24_descr [bt_stringf(10)]	The description of the account.
acct_num_25 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_25_typ [typ 1.0]	The account type of an account number.
acct_num_25_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_25_descr [bt_stringf(10)]	The description of the account.
acct_num_26 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_26_typ [typ 1.0]	The account type of an account number.
acct_num_26_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_26_descr [bt_stringf(10)]	The description of the account.
acct_num_27 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_27_typ [typ 1.0]	The account type of an account number.

Element (type)	Description
acct_num_27_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_27_descr [bt_stringf(10)]	The description of the account.
acct_num_28 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_28_typ [typ 1.0]	The account type of an account number.
acct_num_28_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_28_descr [bt_stringf(10)]	The description of the account.
acct_num_29 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_29_typ [typ 1.0]	The account type of an account number.
acct_num_29_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_29_descr [bt_stringf(10)]	The description of the account.
acct_num_30 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_30_typ [typ 1.0]	The account type of an account number.
acct_num_30_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_30_descr [bt_stringf(10)]	The description of the account.
acct_num_31 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_31_typ [typ 1.0]	The account type of an account number.
acct_num_31_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_31_descr [bt_stringf(10)]	The description of the account.
acct_num_32 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_32_typ [typ 1.0]	The account type of an account number.
acct_num_32_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_32_descr [bt_stringf(10)]	The description of the account.
acct_num_33 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_33_typ [typ 1.0]	The account type of an account number.
acct_num_33_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_33_descr [bt_stringf(10)]	The description of the account.

Element (type)	Description
acct_num_34 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_34_typ [typ 1.0]	The account type of an account number.
acct_num_34_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_34_descr [bt_stringf(10)]	The description of the account.
acct_num_35 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_35_typ [typ 1.0]	The account type of an account number.
acct_num_35_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_35_descr [bt_stringf(10)]	The description of the account.
acct_num_36 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_36_typ [typ 1.0]	The account type of an account number.
acct_num_36_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_36_descr [bt_stringf(10)]	The description of the account.
acct_num_37 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_37_typ [typ 1.0]	The account type of an account number.
acct_num_37_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_37_descr [bt_stringf(10)]	The description of the account.
acct_num_38 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_38_typ [typ 1.0]	The account type of an account number.
acct_num_38_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_38_descr [bt_stringf(10)]	The description of the account.
acct_num_39 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_39_typ [typ 1.0]	The account type of an account number.
acct_num_39_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_39_descr [bt_stringf(10)]	The description of the account.
acct_num_40 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_40_typ [typ 1.0]	The account type of an account number.

Element (type)	Description
acct_num_40_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_40_descr [bt_stringf(10)]	The description of the account.
acct_num_41 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_41_typ [typ 1.0]	The account type of an account number.
acct_num_41_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_41_descr [bt_stringf(10)]	The description of the account.
acct_num_42 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_42_typ [typ 1.0]	The account type of an account number.
acct_num_42_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_42_descr [bt_stringf(10)]	The description of the account.
acct_num_43 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_43_typ [typ 1.0]	The account type of an account number.
acct_num_43_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_43_descr [bt_stringf(10)]	The description of the account.
acct_num_44 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_44_typ [typ 1.0]	The account type of an account number.
acct_num_44_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_44_descr [bt_stringf(10)]	The description of the account.
acct_num_45 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_45_typ [typ 1.0]	The account type of an account number.
acct_num_45_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_45_descr [bt_stringf(10)]	The description of the account.
acct_num_46 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_46_typ [typ 1.0]	The account type of an account number.
acct_num_46_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_46_descr [bt_stringf(10)]	The description of the account.

Element (type)	Description
acct_num_47 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_47_typ [typ 1.0]	The account type of an account number.
acct_num_47_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_47_descr [bt_stringf(10)]	The description of the account.
acct_num_48 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_48_typ [typ 1.0]	The account type of an account number.
acct_num_48_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_48_descr [bt_stringf(10)]	The description of the account.
acct_num_49 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_49_typ [typ 1.0]	The account type of an account number.
acct_num_49_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_49_descr [bt_stringf(10)]	The description of the account.
acct_num_50 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_50_typ [typ 1.0]	The account type of an account number.
acct_num_50_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_50_descr [bt_stringf(10)]	The description of the account.
acct_num_51 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_51_typ [typ 1.0]	The account type of an account number.
acct_num_51_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_51_descr [bt_stringf(10)]	The description of the account.
acct_num_52 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_52_typ [typ 1.0]	The account type of an account number.
acct_num_52_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_52_descr [bt_stringf(10)]	The description of the account.
acct_num_53 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_53_typ [typ 1.0]	The account type of an account number.

Element (type)	Description
acct_num_53_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_53_descr [bt_stringf(10)]	The description of the account.
acct_num_54 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_54_typ [typ 1.0]	The account type of an account number.
acct_num_54_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_54_descr [bt_stringf(10)]	The description of the account.
acct_num_55 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_55_typ [typ 1.0]	The account type of an account number.
acct_num_55_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_55_descr [bt_stringf(10)]	The description of the account.
acct_num_56 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_56_typ [typ 1.0]	The account type of an account number.
acct_num_56_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_56_descr [bt_stringf(10)]	The description of the account.
acct_num_57 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_57_typ [typ 1.0]	The account type of an account number.
acct_num_57_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_57_descr [bt_stringf(10)]	The description of the account.
acct_num_58 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_58_typ [typ 1.0]	The account type of an account number.
acct_num_58_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_58_descr [bt_stringf(10)]	The description of the account.
acct_num_59 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_59_typ [typ 1.0]	The account type of an account number.
acct_num_59_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_59_descr [bt_stringf(10)]	The description of the account.

Element (type)	Description
acct_num_60 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_60_typ [typ 1.0]	The account type of an account number.
acct_num_60_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_60_descr [bt_stringf(10)]	The description of the account.
acct_num_61 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_61_typ [typ 1.0]	The account type of an account number.
acct_num_61_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_61_descr [bt_stringf(10)]	The description of the account.
acct_num_62 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_62_typ [typ 1.0]	The account type of an account number.
acct_num_62_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_62_descr [bt_stringf(10)]	The description of the account.
acct_num_63 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_63_typ [typ 1.0]	The account type of an account number.
acct_num_63_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_63_descr [bt_stringf(10)]	The description of the account.
acct_num_64 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_64_typ [typ 1.0]	The account type of an account number.
acct_num_64_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_64_descr [bt_stringf(10)]	The description of the account.
acct_num_65 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_65_typ [typ 1.0]	The account type of an account number.
acct_num_65_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_65_descr [bt_stringf(10)]	The description of the account.
acct_num_66 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_66_typ [typ 1.0]	The account type of an account number.

Element (type)	Description
acct_num_66_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_66_descr [bt_stringf(10)]	The description of the account.
acct_num_67 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_67_typ [typ 1.0]	The account type of an account number.
acct_num_67_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_67_descr [bt_stringf(10)]	The description of the account.
acct_num_68 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_68_typ [typ 1.0]	The account type of an account number.
acct_num_68_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_68_descr [bt_stringf(10)]	The description of the account.
acct_num_69 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_69_typ [typ 1.0]	The account type of an account number.
acct_num_69_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_69_descr [bt_stringf(10)]	The description of the account.
acct_num_70 [acct_num 1.0]	Account number associated with an instrument type.
acct_num_70_typ [typ 1.0]	The account type of an account number.
acct_num_70_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_num_70_descr [bt_stringf(10)]	The description of the account.
csm_buf [bt_binaryv(1000)]	This variable length field is available to allow customer specific data.

CARD_ACCOUNT_MBYTE (1.0) (crdamd)

The Multi-Byte Card Account Table. Contains information for account numbers belonging to the specified card. This table is used if multi-byte elements are present.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any

Element (type)	Description
pan*[bt_stringf(28)]	combination of alphanumeric and special characters, but without any embedded spaces). Primary Account Number
crd_seq_num*[bt_stringf(3)]	The card sequence number used to identify an individual member when several members have the same card number.
user_fld1 [bt_stringf(1)]	This field is used to provide word alignment for full file refreshes received from a host system.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
cust_id_mbyte [bt_binaryl(56)]	Multi-byte customer id that is associated with a payment instrument type. The customer id value will be the same for each instrument type owned by an individual.
addr_1_mbyte [bt_binaryl(50)]	Multi-byte address line 1. This field contains any combination of alphanumeric and special characters.
addr_2_mbyte [bt_binaryl(50)]	Multi-byte address line 2. This field contains any combination of alphanumeric and special characters.
postal_cde_mbyte [bt_binaryl(20)]	Multi-byte postal code. This field contains any combination of alphanumeric and special characters, but without any embedded spaces.
acct_num_1_descr_mbyte [bt_binaryl(20)]	Multi-byte descriptions of the accounts.
acct_num_2_descr_mbyte [bt_binaryl(20)]	
acct_num_3_descr_mbyte [bt_binaryl(20)]	
acct_num_4_descr_mbyte [bt_binaryl(20)]	
acct_num_5_descr_mbyte [bt_binaryl(20)]	
acct_num_6_descr_mbyte [bt_binaryl(20)]	
acct_num_7_descr_mbyte [bt_binaryl(20)]	
acct_num_8_descr_mbyte [bt_binaryl(20)]	
acct_num_9_descr_mbyte [bt_binaryl(20)]	
acct_num_10_descr_mbyte [bt_binaryl(20)]	
acct_num_11_descr_mbyte [bt_binaryl(20)]	
acct_num_12_descr_mbyte [bt_binaryl(20)]	
acct_num_13_descr_mbyte [bt_binaryl(20)]	

Element (type)	Description
acct_num_14_descr_mbyte [bt_binaryl(20)]	
acct_num_15_descr_mbyte [bt_binaryl(20)]	
acct_num_16_descr_mbyte [bt_binaryl(20)]	
acct_num_17_descr_mbyte [bt_binaryl(20)]	
acct_num_18_descr_mbyte [bt_binaryl(20)]	
acct_num_19_descr_mbyte [bt_binaryl(20)]	
acct_num_20_descr_mbyte [bt_binaryl(20)]	
acct_num_21_descr_mbyte [bt_binaryl(20)]	
acct_num_22_descr_mbyte [bt_binaryl(20)]	
acct_num_23_descr_mbyte [bt_binaryl(20)]	
acct_num_24_descr_mbyte [bt_binaryl(20)]	
acct_num_25_descr_mbyte [bt_binaryl(20)]	
acct_num_26_descr_mbyte [bt_binaryl(20)]	
acct_num_27_descr_mbyte [bt_binaryl(20)]	
acct_num_28_descr_mbyte [bt_binaryl(20)]	
acct_num_29_descr_mbyte [bt_binaryl(20)]	
acct_num_30_descr_mbyte [bt_binaryl(20)]	
acct_num_31_descr_mbyte [bt_binaryl(20)]	
acct_num_32_descr_mbyte [bt_binaryl(20)]	
acct_num_33_descr_mbyte [bt_binaryl(20)]	
acct_num_34_descr_mbyte [bt_binaryl(20)]	
acct_num_35_descr_mbyte [bt_binaryl(20)]	
acct_num_36_descr_mbyte [bt_binaryl(20)]	
acct_num_37_descr_mbyte [bt_binaryl(20)]	
acct_num_38_descr_mbyte [bt_binaryl(20)]	
acct_num_39_descr_mbyte [bt_binaryl(20)]	
acct_num_40_descr_mbyte [bt_binaryl(20)]	
acct_num_41_descr_mbyte [bt_binaryl(20)]	
acct_num_42_descr_mbyte [bt_binaryl(20)]	
acct_num_43_descr_mbyte [bt_binaryl(20)]	
acct_num_44_descr_mbyte [bt_binaryl(20)]	
acct_num_45_descr_mbyte [bt_binaryl(20)]	
acct_num_46_descr_mbyte [bt_binaryl(20)]	
acct_num_47_descr_mbyte [bt_binaryl(20)]	
acct_num_48_descr_mbyte [bt_binaryl(20)]	

Element (type)	Description
acct_num_49_descr_mbyte [bt_binaryl(20)]	
acct_num_50_descr_mbyte [bt_binaryl(20)]	
acct_num_51_descr_mbyte [bt_binaryl(20)]	
acct_num_52_descr_mbyte [bt_binaryl(20)]	
acct_num_53_descr_mbyte [bt_binaryl(20)]	
acct_num_54_descr_mbyte [bt_binaryl(20)]	
acct_num_55_descr_mbyte [bt_binaryl(20)]	
acct_num_56_descr_mbyte [bt_binaryl(20)]	
acct_num_57_descr_mbyte [bt_binaryl(20)]	
acct_num_58_descr_mbyte [bt_binaryl(20)]	
acct_num_59_descr_mbyte [bt_binaryl(20)]	
acct_num_60_descr_mbyte [bt_binaryl(20)]	
acct_num_61_descr_mbyte [bt_binaryl(20)]	
acct_num_62_descr_mbyte [bt_binaryl(20)]	
acct_num_63_descr_mbyte [bt_binaryl(20)]	
acct_num_64_descr_mbyte [bt_binaryl(20)]	
acct_num_65_descr_mbyte [bt_binaryl(20)]	
acct_num_66_descr_mbyte [bt_binaryl(20)]	
acct_num_67_descr_mbyte [bt_binaryl(20)]	
acct_num_68_descr_mbyte [bt_binaryl(20)]	
acct_num_69_descr_mbyte [bt_binaryl(20)]	
acct_num_70_descr_mbyte [bt_binaryl(20)]	
acct_num_71_descr_mbyte [bt_binaryl(20)]	
acct_num_72_descr_mbyte [bt_binaryl(20)]	
acct_num_73_descr_mbyte [bt_binaryl(20)]	
acct_num_74_descr_mbyte [bt_binaryl(20)]	
acct_num_75_descr_mbyte [bt_binaryl(20)]	
acct_num_76_descr_mbyte [bt_binaryl(20)]	
acct_num_77_descr_mbyte [bt_binaryl(20)]	
acct_num_78_descr_mbyte [bt_binaryl(20)]	
acct_num_79_descr_mbyte [bt_binaryl(20)]	
acct_num_80_descr_mbyte [bt_binaryl(20)]	

Card_Block (1.0) (crdbd)

The Card Block data source maintains stop list blocks by card data. The authorization process will use this new data source to determine if the transaction should be declined due to a block on the card data that limits the card's use.

[Audited] [Supports versioning]

OLTP: Card_Block_OLTP

Element (type)	Description
pan* [bt_stringf(28)]	The cardholder primary account number (PAN). This field is required for a block against Card data, therefore, enter the primary account number (PAN) of the cardholder. (Prikey)
crd_seq_num* [bt_stringf(3)]	The cardholder sequence number. If this record is for a block against "a specific" card sequence number, enter the sequence number of the cardholder. If this record is for a block against "any" card sequence number, this field requires only the default entry (all 9s in the data source, and all asterisks on the UI). (Prikey)
exp_dat* [yyyyymm 1.0]	The expiration date of the instrument in yyyyymm format. If this record is for a block against "a specific" expiration date, enter the expiration date of the card. If this record is for a block against "any" expiration date, this field requires only the default entry (all 9s in the data source, and all asterisks on the UI). (Prikey)
user_fld1 [bt_stringf(1)]	One byte filler/user field.
fm_ts [ts 1.0]	File Maintenance Timestamp. Timestamp of last update to the data source record.
refr_ts [yymmddhhmmss 1.0]	Refresh Time Stamp. Timestamp of the refresh that created this record.
refr_id [bt_stringf(32)]	An indicator of the refresh that created this record. This field is informational only.
crd_blk_ts [yymmddhhmmss 1.0]	Card Block Time Stamp. Timestamp that the block on the card was issued. (yymmddhhmmss)
blk_cde [bt_stringf(2)]	A code specifying the type of block/unblock placed on the Card data. Blocks can be configured for the following combination of Card data: * By PAN, Card Sequence Number, and Expiration Date. * By PAN and Card Sequence Number, where Expiration date is all asterisks. * By PAN and Expiration Date, where Card Sequence Number is all asterisks. * By PAN, where Card Sequence Number and Expiration Date are all asterisks. Valid values are any alphanumeric 2 digit code, with spaces being the default.

Card_Impacts (3.0) (crdimd)

The Card Impact table contains updates to the Card table as a result of online transactions. The table is used to impact the Card table following a full file replacement of the Card table.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pan* [bt_stringf(28)]	Primary Account Number
crd_seq_num* [bt_stringf(3)]	The card sequence number used to identify an individual member when several members have the same card number.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
updts [bt_stringv(3000)]	A tagged list of updates to an impacted file.

Card_Verification (1.0) (crdvd)

Card Verification contains information required for the secure management of cards in the system.

[Audited] [Supports versioning]

OLTP: Card_Verification_OLTP

Element (type)	Description
crd_vrfy_prfl* [prfl_def 1.0]	An identifier for the group to which this record applies. This field must contain a value that matches a CV_KEYA_PRFL defined in the Prefix data source.
beg_dat* [yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat* [yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
key_encrypt_1 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key/card verification key used for performing PIN verification/card verification. The value in this field is used when PIN verification/card verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_2 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key/card verification key used for performing PIN verification/card verification. The value in this field is used when PIN verification/card verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_chk_values_1 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_2 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.

Element (type)	Description
key_encrypt_1_hdr [keyx_hdr 1.0]	PIN Verification Key/Card Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_1_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.

Channel_Instrm_Type_Relation (2.0) (citrd)

The Channel Instrument Type Relation table contains one record for each instrument type a channel id supports that is not already specified in the Merchant Delivery Channel table. The Debit, Credit and Adjustment counts and amounts are maintained for each instrument type.

[Audited] [Supports versioning]

Element (type)	Description
chan_id*[chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
instrm_typ*[instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, Amercian Express, MasterCard, etc.
instrm_typ_db_cnt [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Channel_Instrument_Type_Rel (1.0) (cintrd)

The Channel/Instrument Type Relationship Profile data source is used to configure card instruments and channel limit profiles tied to a profile.

[Audited] [Supports versioning]

Element (type)	Description
[]	
chan_instrm_typ_rel_prfl* bt_stringf(16)]	Channel Instrument Type Relationship Profile. It is used to determine the limits profile by instrument type for a specific channel.
[]	
instrm_typ* [bt_stringf(2)]	Instrument Type. It is used to determine the limits profile by channel instrument type relationship profile for a specific channel.
[]	
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
[]	
chan_lmt_prfl [bt_stringf(16)]	Channel Limit Profile. It is used to access the transaction limits data in the Limits data source.
[]	

Channel_Public_Key_Security (3.0) (chnpkd)

Contains the public key information of the Encryption PIN Pad (EPP) of the channel device.

[Audited] [Supports versioning]

Element (type)	Description
chan_id* [chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pk_impl [bt_int16s]	Public Key implementation. Valid values are: 0 - NCR, 1 - Diebold, 2 - Wincor Signature
pk_epp_sig_hdr [keyx_hdr 1.0]	Signature Public Key header required for the Atalla Key Block (AKB) format.
pk_epp_sig_keyx [bt_binaryl(298)]	Public Key of the Encryption PIN Pad (EPP) used for signature/verification.
pk_epp_sig_kam [keyx_kam 1.0]	Signature Public Key MAC value required for the Atalla Key Block (AKB) format.
pk_epp_sig_vvk [bt_stringf(8)]	Signature Public Key - Verification Value. Contains the verification value of the encryption PIN pads (EPP) Signature Public Key. The verification value is used to detect key synchronization errors.
pk_epp_encipher_hdr [keyx_hdr 1.0]	Encipherment Public Key header required for the Atalla Key Block (AKB) format.
pk_epp_encipher_keyx [bt_binaryl(298)]	Public Key of the encryption PIN pad (EPP) used for encipherment/decipherment.

Element (type)	Description
pk_epp_encipher_kam [keyx_kam 1.0]	Encipherment Public Key MAC value required for the Atalla Key Block (AKB) format.
pk_epp_encipher_vvk [bt_stringf(8)]	Encipherment Public Key - Verification Value. Contains the verification value of the encryption PIN Pad (EPP) Encipherment Public Key. The verification value is used to detect key synchronization errors.
cert_iss_info [bt_binaryl(200)]	Contains the issuer information from a public key certificate.
pk_epp_sig_beg_dat [bt_int64s]	First day the EPP signature public key is valid.
pk_epp_sig_end_dat [bt_int64s]	Last day the EPP signature public key is valid.
pk_epp_encipher_beg_dat [bt_int64s]	First day the EPP encipher public key is valid.
pk_epp_encipher_end_dat [bt_int64s]	Last day the EPP encipher public key is valid.
epp_rndm_nonce [bt_binaryf(8)]	Random nonce generated by the terminals encrypting PIN pad (EPP).
host_rndm_nonce [bt_binaryf(8)]	Random nonce generated by the Host.
epp_serl_num [bt_stringf(16)]	Serial Number of the encryption PIN pad (EPP).

Channel_Security (6.0) (csecd)

Channel Security Data Source

[Audited] [Supports versioning]

Element (type)	Description
chan_id [chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pin_pad_char [bt_char]	PIN Pad character used to pad the PIN block. Valid values are 0 - 9, A - F. Default is F.
pin_blk_typ [bt_char]	PIN Block Type - specifies the PIN block format of the PIN in the inbound external messages. Valid values are: 0 - Clear, PINs are not encrypted. 1 - ANSI PIN block (ISO Format 0), default. 3 - PIN/Pad PIN block. 5 - ISO Format 1. 7 - DUKPT. 8 - ISO Format 3.
old_key_timr_lmt [bt_int32s]	This field specifies the timer used for clearing old/previous KAM(s), KDT(s) and KPT(s). This field is displayed as seconds but written to disk as hundredths of seconds. Allowed values in seconds: 0 - 99999. Default is 30.
kkt_pt_keyx [keyx_trpl 1.0]	PIN Transport - Encrypted Key. Contains the PIN key exchange key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_pt_vvk [vvk 1.0]	PIN Transport - Verification Value. Contains the verification value of the PIN key exchange key. The verification value is used to detect key synchronization errors.

Element (type)	Description
kkt_pt_variant [bt_char]	Encryption variant of the PIN key exchange key. Valid values are: 0 - Key Exchange Key Variant. 1 - PIN Encryption Key Variant. 5 - ATM Key Variant (applicable only for channel configuration). Default is 0.
kkt_am_keyx [keyx_trpl 1.0]	Message Authentication Transport - Encrypted Key. Contains the MAC key exchange key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_am_vvk [vvk 1.0]	Message Authentication Transport - Verification Value. Contains the verification value of the MAC key exchange key. The verification value is used to detect key synchronization errors.
kkt_am_variant [bt_char]	Encryption variant of the MAC key exchange key. Valid values are: 0 - Key Exchange Key Variant. 5 - ATM Key Variant. Default is 0.
inbnd_kpt1_keyx [keyx_trpl 1.0]	Inbound PIN Transport - Encrypted Key. Contains the PIN encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kpt1_vvk [vvk 1.0]	Inbound PIN Transport - Verification Value. Contains the verification value of the PIN key. The verification value is used to detect key synchronization errors.
inbnd_kpt_old_keyx [keyx_trpl 1.0]	Old Inbound PIN Transport - Encrypted Key. Contains the PIN encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first eight bytes with the second eight bytes set to spaces) or two parts (first key part in the first eight bytes and the second key part in the second eight bytes).
inbnd_kpt_old_vvk [vvk 1.0]	Old Inbound PIN Transport - Verification Value. Contains the verification value of the PIN key. The verification value is used to detect key synchronization errors.
inbnd_old_pin_timr [timr_id 1.0]	The timer tag for the inbound PIN key.
inbnd_kam1_keyx [keyx_trpl 1.0]	Inbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kam1_vvk [vvk 1.0]	Inbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.
inbnd_kam_old_keyx [keyx_trpl 1.0]	Old Inbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first eight bytes with the second eight bytes set to

Element (type)	Description
	spaces) or two parts (first key part in the first eight bytes and the second key part in the second eight bytes).
inbnd_kam_old_vvk [vvk 1.0]	Old Inbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.
inbnd_old_mac_timr [timr_id 1.0]	The timer tag for the inbound MAC key.
kkt_pt_hdr [keyx_hdr 1.0]	PIN key exchange key header required for the Atalla Key Block (AKB) format.
kkt_pt_lgth [bt_char]	PIN key exchange key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
kkt_pt_kam [keyx_kam 1.0]	PIN key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_am_hdr [keyx_hdr 1.0]	MAC key exchange key header required for the Atalla Key Block (AKB) format.
kkt_am_kam [keyx_kam 1.0]	MAC key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_am_lgth [bt_char]	MAC key exchange key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
inbnd_kpt1_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
inbnd_kpt1_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kpt_lgth [bt_char]	PIN Encryption Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
inbnd_kpt_old_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
inbnd_kpt_old_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kam1_hdr [keyx_hdr 1.0]	Inbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kam1_kam [keyx_kam 1.0]	Inbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kam_lgth [bt_char]	Inbound Message Authentication Transport - Encrypted Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
inbnd_kam_old_hdr [keyx_hdr 1.0]	Inbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kam_old_kam [keyx_kam 1.0]	Inbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
kam_typ [bt_int16s]	The type of Cipher Block Chaining (CBC) to use for MAC generation/verification. Valid values are: 0 - Single length DES Cipher Block Chaining. 1 - 3DES Cipher Block Chaining - uses both the left half and right half of the double length MAC key for all blocks of data (default) 2 - Pseudo 3DES Cipher Block Chaining - uses the left half of the double length MAC key for all blocks of data except the last block. The last data block is processed in a true 3DES operation using both the left and right half of the MAC key. 3 - Single DES Cipher Block Chaining w/ISO 9797-1 Method 2 Padding. 4 - 3DES Cipher Block Chaining w/ISO 9797-1 Method

Element (type)	Description
	2 Padding. 5 - AS2805.4.1 MAB output. 6 - AS2805.4.1 MAC output. 7 - Pseudo 3DES Cipher Block Chaining Method 2 Padding.
kkt_pt_old_hdr [keyx_hdr 1.0]	PIN key exchange key header required for the Atalla Key Block (AKB) format.
kkt_pt_old_keyx [keyx_trpl 1.0]	Old PIN Transport - Exchange Key. Contains the old PIN key exchange key that is encrypted under the master key of the hardware security module. May be one part (contained in the first eight bytes with the second eight bytes set to spaces) or two parts (first key part in the first eight bytes and the second key part in the second eight bytes).
kkt_pt_old_kam [keyx_kam 1.0]	PIN key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_pt_old_vvk [vvk 1.0]	PIN Transport - Old Verification Value. Contains the old verification value of the PIN key exchange key. The verification value is used to detect key synchronization errors.
kkt_am_old_hdr [keyx_hdr 1.0]	MAC key exchange key header required for the Atalla Key Block (AKB) format.
kkt_am_old_keyx [keyx_trpl 1.0]	Old MAC Transport - Exchange Key. Contains the old MAC key exchange key that is encrypted under the master key of the hardware security module. May be one part (contained in the first eight bytes with the second eight bytes set to spaces) or two parts (first key part in the first eight bytes and the second key part in the second eight bytes).
kkt_am_old_kam [keyx_kam 1.0]	MAC key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_am_old_vvk [vvk 1.0]	Message Authentication Transport - Old Verification Value. Contains the old verification value of the MAC key exchange key. The verification value is used to detect key synchronization errors.
kkt_old_pt_timr [timr_id 1.0]	The timer tag for the PIN key exchange key.
kkt_old_am_timr [timr_id 1.0]	The timer tag for the MAC key exchange key.
extrn_key_blk_frmt [bt_char]	The format of the key block that an external entity (e.g., interface, device handler) supports. Valid values are: 0 - Standard Atalla (Atalla only)(default for Atalla). 1 - New Atalla Key Block (AKB) (Atalla only). 2 - ANSI X9.17 method (Racal only). 3 - Variant Method (Racal only) (default for Racal).
encrypt_data_typ [bt_char]	Data encryption data type. Valid values are: B - Binary. U - Unpacked ASCII hexadecimal(default).
encrypt_des_mde [bt_int16s]	Encryption mode for data encryption. Valid values are: 0 - ECB (Electronic Code Book) (default). 1 - CBC (Cipher Block Chaining). 2 - CFB-8 (Cipher Feedback, 8 bits). 3 - CFB-64 (Cipher Feedback, 64 bits). 4 - OFB-64 (Output Feedback, 64 bits). Valid values for EMV: 0 - ECB (default). 1 - CBC.
encrypt_layers [bt_int16s]	Levels of encryption to be performed for data encryption. Valid values are: 1 - One level (inner layer) (default). 2 - Two levels (inner and outer layers).
kkt_dt_hdr [keyx_hdr 1.0]	Data encryption key exchange key header required for the Atalla Key Block (AKB) format.
kkt_dt_keyx [keyx_trpl 1.0]	Data Encryption Transport - Import Encryption Key. Contains the data encryption key exchange key encrypted under the master key of the hardware security module. This key is used for importing data encryption key exchange keys from another system. May be one part (contained in the first 16 bytes with the remaining

Element (type)	Description
	32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_dt_kam [keyx_kam 1.0]	Data encryption key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_dt_vvk [vvk 1.0]	Data Encryption Transport - Verification Value. Contains the verification value of the data encryption import key exchange key. The verification value is used to detect key synchronization errors.
kkt_dt_old_hdr [keyx_hdr 1.0]	Data encryption key exchange key header required for the Atalla Key Block (AKB) format.
kkt_dt_old_keyx [keyx_trpl 1.0]	Old Data Encryption Transport - Exchange Key. Contains the old data encryption key exchange key that is encrypted under the master key of the hardware security module. May be one part (contained in the first eight bytes with the second eight bytes set to spaces) or two parts (first key part in the first eight bytes and the second key part in the second eight bytes).
kkt_dt_old_kam [keyx_kam 1.0]	Data encryption key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_dt_old_vvk [vvk 1.0]	Data Encryption Transport - Old Verification Value. Contains the old verification value of the data encryption key exchange key. The verification value is used to detect key synchronization errors.
kkt_dt_variant [bt_char]	Encryption variant of the data encryption key exchange key. Valid values are: 0 - Key Exchange Key Variant. 2 - Data Encryption Key Variant. Default is 0.
kkt_dt_lgth [bt_char]	Data encryption key exchange key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
kkt_old_dt_timr [timr_id 1.0]	The timer tag for the data encryption key exchange key.
outbnd_iv_hdr [keyx_hdr 1.0]	Initialization Vector header required for the Atalla Key Block (AKB) format.
outbnd_iv_keyx [keyx_trpl 1.0]	Initialization Vector. Contains the Initialization Vector encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_iv_kam [keyx_kam 1.0]	Initialization Vector MAC value required for the Atalla Key Block (AKB) format.
kam_lgth [bt_int16s]	Length of MAC to be returned from a call to a MAC generate function. Valid values are: 1 - 32 bits (default). 2 - 48 bits. 3 - 64 bits.
outbnd_kdt1_lvl1_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl1_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three

Element (type)	Description
	parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt1_lvl1_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl1_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_kdt1_lvl2_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 2 / Outer Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl2_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 2 / Outer Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt1_lvl2_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl2_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 2 / Outer Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_kdt1_lvl1_old_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl1_old_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt1_lvl1_old_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl1_old_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_kdt1_lvl2_old_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 2 / Outer Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl2_old_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 2 / Outer Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt1_lvl2_old_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
outbnd_kdt1_lvl2_old_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 2 / Outer Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_old_data_timr [timr_id 1.0]	The timer tag for the outbound data encryption key.
outbnd_kdt_lgth [bt_char]	Data Encryption Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
kkt_am_export_vrnt [bt_char]	Variant under which the device MAC key will be generated. Valid values are: 0 - Key Exchange Key Variant (default). 3 - MAC Encryption Key Variant. 5 - ATM Master Key Variant.
outbnd_kam1_hdr [keyx_hdr 1.0]	Outbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kam1_keyx [keyx_trpl 1.0]	Outbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kam1_kam [keyx_kam 1.0]	Outbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kam1_vvk [vvk 1.0]	Outbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.
outbnd_old_mac_timr [timr_id 1.0]	The timer tag for the outbound MAC key.
outbnd_kam_old_hdr [keyx_hdr 1.0]	Outbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kam_old_keyx [keyx_trpl 1.0]	Old Outbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first eight bytes with the second eight bytes set to spaces) or two parts (first key part in the first eight bytes and the second key part in the second eight bytes).
outbnd_kam_old_kam [keyx_kam 1.0]	Outbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kam_old_vvk [vvk 1.0]	Old Outbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.
key_rgstr_init [keyx_trpl 1.0]	Initial Key Register for APACS functions. The key register is used with other data to derive a key via a one-way function.
key_rgstr_new [keyx_trpl 1.0]	New Key Register for APACS functions. The key register is used with other data to derive a key via a one-way function.
key_rgstr_cur [keyx_trpl 1.0]	Current Key Register for APACS functions. The key register is used with other data to derive a key via a one-way function.

Element (type)	Description
key_rgstr_prev [keyx_trpl 1.0]	Previous Key Register for APACS functions. The key register is used with other data to derive a key via a one-way function.
ppasn [bt_stringf(18)]	PIN Pad Acquirer Serial Number prefaced with the KM index.
outbnd_kam_lgth [bt_char]	Outbound Message Authentication Transport - Encrypted Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
chan_dev_typ [bt_char]	The device type of the channel. Valid values are: blank (default). A - ATM. P - POS.
inbnd_kam_key_typ [bt_int16s]	Indicates the type of key for the inbound MAC key. Only applicable for Thales AS2805 MACing. Valid values are: 0 - TAK (default). 1 - TAKr
outbnd_kam_key_typ [bt_int16s]	Indicates the type of key for the outbound MAC key. Only applicable for Thales AS2805 MACing. Valid values are: 0 - TAK (default). 1 - TAKs
inbnd_kdt_key_typ [bt_int16s]	Indicates the type of key for the inbound Data Encryption key. Only applicable for Thales AS2805 data encryption. Valid values are: 0 - TEK (default). 1 - TEKr
outbnd_kdt_key_typ [bt_int16s]	Indicates the type of key for the outbound Data Encryption key. Only applicable for Thales AS2805 data encryption. Valid values are: 0 - TEK (default). 1 - TEKs
inbnd_kdt1_lvl1_hdr [keyx_hdr 1.0]	Inbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl1_keyx [keyx_trpl 1.0]	Inbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kdt1_lvl1_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl1_vvk [vvk 1.0]	Inbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
inbnd_kdt_lgth [bt_char DEFAULT 1]	Inbound Data Encryption Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
inbnd_kdt1_lvl1_old_hdr [keyx_hdr 1.0]	Inbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl1_old_keyx [keyx_trpl 1.0]	Inbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kdt1_lvl1_old_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl1_old_vvk [vvk 1.0]	Inbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.

Element (type)	Description
cross_acq_hdr [keyx_hdr 1.0]	AS2805 Cross Acquirer Key (KCA) - Encrypted Key header required for the Atalla Key Block (AKB) format.
cross_acq_keyx [keyx_trpl 1.0]	AS2805 Cross Acquirer Key (KCA). Contains the cross acquirer key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
cross_acq_kam [keyx_kam 1.0]	AS2805 Cross Acquirer Key (KCA) MAC value required for the Atalla Key Block (AKB) format.
cross_acq_vvk [vvk 1.0]	AS2805 Cross Acquirer Key (KCA)- Verification Value. Contains the verification value of the cross acquirer key. The verification value is used to detect key synchronization errors.
cross_acq_lgth [bt_char DEFAULT 1]	AS2805 Cross Acquirer Key (KCA) length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
acq_init_hdr [keyx_hdr 1.0]	AS2805 Initial Acquirer Key (KIA) - Encrypted Key header required for the Atalla Key Block (AKB) format.
acq_init_keyx [keyx_trpl 1.0]	AS2805 Initial Acquirer Key (KIA). Contains the initial acquirer key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
acq_init_kam [keyx_kam 1.0]	AS2805 Initial Acquirer Key (KIA) MAC value required for the Atalla Key Block (AKB) format.
acq_init_vvk [vvk 1.0]	AS2805 Initial Acquirer Key (KIA)- Verification Value. Contains the verification value of the initial acquirer key. The verification value is used to detect key synchronization errors.
acq_init_lgth [bt_char DEFAULT 1]	AS2805 Initial Acquirer Key (KIA) length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
init_kam_hdr [keyx_hdr 1.0]	AS2805 Initial MAC Key (KMACI) - Encrypted Key header required for the Atalla Key Block (AKB) format.
init_kam_keyx [keyx_trpl 1.0]	AS2805 Initial MAC Key (KMACI). Contains the initial MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
init_kam_kam [keyx_kam 1.0]	AS2805 Initial MAC Key (KMACI) MAC value required for the Atalla Key Block (AKB) format.
init_kam_vvk [vvk 1.0]	AS2805 Initial MAC Key (KMACI)- Verification Value. Contains the verification value of the initial MAC key. The verification value is used to detect key synchronization errors.
init_kam_lgth [bt_char DEFAULT 1]	AS2805 Initial MAC Key (KMACI) length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.

Element (type)	Description
mstr1_hdr [keyx_hdr 1.0]	AS2805 Master Key 1 (TMK1/KEK1) - Encrypted Key header required for the Atalla Key Block (AKB) format.
mstr1_keyx [keyx_trpl 1.0]	AS2805 Master Key 1 (TMK1/KEK1). Contains the AS2805 Master Key1 encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
mstr1_kam [keyx_kam 1.0]	AS2805 Master Key 1(TMK1/KEK1) MAC value required for the Atalla Key Block (AKB) format.
mstr1_vvk [vvk 1.0]	AS2805 Master Key 1 (TMK1/KEK1)- Verification Value. Contains the verification value of the Master Key 1. The verification value is used to detect key synchronization errors.
mstr1_lgth [bt_char DEFAULT 1]	AS2805 Master Key 1 (TMK1/KEK1) length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
mstr1_old_hdr [keyx_hdr 1.0]	AS2805 Old Master Key 1 (TMK1/KEK1) - Encrypted Key header required for the Atalla Key Block (AKB) format.
mstr1_old_keyx [keyx_trpl 1.0]	AS2805 Old Master Key 1 (TMK1/KEK1). Contains the AS2805 Old Master Key1 encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
mstr1_old_kam [keyx_kam 1.0]	AS2805 Old Master Key 1(TMK1/KEK1) MAC value required for the Atalla Key Block (AKB) format.
mstr1_old_vvk [vvk 1.0]	AS2805 Old Master Key 1 (TMK1/KEK1)- Verification Value. Contains the verification value of the Old Master Key 1. The verification value is used to detect key synchronization errors.
mstr2_hdr [keyx_hdr 1.0]	AS2805 Master Key 2 (TMK2/KEK2) - Encrypted Key header required for the Atalla Key Block (AKB) format.
mstr2_keyx [keyx_trpl 1.0]	AS2805 Master Key 2 (TMK2/KEK2). Contains the AS2805 Master Key2 encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
mstr2_kam [keyx_kam 1.0]	AS2805 Master Key 2(TMK2/KEK2) MAC value required for the Atalla Key Block (AKB) format.
mstr2_vvk [vvk 1.0]	AS2805 Master Key 2 (TMK2/KEK2)- Verification Value. Contains the verification value of the Master Key 2. The verification value is used to detect key synchronization errors.
mstr2_lgth [bt_char DEFAULT 1]	AS2805 Master Key 2 (TMK2/KEK2) length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
mstr2_old_hdr [keyx_hdr 1.0]	AS2805 Old Master Key 2 (TMK2/KEK2) - Encrypted Key header required for the Atalla Key Block (AKB) format.

Element (type)	Description
mstr2_old_keyx [keyx_trpl 1.0]	AS2805 Old Master Key 2 (TMK2/KEK2). Contains the AS2805 Old Master Key2 encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
mstr2_old_kam [keyx_kam 1.0]	AS2805 Old Master Key 2(TMK2/KEK2) MAC value required for the Atalla Key Block (AKB) format.
mstr2_old_vvk [vvk 1.0]	AS2805 Old Master Key 2 (TMK2/KEK2)- Verification Value. Contains the verification value of the Old Master Key 2. The verification value is used to detect key synchronization errors.
inbnd_old_data_timr [timr_id 1.0]	The timer tag for the inbound data encryption key.
zka_drv_flg [bt_int16s]	Flag indicating if ZKA key derivation is utilized by this channel. Valid values are: 0 = Channel does not use ZKA key derivation (default) 1 = Channel uses ZKA key derivation (This field is used for the German Security feature)
key_gen_num [bt_stringf(2)]	Key Generation Number (KGN) for the Derivation Key. (This field is used for the German Security feature)
key_ver_num [bt_stringf(2)]	Key Version Number (KVN) for the Derivation Key. (This field is used for the German Security feature)
key_table_num [bt_int16s DEFAULT 1]	Key Table Number (KTN) for the Derivation Key. Valid values are: 01 = Production (default) 02 = Emergency Production 03 = Test 04 = Emergency Test (This field is used for the German Security feature)
drv_depth [bt_int16s]	The derivation depth of the Derivation Key. Valid values are: 0 = Derivation Depth 0 (default) 1 = Derivation Depth 1 (This field is used for the German Security feature)
drv_id [bt_stringf(16)]	The derivation id. (This field is used for the German Security feature)
key_hierarchy [bt_char DEFAULT 2]	The key hierarchy used. Valid values are: 2 = two levels of keys used (default) 3 = three levels of keys used
kkt_opt [bt_char DEFAULT 1]	KKT option. Valid values are: 0 = Separate KKTs (i.e. one KKT per working key) 1 = Single KKT (default)

Channel_Security_Future (1.0) (csecfd)

Channel Security Data Source for future/pending keys information

[Audited] [Supports versioning]

Element (type)	Description
chan_id*[chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mstr1_export_futr_hdr [keyx_hdr 1.0]	Future Export Master KEK - Header. Only used with Atalla Key Block key format.
mstr1_export_futr_keyx [keyx_trpl 1.0]	Future Export Master KEK Key value.
mstr1_export_futr_kam [keyx_kam 1.0]	Future Export Master KEK MAC.
mstr1_export_futr_vvk [vvk 1.0]	Future Export Master KEK check digits.
kkt_pt_futr_hdr [keyx_hdr 1.0]	Future Export PIN KEK - Header.
kkt_pt_futr_keyx [keyx_trpl 1.0]	Future Export PIN KEK - Key value.
kkt_pt_futr_kam [keyx_kam 1.0]	Future Export PIN KEK - MAC.
kkt_pt_futr_vvk [vvk 1.0]	Future Export PIN KEK - check digits.
kkt_am_futr_hdr [keyx_hdr 1.0]	Future Export MAC KEK - Header.
kkt_am_futr_keyx [keyx_trpl 1.0]	Future Export MAC KEK - Key value.
kkt_am_futr_kam [keyx_kam 1.0]	Future Export MAC KEK - MAC.
kkt_am_futr_vvk [vvk 1.0]	Future Export MAC KEK - check digits.
kkt_dt_futr_hdr [keyx_hdr 1.0]	Future Export Data KEK - Header.
kkt_dt_futr_keyx [keyx_trpl 1.0]	Future Export Data KEK - Key value.
kkt_dt_futr_kam [keyx_kam 1.0]	Future Export Data KEK - MAC.
kkt_dt_futr_vvk [vvk 1.0]	Future Export Data KEK - check digits.
inbnd_kpt_futr_hdr [keyx_hdr 1.0]	Future Inbound PIN Encryption Key Header.
inbnd_kpt_futr_keyx [keyx_trpl 1.0]	Future Inbound PIN Encryption Key Key value.
inbnd_kpt_futr_kam [keyx_kam 1.0]	Future Inbound PIN Encryption Key MAC.
inbnd_kpt_futr_vvk [vvk 1.0]	Future Inbound PIN Encryption Key check digits.
inbnd_kam_futr_hdr [keyx_hdr 1.0]	Future Inbound MAC Encryption Key Header.
inbnd_kam_futr_keyx [keyx_trpl 1.0]	Future Inbound MAC Encryption Key Key value.
inbnd_kam_futr_kam [keyx_kam 1.0]	Future Inbound MAC Encryption Key MAC.
inbnd_kam_futr_vvk [vvk 1.0]	Future Inbound MAC Encryption Key check digits.
outbnd_kam_futr_hdr [keyx_hdr 1.0]	Future Outbound MAC Encryption Key Header.
outbnd_kam_futr_keyx [keyx_trpl 1.0]	Future Outbound MAC Encryption Key Key value.
outbnd_kam_futr_kam [keyx_kam 1.0]	Future Outbound MAC Encryption Key MAC.
outbnd_kam_futr_vvk [vvk 1.0]	Future Outbound MAC Encryption Key check digits.
inbnd_kdt1_lvl1_futr_hdr [keyx_hdr 1.0]	Future Inbound Data Encryption Key (Level 1) Header.
inbnd_kdt1_lvl1_futr_keyx [keyx_trpl 1.0]	Future Inbound Data Encryption Key (Level 1) Key value.
inbnd_kdt1_lvl1_futr_kam [keyx_kam 1.0]	Future Inbound Data Encryption Key (Level 1) MAC.
inbnd_kdt1_lvl1_futr_vvk [vvk 1.0]	Future Inbound Data Encryption Key (Level 1) check digits.
inbnd_kdt1_lvl2_futr_hdr [keyx_hdr 1.0]	Future Inbound Data Encryption Key (Level 2) Header.

Element (type)	Description
inbnd_kdt1_lvl2_futr_keyx [keyx_trpl 1.0]	Future Inbound Data Encryption Key (Level 2) Key value.
inbnd_kdt1_lvl2_futr_kam [keyx_kam 1.0]	Future Inbound Data Encryption Key (Level 2) MAC.
inbnd_kdt1_lvl2_futr_vvk [vvk 1.0]	Future Inbound Data Encryption Key (Level 2) check digits.
outbnd_kdt1_lvl1_futr_hdr [keyx_hdr 1.0]	Future Outbound Data Encryption Key (Level 1) Header.
outbnd_kdt1_lvl1_futr_keyx [keyx_trpl 1.0]	Future Outbound Data Encryption Key (Level 1) Key value.
outbnd_kdt1_lvl1_futr_kam [keyx_kam 1.0]	Future Outbound Data Encryption Key (Level 1) MAC.
outbnd_kdt1_lvl1_futr_vvk [vvk 1.0]	Future Outbound Data Encryption Key (Level 1) check digits.
outbnd_kdt1_lvl2_futr_hdr [keyx_hdr 1.0]	Future Outbound Data Encryption Key (Level 2) Header.
outbnd_kdt1_lvl2_futr_keyx [keyx_trpl 1.0]	Future Outbound Data Encryption Key (Level 2) Key value.
outbnd_kdt1_lvl2_futr_kam [keyx_kam 1.0]	Future Outbound Data Encryption Key (Level 2) MAC.
outbnd_kdt1_lvl2_futr_vvk [vvk 1.0]	Future Outbound Data Encryption Key (Level 2) check digits.

Chan_Profile_Instrm_Typ_Relation (2.0) (cpitrd)

The Channel Profile Instrument Type Relation table contains one record for each Channel Profile and instrument type combination allowed by the channel.

[Audited] [Supports versioning]

Element (type)	Description
chan_prfl*[prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
instrm_typ*[instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, Amercian Express, MasterCard, etc.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_tot_flg [bt_flag]	A flag indicating whether this instrument types totals should be kept with the Merchant Delivery Channel table or in the Channel Instrument Type Relation table. A limit of 10 entries may be flagged as being kept in the Merchant Delivery Channel table which avoid an extra I/O for performance. Valid values are: 1 - keep totals for instrument type in Merchant Delivery Channel table, 0 - keep totals for instrument type in Channel Instrument Type Relation table. Default value is 1 for the first 10 entries, 0 for entries after the first 10.
captr_mde [bt_int16s]	Capture mode specifying the type of action to be taken. Valid values are: 0 - Authorize only, 1 - Authorize and Capture, 2 - Authorize only with electronic follow-up later on, 3- Channel determines data capture mode for each transaction. (The SPDH only supports authorize only and authorize and capture.)

Element (type)	Description
bal_returned [bt_flag]	A flag indicating whether the channel manager should return the Available Balance to the device. Valid values are 0 – do not return balance, 1 – return the balance. Default value is 0.

Check_Status (1.0) (chkstd)

The Check Status data source contains one record for every pre-approved/ declined or registered check that may be acquired at a terminal.

[Audited] [Supports versioning]

Element (type)	Description
rttn*[bt_stringf(11)]	The routing and transit number of the check issuing institution or check-issuer identification number. This value is derived from the check MICR data. Values are right-justified and zero-filled, containing only numeric characters.
chk_acct_num*[bt_stringf(28)]	The checking account number derived from the check MICR information.
pan*[bt_stringf(28)]	Primary Account Number. Default value is all 9's (all *'s on the UI).
crd_seq_num*[bt_stringf(3)]	The card sequence number used to identify an individual member when several members have the same card number. Default value is all 9's (all *'s on the UI).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record.
refr_ts [yymmddhhmmss 1.0]	Refresh Time Stamp. Timestamp of the refresh that created this record.
refr_id [bt_stringf(32)]	An indicator of the refresh that created this record. This field is informational only.
chk_stat [bt_stringf(1)]	A code specifying the disposition of a check with this routing/transit number and account number. Valid values are as follows: 0 = Accept all checks 1 = Deposit only 2 = Deny all checks Default value is 0 = Accept all checks.
chk_ret_flg [bt_int16s]	The retain status for declined transactions for a check with this routing/transit number and account number. Valid values are as follows: 0 = Return all checks 1 = Retain all checks Default value is 0 = Return all checks.
chk_amt_lmt [bt_int64s]	The maximum acceptable check amount, expressed as a whole currency value, for a check with this routing and transit number and account number. Checks above the specified limit are not authorized. This field is not required if the chk_stat field value indicates that the check should be declined. Default value is zero.
chk_amt_lmt_crncy_cde [crncy_cde 1.0]	A three-digit ISO 4217 code (e.g., 840 for U. S.) indicating the currency of the Check Amount Limit amount. Default value is 840.

Check_Type (1.0) (cktypd)

The Check Type data source provides the institution with the ability to configure the amount of time that a stop payment will be in effect per check type.

[Audited] [Supports versioning]

OLTP: Check_Type_OLTP

Element (type)	Description
inst_id*[inst_id 1.0]	The ID of the financial institution.
chk_typ*[bt_stringf(2)]	The type of check supported by the financial institution. Valid values are 01 - 99. For example: 01 could indicate personal check, 02 could indicate business check, etc. Also, the check type's values may differ from institution to institution. For example, institution BankOne may use 01 to specify a personal check, and institution BankTwo may use 02 to specify a personal check.
chk_typ_descr [bt_stringf(35)]	The description for Check Type (e.g., Personal, Business, Government, etc.) supported by the financial institution. The default value is spaces.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record.
chk_typ_exp_prd_opt [bt_int16s]	The option for the expiration period for the check type. Valid values are: 1 = fixed number of days (default). 2 = fixed number of weeks.
chk_typ_exp_prd_val [bt_int16s]	The check type expiration date period value based on the check type expiration period option. For example: This value would indicate the number of days if the check type expiration period option is 1. This value would indicate the number of weeks if the check type expiration period option is 2. Valid values are: 0 - 999. The default value is 90.

Chip_Authentication (1.0) (cad)

Chip Authentication contains data at a Card Prefix level required by a CAP Transaction which is not in the current EMV Security data source.

[Audited] [Supports versioning]

OLTP: Chip_Authentication_OLTP

Element (type)	Description
chip_auth_prfl*[prfl_def 1.0]	A profile name used to access the Chip Authentication data source. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
beg_dat*[yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat*[yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
emv_auth_key_prfl [prfl_def 1.0]	A profile used to access the Authorization Key file which contains the key data required for CAM verification. This field is left-justified, upper case (containing any

Element (type)	Description
	combination of alphanumeric and special characters, but without embedded spaces). If this field is spaces, CAM authentication will not be performed. The default value is spaces.
iss_appl_data_frmt [bt_char]	Specifies the format of the EMV Issuer Application Data that will be used for the card prefix. A number of predefined formats for Issuer Application Data exist, as specified by the Payment Associations (Visa and Mastercard/Europay), but Issuer specific layouts may also be defined. Issuer Application Data typically contains information which is used in the derivation of the Application Cryptogram. Valid values are: 0 - Unspecified (format unknown, the contents will be transported as passthrough data), 1 - Issuer Application Data Format defined by Visa in the Visa Integrated Circuit Card Specification. (Note this format is used for UKIS cards). 2 - Issuer Application Data format as recommended for Mastercard/Europay MCPA (MCHIP) cards. 3 - M/Chip4.
appl_ichg_prfl [bt_binaryf(2)]	Application Interchange Profile for the Chip Authentication application. For separate Chip Authentication applications this will usually be 0x10000 but it may be different for EMV Payment applications used for Chip Authentication.
predicted_crd_vrfy_rslts [bt_stringf(60)]	The predicted Card Verification Results (CVR) left-justified space padded.
predicted_init_crd_vrfy_rslts [bt_stringf(60)]	The predicted Initial Card Verification Results (CVR) left-justified space padded.
use_init_crd_vrfy_rslts [bt_int16s]	Indicates use of predicted_init_crd_vrfy_rslts. Valid values are: 0 - Never (default), 1 - At ATC == 0, 2 - At ATC == 1.
internet_auth_flg [bt_binaryf(1)]	Chip Authentication Internet Authentication Flags.
iss_prop_bit_map [bt_stringf(88)]	Card Authentication Issuer Proprietary Bitmap, Hex characters, left-justified space padded.
chip_auth_appl [bt_int16s]	Indicates the application implied by the cards AID. Valid values are: 0 - CAP (default). 1 - DPA.
appl_txn_cntr_resync [bt_int16s]	ATC Resynchronization Parameter. Default 0.
hsm_spcf [bt_stringf(64)]	Free format character string for HSM specific parameters.
crypto_ver_num [bt_stringf(2)]	EMV Cryptographic Version Number. Valid values for EMV scheme Visa: 0A, 0E. Valid values for EMV scheme MasterCard: 00 - 0F, 10, 11, 12, 13, 14, 15. Valid values for EMV scheme CCD: x5.

Circuit_Interface (1.0) (crctfd)

The Circuit Interface Table.

[Audited] [Supports versioning]

OLTP: Circuit_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
atm_ind [bt_flag]	This is a boolean flag to indicate the interface supports sending and receiving ATM transactions. A value of false indicates the interface supports POS transactions. Circuit requires different processing and separate connections for ATM and POS.
gtwy_prcsr_id [bt_stringf(10)]	A value assigned by Circuit to identify the Gateway processor in outbound network management requests to Circuit.
gtwy_prcsr_pswd [bt_stringf(16)]	A value assigned by Circuit to identify the Gateway password in inbound network management requests from Circuit.
prtcp_prcsr_id [bt_stringf(10)]	A value assigned by Circuit to identify the Participant processor in outbound network management requests to Circuit.
prtcp_prcsr_pswd [bt_stringf(16)]	A value assigned by Circuit to identify the Participant password in outbound network management requests to Circuit.

CMPTPRFL (1.0) (cmptd)

This data source contains configuration data for ATM BASE24 compatibility processing. This data is accessed through the compatibility profile located on the ATM Static Data Table (ESATDS1).

[Audited] [Supports versioning]

Element (type)	Description
CmptbltyPrflTx*[prfl_def 1.0]	The compatibility profile identifies the elements required for BASE24 compatibility.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
DHPrcsNameTx [bt_stringf(16)]	The name of a device handler process. This element is stored on the ES ATM Configuration Properties file (ATDCNFG). It is only used in cases where the ES device handler is running in a BASE24 Classic system.
AuthPrcsNameTx [bt_stringf(16)]	The authorization process queue name. This data is used when an ES ATM device handler is configured in a BASE24 Classic environment. It contains the name of the authorization process which handles requests from the device.
ShrnGrpTx [bt_stringf(24)]	The ATM sharing group defined for an ATM terminal. The data is configured in the ATD Configuration Profile table (ATDCNFG). It is passed to the authorization system where it is used to determine if the transaction is allowed.

Compiler_Message (2.0) (cmsgd)

The Compiler Message table contains one record for each message which is generated by the script compiler for errors and warnings. The record contains the severity of the message, the message text and message detail.

[Audited] [Supports versioning]

Element (type)	Description
cmplr_msg_num* [bt_int32s]	The script compiler message number.
cmplr_severity [bt_char]	The severity of the script compiler message. Valid values are: I - The message number represents an informational message, W - The message number indicates a compiler warning, E - The message number indicates a compiler error
cmplr_msg_txt [bt_stringf(78)]	The message text of the script compiler information, warning or error condition.
cmplr_msg_detail [bt_stringf(624)]	The optional message detail of the script compiler error or warning message to assist script writers in resolving script compilation problems.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Context (1.0) (ctxd)

This Context table stores context for a client component. If client context exceeds the limits of a single record, the context is stored in multiple records. A context record has an expiration timestamp after which a clean up program will delete the record if the client has not already done so. The assigns for the context tables are defined in the Context Configuration table to allow a number of Context tables to be shared or kept separate by different clients.

[Not Audited] [Supports versioning]

Element (type)	Description
cmpnt_id* [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ctx_key* [bt_stringf(80)]	The context key supplied by the client when storing and retrieving context data.
ctx_rec_num* [bt_int16s]	The number of the context record within a set of records.
ctx_exp_ts [bt_int64s]	The timestamp when the context record should expire and the record can later be deleted.
ctx_clt_data_lgth [bt_int16s]	The length of the client data in the context record.
ctx_timr_data_lgth [bt_int16s]	The length of the timer data in the context record needed to cancel a timer.
ctx_data [bt_binaryv(3956)]	The context data area. Can contain client data and/or timer data.

Context Configuration (1.0) (ctxcd)

The Context Configuration table contains one record for each context group that is defined in the system. The record defines the assign name to use for a Context table. The assign name represents a logical data source which allows multiple Context tables to be defined based on the clients of Context Component.

[Audited] [Supports versioning]

OLTP: Context_Configuration_OLTP

Element (type)	Description
ctx_prfl*[bt_stringf(16)]	The context profile of the client attempting to store or retrieve context. This field is left-justified, upper case (containing any combination of alpha-numeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ctx_asgn_nam [bt_stringf(32)]	The assign name of the Context table. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
descr [bt_stringv(400)]	This field documents the purpose of the specific record.

Context_USEC (1.0) (ucntxt)

Context table

[Audited] [Supports versioning]

Element (type)	Description
ContextID*[bt_int32s]	
Descr [bt_stringf(50)]	

Contingency_Interface (1.0) (ctgyd)

The Contingency Interface configuration table contains a record for each contingency interface defined in the system.

[Audited] [Supports versioning]

OLTP: Contingency_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
enabled_flg [bt_flag]	A flag indicating whether the contingency interface is enabled or disabled. Valid values are: 1 - Contingency Interface is enabled, 0 - Contingency Interface is disabled. Default value is 1.

Credit_Debit_Master_File (1.0) (cdmfd)

This data source is used to populate certain data in the various PRM message formats. If a record is not found for a specific key, values are obtained from a default record.

[Audited] [Supports versioning]

OLTP: Credit_Debit_Master_File_OLTP

Element (type)	Description
prm_fiid* [bt_stringf(9)]	The FIID or ABA number of the financial institution that issued the card. This value must be unique within the logical network.
prm_pan* [bt_stringf(19)]	The card number (PAN) identifying the card (left-justified, blank-filled). This field contains the card number carried in Track 2 of the card.
prev_crd_num [bt_stringf(19)]	The card number (PAN) identifying the previous card for this cardholder (left-justified, blank-filled). Default is spaces.
pri_nam [bt_stringf(40)]	The name of the primary cardholder. Default is spaces.
pri_govt_id [bt_stringf(20)]	Social security number of the primary cardholder. Default is spaces.
pri_dob [bt_stringf(8)]	The primary cardholders date of birth in the format YYYYMMDD. Default is zeroes.
sec_nam [bt_stringf(40)]	The name of the secondary cardholder. Default is spaces.
adnl_nam [bt_stringf(40)]	The name of a third authorized user. This field is optional; the default is spaces.
othr_nam [bt_stringf(40)]	Mothers maiden name. This field is optional; the default is spaces.
prm_addr_1 [bt_stringf(40)]	The first line of the primary cardholders street address. Default is spaces.
prm_addr_2 [bt_stringf(40)]	The second line of the primary cardholders street address. Default is spaces.
prm_city [bt_stringf(30)]	The primary cardholders city of residence. This field is optional; the default is spaces.
prm_st [bt_stringf(30)]	The alpha representation of the primary cardholders state of residence. This field may also contain the province or region where the primary cardholder resides. Refer to the FIPS Processing Standards Publication 6-3 for valid state codes. Default is spaces.
cntry_cde [bt_stringf(3)]	3 Alphabetic characters Country Code.
prm_postal_cde [bt_stringf(16)]	The postal code/zip code for the primary cardholders residence. Default is spaces.
home_phn [bt_stringf(20)]	The primary cardholders home telephone number. This field is optional. The data in this field will be left-justified; the default is spaces.
wrk_phn [bt_stringf(20)]	The primary cardholders work telephone number. This field is optional. The data in this field will be left-justified; the default is spaces.
mob_phn [bt_stringf(20)]	The primary cardholders work telephone number. This field is optional. The data in this field will be left-justified; the default is spaces.
prm_email_addr [bt_stringf(40)]	Email address for the primary cardholder. Default is spaces.

Element (type)	Description
prm_cust_id [bt_stringf(30)]	Customer identification. This field may be used for a customer reference number, password, place of birth, or other security or identifying information. Default is spaces.
prod_typ [bt_stringf(2)]	Code for the product associated with this card; for example, Gold or Classic. Default is spaces.
plastic_typ [bt_stringf(2)]	Type of plastic or cardholder agreement. Default is spaces.
rqst_dat [bt_stringf(8)]	Date of last card request in the format YYYYMMDD. Default is zeroes.
pin_chng [bt_stringf(8)]	Date of last pin change in the format YYYYMMDD. Default is zeroes.
last_iss [bt_stringf(8)]	Last issue date in the format YYYYMMDD. Default is zeroes.
emboss [bt_stringf(8)]	Emboss date in the format YYYYMMDD. Default is zeroes.
last_crv [bt_stringf(8)]	Date of last CRV maintenance in the format YYYYMMDD. Default is zeroes.
last_addr_chng [bt_stringf(8)]	Date of last address change in the format YYYYMMDD. Default is zeroes.
last_stat_chng [bt_stringf(8)]	Date of last status change in the format YYYYMMDD. Default is zeroes.
num_iss [bt_stringf(2)]	Number of cards issued. Default is zeroes.
blk_cde [bt_stringf(1)]	Indicates that a cardholder has been blocked and why. Default is spaces.
reclass_cde [bt_stringf(1)]	Reclassification code or alternate block code. Default is spaces.
bhvr_score [bt_stringf(4)]	Behavioral score. Valid values will be 000-999, with 650-750 being good, less than 650 is bad, more than 750 is very good. Default is spaces.
cash_adv_amt [bt_stringf(12)]	Life high cash advance amount. Default is zeroes.
purch_amt [bt_stringf(12)]	Life high purchase amount. Default is zeroes.
bal_amt [bt_stringf(12)]	Life high balance amount. Default is zeroes.
opn_dat [bt_stringf(8)]	Date the account was opened in the format YYYYMMDD. Default is zeroes.
cust_mstr_amt [bt_stringf(16)]	Amount field to hold any user defined customized amount.
cust_mstr_dat [bt_stringf(8)]	Date field to hold any user defined customized date.
cust_mstr_fld1 [bt_stringf(2)]	Alphanumeric field to hold user defined data.
cust_mstr_fld2 [bt_stringf(4)]	Alphanumeric field to hold user defined data.

CTVRSF (3.0) (cosafd)

Cutover SAF Table. When an ATM is force cut over by the ATM Cutover process, the data to be logged by ES is written here for later transmission to the ES servers.

[Audited] [Supports versioning]

Element (type)	Description
InstIdTx [bt_stringf(20)]	A 20 byte string corresponding to the ES inst_id element. This element is used on the ES ATDS1 table as well as several other tables.

Element (type)	Description
MssgEntrTm*[ts 1.0]	The time, represented as a Julian timestamp, when a transaction message was received by the system. The data is stored in the ATM Cutover SAF table (CTVRSAP). The value was originally set by the ES device handler.
PstnDtTx [bt_stringf(6)]	The current posting date of the ATM terminal. The posting date is stored on the ES ATDD1 table. Its value is managed by the ES device handler.
TermIdTx [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
AdminDt [bt_stringf(6)]	The date on which an administrative transaction was performed. This element is used only in the ATM Cutover SAF table.
AdminTm [bt_stringf(8)]	The time at which an administrative transaction was performed. This element is used only in the ATM Cutover SAF table.
AdminCdeTx [bt_stringf(2)]	The administrative transaction code which identifies a specific administrative transaction. This element is used only in the ATM Cutover SAF table.
Hpr1CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSAP) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr1BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAP) table when performing balancing operations.
Hpr1IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAP) during balancing operations. The value is managed by the ES device handler.
Hpr1DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAP) during balancing operations. The value is managed by the ES device handler.
Hpr1OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAP) during balancing operations. The value is managed by the ES device handler.
Hpr1EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period.

Element (type)	Description
	This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr1CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr2CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSAF) table for logging with terminal balancing transactions. The order of contents in the hopper is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr2BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr2IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr2DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr2OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr2EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr2CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr3CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSAF) table for logging with terminal balancing transactions. The order of contents in the hopper is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains

Element (type)	Description
	information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr3BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr3IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr3DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr3OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr3EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr3CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr4CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSAF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr4BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr4IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing

Element (type)	Description
	period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr4DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr4OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr4EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSF) table when performing balancing operations.
Hpr4CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr5CntrTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr5BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSF) table when performing balancing operations.
Hpr5IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr5DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr5OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF

Element (type)	Description
	table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr5EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSF) table when performing balancing operations.
Hpr5CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr6CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr6BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSF) table when performing balancing operations.
Hpr6IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr6DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr6OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSF) during balancing operations. The value is managed by the ES device handler.
Hpr6EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSF) table when performing balancing operations.
Hpr6CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr7CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover

Element (type)	Description
	SAF (CTVRSAF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr7BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr7IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr7DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr7OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr7EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr7CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr8CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSAF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr8BgnBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the beginning of the terminals current balancing period. This

Element (type)	Description
	value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr8IncrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr8DecrBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr8OutBalNum [bt_int64s]	The total amount/balance of: bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. This value is computed by the ES device handler and stored on the ATM Cutover SAF table (CTVRSAF) during balancing operations. The value is managed by the ES device handler.
Hpr8EndBalNum [bt_int64s]	The current total amount/balance of: bills, cash value items, non-value items or travelers cheques, in the specified hopper at the end of the terminals current balancing period. This value is computed by the ES device handler and stored in the ATM Cutover SAF (CTVRSAF) table when performing balancing operations.
Hpr8CrncCdTx [bt_stringf(3)]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
NmbrOfDpstNum [bt_int32s]	The total number of unverified deposits received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfDpstNum [bt_int64s]	The total value of all deposits into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfCmrcDpstNum [bt_int32s]	The total number of commercial deposits (e.g., from Securomatic devices) received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfCmrcDpstNum [bt_int64s]	The total value of commercial deposits into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfPymnNum [bt_int32s]	The total number of payment envelopes received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfPymnNum [bt_int64s]	The total value of payment transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.

Element (type)	Description
NmbrOfMsgTFiidNum [bt_int32s]	The total number of messages to the financial institution received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
NmbrOfChckNum [bt_int32s]	The total number of checks received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfChckNum [bt_int64s]	The total value of the checks deposited into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfLgOnlyNum [bt_int32s]	The total number of log only transactions completed since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
TotalEnvelopesNum [bt_int32s]	The total number of unverified envelopes received since the terminal was last balanced. This count contains the accumulated values of number of envelopes containing: Deposits, Commercial Deposits, Payments, Checks, and Messages to the Institution. The value in this field is calculated by the ES device handler and stored in the ATM Cutover SAF table (CTVRSF) when a terminal is balanced.
NmbrOfCrdsRtndNum [bt_int32s]	The total number of consumer cards retained by the ATM since the terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
TermCrncCdTx [bt_stringf(3)]	A code indicating the type of currency used to represent the terminals amount fields. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code). The data is configured on the ES ATDD1 table.
TmOfstNum [bt_int32s]	The time difference (plus or minus in minutes) between this ATM terminal and the processor location. The value in this field is added to the time to calculate the local time. The data is configured on the ES ATDS1 table.
MssgAtmpNum [bt_int32s]	The number of times the system has attempted to send an ATM cutover record to the authorization system for logging. The data is stored in the ATM Cutover SAF table (CTVRSF) and is managed by the transmitting process.
AdminCrdNumTx [bt_stringf(19)]	The card number (PAN) of an administrative card. This element is used only in the ATM Cutover SAF table to identify the administrative card initiating an administrative transaction.
AdminCrdMbrNum [bt_int32s]	The member number of an administrative card. This element is used only in the ATM Cutover SAF table to identify the administrative card initiating an administrative transaction.
TrmnRgnTx [bt_stringf(4)]	The region ID for the region in which the terminal is located. The data is configured in the ES ATD Configuration Profile table (ATDCNFG).
TrmnBrncTx [bt_stringf(4)]	The branch ID for the branch in which the terminal is located. The data is configured in the ES ATD Configuration Profile table (ATDCNFG).
NmbrSmrtCrdLdsNum [bt_int32s]	The total number of Smart Card load value transactions completed since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.

Element (type)	Description
AmntSmrtCrdLdsNum [bt_int64s]	The total value loaded onto smart cards at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
TermDbtsNum [bt_int64s]	The unverified amount of terminal debits since the terminal was last balanced. The amount in this field consists of debits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us and not-on-us payment-enclosed transactions On-us and not-on-us transfers On-us and not-on-us payments between accounts The value in this field is stored in the ES ATDD1 table and is managed by the ES device handler.
TermCrdtNum [bt_int64s]	The total amount of terminal credits since the terminal was last balanced. The amount in this field consists of credits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us withdrawals On-us and not-on-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the TERM-CR amount. On-us and not-on-us transfers On-us and not-on-us payments between accounts On-us and not-on-us non-currency dispense transactions The value in this field is stored on the ES ATDD1 table and is managed by the ES device handler.
OnUsDbtsNum [bt_int64s]	The total amount of on-us debits since the ATM terminal was last balanced. The amount in this field consists of debits from the customers point of view. Transaction amounts are added to the balance in this field for: On-us withdrawals On-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the ON-US-DB amount. On-us transfers On-us payments between accounts On-us non-currency dispense transactions The value in this field is managed by the ES device handler. The data is stored on the ES ATDD1 table and copied to the ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed.
OnUsCrdtNum [bt_int64s]	The total amount of on-us credits since the ATM terminal was last balanced. The amount in this field consists of credits from the customers point of view. Transaction amounts are added to the balance in this field for On-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us payment enclosed transactions On-us transfers On-us payments between accounts The value in this field is managed by the ES device handler. The data is stored on the ES ATDD1 table and copied to the ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed.
ProcCodeTx [bt_stringf(6)]	The processing code of a transaction. This element is stored on the ATM Cutover SAF table (CTVRSAP) when adding entries for ATM terminal balancing. The value is logged in the authorization system. The value is managed by the ES device handler.
AdjmntHpprNum [bt_int32s]	The adjustment hopper number for an ATM hopper. This element is used only in the ATM Cutover SAF table.
AdjmntHpprCntnNum [bt_int32s]	The hopper content for an ATM hopper. This element is used only in the ATM Cutover SAF table. Hopper Content defines the type of dispense media in the hopper or cassette.
AdjmntAmtNum [bt_int64s]	The amount of adjustments made at a device. The adjustment amount is sent to the authorization process for logging to the transaction journal when administrative balancing is performed.

Element (type)	Description
MssgStatNum [bt_int32s]	The current status of a record in the ATM Cutover SAF table (CTVRSF). The data is stored in the ATM Cutover SAF table and is managed by the transmitting process.
NmbrOfScsfTrnsNum [bt_int32s]	Count for total number of successful transactions during the current balancing period.
NmbrOfUnscTrnsNum [bt_int32s]	Count for total number of unsuccessful transactions during the current balancing period.
NmbrOfPhCPrchNum [bt_int32s]	The total number of phone card purchase transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler
AmntOfPhCPrchNum [bt_int64s]	The total value of phone card purchase transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfTopUpNum [bt_int32s]	The total number of top-up transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfTopUpNum [bt_int64s]	The total value of top-up transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfEmvFBckNum [bt_int32s]	The total number of EMV fallback transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
TermSuspAcct [acct_num 1.0]	The suspense account to which this terminal is assigned. This optional field, if present, is received from the JDH for each transaction and may be journalled and subsequently extracted if required.

CUP_Institution (1.0) (cupind)

The CUP Institution ID Table.

[Audited] [Supports versioning]

OLTP: CUP_Institution_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inst_id*[inst_id 1.0]	The institution ID. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_bnk_id [bt_stringf(11)]	This the Acquiring Bank ID associated with the Institution ID.

CUP_Interface (1.0) (cupifd)

CUP Interface Component Definitions Proprietary Software Product ACI Worldwide Inc. 330 South 108th Avenue
Omaha, Nebraska 68154 (402) 390-7600 Copyright 2008 by ACI Worldwide Inc. All Rights Reserved

Record of Changes:
Date Version Person ----- 17OCT2008 1.0.00 R. Carpenter Symptom: None. Problem: None. Fix: None.
Reference: WO #080208-01 07APR2010 1.1.00 J. Herbert Symptom: None. Problem: None. Fix: Addition of CUP
institution table to the file. Reference: WO #091108-02

The CUP Interface
Table.

[Audited] [Supports versioning]

OLTP: CUP_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
multi_char_use [bt_flag]	This is a boolean flag to indicate the interface supports sending and receiving multi-byte (Chinese) characters.
rcv_inst_id [bt_stringf(11)]	This the Receiving Institution ID associated with the Interface.

Currency_Conversion_Rate (1.0) (ccrd)

The Currency Conversion Rate data source contains the currency rate to be used to convert an amount from a source currency to a base currency.

[Audited] [Supports versioning]

OLTP: Currency_Conversion_Rate_OLTP

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
src_crncy_cde*[crncy_cde 1.0]	The source currency code. This is the currency code of the amount to be converted to the base currency code.
base_crncy_cde*[crncy_cde 1.0]	The base currency code. This represents the currency to which an amount in a different currency is being converted to.
ccr_eff_dat_tim*[yyyymmddhhmm 1.0]	The date a currency conversion rate becomes effective.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
crncy_conv_rate [bt_stringf(8)]	Currency conversion rate excluding the decimal point. The decimal position is implied and is specified by the first digit. The first digit indicates the number of implied decimal positions (from the right) in currency conversion rate. For example, if the Currency Conversion Rate is 5123456, the actual conversion rate is 1.23456.

dal_tbl (1.0) (daltbl)

Table used for testing DAL drivers.

[Audited] [Supports versioning]

Element (type)	Description
last_nam_fld* [bt_stringf(16)]	
dob_fld [bt_int32s]	
blob_fld [bt_binaryl(4)]	
bal_fld [bt_int32s]	
acct_num_fld [bt_int64s]	
age_fld [bt_int32s]	
weight_fld [bt_int32s]	
avg_dst_to_moon_fld [bt_float64]	
avg_dst_to_sun_fld [bt_float32]	
m_i_fld [bt_char]	
f_i_fld [bt_char]	
some_bool_fld [bt_flag]	
city_fld [bt_stringv(31)]	

DATASRC (1.0) (dtsrccd)

Used for alternate datasource access within the JSF.

[Audited] [Supports versioning]

Element (type)	Description
DataSrcNamTx* [bt_stringf(16)]	Data Source Name
DrvNamTx [bt_stringf(100)]	Specifies the class name of the JDBC driver to use for all database connections
DataSrcURLTx [bt_stringf(255)]	Should be set according to JDBC driver requirements and may include information such as: host or IP address where database resides, port to connect to for database, name of database on the host, or other JDBC driver settings

Element (type)	Description
DataSrcTypTx [bt_stringf(10)]	Data Source Type, such as: JDAL
UserID [bt_stringf(50)]	The users id, for UI login. User ID to use for applications to access the database.
UserPswdTx [bt_stringf(50)]	User password for the User ID above accessing the database
TblPrfxTx [bt_stringf(50)]	Table Prefix index
MaxConns [bt_int32s]	Maximum database connections allowed
StatConns [bt_int32s]	Defines the number of connections to acquire to the database when the jvm starts
ConnWaitTime [bt_int64s]	Defines the amount of time, in milliseconds, to wait for another thread to free a Database connection
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

Derivation_Key (2.0) (drvkd)

This table contains the DUKPT derivation keys that are used by devices that support DUKPT encryption.

[Audited] [Supports versioning]

OLTP: Derivation_Key_OLTP

Element (type)	Description
drv_key_prfl* [prfl_def 1.0]	An identifier for the profile to which this record applies. This field contains the key value to the Derivation Key data source.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
drv_key_hdr [keyx_hdr 1.0]	DUKPT Derivation Key header required for the Atalla Key Block (AKB) format.
drv_key [keyx_trpl 1.0]	DUKPT Derivation Key.
drv_key_kam [keyx_kam 1.0]	DUKPT Derivation Key MAC value required for the Atalla Key Block (AKB) format.
drv_key_vvk [vvk 1.0]	Contains the verification value of the DUKPT derivation key. The verification value is used to detect key synchronization errors.
drv_key_opt [bt_stringf(1)]	Derivation Key Option. Valid values are: 1 - Single (default). 2 - Double.
encrypt_des_mde [bt_int16s]	Encryption mode for data encryption. Valid values are: 0 - ECB (Electronic Code Book). 1 - CBC (Cipher Block Chaining) - default.

DIAS_Interface (1.0) (diasfd)

The DIAS Interface Table.

[Audited] [Supports versioning]

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
swi_setl_dat [bt_stringf(8)]	A date identifying the switch settlement date in field 15. YYYYMMDD

Diebold_Number_Table (1.0) (dntd)

The Diebold Number Table contains information specific to the Diebold Number Table (DNT) PIN verification method.

[Audited] [Supports versioning]

OLTP: Diebold_Number_Table_OLTP

Element (type)	Description
pin_vrfy_prfl*[prfl_def 1.0]	An identifier for the profile to which this record applies. This field must contain a value that matches a PIN Verify Profile defined in the Prefix.
beg_dat*[yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat*[yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dnt_intrn_loc [bt_int16s]	The relative location of the Diebold Number Table within the HSM internal memory. The actual table index is calculated by TSEC based on the relative location specified in this field.
dnt_algo_num [bt_stringf(2)]	The two digit hexadecimal algorithm number to be used as a starting index for the Diebold Number Table for calculations on the PAN. The value of the first digit can be 0-9. The value of the second digit can be 0-9, A-F.
key_encrypt_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
key_encrypt_chk_values [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
dnt_hdr1 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key1 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam1 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk1 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr2 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key2 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam2 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk2 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr3 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key3 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam3 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk3 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr4 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key4 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam4 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk4 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr5 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key5 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam5 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk5 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr6 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key6 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam6 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk6 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr7 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key7 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam7 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk7 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr8 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key8 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam8 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk8 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr9 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key9 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam9 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk9 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr10 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key10 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam10 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk10 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr11 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key11 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam11 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk11 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr12 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key12 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam12 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk12 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr13 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key13 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam13 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk13 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr14 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key14 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam14 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk14 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr15 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key15 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam15 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk15 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr16 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key16 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam16 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk16 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr17 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key17 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam17 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk17 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr18 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key18 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam18 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk18 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr19 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key19 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam19 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk19 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr20 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key20 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam20 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk20 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr21 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key21 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam21 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk21 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr22 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key22 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam22 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk22 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr23 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key23 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam23 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk23 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr24 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key24 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam24 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk24 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr25 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key25 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam25 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk25 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr26 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key26 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam26 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk26 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr27 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key27 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam27 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk27 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr28 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key28 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam28 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk28 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr29 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key29 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam29 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk29 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr30 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key30 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam30 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk30 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr31 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key31 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam31 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.
dnt_vvk31 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_hdr32 [keyx_hdr 1.0]	Diebold Number Table (DNT) header required for the Atalla Key Block (AKB) format.
dnt_key32 [keyx_trpl 1.0]	The Diebold Number Table (DNT) is used to generate a PIN for comparison with a PIN that is entered at a PIN encrypting device. The DNT is a random mapping of the 256 two-digit hexadecimal combinations between 00 and FF. The first entry in the table is restricted to be hexadecimal C0 through CF, inclusive. If the DNT is entered as clear data, 32 rows of 16 hexadecimal characters are entered. If the DNT is entered as encrypted data, 32 rows of encrypted key data is entered.
dnt_kam32 [keyx_kam 1.0]	Diebold Number Table (DNT) MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
dnt_vvk32 [vvk 1.0]	Diebold Number Table (DNT) Verification Value. Contains the verification value of the DNT row.
dnt_entry_typ [bt_char]	Indicates if the Diebold Number Table rows are entered in the clear or encrypted. Valid values are: C - clear (default). E - encrypted.

Discover_Institution (1.0) (dscvnd)

The Discover Institution Table.

[Audited] [Supports versioning]

OLTP: Discover_Institution_OLTP

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_spnsr_bnk_id [bt_stringf(11)]	A code identifying the Acquirer Sponsor Bank in field 32.

Discover_Interface (1.0) (dscvfd)

The Discover Interface Table.

[Audited] [Supports versioning]

OLTP: Discover_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rcv_id_cde [bt_stringf(11)]	A code identifying the receiving institution in field 100.
ver_ind [bt_stringf(5)]	A code identifying the format version number of the Authorization Interface Message format in field 127.

DS_OLTP_Relation (1.0) (doltpd)

The Data Source OLTP Relationship table contains a record for each data source that is used to load an OLTP.

[Audited] [Supports versioning]

Element (type)	Description
asgn_nam*[bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
asgn_nam_oltp*[bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
wbt_dest [bt_stringv(100)]	The destination for the warmboot command (e.g., PCTL). Multiple destinations are allowed, separated by a comma. The total length of all destinations plus comma separators can not exceed 100.

Dual_PIN_Verification (1.0) (dpvnd)

This data source holds the keys used in Dual PIN Verification. It is accessed using a PIN Verification Profile and the expiration date. Emerged as part of German Security features.

[Audited] [Supports versioning]

OLTP: Dual_PIN_Verification_OLTP

Element (type)	Description
dpvn_pin_vrfy_prfl*[prfl_def 1.0]	An identifier for the profile to which this record applies. This field must contain a value that matches a PIN Verify Profile defined in the Prefix.
beg_dat*[yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat*[yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
kgk_pvn1_hdr [keyx_hdr 1.0]	KGK Header for the PVN1 verification key. Only used with AKB key format.
kgk_pvn1_keyx [keyx_trpl 1.0]	KGK Key for the PVN1 verification key.
kgk_pvn1_kam [keyx_kam 1.0]	KGK MAC for the PVN1 verification key used for AKB format keys.
kgk_pvn1_vvk [vvk 1.0]	Check Digits of the KGK for the PVN1 verification key.
kgk_pvn2_hdr [keyx_hdr 1.0]	KGK Header for the PVN2 verification key. Only used with AKB key format.
kgk_pvn2_keyx [keyx_trpl 1.0]	KGK Key for the PVN2 verification key.
kgk_pvn2_kam [keyx_kam 1.0]	KGK MAC for the PVN2 verification key used for AKB format keys.

Element (type)	Description
kgk_pvn2_vvk [vvk 1.0]	Check Digits of the KGK for the PVN2 verification key.

Dynamic_Card_Verification (1.0) (dcrdvd)

The Dynamic Card Verification table contains the key value to be used for dynamic card verification.

[Audited] [Supports versioning]

OLTP: Dynamic_Card_Verification_OLTP

Element (type)	Description
crd_vrfy_prfl*[prfl_def 1.0]	An identifier for the group to which this record applies. This field must contain a value that matches a CV_KEYA_PRFL defined in the Prefix data source.
beg_dat*[yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat*[yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dyn_crd_vrfy_algo [bt_stringf(1)]	Dynamic card verification algorithm. Valid values: 0 - Visa (default). 1 - MasterCard.
key_encrypt_1_hdr [keyx_hdr 1.0]	PIN Verification Key/Card Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_1 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key/card verification key used for performing PIN verification/card verification. The value in this field is used when PIN verification/card verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_1_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.
key_encrypt_chk_values_1 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.

EFunds_Institution (1.0) (efiid)

Efunds Institution Configuration.

[Audited] [Supports versioning]

OLTP: EFunds_Institution_OLTP

Element (type)	Description
cmpnt_id*[bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_bnk_id [bt_stringf(11)]	Acquirer identification code assigned to institution – interface instance pair.
efunds_intf_dpnt_data [bt_stringv(300)]	Efunds interface dependent data. The layout will be defined by a structure in the derived interface and its user interface.

EFunds_Interface (3.0) (efifd)

Efunds Interface Configuration.

[Audited] [Supports versioning]

OLTP: EFunds_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_sec_cde [bt_stringf(8)]	Message Security Code.
acq_spnsr_bnk_id [bt_stringf(11)]	Acquirer Sponsor Bank ID.
efunds_intf_dpnt_data [bt_stringv(300)]	Efunds interface dependent data. The layout will be defined by a structure in the derived interface and its user interface.

EMVPRFL (1.0) (emvprd)

This data source contains the configuration related to ATM EMV processing.

[Audited] [Supports versioning]

Element (type)	Description
EmvPrflTx*[prfl_def 1.0]	The EMV profile identifies the EMV values to be used for the specified ATM.

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
EmvTermCrdDatInTx [bt_stringf(1)]	EMV Terminal Capabilities. Indicates the card data input capabilities of the ATM terminal, as shown below. This field contains binary data. It is stored in the ES ATDD1 table and is managed by the ES device handler. Byte 1 (Card Data Input Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 Reserved for future use 5 Reserved for future use 6 IC with contacts 7 Magnetic stripe 8 Manual key entry
EmvTermScrtTx [bt_stringf(1)]	EMV Terminal Capabilities. Indicates the security capabilities of the ATM terminal, as shown below. This field contains binary data. It is stored in the ES ATDD1 table and is managed by the ES device handler. Byte 3 (Security Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 Reserved for future use 5 Reserved for future use 6 Card capture 7 Dynamic data authentication 8 Static data authentication
EmvTermCvmTx [bt_stringf(1)]	EMV Terminal Capabilities. Indicates the CVM capabilities of the ATM terminal, as shown below. This field contains binary data. It is stored in the ES ATDD1 table and is managed by the ES device handler. Byte 2 (CVM Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 Reserved for future use 5 Enciphered PIN for offline verification 6 Signature (paper) 7 Enciphered PIN for online verification 8 Plaintext PIN for ICC verification

EMV_Card_Vrfrn_Results_Status (1.0) (cvrd)

The EMV Card Verification Results (CVR) Status table defines the Card Verification Results checks that are to be performed during routing and/or authorization of EMV transactions and the actions to be taken for a specific CVR byte/bit setting. The CVR is a proprietary EMV data element (included in the Issuer Application Data).

[Audited] [Supports versioning]

Element (type)	Description
cvr_prfl*[prfl_def 1.0]	Card Verification Results (CVR) profile. Defined at the prefix level and is used as an element in the primary key to the Card Verification Results Status table. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
emv_frmt*[bt_char]	Specifies the format of the EMV Issuer Application Data that will be used for this card prefix. A number of predefined formats for Issuer Application Data exist, as specified by the Payment Associations (VISA and Mastercard/Europay), but Issuer specific layouts may also be defined. Issuer Application Data typically contains information which is used in the derivation of the Application Cryptogram. Valid values are: 0 - Unspecified (format unknown, the contents will be transported as passthrough data.) 1 - Issuer Application Data Format defined by VISA in the VISA Integrated Circuit Card Specification. (Note this format is used for UKIS cards). 2 - Issuer Application Data format as recommended for Mastercard/Europay MCPA (MCHIP) cards. 3 - M/Chip 4. 4 - CCD. 5 - Visa Migrating to CCD. 6 - M/Chip 2.1 Migrating to CCD. 7 - M/Chip 4 Migrating to CCD. 8 to 9 - Reserved for other national or international scheme formats. A - Z - Proprietary format defined for the Issuer. (Cust

Element (type)	Description
cvr_tvr_srch_order*[bt_int16s]	The search order when checking the EMV CVR and/or TVR Results Status tables. It allows CVR/TVR byte/bit settings to be checked in a specific order.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
cvr_byte [bt_int16s]	Identifies a specific byte in the EMV Card Verification Results (CVR) element. The maximum number of CVR bytes is dependent on the EMV format.
cvr_bit [bt_int16s]	Identifies a specific bit in an EMV Card Verification Results (CVR) byte. Bit 8 is the high order bit in a CVR byte.
emv_force_onl_flg [bt_int16s]	Indicates if an EMV transaction should be forced to use the over-the-floor routing configuration. Valid values are: 0 - No, do not force the over-the-floor routing configuration (default). 1 - Yes, force the over-the-floor routing configuration.
act_cde [bt_int16s]	The internal action code which is used to map to an external action code or is the result of a mapping from an external action code. Valid values are 000 - 999.

EMV_Iss_Auth_Dta (1.0) (eiadd)

The EMV Issuer Authentication Data. Allow for configuration of EMV Card Status Update (CSU) and Proprietary Authentication Data (PAD) based on the Internal Action Code and the Method.

[Audited] [Supports versioning]

OLTP: EMV_Iss_Auth_Dta_OLTP

Element (type)	Description
act_cde*[bt_stringf(3)]	Internal Action Code value. Asterisks are also allowed as a valid value.
mthd*[bt_int16s]	Method. Valid values are: 1 - Method 1 2 - Method 2
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
csu [bt_stringf(8)]	Card Status Update value. (8 hex characters)
pad [bt_stringf(16)]	Proprietary Authentication Data. This field is not required but if entered must be 16 hex characters.
pin_try_cntr_set [bt_int16s]	Indicates if the PIN Try Counter value should be included with the CSU data. Value values are: 0 - No 1 - Yes

EMV_Reason_Online_Code_Status (1.0) (rocd)

The EMV Reason Online Code (ROC) Status table defines the Reason Online Code checks that are to be performed during routing and/or authorization of EMV transactions and the actions to be taken for a specific code.

[Audited] [Supports versioning]

Element (type)	Description
roc_prfl*[prfl_def 1.0]	Reason Online Code (ROC) profile. Defined at the prefix level and is used as an element in the primary key to the Reason Online Code Status table. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
rsn_onl_cde*[bt_stringf(4)]	Reason On-line Code. The value of this field indicates the reason the transaction is to be authorized on-line or why a transaction has been completed locally. Values are defined in the ISO 8583 (1993) Standard.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
emv_force_onl_flg [bt_int16s]	Indicates if an EMV transaction should be forced to use the over-the-floor routing configuration. Valid values are: 0 - No, do not force the over-the-floor routing configuration (default). 1 - Yes, force the over-the-floor routing configuration.
act_cde [bt_int16s]	The internal action code which is used to map to an external action code or is the result of a mapping from an external action code. Valid values are 000 - 999.

EMV_Script_Context (1.0) (escd)

This datasource contains information pertinent for EMV scripts.

[Audited] [Supports versioning]

Element (type)	Description
pan*[bt_stringf(28)]	Primary Account Number
pan_app_seq_num*[bt_stringf(2)]	Sequence number associated with a PAN for EMV cards
exp_dat*[yyyyymm 1.0]	The expiration date of an instrument.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
script_waiting_flg [bt_flag]	Indicates a Script is waiting for download to an EMV Card.
script_delivered_flg [bt_flag]	Indicates a Script has been delivered to an EMV Card.
crd_blk_flg [bt_flag]	Indicates a card block script is waiting for download to an EMV Card.
apms_ref_num [bt_stringf(280)]	A reference allocated by the APMS system, which is echoed back in the Notification Messages.

EMV_Security (5.0) (emvsd)

The EMV Security Data. Contains the keys required for EMV security processing and the scheme used.

[Audited] [Supports versioning]

OLTP: EMV_Security_OLTP

Element (type)	Description
emv_auth_key_prfl*[prfl_def 1.0]	A profile used to access the Authorization Key file which contains the key data required for CAM verification. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without embedded spaces). If this field is spaces, CAM authentication will not be performed. The default value is spaces.
beg_dat*[yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat*[yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
emv_scheme [bt_int16s]	This field specifies the scheme the card uses for this EMV Security Profile. Valid values are: 0 - Visa 1 - MasterCard/Europay, 2 - CCD
secure_msg_key [keyx_trpl 1.0]	This key is used as an Issuer Master Key used to generate a unique EMV master key which is used in derivation of a session Key used to MAC Script commands. 32 hex characters (0-9, A-F)
num_crypto_keys [bt_int16s]	The number of cryptographic keys configured. Required Integer
crypto_key_1 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_2 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_3 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_4 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_5 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is

Element (type)	Description
	personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_6 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_7 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_8 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_9 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_10 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_11 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_12 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_13 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_14 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters

Element (type)	Description
crypto_key_15 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_16 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_17 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_18 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_19 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_20 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_21 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_22 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_23 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_24 [keyx_trpl 1.0]	Up to 24 Issuer Master Keys used to generate a unique EMV Master Key for the generation of Application Cryptograms. The specific master key used for an individual ICC is indicated by the Derivation Key Index which is

Element (type)	Description
	personalized in the card and passed in the Request Message. 16 hex characters
crypto_key_1_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_1_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_2_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_2_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_3_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_3_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_4_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_4_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_5_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_5_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_6_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_6_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_7_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_7_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_8_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_8_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_9_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_9_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_10_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_10_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_11_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_11_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_12_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_12_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_13_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_13_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_14_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_14_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_15_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_15_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.

Element (type)	Description
crypto_key_16_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_16_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_17_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_17_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_18_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_18_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_19_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_19_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_20_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_20_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_21_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_21_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_22_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_22_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_23_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_23_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_24_hdr [keyx_hdr 1.0]	EMV Master Key header required for the Atalla Key Block (AKB) format.
crypto_key_24_kam [keyx_kam 1.0]	EMV Master Key MAC value required for the Atalla Key Block (AKB) format.
crypto_key_chk_values_1 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_2 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_3 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_4 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_5 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_6 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_7 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.

Element (type)	Description
crypto_key_chk_values_8 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_9 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_10 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_11 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_12 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_13 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_14 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_15 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_16 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_17 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_18 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_19 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_20 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_21 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_22 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_23 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
crypto_key_chk_values_24 [chk_digits 1.0]	Contains the check digits for the EMV Crypto key. The value in this field is entered as four hexadecimal characters.
secure_msg_key_hdr [keyx_hdr 1.0]	EMV Secure Message Key header required for the Atalla Key Block (AKB) format.
secure_msg_key_kam [keyx_kam 1.0]	EMV Secure Message Key MAC value required for the Atalla Key Block (AKB) format.
secure_msg_key_chk_values [chk_digits 1.0]	Contains the check digits for the EMV Secure Messaging Key. The value in this field is entered as four hexadecimal characters.
secure_msg_cnfdntl_key_hdr [keyx_hdr 1.0]	EMV Secure Message Key for Confidentiality header required for the Atalla Key Block (AKB) format.

Element (type)	Description
secure_msg_cnfdntl_key [keyx_trpl 1.0]	This key is used as an Issuer Master Key used to generate a unique EMV master key which is used in derivation of a Session Key used to encrypt confidential data in Script commands. 32 hex characters (0-9, A-F)
secure_msg_cnfdntl_key_kam [keyx_kam 1.0]	EMV Secure Message Key for Confidentiality MAC value required for the Atalla Key Block (AKB) format.
secure_msg_cnfdntl_vvk [chk_digits 1.0]	Contains the check digits for the EMV Secure Messaging Key for Confidentiality. The value in this field is entered as four hexadecimal characters.
dest_pin_blk_typ [bt_char]	Destination PIN block type specified for an EMV offline PIN change transaction. Valid values are: 0 Standard EMV PIN Block (default for MasterCard). 1 Europay/Mastercard Pay Now & Pay Later (not used). 2 Visa Format Without using Current PIN (default for Visa). 3 - Visa Format using Current PIN (not used).
user_fld1 [bt_stringf(1)]	One byte user field (temporary filler).
crypto_key_idx_1 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 1.
crypto_key_idx_2 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 2.
crypto_key_idx_3 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 3.
crypto_key_idx_4 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 4.
crypto_key_idx_5 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 5.
crypto_key_idx_6 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 6.
crypto_key_idx_7 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 7.
crypto_key_idx_8 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 8.
crypto_key_idx_9 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 9.
crypto_key_idx_10 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 10.
crypto_key_idx_11 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 11.
crypto_key_idx_12 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 12.
crypto_key_idx_13 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 13.
crypto_key_idx_14 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 14.
crypto_key_idx_15 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 15.
crypto_key_idx_16 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 16.
crypto_key_idx_17 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 17.
crypto_key_idx_18 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 18.
crypto_key_idx_19 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 19.
crypto_key_idx_20 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 20.
crypto_key_idx_21 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 21.
crypto_key_idx_22 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 22.
crypto_key_idx_23 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 23.
crypto_key_idx_24 [bt_int16s]	EMV Derivation Key Index value associated with EMV Crypto Key 24.

Element (type)	Description
brch_hght [bt_int16s]	Branch/Height parameter used for EMV cryptographic functions. Valid values are: 0 - Branch factor 2; Tree height 16 (default). 1 - Branch factor 4; Tree height 8.
encrypt_des_mde [bt_int16s]	Encryption mode for data encryption. Valid values are: 0 - ECB (Electronic Code Book) (default). 1 - CBC (Cipher Block Chaining). 2 - CFB-8 (Cipher Feedback, 8 bits). 3 - CFB-64 (Cipher Feedback, 64 bits). 4 - OFB-64 (Output Feedback, 64 bits). Valid values for EMV: 0 - ECB (default). 1 - CBC.
crypto_ver_num [bt_stringf(2)]	EMV Cryptographic Version Number. Valid values for EMV scheme Visa: 0A, 0E. Valid values for EMV scheme MasterCard: 00 - 0F, 10, 11, 12, 13, 14, 15. Valid values for EMV scheme CCD: x5.

EMV_Terminal_Vrfrn_Results_Status (1.0) (tvrdr)

The EMV Terminal Verification Results (TVR) Status table defines the Terminal Verification Results checks that are to be performed during routing and/or authorization of EMV transactions and the actions to be taken for a specific TVR byte/bit setting.

[Audited] [Supports versioning]

Element (type)	Description
tvr_prfl*[prfl_def 1.0]	Terminal Verification Results (TVR) profile. Defined at the prefix level and is used as an element in the primary key to the Terminal Verification Results Status table. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
cvr_tvr_srch_order*[bt_int16s]	The search order when checking the EMV CVR and/or TVR Results Status tables. It allows CVR/TVR byte/bit settings to be checked in a specific order.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
tvr_byte [bt_int16s]	Identifies a specific byte in the EMV Terminal Verification Results (TVR) element. The TVR is a 5 byte field.
tvr_bit [bt_int16s]	Identifies a specific bit in an EMV Terminal Verification Results (TVR) byte. Bit 8 is the high order bit in a TVR byte.
emv_force_onl_flg [bt_int16s]	Indicates if an EMV transaction should be forced to use the over-the-floor routing configuration. Valid values are: 0 - No, do not force the over-the-floor routing configuration (default). 1 - Yes, force the over-the-floor routing configuration.
act_cde [bt_int16s]	The internal action code which is used to map to an external action code or is the result of a mapping from an external action code. Valid values are 000 - 999.

Environment (1.0) (envmtd)

The Environment table contains one record for each attribute name/value pair in the system which overrides the default value of the attribute defined by the application. Any attribute not defined in the Environment table will use an appropriate default value as defined by an application.

[Audited] [Supports versioning]

Element (type)	Description
attr_nam* [bt_stringf(32)]	The name of the attribute. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
attr_val [bt_stringf(70)]	The value of the attribute. This field is left-justified (containing any combination of alphanumeric and special characters).
attr_nam_long [bt_stringf(64)]	The long name of the attribute. This field is left-justified (containing any combination of alphanumeric and special characters).
attr_descr [bt_stringv(500)]	The description of the attribute. This field is left-justified (containing any combination of alphanumeric and special characters).

EPP_Serial_Number (1.0) (epnumd)

The EPP Serial Number data source is used to verify that the EPP serial number received in a message from a device is a valid/known serial number.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pk_impl* [bt_int16s]	Public Key implementation. Valid values are: 0 - NCR, 1 - Diebold, 2 - Wincor Signature
epp_serl_num* [bt_stringf(16)]	Serial Number of the encryption PIN pad (EPP).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
chan_id [chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
epp_val_dat [yyyyymmdd 1.0]	The date the EPP serial number was verified as being a valid serial number.
epp_val_tim [tim_hhmm 1.0]	The time the EPP serial number was verified as being a valid serial number.

EPSNET_Inst (1.0) (epiifd)

EPS-Net Institution data.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mc_mbr_id [bt_stringf(6)]	The MasterCard Member ID.

EPSNET_Interface (1.0) (epsnfd)

EPS-Net Interface data.

[Audited] [Supports versioning]

OLTP: EPSNET_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
edcs_inst_id [bt_stringf(11)]	EDCS Institution Identifier.
avs_logon_typ [bt_char]	The AVS logon type associated with a mci_id. Valid values are: 0 - not supported, 1 - issuer receives complete address data and provides AVS, 2 - issuer receives condensed address data and provides AVS, 3 - issuer receives complete address data and Banknet provides AVS, 4 - issuer receives condensed address data and Banknet provides AVS, 5 - Banknet provides AVS and issuer does not see AVS data.
euro_standin_resp_cde_1 [bt_stringf(2)]	Euro Stand-in Response Code 1. 2 byte alphanumerics field.
euro_standin_resp_cde_2 [bt_stringf(2)]	Euro Stand-in Response Code 2. 2 byte alphanumerics field.
euro_standin_resp_cde_3 [bt_stringf(2)]	Euro Stand-in Response Code 3. 2 byte alphanumerics field.
euro_standin_resp_cde_4 [bt_stringf(2)]	Euro Stand-in Response Code 4. 2 byte alphanumerics field.
euro_standin_resp_cde_5 [bt_stringf(2)]	Euro Stand-in Response Code 5. 2 byte alphanumerics field.
euro_standin_resp_cde_6 [bt_stringf(2)]	Euro Stand-in Response Code 6. 2 byte alphanumerics field.
euro_standin_resp_cde_7 [bt_stringf(2)]	Euro Stand-in Response Code 7. 2 byte alphanumerics field.
euro_standin_resp_cde_8 [bt_stringf(2)]	Euro Stand-in Response Code 8. 2 byte alphanumerics field.
euro_standin_resp_cde_9 [bt_stringf(2)]	Euro Stand-in Response Code 9. 2 byte alphanumerics field.
euro_standin_resp_cde_10 [bt_stringf(2)]	Euro Stand-in Response Code 10. 2 byte alphanumerics field.
euro_standin_resp_cde_11 [bt_stringf(2)]	Euro Stand-in Response Code 11. 2 byte alphanumerics field.
euro_standin_resp_cde_12 [bt_stringf(2)]	Euro Stand-in Response Code 12. 2 byte alphanumerics field.
euro_standin_resp_cde_13 [bt_stringf(2)]	Euro Stand-in Response Code 13. 2 byte alphanumerics field.

Element (type)	Description
euro_standin_resp_cde_14 [bt_stringf(2)]	Euro Stand-in Response Code 14. 2 byte alphanumerics field.
euro_standin_resp_cde_15 [bt_stringf(2)]	Euro Stand-in Response Code 15. 2 byte alphanumerics field.
euro_standin_resp_cde_16 [bt_stringf(2)]	Euro Stand-in Response Code 16. 2 byte alphanumerics field.
euro_standin_resp_cde_17 [bt_stringf(2)]	Euro Stand-in Response Code 17. 2 byte alphanumerics field.
euro_standin_resp_cde_18 [bt_stringf(2)]	Euro Stand-in Response Code 18. 2 byte alphanumerics field.
euro_standin_resp_cde_19 [bt_stringf(2)]	Euro Stand-in Response Code 19. 2 byte alphanumerics field.
euro_standin_resp_cde_20 [bt_stringf(2)]	Euro Stand-in Response Code 20. 2 byte alphanumerics field.
euro_standin_resp_cde_21 [bt_stringf(2)]	Euro Stand-in Response Code 21. 2 byte alphanumerics field.
euro_standin_resp_cde_22 [bt_stringf(2)]	Euro Stand-in Response Code 22. 2 byte alphanumerics field.
euro_standin_resp_cde_23 [bt_stringf(2)]	Euro Stand-in Response Code 23. 2 byte alphanumerics field.
ver_num [bt_stringf(2)]	Version Number. 2 byte alphanumerics and defaults to 30.
pin_blk_frmt [bt_stringf(2)]	PIN Block Format. The following values are supported: 11 - ISO Format 1.
test_flg [bt_stringf(2)]	Test Flag. 2 byte alphanumerics with the following values: 01 - Test Traffic Only 10 - Production Traffic Only.

Equens_Instrm_Typ_Extrn (1.0) (eqnied)

1 - operator intervention is required. This the Receiving Institution ID associated with the Interface. Instrument external type value to internal type value mapping.

[Audited] [Supports versioning]

OLTP: Equens_Instrm_Typ_Extrn_OLTP

Element (type)	Description
equens_instrm_typ_extrn [bt_stringf(4)]	External type value of the instrument.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_extrn_descr [bt_stringf(48)]	Text description of the instrument external type.
instrm_typ [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, Americian Express, MasterCard, etc.

Equens_Instrm_Typ_Intrn (1.0) (eqniid)

Instrument internal type value to external type value mapping.

[Audited] [Supports versioning]

OLTP: Equens_Instrm_Typ_Intrn_OLTP

Element (type)	Description
instrm_typ*[instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, Amercian Express, MasterCard, etc.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_extrn_descr [bt_stringf(48)]	Text description of the instrument external type.
equens_instrm_typ_extrn [bt_stringf(4)]	External type value of the instrument.

Equens_Interface (1.0) (eqnifd)

Equens Interface Table.

[Audited] [Supports versioning]

OLTP: Equens_Interface_OLTP

Element (type)	Description
intf_nam [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
key_xchg_timr_id [bt_binaryl(34)]	Key Exchange Timer Identifier use to cancel the timer.
key_xchg_tim [bt_stringf(4)]	The time of day (hhmm) when a new Session Key should be exchanged. Valid values 0000 to 2359.
logon_key_typ [bt_char]	Indicates which key is to be generated on the next logon. Valid values: T - Transport Key; S - Session Key (default).
logon_retry [bt_flag]	Indicates whether the Logon should be retried. Valid values: 0 - Do not retry logon; 1 - Retry Logon (default)

Element (type)	Description
ipay_rsn_cde [bt_int16s]	Indicates the reason for sending a Logoff request. Valid values: 00 - Normal Logoff (default value) 01 - Node down 02 - Unexpected message 63 - Invalid MAC.
mac_fail_cnt [bt_int16s]	Count of the number of MAC verify failures. Defaults to zero
mac_fail_max [bt_int16s]	Maximum number of MAC Verify allowed before generating new keys. Valid values: 1 to 9999.
session_cnt [bt_int16s]	The number of logon requests (i.e. sessions) initiated using the current Transport key. Defaults to zero.
session_max [bt_int16s]	The maximum number of sessions allowed before a new Transport Key is generated. Incremented for all Logon attempts (both successful and unsuccessful). Valid values: 1 to 999.
msg_fail_cnt [bt_int16s]	Count of the number of consecutive message failures. Defaults to zero.
msg_fail_max [bt_int16s]	Maximum number of consecutive message failures allowed before requiring operator intervention. Valid Values 1 to 9999.
logon_fail_cnt [bt_int16s]	Count of the number of consecutive Logon failures (for any reason - not just bad MAC) before operator intervention is required. Defaults to zero.
last_stan [bt_stringf(6)]	Contains the last STAN received. Used in the detection of duplicate advice transmissions.

ERSB_Interface (1.0) (ersbifd)

The ERSB Interface Table.

[Audited] [Supports versioning]

OLTP: ERSB_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ersb_user_id [bt_stringf(9)]	A code identifying the user, either a banking institution or service provider.
ersb_machine_id [bt_stringf(2)]	A code identifying a machine associated with a user.

ESAPDT (3.0) (eapdtd)

ATM DH Previous Days Totals Table. The data in this table includes hopper counts and transaction counts and amounts. The table is updated at ATM terminal cutover time if previous days totals are configured in the application configuration.

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
PstnDtTx [bt_stringf(6)]	The current posting date of the ATM terminal. The posting date is stored on the ES ATDD1 table. Its value is managed by the ES device handler.
Hpr1BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr1CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr1CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr1CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr1EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr2BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr2CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr2CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr2CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr2EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr3BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr3CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period.

Element (type)	Description
	The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr3CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr3CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr3EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr4BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr4CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr4CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr4CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr4EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr5BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr5CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr5CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr5CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.

Element (type)	Description
Hpr5EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr6BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr6CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr6CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr6CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr6EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr7BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr7CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr7CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr7CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr7EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr8BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr8CntIncrNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.

Element (type)	Description
Hpr8CntDcrsNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr8CntOtNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr8EndCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
NmbrOfEnvlDpstNum [bt_int32s]	The total number of unverified deposit envelopes received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfEnvlDpstNum [bt_int64s]	The total value of envelope deposits into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfCshDpstNum [bt_int32s]	The total number of cash deposits received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfCshDpstNum [bt_int64s]	The total value of cash deposited into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfCmrcDpstNum [bt_int32s]	The total number of commercial deposits (e.g., from Securomatic devices) received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfCmrcDpstNum [bt_int64s]	The total value of commercial deposits into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfPymnNum [bt_int32s]	The total number of payment envelopes received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfPymnNum [bt_int64s]	The total value of payment transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfMsgTFiidNum [bt_int32s]	The total number of messages to the financial institution received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
NmbrOfChckNum [bt_int32s]	The total number of checks received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES

Element (type)	Description
	ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfChckNum [bt_int64s]	The total value of the checks deposited into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfLgOnlyNum [bt_int32s]	The total number of log only transactions completed since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
NmbrOfCrdsRtndNum [bt_int32s]	The total number of consumer cards retained by the ATM since the terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
TermDbtsNum [bt_int64s]	The unverified amount of terminal debits since the terminal was last balanced. The amount in this field consists of debits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us and not-on-us payment-enclosed transactions On-us and not-on-us transfers On-us and not-on-us payments between accounts The value in this field is stored in the ES ATDD1 table and is managed by the ES device handler.
TermCrdtNum [bt_int64s]	The total amount of terminal credits since the terminal was last balanced. The amount in this field consists of credits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us withdrawals On-us and not-on-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the TERM-CR amount. On-us and not-on-us transfers On-us and not-on-us payments between accounts On-us and not-on-us non-currency dispense transactions The value in this field is stored on the ES ATDD1 table and is managed by the ES device handler.
OnUsDbtsNum [bt_int64s]	The total amount of on-us debits since the ATM terminal was last balanced. The amount in this field consists of debits from the customers point of view. Transaction amounts are added to the balance in this field for: On-us withdrawals On-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the ON-US-DB amount. On-us transfers On-us payments between accounts On-us non-currency dispense transactions The value in this field is managed by the ES device handler. The data is stored on the ES ATDD1 table and copied to the ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed.
OnUsCrdtNum [bt_int64s]	The total amount of on-us credits since the ATM terminal was last balanced. The amount in this field consists of credits from the customers point of view. Transaction amounts are added to the balance in this field for On-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us payment enclosed transactions On-us transfers On-us payments between accounts The value in this field is managed by the ES device handler. The data is stored on the ES ATDD1 table and copied to the ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed.

Element (type)	Description
TermCrncCdTx [bt_stringf(3)]	A code indicating the type of currency used to represent the terminals amount fields. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code). The data is configured on the ES ATDD1 table.
DpstCntNum [bt_int32s]	The number of depository bins configured in the ATM. The element is stored on the ES ATDD1 table and is managed by the ES device handler.
Sb1NmbrOfChckNum [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb2NmbrOfChckNum [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb3NmbrOfChckNum [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb4NmbrOfChckNum [bt_int32s]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb1AmntOfChckNum [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb2AmntOfChckNum [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb3AmntOfChckNum [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb4AmntOfChckNum [bt_int64s]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb1DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb2DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb3DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb4DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.

Element (type)	Description
NmbrSmrtCrdLdsNum [bt_int32s]	The total number of Smart Card load value transactions completed since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntSmrtCrdLdsNum [bt_int64s]	The total value loaded onto smart cards at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
LstStlmTime [ts 1.0]	The date and time an ATM was last balanced using an administrative balancing function. The data is stored on the ES ATDD1 table and is managed by the ES device handler.
UsrDfndTxtArTx [bt_stringf(70)]	This field is for informational only data. It is configured on the ES ATDD1 table.
NmbrOfScsfTrnsNum [bt_int32s]	Count for total number of successful transactions during the current balancing period.
NmbrOfUnscTrnsNum [bt_int32s]	Count for total number of unsuccessful transactions during the current balancing period.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
NmbrOfPhCPrchNum [bt_int32s]	The total number of phone card purchase transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfPhCPrchNum [bt_int64s]	The total value of phone card purchase transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfTopUpNum [bt_int32s]	The total number of top-up transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfTopUpNum [bt_int64s]	The total value of top-up transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfEmvFBckNum [bt_int32s]	The total number of EMV fallback transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSAP) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.

ESATDD1 (3.0) (eatd1d)

ATM DH Dynamic Data Table. The data in this table includes hopper counts and transaction counts and amounts. The data in this table is updated per transaction to adjust the counts and amounts.

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
PstnDtTx [bt_stringf(6)]	The current posting date of the ATM terminal. The posting date is stored on the ES ATDD1 table. Its value is managed by the ES device handler.
TranSqncNmbrNum [bt_int32s]	The last transaction sequence number. If the terminal supports the generation of such a number, this number comes from the terminal. Otherwise, it is generated by the ES device handler for the terminal. The data is stored on the ES ATDD1 table.
Hpr1BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr1CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr1CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr1CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr1EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr2BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr2CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr2CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr2CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr2EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.

Element (type)	Description
Hpr3BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr3CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr3CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr3CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr3EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr4BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr4CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr4CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr4CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr4EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr5BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr5CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.

Element (type)	Description
Hpr5CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr5CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr5EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr6BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr6CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr6CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr6CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr6EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr7BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr7CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr7CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr7CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.

Element (type)	Description
Hpr7EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr8BgnCntNum [bt_int32s]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the beginning of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
Hpr8CntIncrNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques added to the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr8CntDcrsNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques removed from the specified hopper via mid-point adjustments during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr8CntOtNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques dispensed from the specified hopper via transactions during the current balancing period. The value is stored on the ES ATDD1 table. This value is maintained by the ES device handler.
Hpr8EndCntNum [bt_int32s DELTA]	The number of bills, cash value items, non-value items or travelers cheques in the specified hopper at the end of the terminals current balancing period. The value is stored in the ES ATDD1 table. This value is managed by the ES device handler.
NmbrOfEnvDpstNum [bt_int32s DELTA]	The total number of unverified deposit envelopes received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfEnvDpstNum [bt_int64s DELTA]	The total value of envelope deposits into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfCshDpstNum [bt_int32s DELTA]	The total number of cash deposits received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfCshDpstNum [bt_int64s DELTA]	The total value of cash deposited into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfCmrcDpstNum [bt_int32s DELTA]	The total number of commercial deposits (e.g., from Securomatic devices) received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfCmrcDpstNum [bt_int64s DELTA]	The total value of commercial deposits into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfPymnNum [bt_int32s DELTA]	The total number of payment envelopes received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM

Element (type)	Description
	Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfPymnNum [bt_int64s DELTA]	The total value of payment transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfMsgTFiidNum [bt_int32s DELTA]	The total number of messages to the financial institution received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
NmbrOfChckNum [bt_int32s DELTA]	The total number of checks received (i.e. cashed or deposited) since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfChckNum [bt_int64s DELTA]	The total value of the checks deposited into an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfLgOnlyNum [bt_int32s DELTA]	The total number of log only transactions completed since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
NmbrOfCrdsRtndNum [bt_int32s DELTA]	The total number of consumer cards retained by the ATM since the terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
TermDbtsNum [bt_int64s DELTA]	The unverified amount of terminal debits since the terminal was last balanced. The amount in this field consists of debits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us and not-on-us payment-enclosed transactions On-us and not-on-us transfers On-us and not-on-us payments between accounts The value in this field is stored in the ES ATDD1 table and is managed by the ES device handler.
TermCrdtNum [bt_int64s DELTA]	The total amount of terminal credits since the terminal was last balanced. The amount in this field consists of credits from the institutions point of view. Transaction amounts are added to the balance in this field for: On-us and not-on-us withdrawals On-us and not-on-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the TERM-CR amount. On-us and not-on-us transfers On-us and not-on-us payments between accounts On-us and not-on-us non-currency dispense transactions The value in this field is stored on the ES ATDD1 table and is managed by the ES device handler.
OnUsDbtsNum [bt_int64s DELTA]	The total amount of on-us debits since the ATM terminal was last balanced. The amount in this field consists of debits from the customers point of view. Transaction amounts are added to the balance in this field for: On-us withdrawals On-us cash checks On-us and not-on-us deposits with cash back. Note that only the cash back amount is included in the ON-US-DB amount. On-us transfers On-us payments

Element (type)	Description
	between accounts On-us non-currency dispense transactions The value in this field is managed by the ES device handler. The data is stored on the ES ATDD1 table and copied to the ATM Cutover SAF table (CTVRSAF) for logging, when an administrative balancing transaction is performed.
OnUsCrdtNum [bt_int64s DELTA]	The total amount of on-us credits since the ATM terminal was last balanced. The amount in this field consists of credits from the customers point of view. Transaction amounts are added to the balance in this field for On-us deposits. This includes all types of deposit transactions (i.e. deposit transactions, split deposit transactions and deposit with cash back transactions). Note that these transactions are supported for envelope, commercial and check deposit types. On-us payment enclosed transactions On-us transfers On-us payments between accounts The value in this field is managed by the ES device handler. The data is stored on the ES ATDD1 table and copied to the ATM Cutover SAF table (CTVRSAF) for logging, when an administrative balancing transaction is performed.
SbChkSprtCd [bt_stringf(1)]	A code indicating whether the ATM terminal supports the SSB Check Application features. The data is stored in the ES ATDD1 table and the value is managed by the ES device handler. Valid values are: 0 = Not configured 1 = Yes - supports the SSB Check Application The default value is 0.
DpstCntNum [bt_int32s]	The number of depository bins configured in the ATM. The element is stored on the ES ATDD1 table and is managed by the ES device handler.
Sb1NmbrOfChckNum [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb2NmbrOfChckNum [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb3NmbrOfChckNum [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb4NmbrOfChckNum [bt_int32s DELTA]	The unverified number of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb1AmntOfChckNum [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb2AmntOfChckNum [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb3AmntOfChckNum [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb4AmntOfChckNum [bt_int64s DELTA]	The unverified amount of checks retained in the specified depository bin. This accumulator is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb1DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for

Element (type)	Description
	Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb2DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb3DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
Sb4DpstSqncNmbrNum [bt_int32s]	The terminal depository bin sequence number for the specified depository. This field contains a sequence number ranging from 0001 to 9999. This value is only used for Self Service Banking (SSB) transactions. The value is stored on the ES ATDD1 table. The value is managed by the ES device handler.
NmbrSmrtCrdLdsNum [bt_int32s DELTA]	The total number of Smart Card load value transactions completed since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntSmrtCrdLdsNum [bt_int64s DELTA]	The total value loaded onto smart cards at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
BlncIndCd [bt_stringf(1)]	An element that indicates how an ATM terminal was last balanced. The data is stored on the ES ATDD1 table and is used only for information purposes. Possible values are Balanced at the terminal = 0 Balanced at the ES UI = 1 Force balanced by the system = 9
CtvrPndnCd [bt_stringf(1)]	A control flag indicating cutover is pending for the ATM. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
NwPstnDtTx [bt_stringf(6)]	The terminal owners posting date (YYMMDD) used while the terminal is waiting to cut over. The data is stored on the ES ATDD1 table. The value in this field is managed by the ES device handler. It is set by the End of Period process and reset by the ES Device Handler.
LstStlmTime [ts 1.0]	The date and time an ATM was last balanced using an administrative balancing function. The data is stored on the ES ATDD1 table and is managed by the ES device handler.
UsrDfndTxtArTx [bt_stringf(70)]	This field is for informational only data. It is configured on the ES ATDD1 table.
DkmPinTranCntrNum [bt_int32s DELTA]	The number of transactions requiring PIN verification since the last PIN key change. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmPinErrCntrNum [bt_int32s DELTA]	The number of consecutive transactions with a PIN verification error since the last PIN key change. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmMacTranCntrNum [bt_int32s DELTA]	The number of transactions requiring MAC verification since the last MAC key change. The element is stored on the ES ATDD1 table and is controlled by the device handler.

Element (type)	Description
DkmMacErrCntrNum [bt_int32s DELTA]	The number of consecutive transactions with a MAC verification error since the last MAC key change. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmKeyChngTime [ts 1.0]	The timestamp of the last PIN working-key change executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
EmvScSndCrdBlkTx [bt_stringf(1)]	This field contains a copy of the issuers script processing flags for EMV. The element is stored in the ES ATDD1 table and is managed by the ES device handler.
EmvScSndPtDataTx [bt_stringf(1)]	This field contains a copy of the issuers script processing flags for EMV. The element is stored in the ES ATDD1 table and is managed by the ES device handler.
OnLnIndCd [bt_stringf(1)]	An indicator of whether the ATM is on-line (i.e., communicating to the data processing center. The data is stored on the ES ATDD1 table. The value in this field is controlled by the ES device handler. Valid values are: 0 = Off-line 1 = On-line 2 = Undetermined The default value is 2. Note that on some platform and messaging middleware combinations, the on-line status cannot be known until a message is actually received by the ES device handler.
OpnIndCd [bt_stringf(1)]	An indicator of whether the ATM is open. An ATM is open only if an Open command response has been received by the ES device handler. The data is stored on the ES ATDD1 table. The value in this field is controlled by the ES device handler. Valid values are: 0 = Closed 1 = Open The default value is 0.
PrvOnLnIndCd [bt_stringf(1)]	The previous value of the On-Line Indicator field (OnLnIndCd). The previous value is recorded here so that the ES UI may display the previous state. The On-Line indicator of whether the ATM is on-line (i.e., communicating to the data processing center. The data is stored on the ES ATDD1 table. The value in this field is controlled by the ES device handler. Valid values are: 0 = Off-line 1 = On-line 2 = Undetermined The default value is 2. Note that on some platform and messaging middleware combinations, the on-line status cannot be known until a message is actually received by the ES device handler.
PrvOpnIndCd [bt_stringf(1)]	The previous value of the Open Indicator field (OpnIndCd). The previous value is recorded here so that the ES UI may display the previous state. The Open Indicator indicates of whether the ATM is open. An ATM is open only if an Open command response has been received by the ES device handler. The data is stored on the ES ATDD1 table. The value in this field is controlled by the ES device handler. Valid values are: 0 = Closed 1 = Open The default value is 0.
DvcSqncNumTx [bt_stringf(3)]	The sequence number of the device. This value is received in the native messages from the device. For devices supporting NDC, this is the Logical Unit Number (LUNO). The element is stored on the ES ATDD1 table and is managed by the ES device handler.
MsgCrnNmTx [bt_stringf(1)]	Transaction msg coordination number extracted from the transaction request. This element is stored on the ES ATDD1 table and is managed by the ES device handler.
MsgLangIndNum [bt_int32s]	Transaction language extracted from the transaction request. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgOpCdDataTx [bt_stringf(8)]	Transaction op keys extracted from the transaction request. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgCrdNmTx [bt_stringf(19)]	Cardholder PAN extracted from the original transaction request. Used in event logging when required on interactive sequences. The data is stored on the ES ATDD1 table and is managed by the SE device handler.

Element (type)	Description
MsgDspn1CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgDspn2CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgDspn3CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgDspn4CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgDspn5CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgDspn6CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgDspn7CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgDspn8CntNum [bt_int32s DELTA]	Transaction valuable media dispense count for the specified hopper number. These values correspond to the dispense counts within the transaction response (Function Command) message. The data is stored in the ES ATDD1 table and is managed by the ES device handler.
MsgTmVrntTx [bt_stringf(8)]	Transaction MAC time variant extracted from the transaction request. The data is stored in the ES ATDD1 table and is managed by the ES device handler. Transaction MAC time variant number MUST be sent back to the ATM in transaction replies if it was sent by the ATM in the request.
ClntTmtCntrNum [bt_int32s DELTA]	A control counter indicating the number of consecutive intertransaction timeouts that have occurred. The counter is recorded on the ES ATDD1 table and is managed by the device handler. If too many consecutive timeouts occur, an event is generated by the ES ATM device handler.
CTranRspnCdNum [bt_int32s]	A control flag indicating the transaction response from the ATM. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CTranStatCd [bt_stringf(1)]	A control flag indicating the current transaction status. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CBInclndCd [bt_stringf(1)]	A control flag indicating balancing is required for the terminal. The flag is recorded on the ES ATDD1 table and is managed by the device handler.

Element (type)	Description
CRBlncIndCd [bt_stringf(1)]	A control flag indicating whether or not rear balancing is in progress at the ATM. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CAdmnBlncStpCd [bt_stringf(1)]	A control flag indicating the stage of processing for an administrative transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CSprvIndCd [bt_stringf(1)]	A control flag indicating the whether or not the ATM has had the supervisor switch set. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CCshEscrFlagCd [bt_stringf(1)]	A control flag indicating cash has been escrowed during the processing of the current transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CChkEscrFlagCd [bt_stringf(1)]	A control flag indicating a check has been escrowed during the processing of the current transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CDsTranFlagCd [bt_stringf(1)]	A control flag indicating whether the customer requested digital audio services at the ATM. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CDspnTypCd [bt_stringf(1)]	A control flag indicating the type of dispense operation to be performed for the current transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CRcptChcFlagCd [bt_stringf(1)]	A control flag indicating whether or not the customer requested a receipt for the transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
COptnRcptStatCd [bt_stringf(1)]	A control flag indicating whether or not the receipts printer is operable or inoperable and whether the corresponding load has been sent to the ATM. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CEmvTranIndCd [bt_stringf(1)]	A control flag indicating whether or not the transaction is an EMV transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CLntrDlgTypCd [bt_stringf(1)]	A control flag indicating what type of interactive dialogue, if any, in which the ATM is involved. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CMltAcctIndCd [bt_stringf(1)]	A control code indicating whether or not the ATM is involved in a multiple account select transaction. The code is recorded on the ES ATDD1 table and is managed by the device handler.
CMltAcctFrIndxNum [bt_int32s]	A control value indicating the index of the from account for the current transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CMltAcctTIndxNum [bt_int32s]	A control value indicating the index of the to account in the current transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CStmnPrntIndCd [bt_stringf(1)]	A control flag indicating whether or not the ATM is involved in a statement print transaction. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CPrtlRvrsPndnCd [bt_stringf(1)]	A control flag indicating whether or not a partial reversal is pending at the ATM. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
CTpOfRcptFlagCd [bt_stringf(1)]	A control flag indicating whether or not receipt data will print at the top of the receipt. The flag is recorded on the ES ATDD1 table and is managed by the device handler.

Element (type)	Description
CRcptPgCntNum [bt_int32s]	A control value indicating the number of pages the receipt will require. The value is recorded on the ES ATDD1 table and is managed by the device handler.
CRcptLnCntNum [bt_int32s]	A control value indicating the number of lines to be printed on a receipt. The value is recorded on the ES ATDD1 table and is managed by the device handler.
LCnfgldTx [bt_stringf(4)]	This field contains the four digit configuration ID (0000 through 9999) associated with the terminals downloaded configuration file. The data is stored on the ES ATDD1 table and is managed by the ES device handler.
AuthMsgTypTx [bt_stringf(4)]	The message type (e.g., 1110, 1210) of the last message received or sent to the authorization system. This data is recorded in the ES ATDD1 table and is used for failure recovery during transaction processing.
AuthPrcCdeTx [bt_stringf(6)]	The processing code of the last transaction response from the authorization system. This data is recorded in the ES ATDD1 table and is used for failure recovery.
AuthSqncNmbrTx [bt_stringf(12)]	The sequence number returned by the authorization process on the last transaction from the ATM. This data is recorded in the ES ATDD1 table for reversal processing in the event of failure.
AuthRspnCdTx [bt_stringf(3)]	The response code returned by the authorization process on the last transaction from the ATM. This data is recorded in the ES ATDD1 table for reversal processing in the event of failure.
InstldTx [bt_stringf(20)]	A 20 byte string corresponding to the ES inst_id element. This element is used on the ES ATDS1 table as well as several other tables.
HrdwAryTx [bt_stringf(25)]	The hardware presence array for an ATM. The data is stored in the ES ATDD1 table and is managed by the ES device handler. The hardware array bytes correspond to hardware sub units in the ATM. Note that only the hardware sub units directly effecting transaction processing are recorded on the ES ATDD1. While other sub units may be present in by the device, their existance is not recorded. The hardware array mapping is defined in the class com.aciworldwide.base24.es.dh.common.valueobjects.device.DeviceMap.java. Values for the hardware Array bytes are defined in the class com.aciworldwide.base24.es.dh.common.valueobjects.device.HardwareConfigInterface.java. Possible values for each byte are Configured (1) or Not Configured (0).
FtnsAryTx [bt_stringf(25)]	The hardware Fitness Array for an ATM. The data is stored in the ES ATDD1 table and is managed by the ES device handler. The fitness array bytes correspond to hardware sub units in the ATM. Note that only the hardware sub units directly effecting transaction processing are recorded on the ES ATDD1. While other sub units may be reported on by the device, their status is not recorded. However, should they fail, an event will be logged. The fitness array mapping is defined in the class com.aciworldwide.base24.es.dh.common.valueobjects.device.DeviceMap.java. Values for the Fitness Array bytes are defined in the class com.aciworldwide.base24.es.dh.common.valueobjects.device.FitnessInterface.java. Not all ATM devices have all possible sub units. For example, the coin dispenser may not be present on many ATM devices. The Hardware Array indicates which of the devices is present on the ATM.
SpilyAryTx [bt_stringf(25)]	The supply data array for an ATM. The data is stored in the ES ATDD1 table and is managed by the ES device handler. The supply data array bytes correspond to various sub devices which require consumable supplies, for within the ATM for example, the receipt printer. The supply array mapping is defined in the class com.aciworldwide.base24.es.dh.common.valueobjects.device.DeviceMap.java.

Element (type)	Description
	Values for the supply array bytes are defined in the class <code>com.aciworldwide.base24.es.dh.common.valueobjects.device.SupplyConfigInterface.java</code> . Possible values for each byte are Unchanged (0), Good (1), Low (2), Out (3) and Overfill(4).
SnsrAryTx [bt_stringf(25)]	The sensor data array for an ATM. The data is stored in the ES ATDD1 table and is managed by the ES device handler. The sensor data array bytes correspond to various sensors within the ATM for example, the vibration sensor. The sensor array mapping is defined in the class <code>com.aciworldwide.base24.es.dh.common.valueobjects.device.DeviceMap.java</code> . Values for the sensor array bytes are defined in the class <code>com.aciworldwide.base24.es.dh.common.valueobjects.device.SensorConfigInterface.java</code> . Possible values for each byte are Active (1) or Inactive (0).
CLdStatCd [bt_stringf(1)]	A control flag indicating whether or not the terminal is involved in a load. The flag is recorded on the ES ATDD1 table and is managed by the device handler.
LoadTmrLng [bt_int64s]	This field contains a unique id of the last load timer started. It is used to avoid conflicts when a cancel message is sent (by an ES device handler process) at about the same time as the expired load timer message (sent by the timer process). The data is stored on the ES ATDD1 table and is managed by the ES device handler.
InActTmrLng [bt_int64s]	This field contains a unique id of the last inactivity timer started. It is used to avoid conflicts when a cancel message is sent (by an ES device handler process) at about the same time as the expired inactivity timer message (sent by the timer process). The value in this field is stored in the ES ATDD1 table and is managed by the ES device handler.
GroupldTx [bt_stringf(4)]	The ATM Load Group ID. The data is stored on the ES ATDS1 table and replicated for the ES User Interface, on the ES ATDD1 table. The base group has a value of 0000.
SftwRlsTx [bt_stringf(20)]	The software release number retrieved from an ATM terminal. The data is stored in the ES ATDD1 table and is available for display purposes. The ATM provides the value. The ES device handler simply records it in the ES ATDD1.
MdlNmbrTx [bt_stringf(10)]	The model number of an ATM. The data is stored in the ES ATDD1 table and is managed by the ES device handler. The data is retrieved from the ATM using a configuration information retrieve request when a full load is performed on the ATM.
LastTranStatEnblCd [bt_char]	This code, stored on the ESATDD1 table, indicates whether the ATM device will send the last transaction status information on the next request. Possible values are 0 - Last transaction status is enabled. 1 - Last transaction status is not enabled. The default value, set in the user interface is 0 (last transaction status is enabled). The element is managed by the ES device handler.
NmbrOfScsfTrnsNum [bt_int32s DELTA]	Count for total number of successful transactions during the current balancing period.
NmbrOfUnscTrnsNum [bt_int32s DELTA]	Count for total number of unsuccessful transactions during the current balancing period.
DkmMsgTranCntrNum [bt_int32s DELTA]	The number of transactions requiring Message Data encryption and verification since the last MSG (Message Data Encryption) working-key change. The element is stored on the ES ATDD1 table and is controlled by the device handler.

Element (type)	Description
DkmMsgErrCntrNum [bt_int32s DELTA]	The number of transactions with Message Data verification error since the last Message Data working-key change. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmMacCsErrCntNum [bt_int32s DELTA]	The number of consecutive MAC errors since the last MAC working-key change. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmTMKeyChngTime [ts 1.0]	The timestamp of the last Terminal Master Key change executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmKEKPINChngTime [ts 1.0]	The timestamp of the last PIN Key Exchange Key change executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmKEKMACChngTime [ts 1.0]	The timestamp of the last MAC Key Exchange Key change executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmKEKMSGChngTime [ts 1.0]	The timestamp of the last MSG (Message Data Encryption) Key Exchange Key change executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmMacKeyChngTime [ts 1.0]	The timestamp of the last MAC working-key change executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmMsgChngTime [ts 1.0]	The timestamp of the last MSG working-key change executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmCertChngTime [ts 1.0]	The timestamp of either the last verification certificate rollover or encryption certificate rollover executed with the ATM. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmCertRlvrTmrLng [bt_int64s]	The next Certificate Rollover timer. It is the certificate's end of validity date minus dh.dkm.premature.certificate.rollover value. The element is stored on the ES ATDD1 table and is controlled by the device handler.
DkmCertConfTmrLng [bt_int64s]	This field contains the certificate confirmation timer value. It is used to determine timeouts after a certificate rollover confirmation was sent to a certificate authority. The value in this field is stored in the ES ATDD1 table and is managed by the ES device handler.
DkmCertConfStsCd [bt_stringf(1)]	This code, stored on the ESATDD1 table, indicates whether a certificate rollover confirmation is being sent to a certificate authority. Possible values are: 0 = No certificate confirmation processing in progress 1 = Certificate confirmation SAFed, no certificate confirmation message in flight 2 = Certificate confirmation message in flight, first time 3 = Certificate confirmation message in flight, second or later time Another certificate rollover will be rejected until the confirmation was successfully sent to the certificate authority. The element is managed by the ES device handler.
DkmRlvrRetryCntNum [bt_int32s]	Number of retries of the automatic certificate rollover (certificate rollover triggered manually via the UI will not be restarted automatically). The rollover will be retried until it is successful or until the maximum number of retries has been reached. If a rollover was successful this field will be reset to 0, otherwise incremented by 1. If the maximum number of retries is reached this field will be reset (and no auto rollover timer will be started). The element is managed by the ES device handler.
DkmKeyRetryCntNum [bt_int32s]	Number of retries for a successful change of a working key. The working key is retried until the maximum number of retries has been reached. The element is managed by the ES device handler.

Element (type)	Description
DkmKEKRetryCntNum [bt_int32s]	Number of retries for a successful change of a key exchange key. The key exchange key is retried until the maximum number of retries has been reached. The element is managed by the ES device handler.
DkmTMKRetryCntNum [bt_int32s]	Number of retries for a successful change of a terminal master key. The terminal master key is retried until the maximum number of retries has been reached. The element is managed by the ES device handler.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dual_site_ind [bt_char]	Indicates if the record/transaction originated on the Local System or the Remote System. Valid values: space or L - Local (default). R - Remote.
NmbrOfPhCPrchNum [bt_int32s DELTA]	The total number of phone card purchase transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler
AmntOfPhCPrchNum [bt_int64s DELTA]	The total value of phone card purchase transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfTopUpNum [bt_int32s DELTA]	The total number of top-up transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.
AmntOfTopUpNum [bt_int64s DELTA]	The total value of top-up transactions performed at an ATM, during a business day. The amount is recorded on the ES ATDD1 table and copied into the ATM Cutover SAF table when a terminal is cut over.
NmbrOfEmvFBckNum [bt_int32s DELTA]	The total number of EMV fallback transactions received since the ATM terminal was last balanced. The data is stored on the ES ATDD1 table and copied to the ES ATM Cutover SAF table (CTVRSF) for logging, when an administrative balancing transaction is performed. The value in this field is managed by the ES device handler.

ESATDD2 (2.0) (eatd2d)

ATM DH Dynamic Data Table. This table contains several scratch pad areas for recording terminal and transaction context while awaiting a response from the ATM device.

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
CmmnTranDataBn [bt_binary(4032)]	Transaction context storage area in ESATDD2. This element is managed by the ES ATM device handler.
fm_ts [ts 1.0]	File Maintenance Time Stamp. uource record by GUI client application. //

ESATDL (1.0) (eatdld)

The ES ATM Terminal Load data. This table is used only when an ATM terminal is being loaded.

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx *[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
LoadDataArea [bt_binaryl(500)]	Currently unused.

ESATDS1 (2.0) (eats1d)

ATM DH Static Data Table. The static, basic data associated with an ATM terminal. When adding a new ATM, using existing profiles, this is the only data that need be added.

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx *[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
TermTypTx [bt_stringf(2)]	A code indicating the type of terminal. The data is configured on the ES ATDs1 table. Valid values are 01 - NCR 5xxx 02 - Diebold 10xx 03 - IFX
InstIdTx [bt_stringf(20)]	A 20 byte string corresponding to the ES inst_id element. This element is used on the ES ATDS1 table as well as several other tables.
AcqrTranPrflTx [bt_stringf(16)]	The Acquirer Transaction Profile ID for an ATM terminal. The profile is used for authorization purposes.
AcqrRtPrflTx [bt_stringf(16)]	The acquirer routing profile ID for an ATM. The profile is stored in the ES ATDS1 table and sent to the authorization system with transactions.
TermOwnrTx [bt_stringf(22)]	The name of the financial institution owning the terminal. The data is configured on the ES ATDS1 table.
TermAdrsTx [bt_stringf(25)]	A unique address which identifies the location of the terminal. This field is used as print information on the ATM customer receipt. The data is configured on the ES ATDS1 table.
TermCtyTx [bt_stringf(13)]	The name of the city where the terminal is located. The data is configured on the ES ATDS1 table.
TermStTx [bt_stringf(3)]	The state, province, or political subdivision where the terminal is located. The entry in this field is used to validate sharing transactions. In the United States, this field contains the ANSI standard state code as specified in States and Outlying Areas of the United States, FIPS PUB 5-1. Codes for other countries must be

Element (type)	Description
	agreed upon by all sharing institutions. The data is configured in the ES ATDS1 table.
TermCntyTx [bt_stringf(3)]	The county where the terminal is located. The entry in this field is used to validate sharing transactions. For the United States, this field contains the ANSI standard county code specified in Counties and County Equivalents of the States of the United States, FIPS PUB 6-1. Codes for other countries must be agreed upon by all sharing institutions. The data is configured on the ES ATDS1 table.
TermCntrTx [bt_stringf(3)]	The country where the terminal is located. The entry in this field is used to validate sharing transactions. Valid values are listed in the ISO Codes For the Representation of Names of Countries, 3166-1981. The data is configured on the ES ATDS1 table.
PstlCdTx [bt_stringf(10)]	The postal code where the ATM terminal is installed. The value is configured on the ES ATDS1 table.
LoadPrflTx [bt_stringf(16)]	The load profile ID which associates an ATM terminal to the ATM Configuration which is downloaded to it. The data is configured on the ES ATDS1 table. The data is also used as a key to the ES ATM Configuration table (ATMCNFG) to retrieve load data during the ATM load process.
ActnCodPrflTx [bt_stringf(16)]	The profile ID used to look up action code conversions. The field is set on the ES ATD data and used in transaction response processing by the authorizer.
HprPrflTx [bt_stringf(16)]	The hopper configuration profile ID associated with an ATM. The hopper prprofile ID is stored in the ES ATDS1 table and is used to link the ATM to its hopper configuration defined in the Hopper Configuration table (HPRPRFL).
CnfgPrflTx [bt_stringf(16)]	The configuration profile ID of an ATM terminal. The value is stored on the ES ATDS1 table and is used to link the terminal to the ES ATM Configuration Profile (ATDCNFG) table entry for the terminal.
RcptPrflTx [bt_stringf(16)]	The profile ID used to link an ATM terminal to the Receipt table (RECEIPT). The data is configured on the ES ATDS1 table.
TmOfstNum [bt_int32s]	The time difference (plus or minus in minutes) between this ATM terminal and the processor location. The value in this field is added to the time to calculate the local time. The data is configured on the ES ATDS1 table.
GroupldTx [bt_stringf(4)]	The ATM Load Group ID. The data is stored on the ES ATDS1 table and replicated for the ES User Interface, on the ES ATDD1 table. The base group has a value of 0000.
HldyPrflTx [prfl_def 1.0]	The Holiday Profile ID on the ES ATDS1 table. Currently unused.
OptnRcptPrflTx [bt_stringf(16)]	The profile ID used to link an ATM terminal to the Optional Receipts table (OPTRCPT). The data is configured on the ES ATDS1 table.
RcptRqrdPrflTx [bt_stringf(16)]	This field, configured on the ES ATDS1 table, contains the profile ID used to look up the receipt required information from the receipt required table (RCPTRQRD).
TSSLctrTx [bt_stringf(16)]	For the ES ATDS1 table, this field contains the TSS Key Locator for obtaining data from the CSEC file. Normally, the value is the terminal ID. The UI should default the value to the terminal ID if the operator does not set the value. The ATM device handlers will use the ATM terminal ID if this data element is not set.
TermLctnIndCd [bt_stringf(1)]	The Terminal Location Indicator indicates the location of the terminal. Valid values are: 0 = On premises of card acceptor facility 1 = Off premises of card acceptor

Element (type)	Description
	facility (remote location). The default value is 0. The data is configured on the ES ATD Configuration Profile table (ATDCNFG).
TrmnRgnTx [bt_stringf(4)]	The region ID for the region in which the terminal is located. The data is configured in the ES ATD Configuration Profile table (ATDCNFG).
TrmnBrncTx [bt_stringf(4)]	The branch ID for the branch in which the terminal is located. The data is configured in the ES ATD Configuration Profile table (ATDCNFG).
AdmnPhnCnctTx [bt_stringf(20)]	The Administrative Contact phone number for an ATM. The element may be used to record a phone number for the person(s) responsible for administering the terminal. The data is recorded on the ES ATM Configuration Profile table (ATDCNFG).
TermSrchrPrflTx [bt_stringf(16)]	This field is used for surcharging. This field identifies the terminal surcharge group of which this terminal is a member. The data is configured on the ES ATDS1. It is passed to the authorization system where it is used for surcharge calculations.
InactTmrPrflTx [phn_num 1.0]	The terminal inactivity profile identifies the inactivity timer values to be used for the specified ATM.
LoadTmrPrflTx [prfl_def 1.0]	The terminal load timer profile identifies the load timer values to be used for the specified ATM.
CmptbltyPrflTx [prfl_def 1.0]	The compatibility profile identifies the elements required for BASE24 compatibility.
FstCshPrflTx [prfl_def 1.0]	The fast cash profile identifies the fast cash setup to be used for the specified ATM.
EmvPrflTx [prfl_def 1.0]	The EMV profile identifies the EMV values to be used for the specified ATM.
MacPrflTx [prfl_def 1.0]	The Message Authentication Code (MAC) profile identifies the MAC processing values to be used for the specified ATM.
StmntPrntPrflTx [prfl_def 1.0]	The statement print profile identifies the statement print parameter setting to be used for the specified ATM.
TermSuspAcct [acct_num 1.0]	The suspense account to which this terminal is assigned. This optional field, if present, is received from the JDH for each transaction and may be journalled and subsequently extracted if required.
HomeSiteInd [bt_char]	Indicates the home site of the device associated with the data record (i.e., which site is primary connection site) Valid values: Alpha-numeric character. The default value will be the Environment parameter named HOME_SITE_ID. If the parameter does not exist, the default will be a space.

Euro_Opted_Currency (1.0) (eocd)

The Euro Opted Currency data source is used to determine if a currency is Euro opted. When a EU country decides to stop using its local currency and begins using the Euro ("opts" in), there is a transitional period in which the local currency becomes "fixed" to the Euro.

[Audited] [Supports versioning]

OLTP: Euro_Opted_Currency_OLTP

Element (type)	Description
crncy_cde* [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
crncy_opt_flg [bt_char]	Indicates if a currency has opted in to the Euro currency. Valid values are: Yes - the currency has opted in (default). No - the currency has not opted in.

Event (1.0) (eventd)

The Event table contains one row for each event which may be logged. Each event contains up to 20 tokens which can be substituted into the message text. Event suppression is also defined in the Event table.

[Not Audited] [Supports versioning]

OLTP: Event_OLTP

Element (type)	Description
gen_ssld* [bt_int32s]	The sub-system id of the generating object.
evt_num* [bt_int32s]	The event number of the exception being logged.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
suppress_typ [bt_int32s]	The type of event suppression performed for this event. Valid values are: 0 - Log the event when the time and/or count threshold has been reached by the network. 1 - Log the event when the time and/or count threshold has been reached by the process. 2 - Never log the event. 3 - Always log the event. Default value is 3. If values of 0 or 1, then the time interval between events or the number of events to skip must be non-zero.
suppress_tim_lmt [bt_int32s]	The time interval, in seconds, between which the event is suppressed. Valid values are: 0 - event is not suppressed by time, 1-9999 - number of seconds between events when event suppression is configured by process or network. Default value is 0.
suppress_cnt_lmt [bt_int32s]	The number of times to suppress the event. Valid values are: 0 - event is not suppressed by count, 1-9999 - number of times between events when event suppression is configured by process or network. Default value is 0.
suppress_ts [bt_int64s]	The timestamp after what time an event can be logged next when event suppression is configured at the network level with a time interval. Default value is 0.
suppress_cnt_rmng [bt_int32s]	The number of events remaining to be suppressed before an event can be logged when event suppression is configured at the network level with a suppression count. Default value is 0.
severity [bt_int32s]	The severity of the event. Valid values are: 0 - Info, 1 - Warning, 2 - Error, 3 - Critical.
evt_txt [bt_stringf(256)]	The event message text. Contains embedded token substitution in the form <n> where n is the token number to substitute in the text location.
evt_txt_lgth [bt_int32s]	The length of the event message text.
tkn_cnt [bt_int32s]	The number of tokens present in the event message text. Must match the number of actual valid token types for this event.

Element (type)	Description
tkn0_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn0_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn1_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn1_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn2_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn2_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn3_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn3_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn4_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn4_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn5_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn5_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn6_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn6_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn7_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).

Element (type)	Description
tkn7_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn8_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn8_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn9_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn9_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn10_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn10_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn11_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn11_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn12_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn12_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn13_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn13_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn14_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn14_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.

Element (type)	Description
tkn15_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn15_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn16_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn16_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn17_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn17_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn18_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn18_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.
tkn19_typ [bt_int32s]	The type of token passed as a parameter. Valid values are: 1 - binary 16, 2 - binary 32, 3 - binary 64, 4 - fixed length string, 5 - null terminated string, 6 - variable length string (length is specified as the next parameter as a binary 32).
tkn19_lgth [bt_int32s]	The length of the string when the token type is 4 - fixed length string. Length of the string must be between 1 and 256. If the token type is not fixed, this field is not used. Default value is 0.

EVENTLOG (1.0) (evtId)

This is a Java Server Framework table. The JSF Log4J component may be configured to log to a database table. This is the database table to which it may log. This table can be configured in addition to any other logging destination. However, it will contain only the log messages emitted by applications running with the Java Server Framework.

[Audited] [Supports versioning]

Element (type)	Description
PrcsID*[bt_stringf(16)]	A unique ID assigned to a process in the Process table (PROCESS).
PrcsThrdTx*[bt_stringf(231)]	The thread ID of a process logging an event. The data is automatically stored with the event in the Event Log table (EVNTLOG).

Element (type)	Description
LogTm*[ts 1.0]	The time, represented as a Julian timestamp, when an event was logged. The data is recorded in the Event Log table (eventlog). The value is determined by the Java Server Framework.
ClsNameTx [bt_stringf(255)]	The fully qualified name, including the package specification, of a class.
SeverityNum [bt_int32s]	The Event Severity is used to define an event message severity. The data is stored in the Event Log table (EVENTLOG) when an event is logged. The logging component defines the event severity when the message is logged. Valid Values are: 0 - Informational 1 - Warning 2 - Critical 3 - Fatal
MssgTx [bt_stringf(2000)]	The text of an event message logged to the Event Log table (EVENTLOG).

Event_Document (1.0) (evdocd)

The Event Document table contains documentation for event messages regarding the sub-system information for each SSID group, the probable cause of the event, action taken by the process when the event happened, the remedy for the situation that caused the event and token descriptions for the event.

[Not Audited] [Supports versioning]

Element (type)	Description
evt_rec_typ*[evt_rec_typ 1.0]	The record type for the event document can be SS - sub-system name, PC - probable cause, AT - action taken, RM - rememdy, TK - token information.
ssid*[bt_int32s]	Subsystem Identification Number which uniquely identifies the class logging the message.
evt_num*[bt_int32s]	The event number of the exception being logged.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
evt_doc_data_lgth [bt_int16s]	The length of the data in the data buffer.
evt_doc_data [bt_stringf(780)]	This field contains data for the event document.

EVENTLOG (1.0) (evtlog)

Event Log.

[Audited] [Supports versioning]

Element (type)	Description
EvntTimeTm*[ts 1.0]	The event generation timestamp.
CmpnIDTx*[bt_stringf(8)]	The component identifier
ChnlIDIntfNameTx [bt_stringf(16)]	An optional Channel Identifier or Interface Name
TaskIDTx [bt_stringf(10)]	The task identifier
ThrdIDTx [bt_stringf(10)]	The thread identifier.

Element (type)	Description
UnqEvntIDTx [bt_stringf(32)]	The unique event identifier.
RltdEvntIDTx [bt_stringf(32)]	An identifier of a related event.
GnrtIDTx [bt_stringf(16)]	An identifier of the event generator.
GnrtBldVsnTx [bt_stringf(32)]	The build version of the generator.
SbjcTx [bt_stringf(64)]	The subject of the event.
SSIDTx [bt_stringf(8)]	The subsystem identifier.
EvntNum [bt_int32s]	The event number.
SvrtNum [bt_int32s]	The event severity. Valid values are: 0 (Informational), 1 (Warning), 2 (Error - default), and 3 (Critical Error).
SSIDOwnrIDTx [bt_stringf(8)]	The identifier of the owner of the subsystem. Not currently used.
SSIDVrsnTx [bt_stringf(6)]	The version of the subsystem. Not currently used.
EvntMsgTx [bt_stringv(3800)]	The event message text.

Exception_Log (2.0) (exlogd)

The Exception Log table contains one record for each exception condition encountered by an end point which requires the external message to be logged.

[Not Audited] [Supports versioning]

Element (type)	Description
ts* [bt_int64s]	The UTC timestamp of when the record is written.
ssid [bt_int32s]	Subsystem Identification Number which uniquely identifies the class logging the message.
evt_num [bt_int32s]	The event number of the exception being logged.
cmpnt_id [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
sym_nam [bt_stringf(16)]	The symbolic name of the entity which sent the external message.
elog_data_lgth [bt_int16s]	The length of the external message.
elog_data [bt_binaryv(4000)]	The external message to be written to the Exception Log table.

EXCPT (1.0) (EXCPT)

Table used for testing Exception Collisions

[Audited] [Does not support versioning]

Element (type)	Description
exception_time* [bt_stringf(26)]	This is the time the exception is written to the exceptions table
text [bt_stringv(3900)]	This is the text of the message. The size of the field is actually much larger, but this is a dummy size to make it variable in size to test on other platforms where this table doesn't exist.

Exported_Operator_Documentation (1.0) (opdocd)

This table contains information about the registered exported operators on a system. The operators description, prerequisites, return values and parameter values are configured in this table.

[Audited] [Supports versioning]

Element (type)	Description
mngl_oper_nam* [bt_stringf(64)]	The mangled name of the exported operator. The operator name is mangled by appending the data types of the parameters separated by #.
oper_nam [bt_stringf(32)]	The name of an exported operator as registered in the OPER_RGSTR macros. This field will be left-justified, space filled. All letters should be capitalized.
cmpnt_nam [bt_stringf(50)]	The Component Name associated with the component that exports an operator to the script engine. This is descriptive test only.
oper_descr [bt_stringf(256)]	A description of an exported operators function and usage.
oper_prreq [bt_stringf(256)]	Any conditions that must be met before an exported operator can be called successfully.
oper_rtrn_typ [bt_int16s]	The data type that the operator will return. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_rtrn_descr [bt_stringf(256)]	A description of the values that can be returned by an operator.
oper_param_typ_1 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_1 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_1 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_2 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_2 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_2 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_3 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean

Element (type)	Description
oper_param_io_3 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_3 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_4 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_4 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_4 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_5 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_5 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_5 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_6 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_6 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_6 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_7 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_7 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_7 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_8 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_8 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_8 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_9 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean
oper_param_io_9 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_9 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
oper_param_typ_10 [bt_int16s]	The data type of a parameter to an exported operator. Must be one of the following values:0 - Invalid, 1 – void, 2 – Number, 3 – String, 4 - Boolean

Element (type)	Description
oper_param_io_10 [bt_int16s]	Indicates whether the operator parameter is input or output. 0 = input 1 = output
oper_param_descr_10 [bt_stringf(128)]	A description of the value to be used as an operators parameter.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

EXTRCNCT (1.0) (extcnd)

The external connection table is used to configure information for a process that is needed to send messages to another process regardless of whether that process is on the same server or a different server. It is used to configure TCP/IP, HTTP, JMS and SMTP connections with configurable message parameters such as 2 byte headers, the es MDS message header and EOT characters, timeout settings and retry counts.

[Audited] [Supports versioning]

Element (type)	Description
ExtrCnctID*[bt_stringf(50)]	Used to uniquely identify an external connection in the External Connection table (EXTRCNCT).
PrcsID*[bt_stringf(16)]	A unique ID assigned to a process in the Process table (PROCESS).
DscrTx [bt_stringf(255)]	This element is used to record descriptive text for entries in the Application Configuration table (APPLCNFG), External Connection table (EXTRCNCT) and the Listener table (LISTENER).
MssgFrmtClasTx [bt_stringf(255)]	The Message Formatter class associated with an external connection. The data is configured on the External Connection table (EXTRCNCT).
PrtcCd [bt_stringf(50)]	The terminal protocol code, configured on the ES ATD Configuration Profile table (ATDCNFG). The value indicates which line protocol is being used for communications with this terminal. Valid values are: A = ASYNC P = X25 PVC X = X25 SVC S = SNA T = TCP/IP The default value is T.
PrtcOptnList [bt_stringf(100)]	The Protocol Option List element is used to indicate the message protocol options to use when sending a message through the Message Services. An example is an option of .EOT. to indicate the message requires an End Of Text character. The data is configured on the External Connection table (EXTRCNCT) and Listener table (LISTENER).
PrtcDfnd1Tx [bt_stringf(255)]	The Protocol Field 1 element is used to indicate protocol specific information to use when sending a message through the Message Services. Valid values for this field are defined in the services that use it. For messages sent via TCPIP, this field might contain the IP address or the port to which to send the message. The data is configured in the External Connection table (EXTRCNCT) and the Listener table (LISTENER).
PrtcDfnd2Tx [bt_stringf(255)]	The Protocol Field 2 element is used to indicate protocol specific information to use when sending a message through the Message Services. Valid values for this field are defined in the services that use it. For messages sent via TCPIP, this field might contain the IP address or the port to which to send the message. The data is configured in the External Connection table (EXTRCNCT) and the Listener table (LISTENER).

Element (type)	Description
PrtcDfnd3Tx [bt_stringf(255)]	The Protocol Field 2 element is used to indicate protocol specific information to use when sending a message through the Message Services. Valid values for this field are defined in the services that use it. For messages sent via TCPIP, this field might contain the IP address or the port to which to send the message. The data is configured in the External Connection table (EXTRCNCT) and the Listener table (LISTENER).
TimeOutNum [bt_int32s]	Used to indicate the amount of time to wait on an external message connection before returning a timeout failure. The data is configured on the External Connection table (EXTRCNCT).
RtryAtmpNum [bt_int32s]	The Retry Attempts defines the maximum number of times Message Services will attempt to resend a failed message. The value is configured in the External Connection table (EXTRCNCT).
InitConnNum [bt_int32s]	This element stores the number of connections to open initially when opening an external connection. The element is stored on the External Connection table (EXTRCNCT).
MaxConnNum [bt_int32s]	Used to indicate the maximum number of Client Sockets to allow to be created for a given host address/port combination and to indicate the maximum number of connections to accept for a Server Socket. This is used in the Listener and External Connection tables.
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

FCSHPRFL (1.0) (fcschd)

This data source contains the ATM configuration for fast cash withdrawal processing. This data source is accessed via the fast cash profile located on the ATM Static Data Table (ESATDS1).

[Audited] [Supports versioning]

Element (type)	Description
FstCshPrflTx*[prfl_def 1.0]	The fast cash profile identifies the fast cash setup to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
FstCsh1AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh2AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh3AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).

Element (type)	Description
FstCsh4AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh5AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh6AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh7AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh8AmntNum [bt_int32s]	The following field contains the whole currency unit for fast cash withdrawals for which the specified Fast Cash key was selected. The fast cash amount used is based on the fast cash key selected at the terminal. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh1CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh2CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh3CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh4CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh5CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh6CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh7CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the

Element (type)	Description
	corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).
FstCsh8CrncCd [crncy_cde 1.0]	The following field contains the currency code for fast cash withdrawals for which the specified Fast Cash key was selected. The currency code pertains to the corresponding fast cash amount. The data is stored on the ES ATM Configuration Profile table (ATDCNFG).

Fees (1.0) (feed)

The Fees Table contains the information needed to calculate a fee for a transaction for a specified fee profile and fee name. (Future Use)

[Audited] [Supports versioning]

OLTP: Fees_OLTP

Element (type)	Description
fee_prfl*[prfl_def 1.0]	The fee profile. Used as part of the primary key to the Fee Table. (Future Use)
fee_nam*[bt_stringf(16)]	A name assigned to a specific fee.
fee_eff_dat*[yyyyymmdd 1.0]	The date a fee becomes effective.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
fee_opt [bt_int16s]	The fee option indicates how a specified fee is to be calculated. Valid values are: 0 - No fee. 1 - Flat fee amount (default). 2 - Percentage of the transaction amount 3 - Lowest amount of options 1 and 2. 4 - Highest amount of options 1 and 2. 5 - Flat fee plus a percentage of the transaction amount.
amt_fee [amt 1.0]	The amount of a specified fee.
fee_pctg [bt_int16s]	The percent of the transaction amount to be included as a fee. This value is expressed in hundredths of a percent (e.g. 100 = 1%).
fee_rvsl_opt [bt_int16s]	Indicates if the fee should be recalculated and reapplied to the new transaction amount in the case of partially reversed transactions. Valid values: 0 – No, do not calculate a new fee (default). 1 – Yes, calculate a new fee based on the completed transaction amount.
crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.

Fields (1.0) (ufield)

Fields Table

[Audited] [Supports versioning]

Element (type)	Description
FieldID*[bt_stringf(30)]	

Element (type)	Description
Descr [bt_stringf(50)]	
DataType [bt_stringf(10)]	
Filterable [bt_stringf(1)]	

Fifth_Third_Intf (1.0) (ftifd)

Fifth Third Interface Table.

[Audited] [Supports versioning]

OLTP: Fifth_Third_Intf_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_set [bt_int16s]	This field indicates the message set that is supported by the interface. (0 - Financial Institution, 1 = Host Data Capture).

file_part_catalog (1.0) (fpctgd)

The File Partition Catalog table specifies the low key range which defines the data source with a key greater than or equal to the low key range.

[Audited] [Supports versioning]

Element (type)	Description
asgn_nam* [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
low_key_range* [bt_stringf(222)]	The low key which defines the starting range associated with a data source until the next key range in the file partition catalog.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
key_lgth [bt_int16s]	The length of the low key range to compare against the built key.
asgn_nam_root [bt_stringf(31)]	The assign name root which when the suffix is added is used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
asgn_nam_suffix [bt_stringf(1)]	The assign name suffix which when added to the assign name root is used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

file_part_fields (1.0) (fpfldd)

The File Partition Fields table contains the fields and attributes associated with an assign. The cumulative character size for all fields may not exceed 256 bytes.

[Audited] [Supports versioning]

OLTP: file_part_fields_OLTP

Element (type)	Description
asgn_nam* [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fld_ord_num* [bt_int16s]	This is the field ordinal number to use when building the key buffer associated with a table.
fld_nam [bt_stringf(32)]	This is the name of the field.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
fld_val_lgth [bt_int16s]	This is the length of the field to make up the key for a file partition.
dflt_val [bt_stringv(256)]	The default value to use when an insert is performed and the field is not supplied. This field must match the default value assigned for the field in metaman.

file_part_list (1.0) (fplstd)

The File Partition List table contains a list of all assigns that point to a File Partition Catalog.

[Audited] [Supports versioning]

OLTP: file_part_list_OLTP

Element (type)	Description
asgn_nam* [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
asgn_nam_data [bt_stringf(32)]	The assign name data used to map to a physical location for the data file associated with a file partition. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

File_Update_Route (1.0) (furd)

The File Update Route table contains configuration on how file update requests should be broadcast to external systems.

[Audited] [Supports versioning]

OLTP: File_Update_Route_OLTP

Element (type)	Description
acq_rte_prfl*[prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
iss_rte_prfl*[prfl_def 1.0]	The route profile of the issuer whose customer initiated the transaction. The issuer route profile is defined where ever the issuer is determine and allows one or more issuers to share routing and authorization configurations. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
file_typ*[bt_stringf(2)]	The type of a file update.
cmpnt_id*[bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Filters (2.0) (uftrs)

Filters table

[Audited] [Supports versioning]

Element (type)	Description
FilterID*[bt_stringf(30)]	
FieldID [bt_stringf(30)]	
BeginValue [bt_stringf(50)]	
EndValue [bt_stringf(50)]	
Descr [bt_stringf(50)]	
LastMaintTS [ts 1.0]	
OwnerID [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.
Active [bt_char DEFAULT Y]	Indicates if the Filter is active. This will allow Filters to go through a staging process before being put in an active state. Valid values are "Y" (default) and "N".
ReadOnly [bt_char DEFAULT N]	Indicates if a Filter can be updated or deleted. This will allow static Filters to be defined. Valid values are "Y" and "N" (default)

FIS_Interface (1.0) (fisifd)

Record of Changes: Date Version Person ----- 10AUG2011 1.0.00 D. Hatfield Initial release. Symptom: None. Problem: None. Fix: None. Reference: WO #02149 FIS Interface Configuration.

[Audited] [Supports versioning]

OLTP: FIS_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_msg_sec_cde [bt_stringf(8)]	Acquirer Message Security Code.
iss_msg_sec_cde [bt_stringf(8)]	Issuer Message Security Code.
enhnc_acq_bnk_id_proc [bt_flag DEFAULT 0]	Enhanced acquirer identification code processing
dflt_acq_bnk_id [bt_stringf(11)]	Default acquirer identification code
ebt_enbl [bt_flag DEFAULT 0]	EBT Enabled flag
setl_inst_id [bt_stringf(11)]	Settlement Institution ID

FldVals (1.0) (ufldvl)

Field Values table

[Audited] [Supports versioning]

Element (type)	Description
FVID [bt_int32s]	
FieldID* [bt_stringf(30)]	
Value* [bt_stringf(50)]	
DisplayValue [bt_stringv(50)]	

FLTROLE (1.0) (uflxrl)

Filter Roles table

[Audited] [Supports versioning]

Element (type)	Description
FilterID* [bt_stringf(30)]	

Element (type)	Description
RoleID*[bt_stringf(30)]	
OwnerID*[bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.

FIXFldVI (1.0) (uflxfl)

Filter Field Values table

[Audited] [Supports versioning]

Element (type)	Description
FilterID*[bt_stringf(30)]	
FVID*[bt_int32s]	

FPID_History (1.0) (fpidd)

The Faster Payment Identifier History data source is used for enhanced duplicate detection, if configured in the interface. It contains one record for each FPID processed by the Interface.

[Audited] [Supports versioning]

Element (type)	Description
hash_val*[bt_int16s]	The hash of the Faster Payment ID (FPID) of the payment. Used to allow partitioning of the queue file.
send_dat*[ts 1.0]	Date sent.
crncy_cde*[crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
pmnt_typ*[txn_cde 1.0]	Payment Type of the FPS payment. Can have one of the following values: 00 - Bulk Authorisation, 10 - Single Immediate Payment, 20 - Return Payment, 25 - Scheme Return Payment, 30 - Standing Order, 40 - Forward Dated Payment, 50 - Corporate Bulk Payment.
txn_ref_num*[bt_stringf(18)]	Transaction Reference Number (TRN).
send_fps_inst*[bt_stringf(11)]	Sending FPS Institution.
inbnd_outbnd_flg*[bt_char]	Indicates whether the transaction is inbound(I) or outbound (O). Default is I.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_typ [bt_stringf(4)]	The message type of the transaction.

FPS_Batch_Config (1.0) (fpbcd)

The FPS Payment Submission data source contains one record per batch process and contains the configuration options for the Batch Payment Submission process.

[Audited] [Supports versioning]

OLTP: FPS_Batch_Config_OLTP

Element (type)	Description
btch_nam*[bt_stringf(16)]	The symbolic name of the Batch Submission Process. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
cmpnt_id [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
delay_timr_lmt [timr_lmt 1.0]	Delay Timer Limit, indicates the number of seconds to wait to check whether records exist in the Batch Submission Input data source. Valid values are: 1 – 9999, 180=Default.
send_timr_lmt [timr_lmt 1.0]	Timer Limit, indicates the number of seconds to wait for a response after sending a Batch Auth record. Valid values are: 1 - 9999, 60=Default.
max_outstnd_rqst_lmt [bt_int16s]	The maximum number of requests that may be outstanding at a time for the configured entity (interface or station). An interfaces maximum outstanding may be greater than or less than the cumulative stations that belong to the interface. Valid values are: 0 - 9999. Default value is 1000 for interfaces and 100 for stations.
max_err_lmt [bt_int16s]	Maximum consecutive error limit for non-fatal processing errors. If non-zero then if this limit is reached, the current processing run is aborted. If set to zero (default) then no limit will apply and the run will continue
max_retries [bt_int16s]	The maximum number of times a Batch Auth record will be resent before the record is deleted. Valid values are 0 to 999. Default value is 3.
pmnt_typ_prfl [prfl_def 1.0]	Payment Type Profile. The Payment type profile holds Single Transaction Limit, Payment Priority Groups and validity information for the FPS Payment Type.

FPS_Batch_Control (1.0) (fpbtcd)

The FPS Payment Submission data source contains one record per batch process and contains the configuration options for the Batch Payment Submission process.

[Audited] [Supports versioning]

Element (type)	Description
cmpnt_id*[bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
btch_id* [bt_stringf(48)]	The identified of the input batch file originating this record. The format of this is dependant on the component ID. Typically, it will be derived from the batch header record.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
btch_ts [ts 1.0]	Timestamp that this record was created by the relevant batch process.
compl_ts [ts 1.0]	Timestamp that the last submission run for this batch completed.
num_recs [bt_int64s]	The number of transaction records in the batch. Set during initial batch processing.
num_proc [bt_int64s]	The number of records processed. Set to zero during initial batch processing and updated during the transaction processing phase of the batch run.
num_err [bt_int64s]	The number of records that could not be processed due to errors in processing the batch.
btch_stat [bt_char]	The status of the batch, one of: P – Pending submit, L – Load in progress, S – Submit in progress, C – Complete OK, E – Complete with errors, R – Rejected during load.
fps_sbmt_dsrc_asgn [bt_stringf(32)]	Assign name of the FPS Submission Data Source that this batch has been applied to.
btch_ctx_buf [bt_binaryv(100)]	This variable length field is available to allow batch processing to hold specific context relating to the batch run in progress.

FPS_Cutover (1.0) (fpsctd)

The Faster Payments Cutover data source has one row per FPS Cutover Cycle. Rows are added when the Faster Payments Central Infrastructure indicates that it has begun a new settlement cycle (indicated by a change in settlement date and/or cycle ID).

[Audited] [Supports versioning]

Element (type)	Description
post_dat* [yyymmdd 1.0]	The current settlement date.
setl_cyc_id* [bt_int16s]	The settlement cycle identifier for Faster Payments.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
setl_beg_ts [ts 1.0]	The beginning time of this settlement cycle.
setl_exp_ts [ts 1.0]	The expiration time of this settlement cycle. After a settlement cycle cutover notification has begun a new settlement cycle, the old settlement period will be held open for transactions in flight until its expiration, faster which payments for the this settlement cycle will be rejected.
setl_cyc_stat [bt_int16s]	This is the status of the current settlement cycle. Possible values are: 0 – settlement cycle active, 1 – settlement cycle cutover started, 2 – settlement cycle cutover complete.

Element (type)	Description
setl_cyc_typ [bt_int16s]	The type of FPS Settlement Cycle this record represents. May be one of: 0 - Current Cycle, 1 - Previous Cycle, 2 - Historic Cycle. There should only be one each of current and previous cycles, but there can be many historic cycles, depending on whether cleanup processing has been invoked.
ttl_jrnl_stat [bt_int16s]	Value indicating the journal status for the totals for this settlement cycle. Values are 0 = not yet logged, 1 = interim totals logged, 2 = final totals logged, 9 = not logged due to error

FPS_Member (2.0) (fpsmd)

The FPS Member Table is read during issuer determine by FPS-aware acquirer interfaces and contains one row for each FPS Scheme member (i.e., Bank, Handling Agency, and Responding Third Party Beneficiary). The Bank Code, used as the Key, is obtained from the ISCD look-up, or provided in the external message.

[Audited] [Supports versioning]

OLTP: FPS_Member_OLTP

Element (type)	Description
fps_bnk_id*[bt_stringf(4)]	Bank ID of the UK bank.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
iss_rte_prfl [prfl_def 1.0]	The route profile of the issuer whose customer initiated the transaction. The issuer route profile is defined where ever the issuer is determine and allows one or more issuers to share routing and authorization configurations. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
rte_typ [bt_stringf(1)]	The route type identifies whether to use the acquirer/issuer profile or issuer profile only. If the acquirer/issuer profile is used, Router will perform a lookup using the Acquirer Issuer Relation table and then use the Route table. If the issuer profile only is used, only the Route table is used. Valid values are: 0 - Acquirer/Issuer, 1 - Issuer only. Default value is 0.
lmt_prfl [prfl_def 1.0]	The limit profile. Used as the key to the Limit Table.
fps_stat [bt_stringf(1)]	The current status of the remote beneficiary, as advised by unsolicited status messages from the Central Infrastructure, or by ah-hoc updates of this table. Valid values are: 0: ACTIVE, 1 – SUSPEND CREDIT, 2 – SUSPEND DEBIT, 3 – NOT CONNECTED.
fps_local [bt_flag]	The FPS Local Flag indicates that this beneficiary connects to the FPS Gateway directly, and not through the Central Infrastructure. It effectively identifies the Beneficiary as on-us.
fps_q_prfl [prfl_def 1.0]	The profile name of the payments queue file(s) for this Beneficiary. Outbound payments are queued if the remote beneficiary is down, and queuing is configured for this payment type.

Element (type)	Description
net_send_thrld_stat [bt_stringf(2)]	The FPS Net Sender Threshold Status.
pmnt_pri_grp_01 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_01 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_02 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_02 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_03 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_03 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_04 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_04 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_05 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_05 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_06 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.

Element (type)	Description
pmnt_pri_avail_06 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_07 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_07 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_08 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_08 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_09 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_09 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
pmnt_pri_grp_10 [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_pri_avail_10 [bt_flag]	The availability flag for the Payment Type Priority Group. Rather than being deleted, payment type priority groups are marked as being made unavailable when no longer used.
fps_setl_mbr [bt_flag]	Indicates if this bank is a settlement member against who we wish to maintain bilateral totals.

FPS_Payment_Pri_Group (2.0) (fppgd)

The FPS Payment Priority Group table has one row per Payment Type Priority Group, as used by the Faster Payments Gateway.

[Audited] [Supports versioning]

OLTP: FPS_Payment_Pri_Group_OLTP

Element (type)	Description
pmnt_pri_grp* [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
filler* [bt_stringf(1)]	One byte filler.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pmnt_pri_descr [bt_stringf(40)]	A brief description of the meaning of the Payment Type Priority Group used by the FPS Scheme.

FPS_Payment_Submission (1.0) (fpsubd)

The FPS Payment Submission data source contains one record per payment transaction in the file submission. Each record will be sent as a separate payment transaction.

[Audited] [Supports versioning]

Element (type)	Description
cmpnt_id* [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
btch_id* [bt_stringf(48)]	The identified of the input batch file originating this record. The format of this is dependant on the component ID. Typically, it will be derived from the batch header record.
seq_num* [bt_int64s]	The sequence number identifying the last transaction performed in the current batch. The value is incremented by one for each occurrence of transaction within a current batch. On close batch transaction processing, the value is reset to zero and accumulation begins within the new batch when the first transaction occurs. This is system protected element.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
send_bnk_id [bt_stringf(4)]	Sending Bank ID of UK Bank submitting a faster payment.
send_fps_inst [bt_stringf(11)]	Sending FPS Institution.
crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
send_dat [ts 1.0]	Date sent.
fps_pmnt_typ [bt_stringf(2)]	Payment type code.
fps_send_enty [bt_stringf(2)]	The Sending FPS Entity for a Faster Payment. Possible values are 10-Member Sender, 20-Agency Sender, 30-DCA Sender – Member,

Element (type)	Description
	40-DCA Sender – Agency, 50-FIM Sender – Member, 60-FIM Sender – Agency. Default is 10 - Member
fps_rcv_enty [bt_stringf(2)]	The Receiving FPS Entity for a Faster Payment. Possible values are 00-Undefined or unknown Receiver/Sponsor, 10-Member Receiver, 20-Agency Receiver, 40-Responding Third Party Beneficiary, 50-Non-Responding Third Party Beneficiary, 60-Bulk Authorisation Member Sponsor, 70-Bulk Authorisation Agency Sponsor. Default is 00- Unknown
txn_ref_num [bt_stringf(18)]	Transaction Reference Number (TRN).
amt_txn [amt 1.0]	Amount of payment.
orig_cr_inst [bt_stringf(11)]	Originating credit institution.
orig_acct [bt_stringf(34)]	Originating customer account number.
orig_acct_nam [bt_stringf(40)]	Originating customer account name.
orig_acct_addr [bt_stringf(140)]	Originating customer account address.
end_to_end_ref [bt_stringf(31)]	End-to-end reference.
agency_mbr_sort [bt_stringf(11)]	Agency sort code with member.
agency_mbr_acct [bt_stringf(34)]	Agency account with member.
bnf_cr_inst [bt_stringf(11)]	Beneficiary credit institution.
bnf_acct [bt_stringf(34)]	Beneficiary customer account number.
bnf_acct_nam [bt_stringf(40)]	Beneficiary customer account name.
bnf_acct_addr [bt_stringf(140)]	Beneficiary customer account address.
rtrn_pmnt_id [bt_stringf(42)]	Returned payment FPID.
pmnt_rtrn_cde [bt_stringf(8)]	Payment return code.
fps_pmnt_subtyp [bt_stringf(3)]	Payment sub-type code.
fps_pmnt_purpose [bt_stringf(3)]	Purpose (transaction type).
fps_acct_typ [bt_stringf(1)]	Type of account code (numeric, set to zero if not used).
fps_num_ref [bt_stringf(4)]	
fps_ref_info [bt_stringf(18)]	Reference information (account identification).
rmt_info [bt_stringf(140)]	Remittance information.
reg_rptg [bt_stringf(105)]	Regulatory reporting.
orig_crncy_cde [crncy_cde 1.0]	Original currency. The numeric currency code as defined in ISO document 4217.
amt_orig [amt 1.0]	Payment amount in original currency.
pmnt_exchg_rate [bt_stringf(12)]	Exchange rate.
fps_chrg_info [bt_stringf(204)]	Charging information.
send_cnt [bt_int16s]	The number of attempts at sending this record.
lst_snd_stat [bt_int16s]	Status at last send – one of 0 – not sent, 1 – message failure, 2 timeout, 3 – beneficiary unavailable, 9 – error.

Element (type)	Description
csm_buf [bt_binaryv(1000)]	This variable length field is available to allow customer specific data.

FPS_Payment_Typ (1.0) (fpptd)

This table holds one row for each Payment Type profile, as used by the Faster Payments Gateway.

[Audited] [Supports versioning]

OLTP: FPS_Payment_Typ_OLTP

Element (type)	Description
pmnt_typ*[txn_cde 1.0]	Payment Type of the FPS payment. Can have one of the following values: 00 - Bulk Authorisation, 10 - Single Immediate Payment, 20 - Return Payment, 25 - Scheme Return Payment, 30 - Standing Order, 40 - Forward Dated Payment, 50 - Corporate Bulk Payment.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
sec_txn_lmt [amt 1.0]	Security Transaction Limit for the Payment Type, as advised by the FPS Scheme.
sec_txn_lmt_prev [amt 1.0]	Security Transaction Limit for the Payment Type, as advised by the FPS Scheme.
pmnt_pri_grp [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
pmnt_typ_avail [bt_flag]	The availability flag for the Payment Type Code. Rather than being deleted, payment type code are marked as being made unavailable when no longer used.
pmnt_q_flg [bt_flag]	Flag to indicate that payments of this type may be queued in the FPS Gateway if the remote beneficiary is unavailable or suspended for the payment class (credit/debit). Payments will be processed asynchronously in the gateway if set to true.

FPS_Queue (1.0) (fpsqd)

The FPQ Queue data source contains one row for each queued payment, waiting to be sent out via the payments interface (typically the FPS Central Infrastructure). It is similar to a SAF, but holds the full context of the queued payment.

[Audited] [Supports versioning]

Element (type)	Description
ts_q*[ts 1.0]	The timestamp that this entry was added to the queue file.
ctx_key*[bt_stringf(80)]	The context key supplied by the client when storing and retrieving context data.

Element (type)	Description
ctx_rec_num [bt_int16s]	The number of the context record within a set of records.
ctx_lgth [bt_int16s]	The length of transaction context in this queue record.
ctx_buf [bt_binaryv(3650)]	The transaction context in this queue record.

FPS_Queue_Assign (1.0) (fpqad)

The FPS Queue Assign contains one assign record for each combination of Queue Profile Name, Payment Priority and queue hash.

[Audited] [Supports versioning]

OLTP: FPS_Queue_Assign_OLTP

Element (type)	Description
fps_q_prfl* [prfl_def 1.0]	The profile name of the payments queue file(s) for this Beneficiary. Outbound payments are queued if the remote beneficiary is down, and queuing is configured for this payment type.
pmnt_pri_grp* [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
hash_val* [bt_int16s]	The hash of the Faster Payment ID (FPID) of the payment. Used to allow partitioning of the queue file.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
q_asgn_nam [bt_stringf(32)]	The assign name in the config.csv that points to the physical queue data source represented by this profile record.

FPS_Queue_Profile (1.0) (fpqpd)

The FPQ Queue data source contains one row for each queued payment, waiting to be sent out via the payments interface (typically the FPS Central Infrastructure). It is similar to a SAF, but holds the full context of the queued payment.

[Audited] [Supports versioning]

OLTP: FPS_Queue_Profile_OLTP

Element (type)	Description
fps_q_prfl* [prfl_def 1.0]	The profile name of the payments queue file(s) for this Beneficiary. Outbound payments are queued if the remote beneficiary is down, and queuing is configured for this payment type.
pmnt_pri_grp* [bt_stringf(1)]	The Payment Type Priority Group for the payment. The Priority Group is used for routing FPS Payments within BASE24-es FPS Gateway, to determine the Source

Element (type)	Description
	Route Profile, and hence the correct FPS CI Interface Instance. New priority groups can be added, and existing ones updated, by unsolicited messages send from the CI.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
q_mgr_nam [bt_stringf(16)]	The symbolic name of the queue manager process.
fps_q_enable [bt_flag]	Indicates if this instance of the FPS Interface can queue outbound payment messages, if the payment transaction indicates it should be queued (i.e., is to be processed asynchronously by the Gateway). If true then the payment will be queued to the appropriate SAF assign (debit or credit). Otherwise, the payment will be re-routed if the payment cannot be processed synchronously.
intf_nam [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
cmpnt_id [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
max_q_outstand_lmt [bt_int16s]	The maximum number of queue records that can be outstanding at a time. Valid values are 1 - 9999.
q_timr_lmt [timr_lmt 1.0]	Queue Timer Limit, indicates the number of seconds to wait for a response after transmitting a queued payment. Valid values are: 1 - 9999, 60=Default.
low_hash_val [bt_int16s]	The low hash value of the Primary Account Number (PAN) for the previous record. If this is the first record, use a value of -1.
max_q_retries_lmt [bt_int16s]	The maximum number of times a queued payment record will be resent before the record is deleted and the payment re-routed. Valid values are 0 to 999. A value of 0 indicates an infinite number of tries. Default value is 3.
q_delay_timr_lmt [timr_lmt 1.0]	Queue Timer Limit, indicates the number of seconds to wait to check whether records exist in the queue file waiting to be sent. Valid values are: 1 - 9999, 300=Default.
q_send_lmt [bt_int16s]	The number of queued payment messages that can be sent in one burst when the SAF delay timer expires. Default value is 1.
q_reset_timr_lmt [bt_int16s]	The number of seconds to wait before resetting the queue file position to the beginning of the file. Default value is 600 with a maximum of 9999

Functs (1.0) (ufuncts)

The Functions table

[Audited] [Supports versioning]

Element (type)	Description
FunctionID* [bt_stringf(30)]	
Descr [bt_stringf(50)]	

Futr_Key (1.0) (futrkd)

The Future Key Data Source holds future inbound and outbound keys used to process PINs.

[Audited] [Supports versioning]

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
inbnd_key_seq_num [bt_stringf(2)]	Key Sequence Number associated with the Inbound Key. This value will be included in the online Interchange message identifying the Working Key to be used in PIN Verification. Valid values: 01 or 02 or 03.
inbnd_kpt_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
inbnd_kpt_keyx [keyx_trpl 1.0]	Inbound Working Key - a future working key which will become the current working key on the next successful key exchange.
inbnd_kpt_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kpt_vvk [vvk 1.0]	Verification Value of the Inbound Working Key.
outbnd_key_seq_num [bt_stringf(2)]	Key Sequence Number associated with the Outbound Key. This value will be included in the online Interchange message identifying the Working Key to be used in PIN Verification. Valid values: 01 or 02 or 03.
outbnd_kpt_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
outbnd_kpt_keyx [keyx_trpl 1.0]	Outbound Working Key - a future working key which will become the current working key on the next successful key exchange.
outbnd_kpt_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kpt_vvk [vvk 1.0]	Verification Value of the Outbound Working Key.

GICC_Acq_SGN (1.0) (giccasd)

The GICC Acquirer SGN Table is used to track the sequence generation number data for inbound transactions.

[Audited] [Supports versioning]

Element (type)	Description
crd_accpt_id* [bt_stringf(15)]	The card acceptor identifier from field 42.
ccti_id* [bt_stringf(2)]	The Credit Card Type Institution identifier, taken from the GICC field 46.
term_id* [bt_stringf(16)]	The terminal identifier for the card acceptor.

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_seq_gen_num [bt_stringf(8)]	The current sequence generation number for this CCTI, taken from field 57.
last_iss_inst_id [bt_stringf(20)]	The issuer institution identifier for the last transaction.
last_pan [bt_stringf(28)]	The primary account number for the last transaction.
last_jrnl_amt [bt_int64s]	The journal amount for the last transaction.
last_seq_num [bt_stringf(12)]	The sequence number for the last transaction.

GICC_Channel (1.0) (giccd)

No description on file.

[Audited] [Supports versioning]

Element (type)	Description
chan_id*[chan_id 1.0]	The identifier of the channel (terminal id). This field is left-justified, uppercase (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ccti_id*[bt_stringf(2)]	Credit Card Type Identifier, taken from the GICC ISO field 46. The GICC equivalent of instrm_typ. Valid values are: 00-09 = American Express, 10-19 = B+S Card Service, 20-29 = Citicorp Kartenservice, 30-39 = Eurocard, 40-49 = Lufthansa AirPlus, 50-89 = Free to be used for other card issuers, 90-ZZ = Reserved for future use. The value 99 is only used in totals and diagnostic messages, indicating that the request message requesting data for all supported credit card types.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mcc [bt_stringf(4).]	Merchant Category Code (The card acceptor business code, crd_accpt_bus_cde) for this CCTI_ID. This optionally overrides the ISO field 18 of the incoming message (when mcc is not blank).
captr_ref [bt_stringf(4)]	The Capture Reference value for this CCTI_ID. Taken from ISO field 17 of the incoming message. Values 0000 through 9999. Incremented on ISO 0510 Totals response messages.
seq_gen_num [bt_stringf(8)]	The current Sequence Generation Number for this CCTI_ID. This is taken from ISO field 57 of the incoming message.
vu_num [bt_stringf(15)]	The Vertragsunternehmernummer for this CCTI_ID. This is the merchant contract number, optionally used to validate ISO field 42 of the incoming message (when vu_num is not blank).
mti_prev [bt_stringf(4)]	The previous transaction data. This information is stored when a transaction is completed and can be used to compose the online key and issuer for the Journal to retrieve the last transaction for this CCTI at this terminal.
pan_prev [bt_stringf(28)]	

Element (type)	Description
amt_prev [bt_stringf(18)]	
seq_num_prev [bt_stringf(12)]	
iss_inst_id_prev [bt_stringf(20)]	
curr_cr_cnt [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
curr_cr_rvsl_cnt [cnt 1.0 DELTA]	The number of credit transaction reversals that have been performed for this instrument type within the balance period.
curr_db_cnt [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
curr_db_rvsl_cnt [cnt 1.0 DELTA]	The number of debit transaction reversals that have been performed for this instrument type within the balance period.
curr_cr_amt [amt 1.0 DELTA]	The total amount (in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
curr_cr_rvsl_amt [amt 1.0 DELTA]	The total amount (in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
curr_db_amt [amt 1.0 DELTA]	The total amount (in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
curr_db_rvsl_amt [amt 1.0 DELTA]	The total amount (in the lowest currency unit) of all debit transaction reversals that have occurred for this instrument type within the balance period.
curr_net_settl_amt [amt 1.0 DELTA]	The net settlement amount (the lowest currency unit) of all transactions that have occurred for this instrument type within the balance period.
prev_cr_cnt [cnt 1.0]	The number of credit transactions that have been performed for this instrument type within the previous balance period.
prev_cr_rvsl_cnt [cnt 1.0]	The number of credit transaction reversals that have been performed for this instrument type within the previous balance period.
prev_db_cnt [cnt 1.0]	The number of debit transactions that have been performed for this instrument type within the previous balance period.
prev_db_rvsl_cnt [cnt 1.0]	The number of debit transaction reversals that have been performed for this instrument type within the previous balance period.
prev_cr_amt [amt 1.0]	The total amount (in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the previous balance period.
prev_cr_rvsl_amt [amt 1.0]	The total amount (in the lowest currency unit) of all credit transaction reversals that have occurred for this instrument type within the previous balance period.
prev_db_amt [amt 1.0]	The total amount (in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the previous balance period.
prev_db_rvsl_amt [amt 1.0]	The total amount (in the lowest currency unit) of all debit transaction reversals that have occurred for this instrument type within the previous balance period.
prev_net_settl_amt [amt 1.0]	The net settlement amount (the lowest currency unit) of all transactions that have occurred for this instrument type within the previous balance period.

GICC_Interface (1.0) (giccifd)

The GICC Interface Table.

[Audited] [Supports versioning]

OLTP: GICC_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dflt_mrch_id [bt_stringf(15)]	This merchant identifier is used in network management messages.
dflt_term_id [bt_stringf(16)]	This terminal identifier is used to get sequence generation numbers for transactions that do not have a terminal. An example is echo test messages.
dflt_ccti_id [bt_stringf(2)]	This Credit Card Type Institution identifier is used to get sequence generation numbers for transactions that do not have a card type or ccti_id.
instrm_typ_prfl [bt_stringf(16)]	The instrument type profile which defines the mapping between internal and external values.
use_gicc_stan [bt_flag]	This flag indicates whether to use the GICC STAN. Valid values are: 0 - Use issuer STAN, 1 - Use GICC STAN. Default value is 0.
valid_acq_seq_gen_num [bt_flag]	This flag indicates whether to validate the acquirer sequence generation number. Values are: 0 - Do not validate, 1 - Do validate. Default value is 0.

GICC_Iss_SGN (1.0) (giccisd)

The GICC Issuer SGN Table is used to track the sequence generation number data for outbound transactions.

[Audited] [Supports versioning]

Element (type)	Description
crd_accpt_id* [bt_stringf(15)]	The card acceptor identifier from field 42.
ccti_id* [bt_stringf(2)]	The Credit Card Type Institution identifier, taken from the GICC field 46.
term_id* [bt_stringf(16)]	The terminal identifier for the card acceptor.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
iss_seq_gen_num [bt_stringf(8)]	The current sequence generation number for this CCTI, taken from field 57.

GISO_ACQ_MSG_HND (1.0) (gamhndd)

The GISO Acquirer Message Handling Table.

[Audited] [Supports versioning]

OLTP: GISO_ACQ_MSG_HND_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_class*[bt_stringf(4)]	The message class of the transaction as determined from the Inbound Message Definition table
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
log_extrn_msg [bt_flag]	This flag indicates whether to log external messages received from the acquirer with this message class. Valid values are: 0 - false, Do not log, 1 - true, Log message Default value is 0.
send_rqst_timeout [bt_stringf(1)]	This value indicates whether a response should be sent to the acquirer when the request has timed out or whether it should just be dropped. Valid values are: 0 - Do not send, 1 - send response Default value is 1.
pro_unmatched_rvsl [bt_flag]	This flag indicates whether the acquire wants the reversal sent to the Issuer when we cannot match the reversal with a request. Valid values are: 0 - false, do not process, 1 - true, process unmatched reversals Default value is 0.
pro_invlid_resp [bt_stringf(1)]	This value indicates the action to be taken when a response from an issuer does not pass response validation. Either the response is dropped or the request is denied and a response sent. Valid values are: 0 - drop the response, 1 - deny and respond to the acquirer Default value is 0.

GISO_CRD_ACPT_RT (1.0) (gcrdrtd)

The GISO Card Acceptor ID / Source Routing table is used to set the routing table

[Audited] [Supports versioning]

OLTP: GISO_CRD_ACPT_RT_OLTP

Element (type)	Description
crd_accpt_id*[bt_stringf(15)]	The card acceptor identifier from field 42.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
src_rte_prfl [bt_stringf(16)]	The Source Routing Profile to be used in routing.

GISO_Interface (1.0) (gisoifd)

The German ISO (GISO) Interface Table.

[Audited] [Supports versioning]

OLTP: GISO_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
use_pri_sta [bt_flag]	This flag indicates whether to use the Primary Station for outbound requests. Valid values are: false - Use any available, true - Use Primary station if available. Default value is true.
dflt_nmm_msg_class [bt_stringf(4)]	This message class is used in network management messages.
dflt_nmm_proc_cde [bt_stringf(6)]	This default proc code is used in network management messages
dflt_nmm_trk_3 [bt_stringf(22)]	This default Track 3 data is used in network management messages
dflt_nmm_term_id [bt_stringf(16)]	This terminal identifier is used for network management messages
dflt_nmm_crd_accpt_id [bt_stringf(15)]	This card acceptor ID is used in network management messages
xfer_pt [bt_int16s]	The transfer point. Valid values are 0 - Default, 1 - Visa, 2 - Mastercard, 3 - American Express, 4 - Diners, 5 - Interlink, 6 - Plus, 7 - Cirrus, 8 - Maestro, 9 - Discover, 10 - JCB, 11 - FDI, 12 - CardProcess, 13 - ATOS, 14 - B&S, 15 Finanzit, 16 - Citicorp Default value is 0.

GISO_IN_MSG_DEF (1.0) (gimdefd)

The GISO Inbound Message Definition.

[Audited] [Supports versioning]

OLTP: GISO_IN_MSG_DEF_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_typ* [bt_stringf(4)]	The message type of the transaction.
proc_cde* [bt_stringf(6)]	The external proc code from the the inbound transaction.
msg_class* [bt_stringf(4)]	The message class of the transaction as determined from the Inbound Message Definition table

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
req_fld [bt_binaryf(24)]	A bit map indicating which of the 192 data elements in the Inbound Message is mandatory when determining the message class. Valid values are: 0 - No, the data element is not required for inbound messages. 1 - Yes, the data element is required for inbound messages. Default value is 0 for each data element.
missing_fld [bt_binaryf(24)]	A bit map indicating which of the 192 data elements in the Inbound Message that must not be present, or must be missing when determining the message class. Valid values are: 0 - No, the data may be present. 1 - the data element must be missing from the inbound messages. Default value is 0 for each data element.
iso_msg_prfl [bt_stringf(16)]	The message profile of the message class which overrides the ISO Message profile for the interface if specified. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
fld_defn_prfl [bt_stringf(16)]	The field definition profile for this message class which contains the individual field definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
act_cde_prfl [bt_stringf(16)]	The Action Code Profile for this message class which contains the internal to external action code mappings. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.

GISO_ISS_MSG_HND (1.0) (gimhndd)

The GISO Issuer Message Handling Table.

[Audited] [Supports versioning]

OLTP: GISO_ISS_MSG_HND_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_class*[bt_stringf(4)]	The message class of the transaction as determined from the Inbound Message Definition table
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
log_extrn_msg [bt_flag]	This flag indicates whether to log external messages sent to and received from the issuer for this message class. Valid values are: 0 - false, Do not log, 1 - true, Log message Default value is 0.
send_unmatched_rvsl [bt_flag]	This flag indicates whether the issuer wants to receive an reversal which could not be matched to the request. Valid values are: 0 - do not send, 1 - send unmatched reversal response on timeout. Default value is 0.

Element (type)	Description
pro_saf_ind [bt_stringf(1)]	This value indicates whether advices and reversals are to be written to the SAF file or should be sent in real time as with requests. Valid values are: 0 - always SAF, 1 - SAF automatic reversals but not manual reversals, 2 - Never SAF Default value is 0.

GISO_OUT_MSG_DEF (1.0) (gomdefd)

The GISO Outbound Message Definition.

[Audited] [Supports versioning]

OLTP: GISO_OUT_MSG_DEF_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_class* [bt_stringf(4)]	The message class of the transaction
msg_typ* [bt_stringf(4)]	The message type of the transaction.
proc_cde* [bt_stringf(6)]	The external proc code from the the inbound transaction.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
iso_msg_prfl [bt_stringf(16)]	The message profile of the message class which overrides the ISO Message profile for the interface if specified. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
fld_defn_prfl [bt_stringf(16)]	The field definition profile for this message class which contains the individual field definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
act_cde_prfl [bt_stringf(16)]	The Action Code Profile for this message class which contains the internal to external action code mappings. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.

HISO87_Interface (9.0) (hi87d)

The ISO 8583-1987 Host Interface configuration data.

[Audited] [Supports versioning]

OLTP: HISO87_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
orig_id [bt_stringf(16)]	Identifies the originator of the Cryptographic Service Message for Dynamic Key Exchange messages. The value in this field must be alphanumeric with a minimum length of 4 bytes. Unused positions must be padded to the right with spaces.
rcv_id [bt_stringf(16)]	Identifies the receiver of the Cryptographic Service Message for Dynamic Key Exchange messages. The value in this field must be alphanumeric with a minimum length of 4 bytes. Unused positions must be padded to the right with spaces.
atm_tkn_prfl [bt_stringf(16)]	Profile value used to read the Token Config table for ATM transactions.
pos_tkn_prfl [bt_stringf(16)]	Profile value used to read the Token Config table for POS transactions.
end_pt_typ [bt_stringf(1)]	This field represents the type of the endpoint. 0 = Host, 1 = Interchange.
atm_act_cde_prfl [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pos_act_cde_prfl [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
atm_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
pos_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
atm_proc_cde_prfl [bt_stringf(16)]	Profile value used to read the Processing Code Mapping tables for ATM transactions.
pos_proc_cde_prfl [bt_stringf(16)]	Profile value used to read the Processing Code Mapping tables for POS transactions.
atm_acq_surch_prfl [prfl_def 1.0]	The Acquirer Surcharge Profile. This allows acquirers to be grouped together in logical surcharging groups for acquirers that perform the same surcharging logic.
pos_acq_surch_prfl [prfl_def 1.0]	The Acquirer Surcharge Profile. This allows acquirers to be grouped together in logical surcharging groups for acquirers that perform the same surcharging logic.
fhm_act_cde_prfl [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fhm_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination

Element (type)	Description
	of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
instrm_stat_prfl [bt_stringf(16)]	Instrument status profile. Used as part of the primary key to read the Instrument Status External to Internal data source. This field is being replaced by a new field on the Interface data source to be used by multiple Interfaces.
instrm_typ_prfl [bt_stringf(16)]	Instrument type profile. Used as part of the primary key to read the Instrument Type External to Internal data source. This field is no longer required and is considered obsolete.
acct_stat_prfl [bt_stringf(16)]	Account Status profile. Used as part of the primary key to read the Account Status External to Internal data source. This field is being replaced by a new field on the Interface data source to be used by multiple Interfaces.
msg_encrypt_sppt [bt_stringf(1) DEFAULT 0]	The message encryption support option. Valid values are: 0 = message encryption is not supported, 1 = full message encryption is supported. Default value is 0.
rvsl_opt [bt_stringf(1) DEFAULT 0]	The reversal option indicates whether HISO87 should reverse the transaction when the late response is received or when the request transaction times out. Valid values are: 0 = reverse on late response, 1 = reverse on time out. Default value is 0.
hdr_data_prfx [bt_stringf(9)]	The Message header data prefix allows the entry of up to 9 characters of data to precede the message when the message is sent. Valid values are: 0-9, A-F. Default value is spaces.
hdr_ims_cics_flg [bt_flag DEFAULT 0]	The Message header IMS/CICS Code Flag indicates if the HISO87 Processing Code data source needs to be read to determine what transaction code should precede the message when the message is sent. Valid values are: 0 = false, 1 = true. Default value is 0.
nmm_mac_opt [bt_stringf(1) DEFAULT 0]	Indicates if all Network Management Messages will be MAC'd if MACing is configured or if only a subset of Network Management Messages will be MAC'd if MACing is configured. Valid values are: 0 – MAC all Network Management Messages (default) 1- Only MAC a subset of Network Management Messages: PIN Key Change Data Key Change New Key Repeat Key Verify Key Default value is 0.
rqst_alt_act [bt_stringf(1) DEFAULT 0]	Indicates the alternate action for a request transaction when a request is received and the interface is in a SAF-only mode: Valid values are: 0 – re-route (default) 1 – deny Default value is 0.
script_nam [bt_stringf(16)]	The name of an executable script. It is used by the BASE24 Migration HISO component to determine which transactions should be placed in the SAF to be sent to BASE24. An entry of all spaces is allowed and indicate that no script execution will be performed. This field is left-justified, upper case(containing any combination of alphanumeric and special characters, but without any embedded spaces).
b24_migr_flg [bt_flag DEFAULT 0]	A flag indicating if the ISO87 interface is to perform customized processing required when communication with BASE24. This flag will default to No. 0 - No Customized Processing (default) 1 - Customized Processing
host_logon_typ [bt_stringf(1) DEFAULT 0]	The Host Logon Type flag. It is used to indicate how the Host will logon/logoff to BSE24-eps. The flag will have the default value 0. Valid values are: 0 - Use the Interface Manager logon_typ value (default) 1 - BASE24 Processing

Element (type)	Description
xlate_encrypt_data [bt_int16s DEFAULT 1]	The Translate Encrypted Data flag. It is used to indicate indicates if the encrypted balance should be translated when mapped to the external message. The flag will have the default value 1. Valid values are: 0 - No, do not translate the encrypted data 1 - Yes, translate the encrypted data (default)

HISO87_Proc_Txn (1.0) (hi8ptd)

The HISO 87 Processing Code to CICS/IMS Transaction Code Table.

[Audited] [Supports versioning]

OLTP: HISO87_Proc_Txn_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
proc_cde*[proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ims_cics_cde [bt_stringf(9)]	The Message header data prefix allows the entry of up to 9 characters of data to precede the message when the message is sent. Valid values are: 0-9, A-F. Default value is spaces.
ims_cics_cde_lgth [bt_int16s]	The length of the IMS/CICS code that will precede the message when the message is sent. Valid values are: 0-9. Default value is 0.

HISO93_Interface (2.0) (hi93d)

The ISO 8583-1993 Host Interface configuration data.

[Audited] [Supports versioning]

OLTP: HISO93_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
end_pt_typ [bt_stringf(1)]	This field represents the type of the endpoint. 0 = Host, 1 = Interchange.
host_sync_flg [bt_int16s]	Flag indicating whether communicating with host is synchronous or asynchronous. Valid values are 0 - Messages are asynchronous, 1 - Messages are synchronous. Default value is 0.

Element (type)	Description
proc_cde_prfl [bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
host_ntfy_msg_flg [bt_flag DEFAULT 1]	Flag indicating whether or not to send Notification Messages to the host, it will be used for Dispute/Exception transactions. Valid values are 0= False, 1= True. Default value is 1.

Holiday (1.0) (hldyd)

The Holiday table contains a record for each holiday date specified as a holiday belonging to a holiday profile.

[Audited] [Supports versioning]

OLTP: Holiday_OLTP

Element (type)	Description
hol_dat_prfl* [prfl_def 1.0]	The holiday date profile is used to define a set of dates as holidays. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
hol_dat* [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Host_Public_Key_Security (1.0) (hspkd)

Contains one row for each public key type (e.g., CA Root, CA Primary, Host Root, Host Primary) as required for each specific AKDS implementation (e.g., NCR Signatures, Diebold Certificates).

[Audited] [Supports versioning]

Element (type)	Description
pk_host_nam* [bt_stringf(16)]	Name of Host Public Key owner. Set to Host.
pk_impl* [bt_int16s]	Public Key implementation. Valid values are: 0 - NCR, 1 - Diebold, 2 - Wincor Signature
pk_key_typ* [bt_int16s]	Type of public key. Valid values: 15 - CA Root. 22 - CA Primary. 28 - Host Root. 11 - Host Primary.
distngsh_nam_hash* [bt_stringf(40)]	Hash value of the Distinguished Name element from the certificate.
key_eff_dat* [bt_stringf(8)]	The date the key becomes effective and is available for use. The format is YYYYMMDD.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
pk_hdr [keyx_hdr 1.0]	Public Key header required for the Atalla Key Block (AKB) format.
pk_keyx [bt_binary(298)]	Public Key used for signature/verification.
pk_kam [keyx_kam 1.0]	Public Key MAC value required for the Atalla Key Block (AKB) format.
pk_vvk [bt_stringf(8)]	Public Key - Verification Value. Contains the verification value of the Public Key. The verification value is used to detect key synchronization errors.
sk_hdr [keyx_hdr 1.0]	Secret Key header required for the Atalla Key Block (AKB) format.
sk_keyx [bt_binary(1248)]	Secret Key used for signature/verification.
sk_kam [keyx_kam 1.0]	Secret Key MAC value required for the Atalla Key Block (AKB) format.
cert_serial_num [bt_binaryf(32)]	The serial number of a public key certificate.
cert_common_nam [bt_stringf(64)]	Common name used in the Host public key certificate.
cert_org_nam [bt_stringf(64)]	Organization name used in the Host public key certificate.
public_key_gen [bt_int16s]	Indicates the status of the public key generation for the Host public key pair. Valid values are: 0 - key generation not in progress (default). 1 - Key generation in progress. 2 - Key generation not allowed.
pk_beg_dat [ts 1.0]	First day the public key is valid.
pk_end_dat [ts 1.0]	Last day the public key is valid.
pk_cert [bt_binaryv(1750)]	Signature/Certificate of the Root Public Key of the Host that is generated by a Certificate Authority (CA).

Host_Public_Key_Security_Primary (1.0) (hspkpd)

Contains the primary public key and secret key information generated for the Host.

[Audited] [Supports versioning]

Element (type)	Description
pk_host_nam* [bt_stringf(16)]	Name of Host Public Key owner. Set to Host.
pk_impl* [bt_int16s]	Public Key implementation. Valid values are: 0 - NCR, 1 - Diebold, 2 - Wincor Signature
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pk_host_pri_hdr [keyx_hdr 1.0]	Host Primary Public Key header required for the Atalla Key Block (AKB) format.
pk_host_pri_keyx [bt_binary(298)]	Primary Public Key of the Host.
pk_host_pri_kam [keyx_kam 1.0]	Host Primary Public Key MAC value required for the Atalla Key Block (AKB) format.
pk_host_pri_vvk [bt_stringf(8)]	Host Primary Public Key - Verification Value. Contains the verification value of the Host Public Key. The verification value is used to detect key synchronization errors.

Element (type)	Description
sk_host_pri_hdr [keyx_hdr 1.0]	Host Primary Secret Key header required for the Atalla Key Block (AKB) format.
sk_host_pri_keyx [bt_binaryl(1248)]	Primary Secret Key of the Host.
sk_host_pri_kam [keyx_kam 1.0]	Host Primary Secret Key MAC value required for the Atalla Key Block (AKB) format.
pk_ca_root_hdr [keyx_hdr 1.0]	Root Certificate Authority's Primary Public Key header required for the Atalla Key Block (AKB) format.
pk_ca_root_keyx [bt_binaryl(298)]	Public Key of the root Certificate Authority.
pk_ca_root_kam [keyx_kam 1.0]	Root Certificate Authority Public Key MAC value required for the Atalla Key Block (AKB) format.
pk_ca_root_vvk [bt_stringf(8)]	Root Certificate Authority Public Key - Verification Value. Contains the verification value of the primary Certificate Authority Public Key. The verification value is used to detect key synchronization errors.
public_key_gen [bt_int16s]	Indicates the status of the public key generation for the Host public key pair. Valid values are: 0 - key generation not in progress (default). 1 - Key generation in progress. 2 - Key generation not allowed.
cert_serial_num [bt_int64s]	The serial number of a public key certificate.
cert_common_nam [bt_stringf(64)]	Common name used in the Host public key certificate.
cert_org_nam [bt_stringf(64)]	Organization name used in the Host public key certificate.
pk_host_pri_sig [bt_binaryv(1750)]	Signature/Certificate of the Primary Public Key of the Host that is generated by a Certificate Authority (CA).

Host_Public_Key_Security_Second (1.0) (hspksd)

Contains the secondary public key and secret key information generated for the Host.

[Audited] [Supports versioning]

Element (type)	Description
pk_host_nam* [bt_stringf(16)]	Name of Host Public Key owner. Set to Host.
pk_impl* [bt_int16s]	Public Key implementation. Valid values are: 0 - NCR, 1 - Diebold, 2 - Wincor Signature
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pk_ca_pri_hdr [keyx_hdr 1.0]	Certificate Authority's Primary Public Key header required for the Atalla Key Block (AKB) format.
pk_ca_pri_keyx [bt_binaryl(298)]	Public Key of the primary Certificate Authority.
pk_ca_pri_kam [keyx_kam 1.0]	Primary Certificate Authority Public Key MAC value required for the Atalla Key Block (AKB) format.
pk_ca_pri_vvk [bt_stringf(8)]	Primary Certificate Authority Public Key - Verification Value. Contains the verification value of the primary Certificate Authority Public Key. The verification value is used to detect key synchronization errors.

Element (type)	Description
pk_ca_scnd_hdr [keyx_hdr 1.0]	Certificate Authoritys Secondary Public Key header required for the Atalla Key Block (AKB) format.
pk_ca_scnd_keyx [bt_binaryl(298)]	Public Key of the secondary Certificate Authority.
pk_ca_scnd_kam [keyx_kam 1.0]	Secondary Certificate Authority Public Key MAC value required for the Atalla Key Block (AKB) format.
pk_ca_scnd_vvk [bt_stringf(8)]	Secondary Certificate Authority Public Key - Verification Value. Contains the verification value of the secondary Certificate Authority Public Key. The verification value is used to detect key synchronization errors.
pk_host_scnd_sig [bt_binaryv(2000)]	Signature/Certificate of the Secondary Public Key of the Host that is generated by a Certificate Authority (CA).

HPDH_Configuration (1.0) (hpdhd)

Configuration data for the Hypercom device handler.

[Audited] [Supports versioning]

OLTP: HPDH_Configuration_OLTP

Element (type)	Description
chan_prfl*[prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
jrnل_term_stat [bt_flag]	A code indicating whether the terminal statistics are journalled. Valid values are: 1 - journal the terminal statistics, 0 - do not journal the terminal statistics. Default value is 1.
NMS_chan_prfl [prfl_def 1.0]	The NMS channel profile will be used to read the NMS Terminal Station Table. This is currently used with the Hypercom Device Handler only. Default is HPDH.
NAC_chan_prfl [prfl_def 1.0]	The NAC channel profile will be used to read the NAC Terminal Station Table. This is currently used with the Hypercom Device Handler only. Default is HPDH.

HPDH_NAC_Term (1.0) (hnacd)

NAC Terminal Station contains one record per Hypercom NAC.

[Audited] [Supports versioning]

OLTP: HPDH_NAC_Term_OLTP

Element (type)	Description
NAC_chan_prfl*[prfl_def 1.0]	The NAC channel profile will be used to read the NAC Terminal Station Table. This is currently used with the Hypercom Device Handler only. Default is HPDH.

Element (type)	Description
inbnd_sta_nam*[bt_stringf(16)]	The symbolic name of the inbound station which receives messages from an interface. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
nms_id*[bt_stringf(2)]	The Hypercom NMS ID. Valid values are 0 - 16.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
outbnd_sta_nam [bt_stringf(16)]	The symbolic name of the outbound station which receives messages from an interface. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).

HPDH_NMS_Term (1.0) (hnmsd)

NMS Terminal Station contains one record per Hypercom NMS terminal.

[Audited] [Supports versioning]

OLTP: HPDH_NMS_Term_OLTP

Element (type)	Description
NMS_chan_prfl*[prfl_def 1.0]	The NMS channel profile will be used to read the NMS Terminal Station Table. This is currently used with the Hypercom Device Handler only. Default is HPDH.
inbnd_sta_nam*[bt_stringf(16)]	The symbolic name of the inbound station which receives messages from an interface. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
NAC_id*[bt_stringf(3)]	The Hypercom NAC ID. Valid values are 0 - 256.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
outbnd_sta_nam [bt_stringf(16)]	The symbolic name of the outbound station which receives messages from an interface. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).

HPRPRFL (2.0) (hprpfd)

Hopper Profile Table. The table contains the static hopper data, such as currency code and standard begin amount. The data is linked to an ATM device via the Hopper Profile.

[Audited] [Supports versioning]

Element (type)	Description
HprPrflTx*[bt_stringf(16)]	The hopper configuration profile ID associated with an ATM. The hopper prprofile ID is stored in the ES ATDS1 table and is used to link the ATM to its hopper configuration defined in the Hopper Configuration table (HPRPRFL).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
Hpr1CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hopper is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr1UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr1StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).
Hpr1CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr1CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
Hpr1DspyOrdrNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).
TBMHoprThrs1Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCD1NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value hopper. Valid values are 1 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMMxBls1Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCD1MaxBlsNum [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.

Element (type)	Description
BMCd1StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd1StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
Hpr2CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hopper is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr2UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr2StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).
Hpr2CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr2CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
Hpr2DspyOrdrNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).
TBMHoprThrs2Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd2NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value

Element (type)	Description
	hopper. Valid values are 1 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMxBIs2Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd2MaxBIsNum [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd2StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd2StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
Hpr3CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr3UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr3StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).
Hpr3CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr3CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05

Element (type)	Description
	maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
Hpr3DspyOrdNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).
TBMHoprThrs3Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd3NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value hopper. Valid values are 1 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMMxBls3Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd3MaxBlsNum [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd3StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd3StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
Hpr4CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr4UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr4StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).

Element (type)	Description
Hpr4CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr4CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E. All other device types use the space character.
Hpr4DspyOrdNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).
TBMHoprThrs4Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCD4NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value hopper. Valid values are 1 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMxBl4Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCD4MaxBl4Num [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.
BMCD4StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCD4StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
Hpr5CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are

Element (type)	Description
	converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr5UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr5StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).
Hpr5CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr5CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
Hpr5DspyOrdrNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).
TBMHoprThrs5Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCD5NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value hopper. Valid values are 1 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMMxBIs5Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCD5MaxBIsNum [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.
BMCD5StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCD5StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense

Element (type)	Description
	Amount field for the specified hopper. Valid values are 0 through 999999999. This field is only used if the Configurable Dispense Algorithm is selected.
Hpr6CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hopper is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr6UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr6StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).
Hpr6CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr6CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E. All other device types use the space character.
Hpr6DspyOrdrNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).
TBMHoprThrs6Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd6NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value hopper. Valid values are 1 through 999999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMxBl6Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).

Element (type)	Description
BMCd6MaxBlsNum [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd6StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd6StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
Hpr7CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hopper is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr7UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr7StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).
Hpr7CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr7CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E. All other device types use the space character.
Hpr7DspyOrdNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).

Element (type)	Description
TBMHoprThrs7Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd7NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value hopper. Valid values are 1 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMMxBIs7Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd7MaxBIsNum [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd7StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd7StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
Hpr8CntnTx [bt_stringf(2)]	A code defining the content type of the specified hopper. The value is stored on the ES Hopper Profile table (HPRPRFL) table. The content is also recorded on the ATM Cutover SAF (CTVRSF) table for logging with terminal balancing transactions. The order of contents in the hoppers is - first coin, next cash, and last Non-currency (NCD). Each type is optional and is omitted if not used. Within each type (coin, cash, NCD), the first hopper always contains information on the lowest denomination; the next hopper always contains information on the next higher denomination, and so on. Non-currency dispense (NCD) items are not required to have a cash value (reference UNIT VALUE). NOTE: For various system displays and when logging terminal totals to the journal, the hopper counts are converted to monetary amount figures by multiplying the counts by the corresponding hopper unit values.
Hpr8UntValNum [bt_int32s]	The denomination of cash, the cash value of the non-currency items in the hopper or the denomination of the travelers cheques. This may contain a value of zero if the hopper contains non-value items. This element is stored on the Hopper Configuration Profile table (HPRPRFL).
Hpr8StndBgnCntNum [bt_int32s]	The standard number of bills, cash value items, non-value items or travelers cheques used to replenish the specified hopper. The use of a standard replenishment amount is valid only for cartridge dispensers where the hopper is replenished by replacing the cartridge. This element is stored in the Hopper Configuration Profile table (HPRPRFL).
Hpr8CrncCd [crncy_cde 1.0]	The currency represented in UNIT VALUE for the specified hopper. Refer to the Codes for the Representation of Currencies and Funds ISO, 4217-1981 to determine the proper code. Example: 840 (The U.S. currency code).
Hpr8CstMpTx [bt_stringf(1)]	The hopper to cassette logical mapping for the specified hopper. Mapping is required for 912 emulations (all Diebold 10xx). The 912 messaging uses references to logical cassettes instead of physical cassettes. Valid values are: Space and characters A - H. The default

Element (type)	Description
	value is based on device type and cash value (as established by vendors recommendation): Diebold 10xx: bill value 1 maps to A bill value 5 maps to B bill value 10 maps to C bill value 20 maps to D bill value 50 maps to E bill value 100 maps to F bill value 500 maps to G bill value 1000 maps to H coin value .01 maps to A coin value .05 maps to B coin value .10 maps to C coin value .25 maps to D coin value .50 maps to E All other device types use the space character.
Hpr8DspyOrdNum [bt_int32s]	The order in which the contents of the specified hopper are displayed during multiple currency transactions. This value is stored on the Hopper Configuration Profile table (HPRPRFL).
TBMHoprThrs8Num [bt_int32s]	A value specifying the threshold value for each hopper. The threshold values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd8NValNum [bt_int32s]	Indicates the non-value dispense threshold for the specified hopper. If the transaction amount is equal to or greater than the threshold, one item is dispensed from the non-value hopper. Valid values are 1 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
TBMMxBIs8Num [bt_int32s]	The maximum number of bills that may be dispensed from the specified hopper in any single dispense operation. The maximum values are used to determine the bills to dispensed using the threshold dispense algorithm. The value is configured on the ES ATD Configuration Profile table (ATDCNFG).
BMCd8MaxBIsNum [bt_int32s]	Specifies the maximum number of bills from the designated hopper that may be dispensed in a transaction. Valid values are 1 through 50. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd8StrtAmntNum [bt_int32s]	Indicates the start dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is equal to or greater than the start dispense amount, bills from the hopper are used. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
BMCd8StpAmntNum [bt_int32s]	Indicates the stop dispense amount for the specified hopper. If the transaction amount, or the amount remaining to be dispensed, is less than the stop dispense amount, bills from the hopper are not used. The value of this field must be less than the Start Dispense Amount field for the specified hopper. Valid values are 0 through 99999999. This field is only used if the Configurable Dispense Algorithm is selected.
DspnMxBIsNum [bt_int32s]	This data elements defines the maximum number of bills/coupons that can be dispensed by an ATM device. This describes the physical limitations of the ATMs bill dispenser.
DspnMxCnsNum [bt_int32s]	This data elements defines the maximum number of coins that can be dispensed by an ATM device. This describes the physical limitations of the ATMs coin dispenser.
DspnAlgrCd [bt_stringf(1)]	A code describing the dispense algorithm used for an ATM terminal. The data is stored on the ES ATM Configuration Properties table (ATDCNFG). The value may be any value mapped to a dispense algorithm implementation class in the DispenseAlgorithms.xml configuration document. ACI Worldwide supplies the class mapping to the following dispense algorithm codes: 0 - Least Number of Bills

HSMCNFG (1.0) (hsmcnf)

This table is required for host security module support.

[Audited] [Supports versioning]

Element (type)	Description
HSMID*[bt_stringf(50)]	
PrcsID*[bt_stringf(16)]	
DscrTx [bt_stringf(255)]	
VndrNum [bt_int16s]	
ModelNum [bt_int16s]	
AddrTx [bt_stringf(50)]	
PortNum [bt_int16s]	
MsgHdrLen [bt_int16s]	
LogConnNum [bt_int16s]	
PinValPad [bt_stringf(1)]	
MaxPinLen [bt_int16s]	
LastUpdtTm [ts 1.0]	

IBM_Context (1.0) (ictxd)

This table is used in a IBM environment only when a data coupling facility is used to store context instead of a VSAM file. This Context table stores context for a client component. If client context exceeds the limits of a single record, the context is stored in multiple records. A context record has an expiration timestamp after which a clean up program will delete the record if the client has not already done so. The assigns for the context tables are defined in the Context Configuration table to allow a number of Context tables to be shared or kept separate by different clients.

[Not Audited] [Supports versioning]

Element (type)	Description
hash_key*[bt_stringf(16)]	The hash value of the context key supplied by the client when storing and retrieving context data.
cmpnt_id [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ctx_key [bt_stringf(80)]	The context key supplied by the client when storing and retrieving context data.
ctx_rec_num [bt_int16s]	The number of the context record within a set of records.
ctx_exp_ts [bt_int64s]	The timestamp when the context record should expire and the record can later be deleted.
ctx_clt_data_lgth [bt_int16s]	The length of the client data in the context record.
ctx_timr_data_lgth [bt_int16s]	The length of the timer data in the context record needed to cancel a timer.
ctx_data [bt_binaryv(3940)]	The context data area. Can contain client data and/or timer data.

IBM_DES (1.0) (idesd)

IBM DES contains information specific to the DES (IBM 3624) PIN verification method.

[Audited] [Supports versioning]

OLTP: IBM_DES_OLTP

Element (type)	Description
pin_vrfy_prfl* [prfl_def 1.0]	An identifier for the profile to which this record applies. This field must contain a value that matches a PIN Verify Profile defined in the Prefix.
beg_dat* [yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat* [yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dec_tbl [bt_stringf(16)]	The decimalization table used for generating the institutions PINs or PIN offsets. The value in this field is used in the verification of customer-entered PINs. Valid values are 0-9.
pan_pad [bt_stringf(1)]	The character used to pad the validation data used in IBM DES PIN verification. Validation data is formed by left-justifying the PAN digits calculated from the values defined in the PAN_VFY_OFST and PAN_VFY_LGTH fields, and padding the data to 16 characters.
pan_vrfy_ofst [bt_int16s]	The first position of the PAN to be used in the formation of the validation data. The first digit in the PAN is at position zero. The value in this field is used along with the value in PAN_VFY_LGTH field to identify the portion of the PAN to be used to create the validation data.
pan_vrfy_lgth [bt_int16s]	The number of positions of the PAN to be used in the formation of the validation data. The value in this field is used along with the value in the PAN_VFY_OFST field to identify the portion of the PAN to be used to create the validation data. Values are 04 to 16.
key_encrypt [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_chk_values [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.

Identikey (1.0) (idntd)

The Identikey data source contains configuration parameters required for the Identikey PIN verification method.

[Audited] [Supports versioning]

OLTP: Identikey_OLTP

Element (type)	Description
pin_vrfy_prfl*[prfl_def 1.0]	An identifier for the profile to which this record applies. This field must contain a value that matches a PIN Verify Profile defined in the Prefix.
beg_dat*[yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat*[yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
bnk_id [bt_stringf(8)]	A value, required by the Identikey algorithm, which may be a two-digit Backward Index, a six-digit Bank ID, or an eight-digit Route and Transit Number.
partial_pan_ofst [bt_int16s]	The position in the PAN to be used as the first digit of the partial PAN. The first digit in the PAN has a positional value of 0. The value in this field is used along with the value in PARTIAL_PAN_LGTH field to identify the portion of the PAN to be used in PIN verification.
partial_pan_lgth [bt_int16s]	The number of digits to take from the PAN to create a partial PAN for input to the Identikey algorithm. Values are 04 to 19. The value in this field is used along with the value in the PARTIAL_PAN_OFST field to identify the portion of the PAN to be used in PIN verification.
cmp_ind [bt_char]	A code specifying which digits of the Identikey number (derived during PIN verification) are compared to a four-digit Identikey PIN Verification Number (PVN). This value is used only if PVNs are four digits in length. For six-digit or eight-digit PVNs, this value has no effect in the algorithm. Valid values are: blank = not used (default). L = Compare left-most four digits of the Identikey number. M = Compare middle four digits of the Identikey number. R = Compare right-most digits of the Identikey number.

IDF (1.0) (idf)

The Institution Definition File (IDF) contains one record for each institution participating in the logical network and defines processing for each institution. The IDF contains routing tables for transaction routing within a BASE24 product and each institution's parameters for cards, dates, processing control, and sharing. The key to records in the IDF is the FIID for the financial institution. This definition of the IDF has been created solely for the Java ATM Device Handler processes. It defines only the BASE and ATM segments.

[Not Audited] [Does not support versioning]

Element (type)	Description
BaseSegLgthShort [bt_int16s]	BASE24 Classic element - The total length of the Base segment of an IDF record.
BaseSegMapInt [bt_int32s]	BASE24 Classic element - This field indicates which other segments are present in this IDF record.
BaseSegFIIDTx* [bt_stringf(4)]	BASE24 Classic element - The FIID identifying the financial institution. The FIID must be unique within an entire BASE24 system.
BaseSegRefrGrpTx [bt_stringf(4)]	BASE24 Classic element - A four-character identifier grouping institutions together for file extracts and refreshes. File extracts and refreshes can be run using this identifier to process certain institutions together.
BaseSegAltkeyTx [bt_stringf(11)]	BASE24 Classic element - The institutions transit/routing number or issuer identification number. Each FIID has a number that is unique to the institution. The number is right-justified, zero- filled to the left.
BaseSegFiNameTx [bt_stringf(22)]	BASE24 Classic element - An ANSI Standard code indicating the state in which this institution is located. This code is used for validating sharing transactions.
BaseSegFiStTx [bt_stringf(2)]	BASE24 Classic element - An ANSI Standard code indicating the state in which this institution is located. This code is used for validating sharing transactions.
BaseSegFiCntyTx [bt_stringf(3)]	BASE24 Classic element - An ANSI Standard code indicating the county in which this institution is located. This code is used for validating sharing transactions.
BaseSegFiCntryTx [bt_stringf(3)]	BASE24 Classic element - The country code associated with the country in which this institution is located.
BaseSegFiPhoneTx [bt_stringf(20)]	BASE24 Classic element - The telephone number of this institution.
BaseSegCrncyCdeTx [bt_stringf(3)]	BASE24 Classic element - The currency used by the institution to compute its cardholder account balances. Valid values are listed in the following booklet: Codes for the Representation of Currencies and Funds, ISO 4217-1981. The value in this field should be set at installation.
BaseSegNEGNameTx [bt_stringf(35)]	BASE24 Classic element - The name of the Negative Card File (NEG) for institutions that use either the Negative Authorization without Usage Accumulation method or Negative Authorization with Usage Accumulation method.
BaseSegUAFNameTx [bt_stringf(35)]	BASE24 Classic element - The name of the Usage Accumulation File (UAF) for institutions that use the Negative Authorization with Usage Accumulation method.
BaseSegCAFNameTx [bt_stringf(35)]	BASE24 Classic element - The name of the Cardholder Authorization File (CAF) for institutions that use either the Positive Authorization, Positive Balance Authorization, or Parametric Authorization methods.
BaseSegPBF1NameTx [bt_stringf(35)]	BASE24 Classic element - The name of the Checking Account PBF for institutions that use the Positive Balance Authorization method. If this institution uses only one PBF for all accounts (i.e., checking, savings, and credit), the PBF1-NAME, PBF2-NAME, and PBF3-NAME fields must contain identical information.
BaseSegPBF2NameTx [bt_stringf(35)]	BASE24 Classic element - The name of the Savings Account PBF for institutions that use the Positive Balance Authorization method. If this institution uses only one PBF for all accounts (i.e., checking, savings, and credit), the PBF1-NAME, PBF2-NAME, and PBF3-NAME fields must contain identical information.

Element (type)	Description
BaseSegPBF3NameTx [bt_stringf(35)]	BASE24 Classic element - The name of the Credit Account PBF for institutions that use the Positive Balance Authorization method. If this institution uses only one PBF for authorization on all accounts (i.e., checking, savings, and credit), the PBF1-NAME, PBF2-NAME, and PBF3-NAME fields must contain identical information.
BaseSegPBF4NameTx [bt_stringf(35)]	BASE24 Classic element - This field was used for the name of the Corporate Positive Balance File (CPBF) by institutions that use the Positive Balance Authorization method and have BASE24-cash manager configured in their system. Support for BASE24-cash manager product has been discontinued. This field was not removed or renamed because it was used by all other products in that system--not just BASE24-cash manager.
BaseSegShrgGrpTx [bt_stringf(24)]	BASE24 Classic element - A list of sharing groups to which this institution belongs. The BASE24-atm Authorization process searches for this group value whenever the terminal owner and card issuer are not the same to determine if the terminal and issuer belong to any of the same sharing groups.
BaseSegCrdStatChkTx [bt_stringf(1)]	BASE24 Classic element - A code indicating whether the CRD-STAT field in the Base segment of the CAF is to be checked during prescreening processing by BASE24. Note that BASE24-pos will check the NEG based on this flag if the NEG is being used in processing rather than the CAF. Valid values: 0 = Send the request to a host without checking the card status. Other = Check the card status: If not valid, decline the request and do not send to a host. The value in this field is used only with authorization level 3 (online/offline) and with Positive Authorization and Positive Balance Authorization methods.
BaseSegExpDatChkTx [bt_stringf(1)]	BASE24 Classic element - A code indicating whether the expiration date should be checked during prescreening processing by BASE24. Valid values are: 0 = Send requests to a host without checking the expiration date. Other = Check the expiration date: If expired, decline the request and do not send the request to a host. When the value in this field is non-zero, the value in the EXP-CHK-IND field in the Base segment of the CPF is used to determine how the expiration date is to be checked. The value in this field is used only with authorization level 3 (online/offline).
BaseSegPinChkTx [bt_stringf(1)]	BASE24 Classic element - A code indicating whether the cardholders entered PIN is to be checked during prescreening processing by BASE24. Valid values are: 0 = Send requests to a host without checking the Customers PIN. Other = Check the customers PIN: If not valid, decline the request and do not send to a host. The value in this field is only used with authorization level 1 (online) and authorization level 3 (online/offline) since prescreening checks are performed only with these authorization levels.
BaseSegPinVrfyTypTx [bt_stringf(2)]	BASE24 Classic element - The PIN verification method used for this institution. This field must contain a valid value, even when the value in the AUTH-TYP field in this IDF segment is set to 0 (host authorization). Valid values are: 00 = No verification. 01 = DES (IBM 3624) 02 = Diebold 03 = Identikey 04 = VISA PVV
BaseSegPinOfstTx [bt_stringf(1)]	BASE24 Classic element - A code specifying the location of the DES (IBM 3624) or Diebold PIN verification method PIN offset, the VISA PVV PIN verification method PIN Verification Value (PVV), or the Identikey PIN verification method PIN Verification Number (PVN). Valid values are: 0 = No offset, 0000 is used if an offset is required for the verification method. Not valid for VISA PVV. 1 = Offset is on the card, the value in the POFST-OFST field in the Base segment of the CPF specifies the exact location on Track 2 of the card. 2 = Offset is specified in the cardholders individual CAF record.
BaseSegAlgoNumTx [bt_stringf(1)]	BASE24 Classic element - A code specifying the location of the algorithm number. Currently the algorithm number is required only for Diebold PIN verification. If another PIN method is used, this field should contain a value of zero. Values are: 0 = The

Element (type)	Description
	algorithm number is not required for PIN verification. 1 = The algorithm number is in the KEYF. 2 = The algorithm number is on Track 2 of the card, the value in the ALGO-OFST field in the Base segment of the CPF specifies the exact location.
BaseSegCrdHldSelctTx [bt_stringf(1)]	BASE24 Classic element - A code, used by BASE24-atm only, identifying whether the institution allows its cardholders to select their PINs. Valid values are: Y = Cardholders select their PINs. N = Cardholders do not select their PINs.
BaseSegPinTriesTx [bt_stringf(1)]	BASE24 Classic element - A code indicating how accumulated bad PIN tries in the CAF, UAF, CUST, or Administrative Card File (ADMN) are to be reset for an institutions cardholders. The ADMN is used by BASE24-pos to keep track of bad PIN tries for administrative cards. The CUST file is used by BASE24-telebanking to keep track of bad PIN tries for Telebanking customers.
BaseSegMaxPinTryShort [bt_int16s]	BASE24 Classic element - The action taken by BASE24 if a cardholder exceeds the maximum number of incorrect PIN entries specified in the MAX-PIN-TRY field. The value in this field is checked when a cardholder enters an incorrect PIN, causing the accumulated number of bad PIN tries in the CAF or UAF to equal the number of incorrect PINs allowed in the MAX-PIN-TRY field of this IDF segment. Values are: 0 = Return the card 1 = Retain the card
BaseSegBadPinDispTx [bt_stringf(1)]	BASE24 Classic element - The action taken by BASE24 if a cardholder exceeds the maximum number of incorrect PIN entries specified in the MAX-PIN-TRY field. The value in this field is checked when a cardholder enters an incorrect PIN, causing the accumulated number of bad PIN tries in the CAF or UAF to equal the number of incorrect PINs allowed in the MAX-PIN-TRY field of this IDF segment. Values are: 0 = Return the card 1 = Retain the card
BaseSegExpChkDispTx [bt_stringf(1)]	BASE24 Classic element - The action taken if the Authorization process detects that a card has expired. Values are: 0 = Return the card 1 = Retain the card
BaseSegLmtChkTx [bt_stringf(1)]	BASE24 Classic element - A code indicating whether the cardholder withdrawal limit fields in the CAF or CPF are to be checked during prescreening processing by BASE24. Valid values are: 0 = Send requests to the host without checking any limits. Other = Check the limits; if exceeded, decline the request and do not send the request to a host. The value in this field is used only with authorization level 1 (online) and authorization level 3 (online/offline) since prescreening is only done with these authorization levels.
BaseSegFldCutoverTx [bt_stringf(1)]	BASE24 Classic element - The parameters that determine when the UAF is to be purged and the usage accumulation fields in the CAF are to begin being reset. The value in this field is used by the Authorization and Settlement Initiator processes to coordinate and clear cardholder usage accumulation. Valid values are: 0 = Purge UAF. 1 = Purge UAF at institution cutover; begin clearing CAF/CUST usage accumulation fields at logical network cutover 2 = Purge UAF at midnight; begin clearing CAF/CUST usage accumulation fields at midnight. 4 = Do not purge UAF; begin clearing the CAF/CUST at logical network cutover. 5 = Do not purge UAF; begin clearing the CAF/CUST at midnight.
BaseSegHostAdjTx [bt_stringf(2)]	BASE24 Classic element - A code indicating how a card-issuer supports processing of adjustment (5400) transactions. The first position of the field indicates how adjustments are processed by the Authorization process. Valid first characters are: 0 = Process adjustments manually. 1 = Process at the processor only (adjust cardholder files if necessary, log, and report as required). If BASE24-atm receives a 5400 message, it will process it against its own files only. No message is sent to the host regardless of authorization level. 2 = Process ES system and also at the host. If BASE24-atm

Element (type)	Description
	receives a 5400 message, it will process it as it can on the ES system and send a 5400 message to the host.
BaseSegPrdLgthShort [bt_int16s]	BASE24 Classic element - A code defining the institutions usage accumulation period length. The length of a usage accumulation period defines how long customer usage data on the CAF and UAF is allowed to accumulate before it is cleared. The value in this field is only referenced if the value in the WRK-DAY field in this IDF segment is set to 0, indicating that the usage accumulation period length should be determined by this field. If the value in the WRK-DAY field is set to 1, 2, or 3, the value in this field must be set to 0. If weekends and holidays affect when the usage accumulation fields are cleared, the value in the WRK- DAY field below must be used.
BaseSegWrkDayTx [bt_stringf(1)]	BASE24 Classic element - A code defining the institutions usage accumulation period length. The length of a usage accumulation period defines how long customer usage data on the CAF and UAF are allowed to accumulate before they are cleared. If codes 1, 2, or 3 are used in this field, the value in the PRD-LGTH field in this IDF segment must be set to 0. If the value in the PRD-LGTH field is to be used to determine the usage accumulation period length, the value in this field must be set to 0. Valid values are: 0 = The value in the PRD-LGTH field above is used to determine the usage accumulation. 1 = Clear usage accumulation fields daily, except on weekends and specified holidays. 2 = Clear usage accumulation fields daily, except on Sundays and specified holidays. 3 = Clear usage accumulation fields daily, except on Saturdays and specified holidays.
BaseSegUserFld1Tx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
BaseSegHol1Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegHol2Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegHol3Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegHol4Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegHol5Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegHol6Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.

[illegible]

Element (type)	Description
	the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegHol19Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegHol20Tx [bt_stringf(6)]	BASE24 Classic element - The values in each of these fields define the dates that are considered holidays by the institution. A maximum of twenty dates (YYMMDD) define the legitimate holidays for this institution. If the WRK-DAY field contains a value of 1, 2, or 3, these fields specify the holidays on which usage accumulation is not cleared.
BaseSegBegDatTx [bt_stringf(6)]	BASE24 Classic element - The starting date (YYMMDD) of the current usage accumulation period for all cardholders belonging to this institution. The date in this field is placed in the LAST-RESET-DAT field in the Base segment of the CAF and in the LAST- USED fields of the BASE24-atm and BASE24-pos segments of the CAF records in which the usage accumulation fields have been cleared. When the value in the CUS-BUS-DAT field in the BASE24- atm or BASE24-pos segments is greater than or equal to the value in the NXT-BEG-DAT field of this IDF segment, the value in the NXT-BEG-DAT field is placed in this field.
BaseSegNxtBegDatTx [bt_stringf(6)]	BASE24 Classic element - The starting date (YYMMDD) of the next usage accumulation period for all cardholders belonging to this institution. When the value in the CUS-BUS-DAT field in the BASE24- atm or BASE24-pos segments is greater than or equal to the value in this field, this value is placed in the BEG-DAT field of this IDF segment. A new value is then computed and placed in this field.
BaseSegTrnTs [bt_binaryf(6)]	BASE24 Classic element - The date and time the last transaction accessed the record.
BaseSegTrnNonstpShort [bt_int16s]	BASE24 Classic element - This field is zero filled.
BaseSegProNumShort [bt_int16s]	BASE24 Classic element - The number of the last process to access this record, as assigned in the Network Environment File (NEF).
BaseSegFmTs [bt_binaryf(6)]	BASE24 Classic element - The date and time of the last file maintenance application.
BaseSegFmUserGrpShort [bt_int16s]	BASE24 Classic element - The group number of the operator that performed the last file maintenance application. This value is taken from the information given when the operator last logged on to BASE24.
BaseSegFmUserNumInt [bt_int32s]	BASE24 Classic element - The user number of the operator that performed the last file maintenance application. This value is taken from the information given when the operator last logged on to BASE24.
BaseSegUpdtTypCd [bt_stringf(1)]	BASE24 Classic element - The type of file maintenance that was last applied to the record. Valid values are: A = Add B = Change before image C = Change after image D = Delete S = Logon security check O = Entry into operator functions
BaseSegStaNumTx [bt_stringf(4)]	BASE24 Classic element - This field is not used.
BaseSegFmFill1Tx [bt_stringf(1)]	BASE24 Classic element - This field is not used.

Element (type)	Description
BaseSegOtherAcctTypCd [bt_stringf(1)]	BASE24 Classic element - This field indicates whether Other accounts will be processed as credit accounts or debit accounts. Valid values are: C - Credit and D - Debit. D is the default.
BaseSegRefrIndCAF1Cd [bt_stringf(1)]	BASE24 Classic element - The following fields are used to control the transaction impacting preformed by the Refresh process after a PBF or CAF has been refreshed. The Authorization process places this indicator in the product specific transaction log file for each transaction processed for this institution. Three settings are used for the PBF because an institution may have three separate PBFs and, therefore, three Refresh processes; one for DDA accounts, one for Savings accounts and for credit accounts. The four PBF indicator is not used. For systems where only one PBF is maintained, only PBF1 is used.
BaseSegRefrIndPBF1Cd [bt_stringf(1)]	BASE24 Classic element - The following fields are used to control the transaction impacting preformed by the Refresh process after a PBF or CAF has been refreshed. The Authorization process places this indicator in the product specific transaction log file for each transaction processed for this institution. Three settings are used for the PBF because an institution may have three separate PBFs and, therefore, three Refresh processes; one for DDA accounts, one for Savings accounts and for credit accounts. The four PBF indicator is not used. For systems where only one PBF is maintained, only PBF1 is used.
BaseSegRefrIndPBF2Cd [bt_stringf(1)]	BASE24 Classic element - The following fields are used to control the transaction impacting preformed by the Refresh process after a PBF or CAF has been refreshed. The Authorization process places this indicator in the product specific transaction log file for each transaction processed for this institution. Three settings are used for the PBF because an institution may have three separate PBFs and, therefore, three Refresh processes; one for DDA accounts, one for Savings accounts and for credit accounts. The four PBF indicator is not used. For systems where only one PBF is maintained, only PBF1 is used.
BaseSegRefrIndPBF3Cd [bt_stringf(1)]	BASE24 Classic element - The following fields are used to control the transaction impacting preformed by the Refresh process after a PBF or CAF has been refreshed. The Authorization process places this indicator in the product specific transaction log file for each transaction processed for this institution. Three settings are used for the PBF because an institution may have three separate PBFs and, therefore, three Refresh processes; one for DDA accounts, one for Savings accounts and for credit accounts. The four PBF indicator is not used. For systems where only one PBF is maintained, only PBF1 is used.
BaseSegRefrIndPBF4Cd [bt_stringf(1)]	BASE24 Classic element - The following fields are used to control the transaction impacting preformed by the Refresh process after a PBF or CAF has been refreshed. The Authorization process places this indicator in the product specific transaction log file for each transaction processed for this institution. Three settings are used for the PBF because an institution may have three separate PBFs and, therefore, three Refresh processes; one for DDA accounts, one for Savings accounts and for credit accounts. The four PBF indicator is not used. For systems where only one PBF is maintained, only PBF1 is used.
BaseSegAltPBF4NameTx [bt_stringf(35)]	BASE24 Classic element - This field was used for the alternate name of the Corporate Positive Balance File (CPBF) by institutions that use the Positive Balance Authorization method and have BASE24-cash manager configured in their system. Support for BASE24-cash manager product has been discontinued. This field was not removed or renamed because it was used by all other products in that system--not just BASE24-cash manager.

Element (type)	Description
BaseSegUserFld3cTx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
BaseSegFIIDSegMapInt [bt_int32s]	BASE24 Classic element - A map indicating the segments supported by this institution for the authorization files (i.e., Cardholder Authorization File (CAF), Negative Card File (NEG), Positive Balance File (PBF), and Usage Accumulation File (UAF)). The map is made up of 32 bits, followed by a second field of 224 bits.
BaseSegFIIDMapExt [bt_binaryf(28)]	BASE24 Classic element - FIID-SEG-MAP extension. This field must always directly follow the FIID-SEG-MAP.
BaseSegSPFNameTx [bt_stringf(35)]	BASE24 Classic element - The name of the Stop Payment File (SPF) for this institution.
BaseSegPersistentUAFCD [bt_stringf(1)]	BASE24 Classic element - This field contains a value that indicates whether this institution utilizes a UAF, and if so, whether the UAF is to be maintained as persistent. Valid values are: 0 - No, UAF is not utilized or Persistent UAF functionality not required (default) 1 - Yes, Persistent UAF with Settlement support. The UAF Cleanup will be initiated automatically by the SETL process at LN or Midnight Cutover, or can be initiated manually by an operator, or automatically via an ECF timer 2 - Yes, Persistent UAF without Settlement support. The UAF Cleanup can be initiated manually by an operator, or automatically via an ECF timer.
BaseSegUserFld3Tx [bt_stringf(78)]	BASE24 Classic element - This field is not used.
BaseSegUserFldACITx [bt_stringf(50)]	BASE24 Classic element - USER-FLD-ACI is reserved for future BASE24 product use only. The designation of product use only provides ACI with the ability to deplete the number of bytes available within USER-FLD-ACI as product enhancements are introduced. When product enhancements require the addition of new fields within this file, the procedure to be followed is to deplete from USER-FLD-ACI bytes and use that number of bytes to define new fields. The new field definition(s) should precede the USER-FLD-ACI field.
BaseSegUserFldRegnTx [bt_stringf(50)]	BASE24 Classic element - USER-FLD-REGN is reserved for regional use only. Only regions are allowed to use USER-FLD-REGN space.
BaseSegUserFldCustTx [bt_stringf(50)]	BASE24 Classic element - USER-FLD-CUST is reserved for customer use only. Only customers are allowed to use USER-FLD-CUST space.
AtmSegSegLgthShort [bt_int16s]	BASE24 Classic element - The total length of the ATM segment of an IDF record. space.
AtmSegSegDataIdShort [bt_int16s]	BASE24 Classic element - The identifier for the ATM segment.
AtmSegSegDataB24Int [bt_int32s]	BASE24 Classic element - This field is not used.
AtmSegPinChngOptCd [bt_stringf(1)]	BASE24 Classic element - A code indicating whether PIN Change transactions are sent to the host. Valid values are: 0 = Do not send to the host, approve and log to the Transaction Log File (TLF). 1 = Send to the host, approve if host is down. 2 = Send to the host, deny if host is down. The value in this field is only used with authorization level 1 (online) and authorization level 3 (online/offline).
AtmSegCustBalInfoCd [bt_stringf(1)]	BASE24 Classic element - A code indicating how customer balance information is to be handled at the terminal. Based on the transaction, this information includes either balance or payment information. Values are: 0 = Give no amount information. 1 = Give the AMT-2 only. 2 = Give the AMT-3 only. 3 = Give both AMT-2 and AMT-3, AMT-2 is

Element (type)	Description
	given preference. 4 = Give both AMT-2 and AMT-3, AMT-3 is given preference. The amounts reflect the amounts in the AMT-1, AMT-2, and AMT-3 fields in the Standard Internal Message (STM).
AtmSegCustBalDspyCd [bt_stringf(1)]	BASE24 Classic element - A code indicating the method in which the card issuer wants balances to be presented to customers. The value in this field is used with the value in the CUST-BAL-DSPY field in the Terminal Data File (TDF). Values are: 0 = Do not print or display. 1 = Display on the screen only. 2 = Print on the receipt only. 3 = Print and display.
AtmSegHostB24BalCd [bt_stringf(1)]	BASE24 Classic element - A code identifying which ATM balance information is printed or displayed. This field is only functional with the Positive Balance Authorization method. With other authorization methods, balance information from the online host is used. Values are: 0 = Use BASE24 balance information. 1 = Use online host balance information.
AtmSegFastCashAcctCd [bt_stringf(2)]	BASE24 Classic element - The account type to be used for fast cash transactions. Also used for Smart Card when funds account unspecified. Valid values are: 00 = Use CAF first primary account. 01 = Use checking account type. 11 = Use savings account type. 31 = Use credit account type.
AtmSegBalCutStrtShort [bt_int16s]	BASE24 Classic element - The ATM balancing window start time (HHMM). The value in this field must be less than or equal to the balance window end time defined in the ATM-BAL-AND- CUTOVER-END field. For institutions that allow their terminals to be balanced only once during a BASE24 processing day (the value in the TERM-BAL-FLG field is set to 0), the value in this field designates the time period during which ATMs are normally balanced with an administrative card or via the Device Control Terminal (DCT). ATMs not balanced by the end of the window are automatically cut over to a new posting date. Refer to the BASE24-atm Settlement and Reporting Manual for a detailed discussion of balancing and cutover.
AtmSegBalCutEndShort [bt_int16s]	BASE24 Classic element - The ATM balancing window stop time (HHMM). The value in this field must be at least 30 minutes prior to the logical network cutover time specified in the ATM-LN-CUTOVER param in the LCONF. For institutions that allow their terminals to be balanced more than once during a BASE24 processing day (the value in the TERM-BAL-FLG field is set to 1), the value in this field designates the time at which the Settlement Initiator process cuts the terminal over to a new posting date. Refer to the BASE24-atm Settlement and Reporting Manual for a detailed discussion of balancing and cutover.
AtmSegTermBalFlgCd [bt_stringf(1)]	BASE24 Classic element - A code identifying the terminal balancing procedures for this institution. Valid values are: 0 = Use terminal balancing window. 1 = Balance terminals anytime but do not update postin date. For value 0, terminals can only be balanced once a day; They must be balanced within the institutions balancing window. A balancing transaction cuts over the value in the POST-DAT field in the TDF. For value 1, terminals can be balanced any time and as many times as desired by the terminal owner without regard for the balancing window. In this case, terminal balancing does not cut over the value in the POST-DAT field in the TDF. The value in the POST-DAT field is instead cut over automatically by the system at the end time specified in the institutions balancing window (the value in the ATM-BAL-AND-CUTOVER- END field).
AtmSegRptBusDatTx [bt_stringf(6)]	BASE24 Classic element - The previous BASE24-atm processing date (YYMMDD). This is one calendar date less than the value in the CUR-BUS-DAT field and is referred to as the reporting business date because the current reports reflect this dates activity.

Element (type)	Description
	The value in this field may be altered for record maintenance purposes (i.e., in the event that the Settlement Initiator process fails).
AtmSegCurBusDatTx [bt_stringf(6)]	BASE24 Classic element - The current BASE24-atm processing date (YYMMDD). The value of this field is incremented by one calendar day at institution cutover (the time specified in the ATM-BAL-AND-CUTOVER-END field). The date is incremented every day, including holidays and weekends. The date can be altered for record maintenance purposes, (i.e., in the event the Settlement Initiator process fails).
AtmSegNxtBusDatTx [bt_stringf(6)]	BASE24 Classic element - The next BASE24-atm processing date (YYMMDD). This is one calendar day greater than the value in the CUR-BUS- DAT field. This date can be altered for record maintenance purposes, (i.e., in the event the Settlement Initiator process fails).
AtmSegCusBusDatTx [bt_stringf(6)]	BASE24 Classic element - The ending date (YYMMDD) of the current usage accumulation period. For institutions that consider holidays, Saturdays, and/or Sundays when determining their usage accumulation periods (the value in the WRK-DAY field in the Base segment of the IDF set to 1, 2, or 3), the value in this field is the end date of the current usage accumulation period. For institutions that determine their usage accumulation periods by the value in the PRD-LGTH field in the Base segment of the IDF, the value in this field is the current BASE24 processing date.
AtmSegHostLogCd [bt_stringf(1)]	BASE24 Classic element - A code indicating whether log-only transactions are sent to the host. Valid values are: 0 = Do not send to the host, approve and log to the Transaction Log File (TLF). 1 = Send to the host, approve if host is down. 2 = Send to the host, deny if host is down. The value in this field is only used with authorization level 1 (online) and authorization level 3 (online/offline).
AtmSegTknRetrvOptCd [bt_stringf(1)]	BASE24 Classic element - The token data retrieval option. When the device handler is processing a reversal, this field indicates where the token data should be retrieved. Valid values are: 0 = no tokens included in the reversal message. 1 = ATD. Token data retrieved from the terminal data file, and appended to the reversal message. 2 = TLF. Token data retrieved from the transaction log file, and appended to the reversal message. The default value is 2.
AtmSegUserFld3dTx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
AtmSegDepSetlImpCd [bt_stringf(1)]	BASE24 Classic element - A code that determines whether deposits at an ATM have settlement impact. An institution can choose to collect paper items without clearing them, and thus these items would not be included in settlement totals. The value in this field is used in the creation of an institutions settlement reports; it does not affect whether a transaction is logged to the TLF. Values are: 0 = Deposits do not have settlement impact. 1 = Envelope and check deposits have settlement impact. 2 = Commercial deposits (e.g., Securomatic deposits) have settlement impact. 3 = Envelope, check and commercial deposits have settlement impact.
AtmSegStmtPrntOnlnCd [bt_stringf(1)]	BASE24 Classic element - Indicates if a statement print transaction should be sent to the Host even if the IDF routing table entry indicates that the transaction should be authorized offline. Valid values: 0 = Do not send the statement print transaction to the Host. 1 = Send the statement print transaction to the Host.
AtmSegUserFld3bTx [bt_stringf(2)]	BASE24 Classic element - This field is not used.
AtmSegRtTbl1PriDPCShort [bt_int16s]	BASE24 Classic element - The DPC number of the host computer to which transactions included under this table entrys processing parameters are routed. This DPC number must correspond to the DPC number assigned to the host computer in the Host

Element (type)	Description
	Configuration File (HCF). Unless a table entry requires absolutely no communications with a host, this field should always contain a DPC number. If no communications are required with a host, the value in this field can be set to zero.
AtmSegRtTbl1SymNameTx [bt_stringf(16)]	BASE24 Classic element - The symbolic name of the Host Interface process used for sending this group of transactions to the host DPC. If used, the value in the SYM-NAME field must match exactly the name given to the Host Interface process in the Network Environment Source File (NEFS). Unless a table entry requires absolutely no communication with a host, this field should always contain the symbolic name of a Host Interface process. If no communication is required with a host, this field may be left blank except for the first table entry. The first table entry must always contain a value.
AtmSegRtTbl1AcctTypTx [bt_stringf(2)]	BASE24 Classic element - The transaction account type to be processed according to this table entrys parameters. A match in the value in this field and the value in the PREFIX-RTE field in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 01 = Checking accounts (used for account types 01-09). 11 = Savings accounts (used for account types 11-19). 31 = Credit accounts (used for account types 31-39). AL = All accounts (will match on any account type). For transactions, such as transfers, involving different account types, the from account and to account sides may be processed differently according to different table entries.
AtmSegRtTbl1PrfxRteTx [bt_stringf(1)]	BASE24 Classic element - The card prefixes processed according to this table entrys parameters. Card prefixes can be grouped in the Card Prefix File (using the values in the PREFIX-RTE field in the Base segment of the CPF for different types of authorization processing). The value in this field ties the card prefix groups to this table entry. A match in the value in this field and the value in the ACCT-TYP in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 0-9 = Prefix routing numbers - must match the prefix group number assigned in the PREFIX-RTE field in the Base segment of the CPF. A = All prefixes. This setting acts as a default value for any prefixes not accounted for by a more specific table entry.
AtmSegRtTbl1AuthTypTx [bt_stringf(1)]	BASE24 Classic element - A code indicating the type of authorization method used to process transactions when the values in the ACCT-TYP and PREFIX-RTE fields on the same line in the table match those of the transaction being processed.
AtmSegRtTbl1AuthLvITx [bt_stringf(1)]	BASE24 Classic element - The authorization level that applies when the values in the ACCT-TYP field and PREFIX-RTE fields in this table entry match those of the transaction being processed.
AtmSegRtTbl1UsrFld4Tx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
AtmSegRtTbl2PriDPCShort [bt_int16s]	BASE24 Classic element - The DPC number of the host computer to which transactions included under this table entrys processing parameters are routed. This DPC number must correspond to the DPC number assigned to the host computer in the Host Configuration File (HCF). Unless a table entry requires absolutely no communications with a host, this field should always contain a DPC number. If no communications are required with a host, the value in this field can be set to zero.
AtmSegRtTbl2SymNameTx [bt_stringf(16)]	BASE24 Classic element - The symbolic name of the Host Interface process used for sending this group of transactions to the host DPC. If used, the value in the SYM-NAME field must match exactly the name given to the Host Interface process in the Network Environment Source File (NEFS). Unless a table entry requires absolutely no communication with a host, this field should always contain the symbolic name of a Host Interface process. If no communication is required with a host, this field may be

Element (type)	Description
	left blank except for the first table entry. The first table entry must always contain a value.
AtmSegRtTbl2AcctTypTx [bt_stringf(2)]	BASE24 Classic element - The transaction account type to be processed according to this table entry's parameters. A match in the value in this field and the value in the PREFIX-RTE field in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 01 = Checking accounts (used for account types 01-09). 11 = Savings accounts (used for account types 11-19). 31 = Credit accounts (used for account types 31-39). AL = All accounts (will match on any account type). For transactions, such as transfers, involving different account types, the from account and to account sides may be processed differently according to different table entries.
AtmSegRtTbl2PrfxRteTx [bt_stringf(1)]	BASE24 Classic element - The card prefixes processed according to this table entry's parameters. Card prefixes can be grouped in the Card Prefix File (using the values in the PREFIX-RTE field in the Base segment of the CPF for different types of authorization processing). The value in this field ties the card prefix groups to this table entry. A match in the value in this field and the value in the ACCT-TYP in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 0-9 = Prefix routing numbers - must match the prefix group number assigned in the PREFIX-RTE field in the Base segment of the CPF. A = All prefixes. This setting acts as a default value for any prefixes not accounted for by a more specific table entry.
AtmSegRtTbl2AuthTypTx [bt_stringf(1)]	BASE24 Classic element - A code indicating the type of authorization method used to process transactions when the values in the ACCT-TYP and PREFIX-RTE fields on the same line in the table match those of the transaction being processed.
AtmSegRtTbl2AuthLvITx [bt_stringf(1)]	BASE24 Classic element - The authorization level that applies when the values in the ACCT-TYP field and PREFIX-RTE fields in this table entry match those of the transaction being processed.
AtmSegRtTbl2UsrFld4Tx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
AtmSegRtTbl3PriDPCShort [bt_int16s]	BASE24 Classic element - The DPC number of the host computer to which transactions included under this table entry's processing parameters are routed. This DPC number must correspond to the DPC number assigned to the host computer in the Host Configuration File (HCF). Unless a table entry requires absolutely no communications with a host, this field should always contain a DPC number. If no communications are required with a host, the value in this field can be set to zero.
AtmSegRtTbl3SymNameTx [bt_stringf(16)]	BASE24 Classic element - The symbolic name of the Host Interface process used for sending this group of transactions to the host DPC. If used, the value in the SYM-NAME field must match exactly the name given to the Host Interface process in the Network Environment Source File (NEFS). Unless a table entry requires absolutely no communication with a host, this field should always contain the symbolic name of a Host Interface process. If no communication is required with a host, this field may be left blank except for the first table entry. The first table entry must always contain a value.
AtmSegRtTbl3AcctTypTx [bt_stringf(2)]	BASE24 Classic element - The transaction account type to be processed according to this table entry's parameters. A match in the value in this field and the value in the PREFIX-RTE field in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 01 = Checking accounts (used for account types 01-09). 11 = Savings accounts (used for account types 11-19). 31 = Credit accounts (used for account types 31-39). AL = All accounts (will match on any account type). For transactions, such as transfers, involving different account types,

Element (type)	Description
	the from account and to account sides may be processed differently according to different table entries.
AtmSegRtTbl3PrfxRteTx [bt_stringf(1)]	BASE24 Classic element - The card prefixes processed according to this table entrys parameters. Card prefixes can be grouped in the Card Prefix File (using the values in the PREFIX-RTE field in the Base segment of the CPF for different types of authorization processing). The value in this field ties the card prefix groups to this table entry. A match in the value in this field and the value in the ACCT-TYP in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 0-9 = Prefix routing numbers - must match the prefix group number assigned in the PREFIX-RTE field in the Base segment of the CPF. A = All prefixes. This setting acts as a default value for any prefixes not accounted for by a more specific table entry.
AtmSegRtTbl3AuthTypTx [bt_stringf(1)]	BASE24 Classic element - A code indicating the type of authorization method used to process transactions when the values in the ACCT-TYP and PREFIX-RTE fields on the same line in the table match those of the transaction being processed.
AtmSegRtTbl3AuthLvITx [bt_stringf(1)]	BASE24 Classic element - The authorization level that applies when the values in the ACCT-TYP field and PREFIX-RTE fields in this table entry match those of the transaction being processed.
AtmSegRtTbl3UsrFld4Tx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
AtmSegRtTbl4PriDPCShort [bt_int16s]	BASE24 Classic element - The DPC number of the host computer to which transactions included under this table entrys processing parameters are routed. This DPC number must correspond to the DPC number assigned to the host computer in the Host Configuration File (HCF). Unless a table entry requires absolutely no communications with a host, this field should always contain a DPC number. If no communications are required with a host, the value in this field can be set to zero.
AtmSegRtTbl4SymNameTx [bt_stringf(16)]	BASE24 Classic element - The symbolic name of the Host Interface process used for sending this group of transactions to the host DPC. If used, the value in the SYM-NAME field must match exactly the name given to the Host Interface process in the Network Environment Source File (NEFS). Unless a table entry requires absolutely no communication with a host, this field should always contain the symbolic name of a Host Interface process. If no communication is required with a host, this field may be left blank except for the first table entry. The first table entry must always contain a value.
AtmSegRtTbl4AcctTypTx [bt_stringf(2)]	BASE24 Classic element - The transaction account type to be processed according to this table entrys parameters. A match in the value in this field and the value in the PREFIX-RTE field in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 01 = Checking accounts (used for account types 01-09). 11 = Savings accounts (used for account types 11-19). 31 = Credit accounts (used for account types 31-39). AL = All accounts (will match on any account type). For transactions, such as transfers, involving different account types, the from account and to account sides may be processed differently according to different table entries.
AtmSegRtTbl4PrfxRteTx [bt_stringf(1)]	BASE24 Classic element - The card prefixes processed according to this table entrys parameters. Card prefixes can be grouped in the Card Prefix File (using the values in the PREFIX-RTE field in the Base segment of the CPF for different types of authorization processing). The value in this field ties the card prefix groups to this table entry. A match in the value in this field and the value in the ACCT-TYP in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 0-9 = Prefix routing numbers - must match the prefix group number assigned in

Element (type)	Description
	the PREFIX-RTE field in the Base segment of the CPF. A = All prefixes. This setting acts as a default value for any prefixes not accounted for by a more specific table entry.
AtmSegRtTbl4AuthTypTx [bt_stringf(1)]	BASE24 Classic element - A code indicating the type of authorization method used to process transactions when the values in the ACCT-TYP and PREFIX-RTE fields on the same line in the table match those of the transaction being processed.
AtmSegRtTbl4AuthLvITx [bt_stringf(1)]	BASE24 Classic element - The authorization level that applies when the values in the ACCT-TYP field and PREFIX-RTE fields in this table entry match those of the transaction being processed.
AtmSegRtTbl4UsrFld4Tx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
AtmSegRtTbl5PriDPCShort [bt_int16s]	BASE24 Classic element - The DPC number of the host computer to which transactions included under this table entrys processing parameters are routed. This DPC number must correspond to the DPC number assigned to the host computer in the Host Configuration File (HCF). Unless a table entry requires absolutely no communications with a host, this field should always contain a DPC number. If no communications are required with a host, the value in this field can be set to zero.
AtmSegRtTbl5SymNameTx [bt_stringf(16)]	BASE24 Classic element - The symbolic name of the Host Interface process used for sending this group of transactions to the host DPC. If used, the value in the SYM-NAME field must match exactly the name given to the Host Interface process in the Network Environment Source File (NEFS). Unless a table entry requires absolutely no communication with a host, this field should always contain the symbolic name of a Host Interface process. If no communication is required with a host, this field may be left blank except for the first table entry. The first table entry must always contain a value.
AtmSegRtTbl5AcctTypTx [bt_stringf(2)]	BASE24 Classic element - The transaction account type to be processed according to this table entrys parameters. A match in the value in this field and the value in the PREFIX-RTE field in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 01 = Checking accounts (used for account types 01-09). 11 = Savings accounts (used for account types 11-19). 31 = Credit accounts (used for account types 31-39). AL = All accounts (will match on any account type). For transactions, such as transfers, involving different account types, the from account and to account sides may be processed differently according to different table entries.
AtmSegRtTbl5PrfxRteTx [bt_stringf(1)]	BASE24 Classic element - The card prefixes processed according to this table entrys parameters. Card prefixes can be grouped in the Card Prefix File (using the values in the PREFIX-RTE field in the Base segment of the CPF for different types of authorization processing). The value in this field ties the card prefix groups to this table entry. A match in the value in this field and the value in the ACCT-TYP in this table entry determines the authorization and routing parameters for a transaction. Valid values are: 0-9 = Prefix routing numbers - must match the prefix group number assigned in the PREFIX-RTE field in the Base segment of the CPF. A = All prefixes. This setting acts as a default value for any prefixes not accounted for by a more specific table entry.
AtmSegRtTbl5AuthTypTx [bt_stringf(1)]	BASE24 Classic element - A code indicating the type of authorization method used to process transactions when the values in the ACCT-TYP and PREFIX-RTE fields on the same line in the table match those of the transaction being processed.
AtmSegRtTbl5AuthLvITx [bt_stringf(1)]	BASE24 Classic element - The authorization level that applies when the values in the ACCT-TYP field and PREFIX-RTE fields in this table entry match those of the transaction being processed.

Element (type)	Description
AtmSegRtTbI5UsrFld4Tx [bt_stringf(1)]	BASE24 Classic element - This field is not used.
AtmSegLogRteCdeShort [bt_int16s]	BASE24 Classic element - A code used by the BASE24-atm Authorization process for routing log messages specifically on behalf of this institution.
AqurTrnsPrflTx [bt_stringf(16)]	BASE24 Classic element - The acquirer transaction profile field is part of the key to the APCF. Each acquirer transaction profile defines a set of transactions supported by an acquirer (i.e., institution, retailer, or terminal). This allows one or more acquirers to share processing code definitions and transactions allowed information.
AtmSegIssTxnPrflTx [bt_stringf(16)]	BASE24 Classic element - Profile used as part of the key to read the IPCF to determine if a specific transaction is allowed by cardholders of this institution.
AtmSegUserFld5Tx [bt_stringf(48)]	BASE24 Classic element - This field is not used.
IDFRemainingSegs [bt_binaryv(1310)]	BASE24 Classic element - J-DH processes only interested in certain fiels in the BASE and ATM segments. ATM is first segment in the IDF. We assume this is present. Treat the remainder of the IDF (variable length depending on which segments present) as a large byte field. If this work then we will not have to breakdown the segment map.

IFXDATA (3.0) (ifxdtd)

The IFX ATM specific data associated with the ES IFX device handler. This table is managed by the device handler. It is viewable read-only through the UI.

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
MacSecObjIdTx [bt_stringf(36)]	The object ID for the Message Authentication Key. This value is set by the ES IFX device handler prior to sending down the key to the IFX ATM.
PINSecObjIdTx [bt_stringf(36)]	The object ID for the PIN Encryption Key. This value is set by the ES IFX device handler prior to sending down the key to the IFX ATM.
MasterSecObjIdTx [bt_stringf(36)]	The object ID for the Master Key. This value is set by the ES IFX device handler prior to sending down the key to the IFX ATM.
TerminalObjIdTx [bt_stringf(36)]	The object ID for the terminal object. This value is set by the ES IFX device handler when a response to a Terminal Object Add message (TermObjAddRq) is received. This is NOT the terminal ID. It is the Id of an object added into the ATM software.
MsgSecObjIdTx [bt_stringf(36)]	The Message Data working Key's SecObjId. The element is stored on the IFXDATA table and is controlled by the device handler.
KEKMsgSecObjIdTx [bt_stringf(36)]	The Message Data Key Exchange Key's SecObjId. The element is stored on the ES IFXDATA table and is controlled by the device handler.
KEKMacSecObjIdTx [bt_stringf(36)]	The MAC Key Exchange Key's SecObjId. The element is stored on the ES IFXDATA table and is controlled by the device handler.

Element (type)	Description
KEKPinSecObjIdTx [bt_stringf(36)]	The PIN Key Exchange Key's SecObjId. The element is stored on the ES IFXDATA table and is controlled by the device handler.
HstCrtSecObjIdTx [bt_stringf(36)]	A unique security object identifier for the host public key certificate. The element is stored on the ES IFXDATA table and is controlled by the device handler.
ATMVCrtSecObjIdTx [bt_stringf(36)]	A unique security object identifier for the ATM public verification key certificate. The element is stored on the ES IFXDATA table and is controlled by the device handler.
ATMECrtSecObjIdTx [bt_stringf(36)]	A unique security object identifier for the ATM public encryption key certificate. The element is stored on the ES IFXDATA table and is controlled by the device handler.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
TMKSignSecObjIdTx [bt_stringf(36)]	The object ID for the Master Key Signature. This value is set by the ES IFX device handler prior to sending down the key to the IFX ATM.
ATMSrINSecObjIdTx [bt_stringf(36)]	A unique security object identifier for the ATM serial number. The element is stored on the ES IFXDATA table and is controlled by the device handler.
ATMEKeySecObjIdTx [bt_stringf(36)]	A unique security object identifier for the ATM public encryption key. The element is stored on the ES IFXDATA table and is controlled by the device handler.
HstKeySecObjIdTx [bt_stringf(36)]	A unique security object identifier for the host public key. The element is stored on the ES IFXDATA table and is controlled by the device handler.

IFX_Host_Action_Code_Int_Ext (1.0) (ifxacd)

The IFX Host Interface Action Code Internal to External table contains one record for every internal action code defined for the action code profile.

[Audited] [Supports versioning]

Element (type)	Description
act_cde_prfl*[prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
act_cde*[bt_int16s]	The internal action code which is used to map to an external action code or is the result of a mapping from an external action code. Valid values are 000 - 999.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
stat_cde_extrn [bt_stringf(4)]	The external status code which is the result of a mapping from an internal action code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Must be 1 to 4 characters in length.

Element (type)	Description
severity_cde_extrn [bt_stringf(5)]	The severity of the event. Valid values are: Info, Warn, Error, Crit.

IFX_Host_Interface (1.0) (ifxhid)

The IFX Host Interface table contains one row for each IFX Host Interface configured.

[Audited] [Supports versioning]

OLTP: IFX_Host_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
nam_spc [bt_stringv(64)]	This field identifies the name space for an IFX message.

Ind_Sort_Code_Directory (1.0) (iscdd)

The Industry Sort Code Directory data source is read during issuer determine by FPS-aware acquirer interfaces if the destination bank code is not known, and is a selection of columns from the UK Banking industry ISCD file, used by the FPS Gateway.

[Audited] [Supports versioning]

OLTP: Ind_Sort_Code_Directory_OLTP

Element (type)	Description
sort_cde*[bt_stringf(6)]	Sort code for the branch.
sub_brch_sfx*[bt_stringf(2)]	The sub branch suffix of the account holding sub-branch.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
bic [bt_stringf(11)]	BIC for the branch.
short_brch_title [bt_stringf(27)]	The short branch title of the account holding bank branch.
short_bnk_nam [bt_stringf(20)]	The short bank title of the account holding bank branch.
full_bnk_nam1 [bt_stringf(35)]	Part 1 of the full bank name of the account holding bank branch.
full_bnk_nam2 [bt_stringf(35)]	Part 2 of the full bank name of the account holding bank branch.
uk_bnk_id [bt_stringf(4)]	Bank Id of the UK bank.
centry_cde [bt_stringf(3)]	3 Alphabetic characters Country Code.
sprvsr_body [bt_stringf(1)]	For bank offices that are agencies in one or more of the clearings, specifies the authorising body. Will be one of: Blank - Not Applicable, A - Bank of

Element (type)	Description
	England, B - Building Society Commission, C - for Jersey, Guernsey, or Isle of Man authorities, D - Other.
del_dat [ts 1.0]	Date that this record will be logically deleted.
lst_chng_dat [ts 1.0]	Date record last changed. Zero displayed as spaces.
prnt_ind [bt_stringf(1)]	Specifies how the bank offices details will appear in the UK Clearings Directory. Values are 0 - No special printing requirements, print all, 1 - Do not print sub or linked after bank office names, 2 - Do not print in the alphabetically sorted section, 3 - Do not print in the numerically sorted section, 4 - Do not print sub or linked after bank office names and do not print in the numerically sorted section, 5 - Do not print any bank office information.
fps_stat_iscd [bt_stringf(1)]	The FPS Status of the bank office for this ISCD record. Values are: M - a bank office of an FPS Member that accepts FPS payments, A - a bank office of an FPS agency bank that accepts FPS payments, N - bank office does not accept FPS payments.
fps_lst_chng_dat [ts 1.0]	The effective date of the last change to the this bank offices Faster Payments data group on the ISCD.
fps_clos_dat [ts 1.0]	The effective date that this bank office will be closed to Faster Payments clearing.
fps_redir_flg [bt_stringf(1)]	If the bank office is set as the redirection sorting code for one or more bank offices, will be set to R, otherwise blank.
fps_redir_sort_cde [bt_stringf(6)]	If set, is the sorting code to which output of this ISCD sort code record will be redirected.
fps_conn_typ_setl [bt_stringf(2)]	FPS Connectivity Type for the settlement bank office. If set, must be 01 (FPS Member).
fps_bnk_id_setl [bt_stringf(4)]	FPS Bank ID Code for the bank member that settles FPS payments for the bank office referred to by this ISCD record.
fps_conn_typ_hndl [bt_stringf(2)]	Connectivity Code of the handling member for this FPS Bank office.
fps_bnk_id_hndl [bt_stringf(4)]	Bank ID of the handling member for this FPS bank office.
fps_accts_numbered_flg [bt_flag]	Accounts numbered flag. Values are: Y - bank office has numbered accounts, on redirection zeroise the account number; N - bank office does not have numbered accounts, on redirection retain the account number.
fps_agency_typ [bt_stringf(1)]	Agency type for Faster Payments, if the FPS status is Agency. Valid values are: D - Direct, bank office receives FPS payment requests directly. I - Indirect, FPS Payment requests are sent via an intermediary bank, which in turn can be an FPS member or direct agency.

Ind_Sort_Code_Directory_Input (1.0) (iscdid)

The Industry Sort Code Database Input data source contains one row for each input record in the full-file ISCD refresh. The native input file will be loaded into this data source as part of ISCD Refresh pre-processing.

[Not Audited] [Does not support versioning]

Element (type)	Description
sort_cde_rec [bt_stringf(1000)]	Input record for the Faster Payments ISCD refresh data source.

Institution (6.0) (instd)

The Institution table contains one record for each institution or retailer in the system acting as a terminal owner or card-issuing authorization entity.

[Audited] [Supports versioning]

OLTP: Institution_OLTP

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inst_nam [bt_stringf(22)]	The institution name associated with the institution identifier. This field is left-justified (containing any combination of alphanumeric and special characters).
inst_id_num [bt_stringf(11)]	The institutions transit/routing number or issuer identification number unique to the institution. This field is left justified (containing only numeric characters).
st [bt_stringf(3)]	The state, province or region code depending upon locale. This field contains alphanumeric and special characters.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
bal_strt_tim [bt_stringf(4)]	The start time for the balance window. This field is in HHMM format. (NOT USED)
cutover_strt_tim [tim_hhmm 1.0]	The start of the balance and cutover window. This field is in HHMM format.
cutover_end_tim [bt_stringf(4)]	The end of the balance and cutover window. This field is in HHMM format.
addr_1 [bt_stringf(25)]	The address line 1. Where only one line of address is supported, this address will be used and addr_2 will be ignored. This field is left-justified (containing any combination of alphanumeric and special characters).
addr_2 [bt_stringf(25)]	The address line 2. This field is left-justified (containing any combination of alphanumeric and special characters).
city [bt_stringf(18)]	The city address. Field is left-justified (containing any combination of alphanumeric and special characteres).
cntry [bt_int16s]	The numeric country code as defined in ISO document 4217.
postal_cde [bt_stringf(10)]	The postal code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
rfrl_phn_num [phn_num 1.0]	The phone number to use when an action code of referral is returned. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
contact1_nam [nam 1.0]	The first contact name. This field is left-justified (containing any combination of alphanumeric and special characters).
contact1_phn_num [phn_num 1.0]	The first contact phone number. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact1_email_addr [email_addr 1.0]	The first contact email address. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact1_comments [comments 1.0]	The first contact comments. This field is left-justified (containing any combination of alphanumeric and special characters).
contact2_nam [nam 1.0]	The second contact name. This field is left-justified (containing any combination of alphanumeric and special characters).
contact2_phn_num [phn_num 1.0]	The second contact phone number. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact2_email_addr [email_addr 1.0]	The second contact email address. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact2_comments [comments 1.0]	The second contact comments. This field is left-justified (containing any combination of alphanumeric and special characters).
hol_dat1 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat2 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat3 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat4 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat5 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat6 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat7 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat8 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.

Element (type)	Description
hol_dat9 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat10 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat11 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat12 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat13 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat14 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat15 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat16 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat17 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat18 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat19 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat20 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
rte_prfl [prfl_def 1.0]	The profile assigned to this entity for use in routing.
base_crncy_cde [crncy_cde 1.0]	The base currency code. This represents the currency to which an amount in a different currency is being converted to.
bal_usg_retn_prd [bt_int16s]	The number of days to retain the accumulated usages for balances defined in the Positive Balance data source. Valid values are 0 - 31 (default value is 5).
atm_bal_flg [bt_int16s]	A flag identifying the ATM balancing procedures for this institution. Valid values are: 0 – use balancing window. 1 – balance ATMs anytime, but do not update capture date. For value 0, ATMs can only be balanced once a day. They must be balanced within the institutions balancing window. A balancing transaction

Element (type)	Description
	cuts over the value in the capture date field in the ATM record. For value 1, ATMs can be balanced any time and as many times as desired by the ATM owner without regard for the balancing window. In this case, ATM balancing does not cut over the value in the capture date field in the ATM record. The value in the capture date field is instead cut over automatically by the system at the end time specified in the institutions balancing window.
inst_proc_day [bt_char]	This field contains an indication of the number of days on which the institution processes during a given week. Valid values are: 0 - No weekends (process 5 days), 1 - 7 day processing. Default value is 1. If no weekends, holidays are also excluded.
lmt_usg_prd_cutover_ofst [bt_int16s]	On the day the usage period is to expires, this field indicates the number of minutes after institution cutover when the usage period expires. Applies to all limit/usage period options except Fixed Number of Hours. Default value is 0, which means the usage period expires at institution cutover. If set to 90, for example, then the usage period expires 90 minutes after institution cutover. Valid values are 0 - 1439. Note that 1439 is 23 hours and 59 minutes.
atm_force_bal_flg [bt_int16s]	Controls the End-of-Period forced balance processing for ATMs. The valid values are: 0 - Snapshot of totals written to journal, counters are NOT reset. 1 - Snapshot of totals are written to journal, counters are reset in order to balance.
addr_1_mbyte [bt_binaryl(50)]	The multi-byte address line 1. Where only one line of address is supported this address will be used and addr_2 will be ignored. This field contains any combination of alphanumeric and special characters.
addr_2_mbyte [bt_binaryl(50)]	The multi-byte address line 2. This field contains any combination of alphanumeric and special characters.
city_mbyte [bt_binaryl(36)]	The multi-byte city address. Field is contains any combination of alphanumeric and special characters.
regn_mbyte [bt_binaryl(6)]	The multi-byte state, province or region code depending upon locale. This field contains alphanumeric and special characters.
postal_cde_mbyte [bt_binaryl(20)]	The multi-byte postal code. This field contains any combination of alphanumeric and special characters, but without any embedded spaces.
cntry_mbyte [bt_binaryl(6)]	Multi-byte country identifier.
contact1_nam_mbyte [bt_binaryl(32)]	The first multi-byte contact name. This field is contains any combination of alphanumeric and special characters.
contact1_phn_num_mbyte [bt_binaryl(40)]	The first multi-byte contact phone number. This field contains any combination of alphanumeric and special characters, but without any embedded spaces.
contact1_email_addr_mbyte [bt_binaryl(100)]	The first multi-byte contact email address. This field contain any combination of alphanumeric and special characters, but without any embedded spaces.
contact1_comments_mbyte [bt_binaryl(100)]	The first multi-byte contact comments. This field is contains any combination of alphanumeric and special characters.
contact2_nam_mbyte [bt_binaryl(32)]	The second multi-byte contact name. This field contains any combination of alphanumeric and special characters.
contact2_phn_num_mbyte [bt_binaryl(40)]	The second multi-byte contact phone number. This field contains any combination of alphanumeric and special characters, but without any embedded spaces.
contact2_email_addr_mbyte [bt_binaryl(100)]	The second multi-byte contact email address. This field contain any combination of alphanumeric and special characters, but without any embedded spaces.

Element (type)	Description
contact2_comments_mbyte [bt_binary(100)]	The second multi-byte contact comments. This field is contains any combination of alphanumeric and special characters.

Instrm_Status_Extrn_to_Intrn (1.0) (iseid)

Instrument external status value to internal status value mapping.

[Audited] [Supports versioning]

Element (type)	Description
instrm_stat_prfl*[bt_stringf(16)]	Instrument status profile. Used as part of the primary key to read the Instrument Status External to Internal data source.
instrm_stat_extrn*[bt_stringf(2)]	External status value of the instrument.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_stat_extrn_descr [bt_stringf(48)]	Text description of the instrument external status.
instrm_stat [bt_stringf(2)]	The status (e.g., lost, stolen, open, etc.) of the instrument type. Values are user-defined.

Instrm_Status_Intrn_to_Extrn (1.0) (isied)

Instrument internal status value to external status value mapping.

[Audited] [Supports versioning]

Element (type)	Description
instrm_stat_prfl*[bt_stringf(16)]	Instrument status profile. Used as part of the primary key to read the Instrument Status External to Internal data source.
instrm_stat*[bt_stringf(2)]	The status (e.g., lost, stolen, open, etc.) of the instrument type. Values are user-defined.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_stat_extrn_descr [bt_stringf(48)]	Text description of the instrument external status.
instrm_stat_extrn [bt_stringf(2)]	External status value of the instrument.

Instrm_Typ_Extrn_to_Intrn (1.0) (iteid)

Instrument external type value to internal type value mapping.

[Audited] [Supports versioning]

OLTP: Instrm_Typ_Extrn_to_Intrn_OLTP

Element (type)	Description
instrm_typ_prfl*[bt_stringf(16)]	Instrument type profile. Used as part of the primary key to read the Instrument Type External to Internal data source.
instrm_typ_extrn*[bt_stringf(2)]	External type value of the instrument.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_extrn_descr [bt_stringf(48)]	Text description of the instrument external type.
instrm_typ [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.

Instrm_Typ_Intrn_to_Extrn (1.0) (ited)

Instrument internal type value to external type value mapping.

[Audited] [Supports versioning]

OLTP: Instrm_Typ_Intrn_to_Extrn_OLTP

Element (type)	Description
instrm_typ_prfl*[bt_stringf(16)]	Instrument type profile. Used as part of the primary key to read the Instrument Type External to Internal data source.
instrm_typ*[instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_extrn_descr [bt_stringf(48)]	Text description of the instrument external type.
instrm_typ_extrn [bt_stringf(2)]	External type value of the instrument.

INSTRUMENT_TYPE (1.0) (itypd)

This data source contains the Instrument Types. This data source is used by the UI to maintain the instrument types and descriptions.

[Audited] [Supports versioning]

Element (type)	Description
instrm_typ* [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_descr [bt_stringf(40)]	The instrument type description.

Instrum_Typ_Interchange_Rel (2.0) (itird)

The Instrument Type to Interchange Relation table maps known instrument types to a known interchange.

[Audited] [Supports versioning]

OLTP: Instrum_Typ_Interchange_Rel_OLTP

Element (type)	Description
instrm_typ* [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.
interchange* [bt_int16s]	The interchange of the instrument type used. Valid values are 0 - Default, 1 - Visa, 2 - Mastercard, 3 - American Express, 4 - Diners, 5 - Interlink, 6 - Plus, 7 - Cirrus, 8 - Maestro, 9 - Discover, 10 - JCB, 11 - FDI, 12 - CardProcess, 13 - ATOS, 14 - B&S, 15 Finanzit, 16 - Citicorp Default value is 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
auth_msg_typ [bt_int16s]	The authorization message type to use. Valid values are 0 - Default, 1 - dual (online authorization with clearing to be performed later), 2 - single (online authorization and clearing performed via single message). Default value is 0.
interchange_acct_typ [bt_int16s]	The account type of the instrument used. Valid values are 0 - Default, 1 - Credit, 2 - Debit. Default value is 0.

Element (type)	Description
netwk_id [bt_stringf(6)]	The network ID associated with the Instrument Type and Interchange combination. This a numeric character field, left justified with no embedded spaces.

Interac_Admin (1.0) (intramd)

The Interac Admin Table.

[Audited] [Supports versioning]

Element (type)	Description
rec_crte_dat*[bt_stringf(6)]	
rec_crte_tim*[bt_stringf(8)]	
inbnd_outbnd_flg [bt_stringf(1)]	
remt_nde_id [bt_stringf(6)]	
acq_nde_id [bt_stringf(6)]	
iss_nde_id [bt_stringf(6)]	
msg_class [bt_stringf(2)]	
admin_msg_subtyp [bt_stringf(2)]	
pan [bt_stringf(19)]	
proc_cde [bt_stringf(6)]	
amt [bt_int32s]	
local_txn_tim [bt_stringf(6)]	
local_txn_dat [bt_stringf(6)]	
captr_dat [bt_stringf(4)]	
orig_txn_fee [bt_int32s]	
retrv_ref_num [bt_stringf(12)]	
term_id [bt_stringf(8)]	
crd_accpt_id [bt_stringf(15)]	
resp_cde [bt_stringf(2)]	
trc_rsn_cde [bt_stringf(2)]	
orig_setl_dat [bt_stringf(6)]	
admin_free_txt_lgth [bt_stringf(3)]	
admin_free_txt [bt_stringf(233)]	

Interac_ATM_IIN (1.0) (intraid)

The Interac ATM (SCD) Institution ID Number Table.

[Not Audited] [Does not support versioning]

OLTP: Interac_ATM_IIN_OLTP

Element (type)	Description
interac_crd_prfx* [bt_stringf(10)]	The card prefix used to identify the Interac Institution.
interac_iin_nde_id [bt_binaryf(3)]	The node id assigned to the Interac Institution in binary Hex format. For example, value 700241 will be stored as %H70 %H02 %H41.

Interac_Base (1.0) (intrbad)

Record of Changes: Date Version Person ----- 09DEC2008 1.0.00 R. Carpenter Symptom: None. Problem: None. Fix: None. Reference: WO #080229-01 03JUN2010 1.0.01 C. Linke Symptom: Interac Phase 2 Enhancement Problem: None. Fix: Modifications required to align Interac Interface processing with Interac Member Network requirements. Reference: WO #080229-01 09JUL2010 1.0.02 C. Linke Symptom: Interac Phase 2 Enhancement Problem: None. Fix: Added fields to Interac Base datasource and OLTP for SAF processing. Reference: WO #080229-01 22JUL2010 1.0.03 C. Linke Symptom: Interac Phase 2 Enhancement Problem: None. Fix: Added missing defaults. Updated IIN OLTPs to the correct format for using radix searches. Reference: WO #080229-01 25AUG2010 1.0.04 C. Linke Symptom: Interac Phase 2 Enhancement Problem: None. Fix: Removed commas after last member before prikey definition. Changed default setting for bt_flag fields from N to 0. Reference: WO #080229-01 09OCT2010 1.0.05 C. Linke Symptom: Interac Phase 2 Enhancement - Change Request 002 Problem: None. Fix: Removed saf_slow_lmt, saf_slow_cnt, saf_fast_lmt, saf_fast_cnt, avg_resp_tim, pacing_cnt and ttl_resp_tim. Reference: WO #080229-01 21FEB2011 1.0.06 C. Linke Symptom: Interac Phase 2 Enhancement - Change Request 002 Problem: None. Fix: Changed the index variables from boolean flags to integer. Added missing members mac_key_xchng_flg, pin_key_xchng_flg and data_key_xchng_flg. Reference: WO #080229-02 Change Request 002. The Interac Base Table.

[Audited] [Supports versioning]

OLTP: Interac_Base_OLTP

Element (type)	Description
cmpnt_id* [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
interac_nde_id [bt_stringf(6)]	Identification code assigned by Interac.
num_days_in_admin [bt_int16s]	Number of days that a record must remain in the ADIMN file.
test_flg [bt_stringf(2) DEFAULT 01]	Indicates the test mode of the connection. Valid values are: 01 - Test, 10 - Production. Default value is 01.
atm_timeouts_to_block [bt_int16s DEFAULT 3]	Indicates the number of transactions that timeout in an interval before the interface will declare the ATM AIL blocked and will notify the Entry Point Manager. Valid values are 1 - 99. Default value is 3.
atm_slow_resp_to_congest [bt_int16s DEFAULT 3]	Indicates the number of slow transactions + timeouts in an interval before the interface will declare the ATM AIL congested and will notify the Entry Point Manager. Valid values are 1 - 99. Default value is 3.

Element (type)	Description
pos_timeouts_to_block [bt_int16s DEFAULT 3]	Indicates the number of transactions that timeout in an interval before the interface will declare the POS AIL blocked and will notify the Entry Point Manager. Valid values are 1 - 99. Default value is 3.
pos_slow_resp_to_congest [bt_int16s DEFAULT 3]	Indicates the number of slow transactions + timeouts in an interval before the interface will declare the POS AIL connection congested and will notify the Entry Point Manager. Valid values are 1 - 99. Default value is 3.
min_pacing_stagger [bt_int16s]	Indicate the minimum pacing stagger interval
pacing_abnormal_lmt [bt_int16s DEFAULT 30]	Indicates the interval (in seconds) between pacing messages sent out by the interface to the Entry Point Manager when the connection is blocked. Valid values are 10 - 32766. Default value is 30.
pacing_normal_lmt [bt_int16s DEFAULT 30]	Indicates the interval (in seconds) between pacing messages sent out by the interface to the Entry Point Manager when the connection is normal. Valid values are 10 - 32766. Default value is 30.
pacing_timr_lmt [bt_int16s DEFAULT 30]	Indicates the interval (in seconds) that the interface will use to re-evaluate response times for pacing changes. Valid values are 10 - 32766. Default value is 30.
saf_pro_dat [bt_stringf(4)]	The current processing date for Store And Forward records. It will be incremented 30 minutes after cutover. Certain message types will not be sent if this date does not match the date in field 17 in the Store And Forward message. MMDD
saf_alarm_timr_lmt [bt_int16s DEFAULT 60]	Indicates the interval (in seconds) between monitoring of SAF mode, rate and record count in order to issue alarm messages based on the SAF status. Valid values are 10 - 32766. Default value is 60.
saf_rec_lmt [bt_int16s DEFAULT 20]	Indicates the threshold number of records on the SAF files for an interface after which warning messages will be issued. re 1 - 32766. Default value is 20.
ail_id [bt_int16s DEFAULT 01]	This number is the AIL ID for acquirer transactions. It is used in the REQ AIL ID in the Interac header for request messages being formatted and sent out. When getting the Interface Record a 0 is used for request messages
dummy_pan [bt_stringf(19) DEFAULT "0011110000001"]	The dummy pan is used for administration transactions from the Interac Browser. This value is never sent out in a message.
rcncl_slot_num [bt_int16s DEFAULT 01]	This number indicates the reconciliation slot number that the that the Interac member will use in DE 48
lwr_ver_num [bt_stringf(4) DEFAULT "0100"]	Indicates the lower version number that this installation supports. The number will be displayed in the UI with an implied decimal place. The format for the display will be nn.nn, where nn must be between 00-99
upr_ver_num [bt_stringf(4) DEFAULT "0110"]	Indicates the upper version number that this installation supports. The number will be displayed in the UI with an implied decimal place. The format for the display will be nn.nn, where nn must be between 00-99
clean_up_time_hour [bt_int16s]	This field indicates what hour of the day that the clean up program should begin. The value is in 24 hour format. Default is midnight.
clean_up_tim_min [bt_int16s]	This field indicates what minute of the hour that the clean up program should begin. Default is 0.

Element (type)	Description
min_fast_intrvl [bt_int16s]	This field will indicate the minimum time, in seconds, that the SAF rate will remain set to "FAST" before it can be changed to "SLOW" by the interface. Default is 0.
min_slow_intrvl [bt_int16s]	This field will indicate the minimum time, in seconds, that the SAF rate will remain set to "SLOW" before it can be set to "FAST" by the interface. Default is 0.
inbound_pacing_intrvl [bt_int16s DEFAULT 30]	The interval in seconds at which the counters for deciding if the inbound path pacing is normal, congested or blocked are tested and reset. Valid values 0 - no pacing 1 - 3600 (1 hour) Default: 30 seconds
slow_percentage_lmt [bt_int16s DEFAULT 80]	The percentage of the configured timeout to consider a message to be slow. This will be used to determine when the interface is becoming congested. Valid values 0 - do not process 50 - 100 Default: 80 percent
abnrml_pcng_timr_id [timr_id 1.0]	Abnormal pacing timer ID - indicates the value passed back from a timer start request for an abnormal pacing timer.
nrml_pcng_timr_id [timr_id 1.0]	Normal pacing timer ID - indicates the value passed back from a timer start request for a normal pacing timer.
clean_up_timr_id [timr_id 1.0]	Clean up timer ID - indicates the value passed back from a timer start request for a clean up timer.
cur_atm_pacing_st [bt_stringf(1) DEFAULT N]	Current inbound pacing state of the ATM AIL. Valid values: N - normal (default) C - congested B - Blocked D - Disabled (Blocked) by an operator command
cur_pos_pacing_st [bt_stringf(1) DEFAULT N]	Current inbound pacing state of the POS AIL. Valid values: N - normal (default) C - congested B - Blocked D - Disabled (Blocked) by an operator command
atm_timeout_txn_cnt [bt_int16s]	The number of ATM transactions time outs that have occurred during the current interval.
pos_timeout_txn_cnt [bt_int16s]	The number of POS transactions time outs that have occurred during the current interval.
atm_slow_txn_cnt [bt_int16s]	The number of slow ATM transactions, other than timeouts, that have occurred during the current interval.
pos_slow_txn_cnt [bt_int16s]	The number of slow POS transactions, other than timeouts that have occurred during the current interval.
inbnd_pcng_timr_id [timr_id 1.0]	Inbound pacing timer id - indicates the value passed back from timer start request for a inbound pacing timer.

Interac_Entry_Point (1.0) (intrepd)

The Interac Entry Point Configuration Table.

[Not Audited] [Does not support versioning]

Element (type)	Description
ep_id*[bt_stringf(6)]	Entry Point identifier

Element (type)	Description
ail_id [bt_stringf(1)]	AIL-ID, 0 for issuer, 1-9 for acquirer.
msg_class [bt_stringf(1)]	Message class 1 - POS, 3 - ATM
subsystem_id [bt_stringf(2)]	Subsystem Id for AIL process
ail_pid [bt_stringf(16)]	Expanded Tandem Process Name (PPD name) for AIL process
cil_pid [bt_stringf(16)]	Expanded Tandem Process Name (PPD name) for Commonitor process
ep_stat [bt_stringf(1)]	Operator state: A for Activated (Started), D for deactivated (Stopped).
ep_filler [bt_stringf(2)]	Space reserved for future use.

Interac_Interface (1.0) (intrifd)

The Interac Interface Table.

[Audited] [Supports versioning]

OLTP: Interac_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
cnct_st [bt_stringf(1)]	Indicates the current connection status information. Valid values are: 0 - down, 1 - ready, 2 - key exchange, 3 - up.
key_sync_lmt [bt_int16s]	Indicates the number of times a key synchronization error may occur before a message is sent to the logger.
key_sync_cnt [bt_int16s]	Counter used to keep track of how many key synchronization errors have occurred. When the counter is greater than or equal to the limit, a message will be sent to the logger.
key_xchg_lmt [bt_int16s]	Indicates the number of times a key exchange error may occur before a message is sent to the logger.
key_xchg_cnt [bt_int16s]	Counter used to keep track of how many key exchange errors have occurred. When the counter is greater than or equal to the limit, a message will be sent to the logger.
key_xchg_timeout_lmt [bt_int16s]	Indicates the number of times a key exchange timeout error may occur before a message is sent to the logger.
key_xchg_timeout_cnt [bt_int16s]	Counter used to keep track of how many key exchange timeout errors have occurred. When the counter is greater than or equal to the limit, a message will be sent to the logger.
key_xchg_rjct_lmt [bt_int16s]	Indicates the number of times a key exchange reject error may occur before a message is sent to the logger.

Element (type)	Description
key_xchg_rjct_cnt [bt_int16s]	Counter used to keep track of how many key exchange reject errors have occurred. When the counter is greater than or equal to the limit, a message will be sent to the logger.
inbnd_kek_cntr [bt_int32s]	Expected key sequence number on inbound key exchanges.
outbnd_kek_cntr [bt_int32s]	Key sequence number used on outbound key exchange.
interac_nde_nam_alpha [bt_stringf(6)]	This field will hold the Interac Node Name in its Alpha format.
key_xchnng_hour [bt_int16s]	This field indicates what hour of the day that the key exchanges should begin. The value is in 24 hour format. Default is midnight.
key_xchnng_min [bt_int16s]	This field indicates what minute of the hour that the key exchanges should begin.
xchnng_data_both_idx [bt_int16s DEFAULT 2]	This field is used to indicate how many more indexes must be exchanged when sending a new data key. Valid Values: 0 - data key exchanges complete 1 - one more index to exchange 2 - two more indexes to exchange
xchnng_mac_both_idx [bt_int16s DEFAULT 2]	This field is used to indicate how many more indexes must be exchanged when sending a new MAC key. Valid Values: 0 - data key exchanges complete 1 - one more index to exchange 2 - two more indexes to exchange
xchnng_pin_both_idx [bt_int16s DEFAULT 2]	This field is used to indicate how many more indexes must be exchanged when sending a new PIN key. Valid Values: 0 - data key exchanges complete 1 - one more index to exchange 2 - two more indexes to exchange
mac_key_xchnng_flg [bt_flag DEFAULT 0]	This flag is set to true when a MAC key exchange has been approved.
pin_key_xchnng_flg [bt_flag DEFAULT 0]	This flag is set to true when a PIN key exchange has been approved.
data_key_xchnng_flg [bt_flag DEFAULT 0]	This flag is set to true when a DATA key exchange has been approved.
key_xchnng_timr_id [timr_id 1.0]	Key exchange timer ID - indicates the value passed back from a timer start request for a daily key exchange timer.

Interac_POS_IIN (1.0) (intrpid)

The Interac POS (IDP) Institution ID Number Table.

[Not Audited] [Does not support versioning]

OLTP: Interac_POS_IIN_OLTP

Element (type)	Description
interac_crd_prfx* [bt_stringf(10)]	The card prefix used to identify the Interac Institution.
interac_iin_nde_id [bt_binaryf(3)]	The node id assigned to the Interac Institution in binary Hex format. For example, value 700241 will be stored as %H70 %H02 %H41.

Interchange_Prefix (3.0) (ipfxd)

The Interchange Prefix table contains one record for each unique prefix and pan length combination identifying an issuer. The instrument type is optional and defaults to spaces. If the instrument type is spaces, the instrument type from the System Prefix table is used.

[Audited] [Supports versioning]

OLTP: Interchange_Prefix_OLTP

Element (type)	Description
pan_lgth *[bt_int16s]	Pan Length.
prfx *[bt_stringf(19)]	The prefix is the first n digits of a Primary Account Number (PAN) which defines the issuer of the PAN. A best match is used where the prefix with the most digits is preferred over a prefix with fewer digits. This field is left-justified (containing numeric characters, without any embedded spaces).
filler [bt_stringf(1)]	One byte filler.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, Amercian Express, MasterCard, etc.
iss_surch_prfl [prfl_def 1.0]	The Issuer Surcharge Profile. This allows Issuers to be grouped together in logical surcharging groups for Issuers that perform the same surcharging logic.

Interchange_Security (5.0) (isecd)

Interchange Security Data Source holds keys that interfaces use to exchange keys, process PINs, and perform message authentication.

[Audited] [Supports versioning]

OLTP: Interchange_Security_OLTP

Element (type)	Description
intf_nam [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pin_blk_typ [bt_char]	PIN Block Type - specifies the PIN block format of the PIN in the inbound external messages. Valid values are: 0 - Clear, PINs are not encrypted. 1 - ANSI PIN

Element (type)	Description
	block (ISO Format 0), default. 3 - PIN/Pad PIN block. 5 - ISO Format 1. 7 - DUKPT. 8 - ISO Format 3.
pin_pad_char [bt_char]	PIN Pad character used to pad the PIN block. Valid values are 0 - 9, A - F. Default is F.
old_key_timr_lmt [bt_int32s]	This field specifies the timer used for clearing old/previous KAM(s), KDT(s) and KPT(s). This field is displayed as seconds but written to disk as hundredths of seconds. Allowed values in seconds: 0 - 99999. Default is 30.
kkt_pt_variant [bt_char]	Encryption variant of the PIN key exchange key. Valid values are: 0 - Key Exchange Key Variant. 1 - PIN Encryption Key Variant. 5 - ATM Key Variant (applicable only for channel configuration). Default is 0.
kkt_am_variant [bt_char]	Encryption variant of the MAC key exchange key. Valid values are: 0 - Key Exchange Key Variant. 5 - ATM Key Variant. Default is 0.
outbnd_kpt1_keyx [keyx_trpl 1.0]	Outbound PIN Transport - Encrypted Key. Contains the PIN encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kpt1_vvk [vvk 1.0]	Outbound PIN Transport - Verification Value. Contains the verification value of the PIN key. The verification value is used to detect key synchronization errors.
outbnd_kpt2_keyx [keyx_trpl 1.0]	Outbound PIN Transport - Encrypted Key. Contains the PIN encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kpt2_vvk [vvk 1.0]	Outbound PIN Transport - Verification Value. Contains the verification value of the PIN key. The verification value is used to detect key synchronization errors.
outbnd_kpt_idx [key_idx 1.0]	The current outbound PIN key index. Indicates which outbound PIN key is currently being used. Valid values are: 1 - key 1 (default). 2 - key 2.
outbnd_u_kpt_cntr [bt_int32s]	Outbound PIN transport counter.
outbnd_old_pin_timr [timr_id 1.0]	The timer tag for the outbound PIN key.
outbnd_kam1_keyx [keyx_trpl 1.0]	Outbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kam1_vvk [vvk 1.0]	Outbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.

Element (type)	Description
outbnd_kam2_keyx [keyx_trpl 1.0]	Outbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kam2_vvk [vvk 1.0]	Outbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.
outbnd_kam_idx [key_idx 1.0]	The current outbound MAC key index. Indicates which outbound MAC key is currently being used. Valid values are: 1 - key 1 (default). 2 - key 2.
outbnd_u_kam_cnr [bt_int32s]	Outbound Message Authentication transport counter.
outbnd_old_mac_timr [timr_id 1.0]	The timer tag for the outbound MAC key.
inbnd_kpt1_keyx [keyx_trpl 1.0]	Inbound PIN Transport - Encrypted Key. Contains the PIN encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kpt1_vvk [vvk 1.0]	Inbound PIN Transport - Verification Value. Contains the verification value of the PIN key. The verification value is used to detect key synchronization errors.
inbnd_kpt2_keyx [keyx_trpl 1.0]	Inbound PIN Transport - Encrypted Key. Contains the PIN encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kpt2_vvk [vvk 1.0]	Inbound PIN Transport - Verification Value. Contains the verification value of the PIN key. The verification value is used to detect key synchronization errors.
inbnd_kpt_idx [key_idx 1.0]	The current inbound PIN key index. Indicates which inbound PIN key is currently being used. Valid values are: 1 - key 1 (default). 2 - key 2.
inbnd_u_kpt_cnr [bt_int32s]	Inbound PIN transport counter.
inbnd_old_pin_timr [timr_id 1.0]	The timer tag for the inbound PIN key.
inbnd_kam1_keyx [keyx_trpl 1.0]	Inbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).

Element (type)	Description
inbnd_kam1_vvk [vvk 1.0]	Inbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.
inbnd_kam2_keyx [keyx_trpl 1.0]	Inbound Message Authentication Transport - Encrypted Key. Contains the MAC key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kam2_vvk [vvk 1.0]	Inbound Message Authentication Transport - Verification Value. Contains the verification value of the MAC key. The verification value is used to detect key synchronization errors.
inbnd_kam_idx [key_idx 1.0]	The current inbound MAC key index. Indicates which inbound MAC key is currently being used. Valid values are: 1 - key 1 (default). 2 - key 2.
inbnd_u_kam_cntr [bt_int32s]	Inbound Message Authentication transport counter.
inbnd_old_mac_timr [timr_id 1.0]	The timer tag for the inbound MAC key.
kkt_pt_lgth [bt_char]	PIN key exchange key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
kkt_am_lgth [bt_char]	MAC key exchange key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
outbnd_kpt1_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
outbnd_kpt1_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kpt2_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
outbnd_kpt2_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kpt_lgth [bt_char]	PIN Encryption Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
outbnd_kam1_hdr [keyx_hdr 1.0]	Outbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kam1_kam [keyx_kam 1.0]	Outbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kam2_hdr [keyx_hdr 1.0]	Outbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kam2_kam [keyx_kam 1.0]	Outbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kam_lgth [bt_char]	Outbound Message Authentication Transport - Encrypted Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
inbnd_kpt1_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.

Element (type)	Description
inbnd_kpt1_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kpt2_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
inbnd_kpt2_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kpt_lgth [bt_char]	PIN Encryption Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
inbnd_kam1_hdr [keyx_hdr 1.0]	Inbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kam1_kam [keyx_kam 1.0]	Inbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kam2_hdr [keyx_hdr 1.0]	Inbound Message Authentication Transport - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kam2_kam [keyx_kam 1.0]	Inbound Message Authentication Transport - Encrypted Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kam_lgth [bt_char]	Inbound Message Authentication Transport - Encrypted Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
kam_typ [bt_int16s]	The type of Cipher Block Chaining (CBC) to use for MAC generation/verification. Valid values are: 0 - Single length DES Cipher Block Chaining. 1 - 3DES Cipher Block Chaining - uses both the left half and right half of the double length MAC key for all blocks of data (default) 2 - Pseudo 3DES Cipher Block Chaining - uses the left half of the double length MAC key for all blocks of data except the last block. The last data block is processed in a true 3DES operation using both the left and right half of the MAC key. 3 - Single DES Cipher Block Chaining w/ISO 9797-1 Method 2 Padding. 4 - 3DES Cipher Block Chaining w/ISO 9797-1 Method 2 Padding. 5 - AS2805.4.1 MAB output. 6 - AS2805.4.1 MAC output. 7 - Pseudo 3DES Cipher Block Chaining Method 2 Padding.
kkt_pt_import_hdr [keyx_hdr 1.0]	PIN key exchange key header required for the Atalla Key Block (AKB) format.
kkt_pt_import_keyx [keyx_trpl 1.0]	PIN Transport - Import Encryption Key. Contains the PIN key exchange key encrypted under the master key of the hardware security module. This key is used for importing PIN key exchange keys from another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_pt_import_kam [keyx_kam 1.0]	PIN key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_pt_import_vvk [vvk 1.0]	PIN Transport - Verification Value. Contains the verification value of the PIN import key exchange key. The verification value is used to detect key synchronization errors.
kkt_pt_export_hdr [keyx_hdr 1.0]	PIN key exchange key header required for the Atalla Key Block (AKB) format.

Element (type)	Description
kkt_pt_export_keyx [keyx_trpl 1.0]	PIN Transport - Export Encryption Key. Contains the PIN key exchange key encrypted under the master key of the hardware security module. This key is used for exporting PIN key exchange keys to another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_pt_export_kam [keyx_kam 1.0]	PIN key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_pt_export_vvk [vvk 1.0]	PIN Transport - Verification Value. Contains the verification value of the PIN export key exchange key. The verification value is used to detect key synchronization errors.
kkt_pt_key_opt [bt_int16s]	Indicates if separate import and export PIN KKTs are used or if the import PIN KKT is used for both import and export functions. Valid values are: 0 - Use import KKT for both import and export functions (default). 1 - Use separate KKTs for import and export functions.
kkt_am_import_hdr [keyx_hdr 1.0]	MAC key exchange key header required for the Atalla Key Block (AKB) format.
kkt_am_import_keyx [keyx_trpl 1.0]	Message Authentication Transport - Import Encryption Key. Contains the MAC key exchange key encrypted under the master key of the hardware security module. This key is used for importing a MAC key from another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_am_import_kam [keyx_kam 1.0]	MAC key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_am_import_vvk [vvk 1.0]	Message Authentication Transport - Verification Value. Contains the verification value of the MAC import key exchange key. The verification value is used to detect key synchronization errors.
kkt_am_export_hdr [keyx_hdr 1.0]	MAC key exchange key header required for the Atalla Key Block (AKB) format.
kkt_am_export_keyx [keyx_trpl 1.0]	Message Authentication Transport - Export Encryption Key. Contains the MAC key exchange key encrypted under the master key of the hardware security module. This key is used for exporting a MAC key from another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_am_export_kam [keyx_kam 1.0]	MAC key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_am_export_vvk [vvk 1.0]	Message Authentication Transport - Verification Value. Contains the verification value of the MAC export key exchange key. The verification value is used to detect key synchronization errors.

Element (type)	Description
kkt_am_key_opt [bt_int16s]	Indicates if separate import and export MAC KKTs are used or if the import MAC KKT is used for both import and export functions. Valid values are: 0 - Use import KKT for both import and export functions (default). 1 - Use separate KKTs for import and export functions.
extrn_key_blk_frmt [bt_char]	The format of the key block that an external entity (e.g., interface, device handler) supports. Valid values are: 0 - Standard Atalla (Atalla only)(default for Atalla). 1 - New Atalla Key Block (AKB) (Atalla only). 2 - ANSI X9.17 method (Racal only). 3 - Variant Method (Racal only) (default for Racal).
encrypt_data_typ [bt_char]	Data encryption data type. Valid values are: B - Binary. U - Unpacked ASCII hexadecimal(default).
encrypt_des_mde [bt_int16s]	Encryption mode for data encryption. Valid values are: 0 - ECB (Electronic Code Book) (default). 1 - CBC (Cipher Block Chaining). 2 - CFB-8 (Cipher Feedback, 8 bits). 3 - CFB-64 (Cipher Feedback, 64 bits). 4 - OFB-64 (Output Feedback, 64 bits). Valid values for EMV: 0 - ECB (default). 1 - CBC.
encrypt_layers [bt_int16s]	Levels of encryption to be performed for data encryption. Valid values are: 1 - One level (inner layer) (default). 2 - Two levels (inner and outer layers).
kkt_dt_import_hdr [keyx_hdr 1.0]	Data encryption key exchange key header required for the Atalla Key Block (AKB) format.
kkt_dt_import_keyx [keyx_trpl 1.0]	Data Encryption Transport - Import Encryption Key. Contains the data encryption key exchange key encrypted under the master key of the hardware security module. This key is used for importing data encryption key exchange keys from another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_dt_import_kam [keyx_kam 1.0]	Data encryption key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_dt_import_vvk [vvk 1.0]	Data Encryption Transport - Verification Value. Contains the verification value of the data encryption import key exchange key. The verification value is used to detect key synchronization errors.
kkt_dt_export_hdr [keyx_hdr 1.0]	Data encryption key exchange key header required for the Atalla Key Block (AKB) format.
kkt_dt_export_keyx [keyx_trpl 1.0]	Data Encryption Transport - Export Encryption Key. Contains the data encryption key exchange key encrypted under the master key of the hardware security module. This key is used for exporting data encryption key exchange keys from another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_dt_export_kam [keyx_kam 1.0]	Data encryption key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_dt_export_vvk [vvk 1.0]	Data Encryption Transport - Verification Value. Contains the verification value of the data encryption export key exchange key. The verification value is used to detect key synchronization errors.

Element (type)	Description
kkt_dt_key_opt [bt_int16s]	Indicates if separate import and export data encryption KKTs are used or if the import PIN KKT is used for both import and export functions. Valid values are: 0 - Use import KKT for both import and export functions (default). 1 - Use separate KKTs for import and export functions. 2 - Keys are not dynamic
kkt_dt_lgth [bt_char]	Data encryption key exchange key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
kkt_dt_variant [bt_char]	Encryption variant of the data encryption key exchange key. Valid values are: 0 - Key Exchange Key Variant. 2 - Data Encryption Key Variant. Default is 0.
inbnd_kdt1_lvl1_hdr [keyx_hdr 1.0]	Inbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl1_keyx [keyx_trpl 1.0]	Inbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kdt1_lvl1_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl1_vvk [vvk 1.0]	Inbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
inbnd_kdt1_lvl2_hdr [keyx_hdr 1.0]	Inbound Data Encryption (Level 2 / Outer Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl2_keyx [keyx_trpl 1.0]	Inbound Data Transport - Encrypted Key (Level 2 / Outer Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kdt1_lvl2_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kdt1_lvl2_vvk [vvk 1.0]	Inbound Data Encryption Authentication Transport - Verification Value (Level 2 / Outer Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
inbnd_kdt2_lvl1_hdr [keyx_hdr 1.0]	Inbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kdt2_lvl1_keyx [keyx_trpl 1.0]	Inbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).

Element (type)	Description
inbnd_kdt2_lvl1_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kdt2_lvl1_vvk [vvk 1.0]	Inbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
inbnd_kdt2_lvl2_hdr [keyx_hdr 1.0]	Inbound Data Encryption (Level 2 / Outer Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
inbnd_kdt2_lvl2_keyx [keyx_trpl 1.0]	Inbound Data Transport - Encrypted Key (Level 2 / Outer Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_kdt2_lvl2_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
inbnd_kdt2_lvl2_vvk [vvk 1.0]	Inbound Data Encryption Authentication Transport - Verification Value (Level 2 / Outer Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
inbnd_kdt_idx [bt_int16s]	The current inbound data encryption key index. Indicates which inbound data encryption key pair is currently being used. Valid values are: 1 - key pair 1 (default). 2 - key pair 2.
inbnd_old_data_timr [timr_id 1.0]	The timer tag for the inbound data encryption key.
outbnd_kdt1_lvl1_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl1_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt1_lvl1_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl1_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_kdt1_lvl2_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 2 / Outer Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl2_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 2 / Outer Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or

Element (type)	Description
	three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt1_lvl2_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kdt1_lvl2_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 2 / Outer Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_kdt2_lvl1_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 1 / Inner Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt2_lvl1_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 1 / Inner Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt2_lvl1_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kdt2_lvl1_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 1 / Inner Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_kdt2_lvl2_hdr [keyx_hdr 1.0]	Outbound Data Encryption (Level 2 / Outer Layer) - Encrypted Key header required for the Atalla Key Block (AKB) format.
outbnd_kdt2_lvl2_keyx [keyx_trpl 1.0]	Outbound Data Transport - Encrypted Key (Level 2 / Outer Layer). Contains the data encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kdt2_lvl2_kam [keyx_kam 1.0]	Data Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kdt2_lvl2_vvk [vvk 1.0]	Outbound Data Encryption Authentication Transport - Verification Value (Level 2 / Outer Layer). Contains the verification value of the data encryption key. The verification value is used to detect key synchronization errors.
outbnd_kdt_idx [bt_int16s]	The current outbound data encryption key index. Indicates which outbound data encryption key pair is currently being used. Valid values are: 1 - key pair 1 (default). 2 - key pair 2.
outbnd_old_data_timr [timr_id 1.0]	The timer tag for the outbound data encryption key.
outbnd_iv_hdr [keyx_hdr 1.0]	Initialization Vector header required for the Atalla Key Block (AKB) format.
outbnd_iv_keyx [keyx_trpl 1.0]	Initialization Vector. Contains the Initialization Vector encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16

Element (type)	Description
	bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_iv_kam [keyx_kam 1.0]	Initialization Vector MAC value required for the Atalla Key Block (AKB) format.
kam_lgth [bt_int16s]	Length of MAC to be returned from a call to a MAC generate function. Valid values are: 1 - 32 bits (default). 2 - 48 bits. 3 - 64 bits.
inbnd_iv_hdr [keyx_hdr 1.0]	Initialization Vector header required for the Atalla Key Block (AKB) format.
inbnd_iv_keyx [keyx_trpl 1.0]	Initialization Vector. Contains the Initialization Vector encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
inbnd_iv_kam [keyx_kam 1.0]	Initialization Vector MAC value required for the Atalla Key Block (AKB) format.
inbnd_kdt_lgth [bt_char]	Data Encryption Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
outbnd_kdt_lgth [bt_char]	Data Encryption Key length. Valid values are: 1 - Single (default). 2 - Double. 3 - Triple.
kkt_pt_mstr_hdr [keyx_hdr 1.0]	PIN key exchange key header required for the Atalla Key Block (AKB) format. Used as the highest level of the 3 - level Dutch Security key scheme.
kkt_pt_mstr_keyx [keyx_trpl 1.0]	PIN Transport - Export Encryption Key. Contains the PIN key exchange key encrypted under the master key of the hardware security module. This key is used for exporting PIN key exchange keys to another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes). Used as the highest level in the 3 - tier Dutch Security key scheme.
kkt_pt_mstr_kam [keyx_kam 1.0]	PIN key exchange key MAC value required for the Atalla Key Block (AKB) format. Used as the highest level in the 3 - tier Dutch Security key scheme
kkt_pt_mstr_vvk [vvk 1.0]	PIN Transport - Verification Value. Contains the verification value of the PIN export key exchange key. The verification value is used to detect key synchronization errors. Used as the highest level in the 3 - tier Dutch Security key scheme.
kkt_am_mstr_hdr [keyx_hdr 1.0]	MAC key exchange key header required for the Atalla Key Block (AKB) format. Used as the highest level in the 3 - tier Dutch Security key scheme
kkt_am_mstr_keyx [keyx_trpl 1.0]	Message Authentication Transport - Import Encryption Key. Contains the MAC key exchange key encrypted under the master key of the hardware security module. This key is used for importing a MAC key from another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes). Used as the highest level in the 3 - tier Dutch Security key scheme.

Element (type)	Description
kkt_am_mstr_kam [keyx_kam 1.0]	MAC key exchange key MAC value required for the Atalla Key Block (AKB) format. Used as the highest level in the 3 - tier Dutch Security key scheme.
kkt_am_mstr_vvk [vvk 1.0]	Message Authentication Transport - Verification Value. Contains the verification value of the MAC import key exchange key. The verification value is used to detect key synchronization errors. Used as the highest level in the 3 - tier Dutch Security key scheme.
inbnd_kam_key_typ [bt_int16s]	Indicates the type of key for the inbound MAC key. Only applicable for Thales AS2805 MACing. Valid values are: 0 - TAK (default). 1 - ZAK. 2 - ZAKr.
outbnd_kam_key_typ [bt_int16s]	Indicates the type of key for the outbound MAC key. Only applicable for Thales AS2805 MACing. Valid values are: 0 - TAK (default). 1 - ZAK. 2 - ZAKs.
inbnd_kdt_key_typ [bt_int16s]	Indicates the type of key for the inbound Data Encryption key. Only applicable for Thales AS2805 data encryption. Valid values are: 0 - ZEK (default). 1 - ZEKr
outbnd_kdt_key_typ [bt_int16s]	Indicates the type of key for the outbound Data Encryption key. Only applicable for Thales AS2805 data encryption. Valid values are: 0 - ZEK (default). 1 - ZEKs.
import_kkt_key_typ [bt_int16s]	Indicates the type of key for the import transport key (KKT). Only applicable for Thales AS2805 data encryption. Valid values are: 0 - KEKr, variant 0 (default). 1 - KEKr, variant 3.
export_kkt_key_typ [bt_int16s]	Indicates the type of key for the export transport key (KKT). Only applicable for Thales AS2805 data encryption. Valid values are: 0 - KEKs, variant 0 (default). 1 - KEKs, variant 4.
kkt_pt_import_old_hdr [keyx_hdr 1.0]	Pending inbound PIN KEK header.
kkt_pt_import_old_keyx [keyx_trpl 1.0]	Pending inbound PIN KEK key.
kkt_pt_import_old_kam [keyx_kam 1.0]	Pending inbound PIN KEK MAC
kkt_pt_import_old_vvk [vvk 1.0]	Pending inbound PIN KEK check digits.
kkt_am_import_old_hdr [keyx_hdr 1.0]	Pending inbound MAC KEK header.
kkt_am_import_old_keyx [keyx_trpl 1.0]	Pending inbound MAC KEK key.
kkt_am_import_old_kam [keyx_kam 1.0]	Pending inbound MAC KEK MAC
kkt_am_import_old_vvk [vvk 1.0]	Pending inbound MAC KEK check digits.
kkt_dt_import_old_hdr [keyx_hdr 1.0]	Pending inbound Data KEK header.
kkt_dt_import_old_keyx [keyx_trpl 1.0]	Pending inbound Data KEK key.
kkt_dt_import_old_kam [keyx_kam 1.0]	Pending inbound Data KEK MAC

Element (type)	Description
kkt_dt_import_old_vvk [vvk 1.0]	Pending inbound Data KEK check digits.
kkt_pt_export_old_hdr [keyx_hdr 1.0]	Pending outbound PIN KEK header.
kkt_pt_export_old_keyx [keyx_trpl 1.0]	Pending outbound PIN KEK key.
kkt_pt_export_old_kam [keyx_kam 1.0]	Pending outbound PIN KEK MAC
kkt_pt_export_old_vvk [vvk 1.0]	Pending outbound PIN KEK check digits.
kkt_am_export_old_hdr [keyx_hdr 1.0]	Pending outbound MAC KEK header.
kkt_am_export_old_keyx [keyx_trpl 1.0]	Pending outbound MAC KEK key.
kkt_am_export_old_kam [keyx_kam 1.0]	Pending outbound MAC KEK MAC
kkt_am_export_old_vvk [vvk 1.0]	Pending outbound MAC KEK check digits.
kkt_dt_export_old_hdr [keyx_hdr 1.0]	Pending outbound Data KEK header.
kkt_dt_export_old_keyx [keyx_trpl 1.0]	Pending outbound Data KEK key.
kkt_dt_export_old_kam [keyx_kam 1.0]	Pending outbound Data KEK MAC
kkt_dt_export_old_vvk [vvk 1.0]	Pending outbound Data KEK check digits.
input_key_typ [bt_int16s]	Indicates if a KEK or ZMK key should be used in the Thales AS2805 commands to generate and translate keys (Thales commands OI, OK, E0 and E2). Valid values are: 0 - ZMK (default) 1 - KEK (i.e., KEKs or KEKr)
zka_drv_flg [bt_int16s]	Flag indicating if ZKA key derivation is utilized by this channel. Valid values are: 0 = Channel does not use ZKA key derivation (default) 1 = Channel uses ZKA key derivation (This field is used for the German Security feature)
key_gen_num [bt_stringf(2)]	Key Generation Number (KGN) for the Derivation Key. (This field is used for the German Security feature)
key_ver_num [bt_stringf(2)]	Key Version Number (KVN) for the Derivation Key. (This field is used for the German Security feature)
key_table_num [bt_int16s DEFAULT 1]	Key Table Number (KTN) for the Derivation Key. Valid values are: 01 = Production (default) 02 = Emergency Production 03 = Test 04 = Emergency Test (This field is used for the German Security feature)
drv_depth [bt_int16s]	The derivation depth of the Derivation Key. Valid values are: 0 = Derivation Depth 0 (default) 1 = Derivation Depth 1 (This field is used for the German Security feature)
drv_id [bt_stringf(16)]	The derivation id. (This field is used for the German Security feature)

Element (type)	Description
key_hierarchy [bt_int16s DEFAULT 2]	Key Hierarchy. Valid values are: 2 two levels (default) 3 - three levels
kkt_opt [bt_int16s DEFAULT 1]	KKT Options. Valid values are: 0 separate KKTs 1 single KKT (default)

Interchange_Security_Future (1.0) (isecfd)

Interchange Security Future Keys Data Source holds future keys that interfaces will use at a later time to exchange keys, process PINs and perform message authentication.

[Audited] [Supports versioning]

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mstr1_export_futr_hdr [keyx_hdr 1.0]	Future Export Master KEK (tier 1/2) - Header. Only used with Atalla Key Block key format.
mstr1_export_futr_keyx [keyx_trpl 1.0]	Future Export Master KEK - key value
mstr1_export_futr_kam [keyx_kam 1.0]	Future Export Master KEK - MAC
mstr1_export_futr_vvk [vvk 1.0]	Future Export Master KEK - check digits
mstr1_import_futr_hdr [keyx_hdr 1.0]	Future Import Master KEK (tier 1/2) - Header. Only used with Atalla Key Block key format.
mstr1_import_futr_keyx [keyx_trpl 1.0]	Future Import Master KEK - key value
mstr1_import_futr_kam [keyx_kam 1.0]	Future Import Master KEK - MAC
mstr1_import_futr_vvk [vvk 1.0]	Future Import Master KEK - check digits
mstr1_import_kkt_pt_futr_hdr [keyx_hdr 1.0]	Future Import Master PIN KEK - Header. Only used with Atalla Key Block key format.
mstr1_import_kkt_pt_futr_keyx [keyx_trpl 1.0]	Future Import Master PIN KEK - key value
mstr1_import_kkt_pt_futr_kam [keyx_kam 1.0]	Future Import Master PIN KEK - MAC
mstr1_import_kkt_pt_futr_vvk [vvk 1.0]	Future Import Master PIN KEK - check digits
mstr1_import_kkt_am_futr_hdr [keyx_hdr 1.0]	Future Import Master MAC KEK - Header. Only used with Atalla Key Block key format.
mstr1_import_kkt_am_futr_keyx [keyx_trpl 1.0]	Future Import Master MAC KEK - key value
mstr1_import_kkt_am_futr_kam [keyx_kam 1.0]	Future Import Master MAC KEK - MAC
mstr1_import_kkt_am_futr_vvk [vvk 1.0]	Future Import Master MAC KEK - check digits
mstr1_import_kkt_dt_futr_hdr [keyx_hdr 1.0]	Future Import Master Data KEK - Header. Only used with Atalla Key Block key format.
mstr1_import_kkt_dt_futr_keyx [keyx_trpl 1.0]	Future Import Master Data KEK - key value

Element (type)	Description
mstr1_import_kkt_dt_futr_kam [keyx_kam 1.0]	Future Import Master Data KEK - MAC
mstr1_import_kkt_dt_futr_vvk [vvk 1.0]	Future Import Master Data KEK - check digits
kkt_pt_export_futr_hdr [keyx_hdr 1.0]	Future Export PIN KEK (tier 2/3 or tier 1/2) - header
kkt_pt_export_futr_keyx [keyx_trpl 1.0]	Future Export PIN KEK - key value
kkt_pt_export_futr_kam [keyx_kam 1.0]	Future Export PIN KEK - MAC
kkt_pt_export_futr_vvk [vvk 1.0]	Future Export PIN KEK - check digits
kkt_pt_import_futr_hdr [keyx_hdr 1.0]	Future Import PIN KEK - header
kkt_pt_import_futr_keyx [keyx_trpl 1.0]	Future Import PIN KEK - key value
kkt_pt_import_futr_kam [keyx_kam 1.0]	Future Import PIN KEK - MAC
kkt_pt_import_futr_vvk [vvk 1.0]	Future Import PIN KEK - check digits
kkt_am_export_futr_hdr [keyx_hdr 1.0]	Future Export MAC KEK (tier 2/3 or tier 1/2) - header
kkt_am_export_futr_keyx [keyx_trpl 1.0]	Future Export MAC KEK - key value
kkt_am_export_futr_kam [keyx_kam 1.0]	Future Export MAC KEK - MAC
kkt_am_export_futr_vvk [vvk 1.0]	Future Export MAC KEK - check digits
kkt_am_import_futr_hdr [keyx_hdr 1.0]	Future Import MAC KEK - header
kkt_am_import_futr_keyx [keyx_trpl 1.0]	Future Import MAC KEK - key value
kkt_am_import_futr_kam [keyx_kam 1.0]	Future Import MAC KEK - MAC
kkt_am_import_futr_vvk [vvk 1.0]	Future Import MAC KEK - check digits
kkt_dt_export_futr_hdr [keyx_hdr 1.0]	Future Export Data KEK (tier 2/3 or tier 1/2) - header
kkt_dt_export_futr_keyx [keyx_trpl 1.0]	Future Export Data KEK - key value
kkt_dt_export_futr_kam [keyx_kam 1.0]	Future Export Data KEK - MAC
kkt_dt_export_futr_vvk [vvk 1.0]	Future Export Data KEK - check digits
kkt_dt_import_futr_hdr [keyx_hdr 1.0]	Future Import Data KEK - header
kkt_dt_import_futr_keyx [keyx_trpl 1.0]	Future Import Data KEK - key value
kkt_dt_import_futr_kam [keyx_kam 1.0]	Future Import Data KEK - MAC
kkt_dt_import_futr_vvk [vvk 1.0]	Future Import Data KEK - check digits
inbnd_kpt_futr_hdr [keyx_hdr 1.0]	Future Inbound PIN Encryption (lowest tier, 2nd or 3rd) header. Only used with Atalla Key Block key format.
inbnd_kpt_futr_keyx [keyx_trpl 1.0]	Future Inbound PIN Encryption key value.
inbnd_kpt_futr_kam [keyx_kam 1.0]	Future Inbound PIN Encryption MAC.
inbnd_kpt_futr_vvk [vvk 1.0]	Future Inbound PIN Encryption check digits.
outbnd_kpt_futr_hdr [keyx_hdr 1.0]	Future Outbound PIN Encryption header. Only used with Atalla Key Block key format.
outbnd_kpt_futr_keyx [keyx_trpl 1.0]	Future Outbound PIN Encryption key value.
outbnd_kpt_futr_kam [keyx_kam 1.0]	Future Outbound PIN Encryption MAC.
outbnd_kpt_futr_vvk [vvk 1.0]	Future Outbound PIN Encryption check digits.

Element (type)	Description
inbnd_kam_futr_hdr [keyx_hdr 1.0]	Future Inbound MAC Encryption (lowest tier, 2nd or 3rd) header. Only used with Atalla Key Block key format.
inbnd_kam_futr_keyx [keyx_trpl 1.0]	Future Inbound MAC Encryption key value.
inbnd_kam_futr_kam [keyx_kam 1.0]	Future Inbound MAC Encryption MAC.
inbnd_kam_futr_vvk [vvk 1.0]	Future Inbound MAC Encryption check digits.
outbnd_kam_futr_hdr [keyx_hdr 1.0]	Future Outbound MAC Encryption header. Only used with Atalla Key Block key format.
outbnd_kam_futr_keyx [keyx_trpl 1.0]	Future Outbound MAC Encryption key value.
outbnd_kam_futr_kam [keyx_kam 1.0]	Future Outbound MAC Encryption MAC.
outbnd_kam_futr_vvk [vvk 1.0]	Future Outbound MAC Encryption check digits.
inbnd_kdt_lvl1_futr_hdr [keyx_hdr 1.0]	Future Inbound Data Encryption (Level 1/Inner Level) header. Lowest tier, 2nd or 3rd. Only used with Atalla Key Block key format.
inbnd_kdt_lvl1_futr_keyx [keyx_trpl 1.0]	Future Inbound Data Encryption (Level 1/Inner Level) key value.
inbnd_kdt_lvl1_futr_kam [keyx_kam 1.0]	Future Inbound Data Encryption (Level 1/Inner Level) MAC.
inbnd_kdt_lvl1_futr_vvk [vvk 1.0]	Future Inbound Data Encryption (Level 1/Inner Level) check digits.
inbnd_kdt_lvl2_futr_hdr [keyx_hdr 1.0]	Future Inbound Data Encryption (Level 2/Outer Level) header. Only used with Atalla Key Block key format.
inbnd_kdt_lvl2_futr_keyx [keyx_trpl 1.0]	Future Inbound Data Encryption (Level 2/Outer Level) key value.
inbnd_kdt_lvl2_futr_kam [keyx_kam 1.0]	Future Inbound Data Encryption (Level 2/Outer Level) MAC.
inbnd_kdt_lvl2_futr_vvk [vvk 1.0]	Future Inbound Data Encryption (Level 2/Outer Level) check digits.
outbnd_kdt_lvl1_futr_hdr [keyx_hdr 1.0]	Future Outbound Data Encryption (Level 1/Inner Level) header. Only used with Atalla Key Block key format.
outbnd_kdt_lvl1_futr_keyx [keyx_trpl 1.0]	Future Outbound Data Encryption (Level 1/Inner Level) key value.
outbnd_kdt_lvl1_futr_kam [keyx_kam 1.0]	Future Outbound Data Encryption (Level 1/Inner Level) MAC.
outbnd_kdt_lvl1_futr_vvk [vvk 1.0]	Future Outbound Data Encryption (Level 1/Inner Level) check digits.
outbnd_kdt_lvl2_futr_hdr [keyx_hdr 1.0]	Future Outbound Data Encryption (Level 2/Outer Level) header. Only used with Atalla Key Block key format.
outbnd_kdt_lvl2_futr_keyx [keyx_trpl 1.0]	Future Outbound Data Encryption (Level 2/Outer Level) key value.
outbnd_kdt_lvl2_futr_kam [keyx_kam 1.0]	Future Outbound Data Encryption (Level 2/Outer Level) MAC.
outbnd_kdt_lvl2_futr_vvk [vvk 1.0]	Future Outbound Data Encryption (Level 2/Outer Level) check digits.

Interface (5.0) (intfd)

The Interface table contains one record for each interface in the system.

[Audited] [Supports versioning]

OLTP: Interface_OLTP

Element (type)	Description
cmpnt_id* [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
swi_setl_hour [bt_int16s]	Interchange settlement and cutover information used for the end of period processing. Local hour of switch settlement. Valid values are: 0 to 23. Default value is 0.
swi_setl_min [bt_int16s]	Interchange settlement and cutover information used for the end of period processing. Local minute of switch settlement. Valid values are: 0 to 59. Default value is 0.
swi_setl_day [bt_char]	Interchange settlement and cutover information used for the end of period processing. This field contains an indication of the number of days on which the switch settles during a given week. Valid values are: 0 - No weekends (process 5 days), 1 - 7 day processing. Default value is 1. If no weekends, holidays are also excluded.
hol_dat1 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat2 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat3 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat4 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat5 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat6 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat7 [yyyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.

Element (type)	Description
hol_dat8 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat9 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat10 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat11 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat12 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat13 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat14 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat15 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
hol_dat16 [yyyymmdd 1.0]	A holiday date (YYYYMMDD) which is used when seven day processing is not used to specify additional dates which should not be processed. Value of spaces indicates no date. Holiday dates must be in the order they occur.
msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
act_cde_prfl [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acq_rte_prfl [prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
acq_txn_prfl [prfl_def 1.0]	The transaction profile for the acquirer who acquired the transaction. The acquirer transaction profile allows one or more acquirers to share processing code definitions and transactions allowed information. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
acq_surch_prfl [prfl_def 1.0]	The Acquirer Surcharge Profile. This allows acquirers to be grouped together in logical surcharging groups for acquirers that perform the same surcharging logic.
inbnd_auth_rqst_tim_lmt [bt_int16s]	The time limit in seconds to wait for a transaction response for an authorization request. Valid values are 1 to 9999. Defalut value is 15 seconds.
bal_opt_info [bt_int16s]	The balance information an acquirer will return on all transactions when the issuer balance information option is no preference. Valid values are: 1 = Ledger Balance Only, 2 = Available Balance or Available Credit Only, 0 = Both Ledger and Available. Default value is 0.
dflt_crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217. Used only if the currency code has not already been set from the external message.
dflt_acq_id_cde [bt_stringf(11)]	A code identifying the acquiring institution or its agent. This code is used only if the institution identifier code has not already been set from the external message.
dflt_acq_cntry_cde [bt_int16s]	The numeric country code of the acquirer as defined in ISO document 4217. This code is used only if the country code has not already been set from the external message.
dflt_crd_accpt_bus_cde [bt_int16s]	The card acceptor business code pertaining to the merchants line of business. This field is 4 numeric digits. This card acceptor business code is used only if the card acceptor business code has not already been set from the external message.
dflt_mrch_id [bt_stringf(15)]	The merchant identifier which defines the card acceptor. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Used only if the merchant identifier has not already been set from the external message. The default value is spaces.
dflt_term_id [bt_stringf(16)]	The identifier for the channel. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Used only if the channel identifier has not already been set from the external message. The default value is spaces.
dflt_pre_auth_hold_incr [bt_char]	The unit of time to retain the authorization hold if not specified in the external message. Valid values are: 1 - days, 2 - hours, 3 - minutes. Default value is 3. Used only if the pre-authorization hold time has not already been set from the external message for a pre-authorization request.
dflt_pre_auth_hold_tim [bt_stringf(2)]	Default time limit to hold a pre-authorization transaction. The value in this element is used when a time limit is not specified in the external message. The value specified corresponds to units of time defined in the PRE_AUTH_HOLD_INCR element. Valid values are: 00 - 99. Default value is 00.
iss_txn_prfl [bt_stringf(16)]	The transaction profile for the issuer to which the customer belongs. The issuer transaction profile allows one of more issuers to share processing code definitions and transactions allowed information. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ctx_prfl [bt_stringf(16)]	The context profile of the client attempting to store or retrieve context. This field is left-justified, upper case (containing any combination of alpha-numeric and special characters, but without any embedded spaces).
outbnd_auth_rqst_tim_lmt [bt_int16s]	The time limit in seconds to wait for a transaction response for an authorization request. Valid values are 1 to 9999. Defalut value is 15 seconds.

Element (type)	Description
min_outbnd_auth_rqst_tim [bt_int16s]	The minimum time limit in seconds than an authorization request can take. If less time is left, the transaction is re-routed to someone else. Valid values are 1 to 9999. Defalut value is 1 second.
queue_tim_lmt [bt_int16s]	The time limit in hundredths of seconds that a message may be queued to a resource before being returned undelivered. Valid values are 0 to 9900. 0 waits indefinitely. Default value is 500 hundredths of a second (5 seconds).
dflt_rfrl_phn_num [phn_num 1.0]	The phone number to use when an action code of referral is returned. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Used only if the referral phone number has not already been set from the external message when processing a response with a referral.
frwd_id_cde [bt_stringf(11)]	A code identifying the forwarding institution or its agent. This code is used when forwarding a request to an interface.
frwd_cntry_cde [bt_int16s]	The numeric country code of the forwarding institution as defined in ISO document 4217. This code is used only if the forwarding institution is set.
crncy_conv_fee_nam [bt_stringf(16)]	Fee name used to locate an entry in the Fee Table for the issuer interface currency conversion fee. (future use)
dflt_captr_mde [bt_stringf(1)]	This field indicates the default capture mode if it can not be determined from the external message. Valid values are: 0 - Authorize Only. 1 - Authorize and Capture.
proc_cde_prfl [bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
swi_tim_zone_diff [bt_int16s]	The time zone difference is the number of minutes between the time zone the network is located in and the time zone the BASE24-eps server is located.
send_unmatched_rvsl [bt_flag]	Indicates whether the interface sends unmatched reversals. Valid values are: 1 - does send unmatched reversals, 0 - does not send unmatched reversals.

Interface_FPS (2.0) (fpsid)

The FPS Interface Configuration data source contains one record for each FPS interface instance, and holds FPS-specific interface data.

[Audited] [Supports versioning]

OLTP: Interface_FPS_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
rcv_bnk_id [bt_stringf(4)]	Bank ID of the default receiving bank, to be used if the Bank ID is not supplied in inbound Faster Payments messages from the CI.
fps_q_enable [bt_flag]	Indicates if this instance of the FPS Interface can queue outbound payment messages, if the payment transaction indicates it should be queued (i.e., is to be processed asynchronously by the Gateway). If true then the payment will be queued to the appropriate SAF assign (debit or credit). Otherwise, the payment will be re-routed if the payment cannot be processed synchronously.
dup_detect_flg [bt_flag]	Duplicate detection flag. If set to True, then enhanced FPS duplicate detection, using the FPID History data source, is performed. Default is True, perform enhanced duplicate detection.
dup_flr_lmt [bt_int64s]	The floor limit for enhanced duplicate detection. Payments greater than or equal to this amount will be subject to enhanced duplicate checking by the interface. Otherwise, no duplicate detection will be performed. Default is 0, check all payments for duplicates.
dup_crncy_cde [bt_int16s]	The numeric currency code of the duplicate detection floor limit for this interface. Default is 826 (UK Sterling).
fpid_hist_asgn_1 [bt_stringf(16)]	Assign name of the FPID History data source configured for the specified day number.
fpid_hist_asgn_2 [bt_stringf(16)]	Assign name of the FPID History data source configured for the specified day number.
fpid_hist_asgn_3 [bt_stringf(16)]	Assign name of the FPID History data source configured for the specified day number.
fpid_hist_asgn_4 [bt_stringf(16)]	Assign name of the FPID History data source configured for the specified day number.
fpid_hist_asgn_5 [bt_stringf(16)]	Assign name of the FPID History data source configured for the specified day number.
fpid_hist_asgn_6 [bt_stringf(16)]	Assign name of the FPID History data source configured for the specified day number.
fpid_hist_asgn_7 [bt_stringf(16)]	Assign name of the FPID History data source configured for the specified day number.
repeat_window [bt_int16s]	The number of seconds the interface will continue to send repeats for.

Interface_Manager (8.0) (ifmgrd)

Interface Manager Data Source, used to store status and performance information for interfaces. It contains one record for each interface defined in the system. The record is updated during online transaction processing.

[Not Audited] [Supports versioning]

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
cmpnt_id [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
max_outstnd_rqst_lmt [bt_int16s]	The maximum number of requests that may be outstanding at a time for the configured entity (interface or station). An interfaces maximum outstanding may be greater than or less than the cumulative stations that belong to the interface. Valid values are: 0 - 9999. Default value is 1000 for interfaces and 100 for stations.
thrhd_outstnd_rqst [bt_int16s]	The threshold outstanding requests limit indicates the point at which the threshold floor limit is applied to transactions outbound to the Host/Switch. This limit must be less than or equal to maximum outstanding request limit. Valid values are: 0 - 9999. Default value is 1000.
thrhd_flr_lmt [bt_int64s]	The threshold floor limit is the amount to which the transaction amount is compared when the threshold outstanding request limit is reached. If the transaction amount is greater than the threshold floor limit, a request is sent if the outstanding count is less than the maximum outstanding request limit. If the transaction amount is less than the threshold floor limit or the maximum outstanding request limit is reached, the transaction is re-routed. Default value is 0.
nmm_enbl_flg [bt_flag]	Flag indicating whether network management messages are enabled or disabled. Valid values are: 0 - Network management messages are disabled, 1 - Network management messages are enabled. Default value is 1.
logon_sppt [bt_flag]	Logon support flag. Valid values are 0 - logon/logoff messages are not supported, 1 - logon/logoff messages are supported. Default value is 1.
nmm_timr_lmt [timr_lmt 1.0]	The number of seconds to wait for a response after transmitting a Network Management Request, including but not limited to Signon, Logon or Echo-Test, to the Host or Interchange. Valid values are: 1 - 9999. Default value is 30.
xnmm_timr_lmt [timr_lmt 1.0]	The number of seconds to wait before sending a network management message after a station is marked down or a network management request has timed out. Valid values are: 1 - 9999. Default is 60 seconds.
wft_timr_lmt [timr_lmt 1.0]	The number of seconds to wait for traffic to ensure the link is up before initiating an echo-test. Valid values are: 1- 9999. Default value is 120.
ovrld_timr_lmt [timr_lmt 1.0]	The overload time limit is the number of seconds to wait when max outstanding requests has been reached before sending any new requests. Valid values are: 1 - 9999. Default value is 30.
max_cnsc_sta_tmout_lmt [bt_int16s]	The maximum number of consecutive non-network messages that are allowed to timeout before the station is marked down. Valid values are: 0-9999. Default value is 0. 0 means no limit, the station is never marked down due to consecutive timeouts.
logon_typ [bt_int16s]	The logon type supported by the interface. A logon type of interface indicates that a single logon message logs on all stations belonging to the interface. A logon type of station indicates that the logon applies only for that station. Separate indicates that both an acquirer and issuer logon are required. Valid values are: 1 = Interface Combined, 2 = Interface Separate, 3 = Station. Default value is 1.

Element (type)	Description
key_mgmt_typ [bt_int16s]	Key Management Type. Valid values are: 0 = None, 1 = Master, 2 = Secondary, 3 = Co-Network. Default value is 0.
key_cnt_flg [bt_int16s]	Key Count Flag, indicates the number of keys supported by this interface. Valid values are: 1 = Combined Keys (inbound and outbound are equal), 2 = Separate Keys (one inbound key and one outbound key). Default is 1.
kpt_timr_lmt [bt_int32s]	PIN Key Timer Limit indicates the amount of time in minutes to use the current PIN Key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of seconds.
max_kpt_txn_cnt [bt_int32s]	The number of PIN Key transactions that are allowed before requesting a new key. Valid values are 0 to 99999. 0 indicates no transaction count limit is used. Default value is 0.
max_kpt_err_cnt [bt_int16s]	The number of PIN key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no error count limit is used. Default value is 0.
kam_timr_lmt [bt_int32s]	MAC Key Timer Limit indicates the amount of time in minutes to use the current MAC key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of seconds.
max_kam_txn_cnt [bt_int32s]	The number of MAC generations/verifications that are allowed before requesting a new key. Valid values are 0 to 99999. 0 indicates no transaction count limit is used. Default value is 0.
max_kam_err_cnt [bt_int16s]	The number of MAC key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no error count limit is used. Default value is 0.
num_iss_sta_avail [bt_int16s]	Indicates the number of issuer stations that are up and logged on. This field is no longer used in Interface Manager Table.
last_seq_num [bt_int32s]	The last sequence number of the message sent to an Interface. Reset to 1 after 999,999.
acq_logon_st [bt_int16s]	The acquirer logon state. Valid values are: 1 = logged on, 2 = logging on, 3 = logged off, 4 = logging off. Default value is 3.
iss_logon_st [bt_int16s]	The issuer logon state. Valid values are: 1 = logged on, 2 = logging on, 3 = logged off, 4 = logging off. Default value is 3.
iss_timr_typ [bt_int16s]	The issuer timer type. Valid values are: 0 = None, 1 = NMM Issuer Logon, 2 = XNMM Issuer Logon, 3 = NMM Issuer Logoff, 4 = XNMM Issuer Logoff, 5 = NMM Both Logon, 6 = XNMM Both Logon, 7 = NMM Both Logoff, 8 = XNMM Both Logoff
iss_timr_id [timr_id 1.0]	The issuer timer identifier used to cancel a timer.
acq_timr_typ [bt_int16s]	Acquirer timer type. Valid values are: 0 = None, 1 = NMM Acquirer Logon, 2 = XNMM Acquirer Logon, 3 = NMM Acquirer Logoff, 4 = XNMM Acquirer Logoff
acq_timr_id [timr_id 1.0]	Acquirer timer identifier used to cancel a timer.
kpt_out_ts [timestamp 1.0]	Timestamp of the last successful exchange of the PIN Key Outbound.
kpt_out_txn_cnt [bt_int32s]	PIN Key Outbound Transaction Count. Counter identifying the number of transactions processed which used the outbound PIN key.

Element (type)	Description
kpt_out_err_cnt [bt_int16s]	PIN Key Outbound Error Count. Counter identifying the number of error transactions processed which used the outbound PIN key.
kpt_in_ts [timestamp 1.0]	Timestamp of the last successful exchange of the PIN Key Inbound.
kpt_in_txn_cnt [bt_int32s]	PIN Key Inbound Transaction Count. Counter identifying the number of transactions processed which used the inbound PIN key.
kpt_in_err_cnt [bt_int16s]	PIN Key Inbound Error Count. Counter identifying the number of error transactions processed which used the inbound PIN key.
kpt_chng_out_timr_typ [bt_int16s]	PIN Key Change Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kpt_chng_out_timr_id [timr_id 1.0]	PIN Key Change Outbound Timer Identifier. Used to cancel a timer.
kpt_chng_in_timr_typ [bt_int16s]	PIN Key Change Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kpt_chng_in_timr_id [timr_id 1.0]	PIN Key Change Inbound Timer Identifier. Used to cancel a timer.
kpt_rpt_out_timr_typ [bt_int16s]	PIN Key Repeat Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kpt_rpt_out_timr_id [timr_id 1.0]	PIN Key Repeat Outbound Timer Identifier. Used to cancel a timer.
kpt_rpt_in_timr_typ [bt_int16s]	PIN Key Repeat Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kpt_rpt_in_timr_id [timr_id 1.0]	PIN Key Repeat Inbound Timer Identifier. Used to cancel a timer.
kpt_vrfy_out_timr_typ [bt_int16s]	PIN Key Verify Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kpt_vrfy_out_timr_id [timr_id 1.0]	PIN Key Verify Outbound Timer Identifier. Used to cancel a timer.
kpt_vrfy_in_timr_typ [bt_int16s]	PIN Key Verify Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kpt_vrfy_in_timr_id [timr_id 1.0]	PIN Key Verify Inbound Timer Identifier. Used to cancel a timer.
kam_out_ts [timestamp 1.0]	Timestamp of the last successful exchange of the MAC Key Outbound.
kam_out_txn_cnt [bt_int32s]	MAC Key Outbound Transaction Count. Counter identifying the number of transactions processed which used the inbound MAC key.
kam_out_err_cnt [bt_int16s]	MAC Key Outbound Error Count. Counter identifying the number of error transactions processed which used the outbound MAC key.
kam_in_ts [timestamp 1.0]	Timestamp of the last successful exchange of the MAC Key Inbound.
kam_in_txn_cnt [bt_int32s]	MAC Key Inbound Transaction Count. Counter identifying the number of transactions processed which used the inbound MAC key.
kam_in_err_cnt [bt_int16s]	MAC Key Inbound Error Count. Counter identifying the number of error transactions processed which used the inbound MAC key.
kam_chng_out_timr_typ [bt_int16s]	MAC Key Change Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM
kam_chng_out_timr_id [timr_id 1.0]	MAC Key Change Outbound Timer Identifier. Used to cancel a timer.

Element (type)	Description
kam_chng_in_timr_typ [bt_int16s]	MAC Key Change Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM
kam_chng_in_timr_id [timr_id 1.0]	MAC Key Change Inbound Timer Identifier. Used to cancel a timer.
kam_rpt_out_timr_typ [bt_int16s]	MAC Key Repeat Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM
kam_rpt_out_timr_id [timr_id 1.0]	MAC Key Repeat Outbound Timer Identifier. Used to cancel a timer.
kam_rpt_in_timr_typ [bt_int16s]	MAC Key Repeat Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM
kam_rpt_in_timr_id [timr_id 1.0]	MAC Key Repeat Inbound Timer Identifier. Used to cancel a timer.
kam_vrfy_out_timr_typ [bt_int16s]	MAC Key Verify Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM
kam_vrfy_out_timr_id [timr_id 1.0]	MAC Key Verify Outbound Timer Identifier. Used to cancel a timer.
kam_vrfy_in_timr_typ [bt_int16s]	MAC Key Verify Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM
kam_vrfy_in_timr_id [timr_id 1.0]	MAC Key Verify Inbound Timer Identifier. Used to cancel a timer.
perf_ts [timestamp 1.0]	Timestamp of when the performance statistics were last reset.
perf_ext_cnt [bt_int32s]	The number of transaction requests sent external included in the performance statistics.
perf_ext_auth_tim [bt_int64s]	The accumulative number of hundredths of seconds it took before an issuer receives a response for the requests sent external included in the performance statistics.
perf_ext_apprv_cnt [bt_int32s]	The number of transactions approved by an external issuer included in the performance statistics.
perf_ext_bad_pin_cnt [bt_int32s]	The number of transactions denied due to a bad pin by an external issuer included in the performance statistics.
perf_ext_key_sync_cnt [bt_int32s]	The number of transactions denied due to a key sync error by an external issuer included in the performance statistics.
perf_ext_deny_cnt [bt_int32s]	The number of transactions denied due to any other error by an external issuer included in the performance statistics.
perf_ext_tmout_cnt [bt_int32s]	The number of transactions which have timed out by an external issuer included in the performance statistics.
perf_int_cnt [bt_int32s]	The number of transaction requests received and a response was sent included in the performance statistics.
perf_int_ttl_tim [bt_int64s]	The accumulative number of hundredths of seconds it took before an acquirer sends a response included in the performance statistics.
perf_int_auth_tim [bt_int64s]	The accumulative number of hundredths of seconds it took before an acquirer sends a response minus any external time due to authorization by an external issuer included in the performance statistics.
perf_int_apprv_cnt [bt_int32s]	The number of acquired transactions that are approved and included in the performance statistics.

Element (type)	Description
perf_int_bad_pin_cnt [bt_int32s]	The number of acquired transactions that are denied due to a bad PIN and included in the performance statistics.
perf_int_key_sync_cnt [bt_int32s]	The number of acquired transactions that are denied due to a key sync error and included in the performance statistics.
perf_int_deny_cnt [bt_int32s]	The number of acquired transactions that are denied due to an other error and included in the performance statistics.
saf_asgn_nam [bt_stringf(32)]	The Store and Forward (SAF) assign name used to map to a physical location for adding SAF records. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). This field is no longer used in Interface Manager Table.
saf_outstnd_asgn_nam [bt_stringf(32)]	The Store and Forward (SAF) outstanding assign name used to map to a physical location for SAF records which have been sent. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). This field is obsolete and no longer used.
max_saf_outstnd_lmt [bt_int16s]	The maximum number of Store and Forward (SAF) records that can be outstanding at a time. Valid values are 1 - 9999. Default value is 1. This field is no longer used in Interface Manager Table.
saf_timr_lmt [timr_lmt 1.0]	Store and Forward (SAF) Timer Limit, indicates the number of seconds to wait for a response after transmitting a SAF record. Valid values are: 1 - 9999, 60=Default. This field is no longer used in Interface Manager Table.
max_saf_retries_lmt [bt_int16s]	The maximum number of times a Store and Forward (SAF) record will be resent before the record is deleted. Valid values are 0 to 999. A value of 0 indicates an infinite number of tries. Default value is 3. This field is no longer used in Interface Manager Table.
last_seq_num_updt_intrvl [bt_int32s]	The last sequence number update interval is the number of transactions that may be generated before reserving a new batch of sequence numbers for the process to use. When a new batch of sequence numbers is reserved, the last_seq_num field is updated by the last_seq_num_updt_intrvl on disk. The process then keeps a local sequence number it increments. Valid values are 0 to 99,999. Default value is 100. A value of 0 indicates to never increment the last_seq_num.
key_usage_updt_intrvl [bt_int32s]	The number of keys to use before updating the disk record with the key counts. Valid values are 0 to 999. Default value is 100. A value of 0 indicates to never increment the key counters.
saf_delay_timr_lmt [timr_lmt 1.0]	Store and Forward (SAF) Timer Limit, indicates the number of seconds to wait to check whether records exist in the SAF waiting to be sent. Valid values are: 1 - 9999, 300=Default. This field is no longer used in Interface Manager Table.
saf_delay_timr_id [timr_id 1.0]	SAF Delay Timer Identifier. Used to cancel a timer. This field is obsolete and no longer used.
auto_logon_flg [bt_flag]	A flag indicating whether to send a logon during startup. Valid values are: 1 - initiate a logon automatically during startup, 0 - Do not initiate a logon automatically during startup. Default value is 0.
trk_outstnd_cnt_flg [bt_flag]	A flag indicating whether to keep track of outstanding counts and perform velocity checks for maximum outstanding financial and maximum SAF

Element (type)	Description
	outstanding requests. Valid values are: 1 - keep track of outstanding counts, 0 - Do not keep track of outstanding counts. Default value is 0.
rec_read_intrvl [bt_int32s]	The number of transactions that may be processed without reading the actual record using values in memory for number of issuer stations available. Valid values are 0 to 999. Default value is 100. A value of 0 indicates to never use this interval. At least one of the interval fields must be non-zero. This field is no longer used in Interface Manager Table.
perf_stat_updt_intrvl [bt_int32s]	The number of transaction responses for which statistics are accumulated before performance statistics are updated. Valid values are 0 to 9999. Default value is 100. A value of 0 indicates to never update the performance statistics.
perf_saf_cnt [bt_int32s]	The number of Store and Forward requests sent external included in the performance statistics, excluding repeats. This field is no longer used in Interface Manager Table.
perf_saf_tim [bt_int64s]	The accumulative number of hundredths of seconds it took between adding a Store and Forward record and the time it took to send the record, excluding repeats. This represents the staging time from adding the SAF to getting it sent out. This field is no longer used in Interface Manager Table.
perf_saf_tim_max [bt_int32s]	The maximum number of hundredths of seconds it took between adding a Store and Forward record and the time it took to send the record, excluding repeats. This represents the staging time from adding the SAF to getting it sent out. This field is no longer used in Interface Manager Table.
swi_setl_timr_id [bt_binary(34)]	The switch settlement timer identifier used to cancel a timer.
last_swi_setl_dat [bt_string(8)]	The last switch settlement date. YYYYMMDD
shrg_netwrk_cnct [bt_flag]	Indicates if the interface is sharing a network connection across sites (0 - is not sharing, 1 - is sharing).
saf_rec_cnt [bt_int32s]	The number of records currently in the SAF file.
saf_max_rec_cnt [bt_int32s]	Maximum record count of all SAF files for an interface.
saf_max_pcmt_full [bt_int16s]	The maximum percent full for accepting new records. Once reached the SAF file will be put into Forward Only mode.
saf_nrml_pcmt_full [bt_int16s]	The percent full at which new records may be added. When this threshold is reached by clearing records from the SAF file, new transactions may be added and the system will resume operating in normal Store and Forward Mode.
saf_pcmt_full_warning [bt_int16s]	The percent full of the SAF file at which we will begin issuing warning messages.
saf_pcmt_full_err [bt_int16s]	The percent full of the SAF file at which we will begin issuing error messages
saf_mde [bt_int16s DEFAULT 1]	SAF processing mode. Valid values are: 1 - normal, 2 - Forward Only, set by interface, 3 - Forward Only manual (set by operator using Process Control). Default value is 1.
saf_rate [bt_int16s DEFAULT 1]	SAF processing rate. Valid values are: 0 - stop, 1 - normal/fast, 2 - slow (set by interface), 3 - slow manual (set by operator using Process Control). Default value is 1.

Element (type)	Description
saf_cnt_updt_intrvl [bt_int16s DEFAULT 100]	The number of SAF updates before the datasource is updated from memory. Valid values are 0 to 9999. Default value is 100. A value of 0 indicates the SAF record count functionality is not used.
kdt_timr_lmt [bt_int32s]	KDT Key Timer Limit indicates the amount of time in minutes to use the current KDT Key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of seconds.
max_kdt_txn_cnt [bt_int32s]	The number of KDT Key transactions that are allowed before requesting a new key. Valid values are 0 to 99999. 0 indicates no transaction count limit is used. Default value is 0.
max_kdt_err_cnt [bt_int16s]	The number of KDT key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no error count limit is used. Default value is 0.
kdt_out_ts [timestamp 1.0]	Timestamp of the last successful exchange of the KDT Key Outbound.
kdt_out_txn_cnt [bt_int32s]	KDT Key Outbound Transaction Count. Counter identifying the number of transactions processed which used the outbound KDT key.
kdt_out_err_cnt [bt_int16s]	KDT Key Outbound Error Count. Counter identifying the number of error transactions processed which used the outbound KDT key.
kdt_in_ts [timestamp 1.0]	Timestamp of the last successful exchange of the KDT Key Inbound.
kdt_in_txn_cnt [bt_int32s]	KDT Key Inbound Transaction Count. Counter identifying the number of transactions processed which used the inbound KDT key.
kdt_in_err_cnt [bt_int16s]	KDT Key Inbound Error Count. Counter identifying the number of error transactions processed which used the inbound KDT key.
kdt_chng_out_timr_typ [bt_int16s]	KDT Key Change Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kdt_chng_out_timr_id [timr_id 1.0]	KDT Key Change Outbound Timer Identifier. Used to cancel a timer.
kdt_chng_in_timr_typ [bt_int16s]	KDT Key Change Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kdt_chng_in_timr_id [timr_id 1.0]	KDT Key Change Inbound Timer Identifier. Used to cancel a timer.
kdt_rpt_out_timr_typ [bt_int16s]	KDT Key Repeat Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kdt_rpt_out_timr_id [timr_id 1.0]	KDT Key Repeat Outbound Timer Identifier. Used to cancel a timer.
kdt_rpt_in_timr_typ [bt_int16s]	KDT Key Repeat Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kdt_rpt_in_timr_id [timr_id 1.0]	KDT Key Repeat Inbound Timer Identifier. Used to cancel a timer.
kdt_vrfy_out_timr_typ [bt_int16s]	KDT Key Verify Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kdt_vrfy_out_timr_id [timr_id 1.0]	KDT Key Verify Outbound Timer Identifier. Used to cancel a timer.
kdt_vrfy_in_timr_typ [bt_int16s]	KDT Key Verify Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kdt_vrfy_in_timr_id [timr_id 1.0]	KDT Key Verify Inbound Timer Identifier. Used to cancel a timer.

Element (type)	Description
key_xchg_cnt_enbl_flg [bt_flag]	This element is a flag to indicate whether the interface should maintain the count of key exchanges. Valid values are: 0 - key exchange count should not be maintained. 1 - key exchange count should be maintained. The default value is 0.
kam_in_xchg_cnt_1 [bt_int32s]	The count to store the number of inbound message authorization keys the interface has exchanged (key 1)
kam_in_xchg_cnt_2 [bt_int32s]	The count to store the number of inbound message authorization keys the interface has exchanged (key 2)
kam_out_xchg_cnt_1 [bt_int32s]	The count to store the number of outbound message authorization keys the interface has exchanged (key 1).
kam_out_xchg_cnt_2 [bt_int32s]	The count to store the number of outbound message authorization keys the interface has exchanged (key 2).
kpt_in_xchg_cnt_1 [bt_int32s]	The count to store the number of inbound PIN encryption keys the interface has exchanged (key 1).
kpt_in_xchg_cnt_2 [bt_int32s]	The count to store the number of inbound PIN encryption keys the interface has exchanged (key 2).
kpt_out_xchg_cnt_1 [bt_int32s]	The count to store the number of outbound PIN encryption keys the interface has exchanged (key 1).
kpt_out_xchg_cnt_2 [bt_int32s]	The count to store the number of outbound PIN encryption keys the interface has exchanged (key 2).
kdt_in_xchg_cnt_1 [bt_int32s]	The count to store the number of inbound data encryption keys the interface has exchanged (key 1).
kdt_in_xchg_cnt_2 [bt_int32s]	The count to store the number of inbound data encryption keys the interface has exchanged (key 2).
kdt_out_xchg_cnt_1 [bt_int32s]	The count to store the number of outbound data encryption keys the interface has exchanged (key 1).
kdt_out_xchg_cnt_2 [bt_int32s]	The count to store the number of outbound data encryption keys the interface has exchanged (key 2).
kek_timr_lmt [bt_int32s]	KEK Key Timer Limit indicates the amount of time in minutes to use the current KEK Key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of seconds.
max_kek_txn_cnt [bt_int32s]	The number of KEK Key transactions that are allowed before requesting a new key. Valid values are 0 to 99999. 0 indicates no transaction count limit is used. Default value is 0.
max_kek_err_cnt [bt_int16s]	The number of KEK key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no error count limit is used. Default value is 0.
kek_out_ts [timestamp 1.0]	Timestamp of the last successful exchange of the KEK Key Outbound.
kek_out_txn_cnt [bt_int32s]	KEK Key Outbound Transaction Count. Counter identifying the number of transactions processed which used the outbound KEK key.
kek_out_err_cnt [bt_int16s]	KEK Key Outbound Error Count. Counter identifying the number of error transactions processed which used the outbound KEK key.
kek_in_ts [timestamp 1.0]	Timestamp of the last successful exchange of the KEK Key Inbound.

Element (type)	Description
kek_in_txn_cnt [bt_int32s]	KEK Key Inbound Transaction Count. Counter identifying the number of transactions processed which used the inbound KEK key.
kek_in_err_cnt [bt_int16s]	KEK Key Inbound Error Count. Counter identifying the number of error transactions processed which used the inbound KEK key.
kek_chng_out_timr_typ [bt_int16s]	KEK Key Change Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kek_chng_out_timr_id [timr_id 1.0]	KEK Key Change Outbound Timer Identifier. Used to cancel a timer.
kek_chng_in_timr_typ [bt_int16s]	KEK Key Change Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kek_chng_in_timr_id [timr_id 1.0]	KEK Key Change Inbound Timer Identifier. Used to cancel a timer.
kek_rpt_out_timr_typ [bt_int16s]	KEK Key Repeat Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kek_rpt_out_timr_id [timr_id 1.0]	KEK Key Repeat Outbound Timer Identifier. Used to cancel a timer.
kek_rpt_in_timr_typ [bt_int16s]	KEK Key Repeat Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kek_rpt_in_timr_id [timr_id 1.0]	KEK Key Repeat Inbound Timer Identifier. Used to cancel a timer.
kek_vrfy_out_timr_typ [bt_int16s]	KEK Key Verify Outbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kek_vrfy_out_timr_id [timr_id 1.0]	KEK Key Verify Outbound Timer Identifier. Used to cancel a timer.
kek_vrfy_in_timr_typ [bt_int16s]	KEK Key Verify Inbound Timer Type. Valid values are: 0 = None, 1 = NMM, 2 = XNMM.
kek_vrfy_in_timr_id [timr_id 1.0]	KEK Key Verify Inbound Timer Identifier. Used to cancel a timer.
kek_in_xchg_cnt_1 [bt_int32s]	The count to store the number of inbound KEK keys the interface has exchanged (key 1)
kek_in_xchg_cnt_2 [bt_int32s]	The count to store the number of inbound KEK keys the interface has exchanged (key 2)
kek_out_xchg_cnt_1 [bt_int32s]	The count to store the number of outbound KEK keys the interface has exchanged (key 1).
kek_out_xchg_cnt_2 [bt_int32s]	The count to store the number of outbound KEK keys the interface has exchanged (key 2).
saf_rate_fast_ts [timestamp 1.0]	Timestamp of the last SAF rate change to 'fast'.
saf_rate_slow_ts [timestamp 1.0]	Timestamp of the last SAF rate change to 'slow'.
all_key_cmd_flg [bt_flag DEFAULT 0]	All key processing flag.

Interface_SAF (3.0) (ifsafd)

The Interface SAF table contains one record for each Store and Forward table associated with an interface in the system.

[Audited] [Supports versioning]

OLTP: Interface_SAF_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pan_hash*[bt_int16s]	The hash value of the Primary Account Number (PAN).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
cmpnt_id [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
saf_asgn_nam [bt_stringf(32)]	The Store and Forward (SAF) assign name used to map to a physical location for adding SAF records. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). This field is no longer used in Interface Manager Table.
saf_mgr_nam [bt_stringf(16)]	The symbolic name of the SAF Manager Process. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
low_hash_val [bt_int16s]	The low hash value of the Primary Account Number (PAN) for the previous record. If this is the first record, use a value of -1.
max_saf_outstnd_lmt [bt_int16s]	The maximum number of Store and Forward (SAF) records that can be outstanding at a time. Valid values are 1 - 9999. Default value is 1. This field is no longer used in Interface Manager Table.
saf_timr_lmt [timr_lmt 1.0]	Store and Forward (SAF) Timer Limit, indicates the number of seconds to wait for a response after transmitting a SAF record. Valid values are: 1 - 9999, 60=Default. This field is no longer used in Interface Manager Table.
max_saf_retries_lmt [bt_int16s]	The maximum number of times a Store and Forward (SAF) record will be resent before the record is deleted. Valid values are 0 to 999. A value of 0 indicates an infinite number of tries. Default value is 3. This field is no longer used in Interface Manager Table.
saf_delay_timr_lmt [timr_lmt 1.0]	Store and Forward (SAF) Timer Limit, indicates the number of seconds to wait to check whether records exist in the SAF waiting to be sent. Valid values are: 1 - 9999, 300=Default. This field is no longer used in Interface Manager Table.
saf_send_lmt [bt_int16s]	The number of Store and Forward (SAF) message that can be sent in one burst when the SAF delay timer expires. Default value is 1. Maximum is 999.
saf_reset_timr_lmt [bt_int16s]	The number of seconds to wait before resetting the Store and Forward (SAF) position to the beginning of the file. Default value is 600 with a maximum of 9999
saf_delay_timr_lmt_slow [timr_lmt 1.0 DEFAULT 60]	The number of seconds to wait to check whether records exist in the SAF waiting to be sent when operating in slow mode. Valid values are: 1 - 9999. Default value is 60.

Interface_Station (2.0) (ifstad)

Interface Station table contains one record per input station. The station record stores status information for stations. There can be multiple stations per interface.

[Not Audited] [Supports versioning]

Element (type)	Description
link_st [bt_int16s]	Link State, indicates whether the station is up or down. Valid values are: 0 = Down, 1 = Up. Default value is 0.
iss_logon_st [bt_int16s]	The issuer logon state. Valid values are: 1 = logged on, 2 = logging on, 3 = logged off, 4 = logging off. Default value is 3.
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inbnd_sta_nam* [bt_stringf(16)]	The symbolic name of the inbound station which receives messages from an interface. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
outbnd_sta_nam [bt_stringf(16)]	The symbolic name of the outbound station which receives messages from an interface. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
max_outstnd_rqst_lmt [bt_int16s]	The maximum number of requests that may be outstanding at a time for the configured entity (interface or station). An interfaces maximum outstanding may be greater than or less than the cumulative stations that belong to the interface. Valid values are: 0 - 9999. Default value is 1000 for interfaces and 100 for stations.
sta_logon_typ [bt_int16s]	Station Logon Type. Valid values are: 1 = Acquirer only, 2 = Issuer only, 3 = Combined acquirer and issuer, 4 = Separate acquirer and issuer. Default value is 3.
acq_logon_st [bt_int16s]	The acquirer logon state. Valid values are: 1 = logged on, 2 = logging on, 3 = logged off, 4 = logging off. Default value is 3.
trffc_flg [bt_int16s]	Traffic Flag, indicates whether or not messages of any type are flowing on a station. Valid values are: 0 = No Traffic, 1 = Traffic. Default value is 0.
outstnd_cnt [bt_int32s]	Outstanding Count, indicates the current number of requests that have not received a reply.
tmout_cnt [bt_int16s]	Timeout Count, indicates the number of timeouts that have occurred since this field was last reset.
timr_typ [bt_int16s]	Timer Type, indicates the type of timer started. Valid values are: 0 = None, 1 = NMM Echo, 2 = XNMM Echo, 3 = WFT.
timr_id [timr_id 1.0]	Timer Identifier, indicates the value passed back from a timer start request.
iss_timr_typ [bt_int16s]	The issuer timer type. Valid values are: 0 = None, 1 = NMM Issuer Logon, 2 = XNMM Issuer Logon, 3 = NMM Issuer Logoff, 4 = XNMM Issuer Logoff, 5 =

Element (type)	Description
	NMM Both Logon, 6 = XNMM Both Logon, 7 = NMM Both Logoff, 8 = XNMM Both Logoff
iss_timr_id [timr_id 1.0]	The issuer timer identifier used to cancel a timer.
acq_timr_typ [bt_int16s]	Acquirer timer type. Valid values are: 0 = None, 1 = NMM Acquirer Logon, 2 = XNMM Acquirer Logon, 3 = NMM Acquirer Logoff, 4 = XNMM Acquirer Logoff
acq_timr_id [timr_id 1.0]	Acquirer timer identifier used to cancel a timer.
ovrld_ts [timestamp 1.0]	Overload Timestamp, used when the number of outstanding requests reaches the maximum allowed.
saf_outstnd_cnt [bt_int16s]	The number of Store and Forward (SAF) records outstanding that have been sent and are waiting for a response. This field is no longer used in Interface Station Table.
intf_dpnt_data [bt_stringv(200)]	Interface dependent data associated with a specific station. Layout is interface specific.
nde_nam [bt_stringf(48)]	The node that the station belong to.

Interface_Terminal (2.0) (iftrmd)

Interface Terminal table.

[Audited] [Supports versioning]

OLTP: Interface_Terminal_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acq_inst_id* [inst_id 1.0]	If the transaction is acquired by a BASE24 terminal, this identifies the owning or sponsoring institution. If the transaction is acquired by a switch, this identifies the switch. If the transaction is acquired by the Host, this field is sent in the external message by the Host.
chnl_id* [chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
intf_term_id [bt_stringf(16)]	Interface terminal id.

Interface_WPS (2.0) (fpswd)

The FPS WPS Interface Configuration data source contains one record for each WPS interface instance, and holds WPS-specific interface data.

[Audited] [Supports versioning]

OLTP: Interface_WPS_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
fps_bnk_id [bt_stringf(4)]	Bank ID of the UK bank.

ISO_Field (1.0) (isofd)

The ISO Field table contains one record for each message profile which defines the characteristics of the fields.

[Audited] [Supports versioning]

OLTP: ISO_Field_OLTP

Element (type)	Description
msg_prfl* [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
iso_ver [bt_int16s]	The version of ISO 8583 being used. Valid values are: 0 - 1987, 1 - 1993, 2 - 2001. Default value is 0.
extrn_char_set [bt_stringf(1)]	The character set an external message is sent and received in. Valid values are: A - ASCII, E - Ebcidic. Default value is A.
mac_char_set [bt_stringf(1)]	The character set the MAC is generated/verified in. Valid values are: A - ASCII, E - Ebcidic. Default value is A.
mti_bcd_flg [bt_flag]	Flag indicating whether the Message Type Identifier (MTI) is in BCD format. Valid values are: 0 - No, the MTI is not in BCD. 1 - Yes, the MTI is in BCD. Default value is 0.
pbit_bcd_flg [bt_flag]	Flag indicating whether the primary bit map is in BCD format. Valid values are: 0 - No, the primary bit map is not in BCD. 1 - Yes, the primary bit map is in BCD. Default value is 0.
lgth_bcd_flg [bt_flag]	Flag indicating whether the lengths for variable length fields is in BCD format. Valid values are: 0 - No, the field lengths are not in BCD. 1 - Yes, the field lengths are in BCD. Default value is 0.
fld_bcd_bit_map [bt_binaryf(24)]	A bit map indicating whether each of the 192 data elements is in BCD format. Each byte represents eight bits. If the data element is represented in BCD format the bit is turned on. Valid values are: 0 - No, the data element is not in BCD. 1 - Yes, the data element is in BCD. Default value is 0 for each data element.

ISO_FLD_DEFN (1.0) (fdefnd)

The ISO Field Definition table can contain one record per message type per field (data element) for each message type in the profile and defines the characteristics of the field.

[Audited] [Supports versioning]

OLTP: ISO_FLD_DEFN_OLTP

Element (type)	Description
fld_defn_prfl* [bt_stringf(16)]	The field definition profile for a Message Class when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
msg_typ* [bt_stringf(4)]	The message type of the transaction.
fld_num* [bt_stringf(3)]	Field number for which the definition applies
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
fld_descr [bt_stringf(16)]	Optional description of the Field, left justified alpha numeric. Default: spaces
lgth_size [bt_int16s]	The size in bytes of the field length, 0 - 4. Fixed format fields should leave this value set to zero. Default: 0
lgth_typ [bt_stringf(1)]	Identifies the Format type of the length Values are: 0 - None, 1 - ASCII, 2 - Binary, 3 - EBCDIC, 4 - Hex Default value is 0.
lgth_rprsnt_bytes [bt_flag]	Indicates if the length value of a variable length BCD field represents the number of bytes or the number of characters of data which follow the length value. Values are 0 - False - Characters, 1 - True = Bytes Default: 0
data_lgth [bt_stringf(4)]	Indicates the number of characters or bytes of data in the field. Maximum value = 9999. Default: 0
data_typ [bt_stringf(2)]	The format of the data in the field. Values are: 1 - ASCII, 2 - ASCII Trk 2, 3 - EBCDIC, 4 - BCD, 5 - BCD left justified 'F' filled, 6 - BCD left justified zero filled, 7 - BCD right justified zero filled, 8 - HEX Track 2/3, 9 - HEX leading EBCDIC Sign, 10 - Transparent
pci_ofst [bt_int16s]	The offset into the field where PCI masking of data should begin.
pci_lgth [bt_int16s]	The length of the data to be masked.
pci_mask [bt_stringf(1)]	The character to use when masking the data
validate_data [bt_flag]	A flag indicating whether the data received in the field should be validated when parsing.
continue_parse [bt_flag]	A flag indicating whether parsing of the message should continue if the parse of this field should fail.

ISO_Message (1.0) (isomd)

The ISO Message table contains one record for each message profile and message type combination in the system.

[Audited] [Supports versioning]

OLTP: ISO_Message_OLTP

Element (type)	Description
msg_prfl*[bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
msg_typ*[bt_stringf(4)]	The message type of the transaction.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_hdr_mac_flg [bt_flag]	Flag indicating whether the message header is included in the MAC calculation. Valid values are: 0 - No, the message header is not included in the MAC calculation. 1 - Yes, the message header is included in the MAC calculation. Default value is 0.
mti_mac_flg [bt_flag]	Flag indicating whether the Message Type Identifier (MTI) is included in the MAC calculation. Valid values are: 0 - No, the MTI is not included in the MAC calculation. 1 - Yes, the MTI is included in the MAC calculation. Default value is 0.
pbit_mac_flg [bt_flag]	Flag indicating whether the primary bit map is included in the MAC calculation. Valid values are: 0 - No, the primary bit map is not included in the MAC calculation. 1 - Yes, the primary bit map is included in the MAC calculation. Default value is 0.
mac_bit_map [bt_binaryf(24)]	A bit map indicating whether each of the 192 data elements are included in the MAC calculation. Each byte represents eight bits. If the data element is included in the MAC Calculation the bit is turned on. Valid values are: 0 - No, the data element is not included in the MAC calculation. 1 - Yes, the data element is included in the MAC calculation. Default value is 0 for each data element.
req_in_bit_map [bt_binaryf(24)]	A bit map indicating whether each of the 192 data elements in the Inbound Message is mandatory. Each byte represents eight bits. If the data element is Mandatory the bit is turned on. Valid values are: 0 - No, the data element is not required for inbound messages. 1 - Yes, the data element is required for inbound messages. Default value is 0 for each data element.
opt_in_bit_map [bt_binaryf(24)]	A bit map indicating whether each of the 192 data elements in the Inbound Message is conditional. Each byte represents eight bits. If the data element is conditional the bit is turned on. Valid values are: 0 - No, the data element is not conditional for inbound messages. 1 - Yes, the data element is conditional for inbound messages. Default value is 0 for each data element.
req_opt_out_bit_map [bt_binaryf(24)]	A bit map indicating whether each of the 192 data elements in the Outbound Message is either mandatory or conditional. Each byte represents eight bits. If the data element is either mandatory or conditional the bit is turned on. Valid values are: 0 - No, the data element is neither mandatory nor conditional for outbound messages. 1 - Yes, the data element is mandatory or conditional for outbound messages. Default value is 0 for each data element.
opt_out_bit_map [bt_binaryf(24)]	A bit map indicating whether each of the 192 data elements in the Outbound Message is conditional. Each byte represents eight bits. If the data element is conditional the bit is turned on. Valid values are: 0 - No, the data element is not conditional for outbound messages. 1 - Yes, the data element is conditional for outbound messages. Default value is 0 for each data element.
echo_out_bit_map [bt_binaryf(24)]	A bit map indicating whether each of the 192 data elements in the Outbound Message is to be echoed. Each byte represents eight bits. If the data element is echoed the bit is turned on. Valid values are: 0 - No, the data element is not echoed in the outbound

Element (type)	Description
	message. 1 - Yes, the data element is echoed in the outbound message. Default value is 0 for each data element.

ISO_PROC_CODE (1.0) (pceid)

The external ISO Processing Code to Internal Processing Code mapping table contains an entry for every external Processing Code which may be received for an endpoint where mapping is required. The external processing code is mapped to a corresponding internal processing code.

[Audited] [Supports versioning]

OLTP: ISO_PROC_CODE_OLTP

Element (type)	Description
proc_cde_prfl*[bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
proc_cde_extrn*[proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
txn_subtyp*[bt_stringf(4)]	An optional value that can be used with an existing BASE24 Classic transaction code to define a new transaction type. Any four characters are permitted. Default value is spaces (not applicable).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
proc_cde [proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.

Issuer_Profile_Map (1.0) (ipmd)

The Issuer Profile Map table contains an entry for each issuer in the system. An issuer may be an institution identifier or an interface name. The table assigns a primary and alternate journal profile for each entry.

[Audited] [Supports versioning]

OLTP: Issuer_Profile_Map_OLTP

Element (type)	Description
iss_inst_id*[inst_id 1.0]	The issuer institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pan_hash*[bt_int16s]	The hash value of the Primary Account Number (PAN).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
jrnلprfl_pri [bt_stringf(16)]	The primary journal profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
jrnلprfl_alt [bt_stringf(16)]	The alternate journal profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Issuer_Route_Profile (1.0) (irtpd)

The Issuer Route Profile table contains an entry for each issuer route profile in the system.

[Audited] [Supports versioning]

Element (type)	Description
iss_rte_prfl*[prfl_def 1.0]	The route profile of the issuer whose customer initiated the transaction. The issuer route profile is defined where ever the issuer is determine and allows one or more issuers to share routing and authorization configurations. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
bus_descr [bt_stringf(32)]	This is the business description for Issuer and Acquirer Route Profiles.

Issuer_Txn_Allowed (1.0) (isstxd)

The Issuer Transaction Allowed table contains one record for each issuer transaction profile, message category code and processing code in the system that are allowed. This table defines the set of transactions that are valid for an issuer for on-us and not-on-us transactions.

[Audited] [Supports versioning]

OLTP: Issuer_Txn_Allowed_OLTP

Element (type)	Description
iss_txn_prfl*[bt_stringf(16)]	The transaction profile for the issuer to which the customer belongs. The issuer transaction profile allows one of more issuers to share processing code definitions and transactions allowed information. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_cat*[bt_stringf(1)]	The message category relative to the message type identifier. It is the second byte of the message type identifier (e.g. the message category for a 1200 message type is 2). Valid values are: 1 - Authorization; 2 - Financial; 3 - File Maintenance; 5 - Settlement; 6 - Administrative; 8 - Network Management.
user_fld1*[bt_stringf(1)]	One byte user field (temporary filler).

Element (type)	Description
proc_cde*[proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
txn_alwd_on_us [bt_stringf(1)]	This field defines whether the transaction is allowed when the acquiring institution and issuing institutions are the same. Valid values are: 0 - Disallowed entirely, 2 - Allowed within the state, 3 - Allowed nationally, 4 = Allowed internationally. Default value is 0.
txn_alwd_not_on_us [bt_stringf(1)]	This field defines whether the transaction is allowed when the acquiring institution and issuing institutions are not the same. Valid values are: 0 - Disallowed entirely, 2 - Allowed within the state, 3 - Allowed nationally, 4 = Allowed internationally. Default value is 0.
discrd_rvsl_flg [bt_stringf(1)]	The discard reversal flag indicates whether reversals are not sent to the issuer. Valid values are: Y = Yes, discard reversals, N - No, do not discard reversals. Default value is N. Note: that all reversals are discarded if this field is set to Y. Financial and non-financial reversals are treated equally.
setl_impact [bt_stringf(1)]	The settlement impact is field is used to indicate whether the transaction has settlement impacts. The field is simply logged to the journal file for reports and extract. This field may contain any alphanumeric or special character. Default value is a space.

ITMRPRFL (1.0) (imtrd)

This data source contains configuration data for ATM channel inactivity processing. This data is accessed through the timer profile located on the ATM Static Data Table (ESATDS1).

[Audited] [Supports versioning]

Element (type)	Description
InactTmrPrflTx*[phn_num 1.0]	The terminal inactivity profile identifies the inactivity timer values to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
IntrTmtsAlwdNum [bt_int32s]	The number of timeouts allowed for non-peak inter-transaction timers. An event is logged if this threshold is exceeded. This data is configured on the ES ATD Configuration Profile table (ATDCNFG).
IntrWrkdStrtPkTx [bt_stringf(15)]	The start of the workday intertransaction peak period represented as HHMM. This time defines the start of the period when the workday peak intertransaction time is used.
IntrWrkdEndPkTx [bt_stringf(15)]	The end of the workday intertransaction peak period represented as HHMM. This time defines the end of the period when the workday peak intertransaction time is used.
IntrWrkdPkIntrNum [bt_int32s]	The time interval, in seconds, for workday, peak transaction periods, which the ES device handler will use for intertransaction timers. If no transaction is received

Element (type)	Description
	for this duration, an event is logged. This data is configured on the ES ATD Configuration Profile table (ATDCNFG).
IntrWkndStrtPkTx [bt_stringf(15)]	The start of the weekend intertransaction peak period represented as HHMM. This time defines the start of the period when the weekend peak intertransaction time is used.
IntrWkndEndPkTx [bt_stringf(15)]	The end of the weekend intertransaction peak period represented as HHMM. This time defines the end of the period when the weekend peak intertransaction time is used.
IntrWkndPkIntrNum [bt_int32s]	The time interval, in seconds, for weekend, peak transaction periods, which the ES device handler will use for intertransaction timers. If no transaction is received for this duration, an event is logged. This data is configured on the ES ATD Configuration Profile table (ATDCNFG).
IntrNPkIntrNum [bt_int32s]	The time interval, in seconds, for non-peak transaction periods, which the ES device handler will use for intertransaction timers. If no transaction is received for this duration, an event is logged. This data is configured on the ES ATD Configuration Profile table (ATDCNFG).

JCB_Institution (1.0) (jcbind)

JCB Institution Table.

[Audited] [Supports versioning]

OLTP: JCB_Institution_OLTP

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_spnsr_bnk_id [bt_stringf(11)]	Acquirer Sponsor Bank ID.

JCB_Interface (1.0) (jcifd)

JCB Interface Table.

[Audited] [Supports versioning]

OLTP: JCB_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
neg_data_acss_cde [bt_stringf(6)]	Negative Data Access Code.
dest_id_cde [bt_stringf(11)]	A code identifying the destination institution or its agent. This code is used when sending a Network Management request to an interface.

Journal (2.0) (jrnlId)

This contains a record for each journalled transaction.

[Audited] [Supports versioning]

Element (type)	Description
pan [bt_stringf(28)]	Primary Account Number
onl_key_amt [bt_int64s]	The amount used for online queries. This is the amount originally requested.
seq_num_char [bt_stringf(12)]	The sequence number which identifies the transaction as set by the acquirer.
discrim [bt_int16s]	The discriminant is used to make the online key unique for duplicate checking.
num_jrnl_rec [bt_int16s]	The number of journal records represents how many physical records were written to represent a single logical transaction. Default value is 1. If 2 or more records are required, set the value to 2 to indicate additional records exist in the Journal Continuation file.
iss_inst_id [inst_id 1.0]	The issuer institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acct_num [acct_num 1.0]	The account number used when processing the transaction.
tran_dat_tim [bt_stringf(16)]	The transaction date in format YYYYMMDDHHMMSShh when the transaction was journalled.
acq_inst_id [inst_id 1.0]	If the transaction is acquired by a BASE24 terminal, this identifies the owning or sponsoring institution. If the transaction is acquired by a switch, this identifies the switch. If the transaction is acquired by the Host, this field is sent in the external message by the Host.
bus_lvl1 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lvl2 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lvl3 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
bus_lvl4 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lvl5 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
mrch_id [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
chan_id [chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
shift_num [cnt 1.0]	The number of shifts performed at the channel. The value is increased by one for every shift transaction processing. On the end of day processing, the value is reset to one.
btch_num [cnt 1.0]	The number of batches performed at a channel. This value is increased by one for every batch transaction performed. When the value is 999, it is reset to one and begins increasing again. This value is also reset to one for every shift close transaction.
rec_frmt [bt_stringf(1)]	A record format identifying the type of journal record. Valid Values are: 1 = Financial Message Record. 5 = Settlement Message Record.
clerk_id [bt_stringf(6)]	The identification number, clerk ID, of the employee logged on to the channel. The value in this field is used for device logon security verification. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dual_site_ind [bt_char]	Indicates if the record/transaction originated on the Local System or the Remote System. Valid values: space or L - Local (default). R - Remote.
jrnل_body [bt_binaryv(3650)]	The body of the journal record containing transaction information.

Journal Continuation (2.0) (jrnلcd)

This contains 1 to n records when a transaction exceeds the storage capacity of the Journal file. The num_jrnل_rec represents the actual number of additional records required to journal the transaction.

[Audited] [Supports versioning]

Element (type)	Description
pan*[bt_stringf(28)]	Primary Account Number
onل_key_amt*[bt_int64s]	The amount used for online queries. This is the amount originally requested.

Element (type)	Description
seq_num_char* [bt_stringf(12)]	The sequence number which identifies the transaction as set by the acquirer.
discrim* [bt_int16s]	The discriminant is used to make the online key unique for duplicate checking.
rec_num* [bt_stringf(3)]	This field is used to make a primary key unique when multiple rows exist for the other fields in the primary key. rec_num begins with value 1 except for the Card Account table which begins with value 0.
num_jrnl_rec [bt_int16s]	The number of journal records represents how many physical records were written to represent a single logical transaction. Default value is 1. If 2 or more records are required, set the value to 2 to indicate additional records exist in the Journal Continuation file.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dual_site_ind [bt_char]	Indicates if the record/transaction originated on the Local System or the Remote System. Valid values: space or L - Local (default). R - Remote.
jrnl_body [bt_binaryv(3650)]	The body of the journal record containing transaction information.

Journal_Data_Suppression (1.0) (jdtsd)

The Journal Transaction Data Element Suppression table contains a record by Institution, message type, transaction code for each TDE Object ID NOT to journal. The message type and/or transaction code may be wildcarded with asterisks.

[Audited] [Supports versioning]

OLTP: Journal_Data_Suppression_OLTP

Element (type)	Description
iss_inst_id* [inst_id 1.0]	The issuer institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
msg_typ* [bt_stringf(4)]	The message type of the transaction.
txn_cde* [bt_stringf(2)]	The transaction code, which is the first 2 bytes of the processing code. The default value is zeroes.
obj_id* [bt_int16s]	The object identifier of the Transaction Data Element (TDE).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Journal_Key_Seq (2.0) (jrnlkd)

This contains a record for each journalled transaction. This table is maintained to give upgrading customers an option to use this table or the new Journal_Key_Seq2 table, which requires the files to be deleted and created due to key changes.

[Audited] [Supports versioning]

Element (type)	Description
pan* [bt_stringf(28)]	Primary Account Number
onl_key_amt* [bt_int64s]	The amount used for online queries. This is the amount originally requested.
seq_num_char* [bt_stringf(12)]	The sequence number which identifies the transaction as set by the acquirer.
discrim* [bt_int16s]	The discriminant is used to make the online key unique for duplicate checking.
num_jrnl_rec [bt_int16s]	The number of journal records represents how many physical records were written to represent a single logical transaction. Default value is 1. If 2 or more records are required, set the value to 2 to indicate additional records exist in the Journal Continuation file.
iss_inst_id [inst_id 1.0]	The issuer institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acct_num [acct_num 1.0]	The account number used when processing the transaction.
tran_dat_tim [bt_stringf(16)]	The transaction date in format YYYYMMDDHHMMSShh when the transaction was journalled.
acq_inst_id [inst_id 1.0]	If the transaction is acquired by a BASE24 terminal, this identifies the owning or sponsoring institution. If the transaction is acquired by a switch, this identifies the switch. If the transaction is acquired by the Host, this field is sent in the external message by the Host.
bus_lv1 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv2 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv3 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv4 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv5 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
mrch_id [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
chan_id [chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
shift_num [cnt 1.0]	The number of shifts performed at the channel. The value is increased by one for every shift transaction processing. On the end of day processing, the value is reset to one.
btch_num [cnt 1.0]	The number of batches performed at a channel. This value is increased by one for every batch transaction performed. When the value is 999, it is reset to one and begins increasing again. This value is also reset to one for every shift close transaction.
rec_frmt [bt_stringf(1)]	A record format identifying the type of journal record. Valid Values are: 1 = Financial Message Record. 5 = Settlement Message Record.
clerk_id [bt_stringf(6)]	The identification number, clerk ID, of the employee logged on to the channel. The value in this field is used for device logon security verification. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dual_site_ind [bt_char]	Indicates if the record/transaction originated on the Local System or the Remote System. Valid values: space or L - Local (default). R - Remote.
jrnl_body [bt_binaryv(3642)]	The body of the journal record containing transaction information.

Journal_Key_Seq2 (4.0) (jrnl2d)

This contains a record for each journalled transaction. This table has an additional alternate key called unique_key than Journal_Key_Seq table to force the table to be ordered in timestamp order for performance, extract and reporting reasons. Journal_Key_Seq remains to allow existing customers to choose when/if they want to uplift to the new table layout which requires new files due to the key changes.

[Audited] [Supports versioning]

Element (type)	Description
pan*[bt_stringf(28)]	Primary Account Number
onl_key_amt*[bt_int64s]	The amount used for online queries. This is the amount originally requested.
seq_num_char*[bt_stringf(12)]	The sequence number which identifies the transaction as set by the acquirer.
discrim*[bt_int16s]	The discriminant is used to make the online key unique for duplicate checking.
num_jrnl_rec [bt_int16s]	The number of journal records represents how many physical records were written to represent a single logical transaction. Default value is 1. If 2 or more records are required, set the value to 2 to indicate additional records exist in the Journal Continuation file.
iss_inst_id [inst_id 1.0]	The issuer institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acct_num [acct_num 1.0]	The account number used when processing the transaction.

Element (type)	Description
tran_dat_tim*[bt_stringf(16)]	The transaction date in format YYYYMMDDHHMMSShh when the transaction was journalled.
acq_inst_id [inst_id 1.0]	If the transaction is acquired by a BASE24 terminal, this identifies the owning or sponsoring institution. If the transaction is acquired by a switch, this identifies the switch. If the transaction is acquired by the Host, this field is sent in the external message by the Host.
bus_lv1 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv2 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv3 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv4 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv5 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
mrch_id [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
chan_id [chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
shift_num [cnt 1.0]	The number of shifts performed at the channel. The value is increased by one for every shift transaction processing. On the end of day processing, the value is reset to one.
btch_num [cnt 1.0]	The number of batches performed at a channel. This value is increased by one for every batch transaction performed. When the value is 999, it is reset to one and begins increasing again. This value is also reset to one for every shift close transaction.
rec_frmt [bt_stringf(1)]	A record format identifying the type of journal record. Valid Values are: 1 = Financial Message Record. 5 = Settlement Message Record.
clerk_id [bt_stringf(6)]	The identification number, clerk ID, of the employee logged on to the channel. The value in this field is used for device logon security verification. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dual_site_ind [bt_char]	Indicates if the record/transaction originated on the Local System or the Remote System. Valid values: space or L - Local (default). R - Remote.
db2_id [bt_stringf(8)]	The db2 identifier for multiples lpars exist. The default value is spaces.
jrnl_body [bt_binaryv(16000)]	The body of the journal record containing transaction information.

Journal_Profile_Group (1.0) (jpgd)

The Journal Profile Group table contains a row for each journal profile in the system.

[Audited] [Supports versioning]

OLTP: Journal_Profile_Group_OLTP

Element (type)	Description
jrnl_prfl* [bt_stringf(16)]	The journal profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
file_frmt [bt_int16s]	The file format identifies whether the data elements are written to the file in native or ascii formats. Valid values are: 0 - Native, 1 - Ascii. Default value is 0.
retn_prd [bt_int16s]	The retention period identifies the number of files to retain beyond the current business date. Valid values are 1 thru 99. Default value is 1.
futr_cnt [bt_int16s]	The number of future journal files in addition to the current file to journal transactions. Valid values are 1 thru 99. Default value is 1.
rec_dat_mdfy [bt_stringf(8)]	The date the record was modified in YYYYMMDD format.
jpg_comment [bt_stringf(50)]	Free form text, which is used to describe the usage of the table entry.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Journal_Profile_Group_Assign (2.0) (jpgad)

The Journal Profile Group Assign table contains one record for each journal profile and index entry. There should be at minimum four assign names for each journal profile (one for previous, one for current, one for future and one for an empty file). The actual number of assigns is defined in the Journal Profile Group table by adding the retention period (previos), future count plus two for the current and empty file.

[Audited] [Supports versioning]

Element (type)	Description
jrnل_prfl*[bt_stringf(16)]	The journal profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
jpga_idx*[bt_int16s]	The index into the Journal Profile Group Assign table for a specific assign name.
asgn_nam [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
cont_asgn_nam [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Journal_Query_Config (4.0) (jqcd)

The Journal Query Configuration table contains a record for each Journal Batch Query that can be performed.

[Audited] [Supports versioning]

Element (type)	Description
jrnل_btch_qry_nam*[bt_stringf(16)]	The symbolic name of the journal batch query. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
jrnل_btch_iss_inst_id [inst_id 1.0]	The journal batch issuer institution identifier is either a valid issuer institution identifier defined in the Issuer Profile Map table or contains all asterisks. If a value of asterisks is specified, all configured journal profiles will be processed. If a specific issuer institution identifier is specified, only the journal profiles belonging to the specified issuer will be processed. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
lst_qry_ts [timestamp 1.0]	The timestamp when the query was last run. Default value is 0.
nxt_qry_ts [timestamp 1.0]	The timestamp when the next query is to run. Default value is 0.
restart_flg [bt_flag]	A flag indicating whether a Journal Query Batch timer should be automatically started during process initialization and to automatically start another timer for the next run. Valid values are 0 - Do not automatically start a timer, 1 - Automatically start a timer during initialization and after a timer expires. Default value is 1.
restart_tim [bt_stringf(4)]	The time to restart the Journal Batch Query run in hhmm format. Default value is 0000 indicating the run is to begin at midnight.
restart_prd_opt [bt_int16s]	The restart period option defines the time period between automatic runs of a Journal Batch Query. Valid values are: 1 - fixed number of days, 2 - one week, 3 - two weeks, 4 - first and 15th of each month, 5 - every month, 6 - every 3 months, 7 - every 6 months, 8 - every year, 9 - daily except Saturdays, Sundays and holidays, 10 - daily except

Element (type)	Description
	Sundays and holidays, 11 - daily except Saturdays and holidays, 12 - daily except Fridays and holidays, 13 - daily except Fridays, Saturdays and holidays, 14 - fixed number of minutes, 15 - fixed number of hours. Default value is 1.
restart_prd_adnl_data [bt_int16s]	The restart period additional data further defines the restart period option values. If restart period option value is 1, 14 or 15, this value specifies the length of the restart period. If the restart period option value is 2 or 3, this value indicates the day of the week that the restart period begins. Valid values are 0 - Monday, 1 - Tuesday, 2 - Wednesday, 3 - Thursday, 4 - Friday, 5 - Saturday, 6 - Sunday. If the restart period option is 5, 6, 7 or 8, this value indicates which day of the month the restart period begins. Valid values are 1 - 28. All other restart period options this field is not applicable. Default value is 1 for all restart period options except day of week which has a default of 6 (Sunday).
hol_dat_prfl [prfl_def 1.0]	The holiday date profile is used to define a set of dates as holidays. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
strt_ofst [bt_int16s]	The time difference, in number of days, to add to or subtract from the current business date to obtain the date of the Journal files to query. If the retain position flag is false, only the specified days journal files will be processed. If the retain position flag is true, this field is only used if no retained position is available for a journal file and all journal files from the specified day to the current day will be processed. For example, if the value of this field is -2 and the current business date is August 25, the date of the Journal files to query is August 23 (two days prior to the current business date). Valid values are less than or equal to zero. Default value is -1.
retn_posn_flg [bt_flag]	A flag indicating whether to retain the position information of the journal batch query run which will be the starting point for the next journal batch query run. Typically extracts will retain position information and reports will not retain position information. Valid values are: 0 - do not retain position information, 1 - retain position information. Default value is 1.
idx_typ [bt_int16s]	The alternate index to use when reading records. This allows records to be sorted by key within a Journal file instead of by transaction date and time within a Journal file. Valid values are: 0 - no alternate index, read by transaction date and time order, 1 - use issuer and account number (account key), 2 - use issuer and pan (pan key), 3 - use acquirer and terminal id (channel key), 4 - use acquirer, business levels, merchant id and terminal id (merchant key). Default value is 0. If retain position flag is not zero, this value must be a zero.
rpt_asgn_nam [bt_stringf(32)]	The assign name used to map to a physical location for the report. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
success_script_nam [nam 1.0]	The name of an executable script to be run when journal batch query is successful. This field is left-justified, upper case (containing any combination of alphanumeric and special character, but without any embedded spaces).
fail_script_nam [nam 1.0]	The name of an executable script to be run when journal batch query is not successful. This field is left-justified, upper case (containing any combination of alphanumeric and special character, but without any embedded spaces).
end_ofst [bt_int16s]	The time difference, in number of days, to add to or subtract from the current business date to obtain the date of the Journal files to stop the query. If the retain position flag is false, only the specified days journal files will be processed. If the retain position flag is true, this field is not used. For example, if the value of this field is the start offset is -2 and the value of the end offset is -1 and the current business date is August 25, the date

Element (type)	Description
	of the Journal files to query is August 23 and August 24 (two days prior to the current business date through 1 day prior to the current business date). Valid values are less than or equal to zero and greater than or equal to the start offset. Default value is -1.
btch_id [bt_int32s]	An identifier that can be written into an extract header if a unique identifier is necessary.
setl_cyc_id [bt_int16s]	The settlement cycle identifier for Faster Payments.

Journal_Query_Config_Output (1.0) (jqcod)

The Journal Query Configuration Output table contains a record for each Output location for a specific Journal Batch Query that can be performed. The Journal Query Output Profile specifies a group of output files that are round-robin to determine the next group of files to write to.

[Audited] [Supports versioning]

Element (type)	Description
jrnل_btch_qry_nam*[bt_stringf(16)]	The symbolic name of the journal batch query. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
jrnل_btch_rec_num*[bt_int16s]	The record number of the journal batch output used to allow multiple outputs to be generated for each run.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
jrnل_btch_hdr_flg [bt_flag]	Flag indicating whether a header is prepended to each record written to the output data source. Header includes a 6 byte length followed by a 2 byte record type. Record types represent FH or BH - file or bank header, DR - data record, CF - first continuation data record, CR - continuation data record, CL - last continuation data record, TR - truncated data record, FT or BT - file or bank trailer. Valid values are: 0 - No header, 1 - a header is prepended to the output records. Default value is 1.
hdr_trlr_typ [bt_stringf(1)]	The record type to prepend to header and trailer records. Valid values are: F - Use FH for header and FT for trailer, B - Use BH for header and BT for trailer. Default value is F.
max_rec_lgth [bt_int16s]	The maximum length of data that may be written to a single line to the output data source.
data_cont_disp [bt_stringf(1)]	A code indicating how oversized records are processed when a record header precedes each output record. Depending on the size of either a single record or a record plus the record header may exceed the maximum record length. When this occurs, this parameter determines how the oversized record is processed. Valid values are: C - The process writes the number of records necessary to process the oversized record with prefixes of CF, CR and CL which represent the first continuation record, continuation record and last continuation record in order. N - The process writes a single record truncated as necessary with the usual data record prefix DR. Truncated records can be identified by comparing the record length to the length specified in the header. T - The process writes a single record truncated as necessary as it does with the value N, however the data record prefix is set to TR. Default value is N. If no record header is present, records are simply truncated.

Element (type)	Description
char_set [bt_stringf(1)]	The character set to write to the output data source. Valid values are: A - ASCII, E - Ebcidic. Default value is A.
append_flg [bt_flag]	Flag indicating whether records should be appended to the output data source or first delete all records in the output data source. Valid values are: 0 - delete all records before processing the header, 1 - do not delete any records. Default value is 0.
rpt_hdr_script_nam [nam 1.0]	The name of the report header script. The results from this script are output at the top of each page of the report. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). Optional.
rpt_trlr_script_nam [nam 1.0]	The name of the report trailer script. The results from this script are output at the bottom of each page of the report. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). Optional.
file_hdr_script_nam [nam 1.0]	The name of the file header script. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). Optional.
data_script_nam [nam 1.0]	The name of the data script. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
file_trlr_script_nam [nam 1.0]	The name of the file trailer script. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). Optional.
jrnل_qry_output_prfl [bt_stringf(16)]	The journal query output profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
lst_jrnل_prfl [bt_stringf(16)]	The last journal profile used for a journal query output. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Journal_Query_Output_Assign (1.0) (jqoad)

The Journal Query Output Assign table contains one record for each journal profile and index entry. There should be at minimum one assign name for each journal profile. This table allows a journal query to exceed the capacity of a single file and records will continue to be written to the next file if the first file fills up.

[Audited] [Supports versioning]

Element (type)	Description
jrnل_prfl*[bt_stringf(16)]	The journal profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
jpga_idx*[bt_int16s]	The index into the Journal Profile Group Assign table for a specific assign name.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
asgn_nam [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Journal_Query_Output_Map (1.0) (jqomd)

The Journal Query Output Map table contains an entry for each journal query output profile in the system. The table defines the ring of journal query profiles to use for a journal query.

[Audited] [Supports versioning]

Element (type)	Description
jrnل_qry_output_prfl*[bt_stringf(16)]	The journal query output profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
jrnل_prfl*[bt_stringf(16)]	The journal profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Journal_Query_Position_Info (2.0) (jqpid)

The Journal Query Position Information table contains a record for each specific Journal Batch Query and Journal Profile combination that has retained position information used to continue a journal batch query.

[Not Audited] [Supports versioning]

Element (type)	Description
jrnل_btch_qry_nam*[bt_stringf(16)]	The symbolic name of the journal batch query. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
jrnل_prfl*[bt_stringf(16)]	The journal profile name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
lst_qry_ts*[timestamp 1.0]	The timestamp when the query was last run. Default value is 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
jrnل_btch_iss_inst_id [inst_id 1.0]	The journal batch issuer institution identifier is either a valid issuer institution identifier defined in the Issuer Profile Map table or contains all asterisks. If a value of asterisks is specified, all configured journal profiles will be processed. If a specific issuer institution identifier is specified, only the journal profiles belonging to the specified issuer will be processed. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
jrnل_strt_asgn_nam [bt_stringf(32)]	The assign name where a Journal Batch Query started. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
data_src_strt_posn_info [bt_binaryl(256)]	The position information where a Journal Batch Query was started.
jrnل_end_asgn_nam [bt_stringf(32)]	The assign name where a Journal Batch Query ended. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
data_src_end_posn_info [bt_binaryl(256)]	The position information where a Journal Batch Query ended.
jrnل_qry_rec_cnt [bt_int64s]	The number of records processed for the journal profile during the specific journal query execution.

Key_Map (1.0) (kymapd)

Key Mapping Data Source maps the Key Zone Index of the relevant working key stored on the Interchange Security data source with the Key Sequence Number specified in the online Interchange message for PIN processing. PINs, and perform message authentication.

[Audited] [Supports versioning]

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
key_dir*[bt_int16s]	The Key Direction identifying an Inbound or Outbound Working Key. Valid values: 0 - Inward (Issuer Working Key), 1 - Outward (Acquirer Working Key).
kpt_idx*[bt_int16s]	KPT Key Index (zone) which is specified in the related Interchange Security data source.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
key_seq_num [bt_stringf(2)]	Key Sequence Number associated with a Working Key. This value will be included in the online Interchange message identifying the Working Key to be used in PIN Verification. Valid values: 01 or 02 or 03.

Key_Token (1.0) (ktd)

This data source holds key token information used in the IBM CryptoExpress2 implementation. Table use is optional for symmetric keys and is used for dynamic key storage in lieu of the Cryptographic Key Data Store (CKDS) that is a part of the Integrated Cryptographic Services Facility (ICSF).

[Audited] [Supports versioning]

Element (type)	Description
key_label* [bt_stringf(64)]	The key label. This field matches the internal format of a key label in the ICSF subsystem.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by the application.
key_token [bt_binaryf(64)]	ICSF Key Token containing encrypted key and validation information. Only present for symmetric keys (non-RSA keys).
pk_keyx [bt_binaryf(298)]	Public Key used to generate the signature of an EPP Encryption Public Key. Only present for RSA Keys.
pk_sig [bt_binaryf(512)]	Signature of the EPP Public Key or Key data. Only present for RSA keys.
pk_data_signed [bt_binaryf(2048)]	Data upon which the signature was generated. For certificate based schemes this is the data signed object. For signature based schemes this is the actual EPP Encryption Public Key.

LCONF (1.0) (lconf)

BASE24 Classic File - The Logical Network Configuration File (LCONF) is the central location of file information and processing information for BASE24, and for this reason, it is one of the main components of every BASE24 logical network. One LCONF exists for each logical network. The records in LCONFs are classified as either assigns or params. This definition covers the Param format only (for Assigns many of the fields are redefined in a different format).

[Not Audited] [Does not support versioning]

Element (type)	Description
ItemTypeCd* [bt_char]	BASE24 Classic Element The type of LCONF item contained within a given record. A = Assign record P = Param record
UserField1Tx* [bt_char]	BASE24 Classic Element This field is not used.
ProcessNameTx* [bt_stringf(16)]	BASE24 Classic Element - The symbolic name of the process using a given assign or param, if needed for process-specific assigns or params. If a process name is not entered, the default is 16 *.
ItemNameTx* [bt_stringf(32)]	BASE24 Classic Element - The name of the assign or param (for example, POS-PTLF or LOGICAL-NET).
ProdIndTx [bt_stringf(32)]	BASE24 Classic Element - A byte map indicating which product(s) use this specific assign or param or if the assign or param is Base.
CommentTextTx [bt_stringf(256)]	BASE24 Classic Element - The user-entered comments providing additional information about the assign or param.
LastChangeTime [bt_binaryf(6)]	BASE24 Classic Element - The timestamp for the latest maintenance to this record.
ParamLgthShort [bt_int16s]	BASE24 Classic Element - The length of the param definition.
ParamTxtTx [bt_stringf(70)]	BASE24 Classic Element - The actual parameter text or value.
UserField3Tx [bt_stringf(48)]	BASE24 Classic Element - This field is not used.

Element (type)	Description
ProdIndAdnlTx [bt_stringf(224)]	BASE24 Classic Element - A byte map for PI indicators 33 - 256 indicating which product(s) use this specific assign or param or if the assign or param is base.
UserField4Tx [bt_stringf(6)]	BASE24 Classic Element - This field is not used.
LastAfmTsLong [bt_int64s]	BASE24 Classic Element - Julian timestamp (date/time) of the last AFM function performed to the data record.
LastAfmUpdtType [bt_int16s]	BASE24 Classic Element - Record maintenance function: 0 - Add 1 - Image before modify 2 - Image after modify 3 - Purge
UserIdGrpNmbrShort [bt_int16s]	BASE24 Classic Element - The group number of the operator that performed the last file maintenance application. This value is taken from the information given when the operator last logged on to BASE24.
UserIdUserNmbrInt [bt_int32s]	BASE24 Classic Element - The user number of the operator that performed the last file maintenance application. This value is taken from the information given when the operator last logged on to BASE24.
LastAfmTermNameTx [bt_stringf(24)]	BASE24 Classic Element - This field contains the terminal ID where the record maintenance occurred. Used only by Pathway servers. Non-Pathway servers default TERM-NAM field to blanks.

Limits (1.0) (Imtd)

This table contains limits that are associated with a payment instrument (e.g., card).

[Audited] [Supports versioning]

OLTP: Limits_OLTP

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
lmt_prfl*[prfl_def 1.0]	The limit profile. Used as the key to the Limit Table.
lmt_usg_nam*[bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
lmt_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
lmt_usg_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours

Element (type)	Description
lmt_usg_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.

Linked_Currency (1.0) (lnkcd)

The Linked Currency data source is used to determine if the transaction acquirer currency and cardholder billing currency are linked. Currencies are linked if the conversion rates and minor units for both currencies are the same.

[Audited] [Supports versioning]

OLTP: Linked_Currency_OLTP

Element (type)	Description
src_crncy_cde*[crncy_cde 1.0]	The source currency code. This is the currency code of the amount to be converted to the base currency code.
dest_crncy_cde*[crncy_cde 1.0]	The destination currency code. This is the currency code to which an amount in the source currency is being converted to.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

LIS5_Interface (1.0) (li5ifd)

LIS5 (Link) Interface Configuration.

[Audited] [Supports versioning]

OLTP: LIS5_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_sec_cde [bt_stringf(8)]	Message Security Code.
netwk_mgmt_opt [bt_stringf(1)]	Network Management Option. Values are: 1 - A single network management message to be used in both acquirer and issuer zones; 2 - Separate network management messages used for each zone.

Element (type)	Description
zn_typ [bt_stringf(1)]	Zone Type. Values are: 0 - Issuer; 1 - Acquirer, 2 - Acquirer and Issuer.
lis5_msg_orig [bt_stringf(1)]	Message Origin for the LIS5 Interface. Values are: 0 - Other; 1 - LINK.

LISTENER (1.0) (lstnd)

The listener table is used to configure information for a process that is needed to receive messages from another process regardless of whether that process is on the same server or a different server. It is used to configure TCP/IP and JMS listeners with configurable message parameters such as 2 byte headers, the es MDS message header and EOT characters.

[Audited] [Supports versioning]

Element (type)	Description
LstnID* [bt_stringf(16)]	The identifier associated with a listener in the Listener table (LISTENER).
PrcsID* [bt_stringf(16)]	A unique ID assigned to a process in the Process table (PROCESS).
DscrTx [bt_stringf(255)]	This element is used to record descriptive text for entries in the Application Configuration table (APPLCNFG), External Connection table (EXTRCNCT) and the Listener table (LISTENER).
Type [bt_stringf(50)]	Used to indicate the type of listener configured in the Message Services in the Listener data source.
PrtcDfnd1Tx [bt_stringf(255)]	The Protocol Field 1 element is used to indicate protocol specific information to use when sending a message through the Message Services. Valid values for this field are defined in the services that use it. For messages sent via TCPIP, this field might contain the IP address or the port to which to send the message. The data is configured in the External Connection table (EXTRCNCT) and the Listener table (LISTENER).
PrtcDfnd2Tx [bt_stringf(255)]	The Protocol Field 2 element is used to indicate protocol specific information to use when sending a message through the Message Services. Valid values for this field are defined in the services that use it. For messages sent via TCPIP, this field might contain the IP address or the port to which to send the message. The data is configured in the External Connection table (EXTRCNCT) and the Listener table (LISTENER).
PrtcDfnd3Tx [bt_stringf(255)]	The Protocol Field 2 element is used to indicate protocol specific information to use when sending a message through the Message Services. Valid values for this field are defined in the services that use it. For messages sent via TCPIP, this field might contain the IP address or the port to which to send the message. The data is configured in the External Connection table (EXTRCNCT) and the Listener table (LISTENER).
MaxConnNum [bt_int32s]	Used to indicate the maximum number of Client Sockets to allow to be created for a given host address/port combination and to indicate the maximum number of connections to accept for a Server Socket. This is used in the Listener and External Connection tables.
PrtcOptnList [bt_stringf(100)]	The Protocol Option List element is used to indicate the message protocol options to use when sending a message through the Message Services. An example is an option of .EOT. to indicate the message requires an End Of Text character. The data

Element (type)	Description
	is configured on the External Connection table (EXTRCNCT) and Listener table (LISTENER).
RspnMsgFrmtClasTx [bt_stringf(255)]	The Message Format Class is used to configure, in a database, a message formatter class name to be dynamically loaded from Message Services. The value is configured in the Listener table (LISTENER).
RspnMsgFrmtMthdTx [bt_stringf(100)]	The Message Format Method is used to configure, in a database, a message formatter class method to be invoked from Message Services. The value is configured in the Listener table (LISTENER).
RqstAdptClasTx [bt_stringf(255)]	The Message Adapter Class is used to configure, in a database, a message adapter class to be dynamically loaded from Message Services. The value is configured in the Listener table (LISTENER).
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

LTMRPRFL (1.0) (ltmrd)

This data source contains configuration data for ATM channel load timeout processing and load peak interval definition. This data is accessed through the timer profile located on the ATM Static Data Table (ESATDS1).

[Audited] [Supports versioning]

Element (type)	Description
LoadTmrPrflTx*[prfl_def 1.0]	The terminal load timer profile identifies the load timer values to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
LdTmtPrdNum [bt_int32s]	Duration (in milliseconds) of a load inactivity timer. If the value is 0 the default value is used, which is configured via property dh.timerdelay.load (previously existing property devicehandler.timerdelay.load).
WrkdStrtPkLdTx [bt_stringf(15)]	The start of the workday peak load period represented as HHMM. The data is configured on the ES ATD Configuration table (ATDCNFG). This time defines the start of the period when the workday peak ATM configuration file is used. The peak load file will be automatically loaded to the ATM.
WrkdEndPkLdTx [bt_stringf(15)]	The end of the workday peak load period represented as HHMM. The data is configured on the ES ATD Configuration table (ATDCNFG). This time defines the end of the period when the workday peak ATM configuration file is used. The non-peak load file will be automatically loaded to the ATM.
WkndStrtPkLdTx [bt_stringf(15)]	The Start of the weekend peak load period represented as HHMM. The data is configured on the ES ATD Configuration table (ATDCNFG). This time defines the start of the period when the weekend peak ATM configuration file is used. The peak load file will be automatically loaded to the ATM.
WkndEndPkLdTx [bt_stringf(15)]	The end of the weekend peak load period represented as HHMM. The data is configured on the ES ATD Configuration table (ATDCNFG). This time defines the

Element (type)	Description
	end of the period when the weekend peak ATM configuration file is used. The non-peak load file will be automatically loaded to the ATM.

MACPRFL (1.0) (macd)

This data source contains the configuration related to ATM Message Authentication Code (MAC) processing.

[Audited] [Supports versioning]

Element (type)	Description
MacPrflTx* [prfl_def 1.0]	The Message Authentication Code (MAC) profile identifies the MAC processing values to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
MacSprtCd [bt_stringf(1)]	The type of message authentication that is supported by the ATM device. The data is stored in the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Not configured 1 = Software Message Authentication 3 = Hardware Message Authentication The default value is 0.
MacDataTypCd [bt_stringf(1)]	The character set that the data to be authenticated is in. The data is configured in the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = ASCII 1 = EBCDIC The default value is 0.
MacSolStatCd [bt_stringf(1)]	A code indicating whether Solicited Status Messages will have a MAC code authenticated. The data is stored on the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Not configured 1 = Authenticate Solicited Status Messages The default value is 0.
MacAthnMthdCd [bt_stringf(1)]	This field determines what type of calculation will be done on the fields in the message. The data is stored in the ES ATD Configuration Profile table (ATDCNFG). For Selective Field MACing, the fields included in the data string to be authenticated are configured via the Field Selection Tables in the Device Handler. Valid values are: 0 = Full Message Authentication 1 = Selective Field Message Authentication The default value is 0.

MDS_BIN_File_Updt (1.0) (mdsbin)

The MDS BIN File Update data source contains the Interchange Prefix updates received from MDS and Banknet. Updates to the Interchange Prefix files will be applied by the MDS IPF Refresh.

[Not Audited] [Does not support versioning]

Element (type)	Description
mds_bin_rec [bt_stringv(80)]	This record contains a MDS Interchange prefix update record. This record may contain a file header, change detail record or a trailer record.

MDS_Brand_Rel (1.0) (mdsbid)

This data source is used by the MDS IPF Refresh to associate the MDS brand with an instrument type and an Interchange Prefix data source.

[Audited] [Supports versioning]

OLTP: MDS_Brand_Rel_OLTP

Element (type)	Description
brand_id* [bt_stringf(1)]	This field identifies the brand in the BIN file.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_1 [instrm_typ 1.0]	A code identifying the instrument type.
data_src_id [data_src 1.0]	The data source ID. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

MDS_Institution (1.0) (mdsiid)

MDS Institution Table

[Audited] [Supports versioning]

OLTP: MDS_Institution_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mds_acq_bnk_id [bt_stringf(9)]	The acquirer bank identifier.

MDS_Interface (1.0) (mdsifd)

The Mastercard Debit Interface configuration data

[Audited] [Supports versioning]

OLTP: MDS_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mds_sec_cde [bt_stringf(16)]	The security code used for network management messages sent to the Mastercard Debit network.
mds_proc_id [bt_stringf(3)]	Mastercard Debit assigned processor code.

Merchant (5.0) (mrchd)

The Merchant table contains one record for each merchant in the system. Each record contains information for use in validating transactions and defining cutover times.

[Audited] [Supports versioning]

OLTP: Merchant_OLTP

Element (type)	Description
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv1 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv2 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv3 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv4 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
bus_lv5 [bt_stringf(10)]	The business level to which the channel belongs. The value in this group is optionally used to group channels for reporting purposes. This field is left justified, upper-case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
mrch_id* [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mrch_stat [bt_stringf(1)]	The current status of the merchant. Valid values are: O - Open and in use and C - Closed. Default value is O.
mrch_nam [bt_stringf(40)]	The name of the merchant. This field is left justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
mrch_acct_num [bt_stringf(28)]	The merchant account number which may be used by Automated Clearing House (ACH). This field is not used in online transaction processing, simply logged. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
addr_1 [bt_stringf(25)]	The address line 1. Where only one line of address is supported, this address will be used and addr_2 will be ignored. This field is left-justified (containing any combination of alphanumeric and special characters).
addr_2 [bt_stringf(25)]	The address line 2. This field is left-justified (containing any combination of alphanumeric and special characters).
city [bt_stringf(18)]	The city address. Field is left-justified (containing any combination of alphanumeric and special characteres).
st [bt_stringf(3)]	The state, province or region code depending upon locale. This field contains alphanumeric and special characters.
postal_cde [bt_stringf(10)]	The postal code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
cntry [bt_int16s]	The numeric country code as defined in ISO document 4217.
tim_ofst [bt_int32s]	The time difference between the device location and the processor location defined in minutes. Valid range is -1400 to +1400.
fncl_cutover_strt_tim [bt_stringf(4)]	The financial cutover start time in HHMM format.
bal_strt_tim [bt_stringf(4)]	The start time for the balance window. This field is in HHMM format.
end_cutover_tim [bt_stringf(4)]	The end of the balance and cutover window. This field is in HHMM format.
contact1_nam [nam 1.0]	The first contact name. This field is left-justified (containing any combination of alphanumeric and special characters).
contact1_phn_num [phn_num 1.0]	The first contact phone number. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact1_email_addr [email_addr 1.0]	The first contact email address. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact1_comments [comments 1.0]	The first contact comments. This field is left-justified (containing any combination of alphanumeric and special characters).
contact2_nam [nam 1.0]	The second contact name. This field is left-justified (containing any combination of alphanumeric and special characters).

Element (type)	Description
contact2_phn_num [phn_num 1.0]	The second contact phone number. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact2_email_addr [email_addr 1.0]	The second contact email address. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
contact2_comments [comments 1.0]	The second contact comments. This field is left-justified (containing any combination of alphanumeric and special characters).
mrch_vrfy_val [bt_stringf(10)]	Merchant Verification Value. A value assigned by Visa to a merchant to indicate its eligibility to participate in merchant incentive programs. Consists of 10 alphanumeric characters. Default value is all spaces.
notes [bt_stringf(100)]	An optional user defined field. This field is left-justified (containing any combination of alphanumeric and special characters). Default value is spaces.
transit_bank_num [bt_stringf(11)]	A code (mostly a number) assigned by a Central Bank, a Bank Supervisory Body or a Bankers Association in a country to all its licensed member banks to identify the bank and its location where an account is held.
dflt_crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217. Used only if the currency code has not already been set from the external message.
dflt_crd_accpt_bus_cde [bt_int16s]	The card acceptor business code pertaining to the merchants line of business. This field is 4 numeric digits. This card acceptor business code is used only if the card acceptor business code has not already been set from the external message.
mail_phn_crd_accpt_bus_cde [bt_int16s]	The card acceptor business code pertaining to the merchant's line of business. This field is 4 numeric digits. This value can be used for card not present transactions.
dflt_oper_envmt [bt_stringf(1)]	The fourth position of the Point of Service Data. This data item indicates if the channel is attended by the card acceptor and its location. Valid values are: 0 - no channel used, 1 - attended on premises of card acceptor, 2 & 5 - unattended on premises of card acceptor, 3 - attended off the premises of card acceptor, 4 - unattended off premises of card acceptor. Default value is 2.
acq_rte_prfl [bt_stringf(16)]	Acquirer Route Profile.
acq_txn_prfl [bt_stringf(16)]	Acquirer Transaction Profile.
acq_lmt_prfl [bt_stringf(16)]	Acquirer Limits Profile.
acq_instrm_typ_rel_prfl [bt_stringf(16)]	Acquirer Instrument Type Relation Profile
mrch_nam_mbyte [bt_binaryl(80)]	The multi-byte name of the merchant.
addr_1_mbyte [bt_binaryl(50)]	Multi-byte address line 1.
addr_2_mbyte [bt_binaryl(50)]	Multi-byte address line 2.
city_mbyte [bt_binaryl(36)]	Multi-byte city address.
st_mbyte [bt_binaryl(6)]	Multi-byte state, province or region code depending upon locale.
postal_cde_mbyte [bt_binaryl(20)]	Multi-byte postal code.

Element (type)	Description
cntry_mbyte [bt_binaryl(6)]	Multi-byte country.
contact1_nam_mbyte [bt_binaryl(32)]	Multi-byte first contact name.
contact1_phn_num_mbyte [bt_binaryl(40)]	Multi-byte first contact phone number.
contact1_email_addr_mbyte [bt_binaryl(100)]	Multi-byte first contact email address.
contact1_comments_mbyte [bt_binaryl(100)]	Multi-byte first contact comments.
contact2_nam_mbyte [bt_binaryl(32)]	Multi-byte second contact name.
contact2_phn_num_mbyte [bt_binaryl(40)]	Multi-byte second contact phone number.
contact2_email_addr_mbyte [bt_binaryl(100)]	Multi-byte second contact email address.
contact2_comments_mbyte [bt_binaryl(100)]	Multi-byte second contact comments.
notes_mbyte [bt_binaryl(200)]	Multi-byte user defined field to store notes.

Merchant_Channel_Profile (3.0) (mcpd)

The Merchant Channel Profile table contains one record for each channel profile.

[Audited] [Supports versioning]

OLTP: Merchant_Channel_Profile_OLTP

Element (type)	Description
chan_prfl*[prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
crd_accpt_bus_cde [bt_int32s]	The card acceptor business code pertaining to the merchants line of business. This field is 4 numeric digits.
inbnd_auth_rqst_tim_lmt [bt_int16s]	The time limit in seconds to wait for a transaction response for an authorization request. Valid values are 1 to 9999. Defalut value is 15 seconds.
bal_support [bt_int16s]	The type of balancing transactions the channel supports. Used when the channel cutover type is 0, 1, or 2. The relevant totals are cleared on a cutover based on the code specified here. Valid values are: 0 - Batch totals are supported, 1 - Batch and shift totals are supported , 2 - Batch and day totals are supported , 3 - Batch, shift and day totals are supported, 4 - Shift and day totals are supported, 5 - Day totals are supported, 9 - No totals are supported.

Element (type)	Description
chan_cutover_typ [bt_int16s]	A code indicating who cuts over the channel. Valid values are: 0 - Channel day close, 1 - Channel shift close, 2 - Channel batch close, 3 - Merchant Component forced cutover, 4 - First financial transaction cutover. Default value is 3.
clos_flg [bt_flag]	A code indicating whether a channel supports implied close of batch, shift and daily totals when the sequence number is not in sync. Valid values are: 1 - channel does support implied close, 0 - channel does not support implied close. Default value is 0.
billing_info [bt_stringf(10)]	User defined information containing billing information that can be added to each balancing/cutover transaction for a channel. This is information data only. Default value is spaces.
cmpl_trk_data [bt_flag]	A flag indicating whether the channel is capable of capturing and transmitting complete track data on transactions initiated by swiping the card through the reader on the channel. Valid values are: 1 - the channel is capable, 0 - the channel is not capable. Default value is 1.
chan_pin_entry [bt_flag]	A flag indicating whether the channel has PIN entry capability. Valid values are: 1 - channel has PIN entry capability, 0 - channel does not have PIN entry capability. Default value is 0.
pin_captr_cap [bt_stringf(1)]	The twelfth position of the Point of Service data. This data item indicates the length of PIN which the acquirer end-point is capable of capturing. Valid values are: 0 - no PIN capture capability, 1 - PIN capture capability unknown, 4 - four characters, 5 - five characters, 6 - six characters, 7 - seven characters, 8 - eight characters, 9 - nine characters, A - ten characters, B - eleven characters, C - twelve characters, S - PIN has been verified. Default value is 0.
mac_ind [bt_flag]	An indicator specifying whether the channel supports MACing. Valid values are: 1 - the channel supports MACing, 0 - the channel does not support MACing. Default value is 0.
apprv_cde_lgth [bt_int16s]	The maximum length of the approval code that the acquirer can handle. Valid values are: 2 to 6. Default value is 6.
clerk_flg [bt_flag]	A flag indicating whether operator (clerk) totals are maintained for the channel. Valid values are: 0 - No totals are maintained, 1 - All totals(debit, credit, adjustment, cash out and check) are maintained. The default value is 0. When this indicator is set to 1, all clerk totals are maintained for the operator who is currently logged on. These totals are journalled and cleared by a batch close transaction or when a new operator logon occurs.
jrnl_btch_ttl [bt_flag]	A code indicating whether batch totals are journaled during a cutover. Valid values are: 1 - journal the batch totals, 0 - do not journal the batch totals. Default value is 1.
jrnl_clerk_ttl [bt_flag]	A code indicating whether the clerk totals are journalled during a cutover. Valid values are: 1 - journal the clerk totals, 0 - do not journal the clerk totals. Default value is 1.
jrnl_shift_ttl [bt_flag]	A code indicating whether the shift totals are journalled during a cutover. Valid values are: 1 - journal the shift totals, 0 - do not journal the shift totals. Default value is 1.
jrnl_dly_ttl [bt_flag]	A code indicating whether the daily totals are journalled during a cutover. Valid values are: 1 - journal the day totals, 0 - do not journal the day totals. Default value is 1.
jrnl_network_ttl [bt_flag]	A code indicating whether the network totals are journalled during a cutover. Valid values are: 1 - journal the network totals, 0 - do not journal the network totals. Default value is 1.

Element (type)	Description
jrnl_instrm_typ_ttl [bt_flag]	A code indicating whether the instrument type totals are journalled during a cutover. Valid values are: 1 - journal the instrument type totals, 0 - do not journal the instrument type totals. Default value is 1.
dflt_pre_auth_hold_incr [bt_char]	The unit of time to retain the authorization hold if not specified in the external message. Valid values are: 1 - days, 2 - hours, 3 - minutes. Default value is 3. Used only if the pre-authorization hold time has not already been set from the external message for a pre-authorization request.
dflt_pre_auth_hold_tim [bt_stringf(2)]	Default time limit to hold a pre-authorization transaction. The value in this element is used when a time limit is not specified in the external message. The value specified corresponds to units of time defined in the PRE_AUTH_HOLD_INCR element. Valid values are: 00 - 99. Default value is 00.
chan_prfl_descr [bt_stringv(20)]	This field documents the purpose of the specific record.
max_kam_cnsc_err_cnt [bt_int16s]	The number of consecutive MAC key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no consecutive error count limit is used. Default value is 0. For the KEYF, if an error limit is configured, a minimum of 5 errors is required.
kpt_timr_lmt [bt_int32s]	PIN Key Timer Limit indicates the amount of time in minutes to use the current PIN Key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of minutes.
max_kpt_txn_cnt [bt_int32s]	The number of PIN Key transactions that are allowed before requesting a new key. Valid values are 0 to 99999 (9,999 for KEYF). 0 indicates no transaction count limit is used. Default value is 0.
kam_timr_lmt [bt_int32s]	MAC Key Timer Limit indicates the amount of time in minutes to use the current MAC key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of minutes.
max_kam_txn_cnt [bt_int32s]	The number of MAC generations/verifications that are allowed before requesting a new key. Valid values are 0 to 99999 (9,999 for KEYF). 0 indicates no transaction count limit is used. Default value is 0.
chan_proto [bt_int16s]	The protocol used by the channel. Valid values are: 0 - Dial-up. 1 - Other (default).
dev_proto [typ 1.0]	A code identifying the device protocol. Valid values are 00 - None (default), 01 - SPDH, 02 - APACS, 03 - HPDH.
btch_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain batch totals for the channel. Valid values are 0 - Batch totals not supported. 1 - Batch totals are supported. The default value is 0.
shift_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain shift totals for the channel. Valid values are 0 - Shift totals not supported. 1 - Shift totals are supported. The default value is 0.
dly_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain daily totals for the channel. Valid values are 0 - Daily totals are not supported. 1 - Daily totals are supported. The default value is 0.
part_auth_alwd [bt_flag]	A flag indicating whether the channel supports partial authorizations. Valid values are 0 - Partial authorizations are not supported. 1 - Partial authorizations are supported. The default value is 0.

Element (type)	Description
net_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain network totals for the channel. Valid values are 0 – network totals should not be supported, 1 – network totals should be supported. Default value is 0.
instrm_ttyp_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain instrument type totals for the channel. Valid values are 0 – instrument type totals should not be supported, 1 – instrument type totals should be supported. Default value is 0.
kdt_txn_lmt [bt_int32s]	Data Encryption Key Transaction Limit. Limit specifying the maximum number of transactions that can occur before a new data encryption key is generated. Default is 0.
kdt_txn_err_lmt [bt_int16s]	Data Encryption Key Transaction Error Limit. Limit specifying the maximum number of unsuccessful transactions that can occur before a new data encryption key is generated. Default is 0.
data_encr_ttyp [bt_char]	A code indicating which type of message data encryption is to be performed and in what form the balance is to be sent to the device. Valid values are: 0 - No data encryption. 1 - Encrypted available balance; sent to device in ASCII form. 2 - Encrypted available balance; sent to device in binary form. The default is 0.
kdt_timr_lmt [bt_int32s]	The data encryption key usage time limit, which indicates how long (in minutes) to use the current data key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit is used. Default value is 0. This field is written to disk as number of minutes.
kam_txn_err_lmt [bt_int32s]	The MAC encryption key error limit, which indicates how many MAC verification errors can occur before a new MAC key is generated. Valid values are: 0 - 9999. 0 indicates no error limit is used. Default value is zero.
kpt_txn_err_lmt [bt_int32s]	The PIN encryption key error limit, which indicates the total number of PIN key sync errors that can occur before a new PIN key is generated. Valid values are: 0 - 9999. 0 indicates no error limit is used. Default value is zero.

Merchant_Delivery_Channel (6.0) (mrchcd)

The Merchant Delivery Channel table contains one record for each controlled channel id in the system. The characteristics of the channel are defined, including attributes, counts and amounts.

[Audited] [Supports versioning]

Element (type)	Description
chan_id*[chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
chan_prfl [prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
mrch_id [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
chan_stat [bt_stringf(1)]	The current status of the channel. Valid values are: N - New and changes to open when it receives the first batch close for a non zero batch, O - Open and in use, C - Closed and P - Pending Close allows only close requests and changes to closed after a successful batch close. Default value is N.
captr_dat [bt_stringf(8)]	The channels current capture date in YYYYMMDD.
pinpad_serial_num [bt_stringf(16)]	The serial number of the PINPAD device. This field is optional and identifies the set of keys to use instead of using the channel id to identify the set of keys. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inventory_cntrl_1 [bt_stringf(16)]	The inventory control 1 field. An optional user defined field which may contain the model/serial number/description associated with the delivery channel equipment. This field is left-justified (containing any combination of alphanumeric and special characters, but without embedded spaces). Default value is spaces.
inventory_cntrl_2 [bt_stringf(16)]	The inventory control 2 field. An optional user defined field which may contain the model/serial number/description associated with the delivery channel equipment. This field is left-justified (containing any combination of alphanumeric and special characters, but without embedded spaces). Default value is spaces.
lst_setl_ts [timestamp 1.0]	The timestamp when the channel was last settled(balanced).
txn_seq_num [bt_int64s]	The transaction sequence number of the last transaction.
btch_num [cnt 1.0]	The number of batches performed at a channel. This value is increased by one for every batch transaction performed. When the value is 999, it is reset to one and begins increasing again. This value is also reset to one for every shift close transaction.
seq_num [bt_int64s]	The sequence number identifying the last transaction performed in the current batch. The value is incremented by one for each occurrence of transaction within a current batch. On close batch transaction processing, the value is reset to zero and accumulation begins within the new batch when the first transaction occurs. This is system protected element.
num_of_btchs [cnt 1.0 DELTA]	The number of batch transactions performed since the last channel cutover. The value is incremented by one for every batch transaction performed within this cutover period. When the channel cuts over, the count is reset to 0.
shift_num [cnt 1.0 DELTA]	The number of shifts performed at the channel. The value is increased by one for every shift transaction processing. On the end of day processing, the value is reset to one.
num_of_shifts [cnt 1.0 DELTA]	The number of shift transactions performed since the last channel cutover. The value is increased by one for each shift transaction processed.
num_of_crds_ret [cnt 1.0 DELTA]	The total number of cards retained since the last cutover.
wait_confirm_stat [bt_int16s]	An indicator specifying how a balance transaction was processed. The channel is waiting for confirmation for the sent balance transaction response. The indicator is reset to not waiting for confirmation when another request is received from the channel that is not a duplicate or a balance transaction. Valid values are: 0 = Not waiting for confirmation, 1 = Waiting confirmation,

Element (type)	Description
	batch close performed, 2 = Waiting confirmation, shift close performed, 3 = Waiting confirmation, daily close performed.
clerk_id [bt_stringf(6)]	The identification number, clerk ID, of the employee logged on to the channel. The value in this field is used for device logon security verification. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
clerk_db_cnt [cnt 1.0 DELTA]	The number of all debit transactions occurring during the current operators logon since the last batch close transaction.
clerk_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all debit transactions occurring during the current operators logon since the last batch close transaction.
clerk_cr_cnt [cnt 1.0 DELTA]	The number of all credit transactions occurring during the current operators logon since the last batch close transaction.
clerk_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all credit transactions occurring during the current operators logon since the last batch close transaction.
clerk_adj_cnt [cnt 1.0 DELTA]	The number of all adjustment transactions occurring during the current operators logon since the last batch close transaction.
clerk_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all adjustment transactions occurring during the current operators logon since the last batch close transaction.
clerk_cb_cnt [cnt 1.0 DELTA]	The number of all cash back transactions occurring during the current operators logon since the last batch close transaction.
clerk_cb_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all cash back transactions occurring during the current operators logon since the last batch close transaction.
clerk_chk_cnt [cnt 1.0 DELTA]	The number of all check transactions occurring during the current operators logon since the last batch close transaction.
clerk_chk_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all check transactions occurring during the current operators logon since the last batch close transaction.
btch_db_cnt [cnt 1.0 DELTA]	The number of all debit transactions processed during the current batch.
btch_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all debit transactions processed during the current batch.
btch_cr_cnt [cnt 1.0 DELTA]	The number of all credit transactions processed during the current batch.
btch_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all credit transactions processed during the current batch.
btch_adj_cnt [cnt 1.0 DELTA]	The number of all adjustment transactions processed during the current batch.
btch_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all adjustment transactions processed during the current batch.
btch_dc_db_cnt [cnt 1.0 DELTA]	The number of all draft capture debit transactions processed during the current batch.

Element (type)	Description
btch_dc_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture debit transactions processed during the current batch.
btch_dc_cr_cnt [cnt 1.0 DELTA]	The number of all draft capture credit transactions processed during the current batch.
btch_dc_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture credit transactions processed during the current batch.
btch_dc_adj_cnt [cnt 1.0 DELTA]	The number of all draft capture adjustment transactions processed during the current batch.
btch_dc_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture adjustment transactions processed during the current batch.
shift_db_cnt [cnt 1.0 DELTA]	The number of all debit transactions processed during the current shift.
shift_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all debit transactions processed during the current shift.
shift_cr_cnt [cnt 1.0 DELTA]	The number of all credit transactions processed during the current shift.
shift_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all credit transactions processed during the current shift.
shift_adj_cnt [cnt 1.0 DELTA]	The number of all adjustment transactions processed during the current shift.
shift_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all adjustment transactions processed during the current shift.
shift_dc_db_cnt [cnt 1.0 DELTA]	The number of all draft capture debit transactions processed during the current shift.
shift_dc_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture debit transactions processed during the current shift.
shift_dc_cr_cnt [cnt 1.0 DELTA]	The number of all draft capture credit transactions processed during the current shift.
shift_dc_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture credit transactions processed during the current shift.
shift_dc_adj_cnt [cnt 1.0 DELTA]	The number of all draft capture adjustment transactions processed during the current shift.
shift_dc_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture adjustment transactions processed during the current shift.
dly_db_cnt [cnt 1.0 DELTA]	The number of all debit transactions processed during the current day.
dly_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all debit transactions processed during the current day.
dly_cr_cnt [cnt 1.0 DELTA]	The number of all credit transactions processed during the current day.
dly_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all credit transactions processed during the current day.
dly_adj_cnt [cnt 1.0 DELTA]	The number of all adjustment transactions processed during the current day.
dly_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all adjustment transactions processed during the current day.

Element (type)	Description
dly_dc_db_cnt [cnt 1.0 DELTA]	The number of all draft capture debit transactions processed during the current day.
dly_dc_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture debit transactions processed during the current day.
dly_dc_cr_cnt [cnt 1.0 DELTA]	The number of all draft capture credit transactions processed during the current day.
dly_dc_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture credit transactions processed during the current day.
dly_dc_adj_cnt [cnt 1.0 DELTA]	The number of all draft capture adjustment transactions processed during the current day.
dly_dc_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture adjustment transactions processed during the current day.
cur_net_db_cnt [cnt 1.0 DELTA]	The number of all debit transactions that have occurred on the channel since the last channel cutover.
cur_net_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all debit transactions that have occurred on the channel since the last cutover.
cur_net_cr_cnt [cnt 1.0 DELTA]	The number of all credit transactions that have occurred on the channel since the last channel cutover.
cur_net_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all credit transactions that have occurred on the channel since the last cutover.
cur_net_adj_cnt [cnt 1.0 DELTA]	The number of all adjustment transactions that have occurred on the channel since the last channel cutover.
cur_net_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all adjustment transactions that have occurred on the channel since the last cutover.
cur_net_dc_db_cnt [cnt 1.0 DELTA]	The number of all draft capture debit transactions that have occurred on the channel since the last channel cutover.
cur_net_dc_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture debit transactions that have occurred on the channel since the last cutover.
cur_net_dc_cr_cnt [cnt 1.0 DELTA]	The number of all draft capture credit transactions that have occurred on the channel since the last channel cutover.
cur_net_dc_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture credit transactions that have occurred on the channel since the last cutover.
cur_net_dc_adj_cnt [cnt 1.0 DELTA]	The number of all draft capture adjustment transactions that have occurred on the channel since the last channel cutover.
cur_net_dc_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture adjustment transactions that have occurred on the channel since the last cutover.
prev_net_db_cnt [cnt 1.0 DELTA]	The number of all debit transactions that have occurred on the channel prior to the most recent channel cutover.

Element (type)	Description
prev_net_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all debit transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_cr_cnt [cnt 1.0 DELTA]	The number of all credit transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all credit transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_adj_cnt [cnt 1.0 DELTA]	The number of all adjustment transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all adjustment transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_dc_db_cnt [cnt 1.0 DELTA]	The number of all draft capture debit transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_dc_db_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture debit transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_dc_cr_cnt [cnt 1.0 DELTA]	The number of all draft capture credit transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_dc_cr_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture credit transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_dc_adj_cnt [cnt 1.0 DELTA]	The number of all draft capture adjustment transactions that have occurred on the channel prior to the most recent channel cutover.
prev_net_dc_adj_amt [amt 1.0 DELTA]	The total amount(the lowest currency unit in the channels currency code) of all draft capture adjustment transactions that have occurred on the channel prior to the most recent channel cutover.
cutover_bal_stat [bt_int16s]	A code identifying how a channel was cutover. Valid values are: 5 = Balanced. Via a close transaction. Totals sent by the channel balanced with the accumulated totals(or no totals sent). Totals are journalled and cleared. 6 = Out of Balance. Via a closed transaction. Totals sent by the channel did not agree with the accumulated totals and require verification. Totals are journalled and cleared. 8 = Forced Balance(incomplete batch). The channel was cutover by the Merchant Component. Totals are journalled and only the Current Network totals are reset to zero. This method is used when the the CHNL_CUTOVER_TYPE is end-of-day or end-of-shift or end-of-batch request and a close transaction has not been received from the channel within the Merchant Cutover Window. 9 = Forced Balanced. Totals are journalled and all totals are cleared. This method is used when CHNL_CUTOVER_TYPE is Merchant Component Force Cutover or First Financial Transaction within a Merchant Cutover Window.
instrm_typ_num [bt_int16s]	The number of instrument types specified for the channel in this data source. Default value: zero.
instrm_typ_1 [instrm_typ 1.0]	A code identifying the instrument type.

Element (type)	Description
instrm_typ_db_cnt_1 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_1 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_1 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_1 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_1 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_1 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_2 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_2 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_2 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_2 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_2 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_2 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_2 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_3 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_3 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_3 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_3 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_3 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_3 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_3 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_4 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_4 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.

Element (type)	Description
instrm_typ_db_amt_4 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_4 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_4 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_4 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_4 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_5 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_5 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_5 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_5 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_5 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_5 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_5 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_6 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_6 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_6 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_6 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_6 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_6 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_6 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_7 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_7 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_7 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.

Element (type)	Description
instrm_typ_cr_cnt_7 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_7 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_7 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_7 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_8 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_8 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_8 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_8 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_8 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_8 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_8 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_9 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_9 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_9 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_9 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.
instrm_typ_cr_amt_9 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_9 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_9 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
instrm_typ_10 [instrm_typ 1.0]	A code identifying the instrument type.
instrm_typ_db_cnt_10 [cnt 1.0 DELTA]	The number of debit transactions that have been performed for this instrument type within the balance period.
instrm_typ_db_amt_10 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all debit transactions that have occurred for this instrument type within the balance period.
instrm_typ_cr_cnt_10 [cnt 1.0 DELTA]	The number of credit transactions that have been performed for this instrument type within the balance period.

Element (type)	Description
instrm_typ_cr_amt_10 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all credit transactions that have occurred for this instrument type within the balance period.
instrm_typ_adj_cnt_10 [cnt 1.0 DELTA]	The number of adjustment transactions that have been performed for this instrument type within the balance period.
instrm_typ_adj_amt_10 [amt 1.0 DELTA]	The total amount(in the lowest currency unit) of all adjustment transactions that have occurred for this instrument type within the balance period.
rtrn_cnt [bt_int16s DELTA]	The number of merchandise return transactions that have occurred at the terminal for the current batch period.
rtrn_amt [bt_int64s DELTA]	The total amount of merchandise return transactions that have occurred at the device during the current batch. This field is used with the Return Limit Amount.
adj_cnt [bt_int16s DELTA]	The number of adjustment transactions that have occurred at the terminal for the current batch period.
adj_amt [bt_int64s DELTA]	The total amount of adjustment transactions that have occurred at the device during the current batch. This field is used with the Adjustment Limit Amount.
kpt_in_ts [timestamp 1.0]	Timestamp of the last successful exchange of the PIN Key Inbound.
kpt_in_txn_cnt [bt_int32s DELTA]	PIN Key Inbound Transaction Count. Counter identifying the number of transactions processed which used the inbound PIN key.
kam_in_cnsc_err_cnt [bt_int16s DELTA]	MAC Key Inbound Consecutive Error Count. Counter identifying the number of consecutive error transactions processed which used the inbound MAC key.
kam_in_ts [timestamp 1.0]	Timestamp of the last successful exchange of the MAC Key Inbound.
kam_in_txn_cnt [bt_int32s DELTA]	MAC Key Inbound Transaction Count. Counter identifying the number of transactions processed which used the inbound MAC key.
chan_dpnt_data [bt_binaryv(1024)]	The channel dependent data. For certain channels, the previous transaction information would be specified here. This would allow the channel to reverse the previous transaction indicated by a code in an incoming request for a new transaction.
dual_site_ind [bt_char]	Indicates if the record/transaction originated on the Local System or the Remote System. Valid values: space or L - Local (default). R - Remote.
chan_nam [bt_stringf(40)]	The name of the merchant. This field is left justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
notes [bt_stringf(100)]	An optional user defined field. This field is left-justified (containing any combination of alphanumeric and special characters). Default value is spaces.
lst_txn_dat_time [ts 1.0]	The date and time of the last transaction. The data is managed by the APACS device handler.
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
dflt_captr_mde [bt_stringf(1)]	This field indicates the default capture mode if it can not be determined from the external message. Valid values are: 0 - Authorize Only. 1 - Authorize and Capture.
proc_cde_prfl [bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions.

Element (type)	Description
	This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
chan_typ [typ 1.0]	A code identifying the type of channel. Valid values are: 00 - Not specified, 43 - NCR 2123/2126, 44 - NCR 2127, 45 - NCR 7000, 70 - VISA I Dial/APACS 20 terminal, 71 - VISA II Dial/APACS 40 terminal, 78 - Merchant Host Interface, D0 - Hypercom TDS, D1 - Custom POS device 1, D2 - Custom POS device 2, D3 - Custom POS device 3, D4 - Custom POS device 4, D5 - Custom POS device 5. Default value is 00.
act_cde_prfl [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
dflt_crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217. Used only if the currency code has not already been set from the external message.
acq_rte_prfl [prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
acq_txn_prfl [prfl_def 1.0]	The transaction profile for the acquirer who acquired the transaction. The acquirer transaction profile allows one or more acquirers to share processing code definitions and transactions allowed information. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
lang_id [bt_int16s]	A code indicating the language table used by the delivery channel when sending responses to the terminal. This code enables responses to be displayed on the terminal in one of three different languages. Valid values are: 1 - Language table 1, 2 - Language table 2, 3 - Language table 3. The particular language represented in each table is up to the discretion of the institution. For example, table 1 could be English, table 2 could be French, and table 3 could be Spanish. Default value is one.
crd_data_input_cap [bt_stringf(1)]	The first position in the Point of Service data. This data item indicates the primary means of getting the information on the contact card into the channel. Valid values are: 0 - unknown, 1 - manual(no channel), 2 - magnetic stripe read, 3 - barcode, 4 - OCR, 5 - ICC, 6 - key entered, 7 - manual and magnetic stripe, 8 - magnetic stripe and EMV, 9 - manual, magnetic stripe, and EMV. Default value is 2.
crdhldr_auth_cap [bt_stringf(1)]	The second position of the Point of Service Data. This data item indicates the primary means of verifying the cardholder at this channel. Valid values are: 0 - no electronic authentication, 1 - PIN, 2 - electronic signature analysis, 3 - biometrics, 4 - biographic, 5 - electronic authentication inoperative, 6 - other. Default value is 0.
crd_captr_cap [bt_stringf(1)]	The third position of the Point of Service data. This data item indicates whether or not the channel has the ability to capture a card. Valid values are: 0 - none, 1 - capture. Default value is 0.
oper_envmt [bt_stringf(1)]	The fourth position of the Point of Service Data. This data item indicates if the channel is attended by the card acceptor and its location. Valid values are: 0

Element (type)	Description
	- no channel used, 1 - attended on premises of card acceptor, 2 & 5 - unattended on premises of card acceptor, 3 - attended off the premises of card acceptor, 4 - unattended off premises of card acceptor. Default value is 2.
crd_data_output_cap [bt_stringf(1)]	The tenth position of the Point of Service data. This data item indicates the ability of the channel to update the card. The valid values are: 0 - unknown, 1 - none, 2 - magnetic strip write, 3 - ICC. Default value is 0.
chan_output_cap [bt_stringf(1)]	The eleventh position of the Point of Service data. This data item indicates the ability of the print/display messages. Valid values are: 0 - unknown, 1 - none, 2 - printing, 3 - display, 4 - printing and display. Default value is 4.
rtrn_lmt_cnt [bt_int16s DELTA]	The maximum number of merchandise return transactions allowed to be performed at the terminal for each terminal batch period. When this limit is exceeded, the action specified by the Return Threshold Action is taken. Valid values are 0 - 9999. The default is 0.
rtrn_lmt_amt [bt_int64s DELTA]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents), that can be accepted at the terminal via merchandise return transactions. This limit is invoked for each terminal batch period. When this limit is exceeded, the action specified by the Return Threshold Action is taken.
rtrn_thrld_act [bt_int16s]	Indicates what action to take when either the Return Count Limit or Return Amount Limit has been exceeded. Valid values are: 0 - Raise an event and continue processing (default). 1 - Deny the transaction. 2 - Refer the transaction.
adj_lmt_cnt [bt_int16s DELTA]	The maximum number of adjustment transactions allowed to be performed at the terminal for each terminal batch period. When this limit is exceeded, the action specified by the Adjustment Threshold Action is taken. Valid values are 0 - 9999. The default is 0.
adj_lmt_amt [bt_int64s DELTA]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents), that can be accepted at the terminal via adjustment transactions. This limit is invoked for each terminal batch period. When this limit is exceeded, the action specified by the Adjustment Threshold Action is taken.
adj_thrld_act [bt_int16s]	Indicates what action to take when either the Adjustment Count Limit or Adjustment Amount Limit has been exceeded. Valid values are: 0 - Raise an event and continue processing (default). 1 - Deny the transaction. 2 - Refer the transaction.
crd_accpt_bus_cde [bt_int32s]	The card acceptor business code pertaining to the merchants line of business. This field is 4 numeric digits.
crdhldr_prsn [bt_stringf(1)]	The fifth position in the Point of Service data. This data item indicates if the cardholder is present at the point of service and if not, why not. Valid values are: 0 - cardholder present, 1 - cardholder not present, unspecified, 2 - cardholder not present, mail order, 3 - cardholder not present, telephone, 4 - cardholder not present, standing authorization, 5 - cardholder electronic order. Default value is 0.
crd_prsn [bt_stringf(1)]	The sixth position in the Point of Service data. This data item indicates if the card is present at the point of service. Valid values are: 0 - card not present, 1 - card present. Default value is 1.
lst_cutover_ts [timestamp 1.0]	The timestamp when the channel was last cut over.

Element (type)	Description
tim_ofst [bt_int32s]	The time difference between the device location and the processor location defined in minutes. Valid range is -1400 to +1400.
addr_1 [bt_stringf(25)]	The address line 1. Where only one line of address is supported, this address will be used and addr_2 will be ignored. This field is left-justified (containing any combination of alphanumeric and special characters).
addr_2 [bt_stringf(25)]	The address line 2. This field is left-justified (containing any combination of alphanumeric and special characters).
city [bt_stringf(18)]	The city address. Field is left-justified (containing any combination of alphanumeric and special characters).
st [bt_stringf(3)]	The state, province or region code depending upon locale. This field contains alphanumeric and special characters.
postal_cde [bt_stringf(10)]	The postal code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
cntry [bt_int16s]	The numeric country code as defined in ISO document 4217.
contact1_nam [nam 1.0]	The first contact name. This field is left-justified (containing any combination of alphanumeric and special characters).
contact1_phn_num [phn_num 1.0]	The first contact phone number. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
emv_term_crd_cap [bt_binaryf(1)]	EMV Terminal Capabilities. Indicates the card data input capabilities of the terminal, as shown below. This field contains binary data. Byte 1 (Card Data Input Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 Reserved for future use 5 Reserved for future use 6 IC with contacts 7 Magnetic stripe 8 Manual key entry
emv_term_cvm [bt_binaryf(1)]	EMV Terminal Capabilities. Indicates the CVM capabilities of the terminal, as shown below. This field contains binary data. Byte 2 (CVM Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 No CVM Required 5 Enciphered PIN for offline verification 6 Signature (paper) 7 Enciphered PIN for online verification 8 Plaintext PIN for ICC verification
emv_term_script [bt_binaryf(1)]	EMV Terminal Capabilities. Indicates the security capabilities of the terminal, as shown below. This field contains binary data. Byte 3 (Security Capability) EMV Bit Position Meaning ----- 1 Reserved for future use 2 Reserved for future use 3 Reserved for future use 4 Combined DDA/CA generation 5 Reserved for future use 6 Card capture 7 Dynamic data authentication 8 Static data authentication
emv_ifd_serial_num [bt_stringf(8)]	The EMV Interface Device (IFD) Serial Number. This is the unique and permanent serial number assigned to the IFD by the manufacturer. This is an optional field that contains alphanumeric characters.
emv_appl_cap_ind [bt_char]	EMV Application Capability Indicator - indicates whether a terminal is able to manage EMV transactions for a given brand, allowing the issuing interface to correctly set the POS entry mode. Valid values are 0=none, 1=Visa only, 2=MasterCard only, and 3=Visa and MasterCard.
ctls_crd_data_input_cap [bt_stringf(1)]	The first position in the Point of Service data. This data item indicates the primary means of getting the information on the contactless card into the

Element (type)	Description
	channel. Valid values are: 0 - unknown or unspecified, 1 - None (contact-only or no terminal used, e.g. voice or ARU authorization), 2 - Proximity magnetic stripe, 3 - Proximity chip, 4 - Proximity magnetic stripe and proximity EMV. Default value is 1.
kdt_txn_cnt [bt_int32s DELTA]	Data Encryption Key Transaction Count. Counter identifying the number of transactions that have used the current data encryption key. Default is 0.
kdt_txn_err_cnt [bt_int16s DELTA]	Data Encryption Key Transaction Error Count. Counter identifying the number of transactions that have used the current data encryption key unsuccessfully. Default is 0.
chan_descr [bt_stringf(40)]	Channel Description. This field is left-justified (containing any combination of alphanumeric and special characters).
chan_descr_mbyte [bt_binaryl(80)]	Multi-byte Channel Description.
addr_1_mbyte [bt_binaryl(50)]	Multi-byte address line 1.
addr_2_mbyte [bt_binaryl(50)]	Multi-byte address line 2.
city_mbyte [bt_binaryl(36)]	Multi-byte city address.
st_mbyte [bt_binaryl(6)]	Multi-byte state, province or region code depending upon locale.
postal_cde_mbyte [bt_binaryl(20)]	Multi-byte postal code.
cntry_mbyte [bt_binaryl(6)]	Multi-byte country code.
contact1_nam_mbyte [bt_binaryl(32)]	Multi-byte contact name.
contact1_phn_num_mbyte [bt_binaryl(40)]	Multi-byte contact phone number.
notes_mbyte [bt_binaryl(200)]	Multi-byte optional user defined field.
chan_lmt_prfl [bt_stringf(16)]	Channel Limit Profile. Spaces indicate that no limits for the channel are configured.
chan_instrm_typ_rel_prfl [bt_stringf(16)]	Channel Instrument Type Relationship Profile. It is used to determine the limits profile by instrument type for a specific channel. Spaces indicate that no limits by channel and instrument type are configured.
home_site_ind [bt_char]	Indicates the home site of the device associated with the data record (i.e., which site is primary connection site) Valid values: Alpha-numeric character. The default value will be the Environment parameter named HOME_SITE_ID. If the parameter does not exist, the default will be a space.
kdt_in_ts [ts 1.0]	Timestamp of the last successful exchange of the data encryption key.
kam_txn_err_cnt [bt_int16s]	The MAC key error count, which indicates the number of unsuccessful MAC verifications that have occurred using the current key. Default is zero.
kpt_txn_err_cnt [bt_int16s]	The PIN key error count, which indicates the number of key sync errors that have occurred with the current key. Default is zero.

Merchant_Delivery_Channel_Profil (3.0) (mdcpd)

The Merchant Delivery Channel Profile table contains one record for each channel profile. This table is no longer used but remains for upgrades from version 06.4 and earlier.

[Audited] [Supports versioning]

Element (type)	Description
chan_prfl*[prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
chan_typ [typ 1.0]	A code identifying the type of channel. Valid values are: 00 - Not specified, 43 - NCR 2123/2126, 44 - NCR 2127, 45 - NCR 7000, 70 - VISA I Dial/APACS 20 terminal, 71 - VISA II Dial/APACS 40 terminal, 78 - Merchant Host Interface, D0 - Hypercom TDS, D1 - Custom POS device 1, D2 - Custom POS device 2, D3 - Custom POS device 3, D4 - Custom POS device 4, D5 - Custom POS device 5. Default value is 00.
act_cde_prfl [prfl_def 1.0]	The action code profile used to translate from an internal action code to an external action code or from an external action code to an internal action code. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
crd_accpt_bus_cde [bt_int32s]	The card acceptor business code pertaining to the merchants line of business. This field is 4 numeric digits.
dflt_crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217. Used only if the currency code has not already been set from the external message.
acq_rte_prfl [prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
acq_txn_prfl [prfl_def 1.0]	The transaction profile for the acquirer who acquired the transaction. The acquirer transaction profile allows one or more acquirers to share processing code definitions and transactions allowed information. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inbnd_auth_rqst_tim_lmt [bt_int16s]	The time limit in seconds to wait for a transaction response for an authorization request. Valid values are 1 to 9999. Defalut value is 15 seconds.
bal_support [bt_int16s]	The type of balancing transactions the channel supports. Used when the channel cutover type is 0, 1, or 2. The relevant totals are cleared on a cutover based on the code specified here. Valid values are: 0 - Batch totals are supported, 1 - Batch and shift totals are supported , 2 - Batch and day totals are supported , 3 - Batch, shift and day totals are supported, 4 - Shift and day totals are supported, 5 - Day totals are supported, 9 - No totals are supported.
chan_cutover_typ [bt_int16s]	A code indicating who cuts over the channel. Valid values are: 0 - Channel day close, 1 - Channel shift close, 2 - Channel batch close, 3 - Merchant Component forced cutover, 4 - First financial transaction cutover. Default value is 3.

Element (type)	Description
clos_flg [bt_flag]	A code indicating whether a channel supports implied close of batch, shift and daily totals when the sequence number is not in sync. Valid values are: 1 - channel does support implied close, 0 - channel does not support implied close. Default value is 0.
billing_info [bt_stringf(10)]	User defined information containing billing information that can be added to each balancing/cutover transaction for a channel. This is information data only. Default value is spaces.
lang_id [bt_int16s]	A code indicating the language table used by the delivery channel when sending responses to the terminal. This code enables responses to be displayed on the terminal in one of three different languages. Valid values are: 1 - Language table 1, 2 - Language table 2, 3 - Language table 3. The particular language represented in each table is up to the discretion of the institution. For example, table 1 could be English, table 2 could be French, and table 3 could be Spanish. Default value is one.
bal_opt_info [bt_int16s]	The balance information an acquirer will return on all transactions when the issuer balance information option is no preference. Valid values are: 1 = Ledger Balance Only, 2 = Available Balance or Available Credit Only, 0 = Both Ledger and Available. Default value is 0.
cmpl_trk_data [bt_flag]	A flag indicating whether the channel is capable of capturing and transmitting complete track data on transactions initiated by swiping the card through the reader on the channel. Valid values are: 1 - the channel is capable, 0 - the channel is not capable. Default value is 1.
chan_pin_entry [bt_flag]	A flag indicating whether the channel has PIN entry capability. Valid values are: 1 - channel has PIN entry capability, 0 - channel does not have PIN entry capability. Default value is 0.
crd_data_input_cap [bt_stringf(1)]	The first position in the Point of Service data. This data item indicates the primary means of getting the information on the card into the channel. Valid values are: 0 - unknown, 1 - manual(no channel), 2 - magnetic stripe read, 3 - barcode, 4 - OCR, 5 - ICC, 6 - key entered, 7 - proximity chip, 8 - proximity magnetic stripe. Default value is 2.
crdhldr_auth_cap [bt_stringf(1)]	The second position of the Point of Service Data. This data item indicates the primary means of verifying the cardholder at this channel. Valid values are: 0 - no electronic authentication, 1 - PIN, 2 - electronic signature analysis, 3 - biometrics, 4 - biographic, 5 - electronic authentication inoperative, 6 - other. Default value is 0.
crd_captr_cap [bt_stringf(1)]	The third position of the Point of Service data. This data item indicates whether or not the channel has the ability to capture a card. Valid values are: 0 - none, 1 - capture. Default value is 0.
oper_envmt [bt_stringf(1)]	The fourth position of the Point of Service Data. This data item indicates if the channel is attended by the card acceptor and its location. Valid values are: 0 - no channel used, 1 - attended on premises of card acceptor, 2 & 5 - unattended on premises of card acceptor, 3 - attended off the premises of card acceptor, 4 - unattended off peremises of card acceptor. Default value is 2.
crd_data_output_cap [bt_stringf(1)]	The tenth position of the Point of Service data. This data item indicates the ability of the channel to update the card. The valid value are: 0 - unknown, 1 - none, 2 - magnetic strip write, 3 - ICC. Default value is 0.
chan_output_cap [bt_stringf(1)]	The eleventh position of the Point of Service data. This data item indicates the ability of the print/display messages. Valid values are: 0 - unknown, 1 - none, 2 - printing, 3 - display, 4 - printing and display. Default value is 4.

Element (type)	Description
pin_captr_cap [bt_stringf(1)]	The twelfth position of the Point of Service data. This data item indicates the length of PIN which the acquirer end-point is capable of capturing. Valid values are: 0 - no PIN capture capability, 1 - PIN capture capability unknown, 4 - four characters, 5 - five characters, 6 - six characters, 7 - seven characters, 8 - eight characters, 9 - nine characters, A - ten characters, B - eleven characters, C - twelve characters, S - PIN has been verified. Default value is 0.
mac_ind [bt_flag]	An indicator specifying whether the channel supports MACing. Valid values are: 1 - the channel supports MACing, 0 - the channel does not support MACing. Default value is 0.
apprv_cde_lgth [bt_int16s]	The maximum length of the approval code that the acquirer can handle. Valid values are: 2 to 6. Default value is 6.
clerk_flg [bt_flag]	A flag indicating whether operator (clerk) totals are maintained for the channel. Valid values are: 0 - No totals are maintained, 1 - All totals(debit, credit, adjustment, cash out and check) are maintained. The default value is 0. When this indicator is set to 1, all clerk totals are maintained for the operator who is currently logged on. These totals are journalled and cleared by a batch close transaction or when a new operator logon occurs.
jrnl_btch_ttl [bt_flag]	A code indicating whether batch totals are journaled during a cutover. Valid values are: 1 - journal the batch totals, 0 - do not journal the batch totals. Default value is 1.
jrnl_clerk_ttl [bt_flag]	A code indicating whether the clerk totals are journalled during a cutover. Valid values are: 1 - journal the clerk totals, 0 - do not journal the clerk totals. Default value is 1.
jrnl_shift_ttl [bt_flag]	A code indicating whether the shift totals are journalled during a cutover. Valid values are: 1 - journal the shift totals, 0 - do not journal the shift totals. Default value is 1.
jrnl_dly_ttl [bt_flag]	A code indicating whether the daily totals are journalled during a cutover. Valid values are: 1 - journal the day totals, 0 - do not journal the day totals. Default value is 1.
jrnl_network_ttl [bt_flag]	A code indicating whether the network totals are journalled during a cutover. Valid values are: 1 - journal the network totals, 0 - do not journal the network totals. Default value is 1.
jrnl_instrm_typ_ttl [bt_flag]	A code indicating whether the instrument type totals are journalled during a cutover. Valid values are: 1 - journal the instrument type totals, 0 - do not journal the instrument type totals. Default value is 1.
dflt_pre_auth_hold_incr [bt_char]	The unit of time to retain the authorization hold if not specified in the external message. Valid values are: 1 - days, 2 - hours, 3 - minutes. Default value is 3. Used only if the pre-authorization hold time has not already been set from the external message for a pre-authorization request.
dflt_pre_auth_hold_tim [bt_stringf(2)]	Default time limit to hold a pre-authorization transaction. The value in this element is used when a time limit is not specified in the external message. The value specified corresponds to units of time defined in the PRE_AUTH_HOLD_INCR element. Valid values are: 00 - 99. Default value is 00.
chan_prfl_descr [bt_stringv(20)]	This field documents the purpose of the specific record.
chan_resp_ttls [bt_stringf(1)]	An indicator of which types of totals to return to a device in a response to a subtotals request. Valid values are: A - All totals. D - Draft capture totals only (default). This field is currently only use by the SPDH.
rvsl_resp [bt_flag]	A flag indicating if a reversal response message should be sent to the device upon receipt of a reversal message. Valid values are: 0 - No, do not send a reversal

Element (type)	Description
	response (default). 1 - Yes, send a reversal response. This field is currently only used by the SPDH.
chan_cnfg_prfl [prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files.
rtrn_lmt_cnt [bt_int16s]	The maximum number of merchandise return transactions allowed to be performed at the terminal for each terminal batch period. When this limit is exceeded, the action specified by the Return Threshold Action is taken. Valid values are 0 - 9999. The default is 0.
rtrn_lmt_amt [bt_int64s]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents), that can be accepted at the terminal via merchandise return transactions. This limit is invoked for each terminal batch period. When this limit is exceeded, the action specified by the Return Threshold Action is taken.
rtrn_thrhd_act [bt_int16s]	Indicates what action to take when either the Return Count Limit or Return Amount Limit has been exceeded. Valid values are: 0 - Raise an event and continue processing (default). 1 - Deny the transaction. 2 - Refer the transaction.
adj_lmt_cnt [bt_int16s]	The maximum number of adjustment transactions allowed to be performed at the terminal for each terminal batch period. When this limit is exceeded, the action specified by the Adjustment Threshold Action is taken. Valid values are 0 - 9999. The default is 0.
adj_lmt_amt [bt_int64s]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents), that can be accepted at the terminal via adjustment transactions. This limit is invoked for each terminal batch period. When this limit is exceeded, the action specified by the Adjustment Threshold Action is taken.
adj_thrhd_act [bt_int16s]	Indicates what action to take when either the Adjustment Count Limit or Adjustment Amount Limit has been exceeded. Valid values are: 0 - Raise an event and continue processing (default). 1 - Deny the transaction. 2 - Refer the transaction.
max_kam_cnsc_err_cnt [bt_int16s]	The number of consecutive MAC key errors allowed before requesting a new key. Valid values are 0 to 9999. 0 indicates no consecutive error count limit is used. Default value is 0. For the KEYF, if an error limit is configured, a minimum of 5 errors is required.
kpt_timr_lmt [bt_int32s]	PIN Key Timer Limit indicates the amount of time in minutes to use the current PIN Key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of minutes.
max_kpt_txn_cnt [bt_int32s]	The number of PIN Key transactions that are allowed before requesting a new key. Valid values are 0 to 99999 (9,999 for KEYF). 0 indicates no transaction count limit is used. Default value is 0.
kam_timr_lmt [bt_int32s]	MAC Key Timer Limit indicates the amount of time in minutes to use the current MAC key. Valid values are: 0 - 99999 minutes. 0 indicates no time limit used. Default value is 0. This field is written to disk as number of minutes.
max_kam_txn_cnt [bt_int32s]	The number of MAC generations/verifications that are allowed before requesting a new key. Valid values are 0 to 99999 (9,999 for KEYF). 0 indicates no transaction count limit is used. Default value is 0.
chan_proc_mde [bt_stringf(1)]	The Channel Processing Mode indicates the mode of operation for the channel. Valid values are: 0 = Single-threaded (default). 1 = Multi-threaded.
chan_data_lgth [bt_int32s]	The length indicating the size of the Channel Data. The range is zero to 1024. Default value is zero.

Element (type)	Description
chan_proto [bt_int16s]	The protocol used by the channel. Valid values are: 0 - Dial-up. 1 - Other (default).
dev_proto [typ 1.0]	A code identifying the device protocol. Valid values are 00 - None (default), 01 - SPDH, 02 - APACS, 03 - HPDH.
flr_lmt_trig_onl_auth_flg [bt_flag]	A flag indicating whether to send floor limit triggering online auth amount to the channel. Valid values are: 0 – do not send, 1 – send. Default value is 0.
flr_lmt_trig_onl_auth_amt [bt_int64s]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents) that can be authorised by the channel without attempting to perform online authorisation.
flr_lmt_onl_auth_fail_flg [bt_flag]	A flag indicating whether to send floor limit online auth fail amount to the channel. Valid values are: 0 – do not send, 1 – send. Default value is 0.
flr_lmt_onl_auth_fail_amt [bt_int64s]	The maximum amount, in whole and fractional currency units (e.g., dollars and cents) that can be authorised by the channel following a failed online authorisation attempt.
btch_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain batch totals for the channel. Valid values are 0 - Batch totals not supported. 1 - Batch totals are supported. The default value is 0.
shift_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain shift totals for the channel. Valid values are 0 - Shift totals not supported. 1 - Shift totals are supported. The default value is 0.
dly_ttl_supported [bt_flag]	A flag indicating whether the channel manager should maintain daily totals for the channel. Valid values are 0 - Daily totals are not supported. 1 - Daily totals are supported. The default value is 0.
part_auth_alwd [bt_flag]	A flag indicating whether the channel supports partial authorizations. Valid values are 0 - Partial authorizations are not supported. 1 - Partial authorizations are supported. The default value is 0.

Merchant_Master_File (1.0) (mmfd)

No description on file.

[Audited] [Supports versioning]

OLTP: Merchant_Master_File_OLTP

Element (type)	Description
prm_fiid* [bt_stringf(4)]	The FIID or ABA number of the financial institution that issued the card. This value must be unique within the logical network.
prm_retl_id* [bt_stringf(19)]	Identifies the retailer or merchant that owns or operates the terminal at which this transaction originated. Equates to a single physical location or internet storefront. Form merchants with multiple store locations, merchant id must be unique per store.
prm_retl_clas [bt_stringf(15)]	Identifier used to group or classify retailers. For example this can be a concatenation of Corporate/region/principal/associate/chain.
prm_fltr_fld [bt_stringf(15)]	Used for Portfolio/Filter identification in the Analysis/Review System.

Element (type)	Description
<code>prm_retl_dba_nam [bt_stringf(40)]</code>	The Merchant doing business as name.
<code>prm_retl_bus_nam [bt_stringf(40)]</code>	The Merchant business name
<code>prm_store_num [bt_stringf(9)]</code>	Store number of the identifier
<code>prm_sic_cde [bt_stringf(4)]</code>	Standard Industrial Classification (SIC) code indicating the retailer's line of business. Valid values are per industry standard.
<code>prm_ecom_ind [bt_stringf(2)]</code>	Indicates whether the merchant can accept e-commerce transactions.
<code>prm_retl_addr_1 [bt_stringf(40)]</code>	First line of the retailer's street address.
<code>prm_retl_addr_2 [bt_stringf(40)]</code>	Second line of the retailer's street address.
<code>prm_retl_city [bt_stringf(30)]</code>	City in which the retailer is located.
<code>prm_retl_st [bt_stringf(3)]</code>	The alpha representation of the primary retailer's state of residence. This field may also contain the province or region where the primary retailer resides. Refer to the FIPS Processing Standards Publication 6-3 for valid state codes. Default is spaces.
<code>prm_retl_cntry [bt_stringf(3)]</code>	The alpha representation of the retailer's country of residence. Refer to ISO 3166 (1988) manual for valid values.
<code>prm_retl_pstl_cde [bt_stringf(16)]</code>	The postal code/zip code for the retailer's residence.
<code>prm_cntct_nam [bt_stringf(40)]</code>	Name of Merchant contact.
<code>prm_cntct_phn_1 [bt_stringf(20)]</code>	Merchant contact telephone number.
<code>prm_cntct_phn_2 [bt_stringf(20)]</code>	Merchant contact alternate telephone number. (For NAB, facimile number).
<code>prm_cntct_email_addr [bt_stringf(40)]</code>	Merchant contact email address.
<code>prm_stat [bt_char]</code>	Merchant status. Valid values include: O -Open, C-Closed, etc.
<code>prm_actvty_stat [bt_char]</code>	Merchant activity status. Valid value include 0 -Inactive, 1 -Active.
<code>prm_opn_dat [bt_stringf(8)]</code>	Date of the account was opened. Format CCYYMMDD.
<code>prm_first_actv_dat [bt_stringf(8)]</code>	Date of the account was first operated. Format CCYYMMDD.
<code>prm_last_actv_dat [bt_stringf(8)]</code>	Date of the account last traded. Format CCYYMMDD.
<code>prm_last_actv_amt [bt_stringf(16)]</code>	Amount of last deposit/refund to the merchant account
<code>prm_clos_dat [bt_stringf(8)]</code>	Date the account was closed.
<code>prm_clos_rsn_cde [bt_stringf(2)]</code>	Reason code indicating why the account was closed
<code>prm_seasonl_cde [bt_char]</code>	Seasonal Code. Valid values include: D -Seasonal, don't bill, B -Seasonal, bill, N -Not Seasonal.
<code>prm_own_typ [bt_char]</code>	Ownership type. Valid values include: C -Corporation, S -Sole proprietorship, P -Partnership.
<code>prm_own_chng_dat [bt_stringf(8)]</code>	Date the Merchant ownership changed Format is CCYYMMDD
<code>prm_own_nam [bt_stringf(40)]</code>	Name of the owner of the business
<code>prm_own_govt_id [bt_stringf(20)]</code>	Merchant's tax or government ID
<code>prm_fi_ind [bt_stringf(10)]</code>	Internal identifier

Element (type)	Description
prm_cust_num_1 [bt_stringf(20)]	Internal defined customer number, electronic banking number, or DDA number
prm_cust_num_2 [bt_stringf(20)]	Internal defined customer number, electronic banking number, or DDA number
prm_setl_acct_detl_1 [bt_stringf(25)]	The Bank and Branch number of the settlement account
prm_setl_acct_detl_2 [bt_stringf(25)]	The Bank and Branch number of the settlement account
prm_expect_yy_vol [bt_stringf(16)]	Expected annual volume
prm_expect_mm_vol [bt_stringf(16)]	Expected monthly volume
prm_flr_lmt [bt_stringf(12)]	Floor limit
prm_norm_bus_hh_strt [bt_stringf(4)]	Normal business hours start time
prm_norm_bus_hh_end [bt_stringf(4)]	Normal business hours end time
prm_sec_corp_nam [bt_stringf(40)]	Secondary or Corporate name of Merchant
prm_sec_addr_1 [bt_stringf(40)]	First line of the secondary street address.
prm_sec_addr_2 [bt_stringf(40)]	Second line of the secondary street address
prm_sec_city [bt_stringf(30)]	City for the secondary address
prm_sec_st [bt_stringf(3)]	State or province for the secondary address
prm_sec_cntry [bt_stringf(3)]	Country for the secondary address.
prm_sec_postal_cde [bt_stringf(16)]	Postal code for the secondary address
prm_cred_bur_scr [bt_stringf(8)]	Credit Bureau Score
prm_expect_yy_vol_num [bt_stringf(8)]	Expected annual number of sales.
prm_expect_mm_vol_num [bt_stringf(8)]	Expected monthly number of sales.
prm_typ_good_serv [bt_stringf(19)]	Primary goods or services offered.
prm_cust_mstr_amt [bt_stringf(16)]	Amount field to hold user-defined amount
prm_cust_mstr_dat [bt_stringf(8)]	Date field to hold user-defined date
prm_cust_mstr fld_1 [bt_stringf(2)]	Alphanumeric field to hold user-defined data
prm_cust_mstr fld_2 [bt_stringf(4)]	Alphanumeric field to hold user-defined data

Merch_Instr_Typ_Relation (2.0) (mitrd)

The Merchant Instrument Type Relation table contains one record for each merchant and instrument type combination allowed that are not already specified in the Merchant Table.

[Audited] [Supports versioning]

Element (type)	Description
mrch_id* [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
instrm_typ* [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.
mrch_id_alt [bt_stringf(15)]	The alternate merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
mrch_pgm [bt_stringf(1)]	The merchant program in which the merchant participates for this instrument type. The meaning is defined by the network associated with this instrument type. Valid values are 0-9, A-Z and a space. Default value is a space.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
alt_acq_inst_id [inst_id 1.0]	Different card schemes assign different Acquiring Institution Identification Codes to the same bank by card type. This would allow support for different Acquiring Institution Identification Codes by card scheme.

MSGCNTX (1.0) (msgctx)

The Message Context file will be used to store server context. This table is required for Single Sign-on (SSO) within a USEC 1.x environment.

[Audited] [Supports versioning]

Element (type)	Description
MsgId* [bt_stringf(200)]	
SeqNum* [bt_int16s]	
ContFlg [bt_stringf(1)]	
ExpTm [ts 1.0]	
Context [bt_binaryl(3845)]	The raw XML that holds the audit record. See the current User Audit XML API Document for the format of this data.

NCR_PIN_Verification (1.0) (ncrd)

This data source holds the keys used in NCR PIN Verification. It is accessed using a Pin Verification Profile and a NCR PIN Version Number.

[Audited] [Supports versioning]

OLTP: NCR_PIN_Verification_OLTP

Element (type)	Description
pin_vrfy_prfl*[prfl_def 1.0]	An identifier for the profile to which this record applies. This field must contain a value that matches a PIN Verify Profile defined in the Prefix.
ncr_pin_ver_num*[bt_stringf(3)]	Version Number tied to a NCR PIN Verification instance. Contains three numeric characters 000 - 999
pvk_scheme [bt_char]	The Thales Key Scheme to be used with NCR PIN Verification keys. Valid values are: O - Old scheme. V - Variant scheme (default).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
key_encrypt [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_chk_values [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.

Netwk_Brand_Instrm_ReIn (1.0) (ipfnd)

Network Brand Relationship Table.

[Audited] [Supports versioning]

OLTP: Netwk_Brand_Instrm_ReIn_OLTP

Element (type)	Description
cmpnt_id*[bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
descr*[bt_stringf(16)]	The description field can vary by data source.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_1 [instrm_typ 1.0]	A code identifying the instrument type.
data_src_id [bt_stringf(16)]	The data source ID. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

NYCE_BIN_File_Updt (1.0) (nybin)

The NYCE BIN File Update data source contains the Interchange Prefix updates received from NYCE. Updates to the Interchange Prefix files will be applied by the NYCE IPF Refresh.

[Not Audited] [Does not support versioning]

Element (type)	Description
nyce_bin_rec [bt_stringv(80)]	This record contains a NYCE Interchange prefix update record. This record may contain a file header, change detail record or a trailer record.

NYCE_Institution (1.0) (nyind)

NYCE Institution Table.

[Audited] [Supports versioning]

OLTP: NYCE_Institution_OLTP

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_spnsr_bnk_id [bt_stringf(11)]	Acquirer Sponsor Bank ID.

NYCE_Interface (1.0) (nyifd)

NYCE Interface Table.

[Audited] [Supports versioning]

OLTP: NYCE_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_sec_cde [bt_stringf(8)]	Message Security Code.

OLTP_Warmboot (1.0) (ooltpd)

The OLTP Warmboot table contains a record for each data source modified that is used to load an OLTP. This data source is used to track OLTPs that need to be loaded and warmbooted as a result of UI updates to data sources.

[Audited] [Supports versioning]

Element (type)	Description
asgn_nam* [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
user_id [bt_stringf(16)]	The user ID of the person logging on into the system. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts_updt [ts 1.0]	File Maintenance Time Stamp of the update. Timestamp of last update to the data source record by GUI client application.
rbld_sbmttd [bt_flag]	Flag indicating whether a rebuild OLTP has been submitted since the data source has been changed.
wbt_sbmttd [bt_flag]	Flag indicating whether a rebuild OLTP has been submitted since the data source has been changed.
rbld_rspns [bt_stringv(1000)]	Response data from the rebuild and warmboot commands. The responses will be separated by the string @rsp@. This string will be placed at the end of each response.

OPERID (1.0) (OIF)

The Operator ID File is used to verify a bank agent has access to the cash vault while rear balancing a Diebold ATM.

[Audited] [Supports versioning]

Element (type)	Description
GrpIDTx* [bt_stringf(2)]	The Operator Group ID for the Operator ID File. This field may be any two characters.
OprtIDNum* [bt_int32s]	The Operator ID. The data is configured on the Diebold ATM Operator ID table (OPERID). The table is accessed by the ES device handler only during administrative transactions for Diebold ATM devices.
TermIDTx* [bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ChstDrwrACSCd [bt_char]	A flag indicating whether or not the operator has access to the cash vault. If the value is Y, access is allowed. Otherwise access is not allowed.

OPTRCPT (1.0) (OR)

ATM Optional Receipts Profile Table. The data here is static data. The table relates the Optional Receipts Profile to the load groups used when a) the printer is operable and b) the printer is inoperable

[Audited] [Supports versioning]

Element (type)	Description
OptnRcptPrflTx* [bt_stringf(16)]	The profile ID used to link an ATM terminal to the Optional Receipts table (OPTRCPT). The data is configured on the ES ATDS1 table.
OptGrpTx [bt_stringf(4)]	Printer operable load group for optional receipts. The data is configured on the Optional Receipts table (OPTRCPT).
InprGrpTx [bt_stringf(4)]	Printer inoperable load group for optional receipts. This element is stored on the Optional Receipts table (OPTRCPT).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Password (2.0) (upswd)

Password table

[Audited] [Supports versioning]

Element (type)	Description
UserID* [bt_stringf(16)]	
Password [bt_stringf(64)]	
CreateTS [ts 1.0]	
StartDate [ts 1.0]	
ExpireDate [ts 1.0]	
LastMaintTS [ts 1.0]	

PBAL_Impacts (3.0) (pblimd)

The table contains updates to the Positive Balance table as a result of online transactions. The table is used to impact the Positive Balance table following a refresh.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acct_num* [acct_num 1.0]	The account number used when processing the transaction.
acct_typ* [typ 1.0]	The account type of an account number.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
updts [bt_stringv(3000)]	A tagged list of updates to an impacted file.

PermDetl (1.0) (uprmdt)

Permission Detail table

[Audited] [Supports versioning]

Element (type)	Description
PermissionID*[bt_stringf(30)]	
ObjectID*[bt_stringf(30)]	
PermissionTypeCode [bt_stringf(2)]	

PermGrp (1.0) (uprmgr)

Permission Group table

[Audited] [Supports versioning]

Element (type)	Description
PermissionGroupID*[bt_stringf(30)]	
Descr [bt_stringf(50)]	
LastMaintTS [ts 1.0]	
OwnerID [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.

Perms (1.0) (uperms)

Permissions table

[Audited] [Supports versioning]

Element (type)	Description
PermissionID*[bt_stringf(30)]	
TaskID [bt_stringf(30)]	
Descr [bt_stringf(50)]	
LastMaintTS [ts 1.0]	
OwnerID [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.

PermType (1.0) (uprmtty)

Permission Type Code table

[Audited] [Supports versioning]

Element (type)	Description
PermissionTypeCode* [bt_stringf(2)]	
PermissionTypeName [bt_stringf(30)]	
Descr [bt_stringf(50)]	

Perusal_Script (1.0) (perscd)

The Perusal Script table contains one record for each user profile, query type and query name in the system. The executable script name is defined.

[Audited] [Supports versioning]

OLTP: Perusal_Script_OLTP

Element (type)	Description
user_prfl* [usr_prfl 1.0]	The user profile to which the operator belongs which dictates access to the reporting scripts available. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
qry_typ* [typ 1.0]	The script query type. Valid values are: SS - Summary script, DS - Detailed Script. Default value is SS.
qry_nam* [bt_stringf(60)]	The query name for a script header and script body combination. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
hdr_script_nam [nam 1.0]	The name of the header script. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
script_nam [nam 1.0]	The name of an executable script. This field is left-justified, upper case (containing any combination of alphanumeric and special character, but without any embedded spaces).

PmGpXPrm (1.0) (upmgpx)

Permission Group Permissions table

[Audited] [Supports versioning]

Element (type)	Description
PermissionGroupID* [bt_stringf(30)]	
PermissionID* [bt_stringf(30)]	

PMX (1.0) (pmxd)

This table is used as output for extract scripts.

[Not Audited] [Does not support versioning]

Element (type)	Description
pmx_element [bt_stringv(4058)]	The character buffer used as output for extract scripts.

Positive_Balance (2.0) (pbald)

The Positive Balance table contains the start of day balances and status information for an account.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acct_num* [acct_num 1.0]	The account number used when processing the transaction.
acct_typ* [typ 1.0]	The account type of an account number.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acct_cat [bt_int16s]	Account Category. Specifies the category of the account type. Valid values are: 0 (debit). 1 (credit).
refr_ts [yymmddhhmmss 1.0]	Refresh Time Stamp. Timestamp of the refresh that created this record.
refr_id [bt_stringf(32)]	An indicator of the refresh that created this record. This field is informational only.
acct_stat [bt_stringf(2)]	The status of the account. Valid values are: 00 - 15 = open (accounts with a status in this range will be included in OAR account selection). All other values are user-defined.
acct_stat_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the account status was changed.
crncy_cde [crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
avail_bal_strt [bt_int64s]	The start of day available balance (debit account).
avail_bal_strt_dat [yyyyymmdd 1.0]	The date of the start of day available balance (debit account).
ledg_bal_strt [bt_int64s]	The start of day ledger balance (debit account).
ledg_bal_strt_dat [yyyyymmdd 1.0]	The date of the start of day ledger balance (debit account).
avail_cr_strt [bt_int64s]	The start of day available credit (credit account).
avail_cr_strt_dat [yyyyymmdd 1.0]	The date of the start of day available credit (credit account).

Element (type)	Description
cr_lmt [bt_int64s]	The credit limit for a credit account. This field does not pertain to debit accounts.
lst_dep_amt [bt_int64s]	The amount of the last deposit to an account.
lst_dep_dat [yymmddhhmmss 1.0]	The date of the last deposit to an account.
lst_wdl_amt [bt_int64s]	The amount of the last withdrawal from an account.
lst_wdl_dat [yymmddhhmmss 1.0]	The date of the last withdrawal from an account.
fee_prfl [prfl_def 1.0]	The fee profile. Used as part of the primary key to the Fee Table. (Future Use)
lmt_prfl [prfl_def 1.0]	The limit profile. Used as the key to the Limit Table.
cash_adv_min [bt_int32s]	The minimum cash advance amount, in whole currency units (e.g., dollars), allowed by the device. A value of zero represents no minimum is used.
cash_adv_incr_amt [bt_int32s]	The standard increment, in whole currency units (e.g., dollars), over the minimum cash advance amount.
intrst_accru_cur [bt_int64s]	The current amount of accrued interest on the account.
intrst_accru_ytd [bt_int64s]	The total amount of year-to-date accrued interest on the account.
min_pmnt_amt [bt_int64s]	The current minimum due of the next payment.
nxt_pmnt_dat [yymmddhhmmss 1.0]	The due date of the next payment.
lmt_usg_1_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_1_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_1_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_1_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_1_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_2_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.

Element (type)	Description
lmt_2_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_2_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_2_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_2_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_3_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_3_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_3_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_3_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_3_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_4_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_4_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.

Element (type)	Description
lmt_usg_4_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_4_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_4_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_5_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_5_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_5_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_5_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_5_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
lmt_usg_6_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_6_max [bt_int64s]	The maximum limit amount/count assigned to a specific limit name. Usages can be maintained to compare against the limit.
lmt_usg_6_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.

Element (type)	Description
lmt_usg_6_prd_opt [bt_int16s]	This value specifies the usage period for the limit. Valid values are: 0 - usages not cleared. 1 - Fixed number of days (default). 2 - One week. 3 - Two weeks. 4 - First and 15th of each month. 5 - Every month. 6 - Every 3 months. 7 - Every 6 months. 8 - Every year. 9 - Daily, except Saturdays, Sundays and holidays. 10 - Daily, except Sundays and holidays. 11 - Daily, except Saturdays and holidays. 12 - Fixed number of hours
lmt_usg_6_prd_adnl_data [bt_int16s]	This value further defines the Usage Period Option values. This field is used in the following ways: 1. If Usage Period Option = 1, this value specifies the length (days) of the usage period. (default is 3). 2. If the Usage Period Option = 2 or 3, this value indicates the day of the week that the usage period begins. Valid values are 1 - Sunday, 2 - Monday, 3 - Tuesday, 4 - Wednesday, 5 - Thursday, 6 - Friday, 7 - Saturday. (default is 1). 3. If the Usage Period Option is 5, 6, 7, or 8, this value indicates which day of the month the usage period begins. Valid values are 1 - 28 (default is 1). 4. If Usage Period Option = 12, this value specifies the length (hours) of the usage period. (default is 6). 5. All other Usage Period Options - this field is not applicable.
csm_buf_chng_dat [yymmddhhmmss 1.0]	Timestamp of the last time the CSM Buffer was changed.
csm_buf [bt_binaryv(1000)]	This variable length field is available to allow customer specific data.
lmt_usg_1_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_2_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_3_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_4_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_5_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).
lmt_usg_6_exp_dat [yyyyymmdd 1.0]	The date that a limit or limit override expires and is no longer used in processing. Must be a date in yyyyymmdd format or spaces (spaces indicates that the limit or limit override does not expire).

POS_TC_Proc_Code (1.0) (pstpd)

The POS Transaction Code to Processing Code table contains an entry for every BASE24 POS transaction code which may be received. The POS transaction code is mapped to a corresponding processing code.

[Audited] [Supports versioning]

Element (type)	Description
proc_cde_prfl*[bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pos_txn_cde*[bt_stringf(6)]	The transaction code used to describe the effect of a transaction on the customer account and the accounts affected. It is composed of the transaction code, the card type, the account type and the category code.
txn_subtyp*[bt_stringf(4)]	An optional value that can be used with an existing BASE24 Classic transaction code to define a new transaction type. Any four characters are permitted. Default value is spaces (not applicable).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
proc_cde [proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.

Prefix (8.0) (prfxd)

The Prefix Data Source defines each prefix that can be processed. One record must exist in the Data Source for each prefix to be processed. Note that if one prefix is used with multiple account number lengths, multiple records must exist in the Data Source--one for each account number length.

[Audited] [Supports versioning]

OLTP: Prefix_OLTP

Element (type)	Description
pan_lgth*[bt_int16s]	Pan Length.
prfx*[bt_stringf(11)]	The prefix is the first n digits of a Primary Account Number (PAN) which defines the issuer of the PAN. A best match is used where the prefix with the most digits is preferred over a prefix with fewer digits. This field is left-justified (containing numeric characters, without any embedded spaces).
rte_typ [bt_stringf(1)]	The route type identifies whether to use the acquirer/issuer profile or issuer profile only. If the acquirer/issuer profile is used, Router will perform a lookup using the Acquirer Issuer Relation table and then use the Route table. If the issuer profile only is used, only the Route table is used. Valid values are: 0 - Acquirer/Issuer, 1 - Issuer only. Default value is 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
inst_id [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
instrm_typ [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number,

Element (type)	Description
	User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.
iss_rte_prfl [prfl_def 1.0]	The route profile of the issuer whose customer initiated the transaction. The issuer route profile is defined where ever the issuer is determine and allows one or more issuers to share routing and authorization configurations. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
iss_txn_prfl [bt_stringf(16)]	The transaction profile for the issuer to which the customer belongs. The issuer transaction profile allows one of more issuers to share processing code definitions and transactions allowed information. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
iss_surch_prfl [prfl_def 1.0]	The Issuer Surcharge Profile. This allows Issuers to be grouped together in logical surcharging groups for Issuers that perform the same surcharging logic.
cv_bad_disp [typ 1.0]	The action which the Authorization processes will take when a cardholder uses a card that contains invalid verification data. The first occurrence of this field is used to set the action that will be taken when the Track data is complete. The second occurrence of this field is used to set the action that will be taken when the Track data is incomplete or its status is unknown. The second occurrence also applies to the CID for AMEX card schemes. This field is only used if the cv_keya_prfl field is not equal to blanks. Valid values for both occurances are: 0 = Note the situation and continue 1 = Deny and return the card 2 = Deny and retain the card 3 = Refer the transaction
cv_eff_dat [yyymm 1.0]	Contains the CVD expiration date. If a card had an expiration date greater than or equal to this date, a CVD value is expected on the card and CVD processing will occur. Otherwise, the card may not have a CVD value and CVD processing will not occur.
cv_chk_typ [bt_stringf(1)]	A flag indicating when card verification is to be attempted when processing complete and uncertain Track2 data. This field is only used if the cv_keya_prfl field is not equal to blanks. Valid values are: 0 = CV disabled - do not check Card Verification Data (CVD) 1 = Check CVD for complete Track2 data only 2 = Check CVD for both complete and uncertain Track2 data. 3 = Check CVD1 (complete track data must be present). If CVD1 is successfully verified, check CVD2, if available. 4 = Check CVD1 (complete track data must be present). If CVD1 is not successfully verified, check CVD2, if available. 5 = Check CVD1 (complete track data must be present). Check CVD2, if available, regardless of the CVD1 result.
cv_dat_chk_typ [bt_stringf(1)]	A flag that indicates the date format to be used in the call to verify Manual CVD information. Valid values are, 0-YYMM, 1-MMY, 2-YYMM first then MMY, 3-MMY first then YYMM.
cv_keya_prfl [prfl_def 1.0]	An identifier used to show the card verification profile to which this record belongs in the Card Verification data source. If this field is not blank, the Authorization processes will use the value of this field, among others, to read the appropriate KEYA card verification record. If this field contains blanks, then card verification will not be performed (if scripted). Valid values are any combination of alphanumeric characters and leading and trailing spaces.
pin_ofst_loc [trk_ofst 1.0]	Depending on the type of PIN verification being performed, this field indicates the location of the DES (IBM 3624) or Diebold PIN verification methods PIN offset, the VISA PVV PIN verification methods PIN Verification Value (PVV), or the Identikey PIN verification methods PIN Verification Number (PVN). It is used by the Authorization processes in PIN verification. This field is only used if the pv_keya_prfl field is not equal to blanks.

Element (type)	Description
	Valid values are: 0 = No offset or PVN is specified, but 0000 is used if an offset is required for the particular verification method. This value is not valid with VISA PVV. 1 = The PIN offset, PVV, or PVN is on the card, with the <code>trk2_pvv_ofst</code> field specifying the exact location on TRACK2, <code>trk1_pvv_ofst</code> specifying the exact location on Track1 and <code>trk3_pvv_ofst</code> specifying the exact location on Track3. 2 = The PIN offset, PVV, or PVN is in the Card Table.
pan_access_typ [bt_stringf(1)]	Indicates whether the member number on the card is to be used to access the cardholder record. Values are: 0 = Access using a member number of zero. 1 = Access using member number from card.
pin_vrfy_typ [typ 1.0]	The type of PIN verification to perform for cards whose prefix matches this record. Valid values are: 00 = No PIN verification, 01 = DES (IBM 3624), 02 = Diebold, 04 = VISA PVV, 05 = NCR (Dutch), 06 = Identikey. Default value is 01.
pv_keya_prfl [prfl_def 1.0]	An identifier used to show the PIN verification profile to which this record belongs on the PIN verification data source (e.g., IBM DES, Diebold, Identikey, Visa PVV). If this field is not blank, the Authorization processes will use the value of this field, among others, to read the appropriate PIN verification record. If this field contains blanks, then the Authorization processes will not perform PIN verification. Valid values are any combination of alphanumeric characters and leading and trailing spaces.
pin_try_reset_opt [bt_stringf(1)]	The point at which the Bad PIN Tries usage is reset. The process compares the value of the Bad PIN Tries usage to the value in the MAX-PIN-TRY limit. Valid values are: 0 = The value of the Bad PIN Tries usage is reset with each usage period. (Default) 1 = The value of the Bad PIN Tries usage is reset when a good PIN is entered providing the MAX-PIN-TRY limit has not been reached. It is also reset with each usage period. 2 = The value of the Bad PIN Tries usage is reset regardless of the value of the MAX-PIN-TRY limit value. It is also reset with each usage period. 3 = The value of the Bad PIN Tries usage is reset when a good PIN is entered providing the MAX-PIN-TRY limit has not been reached. It is not reset with each usage period. 4 = The value of Bad PIN Tries usage is reset regardless of the value of the MAX-PIN-TRY limit value. It is not reset with each usage period.
max_pin_try [bt_int16s]	The number of times that the processes will allow a cardholder to attempt to enter their PIN correctly before declining the request and taking the action specified by the value in the BAD-PIN-DISP field. Valid values are 0-999.
bad_pin_disp [bt_stringf(1)]	The action which the processes will take when a cardholder has exceeded the allowable attempts to enter the correct PIN. This field is only used if the PV-KEYA-GRP field is not equal to blanks. Valid values: 0 = Return the card 1 = Retain the card
exp_chk_ind [bt_stringf(1)]	Indicates the type of card expiration date check to use for this prefix. Values are: 0 = Do not check the expiration date. 1 = Check the expiration date on the card. 2 = Check the expiration date in the Cardholder Account Data Source.
mbr_lgth [bt_int16s]	The length of the member number in the Track of the card. It is assumed the length is the same regardless of which track it is encoded on. This length is used in conjunction with the value in the MBR-OFST field to allow for retrieval of the member number from cards issued with this prefix. The value in this field is used when the value in the PAN-ACCESS-TYPE field is set to 1.
max_pre_auth_hlds [bt_int16s]	The maximum number of preauthorization holds that are allowed. Valid values are 0 through 10. The default value is 2.
algo_typ [bt_stringf(1)]	A flag indicating whether a PAN verification check should be performed as part of acquiring transactions. Authorization scripts may do their own PAN verification checks

Element (type)	Description
	that are not affected by this field. Valid values are: 0 - no check, 1 - double-add-double(MOD 10 Check)
trk_pref [bt_stringf(1)]	Indicates the order of which track is preferred for obtaining track data. A value of 1 indicates Track 1, then Track 2, then Track 3. A value of 2 indicates Track 1, then Track 3, then Track 2. A value of 3 indicates Track 2, then Track 1, then Track 3. A value of 4 indicates Track 2, then Track 3, then Track 1. A value of 5 indicates Track 3, then Track 1, then Track 2. A value of 6 indicates Track 3, then Track 2, then Track 1. Default value is 3.
trk1_algo_ofst [trk_ofst 1.0]	The offset to the algorithm number or VISA PVV PIN verification key indicator in Track 1 of the card (depending on the type of PIN verification being used). This offset allows for retrieval of the indicated value from cards issued with this prefix.
trk1_cv_ofst [trk_ofst 1.0]	The TRACK 1 offset of the card verification data. If this field is equal to zero then card verification will not be performed by the Authorization processes. This field is only used if the CV-KEYA-PRFL field is not equal to blanks. Valid values are 0-99.
trk1_dat_ofst [trk_ofst 1.0]	The offset to the expiration date on Track 1 of the card. This offset is retrieved and checked against today's date when the institution chooses to have the expiration date on cards with this prefix checked (i.e., the value in the EXP-CHK-IND field is set to 1). A zero value is not allowed in this field if the value in the EXP-CHK-IND field is set to 1.
trk1_mbr_ofst [trk_ofst 1.0]	The offset to the member number in Track 1 of the card. This offset allows for retrieval of the member number from cards issued with this prefix.
trk1_pvv_ofst [trk_ofst 1.0]	The offset to the PIN offset, PIN verification value, or PIN verification number in Track 1 of the card (depending on the type of PIN verification being used). This offset allows for retrieval of the indicated value from cards issued with this prefix. The value in this field is required if the indicated value is to be retrieved from the card (i.e., the value in the PIN-OFST-LOC field is set to 1).
trk1_sc_ofst [trk_ofst 1.0]	The TRACK1 offset of the service code data. If this field is equal to zero then card verification will not be performed by the Authorization processes. This field is only used if the CV-KEYA-PRFL field is not equal to blanks. Valid values are 0-99.
trk1_max_lgth [bt_int16s]	Indicates the maximum length of the Track 1 data on the card. Default value is 0.
trk1_min_lgth [bt_int16s]	Indicates the minimum length of the Track 1 data on the card. Default value is 0.
trk2_algo_ofst [trk_ofst 1.0]	The offset to the algorithm number or VISA PVV PIN verification key indicator in Track 2 of the card (depending on the type of PIN verification being used). This offset allows for retrieval of the indicated value from cards issued with this prefix.
trk2_cv_ofst [trk_ofst 1.0]	The TRACK 2 offset of the card verification data. If this field is equal to zero then card verification will not be performed by the Authorization processes. This field is only used if the CV-KEYA-PRFL field is not equal to blanks. Valid values are 0-99.
trk2_dat_ofst [trk_ofst 1.0]	The offset to the expiration date on Track 2 of the card. This offset is retrieved and checked against today's date when the institution chooses to have the expiration date on cards with this prefix checked (i.e., the value in the EXP-CHK-IND field is set to 1). A zero value is not allowed in this field if the value in the EXP-CHK-IND field is set to 1.
trk2_mbr_ofst [trk_ofst 1.0]	The offset to the member number in Track 2 of the card. This offset allows for retrieval of the member number from cards issued with this prefix.

Element (type)	Description
trk2_pvv_ofst [trk_ofst 1.0]	The offset to the PIN offset, PIN verification value, or PIN verification number in Track 2 of the card (depending on the type of PIN verification being used). This offset allows for retrieval of the indicated value from cards issued with this prefix. The value in this field is required if the indicated value is to be retrieved from the card (i.e., the value in the PIN-OFST-LOC field is set to 1).
trk2_sc_ofst [trk_ofst 1.0]	The TRACK 2 offset of the service code data. If this field is equal to zero then card verification will not be performed by the Authorization processes. This field is only used if the CV-KEYA-PRFL field is not equal to blanks. Valid values are 0-99.
trk2_max_lgth [bt_int16s]	Indicates the maximum length of the Track 2 data on the card. Default value is 0.
trk2_min_lgth [bt_int16s]	Indicates the minimum length of the Track 2 data on the card. Default value is 0.
trk3_algo_ofst [trk_ofst 1.0]	The offset to the algorithm number or VISA PVV PIN verification key indicator in Track 3 of the card (depending on the type of PIN verification being used). This offset allows for retrieval of the indicated value from cards issued with this prefix.
trk3_cv_ofst [trk_ofst 1.0]	The TRACK 3 offset of the card verification data. If this field is equal to zero then card verification will not be performed by the Authorization processes. This field is only used if the CV-KEYA-PRFL field is not equal to blanks. Valid values are 0-99.
trk3_dat_ofst [trk_ofst 1.0]	The offset to the expiration date on Track 3 of the card. This offset is retrieved and checked against today's date when the institution chooses to have the expiration date on cards with this prefix checked (i.e., the value in the EXP-CHK-IND field is set to 1). A zero value is not allowed in this field if the value in the EXP-CHK-IND field is set to 1.
trk3_mbr_ofst [trk_ofst 1.0]	The offset to the member number in Track 3 of the card. This offset allows for retrieval of the member number from cards issued with this prefix.
trk3_pvv_ofst [trk_ofst 1.0]	The offset to the PIN offset, PIN verification value, or PIN verification number in Track 3 of the card (depending on the type of PIN verification being used). This offset allows for retrieval of the indicated value from cards issued with this prefix. The value in this field is required if the indicated value is to be retrieved from the card (i.e., the value in the PIN-OFST-LOC field is set to 1).
trk3_sc_ofst [trk_ofst 1.0]	The TRACK 3 offset of the service code data. If this field is equal to zero then card verification will not be performed by the Authorization processes. This field is only used if the CV-KEYA-PRFL field is not equal to blanks. Valid values are 0-99.
trk3_max_lgth [bt_int16s]	Indicates the maximum length of the Track 3 data on the card. Default value is 0.
trk3_min_lgth [bt_int16s]	Indicates the minimum length of the Track 3 data on the card. Default value is 0.
emv_auth_key_prfl [prfl_def 1.0]	A profile used to access the Authorization Key file which contains the key data required for CAM verification. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without embedded spaces). If this field is spaces, CAM authentication will not be performed. The default value is spaces.
cam_chk_typ [bt_int16s]	This field determines the action to be performed if the ARQC has not been validated. Valid values are: 0 - Do not perform CAM check 1 - Perform CAM check only if CAM data is reliable 2 - Perform CAM check if CAM data is reliable or unreliable
bad_cam_act_reliable [bt_int16s]	This field determines the action to be performed if the CAM verification fails and CAM data is reliable. Valid values are: 0 - Continue processing the transaction 1 - Decline

Element (type)	Description
	the transaction and return card 2 - Decline the transaction and retain card 3 - Refer the transaction
bad_cam_act_unreliable [bt_int16s]	This field determines the action to be performed if the CAM verification fails and CAM data is unreliable. Valid values are: 0 - Continue processing the transaction 1 - Decline the transaction and return card 2 - Decline the transaction and retain card 3 - Refer the transaction
emv_frmt [bt_char]	Specifies the format of the EMV Issuer Application Data that will be used for this card prefix. A number of predefined formats for Issuer Application Data exist, as specified by the Payment Associations (VISA and Mastercard/Europay), but Issuer specific layouts may also be defined. Issuer Application Data typically contains information which is used in the derivation of the Application Cryptogram. Valid values are: 0 - Unspecified (format unknown, the contents will be transported as passthrough data.) 1 - Issuer Application Data Format defined by VISA in the VISA Integrated Circuit Card Specification. (Note this format is used for UKIS cards). 2 - M/Chip 2.1. 3 - M/Chip 4. 4 - CCD. 5 - Visa migrating to CCD. 6 - M/Chip 2.1 migrating to CCD. 7 - M/Chip 4 migrating to CCD. 8 to 9 - Reserved for other national or international scheme formats. A - Z - Proprietary format defined for the Issuer. (Custom formatting procedures required).
lmt_prfl [prfl_def 1.0]	The limit profile. Used as the key to the Limit Table.
siv_prfl [prfl_def 1.0]	An identifier for the profile which this record applies. This field must contain a value that matches a profile defined in the Card Verification data source.
siv_chk [bt_stringf(1)]	Secure Internet Validation Check. Valid values are: 0 = Do not verify CAVV Data during pre-screening(default). 1 = Verify CAVV Data during pre-screening.
siv_chk_typ [bt_stringf(1)]	Secure Internet Validation Check Type. Valid values are: 0 = SIV disabled - do not check CAVV Data (default). 1 = SIV enabled.
siv_bad_disp [bt_stringf(1)]	The action which the Authorization processes will take when a cardholder uses a card that contains invalid CAVV data. Valid values are: 0 = Note the situation and continue (default). 1 = Deny the transaction. 2 = Refer the transaction.
siv_not_prsn_disp [bt_stringf(1)]	The action which the Authorization processes will take when CAVV data is not present. Valid values are: 0 = Note the situation and continue (default). 1 = Deny the transaction. 2 = Refer the transaction.
fraud_opt [bt_stringf(1)]	Indicates whether a fraud system is used. Valid values are: 0 - do not use fraud system (default). 1 - score during authorization. 2 - notify after authorization.
pvv_lgth [bt_int16s]	Length of the PIN Verification Value. Valid values are 4 - 12, inclusive. Default value is 4.
combined_bal_flg [bt_char]	Flag that indicates whether the multiple balances can be combined during authorizations. Values are Y and N. The default is N which indicates that balances will not be combined in authorizations.
ovrdrft_options [bt_char]	Options used when calculating balances that are overdraft. The default value is N which indicates no overdraft options are used. The following values are valid: N - No overdraft protection (default). C - Credit line is used for overdraft. S - Savings is used for overdraft. A - Credit then savings is used for overdraft. B - Savings then credit is used for overdraft.
cv_retry [bt_int16s]	If a host/network/switch attempted CVD1 or CVD2 verification on behalf of the issuer and the CVD failed, this field indicates whether BASE24-es should attempt to verify the CVD1/CVD2. Valid values are: 0 = No, do not verify (default). 1 = Yes, verify.
cv2_req [bt_int16s]	Indicates if CVD2/CID verification is required for manually entered cards. Valid values are: 0 = No CVD2/CID verification required (default). 1 = CVD2/CID verification required

Element (type)	Description
	for all manually entered transactions. 2 = CVD2/CID verification required for cardholder not present transactions.
mnl_crd_entry_opt [bt_int16s]	Indicates the options for accepting or denying manually entered transactions. Valid values are: 0 = Do not deny manually entered transactions (default). 1 = Deny manually entered transactions without CVD2/CID where the cardholder does not provide the CVD2/CID value. 2 = Deny manually entered transactions where the cardholder does not provide a CVD2/CID value or the CVD2/CID value is illegible or the merchant does not provide the CVD2/CID value. 3 = Deny manually entered transactions.
offl_bad_pin_tries_act [bt_char]	Offline Bad PIN Tries Action. This field specifies the processing required when a PIN based EMV transaction contains data indicating that the offline PIN bad PIN try limit has been exceeded for the card. Valid values are: 0 = Do not perform EMV-specific processing (default). 1 = Decline the transaction and return the card. 2 = (Reserved). 3 = Perform an implicit Offline PIN Unblock by sending a PIN Unblock or PIN Change Script as indicated by the Offline PIN Management field. Note that this will only be performed if the online PIN and ARQC are successfully verified.
offl_pin_mgmt [bt_char]	Offline PIN Management. This field specifies the processing required when a Pin Change or PIN Unblock transaction is received. Valid values: 0 = Do not perform EMV-specific processing (default). 1 = Generate and return script command (PIN Unblock or PIN Change). 2 = Generate PIN Change script for both PIN Change and PIN Unblock transactions.
offl_pin_sppt_dat [bt_stringf(6)]	Indicates that all cards with this Prefix and Expiry date (or later), will support an Offline Pin. This field would then be used, in conjunction with the Card expiry date and Offline-PIN-Management flag, to determine the action to be performed on PIN Change and PIN Unblock transactions. Date in YYYYMM format. Default to spaces. (Card does not support Offline PIN).
trnsprt_key_loc [bt_stringf(16)]	An identifier (key locator) defining the transport key to be used to encrypt PIN Change data before journaling to the log file and subsequently extracted. Required to allow PIN Change data to be securely shared with card management systems. The field is left-justified, upper case(containing any combination of alphanumeric and special characters, but without any embedded spaces). Default to spaces.
emv_script_mac_lgth [bt_int16s]	Indicates the length of the MAC to be included in an EMV script. Valid values are: 0 – Use the MAC length configured in the script template. 4 (default), 6 or 8 characters.
emv_iss_rte_prfl [prfl_def 1.0]	The EMV route profile of the issuer whose customer initiated the EMV transaction. The EMV issuer route profile, if non-blank, overrides the Prefix issuer route profile for EMV transactions (i.e., transactions where the EMV Status TDE is present). This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
cam_chk_pre_scrn [bt_stringf(1)]	A flag indicating whether the ARQC should be verified before sending the transaction to the host. Valid values are: 0 - Do not verify the ARQC before sending the transaction to the host (default). 1 - Verify the ARQC before sending the transaction to the host.
tvr_chk_pre_scrn [bt_stringf(1)]	A flag indicating whether the Terminal Verification Results (TVR) should be verified before sending the EMV transaction to the host. Valid values are: 0 - Do not verify the TVR before sending the transaction to the host (default). 1 - Verify the TVR before sending the transaction to the host.
cvr_chk_pre_scrn [bt_stringf(1)]	A flag indicating whether the Card Verification Results (CVR) should be verified before sending the EMV transaction to the host. Valid values are: 0 - Do not verify the CVR before sending the transaction to the host (default). 1 - Verify the CVR before sending the transaction to the host.

Element (type)	Description
roc_chk_pre_scrn [bt_stringf(1)]	A flag indicating whether the Reason Online Code (ROC) should be validated before sending the EMV transaction to the host. Valid values are: 0 - Do not validate the ROC before sending the transaction to the host (default). 1 - Validate the ROC before sending the transaction to the host.
tvr_chk [bt_stringf(1)]	A flag indicating whether the Terminal Verification Results (TVR) check is to be performed during Authorization processing. Valid values are: 0 - Do not perform TVR checks (default). 1 - Perform TVR checks
cvr_chk [bt_stringf(1)]	A flag indicating whether the Card Verification Results (CVR) check is to be performed during Authorization processing. Valid values are: 0 - Do not perform CVR checks (default). 1 - Perform CVR checks.
roc_chk [bt_stringf(1)]	A flag indicating whether the Reason Online Code (ROC) value is to be checked Authorization processing. Valid values are: 0 - Do not perform ROC checks (default). 1 - Perform ROC checks.
force_onl_fallback_chk [bt_stringf(1)]	A flag indicating whether an EMV transaction should be forced to use the over-the-floor route destinations regardless of the transaction amount. Valid values are: 0 - Do not force the over-the-floor destinations (default). 1 - Force the over-the-floor destinations.
fallback_chk_pre_scrn [bt_stringf(1)]	A flag indicating whether checks should be performed before sending an EMV transaction to the host to determine if the transaction is a fallback transaction. Valid values are: 0 - Do not perform fallback checks before sending the transaction to the host (default). 1 - Perform fallback checks before sending the transaction to the host.
fallback_act [bt_stringf(1)]	The action to be taken if an EMV transaction is determined to be a fallback transaction. Valid values are: 0 - Continue processing the transaction (default). 1 - Deny the transaction. 2 - Refer the transaction.
emv_cv_eff_dat [yyyyymm 1.0]	This field contains the EMV CVD effective date. If a card has an expiration date greater than or equal to this date, an EMV CVD value is expected on the card and EMV CVD processing will occur. Otherwise, the card may not have an EMV CVD value and EMV CVD processing will not occur. Valid values are dates in the format YYMM. Default value is 200501.
emv_cv_chk_typ [bt_stringf(1)]	This field indicates the circumstances under which card verification should be performed on EMV transactions. Valid values are: 0 = Do not perform card verification (default value). 1 = Perform card verification only when an ARQC is not present. 2 = Perform card verification when an ARQC is not present or the ARQC has not been verified successfully. 3 = Always perform card verification.
emv_cv_chk_mthd [bt_stringf(1)]	This field indicates the algorithm and data used when card verification is performed on EMV transactions. Valid values are: 0 - Use non-EMV card verification (default). 1 - Replace the service code with the EMV service code.
emv_cv_srvc_cde [bt_stringf(3)]	This field contains the EMV service code. Valid values are 000 - 999. Default is 000.
cvr_prfl [prfl_def 1.0]	Card Verification Results (CVR) profile. Defined at the prefix level and is used as an element in the primary key to the Card Verification Results Status table. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
tvr_prfl [prfl_def 1.0]	Terminal Verification Results (TVR) profile. Defined at the prefix level and is used as an element in the primary key to the Terminal Verification Results Status table. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
roc_prfl [prfl_def 1.0]	Reason Online Code (ROC) profile. Defined at the prefix level and is used as an element in the primary key to the Reason Online Code Status table. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
exp_dat_cmp [bt_stringf(1)]	A flag indicating whether the transaction expiration date should be compared with the primary expiration date and secondary expiration date in the Card record to determine if the primary expiration date is no longer valid but the secondary expiration date is valid. Valid values are: 0 - No expiration date comparison required (default). 1 - Expiration date comparison required.
trk1_cv_lgth [bt_int16s]	The length of the Card Verification Digits in Track 1. Valid values are 0 - 5. Default is 3.
trk2_cv_lgth [bt_int16s]	The length of the Card Verification Digits in Track 2. Valid values are 0 - 5. Default is 3.
trk3_cv_lgth [bt_int16s]	The length of the Card Verification Digits in Track 3. Valid values are 0 - 5. Default is 3.
crd_scheme [bt_stringf(1)]	The card scheme. Valid values are: A - AMEX. M - MasterCard. V - Visa. N - Not applicable (default).
dcv_chk_typ [bt_stringf(1)]	A flag which indicates when Dynamic Card Verification should be attempted. This field is only used if the DCV-KEY-LOC field is not equal to blanks. Valid values are: 0 = DCV disabled - do not check Dynamic Card Verification Data (DCVD) - default value. 1 = CVC3 checking enabled. 2 = DCVV checking enabled. 3 = DCVV checking with split ATC in Track 1 enabled.
dcv_key_prfl [prfl_def 1.0]	An identifier which is used to show the Dynamic Card verification group that this prefix belongs to. If this field is not blank, the Authorization processes will send this field to the TSEC component so that the appropriate Dynamic Card Verification record is read in TSEC. If this field contains blanks, then Dynamic Card Verification will not be performed. Valid values are: Any combination of alphanumeric characters Leading and trailing spaces.
trk1_dcv_ofst [bt_int16s]	The offset of the Dynamic Card Verification digits on Track 1. If this field is equal to zero then Dynamic Card Verification will not be performed by the Authorization processes for transactions with Track 1. This field is only used if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0-99 (default is 0).
trk1_dcv_lgth [bt_int16s]	The length of the Dynamic Card Verification digits on Track 1. Valid values are: 0-9 (default is 0).
trk1_atc_ofst [bt_int16s]	The offset of the Application Transaction Counter on Track 1. If this field is equal to zero then Dynamic Card Verification will not be performed by the Authorization processes for transactions with Track 1. This field is used only if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0-99 (default is 0).
trk1_atc_lgth [bt_int16s]	The length of the Application Transaction Counter in Track 1. Valid values are: 0-9 (default is 0).
trk1_unpredict_num_ofst [bt_int16s]	The offset of the Unpredictable Number on Track 1. If this field is equal to zero then Dynamic Card Verification will not be performed by the Authorization processes for MasterCard transactions with Track 1. This field is used only if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0-99 (default is 0).
trk2_dcv_ofst [bt_int16s]	The offset of the Dynamic Card Verification digits on Track 2. If this field is equal to zero then Dynamic Card Verification will not be performed by the Authorization processes

Element (type)	Description
	for transactions with Track 2. This field is only used if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0-99 (default is 0).
trk2_dcv_lgth [bt_int16s]	The length of the Dynamic Card Verification digits on Track 2. Valid values are: 0-9 (default is 0).
trk2_atc_ofst [bt_int16s]	The offset of the Application Transaction Counter on Track 2. If this field is equal to zero then Dynamic Card Verification will not be performed by the Authorization processes for transactions with Track 2. This field is used only if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0-99 (default is 0).
trk2_atc_lgth [bt_int16s]	The length of the Application Transaction Counter in Track 2. Valid values are: 0-9 (default is 0).
trk2_unpredict_num_ofst [bt_int16s]	The offset of the Unpredictable Number on Track 2. If this field is equal to zero then Dynamic Card Verification will not be performed by the Authorization processes for MasterCard transactions with Track 2. This field is used only if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0-99 (default is 0).
dcv_pre_scrn [bt_stringf(1)]	A flag indicating whether a Dynamic Card Verification pre-screen check should be performed by the Authorization processes before sending a transaction to the host. This field is only used if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0 = If the host is online, the transaction request is sent to the host without verifying the Dynamic Card Verification (DCV) Digits (default). 1 = The Dynamic Card Verification (DCV) Digits are verified before attempting to send the transaction request to the host. If the DCV is invalid, the Authorization processes will perform the defined within the DCV-BAD-DISP field.
dcv_bad_disp [bt_stringf(1)]	The action which the Authorization processes will take when a cardholder uses a card that contains invalid Dynamic Card Verification data. This field is only used if the DCV-KEY-PRFL field is not equal to blanks. Valid values are: 0 = Note the situation and continue. 1 = Deny and return the card (default). 2 = Deny and retain the card. 3 = Refer the transaction (POS only).
atc_chk_typ [bt_stringf(1)]	This field determines whether the Application Transaction Counter (ATC) check is to be performed. Valid values are: 0 = Do not perform ATC (default). 1 = Perform ATC check on EMV. 2 = Perform ATC check on contactless magnetic transactions. 3 = Perform ATC check on EMV and contactless magnetic stripe transactions.
atc_pre_scrn [bt_stringf(1)]	A flag indicating whether an Application Transaction Counter (ATC) pre-screen check should be performed by the Authorization processes before sending a transaction to the host. Valid values are: 0 = If the host is online, the transaction request is sent to the host without verifying the Application Transaction Counter (ATC)(default). 1 = The Application Transaction Counter (ATC) is verified according the setting for ATC-CHK-TYP before attempting to send the transaction request to the host. If the ATC is invalid, the Authorization processes will perform the action defined within the ATC-BAD-DISP field.
atc_bad_disp [bt_stringf(1)]	The action which the Authorization processes will take when an ATC check fails. Valid values are: 0 = Note the situation and continue. 1 = Deny and return the card (default). 2 = Deny and retain the card. 3 = Refer the transaction (POS only).
dflt_pre_auth_hold_incr [bt_char]	The unit of time to retain the authorization hold if not specified in the external message. It is only used if the pre-authorization hold time has not already been set from the external message for a pre-authorization request. Valid values are: 1 - days, 2 - hours, 3 - minutes. Default value is 3.
dflt_pre_auth_hold_tim [bt_stringf(2)]	Default time limit to hold a pre-authorization transaction. The value in this element is used when a time limit is not specified in the external message. The value specified

Element (type)	Description
	corresponds to units of time defined in the PRE_AUTH_HOLD_INCR element. Valid values are: 00 - 99. Default value is 00.
hld_bal_chk [bt_flag]	This hold balance check is a flag to indicate whether the authorizer should include the holds in the file while checking the usages and limits. The value of 0 (false) should indicate no holds will be checked. The value of 1(true) indicates the holds will be included during the limits and usages check.
chk_base_flg [bt_int16s]	A flag used to indicate whether check transactions involving checks not defined in the Check Status data source should be included in the Total Cash Advance/Withdrawal usages and checked against the Total Cash Advance/Withdrawal limits. Valid values are: 0 = No, do not include in Total Cash Advance/Withdrawal usages. 1 = Yes, include in Total Cash Advance/Withdrawal usages.
chk_stat_chk_base_flg [bt_int16s]	A flag used to indicate whether check transactions involving checks defined in the Check Status data source should be included in the Total Cash Advance/Withdrawal usages and checked against the Total Cash Advance/Withdrawal limits. Valid values are: 0 = No, do not include in Total Cash Advance/Withdrawal usages. 1 = Yes, include in Total Cash Advance/Withdrawal usages.
spf_chk_pre_scrn [bt_int16s]	A flag indicating whether the Stop Payment data source should be checked before sending a check transaction to the host. Valid values are: 0 = Do not check the Stop Payment data source before sending the transaction to the host (default). 1 = Check the Stop Payment data source before sending the transaction to the host.
chk_stat_pre_scrn [bt_int16s]	A flag indicating whether the Check Status data source should be checked before sending a check transaction to the host. Valid values are: 0 = Do not check the Check Status data source before sending the transaction to the host (default). 1 = Check the Check Status data source before sending the transaction to the host.
nxt_onl_dat_prd [bt_int16s]	The number of days before a chip transaction will be required to be authorized on-line. Valid values are 0 - 999 (default value is 30).
trk2_pvv_ofst_2 [trk_ofst 1.0]	The offset to the PIN offset 2, PIN verification value 2, or PIN verification number 2 in Track 2 of the card (depending on the type of PIN verification being used). This offset allows for retrieval of the indicated value from cards issued with this prefix. The value in this field is required if the indicated value is to be retrieved from the card (i.e., the value in the PIN-OFFST-LOC field is set to 1) and the PIN Verification Type is Dual PVN.

Prefix_Block (1.0) (pfxbd)

The Prefix Block data source maintains stop list blocks by prefix data. The authorization process will use this new data source to determine if the transaction should be declined due to a block on the prefix data that limits the card's use.

[Audited] [Supports versioning]

OLTP: Prefix_Block_OLTP

Element (type)	Description
pan_lgth* [bt_int16s]	PAN Length. (Prikey, Altkey)
prfx* [bt_stringf(11)]	The prefix is the first n digits of a Primary Account Number (PAN) which defines the issuer of the PAN. A best match is used where the prefix with the most digits is preferred over a prefix with fewer digits. This field is left-justified (containing

Element (type)	Description
	numeric characters, without any embedded spaces). This field is required for a block against Prefix data, therefore, enter the prefix of the PAN. (Prikey, Altkey)
exp_dat* [yyyyymm 1.0]	The expiration date of the instrument in yyyyymm format. If this record is for a block against "a specific" expiration date, enter the expiration date of the card. If this record is for a block against "any" expiration date, this field requires only the default entry (all 9s in the data source, and all asterisks on the UI). (Prikey)
user_fld1 [bt_stringf(1)]	One byte filler/user field.
fm_ts [ts 1.0]	File Maintenance Timestamp. Timestamp of last update to the data source record.
refr_ts [yymmddhhmmss 1.0]	Refresh Time Stamp. Timestamp of the refresh that created this record.
refr_id [bt_stringf(32)]	An indicator of the refresh that created this record. This field is informational only.
prfx_blk_ts [yymmddhhmmss 1.0]	Prefix Block Time Stamp. Timestamp that the block on the prefix data was issued. (yymmddhhmmss)
blk_cde [bt_stringf(2)]	A code specifying the type of block/unblock placed on the Prefix data. Blocks can be configured for the following combination of Prefix data: * By PAN Length, Prefix, and Expiration Date. * By PAN Length and Prefix, where Expiration date is all asterisks. Valid values are any alphanumeric 2 digit code, with spaces being the default.

Presto_Interface (1.0) (prifd)

Presto Interface Table.

[Audited] [Supports versioning]

OLTP: Presto_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_sec_cde [bt_stringf(8)]	Message Security Code.
file_updt_id [bt_stringf(4)]	File Update Identifier.

Pre_Auth_Hold (3.0) (preaud)

The Pre-Auth Hold table contains pre-auth transactions for a specified card or account. A card/account can have a total of 70 holds associated with it.

[Audited] [Supports versioning]

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
id_typ* [bt_stringf(2)]	Indicates the type of entity the ID represents. Valid values are CD for card, AC for account.
id* [bt_stringf(28)]	The card or account number based on the id_typ field.
scndry_id* [bt_stringf(3)]	The secondary id associated with a card or account number based on the id_typ field. This could be a card sequence number or an account type. Default value is 000.
rec_num* [bt_stringf(3)]	This field is used to make a primary key unique when multiple rows exist for the other fields in the primary key. rec_num begins with value 1 except for the Card Account table which begins with value 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pre_auth_adnl [bt_int16s]	Indicates if additional pre-auths exist for an instrument type. Valid values are: 0 - No (default). 1 - Yes.
hld_typ_1 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_1 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_1 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_1 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_1 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_2 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_2 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_2 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_2 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_2 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_3 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_3 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_3 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_3 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.

Element (type)	Description
hld_exp_ts_3 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_4 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_4 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_4 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_4 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_4 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_5 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_5 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_5 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_5 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_5 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_6 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_6 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_6 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_6 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_6 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_7 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_7 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_7 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_7 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_7 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_8 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_8 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_8 [crncy_cde 1.0]	The currency code of the amount on hold.

Element (type)	Description
hld_id_8 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_8 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_9 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_9 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_9 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_9 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_9 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_10 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_10 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_10 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_10 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_10 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_11 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_11 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_11 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_11 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_11 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_12 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_12 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_12 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_12 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_12 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.

Element (type)	Description
hld_typ_13 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_13 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_13 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_13 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_13 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_14 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_14 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_14 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_14 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_14 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_15 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_15 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_15 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_15 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_15 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_16 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_16 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_16 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_16 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_16 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_17 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_17 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_17 [crncy_cde 1.0]	The currency code of the amount on hold.

Element (type)	Description
hld_id_17 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_17 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_18 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_18 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_18 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_18 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_18 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_19 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_19 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_19 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_19 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_19 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_20 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_20 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_20 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_20 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_20 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_21 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_21 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_21 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_21 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_21 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.

Element (type)	Description
hld_typ_22 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_22 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_22 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_22 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_22 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_23 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_23 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_23 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_23 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_23 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_24 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_24 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_24 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_24 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_24 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_25 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_25 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_25 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_25 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_25 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_26 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_26 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_26 [crncy_cde 1.0]	The currency code of the amount on hold.

Element (type)	Description
hld_id_26 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_26 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_27 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_27 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_27 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_27 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_27 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_28 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_28 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_28 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_28 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_28 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_29 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_29 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_29 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_29 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_29 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_30 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_30 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_30 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_30 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_30 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.

Element (type)	Description
hld_typ_31 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_31 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_31 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_31 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_31 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_32 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_32 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_32 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_32 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_32 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_33 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_33 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_33 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_33 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_33 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_34 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_34 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_34 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_34 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_34 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_35 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_35 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_35 [crncy_cde 1.0]	The currency code of the amount on hold.

Element (type)	Description
hld_id_35 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_35 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_36 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_36 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_36 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_36 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_36 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_37 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_37 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_37 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_37 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_37 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_38 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_38 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_38 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_38 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_38 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_39 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_39 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_39 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_39 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_39 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.

Element (type)	Description
hld_typ_40 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_40 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_40 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_40 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_40 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_41 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_41 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_41 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_41 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_41 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_42 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_42 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_42 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_42 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_42 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_43 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_43 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_43 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_43 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_43 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_44 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_44 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_44 [crncy_cde 1.0]	The currency code of the amount on hold.

Element (type)	Description
hld_id_44 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_44 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_45 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_45 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_45 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_45 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_45 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_46 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_46 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_46 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_46 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_46 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_47 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_47 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_47 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_47 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_47 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_48 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_48 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_48 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_48 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_48 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.

Element (type)	Description
hld_typ_49 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_49 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_49 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_49 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_49 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_50 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_50 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_50 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_50 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_50 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_51 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_51 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_51 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_51 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_51 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_52 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_52 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_52 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_52 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_52 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_53 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_53 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_53 [crncy_cde 1.0]	The currency code of the amount on hold.

Element (type)	Description
hld_id_53 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_53 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_54 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_54 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_54 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_54 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_54 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_55 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_55 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_55 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_55 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_55 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_56 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_56 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_56 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_56 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_56 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_57 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_57 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_57 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_57 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_57 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.

Element (type)	Description
hld_typ_58 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_58 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_58 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_58 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_58 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_59 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_59 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_59 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_59 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_59 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_60 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_60 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_60 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_60 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_60 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_61 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_61 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_61 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_61 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_61 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_62 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_62 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_62 [crncy_cde 1.0]	The currency code of the amount on hold.

Element (type)	Description
hld_id_62 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_62 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_63 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_63 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_63 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_63 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_63 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_64 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_64 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_64 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_64 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_64 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_65 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_65 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_65 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_65 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_65 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_66 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_66 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_66 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_66 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_66 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.

Element (type)	Description
hld_typ_67 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_67 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_67 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_67 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_67 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_68 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_68 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_68 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_68 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_68 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_69 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_69 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_69 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_69 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_69 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_typ_70 [hld_typ 1.0]	The type of a pre-auth hold transaction. This a user-defined value that can be used to categorize holds. It is an optional field for a pre-auth hold.
hld_amt_70 [hld_amt 1.0]	The amount of a pre-auth hold transaction.
hld_crncy_cde_70 [crncy_cde 1.0]	The currency code of the amount on hold.
hld_id_70 [hld_id 1.0]	The transaction identifier of a pre-auth hold transaction. The hold id must be unique for each pre-auth hold associated with specific card/account. The hold id is used as part of the matching criteria when updating/deleting a hold.
hld_exp_ts_70 [hld_exp_ts 1.0]	The date/time (timestamp) that a pre-auth hold transaction expires.
hld_local_txn_ts_1 [bt_int64s]	Next fields store the acquirers local time stamp at the moment of initiating the transaction.
hld_local_txn_ts_2 [bt_int64s]	
hld_local_txn_ts_3 [bt_int64s]	
hld_local_txn_ts_4 [bt_int64s]	

Element (type)	Description
hld_local_txn_ts_5 [bt_int64s]	
hld_local_txn_ts_6 [bt_int64s]	
hld_local_txn_ts_7 [bt_int64s]	
hld_local_txn_ts_8 [bt_int64s]	
hld_local_txn_ts_9 [bt_int64s]	
hld_local_txn_ts_10 [bt_int64s]	
hld_local_txn_ts_11 [bt_int64s]	
hld_local_txn_ts_12 [bt_int64s]	
hld_local_txn_ts_13 [bt_int64s]	
hld_local_txn_ts_14 [bt_int64s]	
hld_local_txn_ts_15 [bt_int64s]	
hld_local_txn_ts_16 [bt_int64s]	
hld_local_txn_ts_17 [bt_int64s]	
hld_local_txn_ts_18 [bt_int64s]	
hld_local_txn_ts_19 [bt_int64s]	
hld_local_txn_ts_20 [bt_int64s]	
hld_local_txn_ts_21 [bt_int64s]	
hld_local_txn_ts_22 [bt_int64s]	
hld_local_txn_ts_23 [bt_int64s]	
hld_local_txn_ts_24 [bt_int64s]	
hld_local_txn_ts_25 [bt_int64s]	
hld_local_txn_ts_26 [bt_int64s]	
hld_local_txn_ts_27 [bt_int64s]	
hld_local_txn_ts_28 [bt_int64s]	
hld_local_txn_ts_29 [bt_int64s]	
hld_local_txn_ts_30 [bt_int64s]	
hld_local_txn_ts_31 [bt_int64s]	
hld_local_txn_ts_32 [bt_int64s]	
hld_local_txn_ts_33 [bt_int64s]	
hld_local_txn_ts_34 [bt_int64s]	
hld_local_txn_ts_35 [bt_int64s]	
hld_local_txn_ts_36 [bt_int64s]	
hld_local_txn_ts_37 [bt_int64s]	
hld_local_txn_ts_38 [bt_int64s]	
hld_local_txn_ts_39 [bt_int64s]	

Element (type)	Description
hld_local_txn_ts_40 [bt_int64s]	
hld_local_txn_ts_41 [bt_int64s]	
hld_local_txn_ts_42 [bt_int64s]	
hld_local_txn_ts_43 [bt_int64s]	
hld_local_txn_ts_44 [bt_int64s]	
hld_local_txn_ts_45 [bt_int64s]	
hld_local_txn_ts_46 [bt_int64s]	
hld_local_txn_ts_47 [bt_int64s]	
hld_local_txn_ts_48 [bt_int64s]	
hld_local_txn_ts_49 [bt_int64s]	
hld_local_txn_ts_50 [bt_int64s]	
hld_local_txn_ts_51 [bt_int64s]	
hld_local_txn_ts_52 [bt_int64s]	
hld_local_txn_ts_53 [bt_int64s]	
hld_local_txn_ts_54 [bt_int64s]	
hld_local_txn_ts_55 [bt_int64s]	
hld_local_txn_ts_56 [bt_int64s]	
hld_local_txn_ts_57 [bt_int64s]	
hld_local_txn_ts_58 [bt_int64s]	
hld_local_txn_ts_59 [bt_int64s]	
hld_local_txn_ts_60 [bt_int64s]	
hld_local_txn_ts_61 [bt_int64s]	
hld_local_txn_ts_62 [bt_int64s]	
hld_local_txn_ts_63 [bt_int64s]	
hld_local_txn_ts_64 [bt_int64s]	
hld_local_txn_ts_65 [bt_int64s]	
hld_local_txn_ts_66 [bt_int64s]	
hld_local_txn_ts_67 [bt_int64s]	
hld_local_txn_ts_68 [bt_int64s]	
hld_local_txn_ts_69 [bt_int64s]	
hld_local_txn_ts_70 [bt_int64s]	

PRICE_Interface (1.0) (prceifd)

The PRICE Interface Table.

[Audited] [Supports versioning]

OLTP: PRICE_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
app_id_cde [bt_stringf(2)]	A code identifying the PRICE application in field 32.
csb_acq_id_cde [bt_stringf(4)]	A code identifying the CSB acquirer in field 32.

PRM_Interface (3.0) (prmid)

The PRM Interface configuration data source.

[Audited] [Supports versioning]

OLTP: PRM_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
enabled_flg [bt_flag]	A flag indicating whether the contingency interface is enabled or disabled. Valid values are: 1 - Contingency Interface is enabled, 0 - Contingency Interface is disabled. Default value is 1.
nrt_rqst_typ [bt_char]	A flag indicating the type of near real-time request to send. Valid values are: 0 - Scoring and Rules, 1 - Rules only. Default value is 0.
rt_rqst_typ [bt_char]	A flag indicating the type of real-time request to send. Valid values are: 0 - Scoring and Rules, 1 - Rules only, 2 - Scoring only. Default value is 2
acct_num_ind [bt_char]	Value indicating the type to set the account number field. Valid values are: 0 " account number, 1 " PAN, 2 " Customer ID.
proto_hdr_req [bt_flag]	This field identifies whether a protocol specific header (e.g., for TCP/IP message streams) is required to be prepended to the PRM message format by the PRM Interface. Default is 0 (no).

PROCESS (2.0) (procd)

The process table is used to configure processes that are running in an application. This table is used for clustering services so that application processes can broadcast messages between themselves to keep cached application data in sync.

[Audited] [Supports versioning]

Element (type)	Description
PrcsID *[bt_stringf(16)]	A unique ID assigned to a process in the Process table (PROCESS).
PrcsDscrTx [bt_stringf(100)]	The field is used to describe a Process table (PROCESS) entry. The data is configured in the Process table.
ApplID [bt_stringf(16)]	Application ID
ExtrCnctID [bt_stringf(50)]	Used to uniquely identify an external connection in the External Connection table (EXTRCNCT).
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

Proc_Code_ATM_TC (1.0) (atptd)

The Processing Code to ATM Transaction Code table contains an entry for every processing code which may be received. The processing code is mapped to a corresponding ATM transaction code.

[Audited] [Supports versioning]

Element (type)	Description
proc_cde_prfl *[bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
proc_cde *[proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
atm_txn_cde [bt_stringf(6)]	The transaction code used to describe the effect of a transaction on the customer account and the accounts affected. It is composed of the transaction code, the from account type and the to account type.
txn_subtyp [bt_stringf(4)]	An optional value that can be used with an existing BASE24 Classic transaction code to define a new transaction type. Any four characters are permitted. Default value is spaces (not applicable).

PROC_CODE_ISO (1.0) (pcied)

The internal Processing Code to external ISO Processing Code mapping table contains an entry for every external Processing Code which may be sent for an endpoint where mapping is required. The internal processing code is mapped to a corresponding external processing code.

[Audited] [Supports versioning]

OLTP: PROC_CODE_ISO_OLTP

Element (type)	Description
proc_cde_prfl*[bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
proc_cde*[proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
proc_cde_extrn [proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
txn_subtyp [bt_stringf(4)]	An optional value that can be used with an existing BASE24 Classic transaction code to define a new transaction type. Any four characters are permitted. Default value is spaces (not applicable).

Proc_Code_POS_TC (1.0) (psptd)

The Processing Code to POS Transaction Code table contains an entry for every processing code which may be received. The processing code is mapped to a corresponding POS transaction code.

[Audited] [Supports versioning]

Element (type)	Description
proc_cde_prfl*[bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
proc_cde*[proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pos_txn_cde [bt_stringf(6)]	The transaction code used to describe the effect of a transaction on the customer account and the accounts affected. It is composed of the transaction code, the card type, the account type and the category code.
txn_subtyp [bt_stringf(4)]	An optional value that can be used with an existing BASE24 Classic transaction code to define a new transaction type. Any four characters are permitted. Default value is spaces (not applicable).

PswdGrp (1.0) (upswdg)

Password Group table

[Audited] [Supports versioning]

Element (type)	Description
OwnerID*[bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.
PasswordGroupID*[bt_stringf(30)]	
Descr [bt_stringf(50)]	
PswdExpWarnDays [bt_int16s]	
PswdLifetime [bt_int16s]	
MinPswdLen [bt_int16s]	
MaxPswdLen [bt_int16s]	
MinPswdNumChars [bt_int16s]	
MinPswdAlphaChars [bt_int16s]	
MaxNumOldPswds [bt_int16s]	
MaxPswdChgsPerDay [bt_int16s]	
LastMaintTS [ts 1.0]	

PswdHist (3.0) (upswdh)

Password History table

[Audited] [Supports versioning]

Element (type)	Description
UserID*[bt_stringf(16)]	
Password*[bt_stringf(64)]	
ArchiveTS*[ts 1.0]	

Pulse_Institution (1.0) (pinstd)

Pulse Institution Table.

[Audited] [Supports versioning]

OLTP: Pulse_Institution_OLTP

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
frd_aba [bt_stringf(10)]	Star FRD-ABA.

Pulse_Interface (2.0) (pulifd)

Pulse Interface Configuration. Pulse Interface Configuration.

[Audited] [Supports versioning]

OLTP: Pulse_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_sec_cde [bt_stringf(8)]	Message Security Code.
iss_msg_sec_cde [bt_stringf(8)]	Issuer Message Security Code.
acq_spnsr_bnk_id [bt_stringf(11)]	Acquirer Sponsor Bank ID.
acq_reimb_attr1 [bt_stringf(1)]	Acquirer Reimbursement Attribute 1.
acq_reimb_attr2 [bt_stringf(1)]	Acquirer Reimbursement Attribute 2.
enhnc_acq_bnk_id_proc [bt_flag]	Enhanced acquirer identification code processing
dflt_acq_bnk_id [bt_stringf(11)]	Default acquirer identification code

Pulse_Switch_Date (1.0) (pswid)

Pulse Switch Date Table.

[Audited] [Supports versioning]

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
swi_dat [bt_stringf(8)]	Switch Settlement Date. Default is zeroes.

RCPTRQRD (1.0) (rcptrd)

The is an ES device handler table. For any given Receipt Profile and Acquirer Transaction Code, this table defines whether or not a receipt is required. The flags are broken down by Receipt printer and Journal printer. Additionally, the requirement is defined for approved and declined transactions.

[Audited] [Supports versioning]

Element (type)	Description
RcptPrflTx* [bt_stringf(16)]	The profile ID used to link an ATM terminal to the Receipt table (RECEIPT). The data is configured on the ES ATDS1 table.
AcqrTranCd* [bt_stringf(6)]	The Acquirer Transaction Code used as a part of the key to the Receipt Required (RCPTRQRD) table.
RcptTranAprvFlag [bt_int32s]	An indicator, configured on the Receipt Required table (RCPTRQRD), that determines whether a consumer receipt must be printed at the ATM for approved transactions. Possible values are Yes or No.
RcptTranDenyFlag [bt_int32s]	An indicator, configured on the Receipt Required table (RCPTRQRD), that determines whether a consumer receipt must be printed at the ATM for denied transactions. Possible values are Yes or No.
JrnlTranAprvFlag [bt_int32s]	An indicator, configured on the Receipt Required table (RCPTRQRD), that determines whether a journal receipt must be printed at the ATM for approved transactions. Possible values are Yes or No.
JrnlTranDenyFlag [bt_int32s]	An indicator, configured on the Receipt Required table (RCPTRQRD), that determines whether a journal receipt must be printed at the ATM for denied transactions. Possible values are Yes or No.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Real_Time_Feed_Config (2.0) (rtfcd)

The Real Time Feed Config table contains a record for each real time feed interface defined in the system.

[Audited] [Supports versioning]

OLTP: Real_Time_Feed_Config_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
enabled_flg [bt_flag]	A flag indicating whether the contingency interface is enabled or disabled. Valid values are: 1 - Contingency Interface is enabled, 0 - Contingency Interface is disabled. Default value is 1.
script_nam [nam 1.0]	The name of an executable script. This field is left-justified, upper case (containing any combination of alphanumeric and special character, but without any embedded spaces).
rtf_frmt [bt_stringf(16)]	An identifier of the format used for a real-time feed.
rtf_del_on_send [bt_flag]	Flag indicating whether to delete the Real Time Feed SAF record when it is sent immediately or to wait for a text level acknowledgement.

Reason_Online_Code_Description (1.0) (rocdd)

The Reason Online Code Description table contains the description for a reason online code value.

[Audited] [Supports versioning]

Element (type)	Description
rsn_onl_cde* [bt_stringf(4)]	Reason On-line Code. The value of this field indicates the reason the transaction is to be authorized on-line or why a transaction has been completed locally. Values are defined in the ISO 8583 (1993) Standard.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rsn_onl_cde_descr [bt_stringf(50)]	Textual description of a numeric Reason Online Code value.

RECEIPT (1.0) (rcptd)

Receipt Table. The table contains the templates for all receipts generated by the ATM devices.

[Audited] [Supports versioning]

Element (type)	Description
RcptPrflTx* [bt_stringf(16)]	The profile ID used to link an ATM terminal to the Receipt table (RECEIPT). The data is configured on the ES ATDS1 table.
RcptTypeCd* [bt_stringf(25)]	The receipt type field indicates the type of receipt, based on the transaction type (e.g., withdrawal, deposit, etc.). The value is configured on the Receipt table (RECEIPT). It is used to look up receipt templates for transaction receipts. Valid values are defined in the ES UI. Only valid values may be selected in the UI.
LangCd* [bt_stringf(3)]	This field indicates the Language Code indicator associated with a receipt template. The data is configured in the Receipt table (RECEIPT). Valid values are 0 through 9.
TermInstIDTx* [bt_stringf(20)]	The ATM terminals owning institution ID. The field is used as a part of the key in the Receipt Template table (RECEIPT). It is used to look up transaction receipts for transactions.
FromAcntTypeCd* [bt_stringf(2)]	A code defining the From account type for the key to the Receipt table (RECEIPT). A wild card character (**) may be used as well as a specific account type.
ToAcntTypeCd* [bt_stringf(2)]	A code defining the To account type for the key to the Receipt table (RECEIPT). A wild card character (**) may be used as well as a specific account type.
PrntTypeCd* [bt_stringf(1)]	The Receipt Printer Type element defining the type of printer on which a receipt is to be printed. The data is configured as a key element on the Receipt table (RECEIPT). The field may contains a wildcard character when used on the Receipt table. Valid values are: 0 = All 1 = Consumer 2 = Journal 3 = DAS
PrntSubTypeCd* [bt_stringf(1)]	The Receipt Printer Subtype element defines the type of printing technology used by a printer. The data is configured as a key element on the Receipt table

Element (type)	Description
	(RECEIPT). The field may contains a wildcard character when used on the Receipt table. Valid values are: 1 = Standard 2 = Thermal
TmplDataTx [bt_stringf(3000)]	The receipt template data stored in the Receipt Template table (RECEIPT). The data defines the format of a transaction receipt.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Referral (1.0) (rfrld)

The Referral Table contains a row for every transaction that has been referred. It is used by the Voice Authorization subsystem to provide a summary of referred transactions for the UI.

[Audited] [Supports versioning]

OLTP: Referral_OLTP

Element (type)	Description
pan*[bt_stringf(28)]	Primary Account Number.
onl_key_amt*[bt_int64s]	The amount used for online queries. This is the amount originally requested.
crncy_cde [bt_int16s]	Currency Code.
seq_num_char*[bt_stringf(12)]	The sequence number which identifies the transaction as set by the acquirer.
discrim [bt_int16s]	The discriminant is used to make the online key unique for duplicate checking.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
mrch_id [bt_stringf(15)]	The merchant identifier. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
tran_dat_tim [bt_stringf(16)]	The transaction date in format YYYYMMDDHHMMSShh when the transaction was journalled.
rfrl_ind [bt_stringf(2)]	The Referral Indicator. It indicates the reason why a transaction was referred. The codes are soft and defined by the customer.
captr_dat [bt_stringf(8)]	The Capture Date. This is the date when the transaction enters the system. It is stored in the YYYYMMDD format.
inst_id [bt_stringf(20)]	Institution ID.

Roles (2.0) (uroles)

Roles table

[Audited] [Supports versioning]

Element (type)	Description
OwnerID* [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.
RoleID* [bt_stringf(30)]	
Descr [bt_stringf(50)]	
LastMaintTS [ts 1.0]	
Active [bt_char DEFAULT Y]	Indicates if the Role is active. This will allow Roles to go through a staging process before being put in an active state. Valid values are "Y" (default) and "N".
ReadOnly [bt_char DEFAULT N]	Indicates if a Role can be updated or deleted. This will allow static Roles to be defined. Valid values are "Y" and "N" (default)

RoIXPmGp (1.0) (urolxp)

Role Permission Groups table

[Audited] [Supports versioning]

Element (type)	Description
OwnerID* [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.
RoleID* [bt_stringf(30)]	
PermissionGroupID* [bt_stringf(30)]	

Route (2.0) (routed)

The Route table contains one record for each issuer route profile, route code, account 1 type, and account 2 type defined in the system. Through configuration of Route records issuers define the routing and authorization parameters for their transactions. Issuers may share common routing and authorization configurations through the specification of a common issuer route profile. Processing codes share common routing and authorization configurations through the specification of a common route code. A wild-card value of asterisks is supported for the issuer route profile, route code, account 1 type, and account 2 type.

[Audited] [Supports versioning]

OLTP: Route_OLTP

Element (type)	Description
iss_rte_prfl* [prfl_def 1.0]	The route profile of the issuer whose customer initiated the transaction. The issuer route profile is defined where ever the issuer is determine and allows one or more issuers to share routing and authorization configurations. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
rte_cde* [bt_stringf(16)]	The route code is used to group processing codes for routing and authorization purposes. This field is left justified, upper case (containing any combination of

Element (type)	Description
	alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
acct1_typ*[typ 1.0]	The account 1 type is the middle two bytes of the processing code. (txn_cde is the first 2 bytes).
acct2_typ*[typ 1.0]	The account 2 type is the last 2 bytes of the processing code. (txn_cde = first 2 bytes, acct1_typ = next 2 bytes).
cust_auth_mthd*[bt_stringf(1)]	The customer authentication method. Valid values are 0 - None, 1 - PIN, 2 - electronic signature, 3 - biometrics, 4 - biographic, 5 - manual signature, 6 - manual other, * - wild-card. The default value is 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ovr_flr_pri_prescreen_nam [bt_stringf(16)]	Over the floor primary prescreen high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_prescreen_cmpnt_id [bt_stringf(8)]	Over the floor primary prescreen component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_auth_nam [bt_stringf(16)]	Over the floor primary authorizer high level script name or interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_auth_cmpnt_id [bt_stringf(8)]	Over the floor primary authorizer component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_adv1_nam [bt_stringf(16)]	Over the floor primary advice 1 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_adv1_cmpnt_id [bt_stringf(8)]	Over the floor primary advice 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_adv1_req [bt_stringf(1)]	Over the floor primary advice 1 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
ovr_flr_pri_adv2_nam [bt_stringf(16)]	Over the floor primary advice 2 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_adv2_cmpnt_id [bt_stringf(8)]	Over the floor primary advice 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_adv2_req [bt_stringf(1)]	Over the floor primary advice 2 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
ovr_flr_pri_impact1_nam [bt_stringf(16)]	Over the floor primary impact1 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
ovr_flr_pri_impact1_cmpnt_id [bt_stringf(8)]	Over the floor primary impact 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_impact2_nam [bt_stringf(16)]	Over the floor primary impact2 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_pri_impact2_cmpnt_id [bt_stringf(8)]	Over the floor primary impact 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_prescrn_nam [bt_stringf(16)]	Over the floor alternate 1 prescreen high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_prescrn_cmpnt_id [bt_stringf(8)]	Over the floor alternate 1 prescreening component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_auth_nam [bt_stringf(16)]	Over the floor alternate 1 authorizing high level script name or interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_auth_cmpnt_id [bt_stringf(8)]	Over the floor alternate1 authorizing component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_adv1_nam [bt_stringf(16)]	Over the floor alternate 1 advice 1 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_adv1_cmpnt_id [bt_stringf(8)]	Over the floor alternate 1 advice 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_adv1_req [bt_stringf(1)]	Over the floor alternate 1 advice 1 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
ovr_flr_alt1_adv2_nam [bt_stringf(16)]	Over the floor alternate 1 advice 2 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_adv2_cmpnt_id [bt_stringf(8)]	Over the floor alternate 1 advice 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_adv2_req [bt_stringf(1)]	Over the floor alternate 1 advice 2 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
ovr_flr_alt1_impact1_nam [bt_stringf(16)]	Over the floor alternate 1 impact1 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_impact1_cmpnt_id [bt_stringf(8)]	Over the floor alternate 1 impact 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
ovr_flr_alt1_impact2_nam [bt_stringf(16)]	Over the floor alternate 1 impact2 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt1_impact2_cmpnt_id [bt_stringf(8)]	Over the floor alternate 1 impact 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_prescrn_nam [bt_stringf(16)]	Over the floor alternate 2 prescreen high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_prescrn_cmpnt_id [bt_stringf(8)]	Over the floor alternate 2 prescreening component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_auth_nam [bt_stringf(16)]	Over the floor alternate 2 authorizing high level script name or interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_auth_cmpnt_id [bt_stringf(8)]	Over the floor alternate 2 authorizing component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_adv1_nam [bt_stringf(16)]	Over the floor alternate 2 advice 1 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_adv1_cmpnt_id [bt_stringf(8)]	Over the floor alternate 2 advice 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_adv1_req [bt_stringf(1)]	Over the floor alternate 2 advice 1 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
ovr_flr_alt2_adv2_nam [bt_stringf(16)]	Over the floor alternate 2 advice 2 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_adv2_cmpnt_id [bt_stringf(8)]	Over the floor alternate 2 advice 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_adv2_req [bt_stringf(1)]	Over the floor alternate 2 advice 2 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
ovr_flr_alt2_impact1_nam [bt_stringf(16)]	Over the floor alternate 2 impact1 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_impact1_cmpnt_id [bt_stringf(8)]	Over the floor alternate 2 impact 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
ovr_flr_alt2_impact2_nam [bt_stringf(16)]	Over the floor alternate 2 impact2 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
ovr_flr_alt2_impact2_cmpnt_id [bt_stringf(8)]	Over the floor alternate 2 impact 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_prescrn_nam [bt_stringf(16)]	Under the floor primary prescreen high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_prescrn_cmpnt_id [bt_stringf(8)]	Under the floor primary prescreening component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_auth_nam [bt_stringf(16)]	Under the floor primary authorizing high level script name or interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_auth_cmpnt_id [bt_stringf(8)]	Under the floor primary authorizing component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_adv1_nam [bt_stringf(16)]	Under the floor primary advice1 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_adv1_cmpnt_id [bt_stringf(8)]	Under the floor primary advice 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_adv1_req [bt_stringf(1)]	Under the floor primary advice1 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
undr_flr_pri_adv2_nam [bt_stringf(16)]	Under the floor primary advice2 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_adv2_cmpnt_id [bt_stringf(8)]	Under the floor primary advice 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_adv2_req [bt_stringf(1)]	Under the floor primary advice2 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
undr_flr_pri_impact1_nam [bt_stringf(16)]	Under the floor primary impact1 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_impact1_cmpnt_id [bt_stringf(8)]	Under the floor primary impact 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_impact2_nam [bt_stringf(16)]	Under the floor primary impact2 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_pri_impact2_cmpnt_id [bt_stringf(8)]	Under the floor primary impact 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
undr_flr_alt1_prescrn_nam [bt_stringf(16)]	Under the floor alternate 1 prescreen high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_prescrn_cmpt_id [bt_stringf(8)]	Under floor alternate 1 prescreening component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_auth_nam [bt_stringf(16)]	Under the floor alternate 1 authorizing high level script name or interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_auth_cmpnt_id [bt_stringf(8)]	Under the floor alternate 1 authorizing component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_adv1_nam [bt_stringf(16)]	Under the floor alternate 1 advice1 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_adv1_cmpnt_id [bt_stringf(8)]	Under the floor alternate 1 advice 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_adv1_req [bt_stringf(1)]	Under the floor alternate 1 advice1 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
undr_flr_alt1_adv2_nam [bt_stringf(16)]	Under the floor alternate 1 advice2 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_adv2_cmpnt_id [bt_stringf(8)]	Under the floor alternate 1 advice 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_adv2_req [bt_stringf(1)]	Under the floor alternate 1 advice2 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
undr_flr_alt1_impact1_nam [bt_stringf(16)]	Under the floor alternate 1 impact1 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_impact1_cmpnt_id [bt_stringf(8)]	Under the floor alternate 1 impact 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_impact2_nam [bt_stringf(16)]	Under the floor alternate 1 impact2 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt1_impact2_cmpnt_id [bt_stringf(8)]	Under the floor alternate 1 impact 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_prescreen_nam [bt_stringf(16)]	Under the floor alternate 2 prescreen high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Element (type)	Description
undr_flr_alt2_prescrn_cmpt_id [bt_stringf(8)]	Under floor alternate 2 prescreening component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_auth_nam [bt_stringf(16)]	Under the floor alternate 2 authorizing high level script name or interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_auth_cmpt_id [bt_stringf(8)]	Under the floor alternate 2 authorizing component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_adv1_nam [bt_stringf(16)]	Under the floor alternate 2 advice 1 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_adv1_cmpt_id [bt_stringf(8)]	Under the floor alternate 2 advice 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_adv1_req [bt_stringf(1)]	Under the floor alternate 2 advice 1 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
undr_flr_alt2_adv2_nam [bt_stringf(16)]	Under the floor alternate 2 advice 2 interface name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_adv2_cmpt_id [bt_stringf(8)]	Under the floor alternate 2 impact 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_adv2_req [bt_stringf(1)]	Under the floor alternate 2 advice 2 required field. Specifies the conditions when an advice is required. Valid values are: A - approved, D - deny, B - both approved and denied, N - none. Default value is N.
undr_flr_alt2_impact1_nam [bt_stringf(16)]	Under the floor alternate 2 impact1 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_impact1_cmpt_id [bt_stringf(8)]	Under the floor alternate 2 impact 1 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_impact2_nam [bt_stringf(16)]	Under the floor alternate 2 impact2 high level script name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
undr_flr_alt2_impact2_cmpt_id [bt_stringf(8)]	Under the floor alternate 2 impact 2 component id. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
iss_rte_flr_lmt [bt_int64s]	The issuer route floor limit which defines whether to use the under floor routing destination set or the over floor routing destination set. If the route flag is not set, then the transaction amount in the logical network currency is compared against this value to determine which set is used. If the transaction amount is less than the issuer route floor limit, then the under floor destination set is used. Otherwise the overfloor destination set is used. Valid values are 0 to

Element (type)	Description
	999999999999999999. The decimal position is implied by the logical networks currency. The default value is 0.
dflt_auth_flr_lmt [bt_int64s]	The default authorization floor limit which defines whether to use the under action or the over action when default authorization is performed. If the transaction amount in the logical network currency is greater than the default authorization floor limit, then the over action is used. Otherwise the under action is used. Valid values are 0 to 999999999999999999. The decimal position is implied by the logical networks currency. The default value is 0.
ovr_act [bt_stringf(1)]	The action to take if the transaction amount is greater than or equal to the default authorization floor limit. Valid values are: A - approve, D - Deny, R - Refer.
undr_act [bt_stringf(1)]	The action to take if the transaction amount is less than the default authorization floor limit. Valid values are: A - approve, D - Deny, R - Refer.
allow_alt_flr_lmt_chk [bt_flag]	Determines whether alternative floor limit checking is allowed for a routing entry. If set to 1, alternative floor limit checks will be used. Otherwise set to 0 and the standard floor limit checks based on transaction amount and the issuer route floor limit (iss_rte_flr_lmt).
alt_flr_lmt_algo [bt_stringf(16)]	This field indicates the alternate floor limit algorithm to be used to determine routing destinations when the Allow Alternate Floor Limit Check field in the Route record is enabled. Router will invoke a callback function of the component which registered the value of this field. Default value is spaces.
rte_aud_flg [bt_flag]	This field is used to indicate whether transaction (i.e., TDE) auditing is required or not. This field is primarily used for sequentially routed transactions, to indicate that transaction/TDE auditing is not required. This field corresponds with the Disable Transaction Auditing field on the Routing Configuration -- Destinations UI, General Information Tab, Authorization Information. If the field is set to 1 (yes), it indicates that transaction auditing is disabled. Otherwise set to 0 and the standard transaction/TDE auditing is used.

RQUID (2.0) (rquid)

The table is used by the ES IFX device handler and is managed solely by the device handler - it is NOT viewable through the UI. The RqUID (IFX document ReQuest Unique IDentifier) is used for duplicate checking.

[Audited] [Supports versioning]

Element (type)	Description
RqUIDTx*[bt_stringf(36)]	The Request Unique Identifier (RqUID) from the service wrapper of an IFX document.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
UsrDfndTx [bt_stringf(50)]	This field is for informational only data. It is configured on the ES RQUID table.

RVLSAF (1.0) (RS)

The Reversal SAF table is used to temporarily save 1420 reversal messages to BASE24-es authorization when the original reversal times out. The ATM device handlers save the reversal in this table. A De-SAF process retries the 1420 messages a configurable number of times. If the reversal cannot be sent, the message is deleted after the configurable number of retries.

[Audited] [Supports versioning]

Element (type)	Description
InsrtTs* [bt_int64s]	The date and time an row was inserted into the table. This data is used to retrieve the records in the order they were written.
ExtrCnctID [bt_stringf(50)]	Used to uniquely identify an external connection in the External Connection table (EXTRCNCT).
AttmptCnt [bt_int32s]	The number of times a row in the Reversal SAF has been retried. After a configurable number of retries, the row is deleted without being sent.
MsgFrmtTx [bt_stringf(4)]	A code identifying the format of the message stored in the Reversal SAF.
MsgUnqldTx [bt_stringf(64)]	The message Unique ID for a reversal SAF row.
MsgBn [bt_binaryf(3926)]	The message saved in the Reversal SAF table, in its native format.

Script (2.0) (scrptd)

The Script table contains one record for each compiled script statement. The Script Component writes records to this table when compiling scripts.

[Audited] [Supports versioning]

OLTP: Script_OLTP

Element (type)	Description
script_nam* [nam 1.0]	The name of an executable script. This field is left-justified, upper case (containing any combination of alphaumeric and special character, but without any embedded spaces).
stmt_num* [bt_int16s]	The statement number in the compiled script.
stmt_typ [bt_int16s]	The type of script statement. Valid values are: const_number, const_string, else, endif, exit, if, script, operator, invld, case, default, endcase, end_of_script.
rtrn_typ [bt_int16s]	The data type that the script will return. Valid values are: invld, void, number, string, boolean, not_exist, const_string.
num_params [bt_int16s]	The number of parameters the script requires.
mnem_nam [bt_stringf(64)]	The mnemonic name associated with this statement. This field is left-justified (starting with an alphabetic character followed by any combination of alphanumeric and special characters, but without any embedded spaces).
line_num [bt_int16s]	The line number in the Script Source table to which this statement pertains.

Element (type)	Description
line_ofst [bt_int16s]	The offset into the line of the Script Source table to which this statement pertains.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Script_Configuration (2.0) (scptcd)

The Script Configuration table contains one record for each executable script in the system. An executable script may be a high level script or a subscript. The script compiler updates the param types and return values.

[Audited] [Supports versioning]

Element (type)	Description
script_nam*[nam 1.0]	The name of an executable script. This field is left-justified, upper case (containing any combination of alphaumeric and special character, but without any embedded spaces).
script_descr [bt_stringf(60)]	A brief description of the script.
user_id [bt_stringf(16)]	The user ID of the person logging on into the system. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts_config [bt_stringf(46)]	Last file maintenance for the script configuration data source.
fm_ts_script_source [bt_stringf(46)]	Last file maintenance for the script source data source.
fm_ts_cmpl [bt_int64s]	The timestamp indicating the last time a script was compiled.
num_params [bt_int16s]	The number of parameters the script requires.
rtrn_typ [bt_int16s]	The data type that the script will return. Valid values are: invld, void, number, string, boolean, not_exist, const_string.
param_typ_01 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_02 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_03 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_04 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_05 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.

Element (type)	Description
param_typ_06 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_07 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_08 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_09 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
param_typ_10 [bt_int16s]	The type of script signature parameter. Valid values are: undefined, numeric_by_val, numeric_by_ref, string_by_val, string_by_ref, boolean_by_val, boolean_by_ref.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
root_flg [bt_int16s]	Indicates if a script is a Root script. Valid values are: 0 - No (default). 1 - Yes.

Script_Source (2.0) (scsrcd)

The Script Source table contains one record for each line of a script. All lines together define the flow of a script. The script source is compiled and the output is placed in the Script table and updated in the Script Configuration table.

[Audited] [Supports versioning]

Element (type)	Description
script_nam*[nam 1.0]	The name of an executable script. This field is left-justified, upper case (containing any combination of alphanumeric and special character, but without any embedded spaces).
line_num*[bt_int16s]	The line number in the Script Source table to which this statement pertains.
line_text [bt_stringv(132)]	The text of a script line. This field is left-justified (containing any combination of alphanumeric and special characters).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

SecGrp (1.0) (usecgp)

Security Group table

[Audited] [Supports versioning]

Element (type)	Description
OwnerID* [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.
SecurityGroupID* [bt_stringf(30)]	
Descr [bt_stringf(50)]	
StartTime [bt_stringf(4)]	
EndTime [bt_stringf(4)]	
DaysOfWeek [bt_stringf(7)]	
MaxBadLoginAtmpts [bt_int16s]	
BadLognAtmptRstTm [bt_int32s]	
MaxSessions [bt_int16s]	
SessionTimeout [bt_int32s]	
UITimeout [bt_int32s]	
InactiveIDSuspend [bt_int32s]	
PasswordGroupID [bt_stringf(30)]	
LastMaintTS [ts 1.0]	
SysAdminRoleProfl [bt_stringf(30)]	This is a roleID used as a profile for filtering permissions, tasks, filters, perm groups
CreationID [bt_stringf(12)]	Creation ID used in Security group adds

Security_Device_Config (2.0) (secdcd)

Security Device Configuration table. This table defines parameters for hardware security devices. One record will exist for each security device.

[Audited] [Supports versioning]

Element (type)	Description
dev_nam* [bt_stringf(32)]	The assign name of the hardware security device.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
dev_typ [bt_char]	The type of hardware security device. Valid values are A - Atalla, T - Thales (Racal), E - Eracom Mark II.
svc_ind [bt_flag]	The security device service indicator. Valid values are 0 - device out-of-service, 1 - device in-service.
dev_subtyp [bt_int16s]	The subtype of a hardware security device. Hardware security device vendors may have multiple subtypes for each type of device. Valid values for Atalla are: 1 - A10000 AKB (default value). 2 - A10000 Variant. 3 - A9000 AKB. 4 - A9000 Variant. 5 - A8100 AKB. 6 - A8100 Variant. 7 - A10100 AKB. 8 - A10100 Variant. 9 - not used. 10 - A9100 AKB. 11 - A9100 Variant. 12 - not used. 13 - A8000 AKB. 14 - A8000 Variant. 15 - not used. Valid values for Racal/Thales are: 1 - Append start-of-text and end-of-text characters (default). 2 - Do not append start-of-text and

Element (type)	Description
	end-of-text characters. Valid values for Eracom are: 1 - Eracom Mark II Bracketed Message. 2 - Eracom Mark II Non-bracketed Message. 3 - Eracom AMB TCP/IP. 4 - Eracom AMB Ethernet. (NOTE: This field is no longer used by TSEC beginning with Version 2.0 of the Security Device Config data source.)
max_consec_err [bt_int16s]	The maximum consecutive error count allowed before the device is taken out of service. Valid values are 1 - 99 (default is 3).
dev_tim_lmt [bt_int16s]	The amount of time in seconds the IS will wait for a response from a hardware security device. Valid values are 1 - 9999 (default is 5).
ntfy_intrvl [bt_int16s]	The number of times an error occurs before another event will be generated indicating the error. Valid values are 1 - 99 (default is 10).
dev_init_txt [bt_stringf(100)]	Text required to initialize a hardware security device. This text is downloaded to the device.
dev_conf_txt [bt_stringf(100)]	Text required to configure a hardware security device. This text is downloaded to the device.
pki_enbl_flg [bt_flag]	Indicates if the security device supports PKI (e.g., RSA) cryptographic functions. Valid values are: 0 - No (default). 1 - Yes.
user_fld1 [bt_stringf(1)]	One byte user field (temporary filler).
hdwr_mdl [bt_int16s]	The model of the HSM Security Module (HSM). Valid values are: 1 - Atalla Ax000. 2 - Atalla Ax100. 3 - Thales RG7400. 4 - Thales RG71x0. 5 - Thales RG73x0. 6 - Thales HSM8000. 7 - Eracom Mark II. 8 - Eracom AMB.
proto_intf [bt_int16s]	The protocol used in the communication between BASE24-es and the Hardware Security Module (HSM). Valid values are: 1 - Async (NSK). 2 - Ethernet (Blocker NSK). 3 - TCP/IP (Boxcar NSK). 4 - TCP/IP (RAM NSK). 5 - TCP/IP (ICE-XS UNIX). 6 - TCP/IP (Adapter IBM). 7 - UDP/IP (URAM NSK). 8 - SDLC (HIP NSK) 9 - SRM (Thales IBM)
key_scheme [bt_int16s]	Key scheme supported by the Hardware Security Module (HSM). Valid values are: 0 - Not Applicable. 1 - AKB (Atalla). 2 - Variant (Atalla). 3 - ANSI X9.17 (Thales). 4 - Variant (Thales).
firmware_ver [bt_stringf(16)]	The firmware version obtained from the Hardware Security Module (HSM) during HSM initialization.
max_buf_lgth [bt_int32s]	The maximum input buffer length (in bytes) that can be accepted by the Hardware Security Module (HSM).
dev_reset_timr_lmt [bt_int16s]	The amount of time (seconds) that TSEC will wait before attempting communication with a Hardware Security Module (HSM) after the device has reached its maximum error limit and marked out of service. A value of 0 indicates that TSEC will not attempt to reconnect with the HSM. Valid values are 0 - 9999.

SIS_ASYNC_DEST_MAP (2.0) (admf)

Async destination map

[Not Audited] [Supports versioning]

Element (type)	Description
sis_symbolic_name* [bt_stringf(16)]	Symbolic name of process
site_id* [bt_stringf(2)]	Indicates the site that owns the connection.
session_id* [bt_stringf(2)]	In the case of multiple connections from an end-point, the session id indicates which connection this entry in the SIADMF is referencing.
sis_mq_object_name [bt_stringf(48)]	Object name of the MQ object
msg_type [bt_stringf(1)]	The Message type for AS to AR routing.
ice_station_num [bt_stringf(2)]	Station number as used internally within Ice-Xs. Saved for correlation with IceXs trace files.
ice_reserved_num [bt_stringf(2)]	Reserved field used internally within Ice-Xs. Saved for correlation with IceXs trace files.
ice_remote_ipaddr_rlu [bt_stringf(24)]	For tcpip connections this is the 24 byte (4 octet) ip address. For SNA connections this is the remote LU information. For X.25 connections this contains the address of the remote device in X.121 format.
ice_qmgr_name [bt_stringf(48)]	This is the name of the queue manager associated with the Ice-Xs receive queue.
ice_timestamp [bt_stringf(48)]	This is the timestamp of the message as available from msg_tim_get;utc. This is from the 108 byte MDS header.
ice_conn_disconn_flg [bt_stringf(1)]	This is a 1 byte field used to maintain whether we are currently connected or disconnected.
ice_messaging_type [bt_stringf(1)]	This is a one byte field. A 0 indicates that this is an MQ based messaging system. This is for future expansion when we may be using messaging other than MQ.

SMX (1.0) (smxd)

This table is used as output for extract scripts.

[Not Audited] [Does not support versioning]

Element (type)	Description
smx_element [bt_stringv(4058)]	The character buffer used as output for extract scripts.

SPAN2_Interface (3.0) (spifd)

SPAN2 Interface Table.

[Audited] [Supports versioning]

OLTP: SPAN2_Interface_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rcv_id_cde [bt_stringf(11)]	A code identifying the receiving institution.
acq_id_cde [bt_stringf(11)]	A code identifying the acquiring institution.
txn_orig_id_cde [bt_stringf(11)]	Code identifying the institution that is the transaction originator.
atm_last_swi_setl_dat [bt_stringf(8)]	The last switch settlement date received from the switch for ATM transactions. YYYYMMDD
pos_last_swi_setl_dat [bt_stringf(8)]	The last switch settlement date received from the switch for POS transactions. YYYYMMDD
last_out_setl_dat [bt_stringf(8)]	The date of the last outgoing cutover request message. YYYYMMDD
next_out_setl_dat [bt_stringf(8)]	The date of the next scheduled outgoing cutover request message. YYYYMMDD
use_last_out_setl_dat [bt_flag]	Indicates whether to use last date as the current business date in outgoing transactions. Valid values are: 1 – use the date of the last outgoing cutover request message, 0 – Use the date of the next scheduled outgoing cutover request message.

SPAN2_Interface_Terminal (1.0) (sptmd)

SPAN2 Interface Terminal Table.

[Audited] [Supports versioning]

OLTP: SPAN2_Interface_Terminal_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acq_inst_id*[inst_id 1.0]	If the transaction is acquired by a BASE24 terminal, this identifies the owning or sponsoring institution. If the transaction is acquired by a switch, this identifies the switch. If the transaction is acquired by the Host, this field is sent in the external message by the Host.
chnl_id*[chan_id 1.0]	The identifier of the channel. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ext_intf_term_id [bt_stringf(16)]	Extended interface terminal id.

SPDH_act_cde_descr (1.0) (spiad)

The SPDH Action Code Description table contains a text description of the external action code value.

[Audited] [Supports versioning]

OLTP: SPDH_act_cde_descr_OLTP

Element (type)	Description
chan_cnfg_prfl*[prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files.
lang_id*[bt_int16s]	A code indicating the language table used by the delivery channel when sending responses to the terminal. This code enables responses to be displayed on the terminal in one of three different languages. Valid values are: 1 - Language table 1, 2 - Language table 2, 3 - Language table 3. The particular language represented in each table is up to the discretion of the institution. For example, table 1 could be English, table 2 could be French, and table 3 could be Spanish. Default value is one.
act_cde_extrn*[bt_stringf(3)]	The external action code which is used to map to an internal action code or is the result of a mapping from an internal action code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Must be 1 to 3 characters in length.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
act_cde_extrn_descr [bt_stringf(48)]	Contains a text description of the external action code value.

SPDH_Configuration (3.0) (spicd)

Configuration data for the SPDH Channel Manager.

[Audited] [Supports versioning]

OLTP: SPDH_Configuration_OLTP

Element (type)	Description
chan_prfl*[prfl_def 1.0]	The profile for the channel that initiated the transaction. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
chan_resp_ttls [bt_stringf(1)]	An indicator of which types of totals to return to a device in a response to a subtotals request. Valid values are: A - All totals. D - Draft capture totals only (default). This field is currently only use by the SPDH.
rvsl_resp [bt_flag]	A flag indicating if a reversal response message should be sent to the device upon receipt of a reversal message. Valid values are: 0 - No, do not send a reversal response (default). 1 - Yes, send a reversal response. This field is currently only used by the SPDH.

Element (type)	Description
chan_cnfg_prfl [prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files.
chan_proc_mde [bt_stringf(1)]	The Channel Processing Mode indicates the mode of operation for the channel. Valid values are: 0 = Single-threaded (default). 1 = Multi-threaded.
chan_data_lgth [bt_int32s]	The length indicating the size of the Channel Data. The range is zero to 1024. Default value is zero.
ovrrde_chan_dat_tim_flg [bt_flag]	A flag indicating whether BASE24-eps should override the date/time sent in the request from the device. Valid values: 0 - Do not override the device's date/time. 1 - Override the device's date/time. The default is 1.
iop_acq_rte_prfl [prfl_def 1.0]	The route profile for Interac online payments and merchandise returns for the acquirer who acquired the transaction. The route profile is at the SPDH profile level and allows one or more SPDH acquirers to route these transactions differently than other transactions initiated at the device. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is blanks.
fid_x_lookup [bt_stringf(1)]	A flag to indicate whether the SPDH Response Display Text set in FID g is based on FID X. Valid values: N (default) or blank - FID X is not used, Y - FID X is used.
eps_act_cde_lookup [bt_stringf(1)]	A flag to indicate whether the SPDH Response Display Text set in FID g is based on EPS Action Code. // Valid values: N (default) or blank - EPS Action Code is not used, Y - EPS Action Code is used.
spiood_lookup [bt_stringf(1)]	A flag to indicate whether the SPDH Response Display Text set in FID g is based on SPDH Option Response Data file. Valid values: N - SPDH Option Response Data file is not used, Y (default) or blank - SPDH Option Response Data file is used.
Interac_cap [bt_stringf(1)]	A flag representing the Interac capabilities of the set of POS terminals. Valid values are: 0 or blank - Not Interac capable, use standard pre-auth processing if pre-auths are supported (default). 1 - Not Interac capable; use enhanced pre-auth processing if pre-auths are supported. 2 - Interac capable; displaying/printing balances not supported; use enhanced pre-auth processing if pre-auths are supported. 3 - Interac capable; displaying/printing balances supported; use enhanced pre-auth processing if pre-auths are supported.
incl_fid_upper_h_in_mac [bt_flag]	A flag indicating whether FID H (MAC Key) should be included in MAC calculations on all transaction responses. (When the FID is not present in a response, it will simply not be used in the MAC calculation.) Default is false.
incl_fid_upper_i_in_mac [bt_flag]	A flag indicating whether FID I (Data Encryption Key) should be included in MAC calculations on all transaction responses. (When the FID is not present in a response, it will simply not be used in the MAC calculation.) Default is false.
incl_fid_upper_m_in_mac [bt_flag]	A flag indicating whether FID M (PIN Key) should be included in MAC calculations on all transaction responses. (When the FID is not present in a response, it will simply not be used in the MAC calculation.) Default is false.

SPDH_ISO_Response_Code (1.0) (sprcd)

Configuration data for the SPDH ISO Response Code.

[Audited] [Supports versioning]

OLTP: SPDH_ISO_Response_Code_OLTP

Element (type)	Description
chan_cnfg_prfl*[prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files and also allow wildcarding.
intrn_act_cde*[bt_stringf(3)]	The internal action code which is used to map to an external ISO response code. Valid values are 000 - 999.
acct_typ*[bt_stringf(2)]	The account type of an account number and also allow wildcarding "***".
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
iso_resp_cde [bt_stringf(3)]	The ISO response code which is used to SPDH FID X. Valid values are alpha/numeric characters and/or spaces. Typically, it will be set to either a two or three characters code.

SPDH_ISO_Response_Text (1.0) (sprtd)

Configuration data for the SPDH ISO Response Text.

[Audited] [Supports versioning]

OLTP: SPDH_ISO_Response_Text_OLTP

Element (type)	Description
chan_cnfg_prfl*[prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files and also allow wildcarding.
rec_typ*[bt_stringf(1)]	The record type of a SPDH Response Text in the SPDH Response Text table. Valid values are: 0 or Blank = ISO (default), 1 = BASE24-eps.
resp_cde*[bt_stringf(3)]	The EPS response code (if record type specifies BASE24-eps) or freeform response code (if the record type specifies ISO).
lang_id*[bt_int16s]	A code indicating the language table used by the delivery channel when sending response to the terminal. This code enables responses to be displayed on the terminal in one of three different languages. Valid values are: 1 - Language table1, 2 - Language table 2, 3 - Language table 3. The particular language represented in each table is up to the discretion of the institution. For example, table 1 could be English, table 2 could be French, and table 3 could be Spanish. Default value is one.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
resp_txt [bt_stringf(48)]	Contains a text description of the response code.

SPDH_Message (2.0) (spimd)

The SPDH Message table defines the required Field Identifiers (FIDs) and sub-FIDs by transaction code for SPDH request and response messages. FIDs and sub-FIDs to be included in Message Authentication (MAC) calculations

are also defined. Each field is defined as a binaryf 8 data type. Bits 1 through 26 represent FIDs A through Z. Bits 27 through 42 represent FIDs a through z. Bits 53 through 62 represent FIDs 0 through 9. Bits 63 and 64 are not used.

[Audited] [Supports versioning]

OLTP: SPDH_Message_OLTP

Element (type)	Description
chan_cnfg_prfl*[prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files.
txn_cde*[bt_stringf(2)]	The transaction code, which is the first 2 bytes of the processing code. The default value is zeroes.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
rqst_fid_map [bt_binaryf(8)]	Defines the required FIDs that must be present in a device request message. Each byte represents 8 FIDs. If the FID is required, the bit is turned on.
rqst_subfid6_map [bt_binaryf(8)]	Defines the required sub-FIDs that must be present in FID 6 of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
rqst_subfid7_map [bt_binaryf(8)]	Defines the required sub-FIDs that must be present in FID 7 of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
rqst_subfid8_map [bt_binaryf(8)]	Defines the required sub-FIDs that must be present in FID 8 of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
rqst_subfid9_map [bt_binaryf(8)]	Defines the required sub-FIDs that must be present in FID 9 of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
rqst_mac_fid_map [bt_binaryf(8)]	Defines the FIDs that are included in the MAC calculation of a device request message. Each byte represents 8 FIDs. If the FID is required, the bit is turned on.
rqst_mac_subfid6_map [bt_binaryf(8)]	Defines the sub-FIDs of FID6 that are included in the MAC calculation of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
rqst_mac_subfid7_map [bt_binaryf(8)]	Defines the sub-FIDs of FID7 that are included in the MAC calculation of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
rqst_mac_subfid8_map [bt_binaryf(8)]	Defines the sub-FIDs of FID8 that are included in the MAC calculation of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
rqst_mac_subfid9_map [bt_binaryf(8)]	Defines the sub-FIDs of FID9 that are included in the MAC calculation of a device request message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
resp_fid_map [bt_binaryf(8)]	Defines the required or conditional FIDs to be returned in a device response message. Each byte represents 8 FIDs. If the FID is required, or conditional the bit is turned on.

Element (type)	Description
resp_subfid6_map [bt_binaryf(8)]	Defines the required or conditional sub-FIDs to be returned in FID 6 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required or conditional, the bit is turned on.
resp_subfid7_map [bt_binaryf(8)]	Defines the required or conditional sub-FIDs to be returned in FID 7 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required or conditional, the bit is turned on.
resp_subfid8_map [bt_binaryf(8)]	Defines the required or conditional sub-FIDs to be returned in FID 8 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required or conditional, the bit is turned on.
resp_subfid9_map [bt_binaryf(8)]	Defines the required or conditional sub-FIDs to be returned in FID 9 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required or conditional, the bit is turned on.
resp_mac_fid_map [bt_binaryf(8)]	Defines the FIDs that are included in the MAC calculation of a device response message. Each byte represents 8 FIDs. If the FID is required, the bit is turned on.
resp_mac_subfid6_map [bt_binaryf(8)]	Defines the sub-FIDs of FID6 that are included in the MAC calculation of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
resp_mac_subfid7_map [bt_binaryf(8)]	Defines the sub-FIDs of FID7 that are included in the MAC calculation of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
resp_mac_subfid8_map [bt_binaryf(8)]	Defines the sub-FIDs of FID8 that are included in the MAC calculation of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
resp_mac_subfid9_map [bt_binaryf(8)]	Defines the sub-FIDs of FID9 that are included in the MAC calculation of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is required, the bit is turned on.
resp_cond_fid_map [bt_binaryf(8)]	Defines the conditional FIDs to be returned in a device response message. Each byte represents 8 FIDs. If the FID is conditional, the bit is turned on.
resp_cond_subfid6_map [bt_binaryf(8)]	Defines the conditional sub-FIDs to be returned in FID 6 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is conditional, the bit is turned on.
resp_cond_subfid7_map [bt_binaryf(8)]	Defines the conditional sub-FIDs to be returned in FID 7 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is conditional, the bit is turned on.
resp_cond_subfid8_map [bt_binaryf(8)]	Defines the conditional sub-FIDs to be returned in FID 8 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is conditional, the bit is turned on.
resp_cond_subfid9_map [bt_binaryf(8)]	Defines the conditional sub-FIDs to be returned in FID 9 of a device response message. Each byte represents 8 sub-FIDs. If the sub-FID is conditional, the bit is turned on.

SPDH_opt_resp_data (1.0) (spiod)

The SPDH Action Code Description table identifies optional data to be returned in the response message.

[Audited] [Supports versioning]

OLTP: SPDH_opt_resp_data_OLTP

Element (type)	Description
chan_cnfg_prfl*[prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files.
act_cde_extrn*[bt_stringf(3)]	The external action code which is used to map to an internal action code or is the result of a mapping from an internal action code. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces). Must be 1 to 3 characters in length.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
opt_data_1 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_2 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_3 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_4 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_5 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_6 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_7 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_8 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_9 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.
opt_data_10 [bt_stringf(2)]	Specifies optional FID/subFID data to be returned in a device response message.

SPDH_txn_cde_descr (1.0) (spitd)

The SPDH Transaction Code Description table contains the text description of the transaction code that is returned in the SPDH response message.

[Audited] [Supports versioning]

OLTP: SPDH_txn_cde_descr_OLTP

Element (type)	Description
chan_cnfg_prfl*[prfl_def 1.0]	Profile field from the Channel Profile data source that is used as an element in the primary key of the device-specific configuration files.
lang_id*[bt_int16s]	A code indicating the language table used by the delivery channel when sending responses to the terminal. This code enables responses to be displayed on the terminal in one of three different languages. Valid values are: 1 - Language table 1, 2 - Language table 2, 3 - Language table 3. The particular language represented in each table is up to the discretion of the institution. For example, table 1 could be English, table 2 could be French, and table 3 could be Spanish. Default value is one.
txn_cde*[bt_stringf(2)]	The transaction code, which is the first 2 bytes of the processing code. The default value is zeroes.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
txn_cde_descr [bt_stringf(24)]	Text description of the transaction code.

SrchFld (1.0) (usrchf)

Search Field table

[Audited] [Supports versioning]

Element (type)	Description
SFID*[bt_int32s]	
ContextID [bt_int32s]	
SearchField [bt_stringf(30)]	
SearchValue [bt_stringv(50)]	

SRCHPRFL (1.0) (srchd)

This data source contains the ATM Surcharge configuration. The data is accessed via the surcharge profile configured on the ATMDS1 table.

[Audited] [Supports versioning]

Element (type)	Description
TermSrchPrflTx*[bt_stringf(16)]	This field is used for surcharging. This field identifies the terminal surcharge group of which this terminal is a member. The data is configured on the ES ATDS1. It is passed to the authorization system where it is used for surcharge calculations.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
SrchAmntLmtNum [bt_int32s]	This field is used to store the maximum surcharge amount displayed to a cardholder in Non-Interactive Surcharging transactions. The value is configured on the ES ATD Configuration PProfile table (ATDCNFG). This value is downloaded to the terminal as part of the screen configuration. Loading is managed by the Surcharge Amount Limit Indicator. The default value is 0.
SrchAmntLmtCrncCd [crncy_cde 1.0]	This field contains the currency code associated with the maximum surcharge amount displayed to a cardholder in Non-Interactive Surcharging transactions.
TermSrchMthdCd [bt_stringf(1)]	This field is used for surcharging. This field specifies the terminals surcharging method. Valid values are: 0 = Not configured 1 = Interactive Request (pre-auth) Notification 2 = Non-Interactive Surcharging 3 = Interactive Response (post-auth) Notification The default value is 0. The data is configured on the ES ATD COnfiguration Profile table (ATDCNFG).
SrchAmntLmtIndCd [bt_stringf(1)]	A flag indicating the status of the Surcharge Amount Limit. The value is configured in the ES ATD Configuration Profile table (ATDCNFG). This flag is set to the value of 3 when the UI modifies the Surcharge Amount Limit and Non-Interactive Surcharging is configured in Surcharge Type. Valid values are: 0 = Not configured 1 = Download complete 2 = Download in progress 3 = Download pending The default value is 0.

SrchXAdt (1.0) (usrchx)

SearchField Audit Relation table

[Audited] [Supports versioning]

Element (type)	Description
ActivityTS* [ts 1.0]	
ActivityID* [bt_int32s]	
SFID* [bt_int32s]	

Star_BIN_File_Updt (1.0) (strbin)

The Star BIN File Update data source contains the BIN updates received from Star Systems. Updates to the Base24-es Star Interface system prefix files will be applied by the Star IPF Refresh process.

[Not Audited] [Does not support versioning]

Element (type)	Description
star_bin_rec [bt_stringv(80)]	This record contains a Star Interchange prefix update record. This record may contain a file header, change detail record or a trailer record.

Star_Institution (2.0) (sinstd)

Star Institution Table.

[Audited] [Supports versioning]

OLTP: Star_Institution_OLTP

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
frd_aba [bt_stringf(10)]	Star FRD-ABA.
acq_spnsr_bnk_id [bt_stringf(11)]	Acquirer Sponsor Bank ID.

Star_Interface (5.0) (strifd)

Star Interface Configuration.

[Audited] [Supports versioning]

OLTP: Star_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_sec_cde [bt_stringf(8)]	Acquirer Message Security Code.
acq_spnsr_bnk_id [bt_stringf(11)]	Acquirer Sponsor Bank ID.
acq_reimb_attr1 [bt_stringf(1)]	Acquirer Reimbursement Attribute 1.
acq_reimb_attr2 [bt_stringf(3)]	Acquirer Reimbursement Attribute 2.
enhnc_acq_bnk_id_proc [bt_flag]	Enhanced acquirer identification code processing
dflt_acq_bnk_id [bt_stringf(11)]	Default acquirer identification code
iss_msg_sec_cde [bt_stringf(8)]	Issuer Message Security Code.
intf_platform [bt_stringf(1)]	Interface Platform.

STAR_Network_Rel (1.0) (strnid)

This data source contains the configurable relationships between the Star Product Identifier and the Base24-es Instrument Type. This data source is used by the Star IPF Refresh to determine the proper Interchange Prefix data source to update.

[Audited] [Supports versioning]

Element (type)	Description
star_netwk_id* [bt_stringf(3)]	This data element identifies the Star Interface Product / Network Identifier.
rte_to_star [bt_flag]	This data element indicates if a transaction for this Star Interface product type should be included in the Star Interchange Prefix data source(s).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_1 [instrm_typ 1.0]	A code identifying the instrument type.

Star_NE_BIN_File_Updt (1.0) (stnbin)

The Star NE BIN File Update data source contains the Interchange Prefix updates received from Star NE. Updates to the Interchange Prefix files will be applied by the Star NE IPF Refresh.

[Not Audited] [Does not support versioning]

Element (type)	Description
star_ne_bin_rec [bt_stringv(80)]	This record contains a Star NE Interchange prefix update record. This record may contain a file header, change detail record or a trailer record.

Star_NE_Network_Rel (1.0) (stnnid)

This data source is used by the Star NE IPF Refresh to associate the Network ID with an instrument type and an Interchange Prefix data source.

[Audited] [Supports versioning]

OLTP: Star_NE_Network_Rel_OLTP

Element (type)	Description
star_ne_netwk_id* [bt_stringf(5)]	This field identifies the network in the BIN file.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_1 [instrm_typ 1.0]	A code identifying the instrument type.
data_src_id [data_src 1.0]	The data source ID. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

STMPPRFL (1.0) (stmpd)

This data source contains the ATM Statment Print Profile configuration. This configuration is used when formatting the statement print data.

[Audited] [Supports versioning]

Element (type)	Description
StmntPrntPrflTx*[prfl_def 1.0]	The statment print profile identifies the statement print parameter setting to be used for the specified ATM.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
StmnLnsPrPgNum [bt_int32s]	The values in the following fields are used by the ES device handler process for statement print transactions. The value is configured in the ES ATD Configuration Profile table (ATDCNFG). The number of lines on statements printed at the terminal. Valid values are 24 through 88. The default value is 60.
StmnLnsPrInchNum [bt_int32s]	The number of lines per inch on statements printed at the terminal. The value is configured in the ES ATD Configuration Profile table (ATDCNFG). The value in this field is sent to the statement printer by the ES device handler process for each statement print transaction. Valid values are: 6 = 6 lines per inch 8 = 8 lines per inch The default value is 6.
StmnLftMrgnNum [bt_int32s]	A code used by the ES device handler to set the left margin for statements printed at the terminal. The value is configured on the ES ATD Configuration Profile table (ATDCNFG). The value in this field is sent to the statement printer for each statement print transaction. This number must be at least four less than the number specified in the Right Margin field. Valid values are 000 through 128. The default value is 000.
StmnRghtMrgnNum [bt_int32s]	A code used by the ES device handler to set the right margin for statements printed at the terminal. The value is configured in the EA ATD Configuration Profile table (ATDCNFG). The value is sent to the statement printer for each statement print transaction. This number must be at least four greater than the number specified in the Left Margin field. Valid values are 004 through 132. The default value is 080.
StmnFrmtCd [bt_stringf(1)]	This field is not used by the Java DH, and is present for compatibility with the C++ DH. Used for statement data compression, which is not supported by the JDH. If used, this field would indicate to the host whether the ES device handler process supports the data compression message format. The data is configured on the ES ATD Configuration Profile table (ATDCNFG). Valid values are: 0 = Columnar format (data compression is not supported). 1 = BASE24-atm data compression format (data compression is supported). The default value is 0.
StmnIgnrTxtCd [bt_stringf(1)]	This field is not used by the Java DH, and is present for compatibility with the C++ DH. Used for statement data compression, which is not supported by the JDH. If used, this field would indicate to the Device Handler process whether the host can send ignore text codes in its statement print response messages. Ignore text codes enable hosts to set aside a certain number of characters of statement print data for tracking information. This information is echoed back to the host as is. The device handler process ignores the characters when sending the statement print data to the ATM. Because a statement print transaction can involve multiple host requests and responses, the ignore text option can be useful to allow hosts to keep track of where they are in the statement print message sequence. The ignore text code is represented by ?nnn with nnn indicating the number of bytes of text that can be ignored by the Device Handler process in that portion of the message.

STMTDATA (1.0) (stmtd)

ES device handler table. This table is used to temporarily store statement data to be printed in a statement print transaction. The data is saved in this table because it cannot be stored reliably in memory context or in the ES ATD structures. The table is only used in statement print transactions.

[Audited] [Supports versioning]

Element (type)	Description
TermIdTx*[bt_stringf(16)]	A unique identifier for a terminal in the ATM system. The terminal identifier is configured in the ES ATDS1 table and is used to link the ATM terminal to the ES ATDD1, ESATDD2, and ES ATD Load tables.
TranSqncNmbrNum*[bt_int32s]	The last transaction sequence number. If the terminal supports the generation of such a number, this number comes from the terminal. Otherwise, it is generated by the ES device handler for the terminal. The data is stored on the ES ATDD1 table.
StmntSqncNmbrNum*[bt_int32s]	The statement sequence number used to chunk the statement for storage in this table. Since the data is too long to store in one row, the data is spread across multiple rows. Each row has a unique statement sequence number. The values range from 0 to n, where n is the largest possible value that may be stored using the specified data type. The data is stored on the Statement Data table (STMTDATA) and is managed by the ES device handler.
TranTm [ts 1.0]	The transaction date and time stored with statement data in the Statement Data table (STMTDATA). This field is used to detect old statement data so that it can be deleted by a cleanup process. The data is managed by the ES device handler.
StmntData [bt_stringv(4000)]	A chunk of statement data, stored in the Statement Data table (STMTDATA). The data is managed by the ES device handler.

Stop_Payment (1.0) (stppyd)

The Stop Payment data source contains one record for each institution- or customer-initiated stop pay item that should not be honored.

[Audited] [Supports versioning]

Element (type)	Description
inst_id*[inst_id 1.0]	The ID of the financial institution owning the account specified in the acct_num field.
acct_num*[bt_stringf(28)]	The account number of the customer's account at the institution that has a stop payment on the check.
acct_typ*[bt_stringf(2)]	The type of customer account specified in the acct_num field.
hi_chk_num*[bt_stringf(11)]	The check number of the stop payment. For a range of check numbers, this field contains the highest check number in the range. The check number is right-justified and zero-filled on the left.
lo_chk_num*[bt_stringf(11)]	For a range of check numbers, this field will contain the lowest check number in the range. The check number is right-justified and zero-filled on the left. If the stop payment record is for a single check (i.e. not a range of checks), this field will contain the same value as the hi_chk_num field.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record.
refr_ts [yymmddhhmmss 1.0]	Refresh Time Stamp. Timestamp of the refresh that created this record.
refr_id [bt_stringf(32)]	An indicator of the refresh that created this record. This field is informational only.

Element (type)	Description
amt [bt_int64s]	The amount of the check, in whole and fractional currency units, for which the stop payment has been issued. The default value is zero. For a range of check numbers, this field must contain a zero. For a single check number(i.e. not a range), this field can contain a value greater than or equal to zero.
crncy_cde [crncy_cde 1.0]	The ISO currency code of the check amount. The default value is 840 for U.S.
dat [bt_stringf(8)]	The date (YYYYMMDD) of the stop payment. The default value is the current system date.
tim [bt_stringf(6)]	The time (hhmmss) of the stop payment. The default value is the current system time.
exp_dat [bt_stringf(8)]	The expiration date (YYYYMMDD) for the stop payment. The default value is calculated from the stop payment date and the STOP_PMNT_EXP_DAYS environment parameter.
chk_typ [bt_stringf(2)]	The type of check for the stop payment. Valid values are 00 - 99. For example: 01 could indicate personal check, 02 could indicate business check, etc. Also, the check type's values may differ from institution to institution. For example, institution BankOne may use 01 to specify a personal check, and institution BankTwo may use 02 to specify a personal check. The default value is 00, which indicates no check type value (i.e., (None) on the UI).
descr [bt_stringf(35)]	A message regarding the stop payment order. It documents and displays any data about the stop payment order that the institution placed on the file. The default value is spaces.

Store_and_Forward (2.0) (safd)

The Store and Forward (SAF) table contains all the records which are stored to be forwarded to the interface at a later time.

[Audited] [Supports versioning]

Element (type)	Description
fm_ts_saf*[bt_int64s]	The timestamp of when the Store and Forward (SAF) record was initially added.
pan*[bt_stringf(28)]	Primary Account Number
pan_hash [bt_int16s]	The hash value of the Primary Account Number (PAN).
cmpnt_id [bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
intf_nam [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
saf_repeat_flg [bt_flag]	Flag indicating whether the SAF has been sent previously and the next time it is sent, it will be a repeat. Valid values are: 0 - SAF message has not been sent before, 1 - SAF message has been sent before. Default value is 0.
ctx_key [bt_stringf(80)]	The context key supplied by the client when storing and retrieving context data.

Element (type)	Description
saf_msg [bt_binaryv(3900)]	This is the contents of the Store and Forward (SAF) message which is used to send a message to an interface. This may be a fully built message ready to be sent or a partially built message needing additional formatting before sending. The specific interface defines the layout of this field.

Stream (1.0) (strmd)

The Stream table contains one record per line to be written to a write only data source. The line is composed of a single variable length string.

[Not Audited] [Does not support versioning]

Element (type)	Description
stream_element [bt_stringv(4062)]	The stream element is a variable length string to be written to the write only data source.

Stream132 (1.0) (strm2d)

The Stream table contains one record per line to be written to a write only data source. The line is composed of a single variable length string.

[Not Audited] [Does not support versioning]

Element (type)	Description
stream_element [bt_stringv(132)]	The stream element is a variable length string to be written to the write only data source.

Stream_Binary (1.0) (strmbd)

The Stream table contains one record per line to be written to a write only data source. The line is composed of a single variable length binary value.

[Not Audited] [Does not support versioning]

Element (type)	Description
stream_element [bt_binaryv(4062)]	The stream element is a variable length binary to be written to the write only data source.

Surcharge (2.0) (surchd)

This is the surcharge datasource. There is a surcharge relationship between the acquirer and the issuer. An acquirer might support surcharging but not for their own cards for example. Also, different surcharges can be implemented by processing code and transaction currency codes.

[Audited] [Supports versioning]

OLTP: Surcharge_OLTP

Element (type)	Description
acq_surch_prfl*[prfl_def 1.0]	The Acquirer Surcharge Profile. This allows acquirers to be grouped together in logical surcharging groups for acquirers that perform the same surcharging logic.
iss_surch_prfl*[prfl_def 1.0]	The Issuer Surcharge Profile. This allows Issuers to be grouped together in logical surcharging groups for Issuers that perform the same surcharging logic.
proc_cde*[proc_cde 1.0]	The processing code used to describe the effect of a transaction on the customer account and the accounts affected.
crncy_cde*[crncy_cde 1.0]	The numeric currency code as defined in ISO document 4217.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
surch_rvsl_cde [bt_char]	Indicates if a fee should be applied to partial reversals of cash dispenses 1 – no fee 2 – fee
surch_flat_fee [bt_int32s]	This field contains a static surcharge amount in the currency defined in by the transaction currency code, including any implied decimal place.
surch_prctn_fee [bt_int16s]	This field contains a surcharge percentage, expressed in hundredths of a percent (e.g. 100 = 1%).
surch_fee_ind [bt_char]	Indicates the interaction between the Flat Fee and the Percent Fee. 1 – Use the greater of the two fees 2 – Use the lesser of the two fees
surch_min_txn_amt [bt_int64s]	The minimum amount the transaction must be in order to add a surcharge. If the transaction amount is less than the minimum, no surcharge fee is assessed.
surch_max_ovrd [bt_flag]	A flag to indicate whether the maximum the user has previously agreed to in a non-interactive mode can be overridden if the surcharge fee is greater than the fee already presented. This only applies for transactions where an amount is presented to the user prior to performing the transaction and is not zero. Valid values are: 0 – No, use the minimum of the computed fee and the maximum presented at the ATM. 1 – Yes, use the computed fee. Default is 0

Surcharge_Country_Code (1.0) (sucdd)

This data source contains the Surcharge Country Codes. This data source is used by the IPF Refreshes to determine the issuer surcharge profile.

[Audited] [Supports versioning]

OLTP: Surcharge_Country_Code_OLTP

Element (type)	Description
cmpnt_id*[bt_stringf(8)]	The component identifier of a client. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
cnyr_cde*[bt_stringf(3)]	3 Alphabetic characters Country Code.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
iss_surch_prfl [prfl_def 1.0]	The Issuer Surcharge Profile. This allows Issuers to be grouped together in logical surcharging groups for Issuers that perform the same surcharging logic.
no_surch_mbr_prfl [bt_stringf(16)]	The no surcharge member profile allows acquirers and issuers to participate in a no surcharge alliance.

SVS_Interface (1.0) (svsifd)

[Audited] [Supports versioning]

OLTP: SVS_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
enhnc_svs_mrch_num_proc [bt_flag DEFAULT 0]	Enhanced SVS Merchant Number processing
dflt_svs_mrch_num [bt_stringf(6)]	Default acquirer identification code

SVS_Mrch_Num (1.0) (svsmnd)

No description on file.

[Audited] [Supports versioning]

OLTP: SVS_Mrch_Num_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
svs_mrch_num [bt_stringf(6)]	SVS Merchant Number assigned to institution - interface instance pair.

System_Algorithm_Config (1.0) (sacd)

The System Algorithm Configuration table contains one record for each prefix/prefix range and pan length based on the algorithm name.

[Audited] [Supports versioning]

OLTP: System_Algorithm_Config_OLTP

Element (type)	Description
algo_nam*[bt_stringf(16)]	The algorithm name. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
pan_lgth*[bt_int16s]	Pan Length.
low_prfx*[prfx_range 1.0]	The lowest prefix in the range. The prefix is the first n digits of a Primary Account Number (PAN) which defines the issuer of the PAN. The range is specified by the low and high prefix inclusive. This field is left-justified (containing numeric characters, without any embedded spaces).
high_prfx*[prfx_range 1.0]	The high prefix in the range. The prefix is the first n digits of a Primary Account Number (PAN) which defines the issuer of the PAN. The range is specified by the low and high prefix inclusive. This field is left-justified (containing numeric characters, without any embedded spaces). The number of characters in the low and high prefix must match. The high prefix must be greater than or equal to the low prefix.
prfx_lgth*[bt_int16s]	The length of the prefix. This is the number of significant digits are in the prefix.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

System_Prefix (2.0) (sprfxd)

The System Prefix table contains one record for each unknown prefix to search based on Source Logical Network and Acquirer Route Profile to determine the correct issuer. The Acquirer Route Profile may be wildcarded.

[Audited] [Supports versioning]

OLTP: System_Prefix_OLTP

Element (type)	Description
src_lgnt*[lgnt 1.0]	The logical network of the transaction source. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
acq_rte_prfl*[prfl_def 1.0]	The route profile for the acquirer who acquired the transaction. The route profile is defined at the end-point level or at the end-point owners level (e.g., the terminal owner) and allows one or more acquirers to share transaction code definitions. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.

Element (type)	Description
srch_order* [bt_int16s]	The search order when checking whether a prefix exists for the Primary Account Number (PAN) being looked up. It allows multiple System Prefix records to exist for the same Source Logical Network and Acquirer Route Profile combination.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ [instrm_typ 1.0]	One or two character codes which are used to identify instrument types. The same codes must be used for a particular instrument type in all of the files. Instrument type indicates the identification token used to identify a consumer and associate them with a payment account number. The instrument type could be a card, a phone number, User ID, or some other number or code. In a card-based payment system, the instrument type represents the branding of the card, such as Visa Debit, Visa Credit, American Express, MasterCard, etc.
method_typ [bt_stringf(16)]	The prefix method defined for this source logical network, acquirer route profile, and search order combination. Valid values are : PRFX, ICHG_PRFX, DEFAULT or any algorithm name specified in the System Algorithm Configuration table. An algorithm is left-justified, upper case (containing any combination of alphanumeric and special characters, without any embedded spaces).
data_src_id [data_src 1.0]	The data source ID. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
iss_inst_id [inst_id 1.0]	The issuer institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
iss_rte_prfl [prfl_def 1.0]	The route profile of the issuer whose customer initiated the transaction. The issuer route profile is defined where ever the issuer is determine and allows one or more issuers to share routing and authorization configurations. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is asterisks.
iss_surch_prfl [prfl_def 1.0]	The Issuer Surcharge Profile. This allows Issuers to be grouped together in logical surcharging groups for Issuers that perform the same surcharging logic.
rte_typ [bt_stringf(1)]	The route type identifies whether to use the acquirer/issuer profile or issuer profile only. If the acquirer/issuer profile is used, Router will perform a lookup using the Acquirer Issuer Relation table and then use the Route table. If the issuer profile only is used, only the Route table is used. Valid values are: 0 - Acquirer/Issuer, 1 - Issuer only. Default value is 0.
lmt_prfl [prfl_def 1.0]	The limit profile. Used as the key to the Limit Table.

TaskFlds (1.0) (utskfl)

Task Fields table

[Audited] [Supports versioning]

Element (type)	Description
TaskID* [bt_stringf(30)]	
FieldID* [bt_stringf(30)]	

TaskFncs (1.0) (utskfn)

Task Functions table

[Audited] [Supports versioning]

Element (type)	Description
TaskID*[bt_stringf(30)]	
FunctionID*[bt_stringf(30)]	

Tasks (1.0) (utasks)

Tasks table

[Audited] [Supports versioning]

Element (type)	Description
TaskID*[bt_stringf(30)]	
Descr [bt_stringf(50)]	
ParentTaskID [bt_stringf(30)]	

TBP_Daily (2.0) (tbpdd)

The Transaction Based Pricing Daily table contains records by date. Multiple records by date may exist if more data exists than what will fit in a single record.

[Audited] [Supports versioning]

Element (type)	Description
yyyymmdd*[bt_stringf(8)]	The fully qualified date with no field separators.
rec_num_bin*[bt_int16s]	This field is used to make a primary key unique when multiple rows exist for the other fields in the primary key. rec_num begins with value 1.
chk_dgt [bt_int32s]	Check digit to validate buffer and date hasnt been modified.
data_buf [bt_binaryv(4036)]	Buffer used to hold data.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

TERM_LN_FIID_MAP (1.0) (tlnfid)

This table is used to map Logical Network-FIID combinations to specific names or default values. This is used to map configurations on acquired transactions to configurations built as business units in Payments Manager.

[Audited] [Supports versioning]

OLTP: TERM_LN_FIID_MAP_OLTP

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
term_ln*[bt_stringf(4)]	The logical network associated with the terminal for an acquired transaction. Wildcarding (all asterisks) is allowed.
term_fiid*[bt_stringf(4)]	The financial institution ID associated with the terminal for an acquired transaction. Wildcarding (all asterisks) is allowed.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
new_term_ln [bt_stringf(4)]	The logical network that is the desired configuration associated with the terminal for an acquired transaction.
new_term_fiid [bt_stringf(4)]	The financial institution ID that is the desired configuration for the terminal on an acquired transaction.

Ticket (1.0) (utickt)

Ticket table

[Audited] [Supports versioning]

Element (type)	Description
UserID*[bt_stringf(16)]	
AuthorizationID*[bt_stringf(28)]	
ExpireTS [ts 1.0]	

TMX (1.0) (tmxd)

This table is used as output for extract scripts.

[Not Audited] [Does not support versioning]

Element (type)	Description
tmx_element [bt_stringv(4058)]	The character buffer used as output for extract scripts.

Token_Config (1.0) (tknd)

Contains a list of token ids that pertain to the specified profile. Profiles can be defined for extract scripts, IMT and the BASE24 HISO interface.

[Audited] [Supports versioning]

OLTP: Token_Config_OLTP

Element (type)	Description
tkn_prfl* [bt_stringf(16)]	Value used as the primary key to read the Token Config table. Token profiles can be configured in the IMT and HISO 87 tables and can be specified in (P)TLF Extract scripts.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ttl_tkn_cnt [bt_int16s]	The total number of token ids defined in the Token Id buffer.
tkn_id_buf [bt_stringv(1296)]	A buffer containing a string of 2-byte token ids.

Token_Id_List (2.0) (tknid)

Contains a BASE24 token id. This table will be used by the UI for token list suppression.

[Audited] [Supports versioning]

Element (type)	Description
tkn_id* [bt_stringf(2)]	The 2 character id assigned to a BASE24 token.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Totals (1.0) (ttlId)

Totals are defined by the endpoints.

[Audited] [Supports versioning]

Element (type)	Description
endpoint_nam* [bt_stringf(16)]	Interface Name or Channel ID.
ttl_dat* [bt_stringf(8)]	Normally the posting date. YYYYMMDD
ttl_dir* [bt_stringf(1)]	Direction (A = Acquirer, I = Issuer).
ttl_endpoint_key* [bt_stringf(20)]	Defined by endpoint.
ttl_buf [bt_binaryv(1000)]	Defined by endpoint.

Totals_Configuration (1.0) (ttlcd)

Totals configuration.

[Audited] [Supports versioning]

OLTP: Totals_Configuration_OLTP

Element (type)	Description
endpoint_nam*[bt_stringf(16)]	Interface Name or Channel ID.
ttl_onl_asgn_nam [bt_stringf(32)]	Totals Entry Assign Name.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
ttl_mgr_nam [bt_stringf(16)]	Totals Manager Name.
ttl_delay_timr_lmt [bt_int16s]	Totals Delay Timer Limit.
ttl_updt_intrvl [bt_int16s]	Number of totals entries to read before updating.
ttl_retn_prd [bt_int16s]	Used to determine if an entry is stale and when to delete previous totals records.

Totals_Entry (1.0) (ttled)

The Totals Entry data source contains the delta values which will be applied to the Totals data source at a later time. The IS will write an entry with delta values to update the totals.

[Audited] [Supports versioning]

Element (type)	Description
ttl_ts*[bt_int64s]	Totals Timestamp.
pan*[bt_stringf(28)]	Primary Account Number
endpoint_nam [bt_stringf(16)]	Interface Name or Channel ID.
ttl_dat [bt_stringf(8)]	Normally the posting date. YYYYMMDD
ttl_dir [bt_stringf(1)]	Direction (A = Acquirer, I = Issuer).
ttl_endpoint_key [bt_stringf(20)]	Defined by endpoint.
ttl_buf [bt_binaryv(1000)]	Defined by endpoint.

Totals_Entry2 (1.0) (ttle2d)

The Totals Entry data source contains the delta values which will be applied to the Totals data source at a later time. The IS will write an entry with delta values to update the totals.

[Audited] [Supports versioning]

Element (type)	Description
ttl_ts*[bt_int64s]	Totals Timestamp.
pan*[bt_stringf(28)]	Primary Account Number
site_id*[bt_stringf(1)]	Site ID as specified in the Environment Table. Used to make records unique when replicated.
ttl_dir [bt_stringf(1)]	Direction (A = Acquirer, I = Issuer).
endpoint_nam [bt_stringf(16)]	Interface Name or Channel ID.

Element (type)	Description
ttl_dat [bt_stringf(8)]	Normally the posting date. YYYYMMDD
ttl_endpoint_key [bt_stringf(20)]	Defined by endpoint.
ttl_buf [bt_binaryv(1000)]	Defined by endpoint.

Totals_Tag_Documentation (1.0) (ttltd)

Totals tag documentation.

[Audited] [Supports versioning]

Element (type)	Description
tag_id* [bt_stringf(2)]	Tag identifier.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
tag_nam [bt_stringf(20)]	Tag name.
tag_amt_flg [bt_flag]	Indicates whether the tag contains an amount. Valid values are: 1 – tag contains an amount, 0 – tag does not contain an amount.
ttl_desc [bt_stringf(256)]	Totals description.
ttl_usg [bt_stringf(256)]	A list of Endpoint components that use the tag.

Trace (1.0) (trcd)

This is the trace table which contains the output generated from a trace. If all the trace data does not fit into the trace buffer, multiple records are inserted with the record number incremented each time.

[Not Audited] [Supports versioning]

Element (type)	Description
yyyymmddhhmmsslllccc* [bt_stringf(20)]	The fully qualified date and time with no field separators.
sym_pro_id* [bt_stringf(28)]	A symbolic process ID as defined by SIS, which may represent a system and PPD name, CICS region and task name, IP host name and task id or whatever uniquely identifies a specific process on a given platform.
sym_thrd_id* [bt_stringf(8)]	A symbolic thread ID as defined by SIS, used to distinguish between threads/tasks of a single process.
rec_num_bin* [bt_int16s]	This field is used to make a primary key unique when multiple rows exist for the other fields in the primary key. rec_num begins with value 1.
trc_buf [bt_stringv(3992)]	Trace buffer containing trace data.

Trace_Config (1.0) (trccfd)

The Trace Config table contains an entry per process type, which defines whether tracing is enabled, and if so, the trace levels and filters to use.

[Audited] [Supports versioning]

Element (type)	Description
pro_typ* [bt_stringf(4)]	The process type of the executable. Valid values are IS, XMLS, EOPP, JQB, CMCP, RFSH, SAFM, DRVR.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
trc_flg [bt_int16s]	Trace Flag, indicates whether the process should perform tracing or not. Valid values are: 0 = Do not perform any tracing, 1 = Perform tracing. Default value is 0.
trc_hdr_flg [bt_int16s]	Trace Header Flag, indicates whether a trace header should be included in the Trace output which includes the component and trace level along with the data. Valid values are: 0 = Do not include the trace header, 1 = Include the trace header. Default value is 0.
asgn_nam [bt_stringf(32)]	The assign name used to map to a physical location. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
filter_prfl [prfl_def 1.0]	The filter profile. Used as part of the primary key to the Trace Filter Table.
trc_lvls [bt_stringv(300)]	The trace levels concatenated together which the process should perform if trace is enabled.

Trace_Filter (1.0) (trcflf)

The Trace Filter table contains an entry per filter type and filter value for each filter profile.

[Audited] [Supports versioning]

Element (type)	Description
filter_prfl* [prfl_def 1.0]	The filter profile. Used as part of the primary key to the Trace Filter Table.
filter_typ* [bt_int16s]	The type of filter to determine whether trace should be captured. Valid values are: 0 - Symbolic message source, 1 - Symbolic message destination, 2 - Primary Account Number, 3 - Partial Primary Account Number, 4 - acquiring end point name, 5 - issuing end point name, 6 - acquiring institution, 7 - issuing institution, 8 - terminal id, 9 - processing code, 10 - action code.
filter_val* [bt_stringf(28)]	The value of the filter used to determine whether trace should be captured. Maximum length of value varies based on filter type, but must be fixed length to allow it to be a key field.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Transport_Key (1.0) (trnsd)

This table contains a PIN Encryption Key which will be used to encrypt the PIN Block in the PIN Change TDE prior to journaling the TDE. The PIN is translated from the acquirers PIN Encryption Key to the PIN Encryption Key defined in this table. The PIN Encryption Key in this table is known by the card management system. This table also includes a Key Exchange Key - the PIN Encryption Key received from the card management system is encrypted under this Key Exchange Key.

[Audited] [Supports versioning]

OLTP: Transport_Key_OLTP

Element (type)	Description
trnsprt_key_loc*[bt_stringf(16)]	An identifier (key locator) defining the transport key to be used to encrypt PIN Change data before journaling to the log file and subsequently extracted. Required to allow PIN Change data to be securely shared with card management systems. The field is left-justified, upper case(containing any combination of alphanumeric and special characters, but without any embedded spaces). Default to spaces.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
pin_pad_char [bt_char]	PIN Pad character used to pad the PIN block. Valid values are 0 - 9, A - F. Default is F.
pin_blk_typ [bt_char]	PIN Block Type - specifies the PIN block format of the PIN in the inbound external messages. Valid values are: 0 - Clear, PINs are not encrypted. 1 - ANSI PIN block (ISO Format 0), default. 3 - PIN/Pad PIN block. 5 - ISO Format 1.
kkt_pt_import_hdr [keyx_hdr 1.0]	PIN key exchange key header required for the Atalla Key Block (AKB) format.
kkt_pt_import_keyx [keyx_trpl 1.0]	PIN Transport - Import Encryption Key. Contains the PIN key exchange key encrypted under the master key of the hardware security module. This key is used for importing PIN key exchange keys from another system. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16 bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
kkt_pt_import_kam [keyx_kam 1.0]	PIN key exchange key MAC value required for the Atalla Key Block (AKB) format.
kkt_pt_import_vvk [vvk 1.0]	PIN Transport - Verification Value. Contains the verification value of the PIN import key exchange key. The verification value is used to detect key synchronization errors.
outbnd_kpt1_hdr [keyx_hdr 1.0]	PIN Encryption Key header required for the Atalla Key Block (AKB) format.
outbnd_kpt1_keyx [keyx_trpl 1.0]	Outbound PIN Transport - Encrypted Key. Contains the PIN encryption key encrypted under the master key of the hardware security module. May be one part (contained in the first 16 bytes with the remaining 32 bytes set to spaces), two parts (first key part in the first 16 bytes, the second key part in the second 16 bytes with the remaining 16 bytes set to spaces) or three parts (first key part in the first 16

Element (type)	Description
	bytes, second key part in the second 16 bytes and third key part in the last 16 bytes).
outbnd_kpt1_kam [keyx_kam 1.0]	PIN Encryption Key MAC value required for the Atalla Key Block (AKB) format.
outbnd_kpt1_vvk [vvk 1.0]	Outbound PIN Transport - Verification Value. Contains the verification value of the PIN key. The verification value is used to detect key synchronization errors.

UAE_Interface (1.0) (uaeifd)

The UAE Interface Table.

[Audited] [Supports versioning]

Element (type)	Description
intf_nam*[bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
swi_setl_dat [bt_stringf(8)]	The switch settlement date. YYYYMMDD

Usage (2.0) (usgd)

This table contains the usages associated with a card, account or customer. The usages are checked against limits which are defined in the Limit Table.

[Audited] [Supports versioning]

Element (type)	Description
inst_id*[inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
id_typ*[bt_stringf(2)]	Indicates the type of entity the ID represents. Valid values are CD for card, AC for account.
id*[bt_stringf(28)]	The card or account number based on the id_typ field.
scndry_id*[bt_stringf(3)]	The secondary id associated with a card or account number based on the id_typ field. This could be a card sequence number or an account type. Default value is 000.
rec_num*[bt_stringf(3)]	This field is used to make a primary key unique when multiple rows exist for the other fields in the primary key. rec_num begins with value 1 except for the Card Account table which begins with value 0.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

Element (type)	Description
usg_adnl [bt_int16s]	Indicates if additional usages exist for an instrument type. Valid values are: 0 - No (default). 1 - Yes.
lmt_usg_1_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_1_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_1_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_1_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_2_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_2_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_2_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_2_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_3_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_3_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_3_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_3_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_4_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_4_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_4_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_4_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_5_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_5_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_5_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_5_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_6_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_6_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_6_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_6_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_7_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_7_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_7_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_7_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_8_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_8_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_8_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_8_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_9_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_9_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_9_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_9_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_10_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.

Element (type)	Description
lmt_usg_10_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_10_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_10_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_11_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_11_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_11_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_11_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_12_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_12_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_12_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_12_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_13_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_13_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_13_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_13_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_14_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_14_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_14_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_14_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_15_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_15_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_15_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_15_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_16_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_16_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_16_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_16_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_17_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_17_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_17_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_17_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_18_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_18_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_18_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_18_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_19_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_19_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_19_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.

Element (type)	Description
lmt_usg_19_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_20_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_20_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_20_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_20_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_21_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_21_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_21_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_21_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_22_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_22_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_22_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_22_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_23_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_23_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_23_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_23_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_24_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_24_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_24_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_24_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_25_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_25_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_25_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_25_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_26_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_26_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_26_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_26_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_27_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_27_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_27_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_27_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_28_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_28_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_28_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_28_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_29_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.

Element (type)	Description
lmt_usg_29_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_29_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_29_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_30_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_30_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_30_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_30_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_31_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_31_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_31_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_31_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_32_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_32_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_32_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_32_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_33_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_33_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_33_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_33_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_34_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_34_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_34_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_34_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_35_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_35_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_35_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_35_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_36_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_36_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_36_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_36_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_37_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_37_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_37_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_37_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_38_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_38_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_38_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.

Element (type)	Description
lmt_usg_38_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_39_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_39_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_39_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_39_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_40_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_40_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_40_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_40_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_41_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_41_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_41_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_41_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_42_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_42_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_42_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_42_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_43_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_43_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_43_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_43_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_44_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_44_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_44_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_44_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_45_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_45_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_45_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_45_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_46_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_46_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_46_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_46_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_47_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_47_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_47_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_47_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_48_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.

Element (type)	Description
lmt_usg_48_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_48_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_48_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_49_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_49_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_49_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_49_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_50_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_50_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_50_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_50_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_51_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_51_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_51_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_51_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_52_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_52_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_52_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_52_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_53_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_53_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_53_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_53_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_54_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_54_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_54_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_54_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_55_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_55_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_55_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_55_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_56_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_56_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_56_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_56_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_57_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_57_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_57_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.

Element (type)	Description
lmt_usg_57_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_58_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_58_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_58_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_58_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_59_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_59_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_59_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_59_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_60_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_60_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_60_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_60_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_61_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_61_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_61_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_61_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_62_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_62_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_62_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_62_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_63_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_63_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_63_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_63_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_64_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_64_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_64_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_64_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_65_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_65_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_65_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_65_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_66_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_66_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_66_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_66_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_67_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.

Element (type)	Description
lmt_usg_67_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_67_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_67_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_68_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_68_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_68_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_68_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_69_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_69_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_69_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_69_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_70_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_70_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_70_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_70_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_71_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_71_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_71_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_71_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_72_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_72_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_72_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_72_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_73_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_73_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_73_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_73_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_74_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_74_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_74_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_74_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_75_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_75_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_75_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_75_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_76_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_76_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_76_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.

Element (type)	Description
lmt_usg_76_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_77_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_77_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_77_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_77_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_78_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_78_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_78_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_78_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_79_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_79_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_79_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_79_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_80_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_80_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_80_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_80_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_81_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_81_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.

Element (type)	Description
lmt_usg_81_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_81_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_82_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_82_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_82_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_82_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_83_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_83_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_83_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_83_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_84_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_84_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_84_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_84_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_85_nam [bt_stringf(16)]	A name assigned to a specific limit and its associated usage for a payment instrument.
lmt_usg_85_amt_used [bt_int64s]	The current usage amount for the associated limit/usage name. The usage is cleared at the end of the usage period defined for the limit/usage.
lmt_usg_85_crncy_cde [crncy_cde 1.0]	The currency code associated with the usage amount.
lmt_usg_85_nxt_beg_dat [ts 1.0]	The date that the next usage period begins for the associated usage. The usage is cleared at the end of the usage period defined for the limit/usage.

Users (3.0) (uusers)

Users table

[Audited] [Supports versioning]

Element (type)	Description
UserID* [bt_stringf(16)]	
UserStatusCode [bt_stringf(2)]	
FirstName [bt_stringf(30)]	
MiddleName [bt_stringf(20)]	
LastName [bt_stringf(50)]	
EmailAddress [bt_stringf(50)]	
Department [bt_stringf(30)]	
Location [bt_stringf(30)]	
ManagerID [bt_stringf(16)]	
WorkPhoneNum [bt_stringf(20)]	
MobileNum [bt_stringf(20)]	
FaxPhoneNum [bt_stringf(20)]	
BadLoginTries [bt_int16s]	
LastFailedLoginTS [ts 1.0]	
LastLoginTS [ts 1.0]	
CreateTS [ts 1.0]	
SecurityGroupID [bt_stringf(30)]	
LastMaintTS [ts 1.0]	
OwnerID [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.
ContactInfo [bt_binaryl(400)]	Contact Information
UserActiveTS [ts 1.0 DEFAULT 0]	The date a user becomes active.
UserExpireTS [ts 1.0 DEFAULT 0]	The date the user becomes closed. This will be used when temporary users are added to the system.

User_Perusal_Prfl_Relation (1.0) (upprd)

The User Perusal Profile Relation table contains one record for each alias which maps specific users to a user profile.

[Audited] [Supports versioning]

OLTP: User_Perusal_Prfl_Relation_OLTP

Element (type)	Description
user_prfl [usr_prfl 1.0]	The user profile to which the operator belongs which dictates access to the reporting scripts available. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
alias* [bt_stringf(16)]	An alias name for an operator/user which is used to log on to the system. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.

USRAULOG (1.0) (ualogd)

The user audit log table is used to store the User Interface audit records. This table will store information on user interactions with an applications data sources. The data stored in the audit entry detail column in the table is in XML format.

[Audited] [Supports versioning]

Element (type)	Description
UserId* [bt_stringf(50)]	The users id, for UI login. User ID to use for applications to access the database.
AudtEntryTm* [ts 1.0]	Time the audit record was written.
AudtEntryID* [bt_stringf(20)]	An internally generated id to link rows in the user audit log together for activities that occurred in the same user interaction.
AudtEntrySeqNum* [bt_int16s]	Used to provide a unique key when multiple Audit activities where performed in a single request by the user. It will be sequentially incremented for each activity for the same AudtEntryID starting from 1.
AudtSeqNum* [bt_int16s]	The continuation sequence number of an audit record. Audit records that span more than one physical data source row will be sequentially numbered starting with 1.
DataSrc [bt_stringf(25)]	If present, indicates the name of the data source accessed by the user. (This could be an assign name, a service name or the physical name)
AudtEntryType [bt_stringf(20)]	The type of audit entry record. Valid values are: Insert Delete Update-Before Update-After Fetch View Login Logout ChangePassword VerifyPassword
AudtContFlg [bt_stringf(1)]	A flag indicating if there are subsequent rows in the data source that need to be concatenated with the current row to make a complete audit record. Subsequent rows will have a AudtSeqNum sequentially incrementing from the current row number.
SrvclD [bt_stringf(25)]	If present indicates the type of service that logged the record. (This could be product that the data source or user is associated with). The data is stored in the Event Log table (EVNTLOG) when an event is logged.
ApplDfnd [bt_stringf(50)]	An application defined column to use for application specific data that may be used subsequently for extracting rows or perusing rows in the audit log through a User Interface.
AudtEntryDetl [bt_binaryl(3771)]	The raw XML that holds the audit record. See the current User Audit XML API Document for the format of this data.

UsrStat (1.0) (uusrst)

User Status table

[Audited] [Supports versioning]

Element (type)	Description
UserStatusCode* [bt_stringf(2)]	
UserStatusDesc [bt_stringf(15)]	
Descr [bt_stringf(50)]	

USRXFILT (1.0) (uusrxf)

User Filters table

[Audited] [Supports versioning]

Element (type)	Description
UserID* [bt_stringf(16)]	
FilterID* [bt_stringf(30)]	
OwnerID* [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.

UsrXRole (1.0) (uusrxr)

User Roles table

[Audited] [Supports versioning]

Element (type)	Description
UserID* [bt_stringf(16)]	
RoleID* [bt_stringf(30)]	
OwnerID* [bt_stringf(12)]	OwnerID for Distributed System Administration enhancement.

VERSIONS (1.0) (versd)

This table is used by the database initialization logic to check version information to determine if seed data will be loaded to the table.

[Audited] [Supports versioning]

Element (type)	Description
ApplID* [bt_stringf(16)]	Application ID
VersionKey* [bt_stringf(100)]	
VersionValue [bt_stringf(32)]	
VersionDescr [bt_stringf(255)]	Description field.
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

Visa_BIN_File_Updt (1.0) (visbin)

The Visa BIN File Update data source contains the Interchange Prefix updates received from Visa. Updates to the Interchange Prefix files will be applied by the Visa IPF Refresh.

[Not Audited] [Does not support versioning]

Element (type)	Description
visa_bin_rec [bt_stringv(167)]	This record contains a Visa Interchange prefix update record. This record may contain a file header, change detail record or a trailer record.

Visa_Brand_Rel (1.0) (vsbid)

This data source is used by the Visa IPF Refresh to associate the Visa brand with an instrument type and an Interchange Prefix data source.

[Audited] [Supports versioning]

OLTP: Visa_Brand_Rel_OLTP

Element (type)	Description
brand_id* [bt_stringf(1)]	This field identifies the brand in the BIN file.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
instrm_typ_1 [instrm_typ 1.0]	A code identifying the instrument type.
data_src_id [data_src 1.0]	The data source ID. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).

Visa_DPS_Institution (1.0) (vdiid)

Visa DPS Institution Table.

[Audited] [Supports versioning]

OLTP: Visa_DPS_Institution_OLTP

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
acq_spnsr_bnk_id [bt_stringf(11)]	Acquirer Sponsor Bank ID.

Visa_DPS_Interface (2.0) (vdifd)

Visa DPS Interface Configuration.

[Audited] [Supports versioning]

OLTP: Visa_DPS_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
msg_sec_cde [bt_stringf(8)]	Message Security Code.
iss_msg_sec_cde [bt_stringf(8)]	Issuer Message Security Code.
enhnc_acq_bnk_id_proc [bt_flag]	Enhanced acquirer identification code processing
dflt_acq_bnk_id [bt_stringf(11)]	Default Acquirer Sponsor Bank ID.

Visa_Institution (2.0) (vsiid)

Visa Institution Table

[Audited] [Supports versioning]

OLTP: Visa_Institution_OLTP

Element (type)	Description
inst_id* [inst_id 1.0]	The institution identifier uniquely identifying the institution. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
plus_pmc_id [bt_stringf(6)]	This field contains the Plus Proprietary Member Center identifier.
acq_bnk_id [bt_stringf(11)]	The acquirer bank identifier.

Visa_Interface (4.0) (visifd)

The Visa Interface configuration data

[Audited] [Supports versioning]

OLTP: Visa_Interface_OLTP

Element (type)	Description
intf_nam* [bt_stringf(16)]	The symbolic name of the interface. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces).
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
visa_logon_typ [bt_int16s]	The Visa Logon Type defines the type of logon to send to Visa. Valid values are: 0 - Base I, 1 - SMS, 2 - Both
visa_rgn_id [bt_int16s]	Indicates which of the Visa regions whose rules will apply to this interface. Valid values are: 0 - Asia-Pacific Region 1 - Canada Region 2 - CEMEA (Central and Eastern Europe, Middle East and Africa) Region 3 - EU (European Union) Region 4 - Latin America and Caribbean Region 5 - U.S.A. (United States of America) Region
instrm_stat_prfl [bt_stringf(16)]	Instrument status profile. Used as part of the primary key to read the Instrument Status External to Internal data source.
prty_rte_ind [bt_stringf(1)]	This field indicates the type of priority routing. Valid values are 0 – Do not use priority routing, 1 – Use priority routing. Default is 0.
shr_grp_cde [bt_stringf(30)]	These fields identify the sharing groups of which the originating terminal is a part. Set to a value that will be accepted by this endpoint. The default is spaces.
base1_atm_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
base1_pos_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
sms_atm_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
sms_pos_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.
ilink_msg_prfl [bt_stringf(16)]	The message profile of the interface when the interface uses an ISO based message format. This field is left-justified, upper case (containing any combination of alphanumeric and special characters, but without any embedded spaces). The default value is spaces.

Element (type)	Description
proc_cde_prfl [bt_stringf(16)]	The processing code profile used to map an external processing code/transaction code to/from a BASE24-es processing code. The processing code profile allows one or more end points to share processing code definitions. This field is left-justified (containing any combination of alphanumeric and special characters, but without any embedded spaces).
send_pre_auth_compl [bt_flag DEFAULT 0]	Indicates whether the Visa Base 1Base I interface sends pre-authorization completion messages to Visa. Valid values are: 0 - does not send pre-auth completions, 1 - does send pre-auth completions. Default is 0

Visa_PVV (1.0) (vpvvd)

Visa PVV contains information specific to the Visa PVV PIN verification method.

[Audited] [Supports versioning]

OLTP: Visa_PVV_OLTP

Element (type)	Description
pin_vrfy_prfl* [prfl_def 1.0]	An identifier for the profile to which this record applies. This field must contain a value that matches a PIN Verify Profile defined in the Prefix.
beg_dat* [yyyyymm 1.0]	The beginning date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - Signifies that any Card Expiration date that is less than or equal to the specified END-DAT will use this entry. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
end_dat* [yyyyymm 1.0]	The end date of the range of expiration dates which define the use of this entry according to a card expiration date. Valid values are: 200001 - 203512. yyyyymm - Signifies that any Card Expiration Date must be greater than or equal to the Begin Date but less than or equal to the End Date.
fm_ts [ts 1.0]	File Maintenance Time Stamp. Timestamp of last update to the data source record by GUI client application.
key_encrypt_1 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key/card verification key used for performing PIN verification/card verification. The value in this field is used when PIN verification/card verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_2 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key/card verification key used for performing PIN verification/card verification. The value in this field is used when PIN verification/card verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_3 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.

Element (type)	Description
key_encrypt_4 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_5 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_6 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_7 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_8 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_9 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_10 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_11 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_12 [keyx_trpl 1.0]	A security module encrypted version of the PIN verification key used for performing PIN verification. The value in this field is used when PIN verification requests are performed within a hardware security module. The value in this field is 16 hexadecimal digits.
key_encrypt_chk_values_1 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_2 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_3 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_4 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_5 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.

Element (type)	Description
key_encrypt_chk_values_6 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_7 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_8 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_9 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_10 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_11 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_chk_values_12 [chk_digits 1.0]	Contains the check digits for the Key Encrypt key. The value in this field is entered as four hexadecimal characters.
key_encrypt_1_hdr [keyx_hdr 1.0]	PIN Verification Key/Card Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_1_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.
key_encrypt_3_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_3_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.
key_encrypt_5_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_5_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.
key_encrypt_7_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_7_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.
key_encrypt_9_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_9_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.
key_encrypt_11_hdr [keyx_hdr 1.0]	PIN Verification Key header required for the Atalla Key Block (AKB) format.
key_encrypt_11_kam [keyx_kam 1.0]	PIN Verification Key MAC value required for the Atalla Key Block (AKB) format.

WEBAPPOPTS (1.0) (wboptd)

This table defines application options for a web applications.

[Audited] [Supports versioning]

Element (type)	Description
ApplID*[bt_stringf(16)]	Application ID
OptionKey*[bt_stringf(100)]	Key.
OptionValue [bt_stringf(100)]	Value for key.
OptionDescr [bt_stringf(255)]	Description.
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

WEBAPPS (1.0) (webapd)

This table defines configured web applications.

[Audited] [Supports versioning]

Element (type)	Description
ApplID*[bt_stringf(16)]	Application ID
ApplNamTx [bt_stringf(100)]	Name used on screen as default.
ApplBundleNamTx [bt_stringf(32)]	Bundle key to look up name.
ProductID [bt_stringf(16)]	Product Id.
WebAppURL [bt_stringf(256)]	URL to get to this application.
HomePage [bt_stringf(64)]	Home page for application.
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

WEBUSROPTS (1.0) (wbusrd)

This table defines user options for web applications.

[Audited] [Supports versioning]

Element (type)	Description
ApplID*[bt_stringf(16)]	Application ID
UserID*[bt_stringf(64)]	Username.

Element (type)	Description
OptionKey*[bt_stringf(100)]	Key.
OptionValue [bt_stringf(100)]	Value for key.
OptionDescr [bt_stringf(255)]	Description.
LastUpdtTm [ts 1.0]	The Last Update Time, represented as a timestamp, when the database row was last modified by the user interface. On-line processes do not modify Last Update Time.

ZKA_KGK (1.0) (zkgkd)

German Security features. Allow for the storage of KGKs.

[Audited] [Supports versioning]

Element (type)	Description
kgk_key_loc*[bt_stringf(16)]	Channel ID, Interface Name or Profile associated with this record.
kgk_key_typ*[bt_stringf(2)]	The type of KGK key type contained in this record. This is required when multiple KGK's may be required for support of an endpoint (specifically OPT terminals). Default value is 00.
kgk_kgn*[bt_stringf(2)]	The Key Generation Number associated with this key.
kgk_kvn*[bt_stringf(2)]	The Key Version number. Allows for multiple keys for a given endpoint to be stored.
kgk_key_table*[bt_int16s]	The key table (as defined in the German standards) for the associated key. Valid values are: 01 = Production (default) 02 = Emergency Production 03 = Test 04 = Emergency Test
kgk_drv_depth*[bt_int16s]	The derivation depth of the key. Valid values are: 0 = Derivation Depth 0 (default) 1 = Derivation Depth 1
blz_id*[bt_stringf(5)]	Short BLZ (Bank ID). Normally only used with Retail MAC functions (GeldKarte and ecCash).
fm_ts [ts 1.0]	File Maintenance Time Stamp.
key_effective_dat [ts 1.0]	The Key Effective date. This is the first date that the key is available for use. Requests to use the associated key record prior to this date will be denied.
key_expire_dat [ts 1.0]	The Key Expiration date. This is the last date that the key is available for use. Requests to use the associated key record after this date will be denied.
kgk_hdr [keyx_hdr 1.0]	KGK Header. Only used with AKB key format.
kgk_keyx [keyx_trpl 1.0]	KGK Key.
kgk_kam [keyx_kam 1.0]	KGK MAC used for AKB format keys.
kgk_vvk [vvk 1.0]	KGK Check Digits.

List of data elements

This topic provides a list of elements and the data sources to which the element is used. Data sources in bold font indicate that the element is a key element within that data source.

abi_abl_srvc	ABI_Interface ABI_Interface_OLTP
abi_bin_prestitempo	ABI_Interface ABI_Interface_OLTP
abi_cc_rrn	ABI_Interface ABI_Interface_OLTP
abi_e100_gc	ABI_Interface ABI_Interface_OLTP
abi_mac_key	ABI_Key ABI_Key_OLTP
abi_multi_key	ABI_Interface ABI_Interface_OLTP
abi_orig_crncy	ABI_Interface ABI_Interface_OLTP
abi_setl_dat	ABI_Interface ABI_Interface_OLTP
abnrml_pcng_timr_id	Interac_Base
accel_netwk_id	ACCEL_Interface ACCEL_Interface_OLTP
Accn1TypeTx	APCF.xml
Accn2TypeTx	APCF.xml
acct1_typ	Route.xml Route_OLTP.xml
acct2_typ	Route.xml Route_OLTP.xml
acct_cat	Positive_Balance
acct_lgth	Account_Routing.xml Account_Routing_OLTP.xml
acct_num	Journal Journal_Key_Seq Journal_Key_Seq2

	PBAL_Impacts.xml
	Positive_Balance.xml
	Stop_Payment.xml
acct_num_1	Card
	Card_Account
acct_num_10	Card
	Card_Account
acct_num_10_descr	Card
	Card_Account
acct_num_10_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_10_stat	Card
	Card_Account
acct_num_10_typ	Card
	Card_Account
acct_num_11	Card_Account
acct_num_11_descr	Card_Account
acct_num_11_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_11_stat	Card_Account
acct_num_11_typ	Card_Account
acct_num_12	Card_Account
acct_num_12_descr	Card_Account
acct_num_12_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_12_stat	Card_Account
acct_num_12_typ	Card_Account
acct_num_13	Card_Account
acct_num_13_descr	Card_Account
acct_num_13_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_13_stat	Card_Account
acct_num_13_typ	Card_Account
acct_num_14	Card_Account
acct_num_14_descr	Card_Account
acct_num_14_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_14_stat	Card_Account
acct_num_14_typ	Card_Account
acct_num_15	Card_Account
acct_num_15_descr	Card_Account

acct_num_15_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_15_stat	Card_Account
acct_num_15_typ	Card_Account
acct_num_16	Card_Account
acct_num_16_descr	Card_Account
acct_num_16_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_16_stat	Card_Account
acct_num_16_typ	Card_Account
acct_num_17	Card_Account
acct_num_17_descr	Card_Account
acct_num_17_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_17_stat	Card_Account
acct_num_17_typ	Card_Account
acct_num_18	Card_Account
acct_num_18_descr	Card_Account
acct_num_18_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_18_stat	Card_Account
acct_num_18_typ	Card_Account
acct_num_19	Card_Account
acct_num_19_descr	Card_Account
acct_num_19_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_19_stat	Card_Account
acct_num_19_typ	Card_Account
acct_num_1_descr	Card
	Card_Account
acct_num_1_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_1_stat	Card
	Card_Account
acct_num_1_typ	Card
	Card_Account
acct_num_2	Card
	Card_Account
acct_num_20	Card_Account
acct_num_20_descr	Card_Account
acct_num_20_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_20_stat	Card_Account

List of data elements

acct_num_20_typ	Card_Account
acct_num_21	Card_Account
acct_num_21_descr	Card_Account
acct_num_21_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_21_stat	Card_Account
acct_num_21_typ	Card_Account
acct_num_22	Card_Account
acct_num_22_descr	Card_Account
acct_num_22_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_22_stat	Card_Account
acct_num_22_typ	Card_Account
acct_num_23	Card_Account
acct_num_23_descr	Card_Account
acct_num_23_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_23_stat	Card_Account
acct_num_23_typ	Card_Account
acct_num_24	Card_Account
acct_num_24_descr	Card_Account
acct_num_24_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_24_stat	Card_Account
acct_num_24_typ	Card_Account
acct_num_25	Card_Account
acct_num_25_descr	Card_Account
acct_num_25_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_25_stat	Card_Account
acct_num_25_typ	Card_Account
acct_num_26	Card_Account
acct_num_26_descr	Card_Account
acct_num_26_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_26_stat	Card_Account
acct_num_26_typ	Card_Account
acct_num_27	Card_Account
acct_num_27_descr	Card_Account
acct_num_27_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_27_stat	Card_Account
acct_num_27_typ	Card_Account

acct_num_28	Card_Account
acct_num_28_descr	Card_Account
acct_num_28_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_28_stat	Card_Account
acct_num_28_typ	Card_Account
acct_num_29	Card_Account
acct_num_29_descr	Card_Account
acct_num_29_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_29_stat	Card_Account
acct_num_29_typ	Card_Account
acct_num_2_descr	Card
	Card_Account
acct_num_2_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_2_stat	Card
	Card_Account
acct_num_2_typ	Card
	Card_Account
acct_num_3	Card
	Card_Account
acct_num_30	Card_Account
acct_num_30_descr	Card_Account
acct_num_30_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_30_stat	Card_Account
acct_num_30_typ	Card_Account
acct_num_31	Card_Account
acct_num_31_descr	Card_Account
acct_num_31_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_31_stat	Card_Account
acct_num_31_typ	Card_Account
acct_num_32	Card_Account
acct_num_32_descr	Card_Account
acct_num_32_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_32_stat	Card_Account
acct_num_32_typ	Card_Account
acct_num_33	Card_Account
acct_num_33_descr	Card_Account

acct_num_33_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_33_stat	Card_Account
acct_num_33_typ	Card_Account
acct_num_34	Card_Account
acct_num_34_descr	Card_Account
acct_num_34_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_34_stat	Card_Account
acct_num_34_typ	Card_Account
acct_num_35	Card_Account
acct_num_35_descr	Card_Account
acct_num_35_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_35_stat	Card_Account
acct_num_35_typ	Card_Account
acct_num_36	Card_Account
acct_num_36_descr	Card_Account
acct_num_36_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_36_stat	Card_Account
acct_num_36_typ	Card_Account
acct_num_37	Card_Account
acct_num_37_descr	Card_Account
acct_num_37_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_37_stat	Card_Account
acct_num_37_typ	Card_Account
acct_num_38	Card_Account
acct_num_38_descr	Card_Account
acct_num_38_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_38_stat	Card_Account
acct_num_38_typ	Card_Account
acct_num_39	Card_Account
acct_num_39_descr	Card_Account
acct_num_39_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_39_stat	Card_Account
acct_num_39_typ	Card_Account
acct_num_3_descr	Card
	Card_Account
acct_num_3_descr_mbyte	CARD_ACCOUNT_MBYTE

acct_num_3_stat	Card
	Card_Account
acct_num_3_typ	Card
	Card_Account
acct_num_4	Card
	Card_Account
acct_num_40	Card_Account
acct_num_40_descr	Card_Account
acct_num_40_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_40_stat	Card_Account
acct_num_40_typ	Card_Account
acct_num_41	Card_Account
acct_num_41_descr	Card_Account
acct_num_41_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_41_stat	Card_Account
acct_num_41_typ	Card_Account
acct_num_42	Card_Account
acct_num_42_descr	Card_Account
acct_num_42_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_42_stat	Card_Account
acct_num_42_typ	Card_Account
acct_num_43	Card_Account
acct_num_43_descr	Card_Account
acct_num_43_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_43_stat	Card_Account
acct_num_43_typ	Card_Account
acct_num_44	Card_Account
acct_num_44_descr	Card_Account
acct_num_44_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_44_stat	Card_Account
acct_num_44_typ	Card_Account
acct_num_45	Card_Account
acct_num_45_descr	Card_Account
acct_num_45_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_45_stat	Card_Account
acct_num_45_typ	Card_Account

List of data elements

acct_num_46	Card_Account
acct_num_46_descr	Card_Account
acct_num_46_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_46_stat	Card_Account
acct_num_46_typ	Card_Account
acct_num_47	Card_Account
acct_num_47_descr	Card_Account
acct_num_47_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_47_stat	Card_Account
acct_num_47_typ	Card_Account
acct_num_48	Card_Account
acct_num_48_descr	Card_Account
acct_num_48_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_48_stat	Card_Account
acct_num_48_typ	Card_Account
acct_num_49	Card_Account
acct_num_49_descr	Card_Account
acct_num_49_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_49_stat	Card_Account
acct_num_49_typ	Card_Account
acct_num_4_descr	Card
	Card_Account
acct_num_4_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_4_stat	Card
	Card_Account
acct_num_4_typ	Card
	Card_Account
acct_num_5	Card
	Card_Account
acct_num_50	Card_Account
acct_num_50_descr	Card_Account
acct_num_50_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_50_stat	Card_Account
acct_num_50_typ	Card_Account
acct_num_51	Card_Account
acct_num_51_descr	Card_Account

acct_num_51_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_51_stat	Card_Account
acct_num_51_typ	Card_Account
acct_num_52	Card_Account
acct_num_52_descr	Card_Account
acct_num_52_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_52_stat	Card_Account
acct_num_52_typ	Card_Account
acct_num_53	Card_Account
acct_num_53_descr	Card_Account
acct_num_53_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_53_stat	Card_Account
acct_num_53_typ	Card_Account
acct_num_54	Card_Account
acct_num_54_descr	Card_Account
acct_num_54_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_54_stat	Card_Account
acct_num_54_typ	Card_Account
acct_num_55	Card_Account
acct_num_55_descr	Card_Account
acct_num_55_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_55_stat	Card_Account
acct_num_55_typ	Card_Account
acct_num_56	Card_Account
acct_num_56_descr	Card_Account
acct_num_56_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_56_stat	Card_Account
acct_num_56_typ	Card_Account
acct_num_57	Card_Account
acct_num_57_descr	Card_Account
acct_num_57_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_57_stat	Card_Account
acct_num_57_typ	Card_Account
acct_num_58	Card_Account
acct_num_58_descr	Card_Account
acct_num_58_descr_mbyte	CARD_ACCOUNT_MBYTE

List of data elements

acct_num_58_stat	Card_Account
acct_num_58_typ	Card_Account
acct_num_59	Card_Account
acct_num_59_descr	Card_Account
acct_num_59_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_59_stat	Card_Account
acct_num_59_typ	Card_Account
acct_num_5_descr	Card
	Card_Account
acct_num_5_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_5_stat	Card
	Card_Account
acct_num_5_typ	Card
	Card_Account
acct_num_6	Card
	Card_Account
acct_num_60	Card_Account
acct_num_60_descr	Card_Account
acct_num_60_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_60_stat	Card_Account
acct_num_60_typ	Card_Account
acct_num_61	Card_Account
acct_num_61_descr	Card_Account
acct_num_61_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_61_stat	Card_Account
acct_num_61_typ	Card_Account
acct_num_62	Card_Account
acct_num_62_descr	Card_Account
acct_num_62_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_62_stat	Card_Account
acct_num_62_typ	Card_Account
acct_num_63	Card_Account
acct_num_63_descr	Card_Account
acct_num_63_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_63_stat	Card_Account
acct_num_63_typ	Card_Account

acct_num_64	Card_Account
acct_num_64_descr	Card_Account
acct_num_64_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_64_stat	Card_Account
acct_num_64_typ	Card_Account
acct_num_65	Card_Account
acct_num_65_descr	Card_Account
acct_num_65_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_65_stat	Card_Account
acct_num_65_typ	Card_Account
acct_num_66	Card_Account
acct_num_66_descr	Card_Account
acct_num_66_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_66_stat	Card_Account
acct_num_66_typ	Card_Account
acct_num_67	Card_Account
acct_num_67_descr	Card_Account
acct_num_67_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_67_stat	Card_Account
acct_num_67_typ	Card_Account
acct_num_68	Card_Account
acct_num_68_descr	Card_Account
acct_num_68_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_68_stat	Card_Account
acct_num_68_typ	Card_Account
acct_num_69	Card_Account
acct_num_69_descr	Card_Account
acct_num_69_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_69_stat	Card_Account
acct_num_69_typ	Card_Account
acct_num_6_descr	Card
	Card_Account
acct_num_6_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_6_stat	Card
	Card_Account
acct_num_6_typ	Card

	Card_Account
acct_num_7	Card
	Card_Account
acct_num_70	Card_Account
acct_num_70_descr	Card_Account
acct_num_70_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_70_stat	Card_Account
acct_num_70_typ	Card_Account
acct_num_71_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_72_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_73_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_74_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_75_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_76_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_77_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_78_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_79_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_7_descr	Card
	Card_Account
acct_num_7_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_7_stat	Card
	Card_Account
acct_num_7_typ	Card
	Card_Account
acct_num_8	Card
	Card_Account
acct_num_80_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_8_descr	Card
	Card_Account
acct_num_8_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_8_stat	Card
	Card_Account
acct_num_8_typ	Card
	Card_Account
acct_num_9	Card
	Card_Account

acct_num_9_descr	Card
	Card_Account
acct_num_9_descr_mbyte	CARD_ACCOUNT_MBYTE
acct_num_9_stat	Card
	Card_Account
acct_num_9_typ	Card
	Card_Account
acct_num_fld	dal_tbl
acct_num_ind	PRM_Interface
	PRM_Interface_OLTP
acct_num_ttl	Card
acct_stat	Acct_Status_Extrn_to_Intrn
	Acct_Status_Intrn_to_Extrn.xml
	Positive_Balance
acct_stat_chng_dat	Positive_Balance
acct_stat_extrn	Acct_Status_Extrn_to_Intrn.xml
	Acct_Status_Intrn_to_Extrn
acct_stat_extrn_descr	Acct_Status_Extrn_to_Intrn
	Acct_Status_Intrn_to_Extrn
acct_stat_prfl	Acct_Status_Extrn_to_Intrn.xml
	Acct_Status_Intrn_to_Extrn.xml
	HISO87_Interface
	HISO87_Interface_OLTP
acct_typ	Account_Routing.xml
	Account_Routing_OLTP.xml
	PBAL_Impacts.xml
	Positive_Balance.xml
	SPDH_ISO_Response_Code.xml
	SPDH_ISO_Response_Code_OLTP.xml
	Stop_Payment.xml
AcqRtPrflTx	ESATDS1
AcqTranCd	RCPTRQRD.xml
AcqTranPrflTx	ESATDS1
acq_bnk_id	CUP_Institution
	CUP_Institution_OLTP
	EFunds_Institution

	EFunds_Institution_OLTP
	Visa_Institution
	Visa_Institution_OLTP
acq_cat	Cardnet_Interface
	Cardnet_Interface_OLTP
acq_frwd_ovrrd_inst_id	BIC_Interface
	BIC_Interface_OLTP
acq_id_cde	BNFT_Interface
	BNFT_Interface_OLTP
	SPAN2_Interface
	SPAN2_Interface_OLTP
acq_init_hdr	Channel_Security
acq_init_kam	Channel_Security
acq_init_keyx	Channel_Security
acq_init_lgth	Channel_Security
acq_init_vvk	Channel_Security
acq_instrm_typ_rel_prfl	Acquirer_Instrument_Type_Rel.xml
	Acquirer_Instrum_Type_Rel_OLTP.xml
	Merchant
	Merchant_OLTP
acq_inst_id	Cardnet_Interface_Terminal.xml
	Cardnet_Interface_Terminal_OLTP.xml
	Interface_Terminal.xml
	Interface_Terminal_OLTP.xml
	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	SPAN2_Interface_Terminal.xml
	SPAN2_Interface_Terminal_OLTP.xml
acq_lmt_prfl	Acquirer_Instrument_Type_Rel
	Acquirer_Instrum_Type_Rel_OLTP
	Merchant
	Merchant_OLTP
acq_logon_st	Interface_Manager
	Interface_Station
acq_msg_sec_cde	FIS_Interface

	FIS_Interface_OLTP
acq_nde_id	Interac_Admin
acq_ovrrd_inst_id_flg	BIC_Interface
	BIC_Interface_OLTP
acq_reimb_attr1	Pulse_Interface
	Pulse_Interface_OLTP
	Star_Interface
	Star_Interface_OLTP
acq_reimb_attr2	Pulse_Interface
	Pulse_Interface_OLTP
	Star_Interface
	Star_Interface_OLTP
acq_rte_prfl	Acquirer_Issuer_Relation.xml
	Acquirer_Issuer_Relation_OLTP.xml
	Acquirer_Route_Profile.xml
	ATM_DS1
	ATM_DS1_OLTP
	File_Update_Route.xml
	File_Update_Route_OLTP.xml
	Interface
	Interface_Acquirer_OLTP
	Merchant
	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	Merchant_OLTP
	System_Prefix.xml
	System_Prefix_OLTP.xml
acq_seq_gen_num	GICC_Acq_SGN
acq_spnsr_bnk_id	Discover_Institution
	Discover_Institution_OLTP
	EFunds_Interface
	EFunds_Interface_OLTP
	JCB_Institution
	JCB_Institution_OLTP
	NYCE_Institution

	NYCE_Institution_OLTP
	Pulse_Interface
	Pulse_Interface_OLTP
	Star_Institution
	Star_Institution_OLTP
	Star_Interface
	Star_Interface_OLTP
	Visa_DPS_Institution
	Visa_DPS_Institution_OLTP
acq_stand_in_for_conetwork	BIC_Interface
	BIC_Interface_OLTP
acq_surch_prfl	Interface
	Interface_Acquirer_OLTP
	Surcharge.xml
	Surcharge_OLTP.xml
acq_timr_id	Interface_Manager
	Interface_Station
acq_timr_typ	Interface_Manager
	Interface_Station
acq_tran_prfl	ATM_DS1
	ATM_DS1_OLTP
acq_txn_prfl	Acquirer_Instrument_Type_Rel
	Acquirer_Instrum_Type_Rel_OLTP
	Acquirer_Txn_Allowed.xml
	Acquirer_Txn_Allowed_OLTP.xml
	Interface
	Interface_Acquirer_OLTP
	Merchant
	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	Merchant_OLTP
Active	Filters
	Roles
ActivityID	AudDtIPK.xml
	AuditDtl.xml

	AuditTbl.xml
	SrchXAdt.xml
ActivityTS	AudDtlPK.xml
	AuditDtl.xml
	AuditTbl.xml
	SrchXAdt.xml
ActivityType	ActFunc
ActnCodPrflTx	ESATDS1
act_cde	Action_Code_Extrn_to_Intrn
	Action_Code_Extrn_to_Intrn_OLTP
	Action_Code_Intrn_to_Extrn.xml
	Action_Code_Intrn_to_Extrn_OLTP.xml
	EMV_Card_Vrfn_Results_OLTP
	EMV_Card_Vrfn_Results_Order_OLTP
	EMV_Card_Vrfn_Results_Status
	EMV_Iss_Auth_Dta.xml
	EMV_Iss_Auth_Dta_OLTP.xml
	EMV_Reason_Online_Code_OLTP
	EMV_Reason_Online_Code_Status
	EMV_Terminal_Vrfn_Results_Status
	EMV_Term_Vrfn_Results_OLTP
	EMV_Term_Vrfn_Results_Order_OLTP
	IFX_Host_Action_Code_Int_Ext.xml
	IFX_Host_Action_Cod_Int_Ext_OLTP.xml
act_cde_descr	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
act_cde_extrn	Action_Code_Extrn_to_Intrn.xml
	Action_Code_Extrn_to_Intrn_OLTP.xml
	Action_Code_Intrn_to_Extrn
	Action_Code_Intrn_to_Extrn_OLTP
	SPDH_act_cde_descr.xml
	SPDH_act_cde_descr_OLTP.xml
	SPDH_opt_resp_data.xml
	SPDH_opt_resp_data_OLTP.xml
act_cde_extrn_descr	Action_Code_Extrn_to_Intrn
	Action_Code_Intrn_to_Extrn

	SPDH_act_cde_descr
	SPDH_act_cde_descr_OLTP
act_cde_extrn_descr_mbyte	Action_Code_Extrn_to_Intrn
	Action_Code_Intrn_to_Extrn
act_cde_prfl	Action_Code_Extrn_to_Intrn.xml
	Action_Code_Extrn_to_Intrn_OLTP.xml
	Action_Code_Intrn_to_Extrn.xml
	Action_Code_Intrn_to_Extrn_OLTP.xml
	ATM_DS1
	ATM_DS1_OLTP
	GISO_IN_MSG_DEF
	GISO_IN_MSG_DEF_OLTP
	GISO_OUT_MSG_DEF
	GISO_OUT_MSG_DEF_OLTP
	IFX_Host_Action_Code_Int_Ext.xml
	IFX_Host_Action_Cod_Int_Ext_OLTP.xml
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
AddrTx	HSMCNFG
addr_1	Card
	Institution
	Merchant
	Merchant_Delivery_Channel
	Merchant_OLTP
addr_1_mbyte	CARD_ACCOUNT_MBYTE
	Institution
	Merchant
	Merchant_Delivery_Channel
addr_2	Card
	Institution
	Merchant

	Merchant_Delivery_Channel
	Merchant_OLTP
addr_2_mbyte	CARD_ACCOUNT_MBYTE
	Institution
	Merchant
	Merchant_Delivery_Channel
AdjmntAmtNum	CTVRSAF
AdjmntHpprCntnNum	CTVRSAF
AdjmntHpprNum	CTVRSAF
adj_amt	Merchant_Delivery_Channel
adj_cnt	Merchant_Delivery_Channel
adj_lmt_amt	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
adj_lmt_cnt	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
adj_thrhd_act	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
AdminCdeTx	CTVRSAF
AdminCrdMbrNum	CTVRSAF
AdminCrdNumTx	CTVRSAF
AdminDt	CTVRSAF
AdminTm	CTVRSAF
admin_crd_req	Acquirer_Txn_Allowed
	Acquirer_Txn_Allowed_OLTP
admin_free_txt	Interac_Admin
admin_free_txt_lgth	Interac_Admin
admin_msg_subtyp	Interac_Admin
AdmnPhnCnctTx	ESATDS1
adm_n_phone_num	ATM_PRFL
	ATM_PRFL_OLTP
adnl_nam	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
AFID	ActFunc.xml

AfterValue	AuditTbl
agency_mbr_acct	AuditDtl
agency_mbr_sort	FPS_Payment_Submission
age_fld	FPS_Payment_Submission
ail_id	dal_tbl
	Interac_Base
	Interac_Base_OLTP
	Interac_Entry_Point
ail_pid	Interac_Entry_Point
akds_cap_ind	ATM_DS1
	ATM_DS1_OLTP
algo_nam	System_Algorithm_Config.xml
	System_Algorithm_Config_OLTP.xml
algo_typ	Prefix
	Prefix_OLTP
alias	User_Perusal_Prfl_Relation.xml
	User_Perusal_Prfl_Relation_OLTP.xml
allow_alt_flr_lmt_chk	Route
	Route_OLTP
all_key_cmd_flg	Interface_Manager
AltrRtTrnsNmbrTx	ATDCNFG
alt_acq_inst_id	Merch_Instr_Type_Relation_OLTP
	Merch_Instr_Typ_Relation
alt_flr_lmt_algo	Route
	Route_OLTP
alt_route_num	ATM_PRFL
	ATM_PRFL_OLTP
AmntOfChckNum	CTVRSF
	ESAPDT
	ESATDD1
AmntOfCmrcDpstNum	CTVRSF
	ESAPDT
	ESATDD1
AmntOfCshDpstNum	ESAPDT
	ESATDD1
AmntOfDpstNum	CTVRSF

AmntOfEnvlDpstNum	ESAPDT ESATDD1
AmntOfPhCPrchNum	CTVRSAP ESAPDT ESATDD1
AmntOfPymnNum	CTVRSAP ESAPDT ESATDD1
AmntOfTopUpNum	CTVRSAP ESAPDT ESATDD1
AmntSmrtCrdLdsNum	CTVRSAP ESAPDT ESATDD1
amt	Interac_Admin Stop_Payment
amt_fee	Fees Fees_OLTP
amt_orig	FPS_Payment_Submission
amt_prev	GICC_Channel
amt_txn	FPS_Payment_Submission
apacs_hld_flg	APACS_Configuration APACS_Configuration_OLTP
apacs_hld_intrvl	APACS_Configuration APACS_Configuration_OLTP
apacs_hld_timr	APACS_Configuration APACS_Configuration_OLTP
apms_ref_num	EMV_Script_Context
append_flg	Journal_Query_Config_Output
ApplBundleNamTx	WEBAPPS
ApplDfnd	USRAULOG
ApplID	APPLDSRC.xml PROCESS VERSIONS.xml WEBAPPOPTS.xml WEBAPPS.xml

ApplNamTx	WEBUSROPTS.xml
appl_ichg_prfl	WEBAPPS
	Chip_Authentication
	Chip_Authentication_OLTP
appl_txn_cntr_resync	Chip_Authentication
	Chip_Authentication_OLTP
apprv_cde_lgth	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
apprv_thrhd_lmt	Authorization_Script
	Authorization_Script_OLTP
app_id_cde	PRICE_Interface
	PRICE_Interface_OLTP
AqurTrnsPrflTx	APCF.xml
	IDF
ArchiveTS	PswdHist.xml
asgn_nam	DS_OLTP_Relation.xml
	file_part_catalog.xml
	file_part_fields.xml
	file_part_fields_OLTP.xml
	file_part_list.xml
	file_part_list_OLTP.xml
	Journal_Prfl_Group_Assign_OLTP
	Journal_Profile_Group_Assign
	Journal_Query_Output_Assign
	OLTP_Warmboot.xml
asgn_nam_data	Trace_Config
	file_part_list
	file_part_list_OLTP
asgn_nam_oltp	DS_OLTP_Relation.xml
asgn_nam_root	file_part_catalog
asgn_nam_suffix	file_part_catalog
atc_bad_disp	Prefix
	Prefix_OLTP
atc_chk_typ	Prefix

	Prefix_OLTP
atc_pre_scrn	Prefix
	Prefix_OLTP
atc_reset	Card
atc_reset_chng_dat	Card
atmdd2_rec_typ	ATM_DD2.xml
ATMECrtSecObjIdTx	IFXDATA
ATMEKeySecObjIdTx	IFXDATA
atmflw_cond_stat	ATM_FLOW_CNTL.xml
	ATM_FLOW_CNTL_OLTP.xml
atmflw_seq_cntl	ATM_DD1
	ATM_FLOW_CNTL.xml
	ATM_FLOW_CNTL_OLTP.xml
atmflw_svc	ATM_FLOW_CNTL.xml
	ATM_FLOW_CNTL_OLTP.xml
atmflw_svc_buf	ATM_FLOW_CNTL
	ATM_FLOW_CNTL_OLTP
atmflw_svc_cnt	ATM_FLOW_CNTL
	ATM_FLOW_CNTL_OLTP
atmopcd_task_buf	ATM_OP_CDE
	ATM_OP_CDE_OLTP
atmopcd_task_cnt	ATM_OP_CDE
	ATM_OP_CDE_OLTP
AtmSegBalCutEndShort	IDF
AtmSegBalCutStrtShort	IDF
AtmSegCurBusDatTx	IDF
AtmSegCusBusDatTx	IDF
AtmSegCustBalDspyCd	IDF
AtmSegCustBalInfoCd	IDF
AtmSegDepSetImpCd	IDF
AtmSegFastCashAcctCd	IDF
AtmSegHostB24BalCd	IDF
AtmSegHostLogCd	IDF
AtmSegIssTxnPrfITx	IDF
AtmSegLogRteCdeShort	IDF
AtmSegNxtBusDatTx	IDF

AtmSegPinChngOptCd	IDF
AtmSegRptBusDatTx	IDF
AtmSegRtTbl1AcctTypTx	IDF
AtmSegRtTbl1AuthLvITx	IDF
AtmSegRtTbl1AuthTypTx	IDF
AtmSegRtTbl1PrfxRteTx	IDF
AtmSegRtTbl1PriDPCShort	IDF
AtmSegRtTbl1SymNameTx	IDF
AtmSegRtTbl1UsrFld4Tx	IDF
AtmSegRtTbl2AcctTypTx	IDF
AtmSegRtTbl2AuthLvITx	IDF
AtmSegRtTbl2AuthTypTx	IDF
AtmSegRtTbl2PrfxRteTx	IDF
AtmSegRtTbl2PriDPCShort	IDF
AtmSegRtTbl2SymNameTx	IDF
AtmSegRtTbl2UsrFld4Tx	IDF
AtmSegRtTbl3AcctTypTx	IDF
AtmSegRtTbl3AuthLvITx	IDF
AtmSegRtTbl3AuthTypTx	IDF
AtmSegRtTbl3PrfxRteTx	IDF
AtmSegRtTbl3PriDPCShort	IDF
AtmSegRtTbl3SymNameTx	IDF
AtmSegRtTbl3UsrFld4Tx	IDF
AtmSegRtTbl4AcctTypTx	IDF
AtmSegRtTbl4AuthLvITx	IDF
AtmSegRtTbl4AuthTypTx	IDF
AtmSegRtTbl4PrfxRteTx	IDF
AtmSegRtTbl4PriDPCShort	IDF
AtmSegRtTbl4SymNameTx	IDF
AtmSegRtTbl4UsrFld4Tx	IDF
AtmSegRtTbl5AcctTypTx	IDF
AtmSegRtTbl5AuthLvITx	IDF
AtmSegRtTbl5AuthTypTx	IDF
AtmSegRtTbl5PrfxRteTx	IDF
AtmSegRtTbl5PriDPCShort	IDF
AtmSegRtTbl5SymNameTx	IDF

AtmSegRtTbl5UsrFld4Tx	IDF
AtmSegSegDataB24Int	IDF
AtmSegSegDataIdShort	IDF
AtmSegSegLgthShort	IDF
AtmSegStmntPrntOnInCd	IDF
AtmSegTermBalFlgCd	IDF
AtmSegTknRetrvOptCd	IDF
AtmSegUserFld3bTx	IDF
AtmSegUserFld3dTx	IDF
AtmSegUserFld5Tx	IDF
ATMSrINSecObjIdTx	IFXDATA
ATMVCrtSecObjIdTx	IFXDATA
atm_abi_frwd_inst_id	ABI_Interface
	ABI_Interface_OLTP
atm_acq_surch_prfl	HISO87_Interface
	HISO87_Interface_OLTP
atm_act_cde	ATM_STATE_SCRN.xml
	ATM_STATE_SCRN_OLTP.xml
atm_act_cde_prfl	HISO87_Interface
	HISO87_Interface_OLTP
atm_bal_flg	Institution
	Institution_OLTP
atm_char_set	ATM_DS1
	ATM_DS1_OLTP
atm_char_set_bytes	ATM_MBYTE_XLATE
	ATM_MBYTE_XLATE_OLTP
atm_co_owned	ATM_DS1
	ATM_DS1_OLTP
atm_emv_prfl	ATM_DS1
	ATM_DS1_OLTP
	ATM_EMV.xml
	ATM_EMV_OLTP.xml
atm_force_bal_flg	Institution
	Institution_OLTP
atm_ind	Circuit_Interface
	Circuit_Interface_OLTP

atm_last_swi_setl_dat	SPAN2_Interface
atm_mac_prfl	ATM_DS1
	ATM_DS1_OLTP
	ATM_MAC.xml
	ATM_MAC_OLTP.xml
atm_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
atm_max_coins	ATM_HOPR
	ATM_HOPR_OLTP
atm_media_text	ATM_CONSUMER_MEDIA
	ATM_CONSUMER_MEDIA_OLTP
atm_media_text_key	ATM_CONSUMER_MEDIA.xml
	ATM_CONSUMER_MEDIA_OLTP.xml
atm_msg_prfl	HISO87_Interface
	HISO87_Interface_OLTP
atm_oar_ind	ATM_PRFL
	ATM_PRFL_OLTP
atm_peak_load_prfl	ATM_DD1
	ATM_PEAK_LOAD.xml
	ATM_PEAK_LOAD_OLTP.xml
atm_prev_ttl_flg	ATM_DS1
	ATM_DS1_OLTP
atm_proc_cde_prfl	HISO87_Interface
	HISO87_Interface_OLTP
atm_rcv_inst_id	ABI_Interface
	ABI_Interface_OLTP
atm_seq_num	ATM_DD1
	ATM_STMNT_DATA.xml
atm_slow_resp_to_congest	Interac_Base
	Interac_Base_OLTP
atm_slow_txn_cnt	Interac_Base
atm_social_deprivation	ATM_DS1
	ATM_DS1_OLTP
atm_ssb	ABI_Interface
	ABI_Interface_OLTP
atm_sur_prfl	ATM_DS1

	ATM_DS1_OLTP
	ATM_SUR.xml
	ATM_SUR_OLTP.xml
atm_timeouts_to_block	Interac_Base
	Interac_Base_OLTP
atm_timeout_txn_cnt	Interac_Base
atm_tkn_prfl	HISO87_Interface
	HISO87_Interface_OLTP
atm_tm_ofst	ATM_DS1
	ATM_DS1_OLTP
atm_txn_cde	ATM_TC_Proc_Code.xml
	ATM-Tran_Code_Proc_Code_OLTP.xml
	Proc_Code_ATM_TC
	Proc_Code_ATM-Tran_Code_OLTP
AttmptCnt	CACNFSAF
	RVSLSAF
attr_descr	Environment
attr_nam	Environment.xml
attr_nam_long	Environment
attr_val	Environment
AudtContFlg	USRAULOG
AudtEntryDetl	USRAULOG
AudtEntryID	USRAULOG.xml
AudtEntrySeqNum	USRAULOG.xml
AudtEntryTm	USRAULOG.xml
AudtEntryTyp	USRAULOG
AudtSeqNum	USRAULOG.xml
AuthDestTx	APCF
AuthMsgTypTx	ESATDD1
AuthorizationID	Ticket.xml
AuthPrcCdeTx	ESATDD1
AuthPrCsNameTx	CMPTPRFL
AuthRspnCdeTx	ESATDD1
AuthSqncNmbrTx	ESATDD1
auth_cntr_id	Cardnet_Interface
	Cardnet_Interface_OLTP

auth_msg_rsn_cde	AMEX_CAPN_Interface
	AMEX_CAPN_Interface_OLTP
auth_msg_typ	Instrum_Typ_Interchange_Rel
	Instrum_Typ_Interchange_Rel_OLTP
auth_nam	Active_Script_Statistics.xml
	Authorization_Script.xml
	Authorization_Script_OLTP.xml
auto_logon_flg	Interface_Manager
avail_bal_strt	Positive_Balance
avail_bal_strt_dat	Positive_Balance
avail_cr_strt	Positive_Balance
avail_cr_strt_dat	Positive_Balance
avail_dep_typ	ATM_PRFL
	ATM_PRFL_OLTP
avg_dst_to_moon_fld	dal_tbl
avg_dst_to_sun_fld	dal_tbl
AvlbDpstTypCd	ATDCNFG
avs_chk	Card
avs_logon_typ	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
	EPSNET_Interface
	EPSNET_Interface_OLTP
b24_ansi_pan	BASE24_KEYF
b24_encrypt_typ_msg	BASE24_KEYF
b24_exchnng_key	BASE24_KEYF
b24_exchnng_key_extnd	BASE24_KEYF
b24_exchnng_key_vvk	BASE24_KEYF
b24_ext_encrypt_typ	BASE24_KEYF
b24_fiid	BASE24_KEYF.xml
b24_fm_sta_num	BASE24_KEYF
b24_fm_ts_1	BASE24_KEYF
b24_fm_ts_2	BASE24_KEYF
b24_fm_ts_3	BASE24_KEYF
b24_fm_updt_typ	BASE24_KEYF

b24_fm_user_fld	BASE24_KEYF
b24_fm_user_grp	BASE24_KEYF
b24_fm_user_num	BASE24_KEYF
b24_full_encrypt	BASE24_KEYF
b24_full_msg_mac	BASE24_KEYF
b24_interm_key_clear	BASE24_KEYF
b24_interm_key_encrypt	BASE24_KEYF
b24_interm_key_vvk	BASE24_KEYF
b24_int_encrypt_typ	BASE24_KEYF
b24_in_kme_cur_idx	BASE24_KEYF
b24_in_kme_key_cntr_1	BASE24_KEYF
b24_in_kme_key_cntr_2	BASE24_KEYF
b24_in_mac_cur_idx	BASE24_KEYF
b24_in_mac_key_1	BASE24_KEYF
b24_in_mac_key_2	BASE24_KEYF
b24_in_mac_key_cntr	BASE24_KEYF
b24_in_mac_key_cntr_1	BASE24_KEYF
b24_in_mac_key_cntr_2	BASE24_KEYF
b24_in_mac_vvk_1	BASE24_KEYF
b24_in_mac_vvk_2	BASE24_KEYF
b24_in_msg_key_cntr	BASE24_KEYF
b24_in_pin_cur_idx	BASE24_KEYF
b24_in_pin_key_1	BASE24_KEYF
b24_in_pin_key_2	BASE24_KEYF
b24_in_pin_key_cntr	BASE24_KEYF
b24_in_pin_key_cntr_1	BASE24_KEYF
b24_in_pin_key_cntr_2	BASE24_KEYF
b24_in_pin_vvk_1	BASE24_KEYF
b24_in_pin_vvk_2	BASE24_KEYF
b24_kek_seq_num_in	BASE24_KEYF
b24_kek_seq_num_out	BASE24_KEYF
b24_key_lgth	BASE24_KEYF
b24_key_proc_typ	BASE24_KEYF
b24_kmac_sync_err_lmt	BASE24_KEYF
b24_last_txn_id	BASE24_KEYF
b24_last_txn_pro_num	BASE24_KEYF

b24_last_txn_ts_1	BASE24_KEYF
b24_last_txn_ts_2	BASE24_KEYF
b24_last_txn_ts_3	BASE24_KEYF
b24_mac_data_typ	BASE24_KEYF
b24_mac_err_lmt	BASE24_KEYF
b24_mac_exchng_key	BASE24_KEYF
b24_mac_exchng_key_extnd	BASE24_KEYF
b24_mac_exchng_key_vvk	BASE24_KEYF
b24_mac_typ	BASE24_KEYF
b24_migr_flg	HISO87_Interface
	HISO87_Interface_OLTP
b24_msg_cnsc_err_lmt	BASE24_KEYF
b24_msg_err_lmt	BASE24_KEYF
b24_msg_key_timr_lmt	BASE24_KEYF
b24_msg_key_txn_lmt	BASE24_KEYF
b24_msg_vvk	BASE24_KEYF
b24_notarize_flg	BASE24_KEYF
b24_num_keys	BASE24_KEYF
b24_org_id	BASE24_KEYF
b24_out_kme_cur_indx	BASE24_KEYF
b24_out_kme_key_cntr_1	BASE24_KEYF
b24_out_kme_key_cntr_2	BASE24_KEYF
b24_out_mac_cur_indx	BASE24_KEYF
b24_out_mac_key_1	BASE24_KEYF
b24_out_mac_key_2	BASE24_KEYF
b24_out_mac_key_cntr	BASE24_KEYF
b24_out_mac_key_cntr_1	BASE24_KEYF
b24_out_mac_key_cntr_2	BASE24_KEYF
b24_out_mac_vvk_1	BASE24_KEYF
b24_out_mac_vvk_2	BASE24_KEYF
b24_out_msg_key_cntr	BASE24_KEYF
b24_out_pin_cur_indx	BASE24_KEYF
b24_out_pin_key_1	BASE24_KEYF
b24_out_pin_key_2	BASE24_KEYF
b24_out_pin_key_cntr	BASE24_KEYF
b24_out_pin_key_cntr_1	BASE24_KEYF

b24_out_pin_key_cntr_2	BASE24_KEYF
b24_out_pin_vvk_1	BASE24_KEYF
b24_out_pin_vvk_2	BASE24_KEYF
b24_pin_blk	BASE24_KEYF
b24_pin_err_lmt	BASE24_KEYF
b24_rcv_id	BASE24_KEYF
b24_rec_typ	BASE24_KEYF.xml
b24_user_fld10	BASE24_KEYF
b24_user_fld11	BASE24_KEYF
b24_user_fld4	BASE24_KEYF
b24_user_fld5	BASE24_KEYF
b24_user_fld6	BASE24_KEYF
b24_user_fld7	BASE24_KEYF
b24_user_fld8a	BASE24_KEYF
b24_user_fld8b	BASE24_KEYF
b24_user_fld8c	BASE24_KEYF
b24_user_fld9a	BASE24_KEYF
BadLoginTries	Users
BadLognAtmptRstTm	SecGrp
bad_cam_act_reliable	Prefix
	Prefix_OLTP
bad_cam_act_unreliable	Prefix
	Prefix_OLTP
bad_pin_disp	Prefix
	Prefix_OLTP
bad_pin_try	Admin_Card
balance_ind	ATM_DD1
bal_amt	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
bal_fld	dal_tbl
bal_opt_info	Interface
	Interface_Acquirer_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
bal_returned	Chan_Profile_Instrm_Typ_Relation
	Chan_Profile_Instrm_Typ_Rel_OLTP

bal_strt_tim	Institution
	Institution_OLTP
	Merchant
	Merchant_OLTP
bal_support	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
bal_usg_retn_prd	Institution
	Institution_OLTP
base1_atm_msg_prfl	Visa_Interface
	Visa_Interface_OLTP
base1_pos_msg_prfl	Visa_Interface
	Visa_Interface_OLTP
BaseSegAlgoNumTx	IDF
BaseSegAltkeyTx	IDF
BaseSegAltPBF4NameTx	IDF
BaseSegBadPinDispTx	IDF
BaseSegBegDatTx	IDF
BaseSegCAFNameTx	IDF
BaseSegCrdHldSelctTx	IDF
BaseSegCrdStatChkTx	IDF
BaseSegCrncyCdeTx	IDF
BaseSegExpChkDispTx	IDF
BaseSegExpDatChkTx	IDF
BaseSegFiCntryTx	IDF
BaseSegFiCntyTx	IDF
BaseSegFIIDMapExt	IDF
BaseSegFIIDSegMapInt	IDF
BaseSegFIIDTx	IDF.xml
BaseSegFiNameTx	IDF
BaseSegFiPhoneTx	IDF
BaseSegFiStTx	IDF
BaseSegFldCutoverTx	IDF
BaseSegFmFill1Tx	IDF
BaseSegFmTs	IDF

BaseSegFmUserGrpShort	IDF
BaseSegFmUserNumInt	IDF
BaseSegHol10Tx	IDF
BaseSegHol11Tx	IDF
BaseSegHol12Tx	IDF
BaseSegHol13Tx	IDF
BaseSegHol14Tx	IDF
BaseSegHol15Tx	IDF
BaseSegHol16Tx	IDF
BaseSegHol17Tx	IDF
BaseSegHol18Tx	IDF
BaseSegHol19Tx	IDF
BaseSegHol1Tx	IDF
BaseSegHol20Tx	IDF
BaseSegHol2Tx	IDF
BaseSegHol3Tx	IDF
BaseSegHol4Tx	IDF
BaseSegHol5Tx	IDF
BaseSegHol6Tx	IDF
BaseSegHol7Tx	IDF
BaseSegHol8Tx	IDF
BaseSegHol9Tx	IDF
BaseSegHostAdjTx	IDF
BaseSegLgthShort	IDF
BaseSegLmtChkTx	IDF
BaseSegMapInt	IDF
BaseSegMaxPinTryShort	IDF
BaseSegNEGNameTx	IDF
BaseSegNxtBegDatTx	IDF
BaseSegOtherAcctTypCd	IDF
BaseSegPBF1NameTx	IDF
BaseSegPBF2NameTx	IDF
BaseSegPBF3NameTx	IDF
BaseSegPBF4NameTx	IDF
BaseSegPersistentUAFCd	IDF
BaseSegPinChkTx	IDF

BaseSegPinOfstTx	IDF
BaseSegPinTriesTx	IDF
BaseSegPinVrfyTypTx	IDF
BaseSegPrdLgthShort	IDF
BaseSegProNumShort	IDF
BaseSegRefrGrpTx	IDF
BaseSegRefrIndCAF1Cd	IDF
BaseSegRefrIndPBF1Cd	IDF
BaseSegRefrIndPBF2Cd	IDF
BaseSegRefrIndPBF3Cd	IDF
BaseSegRefrIndPBF4Cd	IDF
BaseSegShrgGrpTx	IDF
BaseSegSPFNameTx	IDF
BaseSegStaNumTx	IDF
BaseSegTrnNonstpShort	IDF
BaseSegTrnTs	IDF
BaseSegUAFNameTx	IDF
BaseSegUpdtTypCd	IDF
BaseSegUserFld1Tx	IDF
BaseSegUserFld3cTx	IDF
BaseSegUserFld3Tx	IDF
BaseSegUserFldACITx	IDF
BaseSegUserFldCustTx	IDF
BaseSegUserFldRegnTx	IDF
BaseSegWrkDayTx	IDF
base_crncy_cde	Currency_Conversion_Rate.xml
	Currency_Conversion_Rate_OLTP.xml
	Institution
	Institution_OLTP
BeforeValue	AuditDtl
BeginValue	Filters
beg_dat	Card_Verification.xml
	Card_Verification_OLTP
	Chip_Authentication.xml
	Chip_Authentication_OLTP
	Diebold_Number_Table.xml

	Diebold_Number_Table_OLTP
	Dual_PIN_Verification.xml
	Dual_PIN_Verification_OLTP
	Dynamic_Card_Verification.xml
	Dynamic_Card_Verification_OLTP
	EMV_Security.xml
	EMV_Security_OLTP
	IBM_DES.xml
	IBM_DES_OLTP
	Identikey.xml
	Identikey_OLTP
	Visa_PVV.xml
	Visa_PVV_OLTP
bhvr_score	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
bic	Ind_Sort_Code_Bic_OLTP.xml
	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
billing_info	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
BillPay_Data	BPDATA
BillPay_FullFlag	BPDATA
BillPay_Row	BPDATA.xml
blk_cde	Card_Block
	Card_Block_OLTP
	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
	Prefix_Block
	Prefix_Block_OLTP
BlncIndCd	ESATDD1
blob_fld	dal_tbl
blw_thrhld_chk_dep_bin	ATM_SSB_BIN
	ATM_SSB_BIN_OLTP
blz_id	ZKA_KGK.xml

List of data elements

BMCd1MaxBlNum	HPRPRFL
BMCd1NValNum	HPRPRFL
BMCd1StpAmntNum	HPRPRFL
BMCd1StrtAmntNum	HPRPRFL
BMCd2MaxBlNum	HPRPRFL
BMCd2NValNum	HPRPRFL
BMCd2StpAmntNum	HPRPRFL
BMCd2StrtAmntNum	HPRPRFL
BMCd3MaxBlNum	HPRPRFL
BMCd3NValNum	HPRPRFL
BMCd3StpAmntNum	HPRPRFL
BMCd3StrtAmntNum	HPRPRFL
BMCd4MaxBlNum	HPRPRFL
BMCd4NValNum	HPRPRFL
BMCd4StpAmntNum	HPRPRFL
BMCd4StrtAmntNum	HPRPRFL
BMCd5MaxBlNum	HPRPRFL
BMCd5NValNum	HPRPRFL
BMCd5StpAmntNum	HPRPRFL
BMCd5StrtAmntNum	HPRPRFL
BMCd6MaxBlNum	HPRPRFL
BMCd6NValNum	HPRPRFL
BMCd6StpAmntNum	HPRPRFL
BMCd6StrtAmntNum	HPRPRFL
BMCd7MaxBlNum	HPRPRFL
BMCd7NValNum	HPRPRFL
BMCd7StpAmntNum	HPRPRFL
BMCd7StrtAmntNum	HPRPRFL
BMCd8MaxBlNum	HPRPRFL
BMCd8NValNum	HPRPRFL
BMCd8StpAmntNum	HPRPRFL
BMCd8StrtAmntNum	HPRPRFL
bnat_stat_data	ATM_SSB_BNA
bnf_acct	FPS_Payment_Submission
bnf_acct_addr	FPS_Payment_Submission
bnf_acct_nam	FPS_Payment_Submission

bnf_cr_inst	FPS_Payment_Submission
bnk_id	Identikey
	Identikey_OLTP
bntng_decrypt_key_id	BNTng_Header
	BNTng_Header_OLTP
bntng_encrypt_mthd	BNTng_Header
	BNTng_Header_OLTP
bntng_exch_key_id	BNTng_Header
	BNTng_Header_OLTP
bntng_hdr_key	BNTng_Header.xml
	BNTng_Header_OLTP.xml
bntng_init_data	BNTng_Init_Data
bntng_init_data_id	BNTng_Init_Data.xml
bntng_key_id_typ	BNTng_Header
	BNTng_Header_OLTP
bntng_key_usage	BNTng_Header
	BNTng_Header_OLTP
brand_id	MDS_Brand_Rel.xml
	MDS_Brand_Rel_OLTP.xml
	Visa_Brand_Rel.xml
	Visa_Brand_Rel_OLTP.xml
brch_cde	BLZ_Map.xml
	BLZ_Map2_OLTP
	BLZ_Map_OLTP.xml
brch_hght	EMV_Security
	EMV_Security_OLTP
btch_adj_amt	Merchant_Delivery_Channel
btch_adj_cnt	Merchant_Delivery_Channel
btch_auth_ctx_key	Batch_Auth_Posn.xml
btch_auth_nam	Batch_Auth_Config.xml
	Batch_Auth_Config_OLTP.xml
btch_cr_amt	Merchant_Delivery_Channel
btch_cr_cnt	Merchant_Delivery_Channel
btch_ctx_buf	FPS_Batch_Control
btch_db_amt	Merchant_Delivery_Channel
btch_db_cnt	Merchant_Delivery_Channel

btch_dc_adj_amt	Merchant_Delivery_Channel
btch_dc_adj_cnt	Merchant_Delivery_Channel
btch_dc_cr_amt	Merchant_Delivery_Channel
btch_dc_cr_cnt	Merchant_Delivery_Channel
btch_dc_db_amt	Merchant_Delivery_Channel
btch_dc_db_cnt	Merchant_Delivery_Channel
btch_delay_timr_lmt	Batch_Auth_Config
	Batch_Auth_Config_OLTP
btch_id	FPS_Batch_Control.xml
	FPS_Payment_Submission.xml
	Journal_Query_Config
btch_max_outstnd_lmt	Batch_Auth_Config
	Batch_Auth_Config_OLTP
btch_max_retries	Batch_Auth_Config
	Batch_Auth_Config_OLTP
btch_nam	FPS_Batch_Config.xml
	FPS_Batch_Config_OLTP.xml
btch_num	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant_Delivery_Channel
btch_stat	FPS_Batch_Control
btch_timr_lmt	Batch_Auth_Config
	Batch_Auth_Config_OLTP
btch_ts	FPS_Batch_Control
btch_ttl_supported	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
bus_descr	Acquirer_Route_Profile
	Issuer_Route_Profile
bus_lvl1	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant
	Merchant_OLTP

bus_lvl2	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant
	Merchant_OLTP
bus_lvl3	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant
	Merchant_OLTP
bus_lvl4	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant
	Merchant_OLTP
bus_lvl5	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant
	Merchant_OLTP
CACMsgBn	CACNFSAF
CADDataArea	CACNTX
CAdmnBlncStpCd	ESATDD1
cam_chk_pre_scrn	Prefix
	Prefix_OLTP
cam_chk_typ	Prefix
	Prefix_OLTP
captr_dat	Interac_Admin
	Merchant_Delivery_Channel
	Referral
	Referral_OLTP
captr_mde	Chan_Profile_Instrm_Typ_Relation
	Chan_Profile_Instrm_Typ_Rel_OLTP
captr_ref	GICC_Channel
cardnet_id_cde	Cardnet_ID_Code
	Cardnet_ID_Code_OLTP

List of data elements

cards_retain_cnt	ATM_DD1
	ATM_PREV_TTL
card_capture	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
cash_adv_amt	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
cash_adv_incr_amt	Positive_Balance
cash_adv_min	Positive_Balance
cash_deposit_amt	ATM_DD1
	ATM_PREV_TTL
cash_deposit_cnt	ATM_DD1
	ATM_PREV_TTL
CBInclIndCd	ESATDD1
CChkEscrFlagCd	ESATDD1
ccr_eff_dat_tim	Currency_Conversion_Rate.xml
	Currency_Conversion_Rate_OLTP
CCshEscrFlagCd	ESATDD1
ccti_id	GICC_Acq_SGN.xml
	GICC_Channel.xml
	GICC_Iss_SGN.xml
CDspnTypCd	ESATDD1
CDsTranFlagCd	ESATDD1
CEmvTranIndCd	ESATDD1
CertTypTx	CACNFSAF
	CACNTX
cert_common_nam	Host_Public_Key_Security
	Host_Public_Key_Security_Primary
cert_iss_info	Channel_Public_Key_Security
cert_org_nam	Host_Public_Key_Security
	Host_Public_Key_Security_Primary
cert_serial_num	Host_Public_Key_Security
	Host_Public_Key_Security_Primary
chan_cnfg_prfl	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	SPDH_act_cde_descr.xml
	SPDH_act_cde_descr_OLTP.xml

	SPDH_Configuration
	SPDH_Configuration_OLTP
	SPDH_ISO_Response_Code.xml
	SPDH_ISO_Response_Code_OLTP.xml
	SPDH_ISO_Response_Text.xml
	SPDH_ISO_Response_Text_OLTP.xml
	SPDH_Message.xml
	SPDH_Message_OLTP.xml
	SPDH_opt_resp_data.xml
	SPDH_opt_resp_data_OLTP.xml
	SPDH_txn_cde_descr.xml
	SPDH_txn_cde_descr_OLTP.xml
chan_cutover_typ	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
chan_data_lgth	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	SPDH_Configuration
	SPDH_Configuration_OLTP
chan_descr	Merchant_Delivery_Channel
chan_descr_mbyte	Merchant_Delivery_Channel
chan_dev_typ	Channel_Security
chan_dpnt_data	Merchant_Delivery_Channel
chan_id	Channel_Instrm_Type_Relation.xml
	Channel_Public_Key_Security.xml
	Channel_Security
	Channel_Security_Future.xml
	EPP_Serial_Number
	GICC_Channel.xml
	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant_Delivery_Channel.xml
chan_instrm_typ_rel_prfl	Channel_Instrument_Type_Rel.xml
	Channel_Instrum_Type_Rel_OLTP.xml

chan_lmt_prfl	Merchant_Delivery_Channel
	Channel_Instrument_Type_Rel
	Channel_Instrum_Type_Rel_OLTP
chan_nam	Merchant_Delivery_Channel
	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
chan_output_cap	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
chan_pin_entry	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
chan_prfl	Merchant_Delivery_Chan_Prfl_OLTP
	APACS_Configuration.xml
	APACS_Configuration_OLTP.xml
	AS2805_Config.xml
	AS2805_Config_OLTP.xml
	Chan_Profile_Instrm_Typ_Relation.xml
	Chan_Profile_Instrm_Typ_Rel_OLTP.xml
	HPDH_Configuration.xml
	HPDH_Configuration_OLTP.xml
	Merchant_Channel_Profile.xml
	Merchant_Channel_Profile_OLTP.xml
	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil.xml
	Merchant_Delivery_Chan_Prfl_OLTP.xml
	SPDH_Configuration.xml
chan_prfl_descr	SPDH_Configuration_OLTP.xml
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
chan_proc_mde	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
chan_proto	SPDH_Configuration
	SPDH_Configuration_OLTP
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP

	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
chan_resp_ttls	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	SPDH_Configuration
	SPDH_Configuration_OLTP
chan_stat	Merchant_Delivery_Channel
chan_typ	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
char_set	Journal_Query_Config_Output
char_set_designator	ATM_MBYTE_XLATE
	ATM_MBYTE_XLATE_OLTP
checks_amt	ATM_DD1
	ATM_PREV_TTL
checks_cnt	ATM_DD1
	ATM_PREV_TTL
chip_auth_appl	Chip_Authentication
	Chip_Authentication_OLTP
chip_auth_prfl	Chip_Authentication.xml
	Chip_Authentication_OLTP.xml
chk_acct_num	Check_Status.xml
chk_amt	ATM_SSB_CPL
chk_amt_cur_cde	ATM_SSB_CPL
chk_amt_lmt	Check_Status
chk_amt_lmt_crncy_cde	Check_Status
chk_base_flg	Card
	Prefix
	Prefix_OLTP
chk_dgt	TBP_Daily
chk_micr_data	ATM_SSB_CPL.xml
chk_ret_flg	Check_Status
chk_stat	ATM_SSB_CPL
	Check_Status
chk_stat_chk_base_flg	Card
	Prefix

	Prefix_OLTP
chk_stat_pre_scrn	Prefix
	Prefix_OLTP
chk_typ	Check_Type.xml
	Check_Type_OLTP.xml
	Stop_Payment
chk_typ_descr	Check_Type
	Check_Type_OLTP
chk_typ_exp_prd_opt	Check_Type
	Check_Type_OLTP
chk_typ_exp_prd_val	Check_Type
	Check_Type_OLTP
ChnlIDIntfNameTx	EVNTLOG
chnl_id	Interface_Terminal.xml
	Interface_Terminal_OLTP.xml
	SPAN2_Interface_Terminal.xml
	SPAN2_Interface_Terminal_OLTP.xml
ChstDrwrACSCd	OPERID
cil_pid	Interac_Entry_Point
CIntrDlgtypCd	ESATDD1
CIntrTmtCntrNum	ESATDD1
city	Institution
	Merchant
	Merchant_Delivery_Channel
	Merchant_OLTP
city_fld	dal_tbl
city_mbyte	Institution
	Merchant
	Merchant_Delivery_Channel
CLdStatCd	ESATDD1
clean_up_time_hour	Interac_Base
	Interac_Base_OLTP
clean_up_timr_id	Interac_Base
clean_up_tim_min	Interac_Base
	Interac_Base_OLTP
clerk_adj_amt	Merchant_Delivery_Channel

clerk_adj_cnt	Merchant_Delivery_Channel
clerk_cb_amt	Merchant_Delivery_Channel
clerk_cb_cnt	Merchant_Delivery_Channel
clerk_chk_amt	Merchant_Delivery_Channel
clerk_chk_cnt	Merchant_Delivery_Channel
clerk_cr_amt	Merchant_Delivery_Channel
clerk_cr_cnt	Merchant_Delivery_Channel
clerk_db_amt	Merchant_Delivery_Channel
clerk_db_cnt	Merchant_Delivery_Channel
clerk_flg	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
clerk_id	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant_Delivery_Channel
clerk_nam	Admin_Card
clos_flg	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
ClsNameTx	EVENTLOG
cmd_err_cnt	ATM_DIAL_UP_CMD
cmd_stat	ATM_DIAL_UP_CMD
cmd_val	ATM_DIAL_UP_CMD
CMltAcctFrIndxNum	ESATDD1
CMltAcctTIndxNum	ESATDD1
CMltpAcctIndCd	ESATDD1
CmmnTranDataBn	ESATDD2
cmmn_tran_data	ATM_DD2
cmplr_msg_detail	Compiler_Message
cmplr_msg_num	Compiler_Message.xml
cmplr_msg_txt	Compiler_Message
cmplr_severity	Compiler_Message
cmpl_trk_data	Merchant_Channel_Profile

	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
CmpnIDTx	EVNTLOG.xml
cmpnt_id	Audit_Store_and_Forward_Config.xml
	Context.xml
	EFunds_Institution.xml
	EFunds_Institution_OLTP.xml
	Exception_Log
	File_Update_Route.xml
	File_Update_Route_OLTP
	FPS_Batch_Config
	FPS_Batch_Config_OLTP
	FPS_Batch_Control.xml
	FPS_Payment_Submission.xml
	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP
	IBM_Context
	Interac_Base.xml
	Interac_Base_OLTP.xml
	Interface.xml
	Interface_Manager
	Interface_OLTP.xml
	Interface_SAF
	Netwk_Brand_Instrm_ReIn.xml
	Netwk_Brand_Instrm_ReIn_OLTP.xml
	SAF_Manager_OLTP
	Store_and_Forward
	Surcharge_Country_Code.xml
	Surcharge_Country_Code_OLTP.xml
cmpnt_nam	Exported_Operator_Documentation
CmptbltyPrflTx	CMPTPRFL.xml
	ESATDS1
cmp_ind	Identikey
	Identikey_OLTP
cmrcl_deposit_amt	ATM_DD1

	ATM_PREV_TTL
cmrcl_deposit_cnt	ATM_DD1
	ATM_PREV_TTL
cnct_st	Interac_Interface
CnfgPrflTx	ATDCNFG.xml
	ESATDS1
CnfgPropIDTx	APPLCNFG.xml
CnfgPropValTx	APPLCNFG
cnfg_prfl	ATM_DS1
	ATM_DS1_OLTP
	ATM_PRFL.xml
	ATM_PRFL_OLTP.xml
cntl_bal_ind	ATM_DD1
cntl_intertxn_tout	ATM_DD1
cntl_load_stat	ATM_DD1
cntl_opt_rcpt_stat	ATM_DD1
cntl_part_rvrsl	ATM_DD1
cntl_rcpt_ln_cnt	ATM_DD1
cntl_rcpt_pg_cnt	ATM_DD1
cntl_rear_bal_ind	ATM_DD1
cntl_suprvsr_ind	ATM_DD1
cntl_sur_amt_lmt	ATM_DD1
cntl_txn_stat	ATM_DD1
cndry	Institution
	Institution_ID_OLTP
	Institution_OLTP
	Merchant
	Merchant_Delivery_Channel
	Merchant_OLTP
cndry_cde	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
	Surcharge_Country_Code.xml
	Surcharge_Country_Code_OLTP.xml
cndry_mbyte	Institution

	Merchant
	Merchant_Delivery_Channel
ColumnName	AuditDtl.xml
combined_bal_flg	Prefix
	Prefix_OLTP
CommentTextTx	LCONF
compl_ts	FPS_Batch_Control
cond_descr	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
confirm_auth_flg	APACS_Configuration
	APACS_Configuration_OLTP
confirm_fncl_flg	APACS_Configuration
	APACS_Configuration_OLTP
confirm_rcncl_flg	APACS_Configuration
	APACS_Configuration_OLTP
ConnWaitTime	DATASRC
contact1_comments	Institution
	Merchant
contact1_comments_mbyte	Institution
	Merchant
contact1_email_addr	Institution
	Merchant
contact1_email_addr_mbyte	Institution
	Merchant
contact1_nam	Institution
	Merchant
	Merchant_Delivery_Channel
contact1_nam_mbyte	Institution
	Merchant
	Merchant_Delivery_Channel
contact1_phn_num	Institution
	Merchant
	Merchant_Delivery_Channel
contact1_phn_num_mbyte	Institution
	Merchant
	Merchant_Delivery_Channel

contact2_comments	Institution
	Merchant
contact2_comments_mbyte	Institution
	Merchant
contact2_email_addr	Institution
	Merchant
contact2_email_addr_mbyte	Institution
	Merchant
contact2_nam	Institution
	Merchant
contact2_nam_mbyte	Institution
	Merchant
contact2_phn_num	Institution
	Merchant
contact2_phn_num_mbyte	Institution
	Merchant
ContactInfo	Users
Context	MSGCNTX
ContextID	AuditTbl
	Context_USEC.xml
	SrchFld
ContFlg	MSGCNTX
continue_parse	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
cont_asgn_nam	Journal_Prfl_Group_Assign_OLTP
	Journal_Profile_Group_Assign
COptnRcptStatCd	ESATDD1
CPrtlRvrsPndnCd	ESATDD1
CRBlncIndCd	ESATDD1
CRcptChcFlagCd	ESATDD1
CRcptLnCntNum	ESATDD1
CRcptPgCntNum	ESATDD1
crdhldr_auth_cap	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
crdhldr_prsn	Merchant_Delivery_Channel

crd_accpt_bus_cde	Merchant_Channel_Profile Merchant_Channel_Profile_OLTP Merchant_Delivery_Channel Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
crd_accpt_id	GICC_Acq_SGN.xml GICC_Iss_SGN.xml GISO_CRD_ACPT_RT.xml GISO_CRD_ACPT_RT_OLTP.xml Interac_Admin
crd_blk_flg	EMV_Script_Context
crd_blk_ts	Card_Block Card_Block_OLTP
crd_captr_cap	Merchant_Delivery_Channel Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
crd_data_input_cap	Merchant_Delivery_Channel Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
crd_data_output_cap	Merchant_Delivery_Channel Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
crd_num	Admin_Card.xml
crd_prsn	Merchant_Delivery_Channel
crd_scheme	Prefix Prefix_OLTP
crd_seq_num	Card.xml Card_Account.xml CARD_ACCOUNT_MBYTE.xml Card_Block.xml Card_Block_OLTP Card_Impacts.xml Check_Status.xml
crd_vrfy_prfl	Card_Verification.xml Card_Verification_OLTP.xml Dynamic_Card_Verification.xml

	Dynamic_Card_Verification_OLTP.xml
CreateTS	ActSess
	ACTSESS2
	Password
	Users
CreationID	SecGrp
crncy_cde	Euro_Opted_Currency.xml
	Euro_Opted_Currency_OLTP.xml
	Fees
	Fees_OLTP
	FPID_History.xml
	FPS_Payment_Submission
	FPS_Payment_Typ
	FPS_Payment_Typ_OLTP
	Institution
	Institution_OLTP
	Limits
	Limits_OLTP
	Positive_Balance
	Referral
	Referral_OLTP
	Stop_Payment
	Surcharge.xml
	Surcharge_OLTP.xml
crncy_conv_fee_nam	Interface
	Interface_Issuer_OLTP
crncy_conv_rate	Currency_Conversion_Rate
	Currency_Conversion_Rate_OLTP
crncy_opt_flg	Euro_Opted_Currency
	Euro_Opted_Currency_OLTP
cross_acq_hdr	Channel_Security
cross_acq_kam	Channel_Security
cross_acq_keyx	Channel_Security
cross_acq_lgth	Channel_Security
cross_acq_vvk	Channel_Security
CryptoMetaPrflTx	ATDCNFG

crypto_key_1	EMV_Security EMV_Security_OLTP
crypto_key_10	EMV_Security EMV_Security_OLTP
crypto_key_10_hdr	EMV_Security EMV_Security_OLTP
crypto_key_10_kam	EMV_Security EMV_Security_OLTP
crypto_key_11	EMV_Security EMV_Security_OLTP
crypto_key_11_hdr	EMV_Security EMV_Security_OLTP
crypto_key_11_kam	EMV_Security EMV_Security_OLTP
crypto_key_12	EMV_Security EMV_Security_OLTP
crypto_key_12_hdr	EMV_Security EMV_Security_OLTP
crypto_key_12_kam	EMV_Security EMV_Security_OLTP
crypto_key_13	EMV_Security EMV_Security_OLTP
crypto_key_13_hdr	EMV_Security EMV_Security_OLTP
crypto_key_13_kam	EMV_Security EMV_Security_OLTP
crypto_key_14	EMV_Security EMV_Security_OLTP
crypto_key_14_hdr	EMV_Security EMV_Security_OLTP
crypto_key_14_kam	EMV_Security EMV_Security_OLTP
crypto_key_15	EMV_Security EMV_Security_OLTP
crypto_key_15_hdr	EMV_Security EMV_Security_OLTP

crypto_key_15_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_16	EMV_Security
	EMV_Security_OLTP
crypto_key_16_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_16_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_17	EMV_Security
	EMV_Security_OLTP
crypto_key_17_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_17_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_18	EMV_Security
	EMV_Security_OLTP
crypto_key_18_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_18_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_19	EMV_Security
	EMV_Security_OLTP
crypto_key_19_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_19_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_1_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_1_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_2	EMV_Security
	EMV_Security_OLTP
crypto_key_20	EMV_Security
	EMV_Security_OLTP
crypto_key_20_hdr	EMV_Security
	EMV_Security_OLTP

crypto_key_20_kam	EMV_Security EMV_Security_OLTP
crypto_key_21	EMV_Security EMV_Security_OLTP
crypto_key_21_hdr	EMV_Security EMV_Security_OLTP
crypto_key_21_kam	EMV_Security EMV_Security_OLTP
crypto_key_22	EMV_Security EMV_Security_OLTP
crypto_key_22_hdr	EMV_Security EMV_Security_OLTP
crypto_key_22_kam	EMV_Security EMV_Security_OLTP
crypto_key_23	EMV_Security EMV_Security_OLTP
crypto_key_23_hdr	EMV_Security EMV_Security_OLTP
crypto_key_23_kam	EMV_Security EMV_Security_OLTP
crypto_key_24	EMV_Security EMV_Security_OLTP
crypto_key_24_hdr	EMV_Security EMV_Security_OLTP
crypto_key_24_kam	EMV_Security EMV_Security_OLTP
crypto_key_2_hdr	EMV_Security EMV_Security_OLTP
crypto_key_2_kam	EMV_Security EMV_Security_OLTP
crypto_key_3	EMV_Security EMV_Security_OLTP
crypto_key_3_hdr	EMV_Security EMV_Security_OLTP
crypto_key_3_kam	EMV_Security EMV_Security_OLTP

crypto_key_4	EMV_Security
	EMV_Security_OLTP
crypto_key_4_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_4_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_5	EMV_Security
	EMV_Security_OLTP
crypto_key_5_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_5_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_6	EMV_Security
	EMV_Security_OLTP
crypto_key_6_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_6_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_7	EMV_Security
	EMV_Security_OLTP
crypto_key_7_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_7_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_8	EMV_Security
	EMV_Security_OLTP
crypto_key_8_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_8_kam	EMV_Security
	EMV_Security_OLTP
crypto_key_9	EMV_Security
	EMV_Security_OLTP
crypto_key_9_hdr	EMV_Security
	EMV_Security_OLTP
crypto_key_9_kam	EMV_Security
	EMV_Security_OLTP

crypto_key_chk_values_1	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_10	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_11	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_12	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_13	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_14	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_15	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_16	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_17	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_18	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_19	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_2	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_20	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_21	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_22	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_23	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_24	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_3	EMV_Security EMV_Security_OLTP

crypto_key_chk_values_4	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_5	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_6	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_7	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_8	EMV_Security EMV_Security_OLTP
crypto_key_chk_values_9	EMV_Security EMV_Security_OLTP
crypto_key_idx_1	EMV_Security EMV_Security_OLTP
crypto_key_idx_10	EMV_Security EMV_Security_OLTP
crypto_key_idx_11	EMV_Security EMV_Security_OLTP
crypto_key_idx_12	EMV_Security EMV_Security_OLTP
crypto_key_idx_13	EMV_Security EMV_Security_OLTP
crypto_key_idx_14	EMV_Security EMV_Security_OLTP
crypto_key_idx_15	EMV_Security EMV_Security_OLTP
crypto_key_idx_16	EMV_Security EMV_Security_OLTP
crypto_key_idx_17	EMV_Security EMV_Security_OLTP
crypto_key_idx_18	EMV_Security EMV_Security_OLTP
crypto_key_idx_19	EMV_Security EMV_Security_OLTP
crypto_key_idx_2	EMV_Security EMV_Security_OLTP

List of data elements

crypto_key_idx_20	EMV_Security EMV_Security_OLTP
crypto_key_idx_21	EMV_Security EMV_Security_OLTP
crypto_key_idx_22	EMV_Security EMV_Security_OLTP
crypto_key_idx_23	EMV_Security EMV_Security_OLTP
crypto_key_idx_24	EMV_Security EMV_Security_OLTP
crypto_key_idx_3	EMV_Security EMV_Security_OLTP
crypto_key_idx_4	EMV_Security EMV_Security_OLTP
crypto_key_idx_5	EMV_Security EMV_Security_OLTP
crypto_key_idx_6	EMV_Security EMV_Security_OLTP
crypto_key_idx_7	EMV_Security EMV_Security_OLTP
crypto_key_idx_8	EMV_Security EMV_Security_OLTP
crypto_key_idx_9	EMV_Security EMV_Security_OLTP
crypto_ver_num	Chip_Authentication Chip_Authentication_OLTP EMV_Security EMV_Security_OLTP
cr_lmt	Positive_Balance
csb_acq_id_cde	PRICE_Interface PRICE_Interface_OLTP
csm_buf	Card Card_Account FPS_Payment_Submission Positive_Balance
csm_buf_chng_dat	Card

	Positive_Balance
CSprvIndCd	ESATDD1
CStmnPrntIndCd	ESATDD1
csu	EMV_Iss_Auth_Dta
	EMV_Iss_Auth_Dta_OLTP
ctls_crd_data_input_cap	Merchant_Delivery_Channel
CTpOfRcptFlagCd	ESATDD1
CTranRspnCdNum	ESATDD1
CTranStatCd	ESATDD1
CtvrPndnCd	ESATDD1
ctx_asgn_nam	Context_Configuration
	Context_Configuration_OLTP
ctx_buf	FPS_Queue
ctx_clt_data_lgth	Context
	IBM_Context
ctx_data	Context
	IBM_Context
ctx_exp_ts	Context
	IBM_Context
ctx_key	Context.xml
	FPS_Queue.xml
	IBM_Context
	Store_and_Forward
ctx_lgth	FPS_Queue
ctx_prfl	ATM_DS1
	ATM_DS1_OLTP
	Context_Configuration.xml
	Context_Configuration_OLTP.xml
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
ctx_rec_num	Context.xml
	FPS_Queue
	IBM_Context
ctx_timr_data_lgth	Context
	IBM_Context

curr_cr_amt	GICC_Channel
curr_cr_cnt	GICC_Channel
curr_cr_rvsl_amt	GICC_Channel
curr_cr_rvsl_cnt	GICC_Channel
curr_db_amt	GICC_Channel
curr_db_cnt	GICC_Channel
curr_db_rvsl_amt	GICC_Channel
curr_db_rvsl_cnt	GICC_Channel
curr_net_setl_amt	GICC_Channel
cur_atm_pacing_st	Interac_Base
cur_net_adj_amt	Merchant_Delivery_Channel
cur_net_adj_cnt	Merchant_Delivery_Channel
cur_net_cr_amt	Merchant_Delivery_Channel
cur_net_cr_cnt	Merchant_Delivery_Channel
cur_net_db_amt	Merchant_Delivery_Channel
cur_net_db_cnt	Merchant_Delivery_Channel
cur_net_dc_adj_amt	Merchant_Delivery_Channel
cur_net_dc_adj_cnt	Merchant_Delivery_Channel
cur_net_dc_cr_amt	Merchant_Delivery_Channel
cur_net_dc_cr_cnt	Merchant_Delivery_Channel
cur_net_dc_db_amt	Merchant_Delivery_Channel
cur_net_dc_db_cnt	Merchant_Delivery_Channel
cur_pos_pacing_st	Interac_Base
CustBlncLctnCd	ATDCNFG
CustBlncPrsnCd	ATDCNFG
cust_auth_mthd	Route.xml
	Route_OLTP.xml
cust_bal_loc	ATM_PRFL
	ATM_PRFL_OLTP
cust_bal_presented	ATM_PRFL
	ATM_PRFL_OLTP
cust_id	Card
cust_id_mbyte	CARD_ACCOUNT_MBYTE
cust_mstr_amt	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
cust_mstr_dat	Credit_Debit_Master_File

	Credit_Debit_Master_File_OLTP
cust_mstr_fld1	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
cust_mstr_fld2	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
cutover_bal_stat	Merchant_Delivery_Channel
cutover_end_tim	Institution
	Institution_OLTP
cutover_pending	ATM_DD1
cutover_strt_tim	Institution
	Institution_OLTP
cv2_req	Prefix
	Prefix_OLTP
cvr_bit	EMV_Card_Vrfn_Results_OLTP.xml
	EMV_Card_Vrfn_Results_Order_OLTP
	EMV_Card_Vrfn_Results_Status
cvr_byte	EMV_Card_Vrfn_Results_OLTP.xml
	EMV_Card_Vrfn_Results_Order_OLTP
	EMV_Card_Vrfn_Results_Status
cvr_chk	Prefix
	Prefix_OLTP
cvr_chk_pre_scrn	Prefix
	Prefix_OLTP
cvr_prfl	EMV_Card_Vrfn_Results_OLTP.xml
	EMV_Card_Vrfn_Results_Order_OLTP.xml
	EMV_Card_Vrfn_Results_Status.xml
	Prefix
	Prefix_OLTP
cvr_tvr_srch_order	EMV_Card_Vrfn_Results_OLTP
	EMV_Card_Vrfn_Results_Order_OLTP
	EMV_Card_Vrfn_Results_Status.xml
	EMV_Terminal_Vrfn_Results_Status.xml
	EMV_Term_Vrfn_Results_OLTP
	EMV_Term_Vrfn_Results_Order_OLTP
cv_bad_disp	Prefix
	Prefix_OLTP

cv_chk_typ	Prefix
	Prefix_OLTP
cv_dat_chk_typ	Prefix
	Prefix_OLTP
cv_eff_dat	Prefix
	Prefix_OLTP
cv_keya_prfl	Prefix
	Prefix_OLTP
cv_retry	Prefix
	Prefix_OLTP
dat	Stop_Payment
DataSrc	USRAULOG
DataSrcNamTx	APPLDSRC.xml
	DATASRC.xml
DataSrcTypTx	DATASRC
DataSrcURLTx	DATASRC
DataType	Fields
data_buf	TBP_Daily
data_cont_disp	Journal_Query_Config_Output
data_encr_typ	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
data_key_xchng_flg	Interac_Interface
data_lgth	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
data_script_nam	Journal_Query_Config_Output
data_src_end_posn_info	Journal_Query_Position_Info
data_src_id	MDS_Brand_Rel
	MDS_Brand_Rel_OLTP
	Netwk_Brand_Instrm_ReIn
	Netwk_Brand_Instrm_ReIn_OLTP
	Star_NE_Network_Rel
	Star_NE_Network_Rel_OLTP
	System_Prefix
	System_Prefix_OLTP
	Visa_Brand_Rel
	Visa_Brand_Rel_OLTP

data_src_strt_posn_info	Journal_Query_Position_Info
data_typ	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
DaysOfWeek	SecGrp
db2_id	Journal_Key_Seq2
dbi_field_44	ABI_Interface
	ABI_Interface_OLTP
dcv_bad_disp	Prefix
	Prefix_OLTP
dcv_chk_typ	Prefix
	Prefix_OLTP
dcv_key_prfl	Prefix
	Prefix_OLTP
dcv_pre_scrn	Prefix
	Prefix_OLTP
dec_tbl	IBM_DES
	IBM_DES_OLTP
delay_timr_lmt	FPS_Batch_Config
	FPS_Batch_Config_OLTP
del_dat	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
deny_thrhd_lmt	Authorization_Script
	Authorization_Script_OLTP
Department	Users
depository_bin	ATM_SSB_CPL.xml
dep_bin_prfl	ATM_DS1
	ATM_DS1_OLTP
	ATM_SSB_BIN.xml
	ATM_SSB_BIN_OLTP.xml
dep_bin_seq_num	ATM_SSB_CPL.xml
dep_typ	Card
descr	Context_Configuration
	Context_USEC
	Fields
	Filters
	Functs

	Netwk_Brand_Instrm_ReIn.xml
	Netwk_Brand_Instrm_ReIn_OLTP.xml
	PermGrp
	Perms
	PermType
	PswdGrp
	Roles
	SecGrp
	Stop_Payment
	Tasks
	UsrStat
dest_crncy_cde	Linked_Currency.xml
	Linked_Currency_OLTP.xml
dest_id_cde	ACCEL_Interface
	ACCEL_Interface_OLTP
	JCB_Interface
	JCB_Interface_OLTP
dest_pin_blk_typ	EMV_Security
	EMV_Security_OLTP
device_seq_num	ATM_DD1
dev_conf_txt	Security_Device_Config
dev_init_txt	Security_Device_Config
dev_nam	BNTng_Init_Data.xml
	Security_Device_Config.xml
dev_proto	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
dev_reset_timr_lmt	Security_Device_Config
dev_subtyp	Security_Device_Config
dev_tim_lmt	Security_Device_Config
dev_typ	Security_Device_Config
DfltDpstBinTx	ATDCNFG
dflt_acq_bnk_id	FIS_Interface
	FIS_Interface_OLTP
	Pulse_Interface

	Pulse_Interface_OLTP
	Star_Interface
	Star_Interface_OLTP
	Visa_DPS_Interface
	Visa_DPS_Interface_OLTP
dflt_acq_cntry_cde	Interface
	Interface_Acquirer_OLTP
dflt_acq_id_cde	Interface
	Interface_Acquirer_OLTP
dflt_auth_flr_lmt	Route
	Route_OLTP
dflt_captr_mde	Interface
	Interface_Acquirer_OLTP
	Merchant_Delivery_Channel
dflt_ccti_id	GICC_Interface
	GICC_Interface_OLTP
dflt_crd_accpt_bus_cde	Interface
	Interface_Acquirer_OLTP
	Merchant
	Merchant_OLTP
dflt_crncy_cde	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
	Merchant
	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	Merchant_OLTP
dflt_dpst_bin	ATM_PRFL
	ATM_PRFL_OLTP
dflt_mrch_id	GICC_Interface
	GICC_Interface_OLTP
	Interface
	Interface_Acquirer_OLTP
dflt_nmm_crd_accpt_id	GISO_Interface

	GISO_Interface_OLTP
dflt_nmm_msg_class	GISO_Interface
	GISO_Interface_OLTP
dflt_nmm_proc_cde	GISO_Interface
	GISO_Interface_OLTP
dflt_nmm_term_id	GISO_Interface
	GISO_Interface_OLTP
dflt_nmm_trk_3	GISO_Interface
	GISO_Interface_OLTP
dflt_oper_envmt	Merchant
	Merchant_OLTP
dflt_pre_auth_hold_incr	Interface
	Interface_Acquirer_OLTP
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	Prefix
	Prefix_OLTP
dflt_pre_auth_hold_tim	Interface
	Interface_Acquirer_OLTP
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	Prefix
	Prefix_OLTP
dflt_pri_acct_typ	Card
dflt_rfrl_phn_num	Interface
	Interface_Issuer_OLTP
dflt_svs_mrch_num	SVS_Interface
	SVS_Interface_OLTP
dflt_term_id	GICC_Interface
	GICC_Interface_OLTP
	Interface
	Interface_Acquirer_OLTP

dflt_val	file_part_fields
	file_part_fields_OLTP
DHPrcsNameTx	CMPTPRFL
DialUpFlrActnCd	ATDCNFG
dial_up_call_mgmt	ATM_PRFL
	ATM_PRFL_OLTP
dial_up_fail_act	ATM_PRFL
	ATM_PRFL_OLTP
dial_up_queue_cnt	ATM_DD1
discrd_rvsl_flg	Issuer_Txn_Allowed
	Issuer_Txn_Allowed_OLTP
discrim	Journal
	Journal_Continuation.xml
	Journal_Key_Seq.xml
	Journal_Key_Seq2.xml
	Referral
	Referral_OLTP
dispense_algorithm	ATM_HOPR
	ATM_HOPR_OLTP
DisplayValue	FldVals
disp_algo_fail_act	ATM_PRFL
	ATM_PRFL_OLTP
distngsh_nam_hash	Host_Public_Key_Security.xml
DkmAuthentKeyCnt	ATDCNFG
DkmCertAuthSprtCd	ATDCNFG
DkmCertChngTime	ESATDD1
DkmCertConfStsCd	ESATDD1
DkmCertConfTmrLng	ESATDD1
DkmCertRlvrTmrLng	ESATDD1
DkmKEKMACChngTime	ESATDD1
DkmKEKMSGChngTime	ESATDD1
DkmKEKPINChngTime	ESATDD1
DkmKEKRetryCntNum	ESATDD1
DkmKeyChngTime	ESATDD1
DkmKeyRetryCntNum	ESATDD1
DkmMacCsErrCntNum	ESATDD1

List of data elements

DkmMacErrCntrNum	ESATDD1
DkmMacKeyChngTime	ESATDD1
DkmMacTranCntrNum	ESATDD1
DkmMsgChngTime	ESATDD1
DkmMsgErrCntrNum	ESATDD1
DkmMsgTranCntrNum	ESATDD1
DkmPinErrCntrNum	ESATDD1
DkmPinTranCntrNum	ESATDD1
DkmRlvrRetryCntNum	ESATDD1
DkmTMKeyChngTime	ESATDD1
DkmTMKRetryCntNum	ESATDD1
dkm_cnsc_mac_err_cnt	ATM_DD1
dkm_cnsc_mac_err_lmt	ATM_DKM
	ATM_DKM_OLTP
dkm_key_chng_tm	ATM_DD1
dkm_key_chng_tm_intrvl	ATM_DKM
	ATM_DKM_OLTP
dkm_mac_err_cnt	ATM_DD1
dkm_mac_err_lmt	ATM_DKM
	ATM_DKM_OLTP
dkm_mac_txn_cnt	ATM_DD1
dkm_mac_txn_lmt	ATM_DKM
	ATM_DKM_OLTP
dkm_pin_err_cnt	ATM_DD1
dkm_pin_err_lmt	ATM_DKM
	ATM_DKM_OLTP
dkm_pin_txn_cnt	ATM_DD1
dkm_pin_txn_lmt	ATM_DKM
	ATM_DKM_OLTP
dkm_prfl	ATM_DKM.xml
	ATM_DKM_OLTP.xml
	ATM_DS1
	ATM_DS1_OLTP
dly_adj_amt	Merchant_Delivery_Channel
dly_adj_cnt	Merchant_Delivery_Channel
dly_cr_amt	Merchant_Delivery_Channel

dly_cr_cnt	Merchant_Delivery_Channel
dly_db_amt	Merchant_Delivery_Channel
dly_db_cnt	Merchant_Delivery_Channel
dly_dc_adj_amt	Merchant_Delivery_Channel
dly_dc_adj_cnt	Merchant_Delivery_Channel
dly_dc_cr_amt	Merchant_Delivery_Channel
dly_dc_cr_cnt	Merchant_Delivery_Channel
dly_dc_db_amt	Merchant_Delivery_Channel
dly_dc_db_cnt	Merchant_Delivery_Channel
dly_ttl_supported	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
dnt_algo_num	Diebold_Number_Table
	Diebold_Number_Table_OLTP
dnt_entry_typ	Diebold_Number_Table
dnt_hdr1	Diebold_Number_Table
dnt_hdr10	Diebold_Number_Table
dnt_hdr11	Diebold_Number_Table
dnt_hdr12	Diebold_Number_Table
dnt_hdr13	Diebold_Number_Table
dnt_hdr14	Diebold_Number_Table
dnt_hdr15	Diebold_Number_Table
dnt_hdr16	Diebold_Number_Table
dnt_hdr17	Diebold_Number_Table
dnt_hdr18	Diebold_Number_Table
dnt_hdr19	Diebold_Number_Table
dnt_hdr2	Diebold_Number_Table
dnt_hdr20	Diebold_Number_Table
dnt_hdr21	Diebold_Number_Table
dnt_hdr22	Diebold_Number_Table
dnt_hdr23	Diebold_Number_Table
dnt_hdr24	Diebold_Number_Table
dnt_hdr25	Diebold_Number_Table
dnt_hdr26	Diebold_Number_Table
dnt_hdr27	Diebold_Number_Table

dnt_hdr28	Diebold_Number_Table
dnt_hdr29	Diebold_Number_Table
dnt_hdr3	Diebold_Number_Table
dnt_hdr30	Diebold_Number_Table
dnt_hdr31	Diebold_Number_Table
dnt_hdr32	Diebold_Number_Table
dnt_hdr4	Diebold_Number_Table
dnt_hdr5	Diebold_Number_Table
dnt_hdr6	Diebold_Number_Table
dnt_hdr7	Diebold_Number_Table
dnt_hdr8	Diebold_Number_Table
dnt_hdr9	Diebold_Number_Table
dnt_intrn_loc	Diebold_Number_Table
	Diebold_Number_Table_OLTP
dnt_kam1	Diebold_Number_Table
dnt_kam10	Diebold_Number_Table
dnt_kam11	Diebold_Number_Table
dnt_kam12	Diebold_Number_Table
dnt_kam13	Diebold_Number_Table
dnt_kam14	Diebold_Number_Table
dnt_kam15	Diebold_Number_Table
dnt_kam16	Diebold_Number_Table
dnt_kam17	Diebold_Number_Table
dnt_kam18	Diebold_Number_Table
dnt_kam19	Diebold_Number_Table
dnt_kam2	Diebold_Number_Table
dnt_kam20	Diebold_Number_Table
dnt_kam21	Diebold_Number_Table
dnt_kam22	Diebold_Number_Table
dnt_kam23	Diebold_Number_Table
dnt_kam24	Diebold_Number_Table
dnt_kam25	Diebold_Number_Table
dnt_kam26	Diebold_Number_Table
dnt_kam27	Diebold_Number_Table
dnt_kam28	Diebold_Number_Table
dnt_kam29	Diebold_Number_Table

dnt_kam3	Diebold_Number_Table
dnt_kam30	Diebold_Number_Table
dnt_kam31	Diebold_Number_Table
dnt_kam32	Diebold_Number_Table
dnt_kam4	Diebold_Number_Table
dnt_kam5	Diebold_Number_Table
dnt_kam6	Diebold_Number_Table
dnt_kam7	Diebold_Number_Table
dnt_kam8	Diebold_Number_Table
dnt_kam9	Diebold_Number_Table
dnt_key1	Diebold_Number_Table
dnt_key10	Diebold_Number_Table
dnt_key11	Diebold_Number_Table
dnt_key12	Diebold_Number_Table
dnt_key13	Diebold_Number_Table
dnt_key14	Diebold_Number_Table
dnt_key15	Diebold_Number_Table
dnt_key16	Diebold_Number_Table
dnt_key17	Diebold_Number_Table
dnt_key18	Diebold_Number_Table
dnt_key19	Diebold_Number_Table
dnt_key2	Diebold_Number_Table
dnt_key20	Diebold_Number_Table
dnt_key21	Diebold_Number_Table
dnt_key22	Diebold_Number_Table
dnt_key23	Diebold_Number_Table
dnt_key24	Diebold_Number_Table
dnt_key25	Diebold_Number_Table
dnt_key26	Diebold_Number_Table
dnt_key27	Diebold_Number_Table
dnt_key28	Diebold_Number_Table
dnt_key29	Diebold_Number_Table
dnt_key3	Diebold_Number_Table
dnt_key30	Diebold_Number_Table
dnt_key31	Diebold_Number_Table
dnt_key32	Diebold_Number_Table

dnt_key4	Diebold_Number_Table
dnt_key5	Diebold_Number_Table
dnt_key6	Diebold_Number_Table
dnt_key7	Diebold_Number_Table
dnt_key8	Diebold_Number_Table
dnt_key9	Diebold_Number_Table
dnt_vvk1	Diebold_Number_Table
dnt_vvk10	Diebold_Number_Table
dnt_vvk11	Diebold_Number_Table
dnt_vvk12	Diebold_Number_Table
dnt_vvk13	Diebold_Number_Table
dnt_vvk14	Diebold_Number_Table
dnt_vvk15	Diebold_Number_Table
dnt_vvk16	Diebold_Number_Table
dnt_vvk17	Diebold_Number_Table
dnt_vvk18	Diebold_Number_Table
dnt_vvk19	Diebold_Number_Table
dnt_vvk2	Diebold_Number_Table
dnt_vvk20	Diebold_Number_Table
dnt_vvk21	Diebold_Number_Table
dnt_vvk22	Diebold_Number_Table
dnt_vvk23	Diebold_Number_Table
dnt_vvk24	Diebold_Number_Table
dnt_vvk25	Diebold_Number_Table
dnt_vvk26	Diebold_Number_Table
dnt_vvk27	Diebold_Number_Table
dnt_vvk28	Diebold_Number_Table
dnt_vvk29	Diebold_Number_Table
dnt_vvk3	Diebold_Number_Table
dnt_vvk30	Diebold_Number_Table
dnt_vvk31	Diebold_Number_Table
dnt_vvk32	Diebold_Number_Table
dnt_vvk4	Diebold_Number_Table
dnt_vvk5	Diebold_Number_Table
dnt_vvk6	Diebold_Number_Table
dnt_vvk7	Diebold_Number_Table

dnt_vvk8	Diebold_Number_Table
dnt_vvk9	Diebold_Number_Table
dob_fld	dal_tbl
DpstCntNum	ESAPDT
	ESATDD1
dpgn_pin_vrfy_prfl	Dual_PIN_Verification.xml
	Dual_PIN_Verification_OLTP.xml
DrvrNamTx	DATASRC
drv_depth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
drv_id	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
drv_key	Derivation_Key
	Derivation_Key_OLTP
drv_key_hdr	Derivation_Key
	Derivation_Key_OLTP
drv_key_kam	Derivation_Key
	Derivation_Key_OLTP
drv_key_opt	Derivation_Key
	Derivation_Key_OLTP
drv_key_prfl	Derivation_Key.xml
	Derivation_Key_OLTP.xml
drv_key_vvk	Derivation_Key
	Derivation_Key_OLTP
DscrTagTx	APCF
DscrTx	APPLCNFG
	EXTRCNCT
	HSMCNFG
	LISTENER
DspnAlgrCd	HPRPRFL
DspnMxBllsNum	HPRPRFL
DspnMxCnsNum	HPRPRFL
dual_site_ind	ATM_DD1
	ESATDD1

	Journal
	Journal_Continuation
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant_Delivery_Channel
dummy_pan	Interac_Base
	Interac_Base_OLTP
dup_crncy_cde	Interface_FPS
	Interface_FPS_OLTP
dup_detect_flg	Interface_FPS
	Interface_FPS_OLTP
dup_flr_lmt	Interface_FPS
	Interface_FPS_OLTP
DvcSqncNumTx	ESATDD1
dyn_crd_vrfy_algo	Dynamic_Card_Verification
	Dynamic_Card_Verification_OLTP
ebt_enbl	FIS_Interface
	FIS_Interface_OLTP
echo_out_bit_map	ISO_Message
	ISO_Message_OLTP
edcs_inst_id	EPSNET_Interface
	EPSNET_Interface_OLTP
eff_dat	Card
eff_dat_chng_dat	Card
eff_dat_scnd	Card
efunds_intf_dpnt_data	EFunds_Institution
	EFunds_Institution_OLTP
	EFunds_Interface
	EFunds_Interface_OLTP
elog_data	Exception_Log
elog_data_lgth	Exception_Log
EmailAddress	Users
emboss	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
EmvPrfITx	EMVPRFL.xml
	ESATDS1

EmvScSndCrdBlkTx	ESATDD1
EmvScSndPtDataTx	ESATDD1
EmvTermCrdDatInTx	EMVPRFL
EmvTermCvmTx	EMVPRFL
EmvTermScrtTx	EMVPRFL
emv_appl_cap_ind	Merchant_Delivery_Channel
emv_auth_key_prfl	Chip_Authentication
	Chip_Authentication_OLTP
	EMV_Security.xml
	EMV_Security_OLTP.xml
	Prefix
	Prefix_OLTP
emv_capable	ATM_DS1
	ATM_DS1_OLTP
emv_cv_chk_mthd	Prefix
	Prefix_OLTP
emv_cv_chk_typ	Prefix
	Prefix_OLTP
emv_cv_eff_dat	Prefix
	Prefix_OLTP
emv_cv_srvc_cde	Prefix
	Prefix_OLTP
emv_force_onl_flg	EMV_Card_Vrfn_Results_OLTP
	EMV_Card_Vrfn_Results_Order_OLTP
	EMV_Card_Vrfn_Results_Status
	EMV_Reason_Online_Code_OLTP
	EMV_Reason_Online_Code_Status
	EMV_Terminal_Vrfn_Results_Status
	EMV_Term_Vrfn_Results_OLTP
	EMV_Term_Vrfn_Results_Order_OLTP
emv_frmt	EMV_Card_Vrfn_Results_OLTP.xml
	EMV_Card_Vrfn_Results_Order_OLTP.xml
	EMV_Card_Vrfn_Results_Status.xml
	Prefix
	Prefix_OLTP
emv_ifd_serial_num	Merchant_Delivery_Channel

emv_iss_rte_prfl	Prefix Prefix_OLTP
emv_scheme	EMV_Security EMV_Security_OLTP
emv_script_mac_lgth	Prefix Prefix_OLTP
emv_script_crd_blk	ATM_DD1
emv_script_put_data	ATM_DD1
emv_term_crd_cap	ATM_EMV ATM_EMV_OLTP Merchant_Delivery_Channel
emv_term_cvm	ATM_EMV ATM_EMV_OLTP Merchant_Delivery_Channel
emv_term_script	ATM_EMV ATM_EMV_OLTP Merchant_Delivery_Channel
enabled_flg	Contingency_Interface Contingency_Interface_OLTP PRM_Interface PRM_Interface_OLTP Real_Time_Feed_Config Real_Time_Feed_Config_OLTP
EncrDevTypCd	ATDCNFG
encrypt_data_typ	Channel_Security Interchange_Security Interchange_Security_OLTP
encrypt_des_mde	Channel_Security Derivation_Key Derivation_Key_OLTP EMV_Security EMV_Security_OLTP Interchange_Security Interchange_Security_OLTP
encrypt_layers	Channel_Security Interchange_Security

	Interchange_Security_OLTP
encrypt_typ	BIC_Interface
	BIC_Interface_OLTP
endpoint_nam	Totals.xml
	Totals_Configuration.xml
	Totals_Configuration_OLTP.xml
	Totals_Entry
	Totals_Entry2
	Totals_Manager_Cnfg_OLTP
EndTime	SecGrp
EndValue	Filters
end_cutover_tim	Merchant
	Merchant_OLTP
end_dat	Card_Verification.xml
	Card_Verification_OLTP
	Chip_Authentication.xml
	Chip_Authentication_OLTP
	Diebold_Number_Table.xml
	Diebold_Number_Table_OLTP
	Dual_PIN_Verification.xml
	Dual_PIN_Verification_OLTP
	Dynamic_Card_Verification.xml
	Dynamic_Card_Verification_OLTP
	EMV_Security.xml
	EMV_Security_OLTP
	IBM_DES.xml
	IBM_DES_OLTP
	Identikey.xml
	Identikey_OLTP
	Visa_PVV.xml
	Visa_PVV_OLTP
end_ofst	Journal_Query_Config
end_pt_typ	HISO87_Interface
	HISO87_Interface_OLTP
	HISO93_Interface
	HISO93_Interface_OLTP

end_to_end_ref	FPS_Payment_Submission
enhnc_acq_bnk_id_proc	FIS_Interface
	FIS_Interface_OLTP
	Pulse_Interface
	Pulse_Interface_OLTP
	Star_Interface
	Star_Interface_OLTP
	Visa_DPS_Interface
	Visa_DPS_Interface_OLTP
enhnc_svs_mrch_num_proc	SVS_Interface
	SVS_Interface_OLTP
EntryTemplate	APPLCNFG
envl_deposit_amt	ATM_DD1
	ATM_PREV_TTL
envl_deposit_cnt	ATM_DD1
	ATM_PREV_TTL
epp_mfg	ATM_DS1
	ATM_DS1_OLTP
epp_rndm_nonce	Channel_Public_Key_Security
epp_serl_num	Channel_Public_Key_Security
	EPP_Serial_Number.xml
epp_val_dat	EPP_Serial_Number
epp_val_tim	EPP_Serial_Number
epp_vrfy_flg	ATM_DS1
	ATM_DS1_OLTP
eps_act_cde_lookup	SPDH_Configuration
	SPDH_Configuration_OLTP
ep_filler	Interac_Entry_Point
ep_id	Interac_Entry_Point.xml
ep_stat	Interac_Entry_Point
equens_instrm_typ_extrn	Equens_Instrm_Typ_Extrn
	Equens_Instrm_Typ_Extrn_OLTP.xml
	Equens_Instrm_Typ_Intrn
	Equens_Instrm_Typ_Intrn_OLTP
ErrorData	AuditTbl
ersb_machine_id	ERSB_Interface

	ERSB_Interface_OLTP
ersb_user_id	ERSB_Interface
	ERSB_Interface_OLTP
euro_standin_resp_cde_1	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_10	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_11	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_12	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_13	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_14	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_15	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_16	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_17	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_18	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_19	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_2	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_20	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_21	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_22	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_23	EPSNET_Interface
	EPSNET_Interface_OLTP
euro_standin_resp_cde_3	EPSNET_Interface

euro_standin_resp_cde_4	EPSNET_Interface_OLTP
euro_standin_resp_cde_5	EPSNET_Interface
euro_standin_resp_cde_6	EPSNET_Interface_OLTP
euro_standin_resp_cde_7	EPSNET_Interface
euro_standin_resp_cde_8	EPSNET_Interface_OLTP
euro_standin_resp_cde_9	EPSNET_Interface
EvntMsgTx	EPSNET_Interface_OLTP
EvntNum	EVNTLOG
EvntTimeTm	EVNTLOG
evt_doc_data	EVNTLOG.xml
evt_doc_data_lgth	Event_Document
evt_num	Event_Document
evt_rec_typ	Event.xml
evt_txt	Event_Document.xml
evt_txt_lgth	Event_OLTP.xml
exception_time	Exception_Log
exec_pri	Event_Document.xml
ExpireDate	Event
ExpireTS	Event_OLTP
export_kkt_key_typ	Event
ExpTm	Event_OLTP
exp_chk_ind	EXCPT.xml
	ATM_DIAL_UP_CMD.xml
	Password
	Ticket
	Interchange_Security
	Interchange_Security_OLTP
	CACNTX
	MSGCNTX
	Prefix

exp_dat	Prefix_OLTP Card Card_Block.xml Card_Block_OLTP EMV_Script_Context.xml Prefix_Block.xml Prefix_Block_OLTP Stop_Payment
exp_dat_chng_dat	Card
exp_dat_cmp	Prefix Prefix_OLTP
exp_dat_scnd	Card
ExtrCnctID	CACNFSAF EXTRCNCT.xml PROCESS RVSLSAF
extrn_char_set	ISO_Field ISO_Field_OLTP
extrn_key_blk_frmt	Channel_Security Interchange_Security Interchange_Security_OLTP
ext_intf_term_id	SPAN2_Interface_Terminal SPAN2_Interface_Terminal_OLTP
fail_script_nam	Journal_Query_Config
fallback_act	Prefix Prefix_OLTP
fallback_chk_pre_scrn	Prefix Prefix_OLTP
fast_cash_amt_1	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_amt_2	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_amt_3	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_amt_4	ATM_FAST_CASH ATM_FAST_CASH_OLTP

List of data elements

fast_cash_amt_5	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_amt_6	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_amt_7	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_amt_8	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_1	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_2	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_3	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_4	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_5	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_6	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_7	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_cur_8	ATM_FAST_CASH ATM_FAST_CASH_OLTP
fast_cash_prfl	ATM_DS1 ATM_DS1_OLTP ATM_FAST_CASH.xml ATM_FAST_CASH_OLTP.xml
FaxPhoneNum	Users
fee_eff_dat	Fees.xml Fees_OLTP
fee_nam	Fees.xml Fees_OLTP.xml
fee_opt	Fees Fees_OLTP
fee_pctg	Fees

	Fees_OLTP
fee_prfl	Fees.xml
	Fees_OLTP.xml
	Positive_Balance
fee_rvsl_opt	Fees
	Fees_OLTP
fhm_act_cde_prfl	HISO87_Interface
	HISO87_Interface_OLTP
fhm_msg_prfl	HISO87_Interface
	HISO87_Interface_OLTP
fid_x_lookup	SPDH_Configuration
	SPDH_Configuration_OLTP
FieldID	Fields.xml
	Filters
	FldVals.xml
	TaskFlds.xml
file_frmt	Journal_Profile_Group
	Journal_Profile_Group_OLTP
file_hdr_script_nam	Journal_Query_Config_Output
file_trlr_script_nam	Journal_Query_Config_Output
file_typ	B24_filetyp_map
	B24_filetyp_map_OLTP
	File_Update_Route.xml
	File_Update_Route_OLTP.xml
file_updt_id	Presto_Interface
	Presto_Interface_OLTP
filler	FPS_Payment_Pri_Group.xml
	FPS_Payment_Pri_Group_OLTP.xml
	Ind_Sort_Code_Bic_OLTP
	Interchange_Prefix
Filterable	Fields
FilterID	Filters.xml
	FLTXROLE.xml
	FIXFldVI.xml
	USRXFILT.xml
filter_prfl	Trace_Config

filter_typ	Trace_Filter.xml
filter_val	Trace_Filter.xml
firmware_ver	Trace_Filter.xml
FirstName	Security_Device_Config
fitness_array	Users
fld_bcd_bit_map	ATM_DD1
	ISO_Field
	ISO_Field_OLTP
fld_defn_prfl	GISO_IN_MSG_DEF
	GISO_IN_MSG_DEF_OLTP
	GISO_OUT_MSG_DEF
	GISO_OUT_MSG_DEF_OLTP
	ISO_FLD_DEFN.xml
	ISO_FLD_DEFN_OLTP.xml
fld_descr	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
fld_nam	file_part_fields
	file_part_fields_OLTP
fld_num	ISO_FLD_DEFN.xml
	ISO_FLD_DEFN_OLTP.xml
fld_ord_num	file_part_fields.xml
	file_part_fields_OLTP
fld_val_lgth	file_part_fields
	file_part_fields_OLTP
fllr_lmt_onl_auth_fail_amt	APACS_Configuration
	APACS_Configuration_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
fllr_lmt_onl_auth_fail_flg	APACS_Configuration
	APACS_Configuration_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
fllr_lmt_trig_onl_auth_amt	APACS_Configuration
	APACS_Configuration_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP

flr_lmt_trig_onl_auth_flg

APACS_Configuration

APACS_Configuration_OLTP

Merchant_Delivery_Channel_Profil

Merchant_Delivery_Chan_Prfl_OLTP

fm_ts

ABI_Interface

ABI_Key

ACCEL_Interface

Account_Routing

Acct_Status_Extrn_to_Intrn

Acct_Status_Intrn_to_Extrn

Acquirer_Instrument_Type_Rel

Acquirer_Issuer_Relation

Acquirer_Route_Profile

Acquirer_Txn_Allowed

Action_Code_Extrn_to_Intrn

Action_Code_Intrn_to_Extrn

Admin_Card

AEGN_Interface

AMEX_CAPN_Interface

APACS_Configuration

AS2805_Config

AS2805_Interface

ATDCNFG

ATM_CONSUMER_MEDIA

ATM_DD1

ATM_DD2

ATM_DKM

ATM_DS1

ATM_EMV

ATM_FAST_CASH

ATM_FLOW_CNTL

ATM_HOPR

ATM_IFXDATA

ATM_INACT

ATM_MAC

ATM_MBYTE_XLATE

ATM_OPER
ATM_OP_CDE
ATM_PEAK_LOAD
ATM_PREV_TTL
ATM_PRFL
ATM_RECEIPT
ATM_REQ_RCPT
ATM_RQUID
ATM_SSB_BIN
ATM_STATE_SCRN
ATM_STMNT_PRNT
ATM_SUR
ATM_TC_Proc_Code
Audit_Store_and_Forward_Config
Authorization_Script
B24EPS_Ignt_map
B24_filetyp_map
B53_Institution
Banknet_Configuration
Banknet_Institution_Id
Banknet_Institution_Id2
Banknet_Merchant_Program
Batch_Auth_Config
Batch_Auth_Posn
BEPS_Instrm_Prty
BIC_Interface
BLZ_Map
BNFT_Interface
BNTng_Header
BNTng_Init_Data
Card
Cardnet_ID_Code
Cardnet_Interface
Cardnet_Interface_Terminal
Card_Account
CARD_ACCOUNT_MBYTE

Card_Block
Card_Impacts
Card_Verification
Channel_Instrm_Type_Relation
Channel_Instrument_Type_Rel
Channel_Public_Key_Security
Channel_Security
Channel_Security_Future
Chan_Profile_Instrm_Typ_Relation
Check_Status
Check_Type
Chip_Authentication
Circuit_Interface
CMPTPRFL
Compiler_Message
Context_Configuration
Contingency_Interface
CUP_Institution
CUP_Interface
Currency_Conversion_Rate
Derivation_Key
DIAS_Interface
Diebold_Number_Table
Discover_Institution
Discover_Interface
DS_OLTP_Relation
Dual_PIN_Verification
Dynamic_Card_Verification
EFunds_Institution
EFunds_Interface
EMVPRFL
EMV_Card_Vrfrn_Results_Status
EMV_Iss_Auth_Dta
EMV_Reason_Online_Code_Status
EMV_Script_Context
EMV_Security

EMV_Terminal_Vrfrn_Results_Status
Environment
EPP_Serial_Number
EPSNET_Inst
EPSNET_Interface
Equens_Instrm_Typ_Extrn
Equens_Instrm_Typ_Intrn
Equens_Interface
ERSB_Interface
ESAPDT
ESATDD1
ESATDD2
ESATDS1
Euro_Opted_Currency
Event
Event_Document
Exported_Operator_Documentation
FCSHPRFL
Fees
Fifth_Third_Intf
file_part_catalog
file_part_fields
file_part_list
File_Update_Route
FIS_Interface
FPID_History
FPS_Batch_Config
FPS_Batch_Control
FPS_Cutover
FPS_Member
FPS_Payment_Pri_Group
FPS_Payment_Submission
FPS_Payment_Typ
FPS_Queue_Assign
FPS_Queue_Profile
Futr_Key

GICC_Acq_SGN
GICC_Channel
GICC_Interface
GICC_Iss_SGN
GISO_ACQ_MSG_HND
GISO_CRD_ACPT_RT
GISO_Interface
GISO_IN_MSG_DEF
GISO_ISS_MSG_HND
GISO_OUT_MSG_DEF
HISO87_Interface
HISO87_Proc_Txn
HISO93_Interface
Holiday
Host_Public_Key_Security
Host_Public_Key_Security_Primary
Host_Public_Key_Security_Second
HPDH_Configuration
HPDH_NAC_Term
HPDH_NMS_Term
HPRPRFL
IBM_DES
Identikey
IFXDATA
IFX_Host_Action_Code_Int_Ext
IFX_Host_Interface
Ind_Sort_Code_Directory
Institution
Instrm_Status_Extrn_to_Intrn
Instrm_Status_Intrn_to_Extrn
Instrm_Typ_Extrn_to_Intrn
Instrm_Typ_Intrn_to_Extrn
INSTRUMENT_TYPE
Instrum_Typ_Interchange_Rel
Interac_Base
Interac_Interface

Interchange_Prefix
Interchange_Security
Interchange_Security_Future
Interface
Interface_FPS
Interface_Manager
Interface_SAF
Interface_Station
Interface_Terminal
Interface_WPS
ISO_Field
ISO_FLD_DEFN
ISO_Message
ISO_PROC_CODE
Issuer_Profile_Map
Issuer_Route_Profile
Issuer_Txn_Allowed
ITMRPRFL
JCB_Institution
JCB_Interface
Journal
Journal_Continuation
Journal_Data_Suppression
Journal_Key_Seq
Journal_Key_Seq2
Journal_Profile_Group
Journal_Profile_Group_Assign
Journal_Query_Config
Journal_Query_Config_Output
Journal_Query_Output_Assign
Journal_Query_Output_Map
Journal_Query_Position_Info
Key_Map
Key_Token
Limits
Linked_Currency

LIS5_Interface
LTMRPRFL
MACPRFL
MDS_Brand_Rel
MDS_Institution
MDS_Interface
Merchant
Merchant_Channel_Profile
Merchant_Delivery_Channel
Merchant_Delivery_Channel_Profil
Merch_Instr_Typ_Relation
NCR_PIN_Verification
Netwk_Brand_Instrm_ReIn
NYCE_Institution
NYCE_Interface
OLTP_Warmboot
OPERID
OPTRCPT
PBAL_Impacts
Perusal_Script
Positive_Balance
POS_TC_Proc_Code
Prefix
Prefix_Block
Presto_Interface
Pre_Auth_Hold
PRICE_Interface
PRM_Interface
Proc_Code_ATM_TC
PROC_CODE_ISO
Proc_Code_POS_TC
Pulse_Institution
Pulse_Interface
Pulse_Switch_Date
RCPTRQRD
Real_Time_Feed_Config

Reason_Online_Code_Description
RECEIPT
Referral
Route
RQUID
Script
Script_Configuration
Script_Source
Security_Device_Config
SPAN2_Interface
SPAN2_Interface_Terminal
SPDH_act_cde_descr
SPDH_Configuration
SPDH_ISO_Response_Code
SPDH_ISO_Response_Text
SPDH_Message
SPDH_opt_resp_data
SPDH_txn_cde_descr
SRCHPRFL
Star_Institution
Star_Interface
STAR_Network_Rel
Star_NE_Network_Rel
STMPPRFL
Stop_Payment
Surcharge
Surcharge_Country_Code
SVS_Interface
SVS_Mrch_Num
System_Algorithm_Config
System_Prefix
TBP_Daily
TERM_LN_FIID_MAP
Token_Config
Token_Id_List
Totals_Configuration

	Totals_Tag_Documentation
	Trace_Config
	Trace_Filter
	Transport_Key
	UAE_Interface
	Usage
	User_Perusal_Prfl_Relation
	Visa_Brand_Rel
	Visa_DPS_Institution
	Visa_DPS_Interface
	Visa_Institution
	Visa_Interface
	Visa_PVV
	ZKA_KGK
fm_ts_aud_saf	Audit_Store_and_Forward.xml
fm_ts_cmpl	Script_Configuration
fm_ts_config	Script_Configuration
fm_ts_saf	Store_and_Forward.xml
fm_ts_script_source	Script_Configuration
fm_ts_updt	OLTP_Warmboot
fncl_cutover_strt_tim	Merchant
	Merchant_OLTP
forced_cutover_aud_ind	ATM_DS1
	ATM_DS1_OLTP
force_onl_fallback_chk	Prefix
	Prefix_OLTP
fpid_hist_asgn_1	Interface_FPS
	Interface_FPS_OLTP
fpid_hist_asgn_2	Interface_FPS
	Interface_FPS_OLTP
fpid_hist_asgn_3	Interface_FPS
	Interface_FPS_OLTP
fpid_hist_asgn_4	Interface_FPS
	Interface_FPS_OLTP
fpid_hist_asgn_5	Interface_FPS
	Interface_FPS_OLTP

fpid_hist_asgn_6	Interface_FPS
	Interface_FPS_OLTP
fpid_hist_asgn_7	Interface_FPS
	Interface_FPS_OLTP
fps_accts_numbered_flg	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_acct_typ	FPS_Payment_Submission
fps_agency_typ	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_bnk_id	FPS_Member.xml
	FPS_Member_OLTP.xml
	Interface_WPS
	Interface_WPS_OLTP
fps_bnk_id_hndl	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_bnk_id_setl	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_chrg_info	FPS_Payment_Submission
fps_clos_dat	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_conn_typ_hndl	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_conn_typ_setl	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_local	FPS_Member
	FPS_Member_OLTP
fps_lst_chng_dat	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_num_ref	FPS_Payment_Submission
fps_pmnt_purpose	FPS_Payment_Submission
fps_pmnt_subtyp	FPS_Payment_Submission
fps_pmnt_typ	FPS_Payment_Submission
fps_q_enable	FPS_Queue_Manager_OLTP
	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP
	Interface_FPS

	Interface_FPS_OLTP
fps_q_prfl	FPS_Member
	FPS_Member_OLTP
	FPS_Queue_Assign.xml
	FPS_Queue_Assign_OLTP.xml
	FPS_Queue_Manager_OLTP.xml
	FPS_Queue_Profile.xml
	FPS_Queue_Profile_OLTP
fps_rcv_enty	FPS_Payment_Submission
fps_redir_flg	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_redir_sort_cde	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fps_ref_info	FPS_Payment_Submission
fps_sbmt_dsrc_asgn	FPS_Batch_Control
fps_send_enty	FPS_Payment_Submission
fps_setl_mbr	FPS_Member
	FPS_Member_OLTP
fps_stat	FPS_Member
	FPS_Member_OLTP
fps_stat_iscd	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
fraud_opt	Prefix
	Prefix_OLTP
frd_aba	Pulse_Institution
	Pulse_Institution_OLTP
	Star_Institution
	Star_Institution_OLTP
fri_peak1_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
fri_peak1_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
fri_peak1_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
fri_peak2_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP

fri_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
fri_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
fri_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
FromAcntTypeCd	RECEIPT.xml
frwd_cntry_cde	Interface
	Interface_Issuer_OLTP
frwd_id_cde	Interface
	Interface_Issuer_OLTP
frwd_ovrrd_inst_id_flg	BIC_Interface
	BIC_Interface_OLTP
FstCsh1AmntNum	FCSHPRFL
FstCsh1CrncCd	FCSHPRFL
FstCsh2AmntNum	FCSHPRFL
FstCsh2CrncCd	FCSHPRFL
FstCsh3AmntNum	FCSHPRFL
FstCsh3CrncCd	FCSHPRFL
FstCsh4AmntNum	FCSHPRFL
FstCsh4CrncCd	FCSHPRFL
FstCsh5AmntNum	FCSHPRFL
FstCsh5CrncCd	FCSHPRFL
FstCsh6AmntNum	FCSHPRFL
FstCsh6CrncCd	FCSHPRFL
FstCsh7AmntNum	FCSHPRFL
FstCsh7CrncCd	FCSHPRFL
FstCsh8AmntNum	FCSHPRFL
FstCsh8CrncCd	FCSHPRFL
FstCshPrflTx	ESATDS1
	FCSHPRFL.xml
FtnsAryTx	ESATDD1
full_bnk_nam1	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
full_bnk_nam2	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP

FunctionID	Functs.xml
	TaskFncs.xml
futr_cnt	Journal_Profile_Group
	Journal_Profile_Group_OLTP
FVID	FldVals
	FIXFldVI.xml
f_i_fld	dal_tbl
gen_ssid	Event.xml
	Event_OLTP.xml
GnrtBldVsnTx	EVNTLOG
GnrtIDTx	EVNTLOG
GroupIDTx	ATMCNFG.xml
	ESATDD1
	ESATDS1
GrpIDTx	OPERID.xml
gtwy_prcsr_id	Circuit_Interface
	Circuit_Interface_OLTP
gtwy_prcsr_pswd	Circuit_Interface
	Circuit_Interface_OLTP
hardware_array	ATM_DD1
hash_key	IBM_Context.xml
hash_val	FPID_History.xml
	FPS_Queue_Assign.xml
	FPS_Queue_Assign_OLTP
hdr_data_prfx	HISO87_Interface
	HISO87_Interface_OLTP
hdr_ims_cics_flg	HISO87_Interface
	HISO87_Interface_OLTP
hdr_script_nam	Perusal_Script
	Perusal_Script_OLTP
hdr_trlr_typ	Journal_Query_Config_Output
hdwr_mdI	Security_Device_Config
high_prfx	System_Algorithm_Config.xml
	System_Algorithm_Config_OLTP
hi_chk_num	Stop_Payment.xml
HldyPrfITx	ESATDS1

hld_amt_1	Pre_Auth_Hold
hld_amt_10	Pre_Auth_Hold
hld_amt_11	Pre_Auth_Hold
hld_amt_12	Pre_Auth_Hold
hld_amt_13	Pre_Auth_Hold
hld_amt_14	Pre_Auth_Hold
hld_amt_15	Pre_Auth_Hold
hld_amt_16	Pre_Auth_Hold
hld_amt_17	Pre_Auth_Hold
hld_amt_18	Pre_Auth_Hold
hld_amt_19	Pre_Auth_Hold
hld_amt_2	Pre_Auth_Hold
hld_amt_20	Pre_Auth_Hold
hld_amt_21	Pre_Auth_Hold
hld_amt_22	Pre_Auth_Hold
hld_amt_23	Pre_Auth_Hold
hld_amt_24	Pre_Auth_Hold
hld_amt_25	Pre_Auth_Hold
hld_amt_26	Pre_Auth_Hold
hld_amt_27	Pre_Auth_Hold
hld_amt_28	Pre_Auth_Hold
hld_amt_29	Pre_Auth_Hold
hld_amt_3	Pre_Auth_Hold
hld_amt_30	Pre_Auth_Hold
hld_amt_31	Pre_Auth_Hold
hld_amt_32	Pre_Auth_Hold
hld_amt_33	Pre_Auth_Hold
hld_amt_34	Pre_Auth_Hold
hld_amt_35	Pre_Auth_Hold
hld_amt_36	Pre_Auth_Hold
hld_amt_37	Pre_Auth_Hold
hld_amt_38	Pre_Auth_Hold
hld_amt_39	Pre_Auth_Hold
hld_amt_4	Pre_Auth_Hold
hld_amt_40	Pre_Auth_Hold
hld_amt_41	Pre_Auth_Hold

hld_amt_42	Pre_Auth_Hold
hld_amt_43	Pre_Auth_Hold
hld_amt_44	Pre_Auth_Hold
hld_amt_45	Pre_Auth_Hold
hld_amt_46	Pre_Auth_Hold
hld_amt_47	Pre_Auth_Hold
hld_amt_48	Pre_Auth_Hold
hld_amt_49	Pre_Auth_Hold
hld_amt_5	Pre_Auth_Hold
hld_amt_50	Pre_Auth_Hold
hld_amt_51	Pre_Auth_Hold
hld_amt_52	Pre_Auth_Hold
hld_amt_53	Pre_Auth_Hold
hld_amt_54	Pre_Auth_Hold
hld_amt_55	Pre_Auth_Hold
hld_amt_56	Pre_Auth_Hold
hld_amt_57	Pre_Auth_Hold
hld_amt_58	Pre_Auth_Hold
hld_amt_59	Pre_Auth_Hold
hld_amt_6	Pre_Auth_Hold
hld_amt_60	Pre_Auth_Hold
hld_amt_61	Pre_Auth_Hold
hld_amt_62	Pre_Auth_Hold
hld_amt_63	Pre_Auth_Hold
hld_amt_64	Pre_Auth_Hold
hld_amt_65	Pre_Auth_Hold
hld_amt_66	Pre_Auth_Hold
hld_amt_67	Pre_Auth_Hold
hld_amt_68	Pre_Auth_Hold
hld_amt_69	Pre_Auth_Hold
hld_amt_7	Pre_Auth_Hold
hld_amt_70	Pre_Auth_Hold
hld_amt_8	Pre_Auth_Hold
hld_amt_9	Pre_Auth_Hold
hld_bal_chk	Prefix
	Prefix_OLTP

hld_crncy_cde_1	Pre_Auth_Hold
hld_crncy_cde_10	Pre_Auth_Hold
hld_crncy_cde_11	Pre_Auth_Hold
hld_crncy_cde_12	Pre_Auth_Hold
hld_crncy_cde_13	Pre_Auth_Hold
hld_crncy_cde_14	Pre_Auth_Hold
hld_crncy_cde_15	Pre_Auth_Hold
hld_crncy_cde_16	Pre_Auth_Hold
hld_crncy_cde_17	Pre_Auth_Hold
hld_crncy_cde_18	Pre_Auth_Hold
hld_crncy_cde_19	Pre_Auth_Hold
hld_crncy_cde_2	Pre_Auth_Hold
hld_crncy_cde_20	Pre_Auth_Hold
hld_crncy_cde_21	Pre_Auth_Hold
hld_crncy_cde_22	Pre_Auth_Hold
hld_crncy_cde_23	Pre_Auth_Hold
hld_crncy_cde_24	Pre_Auth_Hold
hld_crncy_cde_25	Pre_Auth_Hold
hld_crncy_cde_26	Pre_Auth_Hold
hld_crncy_cde_27	Pre_Auth_Hold
hld_crncy_cde_28	Pre_Auth_Hold
hld_crncy_cde_29	Pre_Auth_Hold
hld_crncy_cde_3	Pre_Auth_Hold
hld_crncy_cde_30	Pre_Auth_Hold
hld_crncy_cde_31	Pre_Auth_Hold
hld_crncy_cde_32	Pre_Auth_Hold
hld_crncy_cde_33	Pre_Auth_Hold
hld_crncy_cde_34	Pre_Auth_Hold
hld_crncy_cde_35	Pre_Auth_Hold
hld_crncy_cde_36	Pre_Auth_Hold
hld_crncy_cde_37	Pre_Auth_Hold
hld_crncy_cde_38	Pre_Auth_Hold
hld_crncy_cde_39	Pre_Auth_Hold
hld_crncy_cde_4	Pre_Auth_Hold
hld_crncy_cde_40	Pre_Auth_Hold
hld_crncy_cde_41	Pre_Auth_Hold

hld_crncy_cde_42	Pre_Auth_Hold
hld_crncy_cde_43	Pre_Auth_Hold
hld_crncy_cde_44	Pre_Auth_Hold
hld_crncy_cde_45	Pre_Auth_Hold
hld_crncy_cde_46	Pre_Auth_Hold
hld_crncy_cde_47	Pre_Auth_Hold
hld_crncy_cde_48	Pre_Auth_Hold
hld_crncy_cde_49	Pre_Auth_Hold
hld_crncy_cde_5	Pre_Auth_Hold
hld_crncy_cde_50	Pre_Auth_Hold
hld_crncy_cde_51	Pre_Auth_Hold
hld_crncy_cde_52	Pre_Auth_Hold
hld_crncy_cde_53	Pre_Auth_Hold
hld_crncy_cde_54	Pre_Auth_Hold
hld_crncy_cde_55	Pre_Auth_Hold
hld_crncy_cde_56	Pre_Auth_Hold
hld_crncy_cde_57	Pre_Auth_Hold
hld_crncy_cde_58	Pre_Auth_Hold
hld_crncy_cde_59	Pre_Auth_Hold
hld_crncy_cde_6	Pre_Auth_Hold
hld_crncy_cde_60	Pre_Auth_Hold
hld_crncy_cde_61	Pre_Auth_Hold
hld_crncy_cde_62	Pre_Auth_Hold
hld_crncy_cde_63	Pre_Auth_Hold
hld_crncy_cde_64	Pre_Auth_Hold
hld_crncy_cde_65	Pre_Auth_Hold
hld_crncy_cde_66	Pre_Auth_Hold
hld_crncy_cde_67	Pre_Auth_Hold
hld_crncy_cde_68	Pre_Auth_Hold
hld_crncy_cde_69	Pre_Auth_Hold
hld_crncy_cde_7	Pre_Auth_Hold
hld_crncy_cde_70	Pre_Auth_Hold
hld_crncy_cde_8	Pre_Auth_Hold
hld_crncy_cde_9	Pre_Auth_Hold
hld_exp_ts_1	Pre_Auth_Hold
hld_exp_ts_10	Pre_Auth_Hold

hld_exp_ts_11	Pre_Auth_Hold
hld_exp_ts_12	Pre_Auth_Hold
hld_exp_ts_13	Pre_Auth_Hold
hld_exp_ts_14	Pre_Auth_Hold
hld_exp_ts_15	Pre_Auth_Hold
hld_exp_ts_16	Pre_Auth_Hold
hld_exp_ts_17	Pre_Auth_Hold
hld_exp_ts_18	Pre_Auth_Hold
hld_exp_ts_19	Pre_Auth_Hold
hld_exp_ts_2	Pre_Auth_Hold
hld_exp_ts_20	Pre_Auth_Hold
hld_exp_ts_21	Pre_Auth_Hold
hld_exp_ts_22	Pre_Auth_Hold
hld_exp_ts_23	Pre_Auth_Hold
hld_exp_ts_24	Pre_Auth_Hold
hld_exp_ts_25	Pre_Auth_Hold
hld_exp_ts_26	Pre_Auth_Hold
hld_exp_ts_27	Pre_Auth_Hold
hld_exp_ts_28	Pre_Auth_Hold
hld_exp_ts_29	Pre_Auth_Hold
hld_exp_ts_3	Pre_Auth_Hold
hld_exp_ts_30	Pre_Auth_Hold
hld_exp_ts_31	Pre_Auth_Hold
hld_exp_ts_32	Pre_Auth_Hold
hld_exp_ts_33	Pre_Auth_Hold
hld_exp_ts_34	Pre_Auth_Hold
hld_exp_ts_35	Pre_Auth_Hold
hld_exp_ts_36	Pre_Auth_Hold
hld_exp_ts_37	Pre_Auth_Hold
hld_exp_ts_38	Pre_Auth_Hold
hld_exp_ts_39	Pre_Auth_Hold
hld_exp_ts_4	Pre_Auth_Hold
hld_exp_ts_40	Pre_Auth_Hold
hld_exp_ts_41	Pre_Auth_Hold
hld_exp_ts_42	Pre_Auth_Hold
hld_exp_ts_43	Pre_Auth_Hold

hld_exp_ts_44	Pre_Auth_Hold
hld_exp_ts_45	Pre_Auth_Hold
hld_exp_ts_46	Pre_Auth_Hold
hld_exp_ts_47	Pre_Auth_Hold
hld_exp_ts_48	Pre_Auth_Hold
hld_exp_ts_49	Pre_Auth_Hold
hld_exp_ts_5	Pre_Auth_Hold
hld_exp_ts_50	Pre_Auth_Hold
hld_exp_ts_51	Pre_Auth_Hold
hld_exp_ts_52	Pre_Auth_Hold
hld_exp_ts_53	Pre_Auth_Hold
hld_exp_ts_54	Pre_Auth_Hold
hld_exp_ts_55	Pre_Auth_Hold
hld_exp_ts_56	Pre_Auth_Hold
hld_exp_ts_57	Pre_Auth_Hold
hld_exp_ts_58	Pre_Auth_Hold
hld_exp_ts_59	Pre_Auth_Hold
hld_exp_ts_6	Pre_Auth_Hold
hld_exp_ts_60	Pre_Auth_Hold
hld_exp_ts_61	Pre_Auth_Hold
hld_exp_ts_62	Pre_Auth_Hold
hld_exp_ts_63	Pre_Auth_Hold
hld_exp_ts_64	Pre_Auth_Hold
hld_exp_ts_65	Pre_Auth_Hold
hld_exp_ts_66	Pre_Auth_Hold
hld_exp_ts_67	Pre_Auth_Hold
hld_exp_ts_68	Pre_Auth_Hold
hld_exp_ts_69	Pre_Auth_Hold
hld_exp_ts_7	Pre_Auth_Hold
hld_exp_ts_70	Pre_Auth_Hold
hld_exp_ts_8	Pre_Auth_Hold
hld_exp_ts_9	Pre_Auth_Hold
hld_id_1	Pre_Auth_Hold
hld_id_10	Pre_Auth_Hold
hld_id_11	Pre_Auth_Hold
hld_id_12	Pre_Auth_Hold

hld_id_13	Pre_Auth_Hold
hld_id_14	Pre_Auth_Hold
hld_id_15	Pre_Auth_Hold
hld_id_16	Pre_Auth_Hold
hld_id_17	Pre_Auth_Hold
hld_id_18	Pre_Auth_Hold
hld_id_19	Pre_Auth_Hold
hld_id_2	Pre_Auth_Hold
hld_id_20	Pre_Auth_Hold
hld_id_21	Pre_Auth_Hold
hld_id_22	Pre_Auth_Hold
hld_id_23	Pre_Auth_Hold
hld_id_24	Pre_Auth_Hold
hld_id_25	Pre_Auth_Hold
hld_id_26	Pre_Auth_Hold
hld_id_27	Pre_Auth_Hold
hld_id_28	Pre_Auth_Hold
hld_id_29	Pre_Auth_Hold
hld_id_3	Pre_Auth_Hold
hld_id_30	Pre_Auth_Hold
hld_id_31	Pre_Auth_Hold
hld_id_32	Pre_Auth_Hold
hld_id_33	Pre_Auth_Hold
hld_id_34	Pre_Auth_Hold
hld_id_35	Pre_Auth_Hold
hld_id_36	Pre_Auth_Hold
hld_id_37	Pre_Auth_Hold
hld_id_38	Pre_Auth_Hold
hld_id_39	Pre_Auth_Hold
hld_id_4	Pre_Auth_Hold
hld_id_40	Pre_Auth_Hold
hld_id_41	Pre_Auth_Hold
hld_id_42	Pre_Auth_Hold
hld_id_43	Pre_Auth_Hold
hld_id_44	Pre_Auth_Hold
hld_id_45	Pre_Auth_Hold

hld_id_46	Pre_Auth_Hold
hld_id_47	Pre_Auth_Hold
hld_id_48	Pre_Auth_Hold
hld_id_49	Pre_Auth_Hold
hld_id_5	Pre_Auth_Hold
hld_id_50	Pre_Auth_Hold
hld_id_51	Pre_Auth_Hold
hld_id_52	Pre_Auth_Hold
hld_id_53	Pre_Auth_Hold
hld_id_54	Pre_Auth_Hold
hld_id_55	Pre_Auth_Hold
hld_id_56	Pre_Auth_Hold
hld_id_57	Pre_Auth_Hold
hld_id_58	Pre_Auth_Hold
hld_id_59	Pre_Auth_Hold
hld_id_6	Pre_Auth_Hold
hld_id_60	Pre_Auth_Hold
hld_id_61	Pre_Auth_Hold
hld_id_62	Pre_Auth_Hold
hld_id_63	Pre_Auth_Hold
hld_id_64	Pre_Auth_Hold
hld_id_65	Pre_Auth_Hold
hld_id_66	Pre_Auth_Hold
hld_id_67	Pre_Auth_Hold
hld_id_68	Pre_Auth_Hold
hld_id_69	Pre_Auth_Hold
hld_id_7	Pre_Auth_Hold
hld_id_70	Pre_Auth_Hold
hld_id_8	Pre_Auth_Hold
hld_id_9	Pre_Auth_Hold
hld_local_txn_ts_1	Pre_Auth_Hold
hld_local_txn_ts_10	Pre_Auth_Hold
hld_local_txn_ts_11	Pre_Auth_Hold
hld_local_txn_ts_12	Pre_Auth_Hold
hld_local_txn_ts_13	Pre_Auth_Hold
hld_local_txn_ts_14	Pre_Auth_Hold

hld_local_txn_ts_15	Pre_Auth_Hold
hld_local_txn_ts_16	Pre_Auth_Hold
hld_local_txn_ts_17	Pre_Auth_Hold
hld_local_txn_ts_18	Pre_Auth_Hold
hld_local_txn_ts_19	Pre_Auth_Hold
hld_local_txn_ts_2	Pre_Auth_Hold
hld_local_txn_ts_20	Pre_Auth_Hold
hld_local_txn_ts_21	Pre_Auth_Hold
hld_local_txn_ts_22	Pre_Auth_Hold
hld_local_txn_ts_23	Pre_Auth_Hold
hld_local_txn_ts_24	Pre_Auth_Hold
hld_local_txn_ts_25	Pre_Auth_Hold
hld_local_txn_ts_26	Pre_Auth_Hold
hld_local_txn_ts_27	Pre_Auth_Hold
hld_local_txn_ts_28	Pre_Auth_Hold
hld_local_txn_ts_29	Pre_Auth_Hold
hld_local_txn_ts_3	Pre_Auth_Hold
hld_local_txn_ts_30	Pre_Auth_Hold
hld_local_txn_ts_31	Pre_Auth_Hold
hld_local_txn_ts_32	Pre_Auth_Hold
hld_local_txn_ts_33	Pre_Auth_Hold
hld_local_txn_ts_34	Pre_Auth_Hold
hld_local_txn_ts_35	Pre_Auth_Hold
hld_local_txn_ts_36	Pre_Auth_Hold
hld_local_txn_ts_37	Pre_Auth_Hold
hld_local_txn_ts_38	Pre_Auth_Hold
hld_local_txn_ts_39	Pre_Auth_Hold
hld_local_txn_ts_4	Pre_Auth_Hold
hld_local_txn_ts_40	Pre_Auth_Hold
hld_local_txn_ts_41	Pre_Auth_Hold
hld_local_txn_ts_42	Pre_Auth_Hold
hld_local_txn_ts_43	Pre_Auth_Hold
hld_local_txn_ts_44	Pre_Auth_Hold
hld_local_txn_ts_45	Pre_Auth_Hold
hld_local_txn_ts_46	Pre_Auth_Hold
hld_local_txn_ts_47	Pre_Auth_Hold

hld_local_txn_ts_48	Pre_Auth_Hold
hld_local_txn_ts_49	Pre_Auth_Hold
hld_local_txn_ts_5	Pre_Auth_Hold
hld_local_txn_ts_50	Pre_Auth_Hold
hld_local_txn_ts_51	Pre_Auth_Hold
hld_local_txn_ts_52	Pre_Auth_Hold
hld_local_txn_ts_53	Pre_Auth_Hold
hld_local_txn_ts_54	Pre_Auth_Hold
hld_local_txn_ts_55	Pre_Auth_Hold
hld_local_txn_ts_56	Pre_Auth_Hold
hld_local_txn_ts_57	Pre_Auth_Hold
hld_local_txn_ts_58	Pre_Auth_Hold
hld_local_txn_ts_59	Pre_Auth_Hold
hld_local_txn_ts_6	Pre_Auth_Hold
hld_local_txn_ts_60	Pre_Auth_Hold
hld_local_txn_ts_61	Pre_Auth_Hold
hld_local_txn_ts_62	Pre_Auth_Hold
hld_local_txn_ts_63	Pre_Auth_Hold
hld_local_txn_ts_64	Pre_Auth_Hold
hld_local_txn_ts_65	Pre_Auth_Hold
hld_local_txn_ts_66	Pre_Auth_Hold
hld_local_txn_ts_67	Pre_Auth_Hold
hld_local_txn_ts_68	Pre_Auth_Hold
hld_local_txn_ts_69	Pre_Auth_Hold
hld_local_txn_ts_7	Pre_Auth_Hold
hld_local_txn_ts_70	Pre_Auth_Hold
hld_local_txn_ts_8	Pre_Auth_Hold
hld_local_txn_ts_9	Pre_Auth_Hold
hld_typ_1	Pre_Auth_Hold
hld_typ_10	Pre_Auth_Hold
hld_typ_11	Pre_Auth_Hold
hld_typ_12	Pre_Auth_Hold
hld_typ_13	Pre_Auth_Hold
hld_typ_14	Pre_Auth_Hold
hld_typ_15	Pre_Auth_Hold
hld_typ_16	Pre_Auth_Hold

hld_typ_17	Pre_Auth_Hold
hld_typ_18	Pre_Auth_Hold
hld_typ_19	Pre_Auth_Hold
hld_typ_2	Pre_Auth_Hold
hld_typ_20	Pre_Auth_Hold
hld_typ_21	Pre_Auth_Hold
hld_typ_22	Pre_Auth_Hold
hld_typ_23	Pre_Auth_Hold
hld_typ_24	Pre_Auth_Hold
hld_typ_25	Pre_Auth_Hold
hld_typ_26	Pre_Auth_Hold
hld_typ_27	Pre_Auth_Hold
hld_typ_28	Pre_Auth_Hold
hld_typ_29	Pre_Auth_Hold
hld_typ_3	Pre_Auth_Hold
hld_typ_30	Pre_Auth_Hold
hld_typ_31	Pre_Auth_Hold
hld_typ_32	Pre_Auth_Hold
hld_typ_33	Pre_Auth_Hold
hld_typ_34	Pre_Auth_Hold
hld_typ_35	Pre_Auth_Hold
hld_typ_36	Pre_Auth_Hold
hld_typ_37	Pre_Auth_Hold
hld_typ_38	Pre_Auth_Hold
hld_typ_39	Pre_Auth_Hold
hld_typ_4	Pre_Auth_Hold
hld_typ_40	Pre_Auth_Hold
hld_typ_41	Pre_Auth_Hold
hld_typ_42	Pre_Auth_Hold
hld_typ_43	Pre_Auth_Hold
hld_typ_44	Pre_Auth_Hold
hld_typ_45	Pre_Auth_Hold
hld_typ_46	Pre_Auth_Hold
hld_typ_47	Pre_Auth_Hold
hld_typ_48	Pre_Auth_Hold
hld_typ_49	Pre_Auth_Hold

hld_typ_5	Pre_Auth_Hold
hld_typ_50	Pre_Auth_Hold
hld_typ_51	Pre_Auth_Hold
hld_typ_52	Pre_Auth_Hold
hld_typ_53	Pre_Auth_Hold
hld_typ_54	Pre_Auth_Hold
hld_typ_55	Pre_Auth_Hold
hld_typ_56	Pre_Auth_Hold
hld_typ_57	Pre_Auth_Hold
hld_typ_58	Pre_Auth_Hold
hld_typ_59	Pre_Auth_Hold
hld_typ_6	Pre_Auth_Hold
hld_typ_60	Pre_Auth_Hold
hld_typ_61	Pre_Auth_Hold
hld_typ_62	Pre_Auth_Hold
hld_typ_63	Pre_Auth_Hold
hld_typ_64	Pre_Auth_Hold
hld_typ_65	Pre_Auth_Hold
hld_typ_66	Pre_Auth_Hold
hld_typ_67	Pre_Auth_Hold
hld_typ_68	Pre_Auth_Hold
hld_typ_69	Pre_Auth_Hold
hld_typ_7	Pre_Auth_Hold
hld_typ_70	Pre_Auth_Hold
hld_typ_8	Pre_Auth_Hold
hld_typ_9	Pre_Auth_Hold
hndlr_repeat_msg	ABI_Interface
	ABI_Interface_OLTP
hol_dat	Holiday.xml
	Holiday_OLTP.xml
hol_dat1	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP

hol_dat10	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat11	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat12	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat13	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat14	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat15	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP

hol_dat16	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat17	Institution
	Institution_OLTP
hol_dat18	Institution
	Institution_OLTP
hol_dat19	Institution
	Institution_OLTP
hol_dat2	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat20	Institution
	Institution_OLTP
hol_dat3	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat4	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
hol_dat5	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP

hol_dat6	Interface_Issuer_OLTP
	Interface_OLTP
	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
hol_dat7	Interface_Issuer_OLTP
	Interface_OLTP
	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
hol_dat8	Interface_Issuer_OLTP
	Interface_OLTP
	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
hol_dat9	Interface_Issuer_OLTP
	Interface_OLTP
	Institution
	Institution_OLTP
	Interface
	Interface_Acquirer_OLTP
hol_dat_prfl	Interface_Issuer_OLTP
	Interface_OLTP
	Holiday.xml
	Holiday_OLTP.xml
	Journal_Query_Config
	ATM_PEAK_LOAD
hol_peak1_end_tm	ATM_PEAK_LOAD_OLTP
	ATM_PEAK_LOAD
hol_peak1_load_grps	ATM_PEAK_LOAD_OLTP
	ATM_PEAK_LOAD
hol_peak1_strt_tm	ATM_PEAK_LOAD_OLTP
	ATM_PEAK_LOAD
hol_peak2_end_tm	ATM_PEAK_LOAD_OLTP
	ATM_PEAK_LOAD

	ATM_PEAK_LOAD_OLTP
hol_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
hol_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
hol_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
HomePage	WEBAPPS
HomeSiteInd	ESATDS1
home_phn	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
home_site_ind	ATM_DS1
	ATM_DS1_OLTP
	Merchant_Delivery_Channel
host_logon_typ	HISO87_Interface
	HISO87_Interface_OLTP
host_ntfy_msg_flg	HISO93_Interface
	HISO93_Interface_OLTP
host_rndm_nonce	Channel_Public_Key_Security
host_sync_flg	HISO93_Interface
	HISO93_Interface_OLTP
Hpr1BgnBalNum	CTVRSF
Hpr1BgnCntNum	ESAPDT
	ESATDD1
Hpr1CntDcrsNum	ESAPDT
	ESATDD1
Hpr1CntIncrNum	ESAPDT
	ESATDD1
Hpr1CntnTx	CTVRSF
	HPRPRFL
Hpr1CntOtNum	ESAPDT
	ESATDD1
Hpr1CrncCd	HPRPRFL
Hpr1CrncCdTx	CTVRSF
Hpr1CstMpTx	HPRPRFL
Hpr1DecrBalNum	CTVRSF

List of data elements

Hpr1DspyOrdrNum	HPRPRFL
Hpr1EndBalNum	CTVRSAF
Hpr1EndCntNum	ESAPDT
	ESATDD1
Hpr1IncrBalNum	CTVRSAF
Hpr1OutBalNum	CTVRSAF
Hpr1StndBgnCntNum	HPRPRFL
Hpr1UntValNum	HPRPRFL
hpr1_amt_beg	ATM_DD1
	ATM_PREV_TTL
hpr1_amt_decr	ATM_DD1
	ATM_PREV_TTL
hpr1_amt_end	ATM_DD1
	ATM_PREV_TTL
hpr1_amt_incr	ATM_DD1
	ATM_PREV_TTL
hpr1_amt_out	ATM_DD1
	ATM_PREV_TTL
hpr1_cassette_map	ATM_HOPR
	ATM_HOPR_OLTP
hpr1_contents	ATM_HOPR
	ATM_HOPR_OLTP
hpr1_cur_cde	ATM_DD1
	ATM_HOPR
	ATM_HOPR_OLTP
	ATM_PREV_TTL
hpr1_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
hpr1_mcur_disp_ord	ATM_HOPR
	ATM_HOPR_OLTP
hpr1_nval_thrshld	ATM_HOPR
	ATM_HOPR_OLTP
hpr1_stnd_beg_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr1_stop_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP

hpr1_strt_disp_amt	ATM_HOPR ATM_HOPR_OLTP
hpr1_threshold	ATM_HOPR ATM_HOPR_OLTP
hpr1_unit_val	ATM_HOPR ATM_HOPR_OLTP
Hpr2BgnBalNum	CTVRSAF
Hpr2BgnCntNum	ESAPDT ESATDD1
Hpr2CntDcrsNum	ESAPDT ESATDD1
Hpr2CntIncrNum	ESAPDT ESATDD1
Hpr2CntnTx	CTVRSAF HPRPRFL
Hpr2CntOtNum	ESAPDT ESATDD1
Hpr2CrncCd	HPRPRFL
Hpr2CrncCdTx	CTVRSAF
Hpr2CstMpTx	HPRPRFL
Hpr2DecrBalNum	CTVRSAF
Hpr2DspyOrdrNum	HPRPRFL
Hpr2EndBalNum	CTVRSAF
Hpr2EndCntNum	ESAPDT ESATDD1
Hpr2IncrBalNum	CTVRSAF
Hpr2OutBalNum	CTVRSAF
Hpr2StndBgnCntNum	HPRPRFL
Hpr2UntValNum	HPRPRFL
hpr2_amt_beg	ATM_DD1 ATM_PREV_TTL
hpr2_amt_decr	ATM_DD1 ATM_PREV_TTL
hpr2_amt_end	ATM_DD1 ATM_PREV_TTL
hpr2_amt_incr	ATM_DD1

	ATM_PREV_TTL
hpr2_amt_out	ATM_DD1
	ATM_PREV_TTL
hpr2_cassette_map	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_contents	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_cur_cde	ATM_DD1
	ATM_HOPR
	ATM_HOPR_OLTP
	ATM_PREV_TTL
hpr2_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_mcur_disp_ord	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_nval_thrshld	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_stnd_beg_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_stop_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_strt_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_threshold	ATM_HOPR
	ATM_HOPR_OLTP
hpr2_unit_val	ATM_HOPR
	ATM_HOPR_OLTP
Hpr3BgnBalNum	CTVRSF
Hpr3BgnCntNum	ESAPDT
	ESATDD1
Hpr3CntDcrsNum	ESAPDT
	ESATDD1
Hpr3CntIncrNum	ESAPDT
	ESATDD1
Hpr3CntnTx	CTVRSF
	HPRPRFL

Hpr3CntOtNum	ESAPDT
	ESATDD1
Hpr3CrncCd	HPRPRFL
Hpr3CrncCdTx	CTVRSF
Hpr3CstMpTx	HPRPRFL
Hpr3DecrBalNum	CTVRSF
Hpr3DspyOrdrNum	HPRPRFL
Hpr3EndBalNum	CTVRSF
Hpr3EndCntNum	ESAPDT
	ESATDD1
Hpr3IncrBalNum	CTVRSF
Hpr3OutBalNum	CTVRSF
Hpr3StndBgnCntNum	HPRPRFL
Hpr3UntValNum	HPRPRFL
hpr3_amt_beg	ATM_DD1
	ATM_PREV_TTL
hpr3_amt_decr	ATM_DD1
	ATM_PREV_TTL
hpr3_amt_end	ATM_DD1
	ATM_PREV_TTL
hpr3_amt_incr	ATM_DD1
	ATM_PREV_TTL
hpr3_amt_out	ATM_DD1
	ATM_PREV_TTL
hpr3_cassette_map	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_contents	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_cur_cde	ATM_DD1
	ATM_HOPR
	ATM_HOPR_OLTP
	ATM_PREV_TTL
hpr3_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_mcur_disp_ord	ATM_HOPR
	ATM_HOPR_OLTP

List of data elements

hpr3_nval_thrshld	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_stnd_beg_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_stop_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_strt_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_threshold	ATM_HOPR
	ATM_HOPR_OLTP
hpr3_unit_val	ATM_HOPR
	ATM_HOPR_OLTP
Hpr4BgnBalNum	CTVRSAF
Hpr4BgnCntNum	ESAPDT
	ESATDD1
Hpr4CntDcrsNum	ESAPDT
	ESATDD1
Hpr4CntIncrNum	ESAPDT
	ESATDD1
Hpr4CntnTx	CTVRSAF
	HPRPRFL
Hpr4CntOtNum	ESAPDT
	ESATDD1
Hpr4CrncCd	HPRPRFL
Hpr4CrncCdTx	CTVRSAF
Hpr4CstMpTx	HPRPRFL
Hpr4DecrBalNum	CTVRSAF
Hpr4DspyOrdrNum	HPRPRFL
Hpr4EndBalNum	CTVRSAF
Hpr4EndCntNum	ESAPDT
	ESATDD1
Hpr4IncrBalNum	CTVRSAF
Hpr4OutBalNum	CTVRSAF
Hpr4StndBgnCntNum	HPRPRFL
Hpr4UntValNum	HPRPRFL
hpr4_amt_beg	ATM_DD1

	ATM_PREV_TTL
hpr4_amt_decr	ATM_DD1
	ATM_PREV_TTL
hpr4_amt_end	ATM_DD1
	ATM_PREV_TTL
hpr4_amt_incr	ATM_DD1
	ATM_PREV_TTL
hpr4_amt_out	ATM_DD1
	ATM_PREV_TTL
hpr4_cassette_map	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_contents	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_cur_cde	ATM_DD1
	ATM_HOPR
	ATM_HOPR_OLTP
	ATM_PREV_TTL
hpr4_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_mcur_disp_ord	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_nval_thrshld	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_stnd_beg_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_stop_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_strt_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_threshold	ATM_HOPR
	ATM_HOPR_OLTP
hpr4_unit_val	ATM_HOPR
	ATM_HOPR_OLTP
Hpr5BgnBalNum	CTVRSF
Hpr5BgnCntNum	ESAPDT
	ESATDD1

List of data elements

Hpr5CntDcrsNum	ESAPDT ESATDD1
Hpr5CntIncrNum	ESAPDT ESATDD1
Hpr5CntnTx	CTVRSFAF HPRPRFL
Hpr5CntOtNum	ESAPDT ESATDD1
Hpr5CrncCd	HPRPRFL
Hpr5CrncCdTx	CTVRSFAF
Hpr5CstMpTx	HPRPRFL
Hpr5DecrBalNum	CTVRSFAF
Hpr5DspyOrdrNum	HPRPRFL
Hpr5EndBalNum	CTVRSFAF
Hpr5EndCntNum	ESAPDT ESATDD1
Hpr5IncrBalNum	CTVRSFAF
Hpr5OutBalNum	CTVRSFAF
Hpr5StndBgnCntNum	HPRPRFL
Hpr5UntValNum	HPRPRFL
hpr5_amt_beg	ATM_DD1 ATM_PREV_TTL
hpr5_amt_decr	ATM_DD1 ATM_PREV_TTL
hpr5_amt_end	ATM_DD1 ATM_PREV_TTL
hpr5_amt_incr	ATM_DD1 ATM_PREV_TTL
hpr5_amt_out	ATM_DD1 ATM_PREV_TTL
hpr5_cassette_map	ATM_HOPR ATM_HOPR_OLTP
hpr5_contents	ATM_HOPR ATM_HOPR_OLTP
hpr5_cur_cde	ATM_DD1 ATM_HOPR

	ATM_HOPR_OLTP
	ATM_PREV_TTL
hpr5_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
hpr5_mcur_disp_ord	ATM_HOPR
	ATM_HOPR_OLTP
hpr5_nval_thrshld	ATM_HOPR
	ATM_HOPR_OLTP
hpr5_stnd_beg_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr5_stop_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr5_strt_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr5_threshold	ATM_HOPR
	ATM_HOPR_OLTP
hpr5_unit_val	ATM_HOPR
	ATM_HOPR_OLTP
Hpr6BgnBalNum	CTVRSAF
Hpr6BgnCntNum	ESAPDT
	ESATDD1
Hpr6CntDcrsNum	ESAPDT
	ESATDD1
Hpr6CntIncrNum	ESAPDT
	ESATDD1
Hpr6CntnTx	CTVRSAF
	HPRPRFL
Hpr6CntOtNum	ESAPDT
	ESATDD1
Hpr6CrncCd	HPRPRFL
Hpr6CrncCdTx	CTVRSAF
Hpr6CstMpTx	HPRPRFL
Hpr6DecrBalNum	CTVRSAF
Hpr6DspyOrdrNum	HPRPRFL
Hpr6EndBalNum	CTVRSAF
Hpr6EndCntNum	ESAPDT

	ESATDD1
Hpr6IncrBalNum	CTVRSAP
Hpr6OutBalNum	CTVRSAP
Hpr6StndBgnCntNum	HPRPRFL
Hpr6UntValNum	HPRPRFL
hpr6_amt_beg	ATM_DD1
	ATM_PREV_TTL
hpr6_amt_decr	ATM_DD1
	ATM_PREV_TTL
hpr6_amt_end	ATM_DD1
	ATM_PREV_TTL
hpr6_amt_incr	ATM_DD1
	ATM_PREV_TTL
hpr6_amt_out	ATM_DD1
	ATM_PREV_TTL
hpr6_cassette_map	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_contents	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_cur_cde	ATM_DD1
	ATM_HOPR
	ATM_HOPR_OLTP
	ATM_PREV_TTL
hpr6_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_mcur_disp_ord	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_nval_thrshld	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_stnd_beg_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_stop_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_strt_disp_amt	ATM_HOPR
	ATM_HOPR_OLTP
hpr6_threshold	ATM_HOPR

	ATM_HOPR_OLTP
hpr6_unit_val	ATM_HOPR
	ATM_HOPR_OLTP
Hpr7BgnBalNum	CTVRSF
Hpr7BgnCntNum	ESAPDT
	ESATDD1
Hpr7CntDcrsNum	ESAPDT
	ESATDD1
Hpr7CntIncrNum	ESAPDT
	ESATDD1
Hpr7CntnTx	CTVRSF
	HPRPRFL
Hpr7CntOtNum	ESAPDT
	ESATDD1
Hpr7CrncCd	HPRPRFL
Hpr7CrncCdTx	CTVRSF
Hpr7CstMpTx	HPRPRFL
Hpr7DecrBalNum	CTVRSF
Hpr7DspyOrdrNum	HPRPRFL
Hpr7EndBalNum	CTVRSF
Hpr7EndCntNum	ESAPDT
	ESATDD1
Hpr7IncrBalNum	CTVRSF
Hpr7OutBalNum	CTVRSF
Hpr7StndBgnCntNum	HPRPRFL
Hpr7UntValNum	HPRPRFL
hpr7_amt_beg	ATM_DD1
	ATM_PREV_TTL
hpr7_amt_decr	ATM_DD1
	ATM_PREV_TTL
hpr7_amt_end	ATM_DD1
	ATM_PREV_TTL
hpr7_amt_incr	ATM_DD1
	ATM_PREV_TTL
hpr7_amt_out	ATM_DD1
	ATM_PREV_TTL

hpr7_cassette_map	ATM_HOPR ATM_HOPR_OLTP
hpr7_contents	ATM_HOPR ATM_HOPR_OLTP
hpr7_cur_cde	ATM_DD1 ATM_HOPR ATM_HOPR_OLTP ATM_PREV_TTL
hpr7_max_bills	ATM_HOPR ATM_HOPR_OLTP
hpr7_mcur_disp_ord	ATM_HOPR ATM_HOPR_OLTP
hpr7_nval_thrshld	ATM_HOPR ATM_HOPR_OLTP
hpr7_stnd_beg_amt	ATM_HOPR ATM_HOPR_OLTP
hpr7_stop_disp_amt	ATM_HOPR ATM_HOPR_OLTP
hpr7_strt_disp_amt	ATM_HOPR ATM_HOPR_OLTP
hpr7_threshold	ATM_HOPR ATM_HOPR_OLTP
hpr7_unit_val	ATM_HOPR ATM_HOPR_OLTP
Hpr8BgnBalNum	CTVRSF
Hpr8BgnCntNum	ESAPDT ESATDD1
Hpr8CntDcrsNum	ESAPDT ESATDD1
Hpr8CntIncrNum	ESAPDT ESATDD1
Hpr8CntnTx	CTVRSF HPRPRFL
Hpr8CntOtNum	ESAPDT ESATDD1
Hpr8CrncCd	HPRPRFL

Hpr8CrncCdTx	CTVRSAF
Hpr8CstMpTx	HPRPRFL
Hpr8DecrBalNum	CTVRSAF
Hpr8DspyOrdNum	HPRPRFL
Hpr8EndBalNum	CTVRSAF
Hpr8EndCntNum	ESAPDT
	ESATDD1
Hpr8IncrBalNum	CTVRSAF
Hpr8OutBalNum	CTVRSAF
Hpr8StndBgnCntNum	HPRPRFL
Hpr8UntValNum	HPRPRFL
hpr8_amt_beg	ATM_DD1
	ATM_PREV_TTL
hpr8_amt_decr	ATM_DD1
	ATM_PREV_TTL
hpr8_amt_end	ATM_DD1
	ATM_PREV_TTL
hpr8_amt_incr	ATM_DD1
	ATM_PREV_TTL
hpr8_amt_out	ATM_DD1
	ATM_PREV_TTL
hpr8_cassette_map	ATM_HOPR
	ATM_HOPR_OLTP
hpr8_contents	ATM_HOPR
	ATM_HOPR_OLTP
hpr8_cur_cde	ATM_DD1
	ATM_HOPR
	ATM_HOPR_OLTP
	ATM_PREV_TTL
hpr8_max_bills	ATM_HOPR
	ATM_HOPR_OLTP
hpr8_mcur_disp_ord	ATM_HOPR
	ATM_HOPR_OLTP
hpr8_nval_thrshld	ATM_HOPR
	ATM_HOPR_OLTP
hpr8_stnd_beg_amt	ATM_HOPR

hpr8_stop_disp_amt	ATM_HOPR_OLTP ATM_HOPR ATM_HOPR_OLTP
hpr8_strt_disp_amt	ATM_HOPR ATM_HOPR_OLTP
hpr8_threshold	ATM_HOPR ATM_HOPR_OLTP
hpr8_unit_val	ATM_HOPR ATM_HOPR_OLTP
HprPrflTx	ESATDS1 HPRPRFL.xml
hpr_prfl	ATM_DS1 ATM_DS1_OLTP ATM_HOPR.xml ATM_HOPR_OLTP.xml
HrdwAryTx	ESATDD1
HSMID	HSMCNFG.xml
hsm_spcf	Chip_Authentication Chip_Authentication_OLTP
HstCrtSecObjIdTx	IFXDATA
HstKeySecObjIdTx	IFXDATA
ice_conn_disconn_flg	SIS_ASYNC_DEST_MAP
ice_messaging_type	SIS_ASYNC_DEST_MAP
ice_qmgr_name	SIS_ASYNC_DEST_MAP
ice_remote_ipaddr_rlu	SIS_ASYNC_DEST_MAP
ice_reserved_num	SIS_ASYNC_DEST_MAP
ice_station_num	SIS_ASYNC_DEST_MAP
ice_timestamp	SIS_ASYNC_DEST_MAP
id	Pre_Auth_Hold.xml Usage.xml
IDFRemainingSegs	IDF
idx_typ	Journal_Query_Config
id_typ	Pre_Auth_Hold.xml Usage.xml
ilink_msg_prfl	Visa_Interface Visa_Interface_OLTP

import_kkt_key_typ	Interchange_Security Interchange_Security_OLTP
ims_cics_cde	HISO87_Proc_Txn HISO87_Proc_Txn_OLTP
ims_cics_cde_lgth	HISO87_Proc_Txn HISO87_Proc_Txn_OLTP
InactiveIDSuspend	SecGrp
inactivity_timer	ATM_DD1
InActTmrLng	ESATDD1
InactTmrPrflTx	ESATDS1 ITMRPRFL.xml
inact_non_peak	ATM_INACT ATM_INACT_OLTP
inact_tmouts_alwd	ATM_INACT ATM_INACT_OLTP
inact_wkend_end_pk	ATM_INACT ATM_INACT_OLTP
inact_wknd_peak	ATM_INACT ATM_INACT_OLTP
inact_wknd_strt_pk	ATM_INACT ATM_INACT_OLTP
inact_wrkd_end_pk	ATM_INACT ATM_INACT_OLTP
inact_wrkd_peak	ATM_INACT ATM_INACT_OLTP
inact_wrkd_strt_pk	ATM_INACT ATM_INACT_OLTP
inbnd_auth_rqst_tim_lmt	Interface Interface_Acquirer_OLTP Merchant_Channel_Profile Merchant_Channel_Profile_OLTP Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
inbnd_iv_hdr	Interchange_Security Interchange_Security_OLTP
inbnd_iv_kam	Interchange_Security

	Interchange_Security_OLTP
inbnd_iv_keyx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam1_hdr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam1_kam	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam1_keyx	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam1_vvk	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam2_hdr	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam2_kam	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam2_keyx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam2_vvk	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam_futr_hdr	Channel_Security_Future
	Interchange_Security_Future
inbnd_kam_futr_kam	Channel_Security_Future
	Interchange_Security_Future
inbnd_kam_futr_keyx	Channel_Security_Future
	Interchange_Security_Future
inbnd_kam_futr_vvk	Channel_Security_Future
	Interchange_Security_Future
inbnd_kam_idx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam_key_typ	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP

inbnd_kam_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kam_old_hdr	Channel_Security
inbnd_kam_old_kam	Channel_Security
inbnd_kam_old_keyx	Channel_Security
inbnd_kam_old_vvk	Channel_Security
inbnd_kam_variant	BASE24_KEYF
inbnd_kdt1_lvl1_futr_hdr	Channel_Security_Future
inbnd_kdt1_lvl1_futr_kam	Channel_Security_Future
inbnd_kdt1_lvl1_futr_keyx	Channel_Security_Future
inbnd_kdt1_lvl1_futr_vvk	Channel_Security_Future
inbnd_kdt1_lvl1_hdr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt1_lvl1_kam	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt1_lvl1_keyx	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt1_lvl1_old_hdr	Channel_Security
inbnd_kdt1_lvl1_old_kam	Channel_Security
inbnd_kdt1_lvl1_old_keyx	Channel_Security
inbnd_kdt1_lvl1_old_vvk	Channel_Security
inbnd_kdt1_lvl1_vvk	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt1_lvl2_futr_hdr	Channel_Security_Future
inbnd_kdt1_lvl2_futr_kam	Channel_Security_Future
inbnd_kdt1_lvl2_futr_keyx	Channel_Security_Future
inbnd_kdt1_lvl2_futr_vvk	Channel_Security_Future
inbnd_kdt1_lvl2_hdr	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt1_lvl2_kam	Interchange_Security
	Interchange_Security_OLTP

inbnd_kdt1_lvl2_keyx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt1_lvl2_vvk	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl1_hdr	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl1_kam	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl1_keyx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl1_vvk	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl2_hdr	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl2_kam	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl2_keyx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt2_lvl2_vvk	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt_idx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt_key_typ	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kdt_lvl1_futr_hdr	Interchange_Security_Future
inbnd_kdt_lvl1_futr_kam	Interchange_Security_Future
inbnd_kdt_lvl1_futr_keyx	Interchange_Security_Future
inbnd_kdt_lvl1_futr_vvk	Interchange_Security_Future
inbnd_kdt_lvl2_futr_hdr	Interchange_Security_Future
inbnd_kdt_lvl2_futr_kam	Interchange_Security_Future
inbnd_kdt_lvl2_futr_keyx	Interchange_Security_Future
inbnd_kdt_lvl2_futr_vvk	Interchange_Security_Future

inbnd_kek_cntr	Interac_Interface
inbnd_key_seq_num	Futr_Key
inbnd_kpt1_hdr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt1_kam	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt1_keyx	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt1_vvk	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt2_hdr	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt2_kam	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt2_keyx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt2_vvk	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt_futr_hdr	Channel_Security_Future
	Interchange_Security_Future
inbnd_kpt_futr_kam	Channel_Security_Future
	Interchange_Security_Future
inbnd_kpt_futr_keyx	Channel_Security_Future
	Interchange_Security_Future
inbnd_kpt_futr_vvk	Channel_Security_Future
	Interchange_Security_Future
inbnd_kpt_hdr	Futr_Key
inbnd_kpt_idx	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt_kam	Futr_Key
inbnd_kpt_keyx	Futr_Key
inbnd_kpt_lgth	Channel_Security

	Interchange_Security
	Interchange_Security_OLTP
inbnd_kpt_old_hdr	Channel_Security
inbnd_kpt_old_kam	Channel_Security
inbnd_kpt_old_keyx	Channel_Security
inbnd_kpt_old_vvk	Channel_Security
inbnd_kpt_variant	BASE24_KEYF
inbnd_kpt_vvk	Futr_Key
inbnd_old_data_timr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_old_mac_timr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_old_pin_timr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
inbnd_outbnd_flg	FPID_History.xml
	Interac_Admin
inbnd_pcng_timr_id	Interac_Base
inbnd_sta_nam	Banknet_Group_Timers
	HPDH_NAC_Term.xml
	HPDH_NAC_Term_OLTP.xml
	HPDH_NMS_Term.xml
	HPDH_NMS_Term_OLTP.xml
	Inbound_Station_OLTP.xml
	Interface_Station.xml
	Outbound_Station_OLTP
inbnd_u_kam_cntr	BIC_Interface
	BNFT_Interface
	Interchange_Security
	Interchange_Security_OLTP
inbnd_u_kpt_cntr	BIC_Interface
	BNFT_Interface
	Interchange_Security
	Interchange_Security_OLTP

inbound_pacing_intrvl	Interac_Base
	Interac_Base_OLTP
incl_fid_upper_h_in_mac	SPDH_Configuration
	SPDH_Configuration_OLTP
incl_fid_upper_i_in_mac	SPDH_Configuration
	SPDH_Configuration_OLTP
incl_fid_upper_m_in_mac	SPDH_Configuration
	SPDH_Configuration_OLTP
inf_pro_flg	Banknet_Configuration
	Banknet_Configuration_OLTP
InitConnNum	EXTRCNCT
init_kam_hdr	Channel_Security
init_kam_kam	Channel_Security
init_kam_keyx	Channel_Security
init_kam_lgth	Channel_Security
init_kam_vvk	Channel_Security
InprGrpTx	OPTRCPT
input_key_typ	Interchange_Security
	Interchange_Security_OLTP
InsrtTmTx	ATMLOG
InsrtTs	ATMLOG.xml
	CACNFSAF.xml
	RVSLSAF.xml
insrt_lgth	Account_Routing
	Account_Routing_OLTP
insrt_pos	Account_Routing
	Account_Routing_OLTP
insrt_val	Account_Routing
	Account_Routing_OLTP
InstldTx	CTVRSFAF.xml
	ESATDD1
	ESATDS1
instrm_stat	Card
	Instrm_Status_Extrn_to_Intrn
	Instrm_Status_Intrn_to_Extrn.xml
instrm_stat_chng_dat	Card

instrm_stat_extrn	Instrm_Status_Extrn_to_Intrn.xml
	Instrm_Status_Intrn_to_Extrn
instrm_stat_extrn_descr	Instrm_Status_Extrn_to_Intrn
	Instrm_Status_Intrn_to_Extrn
instrm_stat_prfl	HISO87_Interface
	HISO87_Interface_OLTP
	Instrm_Status_Extrn_to_Intrn.xml
	Instrm_Status_Intrn_to_Extrn.xml
	Visa_Interface
	Visa_Interface_OLTP
instrm_stat_scnd	Card
instrm_stat_scnd_chng_dat	Card
instrm_typ	Acquirer_Instrument_Type_Rel.xml
	Acquirer_Instrum_Type_Rel_OLTP.xml
	BEPS_Instrm_Prty.xml
	BEPS_Instrm_Prty_OLTP.xml
	Card
	Channel_Instrm_Type_Relation.xml
	Channel_Instrument_Type_Rel.xml
	Channel_Instrum_Type_Rel_OLTP.xml
	Chan_Profile_Instrm_Typ_Relation.xml
	Chan_Profile_Instrm_Typ_Rel_OLTP.xml
	Equens_Instrm_Typ_Extrn
	Equens_Instrm_Typ_Extrn_OLTP
	Equens_Instrm_Typ_Intrn.xml
	Equens_Instrm_Typ_Intrn_OLTP.xml
	Instrm_Typ_Extrn_to_Intrn
	Instrm_Typ_Extrn_to_Intrn_OLTP
	Instrm_Typ_Intrn_to_Extrn.xml
	Instrm_Typ_Intrn_to_Extrn_OLTP.xml
	INSTRUMENT_TYPE.xml
	Instrum_Typ_Interchange_Rel.xml
	Instrum_Typ_Interchange_Rel_OLTP.xml
	Interchange_Prefix
	Interchange_Prefix_OLTP
	Merch_Instr_Type_Relation_OLTP.xml

	Merch_Instr_Typ_Relation.xml
	Prefix
	Prefix_OLTP
	System_Prefix
	System_Prefix_OLTP
instrm_typ_1	MDS_Brand_Rel
	MDS_Brand_Rel_OLTP
	Merchant_Delivery_Channel
	Netwk_Brand_Instrm_ReIn
	Netwk_Brand_Instrm_ReIn_OLTP
	Star_Netwk_Rel_OLTP
	STAR_Network_Rel
	Star_NE_Network_Rel
	Star_NE_Network_Rel_OLTP
	Visa_Brand_Rel
	Visa_Brand_Rel_OLTP
instrm_typ_10	Merchant_Delivery_Channel
instrm_typ_2	Merchant_Delivery_Channel
instrm_typ_3	Merchant_Delivery_Channel
instrm_typ_4	Merchant_Delivery_Channel
instrm_typ_5	Merchant_Delivery_Channel
instrm_typ_6	Merchant_Delivery_Channel
instrm_typ_7	Merchant_Delivery_Channel
instrm_typ_8	Merchant_Delivery_Channel
instrm_typ_9	Merchant_Delivery_Channel
instrm_typ_adj_amt	Channel_Instrm_Type_Relation
instrm_typ_adj_amt_1	Merchant_Delivery_Channel
instrm_typ_adj_amt_10	Merchant_Delivery_Channel
instrm_typ_adj_amt_2	Merchant_Delivery_Channel
instrm_typ_adj_amt_3	Merchant_Delivery_Channel
instrm_typ_adj_amt_4	Merchant_Delivery_Channel
instrm_typ_adj_amt_5	Merchant_Delivery_Channel
instrm_typ_adj_amt_6	Merchant_Delivery_Channel
instrm_typ_adj_amt_7	Merchant_Delivery_Channel
instrm_typ_adj_amt_8	Merchant_Delivery_Channel
instrm_typ_adj_amt_9	Merchant_Delivery_Channel

instrm_typ_adj_cnt	Channel_Instrm_Type_Relation
instrm_typ_adj_cnt_1	Merchant_Delivery_Channel
instrm_typ_adj_cnt_10	Merchant_Delivery_Channel
instrm_typ_adj_cnt_2	Merchant_Delivery_Channel
instrm_typ_adj_cnt_3	Merchant_Delivery_Channel
instrm_typ_adj_cnt_4	Merchant_Delivery_Channel
instrm_typ_adj_cnt_5	Merchant_Delivery_Channel
instrm_typ_adj_cnt_6	Merchant_Delivery_Channel
instrm_typ_adj_cnt_7	Merchant_Delivery_Channel
instrm_typ_adj_cnt_8	Merchant_Delivery_Channel
instrm_typ_adj_cnt_9	Merchant_Delivery_Channel
instrm_typ_cr_amt	Channel_Instrm_Type_Relation
instrm_typ_cr_amt_1	Merchant_Delivery_Channel
instrm_typ_cr_amt_10	Merchant_Delivery_Channel
instrm_typ_cr_amt_2	Merchant_Delivery_Channel
instrm_typ_cr_amt_3	Merchant_Delivery_Channel
instrm_typ_cr_amt_4	Merchant_Delivery_Channel
instrm_typ_cr_amt_5	Merchant_Delivery_Channel
instrm_typ_cr_amt_6	Merchant_Delivery_Channel
instrm_typ_cr_amt_7	Merchant_Delivery_Channel
instrm_typ_cr_amt_8	Merchant_Delivery_Channel
instrm_typ_cr_amt_9	Merchant_Delivery_Channel
instrm_typ_cr_cnt	Channel_Instrm_Type_Relation
instrm_typ_cr_cnt_1	Merchant_Delivery_Channel
instrm_typ_cr_cnt_10	Merchant_Delivery_Channel
instrm_typ_cr_cnt_2	Merchant_Delivery_Channel
instrm_typ_cr_cnt_3	Merchant_Delivery_Channel
instrm_typ_cr_cnt_4	Merchant_Delivery_Channel
instrm_typ_cr_cnt_5	Merchant_Delivery_Channel
instrm_typ_cr_cnt_6	Merchant_Delivery_Channel
instrm_typ_cr_cnt_7	Merchant_Delivery_Channel
instrm_typ_cr_cnt_8	Merchant_Delivery_Channel
instrm_typ_cr_cnt_9	Merchant_Delivery_Channel
instrm_typ_db_amt	Channel_Instrm_Type_Relation
instrm_typ_db_amt_1	Merchant_Delivery_Channel
instrm_typ_db_amt_10	Merchant_Delivery_Channel

instrm_typ_db_amt_2	Merchant_Delivery_Channel
instrm_typ_db_amt_3	Merchant_Delivery_Channel
instrm_typ_db_amt_4	Merchant_Delivery_Channel
instrm_typ_db_amt_5	Merchant_Delivery_Channel
instrm_typ_db_amt_6	Merchant_Delivery_Channel
instrm_typ_db_amt_7	Merchant_Delivery_Channel
instrm_typ_db_amt_8	Merchant_Delivery_Channel
instrm_typ_db_amt_9	Merchant_Delivery_Channel
instrm_typ_db_cnt	Channel_Instrm_Type_Relation
instrm_typ_db_cnt_1	Merchant_Delivery_Channel
instrm_typ_db_cnt_10	Merchant_Delivery_Channel
instrm_typ_db_cnt_2	Merchant_Delivery_Channel
instrm_typ_db_cnt_3	Merchant_Delivery_Channel
instrm_typ_db_cnt_4	Merchant_Delivery_Channel
instrm_typ_db_cnt_5	Merchant_Delivery_Channel
instrm_typ_db_cnt_6	Merchant_Delivery_Channel
instrm_typ_db_cnt_7	Merchant_Delivery_Channel
instrm_typ_db_cnt_8	Merchant_Delivery_Channel
instrm_typ_db_cnt_9	Merchant_Delivery_Channel
instrm_typ_descr	INSTRUMENT_TYPE
instrm_typ_extrn	Instrm_Typ_Extrn_to_Intrn.xml
	Instrm_Typ_Extrn_to_Intrn_OLTP.xml
	Instrm_Typ_Intrn_to_Extrn
	Instrm_Typ_Intrn_to_Extrn_OLTP
instrm_typ_extrn_descr	Equens_Instrm_Typ_Extrn
	Equens_Instrm_Typ_Extrn_OLTP
	Equens_Instrm_Typ_Intrn
	Equens_Instrm_Typ_Intrn_OLTP
	Instrm_Typ_Extrn_to_Intrn
	Instrm_Typ_Intrn_to_Extrn
instrm_typ_num	Merchant_Delivery_Channel
instrm_typ_prfl	GICC_Interface
	GICC_Interface_OLTP
	HISO87_Interface
	HISO87_Interface_OLTP
	Instrm_Typ_Extrn_to_Intrn.xml

	Instrm_Typ_Extrn_to_Intrn_OLTP.xml
	Instrm_Typ_Intrn_to_Extrn.xml
	Instrm_Typ_Intrn_to_Extrn_OLTP.xml
instrm_typ_prty	BEPS_Instrm_Prty
	BEPS_Instrm_Prty_OLTP
instrm_typ_tot_flg	Chan_Profile_Instrm_Typ_Relation
	Chan_Profile_Instrm_Typ_Rel_OLTP
instrm_typ_ttl_supported	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
InstRtTrnsNmbrTx	ATDCNFG
inst_acronym	B53_Institution
	B53_Institution_OLTP
inst_id	ATM_DD1
	ATM_DS1
	ATM_DS1_OLTP
	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
	B53_Institution.xml
	B53_Institution_OLTP.xml
	Banknet_Group_Timers
	Banknet_Institution_Id.xml
	Banknet_Institution_Id2.xml
	Banknet_Institution_Id2_OLTP.xml
	Banknet_Institution_Id_OLTP.xml
	Card.xml
	Cardnet_ID_Code.xml
	Cardnet_ID_Code_OLTP.xml
	Card_Account.xml
	CARD_ACCOUNT_MBYTE.xml
	Card_Impacts.xml
	Check_Type.xml
	Check_Type_OLTP.xml
	CUP_Institution.xml
	CUP_Institution_OLTP.xml

Currency_Conversion_Rate.xml
Currency_Conversion_Rate_OLTP.xml
Discover_Institution.xml
Discover_Institution_OLTP.xml
EFunds_Institution.xml
EFunds_Institution_OLTP.xml
EPP_Serial_Number.xml
EPSNET_Inst.xml
EPSNET_Institution_OLTP.xml
FPS_Member
FPS_Member_OLTP
FPS_Payment_Submission
Institution.xml
Institution_ID_OLTP
Institution_OLTP.xml
JCB_Institution.xml
JCB_Institution_OLTP.xml
Limits.xml
Limits_OLTP.xml
MDS_Institution.xml
MDS_Institution_OLTP.xml
Merchant
Merchant_Delivery_Channel
Merchant_OLTP
NYCE_Institution.xml
NYCE_Institution_OLTP.xml
PBAL_Impacts.xml
Positive_Balance.xml
Prefix
Prefix_OLTP
Pre_Auth_Hold.xml
Pulse_Institution.xml
Pulse_Institution_OLTP.xml
Referral
Referral_OLTP
Star_Institution.xml

	Star_Institution_OLTP.xml
	Stop_Payment.xml
	SVS_Mrch_Num.xml
	SVS_Mrch_Num_OLTP.xml
	Usage.xml
	Visa_DPS_Institution.xml
	Visa_DPS_Institution_OLTP.xml
	Visa_Institution.xml
	Visa_Institution_OLTP.xml
inst_id_num	Account_Routing
	Account_Routing_OLTP
	ATM_SSB_BIN.xml
	ATM_SSB_BIN_OLTP.xml
	Institution
	Institution_ID_OLTP.xml
	Institution_OLTP
inst_nam	Institution
inst_proc_day	Institution
	Institution_OLTP
inst_route_num	ATM_PRFL
	ATM_PRFL_OLTP
interact_cond_stat	ATM_DD1
Interac_cap	SPDH_Configuration
	SPDH_Configuration_OLTP
interac_crd_prfx	Interac_ATM_IIN.xml
	Interac_ATM_IIN_OLTP.xml
	Interac_POS_IIN.xml
	Interac_POS_IIN_OLTP.xml
interac_iin_nde_id	Interac_ATM_IIN
	Interac_ATM_IIN_OLTP
	Interac_POS_IIN
	Interac_POS_IIN_OLTP
interac_nde_id	Interac_Base
	Interac_Base_OLTP
interac_nde_nam_alpha	Interac_Interface
	Interac_Interface_OLTP

interchange	Instrum_Typ_Interchange_Rel.xml
	Instrum_Typ_Interchange_Rel_OLTP
interchange_acct_typ	Instrum_Typ_Interchange_Rel
	Instrum_Typ_Interchange_Rel_OLTP
internet_auth_flg	Chip_Authentication
	Chip_Authentication_OLTP
intf_dpnt_data	Interface_Station
intf_nam	ABI_Interface.xml
	ABI_Interface_OLTP.xml
	ABI_Key.xml
	ABI_Key_OLTP.xml
	ACCEL_Interface.xml
	ACCEL_Interface_OLTP.xml
	AEGN_Interface.xml
	AEGN_Interface_OLTP.xml
	AMEX_CAPN_Interface.xml
	AMEX_CAPN_Interface_OLTP.xml
	AS2805_Interface.xml
	AS2805_Interface_OLTP.xml
	B24EPS_Ignt_map.xml
	B24EPS_Ignt_map_OLTP.xml
	B53_Institution.xml
	B53_Institution_OLTP.xml
	Banknet_Configuration.xml
	Banknet_Configuration_OLTP.xml
	Banknet_Institution_Id2.xml
	Banknet_Institution_Id2_OLTP.xml
	BASE24_KEYF.xml
	BIC_Interface.xml
	BIC_Interface_OLTP.xml
	BNFT_Interface.xml
	BNFT_Interface_OLTP.xml
	Cardnet_ID_Code.xml
	Cardnet_ID_Code_OLTP.xml
	Cardnet_Interface.xml
	Cardnet_Interface_OLTP.xml

Cardnet_Interface_Terminal.xml
Cardnet_Interface_Terminal_OLTP.xml
Circuit_Interface.xml
Circuit_Interface_OLTP.xml
Contingency_Interface.xml
Contingency_Interface_OLTP.xml
CUP_Institution.xml
CUP_Institution_OLTP.xml
CUP_Interface.xml
CUP_Interface_OLTP.xml
DIAS_Interface.xml
Discover_Interface.xml
Discover_Interface_OLTP.xml
EFunds_Institution.xml
EFunds_Institution_OLTP.xml
EFunds_Interface.xml
EFunds_Interface_OLTP.xml
EPSNET_Interface.xml
EPSNET_Interface_OLTP.xml
Equens_Interface
Equens_Interface_OLTP.xml
ERSB_Interface.xml
ERSB_Interface_OLTP.xml
Fifth_Third_Intf.xml
Fifth_Third_Intf_OLTP.xml
File_Update_Route.xml
File_Update_Route_OLTP
FIS_Interface.xml
FIS_Interface_OLTP.xml
FPS_Queue_Profile
FPS_Queue_Profile_OLTP
Futr_Key.xml
GICC_Interface.xml
GICC_Interface_OLTP.xml
GISO_ACQ_MSG_HND.xml
GISO_ACQ_MSG_HND_OLTP.xml

GISO_Interface.xml
GISO_Interface_OLTP.xml
GISO_IN_MSG_DEF.xml
GISO_IN_MSG_DEF_OLTP.xml
GISO_ISS_MSG_HND.xml
GISO_ISS_MSG_HND_OLTP.xml
GISO_OUT_MSG_DEF.xml
GISO_OUT_MSG_DEF_OLTP.xml
HISO87_Interface.xml
HISO87_Interface_OLTP.xml
HISO87_Proc_Txn.xml
HISO87_Proc_Txn_OLTP.xml
HISO93_Interface.xml
HISO93_Interface_OLTP.xml
IFX_Host_Interface.xml
IFX_Host_Interface_OLTP.xml
Inbound_Station_OLTP
Interac_Interface.xml
Interac_Interface_OLTP.xml
Interchange_Security
Interchange_Security_Future.xml
Interchange_Security_OLTP
Interface.xml
Interface_Acquirer_OLTP.xml
Interface_FPS.xml
Interface_FPS_OLTP.xml
Interface_Issuer_OLTP.xml
Interface_Manager.xml
Interface_OLTP.xml
Interface_SAF.xml
Interface_SAF_OLTP.xml
Interface_Station.xml
Interface_Terminal.xml
Interface_Terminal_OLTP.xml
Interface_WPS.xml
Interface_WPS_OLTP.xml

JCB_Interface.xml
JCB_Interface_OLTP.xml
Key_Map.xml
LIS5_Interface.xml
LIS5_Interface_OLTP.xml
MDS_Institution.xml
MDS_Institution_OLTP.xml
MDS_Interface.xml
MDS_Interface_OLTP.xml
NYCE_Interface.xml
NYCE_Interface_OLTP.xml
Outbound_Station_OLTP
Presto_Interface.xml
Presto_Interface_OLTP.xml
PRICE_Interface.xml
PRICE_Interface_OLTP.xml
PRM_Interface.xml
PRM_Interface_OLTP.xml
Pulse_Interface.xml
Pulse_Interface_OLTP.xml
Pulse_Switch_Date.xml
Real_Time_Feed_Config.xml
Real_Time_Feed_Config_OLTP.xml
SAF_Manager_OLTP
SPAN2_Interface.xml
SPAN2_Interface_OLTP.xml
SPAN2_Interface_Terminal.xml
SPAN2_Interface_Terminal_OLTP.xml
Star_Interface.xml
Star_Interface_OLTP.xml
Store_and_Forward
SVS_Interface.xml
SVS_Interface_OLTP.xml
SVS_Mrch_Num.xml
SVS_Mrch_Num_OLTP.xml
TERM_LN_FIID_MAP.xml

	TERM_LN_FIID_MAP_OLTP.xml
	UAE_Interface.xml
	Visa_DPS_Interface.xml
	Visa_DPS_Interface_OLTP.xml
	Visa_Interface.xml
	Visa_Interface_OLTP.xml
intf_platform	Star_Interface
	Star_Interface_OLTP
intf_term_id	Cardnet_Interface_Terminal.xml
	Cardnet_Interface_Terminal_OLTP.xml
	Interface_Terminal
	Interface_Terminal_OLTP
IntrNPkIntrNum	ITMRPRFL
intrn_act_cde	SPDH_ISO_Response_Code.xml
	SPDH_ISO_Response_Code_OLTP.xml
intrst_accru_cur	Positive_Balance
intrst_accru_ytd	Positive_Balance
IntrTmtsAlwdNum	ITMRPRFL
IntrWkndEndPkTx	ITMRPRFL
IntrWkndPkIntrNum	ITMRPRFL
IntrWkndStrtPkTx	ITMRPRFL
IntrWrkdEndPkTx	ITMRPRFL
IntrWrkdPkIntrNum	ITMRPRFL
IntrWrkdStrtPkTx	ITMRPRFL
inventory_cntrl_1	Merchant_Delivery_Channel
inventory_cntrl_2	Merchant_Delivery_Channel
iop_acq_rte_prfl	SPDH_Configuration
	SPDH_Configuration_OLTP
ipay_rsn_cde	Equens_Interface
	Equens_Interface_OLTP
iso_msg_prfl	GISO_IN_MSG_DEF
	GISO_IN_MSG_DEF_OLTP
	GISO_OUT_MSG_DEF
	GISO_OUT_MSG_DEF_OLTP
iso_resp_cde	SPDH_ISO_Response_Code
	SPDH_ISO_Response_Code_OLTP

List of data elements

iso_ver	ISO_Field
iss_appl_data_frmt	Chip_Authentication
	Chip_Authentication_OLTP
iss_inst_id	Issuer_Profile_Map.xml
	Issuer_Profile_Map_OLTP.xml
	Journal
	Journal_Data_Suppression.xml
	Journal_Data_Suppression_OLTP.xml
	Journal_Key_Seq
	Journal_Key_Seq2
	System_Prefix
	System_Prefix_OLTP
iss_inst_id_prev	GICC_Channel
iss_logon_st	Interface_Manager
	Interface_Station
iss_msg_sec_cde	FIS_Interface
	FIS_Interface_OLTP
	Pulse_Interface
	Pulse_Interface_OLTP
	Star_Interface
	Star_Interface_OLTP
	Visa_DPS_Interface
	Visa_DPS_Interface_OLTP
iss_nde_id	Interac_Admin
iss_prop_bit_map	Chip_Authentication
	Chip_Authentication_OLTP
iss_rte_flr_lmt	Route
	Route_OLTP
iss_rte_prfl	Acquirer_Issuer_Relation.xml
	Acquirer_Issuer_Relation_OLTP.xml
	File_Update_Route.xml
	File_Update_Route_OLTP.xml
	FPS_Member
	FPS_Member_OLTP
	Issuer_Route_Profile.xml
	Prefix

	Prefix_OLTP
	Route.xml
	Route_OLTP.xml
	System_Prefix
	System_Prefix_OLTP
iss_seq_gen_num	GICC_Iss_SGN
iss_stand_in_for_conetwork	BIC_Interface
	BIC_Interface_OLTP
iss_surch_prfl	Interchange_Prefix
	Interchange_Prefix_OLTP
	Prefix
	Prefix_OLTP
	Surcharge.xml
	Surcharge_Country_Code
	Surcharge_Country_Code_OLTP
	Surcharge_OLTP.xml
	System_Prefix
	System_Prefix_OLTP
iss_timr_id	Interface_Manager
	Interface_Station
iss_timr_typ	Interface_Manager
	Interface_Station
iss_txn_prfl	Interface
	Interface_Issuer_OLTP
	Issuer_Txn_Allowed.xml
	Issuer_Txn_Allowed_OLTP.xml
	Prefix
	Prefix_OLTP
ItemNameTx	LCONF.xml
ItemTypeCd	LCONF.xml
jpga_idx	Journal_Prfl_Group_Assign_OLTP.xml
	Journal_Profile_Group_Assign.xml
	Journal_Query_Output_Assign.xml
jpg_comment	Journal_Profile_Group
JrnlTranAprvFlag	RCPTRQRD
JrnlTranDenyFlag	RCPTRQRD

jrnl_body	Journal Journal_Continuation Journal_Key_Seq Journal_Key_Seq2
jrnl_btch_hdr_flg	Journal_Query_Config_Output
jrnl_btch_iss_inst_id	Journal_Query_Config Journal_Query_Position_Info
jrnl_btch_qry_nam	Journal_Query_Config.xml Journal_Query_Config_Output.xml Journal_Query_Position_Info.xml
jrnl_btch_rec_num	Journal_Query_Config_Output.xml
jrnl_btch_ttl	Merchant_Channel_Profile Merchant_Channel_Profile_OLTP Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
jrnl_clerk_ttl	Merchant_Channel_Profile Merchant_Channel_Profile_OLTP Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
jrnl_dly_ttl	Merchant_Channel_Profile Merchant_Channel_Profile_OLTP Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
jrnl_end_asgn_nam	Journal_Query_Position_Info
jrnl_instrm_typ_ttl	Merchant_Channel_Profile Merchant_Channel_Profile_OLTP Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
jrnl_network_ttl	Merchant_Channel_Profile Merchant_Channel_Profile_OLTP Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP
jrnl_prfl	Journal_Prfl_Group_Assign_OLTP.xml Journal_Profile_Group.xml Journal_Profile_Group_Assign.xml Journal_Profile_Group_OLTP.xml

	Journal_Query_Output_Assign.xml
	Journal_Query_Output_Map.xml
	Journal_Query_Position_Info.xml
jrnl_prfl_alt	Issuer_Profile_Map
	Issuer_Profile_Map_OLTP
jrnl_prfl_pri	Issuer_Profile_Map
	Issuer_Profile_Map_OLTP
jrnl_qry_output_prfl	Journal_Query_Config_Output
	Journal_Query_Output_Map.xml
jrnl_qry_rec_cnt	Journal_Query_Position_Info
jrnl_shift_ttl	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
jrnl_strt_asgn_nam	Journal_Query_Position_Info
jrnl_term_stat	HPDH_Configuration
	HPDH_Configuration_OLTP
jrnl_txn_aprv_ind	ATM_REQ_RCPT
	ATM_REQ_RCPT_OLTP
jrnl_txn_deny_ind	ATM_REQ_RCPT
	ATM_REQ_RCPT_OLTP
kam_chng_in_timr_id	Interface_Manager
kam_chng_in_timr_typ	Interface_Manager
kam_chng_out_timr_id	Interface_Manager
kam_chng_out_timr_typ	Interface_Manager
kam_in_cnsc_err_cnt	Merchant_Delivery_Channel
kam_in_err_cnt	Interface_Manager
kam_in_ts	Interface_Manager
	Merchant_Delivery_Channel
kam_in_txn_cnt	Interface_Manager
	Merchant_Delivery_Channel
kam_in_xchg_cnt_1	Interface_Manager
kam_in_xchg_cnt_2	Interface_Manager
kam_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP

kam_out_err_cnt	Interface_Manager
kam_out_ts	Interface_Manager
kam_out_txn_cnt	Interface_Manager
kam_out_xchg_cnt_1	Interface_Manager
kam_out_xchg_cnt_2	Interface_Manager
kam_rpt_in_timr_id	Interface_Manager
kam_rpt_in_timr_typ	Interface_Manager
kam_rpt_out_timr_id	Interface_Manager
kam_rpt_out_timr_typ	Interface_Manager
kam_timr_lmt	BASE24_KEYF
	Interface_Manager
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
kam_txn_err_cnt	Merchant_Delivery_Channel
kam_txn_err_lmt	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
kam_typ	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kam_vrfy_in_timr_id	Interface_Manager
kam_vrfy_in_timr_typ	Interface_Manager
kam_vrfy_out_timr_id	Interface_Manager
kam_vrfy_out_timr_typ	Interface_Manager
kdt_chng_in_timr_id	Interface_Manager
kdt_chng_in_timr_typ	Interface_Manager
kdt_chng_out_timr_id	Interface_Manager
kdt_chng_out_timr_typ	Interface_Manager
kdt_in_err_cnt	Interface_Manager
kdt_in_ts	Interface_Manager
	Merchant_Delivery_Channel
kdt_in_txn_cnt	Interface_Manager
kdt_in_xchg_cnt_1	Interface_Manager
kdt_in_xchg_cnt_2	Interface_Manager
kdt_out_err_cnt	Interface_Manager

kdt_out_ts	Interface_Manager
kdt_out_txn_cnt	Interface_Manager
kdt_out_xchg_cnt_1	Interface_Manager
kdt_out_xchg_cnt_2	Interface_Manager
kdt_rpt_in_timr_id	Interface_Manager
kdt_rpt_in_timr_typ	Interface_Manager
kdt_rpt_out_timr_id	Interface_Manager
kdt_rpt_out_timr_typ	Interface_Manager
kdt_timr_lmt	Interface_Manager
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
kdt_txn_cnt	Merchant_Delivery_Channel
kdt_txn_err_cnt	Merchant_Delivery_Channel
kdt_txn_err_lmt	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
kdt_txn_lmt	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
kdt_vrfy_in_timr_id	Interface_Manager
kdt_vrfy_in_timr_typ	Interface_Manager
kdt_vrfy_out_timr_id	Interface_Manager
kdt_vrfy_out_timr_typ	Interface_Manager
KEKMacSecObjIdTx	IFXDATA
KEKMsgSecObjIdTx	IFXDATA
KEKPinSecObjIdTx	IFXDATA
kek_chng_in_timr_id	Interface_Manager
kek_chng_in_timr_typ	Interface_Manager
kek_chng_out_timr_id	Interface_Manager
kek_chng_out_timr_typ	Interface_Manager
kek_in_err_cnt	Interface_Manager
kek_in_ts	Interface_Manager
kek_in_txn_cnt	Interface_Manager
kek_in_xchg_cnt_1	Interface_Manager
kek_in_xchg_cnt_2	Interface_Manager
kek_out_err_cnt	Interface_Manager
kek_out_ts	Interface_Manager
kek_out_txn_cnt	Interface_Manager

kek_out_xchg_cnt_1	Interface_Manager
kek_out_xchg_cnt_2	Interface_Manager
kek_rpt_in_timr_id	Interface_Manager
kek_rpt_in_timr_typ	Interface_Manager
kek_rpt_out_timr_id	Interface_Manager
kek_rpt_out_timr_typ	Interface_Manager
kek_timr_lmt	Interface_Manager
kek_vrfy_in_timr_id	Interface_Manager
kek_vrfy_in_timr_typ	Interface_Manager
kek_vrfy_out_timr_id	Interface_Manager
kek_vrfy_out_timr_typ	Interface_Manager
KeyHierIndCd	ATDCNFG
KeyOwnrIdTx	CACNFSAF
	CACNTX
KeyOwnrTypTx	CACNFSAF
	CACNTX
key_cnt_flg	Interface_Manager
key_dir	Key_Map.xml
key_effective_dat	ZKA_KGK
key_eff_dat	Host_Public_Key_Security.xml
key_encrypt	Diebold_Number_Table
	IBM_DES
	IBM_DES_OLTP
	NCR_PIN_Verification
	NCR_PIN_Verification_OLTP
key_encrypt_1	Card_Verification
	Card_Verification_OLTP
	Dynamic_Card_Verification
	Dynamic_Card_Verification_OLTP
	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_10	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_11	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_11_hdr	Visa_PVV

	Visa_PVV_OLTP
key_encrypt_11_kam	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_12	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_1_hdr	Card_Verification
	Card_Verification_OLTP
	Dynamic_Card_Verification
	Dynamic_Card_Verification_OLTP
	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_1_kam	Card_Verification
	Card_Verification_OLTP
	Dynamic_Card_Verification
	Dynamic_Card_Verification_OLTP
	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_2	Card_Verification
	Card_Verification_OLTP
	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_3	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_3_hdr	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_3_kam	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_4	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_5	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_5_hdr	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_5_kam	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_6	Visa_PVV

	Visa_PVV_OLTP
key_encrypt_7	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_7_hdr	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_7_kam	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_8	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_9	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_9_hdr	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_9_kam	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_chk_values	Diebold_Number_Table
	IBM_DES
	IBM_DES_OLTP
	NCR_PIN_Verification
	NCR_PIN_Verification_OLTP
key_encrypt_chk_values_1	Card_Verification
	Card_Verification_OLTP
	Dynamic_Card_Verification
	Dynamic_Card_Verification_OLTP
	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_chk_values_10	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_chk_values_11	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_chk_values_12	Visa_PVV
	Visa_PVV_OLTP
key_encrypt_chk_values_2	Card_Verification
	Card_Verification_OLTP
	Visa_PVV
	Visa_PVV_OLTP

key_encrypt_chk_values_3	Visa_PVV Visa_PVV_OLTP
key_encrypt_chk_values_4	Visa_PVV Visa_PVV_OLTP
key_encrypt_chk_values_5	Visa_PVV Visa_PVV_OLTP
key_encrypt_chk_values_6	Visa_PVV Visa_PVV_OLTP
key_encrypt_chk_values_7	Visa_PVV Visa_PVV_OLTP
key_encrypt_chk_values_8	Visa_PVV Visa_PVV_OLTP
key_encrypt_chk_values_9	Visa_PVV Visa_PVV_OLTP
key_encrypt_hdr	Diebold_Number_Table IBM_DES IBM_DES_OLTP NCR_PIN_Verification NCR_PIN_Verification_OLTP
key_encrypt_kam	Diebold_Number_Table IBM_DES IBM_DES_OLTP NCR_PIN_Verification NCR_PIN_Verification_OLTP
key_expire_dat	ZKA_KGK
key_gen_num	Channel_Security Interchange_Security Interchange_Security_OLTP
key_hierarchy	Channel_Security Interchange_Security Interchange_Security_OLTP
key_label	Key_Token.xml
key_lgth	file_part_catalog
key_mgmt	AS2805_Config AS2805_Config_OLTP
key_mgmt_typ	Interface_Manager

key_rgstr_cur	Channel_Security
key_rgstr_init	Channel_Security
key_rgstr_new	Channel_Security
key_rgstr_prev	Channel_Security
key_scheme	Security_Device_Config
key_seq_num	Key_Map
key_sync_cnt	Interac_Interface
key_sync_lmt	Interac_Interface
	Interac_Interface_OLTP
key_table_num	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
key_token	Key_Token
key_usage_updt_intrvl	Interface_Manager
key_ver_num	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
key_xchg_cnt	Interac_Interface
key_xchg_cnt_enbl_flg	Interface_Manager
key_xchg_lmt	Interac_Interface
	Interac_Interface_OLTP
key_xchg_rjct_cnt	Interac_Interface
key_xchg_rjct_lmt	Interac_Interface
	Interac_Interface_OLTP
key_xchg_tim	Equens_Interface
	Equens_Interface_OLTP
key_xchg_timeout_cnt	Interac_Interface
key_xchg_timeout_lmt	Interac_Interface
	Interac_Interface_OLTP
key_xchg_timr_id	Equens_Interface
	Equens_Interface_OLTP
key_xchnng_hour	Interac_Interface
	Interac_Interface_OLTP
key_xchnng_min	Interac_Interface
	Interac_Interface_OLTP
key_xchnng_timr_id	Interac_Interface

kgk_drv_depth	ZKA_KGK.xml
kgk_hdr	ZKA_KGK
kgk_kam	ZKA_KGK
kgk_keyx	ZKA_KGK
kgk_key_loc	ZKA_KGK.xml
kgk_key_table	ZKA_KGK.xml
kgk_key_typ	ZKA_KGK.xml
kgk_kgn	ZKA_KGK.xml
kgk_kvn	ZKA_KGK.xml
kgk_pvn1_hdr	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_pvn1_kam	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_pvn1_keyx	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_pvn1_vvk	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_pvn2_hdr	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_pvn2_kam	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_pvn2_keyx	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_pvn2_vvk	Dual_PIN_Verification
	Dual_PIN_Verification_OLTP
kgk_vvk	ZKA_KGK
kkt_am_export_futr_hdr	Interchange_Security_Future
kkt_am_export_futr_kam	Interchange_Security_Future
kkt_am_export_futr_keyx	Interchange_Security_Future
kkt_am_export_futr_vvk	Interchange_Security_Future
kkt_am_export_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_am_export_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_am_export_keyx	Interchange_Security
	Interchange_Security_OLTP

kkt_am_export_old_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_am_export_old_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_am_export_old_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_am_export_old_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_am_export_vrnt	Channel_Security
kkt_am_export_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_am_futr_hdr	Channel_Security_Future
kkt_am_futr_kam	Channel_Security_Future
kkt_am_futr_keyx	Channel_Security_Future
kkt_am_futr_vvk	Channel_Security_Future
kkt_am_hdr	Channel_Security
kkt_am_import_futr_hdr	Interchange_Security_Future
kkt_am_import_futr_kam	Interchange_Security_Future
kkt_am_import_futr_keyx	Interchange_Security_Future
kkt_am_import_futr_vvk	Interchange_Security_Future
kkt_am_import_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_am_import_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_am_import_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_am_import_old_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_am_import_old_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_am_import_old_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_am_import_old_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_am_import_vvk	Interchange_Security
	Interchange_Security_OLTP

kkt_am_kam	Channel_Security
kkt_am_keyx	Channel_Security
kkt_am_key_opt	Interchange_Security
	Interchange_Security_OLTP
kkt_am_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kkt_am_mstr_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_am_mstr_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_am_mstr_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_am_mstr_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_am_old_hdr	Channel_Security
kkt_am_old_kam	Channel_Security
kkt_am_old_keyx	Channel_Security
kkt_am_old_vvk	Channel_Security
kkt_am_variant	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kkt_am_vvk	Channel_Security
kkt_dt_export_futr_hdr	Interchange_Security_Future
kkt_dt_export_futr_kam	Interchange_Security_Future
kkt_dt_export_futr_keyx	Interchange_Security_Future
kkt_dt_export_futr_vvk	Interchange_Security_Future
kkt_dt_export_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_export_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_export_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_export_old_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_export_old_kam	Interchange_Security

	Interchange_Security_OLTP
kkt_dt_export_old_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_export_old_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_export_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_futr_hdr	Channel_Security_Future
kkt_dt_futr_kam	Channel_Security_Future
kkt_dt_futr_keyx	Channel_Security_Future
kkt_dt_futr_vvk	Channel_Security_Future
kkt_dt_hdr	Channel_Security
kkt_dt_import_futr_hdr	Interchange_Security_Future
kkt_dt_import_futr_kam	Interchange_Security_Future
kkt_dt_import_futr_keyx	Interchange_Security_Future
kkt_dt_import_futr_vvk	Interchange_Security_Future
kkt_dt_import_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_import_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_import_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_import_old_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_import_old_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_import_old_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_import_old_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_import_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_kam	Channel_Security
kkt_dt_keyx	Channel_Security
kkt_dt_key_opt	Interchange_Security
	Interchange_Security_OLTP

kkt_dt_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_old_hdr	Channel_Security
kkt_dt_old_kam	Channel_Security
kkt_dt_old_keyx	Channel_Security
kkt_dt_old_vvk	Channel_Security
kkt_dt_variant	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kkt_dt_vvk	Channel_Security
kkt_old_am_timr	Channel_Security
kkt_old_dt_timr	Channel_Security
kkt_old_pt_timr	Channel_Security
kkt_opt	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_futr_hdr	Interchange_Security_Future
kkt_pt_export_futr_kam	Interchange_Security_Future
kkt_pt_export_futr_keyx	Interchange_Security_Future
kkt_pt_export_futr_vvk	Interchange_Security_Future
kkt_pt_export_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_old_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_old_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_old_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_old_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_export_vvk	Interchange_Security

kkt_pt_futr_hdr	Interchange_Security_OLTP
kkt_pt_futr_kam	Channel_Security_Future
kkt_pt_futr_keyx	Channel_Security_Future
kkt_pt_futr_vvk	Channel_Security_Future
kkt_pt_hdr	Channel_Security
kkt_pt_import_futr_hdr	Interchange_Security_Future
kkt_pt_import_futr_kam	Interchange_Security_Future
kkt_pt_import_futr_keyx	Interchange_Security_Future
kkt_pt_import_futr_vvk	Interchange_Security_Future
kkt_pt_import_hdr	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
kkt_pt_import_kam	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
kkt_pt_import_keyx	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
kkt_pt_import_old_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_import_old_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_import_old_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_import_old_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_import_vvk	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
kkt_pt_kam	Channel_Security
kkt_pt_keyx	Channel_Security

kkt_pt_key_opt	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_mstr_hdr	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_mstr_kam	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_mstr_keyx	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_mstr_vvk	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_old_hdr	Channel_Security
kkt_pt_old_kam	Channel_Security
kkt_pt_old_keyx	Channel_Security
kkt_pt_old_vvk	Channel_Security
kkt_pt_variant	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
kkt_pt_vvk	Channel_Security
kpt_chng_in_timr_id	Interface_Manager
kpt_chng_in_timr_typ	Interface_Manager
kpt_chng_out_timr_id	Interface_Manager
kpt_chng_out_timr_typ	Interface_Manager
kpt_idx	Key_Map.xml
kpt_in_err_cnt	Interface_Manager
kpt_in_ts	Interface_Manager
	Merchant_Delivery_Channel
kpt_in_txn_cnt	Interface_Manager
	Merchant_Delivery_Channel
kpt_in_xchg_cnt_1	Interface_Manager
kpt_in_xchg_cnt_2	Interface_Manager
kpt_out_err_cnt	Interface_Manager
kpt_out_ts	Interface_Manager
kpt_out_txn_cnt	Interface_Manager

kpt_out_xchg_cnt_1	Interface_Manager
kpt_out_xchg_cnt_2	Interface_Manager
kpt_rpt_in_timr_id	Interface_Manager
kpt_rpt_in_timr_typ	Interface_Manager
kpt_rpt_out_timr_id	Interface_Manager
kpt_rpt_out_timr_typ	Interface_Manager
kpt_timr_lmt	BASE24_KEYF
	Interface_Manager
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
kpt_txn_err_cnt	Merchant_Delivery_Channel
kpt_txn_err_lmt	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
kpt_vrfy_in_timr_id	Interface_Manager
kpt_vrfy_in_timr_typ	Interface_Manager
kpt_vrfy_out_timr_id	Interface_Manager
kpt_vrfy_out_timr_typ	Interface_Manager
KySgnrTx	ATDCNFG
LangBankIdTx	ATMCNFG.xml
LangCd	RECEIPT.xml
lang_bank_id	ATM_CONF.xml
lang_id	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
	SPDH_act_cde_descr.xml
	SPDH_act_cde_descr_OLTP.xml
	SPDH_ISO_Response_Text.xml
	SPDH_ISO_Response_Text_OLTP.xml
	SPDH_txn_cde_descr.xml
	SPDH_txn_cde_descr_OLTP.xml
LastAfmTermNameTx	APCF
	LCONF
LastAfmTsLong	APCF
	LCONF

LastAfmUpdtType	APCF
	LCONF
LastChangeTime	LCONF
LastFailedLoginTS	Users
LastLoginTS	Users
LastMaintTS	Filters
	Password
	PermGrp
	Perms
	PswdGrp
	Roles
	SecGrp
	Users
LastName	Users
LastTranStatEnblCd	ESATDD1
LastUpdtTm	ACTSESS2
	APPLCNFG
	DATASRC
	EXTRCNCT
	HSMCNFG
	LISTENER
	PROCESS
	VERSIONS
	WEBAPPOPTS
	WEBAPPS
	WEBUSROPTS
last_addr_chng	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
last_crv	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
last_iss	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
last_iss_inst_id	GICC_Acq_SGN
last_jrnl_amt	GICC_Acq_SGN
last_nam_fld	dal_tbl.xml
last_out_setl_dat	SPAN2_Interface

List of data elements

last_pan	GICC_Acq_SGN
last_seq_num	GICC_Acq_SGN
	Interface_Manager
last_seq_num_updt_intrvl	Interface_Manager
last_settle_tm	ATM_DD1
	ATM_PREV_TTL
last_stan	Equens_Interface
	Equens_Interface_OLTP
last_stat_chng	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
last_swi_setl_dat	Interface_Manager
last_txn_captr_dat	ATM_DD1
last_txn_cur_cde	ATM_DD1
last_txn_iss_inst_id	ATM_DD1
last_txn_proc_cde	ATM_DD1
last_txn_stat_capable	ATM_DS1
	ATM_DS1_OLTP
LclPinVrfyTypCd	ATDCNFG
LCnfgldTx	ESATDD1
LdTmtPrdNum	LTMRPRFL
ledg_bal_strt	Positive_Balance
ledg_bal_strt_dat	Positive_Balance
lgth_bcd_flg	ISO_Field
	ISO_Field_OLTP
lgth_rprsnt_bytes	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
lgth_size	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
lgth_typ	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
line_num	Script
	Script_OLTP
	Script_Source.xml
line_ofst	Script
	Script_OLTP
line_text	Script_Source

link_st	Interface_Station
lis5_msg_orig	LIS5_Interface
	LIS5_Interface_OLTP
lmt_1_max	Card
	Positive_Balance
lmt_2_max	Card
	Positive_Balance
lmt_3_max	Card
	Positive_Balance
lmt_4_max	Card
	Positive_Balance
lmt_5_max	Card
	Positive_Balance
lmt_6_max	Card
	Positive_Balance
lmt_max	Limits
	Limits_OLTP
lmt_prfl	Card
	FPS_Member
	FPS_Member_OLTP
	Limits.xml
	Limits_OLTP.xml
	Positive_Balance
	Prefix
	Prefix_OLTP
	System_Prefix
	System_Prefix_OLTP
lmt_usg_10_amt_used	Usage
lmt_usg_10_crncy_cde	Usage
lmt_usg_10_nam	Usage
lmt_usg_10_nxt_beg_dat	Usage
lmt_usg_11_amt_used	Usage
lmt_usg_11_crncy_cde	Usage
lmt_usg_11_nam	Usage
lmt_usg_11_nxt_beg_dat	Usage
lmt_usg_12_amt_used	Usage

List of data elements

lmt_usg_12_crncy_cde	Usage
lmt_usg_12_nam	Usage
lmt_usg_12_nxt_beg_dat	Usage
lmt_usg_13_amt_used	Usage
lmt_usg_13_crncy_cde	Usage
lmt_usg_13_nam	Usage
lmt_usg_13_nxt_beg_dat	Usage
lmt_usg_14_amt_used	Usage
lmt_usg_14_crncy_cde	Usage
lmt_usg_14_nam	Usage
lmt_usg_14_nxt_beg_dat	Usage
lmt_usg_15_amt_used	Usage
lmt_usg_15_crncy_cde	Usage
lmt_usg_15_nam	Usage
lmt_usg_15_nxt_beg_dat	Usage
lmt_usg_16_amt_used	Usage
lmt_usg_16_crncy_cde	Usage
lmt_usg_16_nam	Usage
lmt_usg_16_nxt_beg_dat	Usage
lmt_usg_17_amt_used	Usage
lmt_usg_17_crncy_cde	Usage
lmt_usg_17_nam	Usage
lmt_usg_17_nxt_beg_dat	Usage
lmt_usg_18_amt_used	Usage
lmt_usg_18_crncy_cde	Usage
lmt_usg_18_nam	Usage
lmt_usg_18_nxt_beg_dat	Usage
lmt_usg_19_amt_used	Usage
lmt_usg_19_crncy_cde	Usage
lmt_usg_19_nam	Usage
lmt_usg_19_nxt_beg_dat	Usage
lmt_usg_1_amt_used	Usage
lmt_usg_1_crncy_cde	Card
	Positive_Balance
	Usage
lmt_usg_1_exp_dat	Card

	Positive_Balance
lmt_usg_1_nam	Card
	Positive_Balance
	Usage
lmt_usg_1_nxt_beg_dat	Usage
lmt_usg_1_prd_adnl_data	Card
	Positive_Balance
lmt_usg_1_prd_opt	Card
	Positive_Balance
lmt_usg_20_amt_used	Usage
lmt_usg_20_crncy_cde	Usage
lmt_usg_20_nam	Usage
lmt_usg_20_nxt_beg_dat	Usage
lmt_usg_21_amt_used	Usage
lmt_usg_21_crncy_cde	Usage
lmt_usg_21_nam	Usage
lmt_usg_21_nxt_beg_dat	Usage
lmt_usg_22_amt_used	Usage
lmt_usg_22_crncy_cde	Usage
lmt_usg_22_nam	Usage
lmt_usg_22_nxt_beg_dat	Usage
lmt_usg_23_amt_used	Usage
lmt_usg_23_crncy_cde	Usage
lmt_usg_23_nam	Usage
lmt_usg_23_nxt_beg_dat	Usage
lmt_usg_24_amt_used	Usage
lmt_usg_24_crncy_cde	Usage
lmt_usg_24_nam	Usage
lmt_usg_24_nxt_beg_dat	Usage
lmt_usg_25_amt_used	Usage
lmt_usg_25_crncy_cde	Usage
lmt_usg_25_nam	Usage
lmt_usg_25_nxt_beg_dat	Usage
lmt_usg_26_amt_used	Usage
lmt_usg_26_crncy_cde	Usage
lmt_usg_26_nam	Usage

List of data elements

lmt_usg_26_nxt_beg_dat	Usage
lmt_usg_27_amt_used	Usage
lmt_usg_27_crncy_cde	Usage
lmt_usg_27_nam	Usage
lmt_usg_27_nxt_beg_dat	Usage
lmt_usg_28_amt_used	Usage
lmt_usg_28_crncy_cde	Usage
lmt_usg_28_nam	Usage
lmt_usg_28_nxt_beg_dat	Usage
lmt_usg_29_amt_used	Usage
lmt_usg_29_crncy_cde	Usage
lmt_usg_29_nam	Usage
lmt_usg_29_nxt_beg_dat	Usage
lmt_usg_2_amt_used	Usage
lmt_usg_2_crncy_cde	Card
	Positive_Balance
	Usage
lmt_usg_2_exp_dat	Card
	Positive_Balance
lmt_usg_2_nam	Card
	Positive_Balance
	Usage
lmt_usg_2_nxt_beg_dat	Usage
lmt_usg_2_prd_adnl_data	Card
	Positive_Balance
lmt_usg_2_prd_opt	Card
	Positive_Balance
lmt_usg_30_amt_used	Usage
lmt_usg_30_crncy_cde	Usage
lmt_usg_30_nam	Usage
lmt_usg_30_nxt_beg_dat	Usage
lmt_usg_31_amt_used	Usage
lmt_usg_31_crncy_cde	Usage
lmt_usg_31_nam	Usage
lmt_usg_31_nxt_beg_dat	Usage
lmt_usg_32_amt_used	Usage

lmt_usg_32_crncy_cde	Usage
lmt_usg_32_nam	Usage
lmt_usg_32_nxt_beg_dat	Usage
lmt_usg_33_amt_used	Usage
lmt_usg_33_crncy_cde	Usage
lmt_usg_33_nam	Usage
lmt_usg_33_nxt_beg_dat	Usage
lmt_usg_34_amt_used	Usage
lmt_usg_34_crncy_cde	Usage
lmt_usg_34_nam	Usage
lmt_usg_34_nxt_beg_dat	Usage
lmt_usg_35_amt_used	Usage
lmt_usg_35_crncy_cde	Usage
lmt_usg_35_nam	Usage
lmt_usg_35_nxt_beg_dat	Usage
lmt_usg_36_amt_used	Usage
lmt_usg_36_crncy_cde	Usage
lmt_usg_36_nam	Usage
lmt_usg_36_nxt_beg_dat	Usage
lmt_usg_37_amt_used	Usage
lmt_usg_37_crncy_cde	Usage
lmt_usg_37_nam	Usage
lmt_usg_37_nxt_beg_dat	Usage
lmt_usg_38_amt_used	Usage
lmt_usg_38_crncy_cde	Usage
lmt_usg_38_nam	Usage
lmt_usg_38_nxt_beg_dat	Usage
lmt_usg_39_amt_used	Usage
lmt_usg_39_crncy_cde	Usage
lmt_usg_39_nam	Usage
lmt_usg_39_nxt_beg_dat	Usage
lmt_usg_3_amt_used	Usage
lmt_usg_3_crncy_cde	Card
	Positive_Balance
	Usage
lmt_usg_3_exp_dat	Card

	Positive_Balance
lmt_usg_3_nam	Card
	Positive_Balance
	Usage
lmt_usg_3_nxt_beg_dat	Usage
lmt_usg_3_prd_adnl_data	Card
	Positive_Balance
lmt_usg_3_prd_opt	Card
	Positive_Balance
lmt_usg_40_amt_used	Usage
lmt_usg_40_crncy_cde	Usage
lmt_usg_40_nam	Usage
lmt_usg_40_nxt_beg_dat	Usage
lmt_usg_41_amt_used	Usage
lmt_usg_41_crncy_cde	Usage
lmt_usg_41_nam	Usage
lmt_usg_41_nxt_beg_dat	Usage
lmt_usg_42_amt_used	Usage
lmt_usg_42_crncy_cde	Usage
lmt_usg_42_nam	Usage
lmt_usg_42_nxt_beg_dat	Usage
lmt_usg_43_amt_used	Usage
lmt_usg_43_crncy_cde	Usage
lmt_usg_43_nam	Usage
lmt_usg_43_nxt_beg_dat	Usage
lmt_usg_44_amt_used	Usage
lmt_usg_44_crncy_cde	Usage
lmt_usg_44_nam	Usage
lmt_usg_44_nxt_beg_dat	Usage
lmt_usg_45_amt_used	Usage
lmt_usg_45_crncy_cde	Usage
lmt_usg_45_nam	Usage
lmt_usg_45_nxt_beg_dat	Usage
lmt_usg_46_amt_used	Usage
lmt_usg_46_crncy_cde	Usage
lmt_usg_46_nam	Usage

lmt_usg_46_nxt_beg_dat	Usage
lmt_usg_47_amt_used	Usage
lmt_usg_47_crncy_cde	Usage
lmt_usg_47_nam	Usage
lmt_usg_47_nxt_beg_dat	Usage
lmt_usg_48_amt_used	Usage
lmt_usg_48_crncy_cde	Usage
lmt_usg_48_nam	Usage
lmt_usg_48_nxt_beg_dat	Usage
lmt_usg_49_amt_used	Usage
lmt_usg_49_crncy_cde	Usage
lmt_usg_49_nam	Usage
lmt_usg_49_nxt_beg_dat	Usage
lmt_usg_4_amt_used	Usage
lmt_usg_4_crncy_cde	Card
	Positive_Balance
	Usage
lmt_usg_4_exp_dat	Card
	Positive_Balance
lmt_usg_4_nam	Card
	Positive_Balance
	Usage
lmt_usg_4_nxt_beg_dat	Usage
lmt_usg_4_prd_adnl_data	Card
	Positive_Balance
lmt_usg_4_prd_opt	Card
	Positive_Balance
lmt_usg_50_amt_used	Usage
lmt_usg_50_crncy_cde	Usage
lmt_usg_50_nam	Usage
lmt_usg_50_nxt_beg_dat	Usage
lmt_usg_51_amt_used	Usage
lmt_usg_51_crncy_cde	Usage
lmt_usg_51_nam	Usage
lmt_usg_51_nxt_beg_dat	Usage
lmt_usg_52_amt_used	Usage

List of data elements

lmt_usg_52_crncy_cde	Usage
lmt_usg_52_nam	Usage
lmt_usg_52_nxt_beg_dat	Usage
lmt_usg_53_amt_used	Usage
lmt_usg_53_crncy_cde	Usage
lmt_usg_53_nam	Usage
lmt_usg_53_nxt_beg_dat	Usage
lmt_usg_54_amt_used	Usage
lmt_usg_54_crncy_cde	Usage
lmt_usg_54_nam	Usage
lmt_usg_54_nxt_beg_dat	Usage
lmt_usg_55_amt_used	Usage
lmt_usg_55_crncy_cde	Usage
lmt_usg_55_nam	Usage
lmt_usg_55_nxt_beg_dat	Usage
lmt_usg_56_amt_used	Usage
lmt_usg_56_crncy_cde	Usage
lmt_usg_56_nam	Usage
lmt_usg_56_nxt_beg_dat	Usage
lmt_usg_57_amt_used	Usage
lmt_usg_57_crncy_cde	Usage
lmt_usg_57_nam	Usage
lmt_usg_57_nxt_beg_dat	Usage
lmt_usg_58_amt_used	Usage
lmt_usg_58_crncy_cde	Usage
lmt_usg_58_nam	Usage
lmt_usg_58_nxt_beg_dat	Usage
lmt_usg_59_amt_used	Usage
lmt_usg_59_crncy_cde	Usage
lmt_usg_59_nam	Usage
lmt_usg_59_nxt_beg_dat	Usage
lmt_usg_5_amt_used	Usage
lmt_usg_5_crncy_cde	Card
	Positive_Balance
	Usage
lmt_usg_5_exp_dat	Card

	Positive_Balance
lmt_usg_5_nam	Card
	Positive_Balance
	Usage
lmt_usg_5_nxt_beg_dat	Usage
lmt_usg_5_prd_adnl_data	Card
	Positive_Balance
lmt_usg_5_prd_opt	Card
	Positive_Balance
lmt_usg_60_amt_used	Usage
lmt_usg_60_crncy_cde	Usage
lmt_usg_60_nam	Usage
lmt_usg_60_nxt_beg_dat	Usage
lmt_usg_61_amt_used	Usage
lmt_usg_61_crncy_cde	Usage
lmt_usg_61_nam	Usage
lmt_usg_61_nxt_beg_dat	Usage
lmt_usg_62_amt_used	Usage
lmt_usg_62_crncy_cde	Usage
lmt_usg_62_nam	Usage
lmt_usg_62_nxt_beg_dat	Usage
lmt_usg_63_amt_used	Usage
lmt_usg_63_crncy_cde	Usage
lmt_usg_63_nam	Usage
lmt_usg_63_nxt_beg_dat	Usage
lmt_usg_64_amt_used	Usage
lmt_usg_64_crncy_cde	Usage
lmt_usg_64_nam	Usage
lmt_usg_64_nxt_beg_dat	Usage
lmt_usg_65_amt_used	Usage
lmt_usg_65_crncy_cde	Usage
lmt_usg_65_nam	Usage
lmt_usg_65_nxt_beg_dat	Usage
lmt_usg_66_amt_used	Usage
lmt_usg_66_crncy_cde	Usage
lmt_usg_66_nam	Usage

List of data elements

lmt_usg_66_nxt_beg_dat	Usage
lmt_usg_67_amt_used	Usage
lmt_usg_67_crncy_cde	Usage
lmt_usg_67_nam	Usage
lmt_usg_67_nxt_beg_dat	Usage
lmt_usg_68_amt_used	Usage
lmt_usg_68_crncy_cde	Usage
lmt_usg_68_nam	Usage
lmt_usg_68_nxt_beg_dat	Usage
lmt_usg_69_amt_used	Usage
lmt_usg_69_crncy_cde	Usage
lmt_usg_69_nam	Usage
lmt_usg_69_nxt_beg_dat	Usage
lmt_usg_6_amt_used	Usage
lmt_usg_6_crncy_cde	Card
	Positive_Balance
	Usage
lmt_usg_6_exp_dat	Card
	Positive_Balance
lmt_usg_6_nam	Card
	Positive_Balance
	Usage
lmt_usg_6_nxt_beg_dat	Usage
lmt_usg_6_prd_adnl_data	Card
	Positive_Balance
lmt_usg_6_prd_opt	Card
	Positive_Balance
lmt_usg_70_amt_used	Usage
lmt_usg_70_crncy_cde	Usage
lmt_usg_70_nam	Usage
lmt_usg_70_nxt_beg_dat	Usage
lmt_usg_71_amt_used	Usage
lmt_usg_71_crncy_cde	Usage
lmt_usg_71_nam	Usage
lmt_usg_71_nxt_beg_dat	Usage
lmt_usg_72_amt_used	Usage

lmt_usg_72_crncy_cde	Usage
lmt_usg_72_nam	Usage
lmt_usg_72_nxt_beg_dat	Usage
lmt_usg_73_amt_used	Usage
lmt_usg_73_crncy_cde	Usage
lmt_usg_73_nam	Usage
lmt_usg_73_nxt_beg_dat	Usage
lmt_usg_74_amt_used	Usage
lmt_usg_74_crncy_cde	Usage
lmt_usg_74_nam	Usage
lmt_usg_74_nxt_beg_dat	Usage
lmt_usg_75_amt_used	Usage
lmt_usg_75_crncy_cde	Usage
lmt_usg_75_nam	Usage
lmt_usg_75_nxt_beg_dat	Usage
lmt_usg_76_amt_used	Usage
lmt_usg_76_crncy_cde	Usage
lmt_usg_76_nam	Usage
lmt_usg_76_nxt_beg_dat	Usage
lmt_usg_77_amt_used	Usage
lmt_usg_77_crncy_cde	Usage
lmt_usg_77_nam	Usage
lmt_usg_77_nxt_beg_dat	Usage
lmt_usg_78_amt_used	Usage
lmt_usg_78_crncy_cde	Usage
lmt_usg_78_nam	Usage
lmt_usg_78_nxt_beg_dat	Usage
lmt_usg_79_amt_used	Usage
lmt_usg_79_crncy_cde	Usage
lmt_usg_79_nam	Usage
lmt_usg_79_nxt_beg_dat	Usage
lmt_usg_7_amt_used	Usage
lmt_usg_7_crncy_cde	Usage
lmt_usg_7_nam	Usage
lmt_usg_7_nxt_beg_dat	Usage
lmt_usg_80_amt_used	Usage

List of data elements

lmt_usg_80_crncy_cde	Usage
lmt_usg_80_nam	Usage
lmt_usg_80_nxt_beg_dat	Usage
lmt_usg_81_amt_used	Usage
lmt_usg_81_crncy_cde	Usage
lmt_usg_81_nam	Usage
lmt_usg_81_nxt_beg_dat	Usage
lmt_usg_82_amt_used	Usage
lmt_usg_82_crncy_cde	Usage
lmt_usg_82_nam	Usage
lmt_usg_82_nxt_beg_dat	Usage
lmt_usg_83_amt_used	Usage
lmt_usg_83_crncy_cde	Usage
lmt_usg_83_nam	Usage
lmt_usg_83_nxt_beg_dat	Usage
lmt_usg_84_amt_used	Usage
lmt_usg_84_crncy_cde	Usage
lmt_usg_84_nam	Usage
lmt_usg_84_nxt_beg_dat	Usage
lmt_usg_85_amt_used	Usage
lmt_usg_85_crncy_cde	Usage
lmt_usg_85_nam	Usage
lmt_usg_85_nxt_beg_dat	Usage
lmt_usg_8_amt_used	Usage
lmt_usg_8_crncy_cde	Usage
lmt_usg_8_nam	Usage
lmt_usg_8_nxt_beg_dat	Usage
lmt_usg_9_amt_used	Usage
lmt_usg_9_crncy_cde	Usage
lmt_usg_9_nam	Usage
lmt_usg_9_nxt_beg_dat	Usage
lmt_usg_nam	Limits.xml
	Limits_OLTP.xml
lmt_usg_prd_adnl_data	Limits
	Limits_OLTP
lmt_usg_prd_cutover_ofst	Institution

	Institution_OLTP
lmt_usg_prd_opt	Limits
	Limits_OLTP
LoadDataArea	ESATDL
LoadDataBn	ATMCNFG
LoadPrflTx	ATMCNFG.xml
	ESATDS1
LoadTmrLng	ESATDD1
LoadTmrPrflTx	ESATDS1
	LTMRPRFL.xml
load_config_id	ATM_DD1
load_data_bin	ATM_CONF
load_group_area	ATM_DS1
	ATM_DS1_OLTP
load_group_id	ATM_CONF.xml
	ATM_DD1
load_prfl	ATM_CONF.xml
	ATM_CONSUMER_MEDIA.xml
	ATM_CONSUMER_MEDIA_OLTP.xml
	ATM_DS1
	ATM_DS1_OLTP
	ATM_MBYTE_XLATE.xml
	ATM_MBYTE_XLATE_OLTP.xml
	ATM_OP_CDE.xml
	ATM_OP_CDE_OLTP.xml
	ATM_STATE_SCRN.xml
	ATM_STATE_SCRN_OLTP.xml
load_tkn_repl	ATM_CONF
local_pin_vrfy_typ	ATM_PRFL
	ATM_PRFL_OLTP
local_txn_dat	Interac_Admin
local_txn_tim	Interac_Admin
Location	Users
LogAuthDestRespTx	APCF
LogConnNum	HSMCNFG
logon_fail_cnt	Equens_Interface

logon_key_typ	Equens_Interface_OLTP Equens_Interface Equens_Interface_OLTP
logon_retry	Equens_Interface Equens_Interface_OLTP
logon_sppt	Interface_Manager
logon_timr_typ	Banknet_Group_Timers.xml
logon_typ	Interface_Manager
LogTm	EVENTLOG.xml
log_extrn_msg	GISO_ACQ_MSG_HND GISO_ACQ_MSG_HND_OLTP GISO_ISS_MSG_HND GISO_ISS_MSG_HND_OLTP
log_only_cnt	ATM_DD1 ATM_PREV_TTL
long_blz	BLZ_Map BLZ_Map2_OLTP.xml BLZ_Map_OLTP
low_hash_val	FPS_Queue_Profile FPS_Queue_Profile_OLTP Interface_SAF SAF_Manager_OLTP
low_key_range	file_part_catalog.xml
low_prfx	System_Algorithm_Config.xml System_Algorithm_Config_OLTP
lo_chk_num	Stop_Payment.xml
LrgMsgMxSzNum	ATDCNFG
lrg_msg_max_size	ATM_PRFL ATM_PRFL_OLTP
LstnID	LISTENER.xml
LstStlmTime	ESAPDT ESATDD1
lst_chng_dat	Ind_Sort_Code_Directory Ind_Sort_Code_Directory_OLTP
lst_cutover_ts	Merchant_Delivery_Channel
lst_data_rec_num	Batch_Auth_Posn

lst_dep_amt	Positive_Balance
lst_dep_dat	Positive_Balance
lst_jrnl_prfl	Journal_Query_Config_Output
lst_qry_ts	Journal_Query_Config
	Journal_Query_Position_Info.xml
lst_reset_dat	Admin_Card
lst_setl_ts	Merchant_Delivery_Channel
lst_snd_stat	FPS_Payment_Submission
lst_txn_dat_time	Merchant_Delivery_Channel
lst_txn_stat_enab	ATM_DD1
lst_used_dat	Admin_Card
lst_wdl_amt	Positive_Balance
lst_wdl_dat	Positive_Balance
lwr_ver_num	Interac_Base
	Interac_Base_OLTP
MacAthnMthdCd	MACPRFL
MacDataTypCd	MACPRFL
MacPrflTx	ESATDS1
	MACPRFL.xml
MacSecObjldTx	IFXDATA
MacSolStatCd	MACPRFL
MacSprtCd	MACPRFL
mac_auth_method	ATM_MAC
	ATM_MAC_OLTP
mac_bit_map	ISO_Message
	ISO_Message_OLTP
mac_char_set	ISO_Field
	ISO_Field_OLTP
mac_data_typ	ATM_MAC
	ATM_MAC_OLTP
mac_fail_cnt	Equens_Interface
	Equens_Interface_OLTP
mac_fail_max	Equens_Interface
	Equens_Interface_OLTP
mac_ind	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP

	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
mac_key_xchnng_flg	Interac_Interface
mac_sec_obj_id	ATM_IFXDATA
mac_sol_stat	ATM_MAC
	ATM_MAC_OLTP
mac_sppt_typ	BIC_Interface
	BIC_Interface_OLTP
mail_phn_crd_accpt_bus_cde	Merchant
	Merchant_OLTP
ManagerID	Users
MasterSecObjIdTx	IFXDATA
master_key_loaded	ATM_DD1
MaxBadLoginAttmpts	SecGrp
MaxConnNum	EXTRCNCT
	LISTENER
MaxConns	DATASRC
MaxNumOldPswds	PswdGrp
MaxPinLen	HSMCNFG
MaxPswdChgsPerDay	PswdGrp
MaxPswdLen	PswdGrp
MaxSessions	SecGrp
max_buf_lgth	Security_Device_Config
max_cnsc_sta_tmout_lmt	Interface_Manager
max_consec_err	Security_Device_Config
max_err_lmt	FPS_Batch_Config
	FPS_Batch_Config_OLTP
max_kam_cnsc_err_cnt	BASE24_KEYF
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
max_kam_err_cnt	Interface_Manager
max_kam_txn_cnt	BASE24_KEYF
	Interface_Manager
	Merchant_Channel_Profile

	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
max_kdt_err_cnt	Interface_Manager
max_kdt_txn_cnt	Interface_Manager
max_kek_err_cnt	Interface_Manager
max_kek_txn_cnt	Interface_Manager
max_kpt_cnsc_err_cnt	BASE24_KEYF
max_kpt_err_cnt	Interface_Manager
max_kpt_txn_cnt	BASE24_KEYF
	Interface_Manager
	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
max_lines_per_rcpt	ATM_PRFL
	ATM_PRFL_OLTP
max_outstnd_rqst_lmt	FPS_Batch_Config
	FPS_Batch_Config_OLTP
	Interface_Manager
	Interface_Station
max_pin_try	Prefix
	Prefix_OLTP
max_pre_auth_hlds	Prefix
	Prefix_OLTP
max_q_outstand_lmt	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP
max_q_retries_lmt	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP
max_rec_lgth	Journal_Query_Config_Output
max_retries	FPS_Batch_Config
	FPS_Batch_Config_OLTP
max_saf_outstnd_lmt	Audit_Store_and_Forward_Config
	Interface_Manager
	Interface_SAF
	SAF_Manager_OLTP

max_saf_retries_lmt	Audit_Store_and_Forward_Config Interface_Manager Interface_SAF SAF_Manager_OLTP
mbr_lgth	Prefix Prefix_OLTP
mcc	GICC_Channel
mci_criteria_typ_1	Banknet_Institution_Id Banknet_Institution_Id2 Banknet_Institution_Id2_OLTP Banknet_Institution_Id_OLTP
mci_criteria_typ_2	Banknet_Institution_Id Banknet_Institution_Id2 Banknet_Institution_Id2_OLTP Banknet_Institution_Id_OLTP
mci_criteria_typ_3	Banknet_Institution_Id Banknet_Institution_Id2 Banknet_Institution_Id2_OLTP Banknet_Institution_Id_OLTP
mci_criteria_typ_4	Banknet_Institution_Id Banknet_Institution_Id2 Banknet_Institution_Id2_OLTP Banknet_Institution_Id_OLTP
mci_criteria_typ_5	Banknet_Institution_Id Banknet_Institution_Id2 Banknet_Institution_Id2_OLTP Banknet_Institution_Id_OLTP
mci_criteria_typ_6	Banknet_Institution_Id Banknet_Institution_Id2 Banknet_Institution_Id2_OLTP Banknet_Institution_Id_OLTP
mci_criteria_val_1	Banknet_Institution_Id Banknet_Institution_Id2 Banknet_Institution_Id2_OLTP Banknet_Institution_Id_OLTP
mci_criteria_val_2	Banknet_Institution_Id

	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_criteria_val_3	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_criteria_val_4	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_criteria_val_5	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_criteria_val_6	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_id	Banknet_Configuration
	Banknet_Configuration_OLTP
	Banknet_Group_Timers.xml
	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_id_1	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_id_2	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_id_3	Banknet_Institution_Id
	Banknet_Institution_Id2

List of data elements

	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_id_4	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_id_5	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_id_6	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
mci_mult_ind	Banknet_Configuration
	Banknet_Configuration_OLTP
mc_mbr_id	EPSNET_Inst
	EPSNET_Institution_OLTP
MdINmbrTx	ESATDD1
mds_acq_bnk_id	MDS_Institution
	MDS_Institution_OLTP
mds_bin_rec	MDS_BIN_File_Updt
mds_proc_id	MDS_Interface
	MDS_Interface_OLTP
mds_sec_cde	MDS_Interface
	MDS_Interface_OLTP
media_act	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
media_lang_id	ATM_CONSUMER_MEDIA.xml
	ATM_CONSUMER_MEDIA_OLTP.xml
	ATM_MBYTE_XLATE.xml
	ATM_MBYTE_XLATE_OLTP.xml
media_typ	ATM_MBYTE_XLATE.xml
	ATM_MBYTE_XLATE_OLTP.xml
method_typ	System_Prefix
	System_Prefix_OLTP

MiddleName	Users
MinPswdAlphaChars	PswdGrp
MinPswdLen	PswdGrp
MinPswdNumChars	PswdGrp
min_fast_intrvl	Interac_Base
	Interac_Base_OLTP
min_oper_lvl	Acquirer_Txn_Allowed
	Acquirer_Txn_Allowed_OLTP
min_outbnd_auth_rqst_tim	Interface
	Interface_Issuer_OLTP
min_pacing_stagger	Interac_Base
	Interac_Base_OLTP
min_pmnt_amt	Positive_Balance
min_script_txn_cnt	Authorization_Script
	Authorization_Script_OLTP
min_slow_intrvl	Interac_Base
	Interac_Base_OLTP
missing_fld	GISO_IN_MSG_DEF
	GISO_IN_MSG_DEF_OLTP
MltpAcctAcqCapCd	ATDCNFG
MltpAcctMxNum	ATDCNFG
MltpAcctSlctCd	ATDCNFG
MltpTrnsPrRcptCd	ATDCNFG
mnem_nam	Script
	Script_OLTP
mngl_oper_nam	Exported_Operator_Documentation.xml
mnl_crd_entry_opt	Prefix
	Prefix_OLTP
MobileNum	Users
mob_phn	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
ModelNum	HSMCNFG
model_num	ATM_DD1
monitor_script_flg	Authorization_Script
	Authorization_Script_OLTP
mon_peak1_end_tm	ATM_PEAK_LOAD

	ATM_PEAK_LOAD_OLTP
mon_peak1_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
mon_peak1_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
mon_peak2_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
mon_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
mon_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
mon_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
mrch_acct_num	Merchant
	Merchant_OLTP
mrch_contract_co_cde	Cardnet_Interface
	Cardnet_Interface_OLTP
mrch_co_cde	Cardnet_Interface
	Cardnet_Interface_OLTP
mrch_id	Admin_Card
	Journal
	Journal_Key_Seq
	Journal_Key_Seq2
	Merchant.xml
	Merchant_Delivery_Channel
	Merchant_OLTP.xml
	Merch_Instr_Type_Relation_OLTP.xml
	Merch_Instr_Typ_Relation.xml
	Referral
	Referral_OLTP
mrch_id_alt	Merch_Instr_Type_Relation_OLTP
	Merch_Instr_Typ_Relation
mrch_nam	Merchant
	Merchant_OLTP
mrch_nam_mbyte	Merchant
mrch_num	Cardnet_Interface

	Cardnet_Interface_OLTP
	Cardnet_Interface_Terminal
	Cardnet_Interface_Terminal_OLTP
mrch_pgm	Banknet_Merchant_Program.xml
	Banknet_Merchant_Program_OLTP.xml
	Merch_Instr_Type_Relation_OLTP
	Merch_Instr_Typ_Relation
mrch_pgm_cde	Banknet_Merchant_Program
	Banknet_Merchant_Program_OLTP
mrch_stat	Merchant
	Merchant_OLTP
mrch_term_num	Cardnet_Interface
	Cardnet_Interface_OLTP
	Cardnet_Interface_Terminal
	Cardnet_Interface_Terminal_OLTP
mrch_vrfy_val	Merchant
	Merchant_OLTP
MsgBn	RVSLSAF
MsgCrdNmTx	ESATDD1
MsgCrdrNmTx	ESATDD1
MsgDataBn	ATMLOG
MsgDataEncrMthdCd	ATDCNFG
MsgDataEncrSprtCd	ATDCNFG
MsgDataEncrTypCd	ATDCNFG
MsgDrctTx	ATMLOG.xml
MsgDspn1CntNum	ESATDD1
MsgDspn2CntNum	ESATDD1
MsgDspn3CntNum	ESATDD1
MsgDspn4CntNum	ESATDD1
MsgDspn5CntNum	ESATDD1
MsgDspn6CntNum	ESATDD1
MsgDspn7CntNum	ESATDD1
MsgDspn8CntNum	ESATDD1
MsgFailTx	ATMLOG.xml
MsgFrmtTx	CACNFSAF
	RVSLSAF

List of data elements

MsgHdrLen	HSMCNFG
MsgId	MSGCNTX.xml
MsgIdTx	CACNFSAF
	CACNTX.xml
MsgLangIndNum	ESATDD1
MsgOpCdDataTx	ESATDD1
MsgPartNum	ATMLOG.xml
MsgPrclsID	ATMLOG
MsgSecObjIdTx	IFXDATA
msgs_to_fiid_cnt	ATM_DD1
	ATM_PREV_TTL
MsgTmVrntTx	ESATDD1
MsgUnqlIdTx	RVSLSAF
msg_cat	Acquirer_Txn_Allowed.xml
	Acquirer_Txn_Allowed_OLTP.xml
	Issuer_Txn_Allowed.xml
	Issuer_Txn_Allowed_OLTP.xml
msg_class	GISO_ACQ_MSG_HND.xml
	GISO_ACQ_MSG_HND_OLTP.xml
	GISO_IN_MSG_DEF.xml
	GISO_IN_MSG_DEF_OLTP
	GISO_ISS_MSG_HND.xml
	GISO_ISS_MSG_HND_OLTP.xml
	GISO_OUT_MSG_DEF.xml
	GISO_OUT_MSG_DEF_OLTP.xml
	Interac_Admin
	Interac_Entry_Point
msg_coord_num	ATM_DD1
msg_encrypt_sppt	HISO87_Interface
	HISO87_Interface_OLTP
msg_fail_cnt	Equens_Interface
	Equens_Interface_OLTP
msg_fail_max	Equens_Interface
	Equens_Interface_OLTP
msg_hdr_mac_flg	ISO_Message
	ISO_Message_OLTP

msg_prfl	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
	ISO_Field.xml
	ISO_Field_OLTP.xml
	ISO_Message.xml
	ISO_Message_OLTP.xml
msg_sec_cde	EFunds_Interface
	EFunds_Interface_OLTP
	LIS5_Interface
	LIS5_Interface_OLTP
	NYCE_Interface
	NYCE_Interface_OLTP
	Presto_Interface
	Presto_Interface_OLTP
	Pulse_Interface
	Pulse_Interface_OLTP
	Star_Interface
	Star_Interface_OLTP
	Visa_DPS_Interface
	Visa_DPS_Interface_OLTP
msg_set	Fifth_Third_Intf
	Fifth_Third_Intf_OLTP
msg_typ	Active_Script_Statistics.xml
	Authorization_Script.xml
	Authorization_Script_OLTP.xml
	FPID_History
	GISO_IN_MSG_DEF.xml
	GISO_IN_MSG_DEF_OLTP.xml
	GISO_OUT_MSG_DEF.xml
	GISO_OUT_MSG_DEF_OLTP.xml
	ISO_FLD_DEFN.xml
	ISO_FLD_DEFN_OLTP.xml
	ISO_Message.xml
	ISO_Message_OLTP.xml

msg_type
MssgAtmpNum
MssgCtgrCd
MssgEntrTm
MssgFrmtClasTx
MssgStatNum
MssgTx
mstr1_export_futr_hdr

mstr1_export_futr_kam

mstr1_export_futr_keyx

mstr1_export_futr_vvk

mstr1_hdr
mstr1_import_futr_hdr
mstr1_import_futr_kam
mstr1_import_futr_keyx
mstr1_import_futr_vvk
mstr1_import_kkt_am_futr_hdr
mstr1_import_kkt_am_futr_kam
mstr1_import_kkt_am_futr_keyx
mstr1_import_kkt_am_futr_vvk
mstr1_import_kkt_dt_futr_hdr
mstr1_import_kkt_dt_futr_kam
mstr1_import_kkt_dt_futr_keyx
mstr1_import_kkt_dt_futr_vvk
mstr1_import_kkt_pt_futr_hdr
mstr1_import_kkt_pt_futr_kam
mstr1_import_kkt_pt_futr_keyx
mstr1_import_kkt_pt_futr_vvk
mstr1_kam
mstr1_keyx

Journal_Data_Suppression.xml
Journal_Data_Suppression_OLTP.xml
SIS_ASYNC_DEST_MAP
CTVRSF
APCF.xml
CTVRSF.xml
EXTRCNCT
CTVRSF
EVENTLOG
Channel_Security_Future
Interchange_Security_Future
Channel_Security_Future
Interchange_Security_Future
Channel_Security_Future
Interchange_Security_Future
Channel_Security_Future
Interchange_Security_Future
Channel_Security
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Interchange_Security_Future
Channel_Security
Channel_Security

mstr1_lgth	Channel_Security
mstr1_old_hdr	Channel_Security
mstr1_old_kam	Channel_Security
mstr1_old_keyx	Channel_Security
mstr1_old_vvk	Channel_Security
mstr1_vvk	Channel_Security
mstr2_hdr	Channel_Security
mstr2_kam	Channel_Security
mstr2_keyx	Channel_Security
mstr2_lgth	Channel_Security
mstr2_old_hdr	Channel_Security
mstr2_old_kam	Channel_Security
mstr2_old_keyx	Channel_Security
mstr2_old_vvk	Channel_Security
mstr2_vvk	Channel_Security
mstr_sec_obj_id	ATM_IFXDATA
mthd	EMV_Iss_Auth_Dta.xml
	EMV_Iss_Auth_Dta_OLTP.xml
mti_bcd_flg	ISO_Field
	ISO_Field_OLTP
mti_mac_flg	ISO_Message
	ISO_Message_OLTP
mti_prev	GICC_Channel
multi_byte_chars	ATM_MBYTE_XLATE.xml
	ATM_MBYTE_XLATE_OLTP.xml
multi_byte_xlate_descr	ATM_MBYTE_XLATE
	ATM_MBYTE_XLATE_OLTP
multi_char_use	CUP_Interface
	CUP_Interface_OLTP
mult_tran_per_rcpt	ATM_PRFL
	ATM_PRFL_OLTP
MxLnsPrRcptNum	ATDCNFG
m_i_fld	dal_tbl
NAC_chan_prfl	HPDH_Configuration
	HPDH_Configuration_OLTP
	HPDH_NAC_Term.xml

NAC_id	HPDH_NAC_Term_OLTP.xml
	HPDH_NMS_Term.xml
	HPDH_NMS_Term_OLTP.xml
nam_spc	IFX_Host_Interface
	IFX_Host_Interface_OLTP
NcdCIsOnMsdsCd	ATDCNFG
NcdNValFrChckCd	ATDCNFG
NcdNValFrCrdtCd	ATDCNFG
NcdNValFrSvngCd	ATDCNFG
NcdRtTrnsNmbrTx	ATDCNFG
ncd_close_on_msds	ATM_PRFL
	ATM_PRFL_OLTP
ncd_non_val_checking	ATM_PRFL
	ATM_PRFL_OLTP
ncd_non_val_credit	ATM_PRFL
	ATM_PRFL_OLTP
ncd_non_val_savings	ATM_PRFL
	ATM_PRFL_OLTP
ncd_route_num	ATM_PRFL
	ATM_PRFL_OLTP
ncr_pin_ver_num	NCR_PIN_Verification.xml
	NCR_PIN_Verification_OLTP.xml
nde_nam	Interface_Station
neg_data_acss_cde	JCB_Interface
	JCB_Interface_OLTP
netwk_asgn_tcc	Banknet_Configuration
	Banknet_Configuration_OLTP
netwk_id	Instrum_Typ_Interchange_Rel
	Instrum_Typ_Interchange_Rel_OLTP
netwk_mgmt_opt	LIS5_Interface
	LIS5_Interface_OLTP
net_send_thrhd_stat	FPS_Member
	FPS_Member_OLTP
net_ttl_supported	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
new_post_dat	ATM_DD1

new_term_fiid	TERM_LN_FIID_MAP
	TERM_LN_FIID_MAP_OLTP
new_term_ln	TERM_LN_FIID_MAP
	TERM_LN_FIID_MAP_OLTP
next_out_setl_dat	SPAN2_Interface
NmbrOfChckNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfCmrcDpstNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfCrdsRtndNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfCshDpstNum	ESAPDT
	ESATDD1
NmbrOfDpstNum	CTVRSAP
NmbrOfEmvFBckNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfEnvlDpstNum	ESAPDT
	ESATDD1
NmbrOfLgOnlyNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfMsgTFiidNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfPhCPrchNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfPymnNum	CTVRSAP
	ESAPDT
	ESATDD1
NmbrOfScsfTrnsNum	CTVRSAP
	ESAPDT

	ESATDD1
NmbrOfTopUpNum	CTVRSAF
	ESAPDT
	ESATDD1
NmbrOfUnscTrnsNum	CTVRSAF
	ESAPDT
	ESATDD1
NmbrSmrtCrdLdsNum	CTVRSAF
	ESAPDT
	ESATDD1
nmm_enbl_flg	Interface_Manager
nmm_mac_opt	HISO87_Interface
	HISO87_Interface_OLTP
nmm_msg_rsn_cde	AMEX_CAPN_Interface
	AMEX_CAPN_Interface_OLTP
nmm_timr_lmt	Banknet_Configuration
	Banknet_Configuration_OLTP
	Interface_Manager
NMS_chan_prfl	HPDH_Configuration
	HPDH_Configuration_OLTP
	HPDH_NMS_Term.xml
	HPDH_NMS_Term_OLTP.xml
nms_id	HPDH_NAC_Term.xml
	HPDH_NAC_Term_OLTP.xml
notes	Merchant
	Merchant_Delivery_Channel
notes_mbyte	Merchant
	Merchant_Delivery_Channel
no_surch_mbr_prfl	Surcharge_Country_Code
	Surcharge_Country_Code_OLTP
nrml_pcng_timr_id	Interac_Base
nrt_rqst_typ	PRM_Interface
	PRM_Interface_OLTP
ntfy_intrvl	Security_Device_Config
num_atmdd2_recs	ATM_DD2
num_crypto_keys	EMV_Security

	EMV_Security_OLTP
num_days_in_admin	Interac_Base
	Interac_Base_OLTP
num_err	FPS_Batch_Control
num_iss	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
num_iss_sta_avail	Interface_Manager
num_jrnl_rec	Journal
	Journal_Continuation
	Journal_Key_Seq
	Journal_Key_Seq2
num_of_btchs	Merchant_Delivery_Channel
num_of_crds_ret	Merchant_Delivery_Channel
num_of_shifts	Merchant_Delivery_Channel
num_params	Script
	Script_Configuration
	Script_OLTP
num_proc	FPS_Batch_Control
num_recs	FPS_Batch_Control
NwPstnDtTx	ESATDD1
nxt_onl_dat_prd	Prefix
	Prefix_OLTP
nxt_pmnt_dat	Positive_Balance
nxt_qry_ts	Journal_Query_Config
nyce_bin_rec	NYCE_BIN_File_Updt
oar_acq_cap	ATM_PRFL
	ATM_PRFL_OLTP
oar_max_accts	ATM_PRFL
	ATM_PRFL_OLTP
ObjectID	PermDetl.xml
obj_id	Journal_Data_Suppression.xml
	Journal_Data_Suppression_OLTP
offl_bad_pin_tries_act	Prefix
	Prefix_OLTP
offl_pin_mgmt	Prefix
	Prefix_OLTP

offl_pin_sppt_dat	Prefix
	Prefix_OLTP
old_key_timr_lmt	BASE24_KEYF
	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
online_ind	ATM_DD1
OnLnIndCd	ESATDD1
onl_key_amt	ATM_DD1
	Journal
	Journal_Continuation.xml
	Journal_Key_Seq.xml
	Journal_Key_Seq2.xml
	Referral.xml
	Referral_OLTP.xml
onl_key_discrim	ATM_DD1
onl_key_pan	ATM_DD1
onl_key_seq_num	ATM_DD1
OnUsCrdtNum	CTVRSF
	ESAPDT
	ESATDD1
OnUsDbtsNum	CTVRSF
	ESAPDT
	ESATDD1
on_us_credits	ATM_DD1
	ATM_PREV_TTL
on_us_debits	ATM_DD1
	ATM_PREV_TTL
open_ind	ATM_DD1
oper_cash_access	ATM_OPER
	ATM_OPER_OLTP
oper_descr	Exported_Operator_Documentation
oper_envmt	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
oper_grp_id	ATM_OPER.xml

oper_id	ATM_OPER_OLTP.xml
	ATM_OPER.xml
	ATM_OPER_OLTP.xml
oper_nam	Exported_Operator_Documentation
oper_param_descr_1	Exported_Operator_Documentation
oper_param_descr_10	Exported_Operator_Documentation
oper_param_descr_2	Exported_Operator_Documentation
oper_param_descr_3	Exported_Operator_Documentation
oper_param_descr_4	Exported_Operator_Documentation
oper_param_descr_5	Exported_Operator_Documentation
oper_param_descr_6	Exported_Operator_Documentation
oper_param_descr_7	Exported_Operator_Documentation
oper_param_descr_8	Exported_Operator_Documentation
oper_param_descr_9	Exported_Operator_Documentation
oper_param_io_1	Exported_Operator_Documentation
oper_param_io_10	Exported_Operator_Documentation
oper_param_io_2	Exported_Operator_Documentation
oper_param_io_3	Exported_Operator_Documentation
oper_param_io_4	Exported_Operator_Documentation
oper_param_io_5	Exported_Operator_Documentation
oper_param_io_6	Exported_Operator_Documentation
oper_param_io_7	Exported_Operator_Documentation
oper_param_io_8	Exported_Operator_Documentation
oper_param_io_9	Exported_Operator_Documentation
oper_param_typ_1	Exported_Operator_Documentation
oper_param_typ_10	Exported_Operator_Documentation
oper_param_typ_2	Exported_Operator_Documentation
oper_param_typ_3	Exported_Operator_Documentation
oper_param_typ_4	Exported_Operator_Documentation
oper_param_typ_5	Exported_Operator_Documentation
oper_param_typ_6	Exported_Operator_Documentation
oper_param_typ_7	Exported_Operator_Documentation
oper_param_typ_8	Exported_Operator_Documentation
oper_param_typ_9	Exported_Operator_Documentation
oper_prereq	Exported_Operator_Documentation
oper_rtrn_descr	Exported_Operator_Documentation

oper_rtrn_typ	Exported_Operator_Documentation
OpnIndCd	ESATDD1
opn_dat	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
OpptGrpTx	OPTRCPT
OpptIDNum	OPERID.xml
optional_rcpt_typ	ATM_PRFL
	ATM_PRFL_OLTP
OptionDescr	WEBAPPOPTS
	WEBUSROPTS
OptionKey	WEBAPPOPTS.xml
	WEBUSROPTS.xml
OptionValue	WEBAPPOPTS
	WEBUSROPTS
optnl_rcpt_inop_gp	ATM_DS1
	ATM_DS1_OLTP
optnl_rcpt_ld_grp	ATM_DS1
	ATM_DS1_OLTP
OptnRcptPrflTx	ESATDS1
	OPTRCPT.xml
OptnRcptTypCd	ATDCNFG
opt_data_1	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_10	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_2	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_3	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_4	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_5	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_6	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_7	SPDH_opt_resp_data

	SPDH_opt_resp_data_OLTP
opt_data_8	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_data_9	SPDH_opt_resp_data
	SPDH_opt_resp_data_OLTP
opt_in_bit_map	ISO_Message
	ISO_Message_OLTP
opt_out_bit_map	ISO_Message
	ISO_Message_OLTP
op_cde_buf	ATM_OP_CDE.xml
	ATM_OP_CDE_OLTP.xml
orig_acct	FPS_Payment_Submission
orig_acct_addr	FPS_Payment_Submission
orig_acct_nam	FPS_Payment_Submission
orig_crncy_cde	FPS_Payment_Submission
orig_cr_inst	FPS_Payment_Submission
orig_id	BNFT_Interface
	BNFT_Interface_OLTP
	HISO87_Interface
	HISO87_Interface_OLTP
orig_setl_dat	Interac_Admin
orig_txn_fee	Interac_Admin
othr_nam	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
outbnd_auth_rqst_tim_lmt	Interface
	Interface_Issuer_OLTP
outbnd_iv_hdr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_iv_kam	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_iv_keyx	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam1_hdr	Channel_Security

	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam1_kam	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam1_keyx	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam1_vvk	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam2_hdr	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam2_kam	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam2_keyx	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam2_vvk	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam_futr_hdr	Channel_Security_Future
	Interchange_Security_Future
outbnd_kam_futr_kam	Channel_Security_Future
	Interchange_Security_Future
outbnd_kam_futr_keyx	Channel_Security_Future
	Interchange_Security_Future
outbnd_kam_futr_vvk	Channel_Security_Future
	Interchange_Security_Future
outbnd_kam_idx	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam_key_typ	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kam_old_hdr	Channel_Security

outbnd_kam_old_kam	Channel_Security
outbnd_kam_old_keyx	Channel_Security
outbnd_kam_old_vvk	Channel_Security
outbnd_kdt1_lvl1_futr_hdr	Channel_Security_Future
outbnd_kdt1_lvl1_futr_kam	Channel_Security_Future
outbnd_kdt1_lvl1_futr_keyx	Channel_Security_Future
outbnd_kdt1_lvl1_futr_vvk	Channel_Security_Future
outbnd_kdt1_lvl1_hdr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt1_lvl1_kam	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt1_lvl1_keyx	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt1_lvl1_old_hdr	Channel_Security
outbnd_kdt1_lvl1_old_kam	Channel_Security
outbnd_kdt1_lvl1_old_keyx	Channel_Security
outbnd_kdt1_lvl1_old_vvk	Channel_Security
outbnd_kdt1_lvl1_vvk	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt1_lvl2_futr_hdr	Channel_Security_Future
outbnd_kdt1_lvl2_futr_kam	Channel_Security_Future
outbnd_kdt1_lvl2_futr_keyx	Channel_Security_Future
outbnd_kdt1_lvl2_futr_vvk	Channel_Security_Future
outbnd_kdt1_lvl2_hdr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt1_lvl2_kam	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt1_lvl2_keyx	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP

outbnd_kdt1_lvl2_old_hdr	Channel_Security
outbnd_kdt1_lvl2_old_kam	Channel_Security
outbnd_kdt1_lvl2_old_keyx	Channel_Security
outbnd_kdt1_lvl2_old_vvk	Channel_Security
outbnd_kdt1_lvl2_vvk	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl1_hdr	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl1_kam	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl1_keyx	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl1_vvk	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl2_hdr	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl2_kam	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl2_keyx	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt2_lvl2_vvk	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt_idx	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt_key_typ	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt_lgth	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_kdt_lvl1_futr_hdr	Interchange_Security_Future
outbnd_kdt_lvl1_futr_kam	Interchange_Security_Future
outbnd_kdt_lvl1_futr_keyx	Interchange_Security_Future
outbnd_kdt_lvl1_futr_vvk	Interchange_Security_Future
outbnd_kdt_lvl2_futr_hdr	Interchange_Security_Future

outbnd_kdt_lvl2_futr_kam	Interchange_Security_Future
outbnd_kdt_lvl2_futr_keyx	Interchange_Security_Future
outbnd_kdt_lvl2_futr_vvk	Interchange_Security_Future
outbnd_kek_cntr	Interac_Interface
outbnd_key_seq_num	Futr_Key
outbnd_kpt1_hdr	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
outbnd_kpt1_kam	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
outbnd_kpt1_keyx	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
outbnd_kpt1_vvk	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
outbnd_kpt2_hdr	Interchange_Security
	Interchange_Security_OLTP
outbnd_kpt2_kam	Interchange_Security
	Interchange_Security_OLTP
outbnd_kpt2_keyx	Interchange_Security
	Interchange_Security_OLTP
outbnd_kpt2_vvk	Interchange_Security
	Interchange_Security_OLTP
outbnd_kpt_futr_hdr	Interchange_Security_Future
outbnd_kpt_futr_kam	Interchange_Security_Future
outbnd_kpt_futr_keyx	Interchange_Security_Future
outbnd_kpt_futr_vvk	Interchange_Security_Future
outbnd_kpt_hdr	Futr_Key
outbnd_kpt_idx	Interchange_Security
	Interchange_Security_OLTP

outbnd_kpt_kam	Futr_Key
outbnd_kpt_keyx	Futr_Key
outbnd_kpt_lgth	Interchange_Security
	Interchange_Security_OLTP
outbnd_kpt_vvk	Futr_Key
outbnd_old_data_timr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_old_mac_timr	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
outbnd_old_pin_timr	Interchange_Security
	Interchange_Security_OLTP
outbnd_sta_nam	HPDH_NAC_Term
	HPDH_NAC_Term_OLTP
	HPDH_NMS_Term
	HPDH_NMS_Term_OLTP
	Inbound_Station_OLTP
	Interface_Station
	Outbound_Station_OLTP.xml
outbnd_u_kam_cntr	BIC_Interface
	BNFT_Interface
	Interchange_Security
	Interchange_Security_OLTP
outbnd_u_kpt_cntr	BIC_Interface
	BNFT_Interface
	Interchange_Security
	Interchange_Security_OLTP
outstnd_cnt	Interface_Station
ovrdrft_options	Prefix
	Prefix_OLTP
ovrld_timr_lmt	Interface_Manager
ovrld_ts	Interface_Station
ovrrde_chan_dat_tim_flg	SPDH_Configuration
	SPDH_Configuration_OLTP
ovr_act	Route

	Route_OLTP
ovr_flr_alt1_adv1_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt1_adv1_nam	Route
	Route_OLTP
ovr_flr_alt1_adv1_req	Route
	Route_OLTP
ovr_flr_alt1_adv2_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt1_adv2_nam	Route
	Route_OLTP
ovr_flr_alt1_adv2_req	Route
	Route_OLTP
ovr_flr_alt1_auth_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt1_auth_nam	Route
	Route_OLTP
ovr_flr_alt1_impact1_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt1_impact1_nam	Route
	Route_OLTP
ovr_flr_alt1_impact2_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt1_impact2_nam	Route
	Route_OLTP
ovr_flr_alt1_prescrn_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt1_prescrn_nam	Route
	Route_OLTP
ovr_flr_alt2_adv1_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt2_adv1_nam	Route
	Route_OLTP
ovr_flr_alt2_adv1_req	Route
	Route_OLTP
ovr_flr_alt2_adv2_cmpnt_id	Route

	Route_OLTP
ovr_flr_alt2_adv2_nam	Route
	Route_OLTP
ovr_flr_alt2_adv2_req	Route
	Route_OLTP
ovr_flr_alt2_auth_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt2_auth_nam	Route
	Route_OLTP
ovr_flr_alt2_impact1_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt2_impact1_nam	Route
	Route_OLTP
ovr_flr_alt2_impact2_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt2_impact2_nam	Route
	Route_OLTP
ovr_flr_alt2_prescrn_cmpnt_id	Route
	Route_OLTP
ovr_flr_alt2_prescrn_nam	Route
	Route_OLTP
ovr_flr_pri_adv21_cmpnt_id	Route
	Route_OLTP
ovr_flr_pri_adv21_nam	Route
	Route_OLTP
ovr_flr_pri_adv21_req	Route
	Route_OLTP
ovr_flr_pri_adv22_cmpnt_id	Route
	Route_OLTP
ovr_flr_pri_adv22_nam	Route
	Route_OLTP
ovr_flr_pri_adv22_req	Route
	Route_OLTP
ovr_flr_pri_auth_cmpnt_id	Route
	Route_OLTP
ovr_flr_pri_auth_nam	Route

	Route_OLTP
ovr_flr_pri_impact1_cmpnt_id	Route
	Route_OLTP
ovr_flr_pri_impact1_nam	Route
	Route_OLTP
ovr_flr_pri_impact2_cmpnt_id	Route
	Route_OLTP
ovr_flr_pri_impact2_nam	Route
	Route_OLTP
ovr_flr_pri_prescreen_cmpnt_id	Route
	Route_OLTP
ovr_flr_pri_prescreen_nam	Route
	Route_OLTP
OwnerID	Filters
	FLTXROLE.xml
	PermGrp
	Perms
	PswdGrp.xml
	Roles.xml
	RolXPmGp.xml
	SecGrp.xml
	Users
	USRXFILT.xml
	UsrXRole.xml
pacing_abnormal_lmt	Interac_Base
	Interac_Base_OLTP
pacing_normal_lmt	Interac_Base
	Interac_Base_OLTP
pacing_timr_lmt	Interac_Base
	Interac_Base_OLTP
pad	EMV_Iss_Auth_Dta
	EMV_Iss_Auth_Dta_OLTP
pan	Card.xml
	Card_Account.xml
	CARD_ACCOUNT_MBYTE.xml
	Card_Block.xml

	Card_Block_OLTP.xml
	Card_Impacts.xml
	Check_Status.xml
	EMV_Script_Context.xml
	Interac_Admin
	Journal
	Journal_Continuation.xml
	Journal_Key_Seq.xml
	Journal_Key_Seq2.xml
	Referral.xml
	Referral_OLTP.xml
	Store_and_Forward.xml
	Totals_Entry.xml
	Totals_Entry2.xml
pan_access_typ	Prefix
	Prefix_OLTP
pan_app_seq_num	EMV_Script_Context.xml
pan_hash	Interface_SAF.xml
	Interface_SAF_OLTP
	Issuer_Profile_Map.xml
	Issuer_Profile_Map_OLTP
	SAF_Manager_OLTP
	Store_and_Forward
pan_lgth	Interac_ATM_IIN_OLTP.xml
	Interac_POS_IIN_OLTP.xml
	Interchange_Prefix.xml
	Interchange_Prefix_OLTP.xml
	Prefix.xml
	Prefix_Block.xml
	Prefix_Block_OLTP.xml
	Prefix_OLTP.xml
	System_Algorithm_Config.xml
	System_Algorithm_Config_OLTP.xml
pan_pad	IBM_DES
	IBM_DES_OLTP
pan_prev	GICC_Channel

pan_vrfy_lgth	IBM_DES
	IBM_DES_OLTP
pan_vrfy_ofst	IBM_DES
	IBM_DES_OLTP
ParamLgthShort	LCONF
ParamTxtTx	LCONF
param_typ_01	Script_Configuration
param_typ_02	Script_Configuration
param_typ_03	Script_Configuration
param_typ_04	Script_Configuration
param_typ_05	Script_Configuration
param_typ_06	Script_Configuration
param_typ_07	Script_Configuration
param_typ_08	Script_Configuration
param_typ_09	Script_Configuration
param_typ_10	Script_Configuration
ParentTaskID	Tasks
partial_pan_lgth	Identikey
	Identikey_OLTP
partial_pan_ofst	Identikey
	Identikey_OLTP
part_auth_alwd	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
Password	Password
	PswdHist.xml
PasswordGroupID	PswdGrp.xml
	SecGrp
payments_amt	ATM_DD1
	ATM_PREV_TTL
payments_cnt	ATM_DD1
	ATM_PREV_TTL
pbit_bcd_flg	ISO_Field
	ISO_Field_OLTP
pbit_mac_flg	ISO_Message

	ISO_Message_OLTP
pci_lgth	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
pci_mask	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
pci_ofst	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
perf_ext_apprv_cnt	Interface_Manager
perf_ext_auth_tim	Interface_Manager
perf_ext_bad_pin_cnt	Interface_Manager
perf_ext_cnt	Interface_Manager
perf_ext_deny_cnt	Interface_Manager
perf_ext_key_sync_cnt	Interface_Manager
perf_ext_tmout_cnt	Interface_Manager
perf_int_apprv_cnt	Interface_Manager
perf_int_auth_tim	Interface_Manager
perf_int_bad_pin_cnt	Interface_Manager
perf_int_cnt	Interface_Manager
perf_int_deny_cnt	Interface_Manager
perf_int_key_sync_cnt	Interface_Manager
perf_int_ttl_tim	Interface_Manager
perf_saf_cnt	Interface_Manager
perf_saf_tim	Interface_Manager
perf_saf_tim_max	Interface_Manager
perf_stat_updt_intrvl	Interface_Manager
perf_ts	Interface_Manager
PermissionGroupID	PermGrp.xml
	PmGpXPm.xml
	RolXPmGp.xml
PermissionID	PermDetl.xml
	Perms.xml
	PmGpXPm.xml
PermissionTypeCode	PermDetl
	PermType.xml
PermissionTypeName	PermType
pinpad_serial_num	Merchant_Delivery_Channel

PINSecObjIdTx	IFXDATA
PinValPad	HSMCNFG
pin_blk_frmt	EPSNET_Interface
	EPSNET_Interface_OLTP
pin_blk_typ	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
pin_captr_cap	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
pin_chng	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
pin_chng_dat	Card
pin_key_xchng_flg	Interac_Interface
pin_ofst_loc	Prefix
	Prefix_OLTP
pin_pad_char	BASE24_KEYF
	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
	Transport_Key
	Transport_Key_OLTP
pin_sec_obj_id	ATM_IFXDATA
pin_try_cntr_set	EMV_Iss_Auth_Dta
	EMV_Iss_Auth_Dta_OLTP
pin_try_reset_opt	Prefix
	Prefix_OLTP
pin_vrfy_prfl	Diebold_Number_Table.xml
	Diebold_Number_Table_OLTP.xml
	IBM_DES.xml
	IBM_DES_OLTP.xml
	Identikey.xml
	Identikey_OLTP.xml

pin_vrfy_typ

pk_enbl_flg

pk_beg_dat

pk_ca_pri_hdr

pk_ca_pri_kam

pk_ca_pri_keyx

pk_ca_pri_vvk

pk_ca_root_hdr

pk_ca_root_kam

pk_ca_root_keyx

pk_ca_root_vvk

pk_ca_scnd_hdr

pk_ca_scnd_kam

pk_ca_scnd_keyx

pk_ca_scnd_vvk

pk_cert

pk_data_signed

pk_end_dat

pk_epp_encipher_beg_dat

pk_epp_encipher_end_dat

pk_epp_encipher_hdr

pk_epp_encipher_kam

pk_epp_encipher_keyx

pk_epp_encipher_vvk

pk_epp_sig_beg_dat

pk_epp_sig_end_dat

pk_epp_sig_hdr

pk_epp_sig_kam

pk_epp_sig_keyx

pk_epp_sig_vvk

pk_hdr

NCR_PIN_Verification.xml

NCR_PIN_Verification_OLTP.xml

Visa_PVV.xml

Visa_PVV_OLTP.xml

Prefix

Prefix_OLTP

Security_Device_Config

Host_Public_Key_Security

Host_Public_Key_Security_Second

Host_Public_Key_Security_Second

Host_Public_Key_Security_Second

Host_Public_Key_Security_Second

Host_Public_Key_Security_Primary

Host_Public_Key_Security_Primary

Host_Public_Key_Security_Primary

Host_Public_Key_Security_Primary

Host_Public_Key_Security_Second

Host_Public_Key_Security_Second

Host_Public_Key_Security_Second

Host_Public_Key_Security_Second

Host_Public_Key_Security

Key_Token

Host_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Channel_Public_Key_Security

Host_Public_Key_Security

pk_host_nam	ATM_DS1
	ATM_DS1_OLTP
	Host_Public_Key_Security.xml
	Host_Public_Key_Security_Primary.xml
	Host_Public_Key_Security_Second.xml
pk_host_pri_hdr	Host_Public_Key_Security_Primary
pk_host_pri_kam	Host_Public_Key_Security_Primary
pk_host_pri_keyx	Host_Public_Key_Security_Primary
pk_host_pri_sig	Host_Public_Key_Security_Primary
pk_host_pri_vvk	Host_Public_Key_Security_Primary
pk_host_scnd_sig	Host_Public_Key_Security_Second
pk_impl	Channel_Public_Key_Security
	EPP_Serial_Number.xml
	Host_Public_Key_Security.xml
	Host_Public_Key_Security_Primary.xml
	Host_Public_Key_Security_Second.xml
pk_kam	Host_Public_Key_Security
pk_keyx	Host_Public_Key_Security
	Key_Token
pk_key_typ	Host_Public_Key_Security.xml
pk_sig	Key_Token
pk_vvk	Host_Public_Key_Security
plastic_typ	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
plus_pmc_id	Visa_Institution
	Visa_Institution_OLTP
pmnt_exchg_rate	FPS_Payment_Submission
pmnt_pri_avail_01	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_02	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_03	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_04	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_05	FPS_Member

	FPS_Member_OLTP
pmnt_pri_avail_06	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_07	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_08	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_09	FPS_Member
	FPS_Member_OLTP
pmnt_pri_avail_10	FPS_Member
	FPS_Member_OLTP
pmnt_pri_descr	FPS_Payment_Pri_Group
	FPS_Payment_Pri_Group_OLTP
pmnt_pri_grp	FPS_Payment_Pri_Group.xml
	FPS_Payment_Pri_Group_OLTP.xml
	FPS_Payment_Typ
	FPS_Payment_Typ_OLTP
	FPS_Queue_Assign.xml
	FPS_Queue_Assign_OLTP.xml
	FPS_Queue_Manager_OLTP.xml
	FPS_Queue_Profile.xml
	FPS_Queue_Profile_OLTP
pmnt_pri_grp_01	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_02	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_03	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_04	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_05	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_06	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_07	FPS_Member
	FPS_Member_OLTP

pmnt_pri_grp_08	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_09	FPS_Member
	FPS_Member_OLTP
pmnt_pri_grp_10	FPS_Member
	FPS_Member_OLTP
pmnt_q_flg	FPS_Payment_Typ
	FPS_Payment_Typ_OLTP
pmnt_rtrn_cde	FPS_Payment_Submission
pmnt_typ	FPID_History.xml
	FPS_Payment_Typ.xml
	FPS_Payment_Typ_OLTP.xml
pmnt_typ_avail	FPS_Payment_Typ
	FPS_Payment_Typ_OLTP
pmnt_typ_prfl	FPS_Batch_Config
	FPS_Batch_Config_OLTP
pmx_element	PMX
PortNum	HSMCNFG
posn_info_cleanup_tim	Batch_Auth_Config
	Batch_Auth_Config_OLTP
posn_info_retn	Batch_Auth_Config
	Batch_Auth_Config_OLTP
posn_updt_intrvl	Batch_Auth_Config
	Batch_Auth_Config_OLTP
postal_cde	ATM_DS1
	ATM_DS1_OLTP
	Card
	Institution
	Merchant
	Merchant_Delivery_Channel
	Merchant_OLTP
postal_cde_mbyte	ATM_DS1
	ATM_DS1_OLTP
	CARD_ACCOUNT_MBYTE
	Institution
	Merchant

post_dat	Merchant_Delivery_Channel ATM_DD1 ATM_PREV_TTL FPS_Cutover.xml
pos_acq_surch_prfl	HISO87_Interface HISO87_Interface_OLTP
pos_act_cde_prfl	HISO87_Interface HISO87_Interface_OLTP
pos_dest_circuit_inst_id	ABI_Interface ABI_Interface_OLTP
pos_dflt_rtlr	ABI_Interface ABI_Interface_OLTP
pos_fl2_type	ABI_Interface ABI_Interface_OLTP
pos_last_swi_setl_dat	SPAN2_Interface
pos_msg_prfl	HISO87_Interface HISO87_Interface_OLTP
pos_proc_cde_prfl	HISO87_Interface HISO87_Interface_OLTP
pos_rcncl_hour	ABI_Interface ABI_Interface_OLTP
pos_rcncl_min	ABI_Interface ABI_Interface_OLTP
pos_rcv_inst_id	ABI_Interface ABI_Interface_OLTP
pos_restart_1520_tim	ABI_Interface ABI_Interface_OLTP
pos_send_1220	ABI_Interface ABI_Interface_OLTP
pos_send_moto_1220	ABI_Interface ABI_Interface_OLTP
pos_slow_resp_to_congest	Interac_Base Interac_Base_OLTP
pos_slow_txn_cnt	Interac_Base
pos_timeouts_to_block	Interac_Base Interac_Base_OLTP

pos_timeout_txn_cnt	Interac_Base
pos_tkn_prfl	HISO87_Interface
	HISO87_Interface_OLTP
pos_tran_orig_inst_id	ABI_Interface
	ABI_Interface_OLTP
pos_txn_cde	POS_TC_Proc_Code.xml
	POS_Tran_Code_Proc_Code_OLTP.xml
	Proc_Code_POS_TC
	Proc_Code_POS_Tran_Code_OLTP
ppasn	Channel_Security
PrcsDscrTx	PROCESS
PrcsID	APPLCNFG.xml
	EVENTLOG.xml
	EXTRCNCT.xml
	HSMCNFG.xml
	LISTENER.xml
	PROCESS.xml
PrcsThrdTx	EVENTLOG.xml
predicted_crd_vrfy_rslts	Chip_Authentication
	Chip_Authentication_OLTP
predicted_init_crd_vrfy_rslts	Chip_Authentication
	Chip_Authentication_OLTP
prev_crd_num	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prev_cr_amt	GICC_Channel
prev_cr_cnt	GICC_Channel
prev_cr_rvsl_amt	GICC_Channel
prev_cr_rvsl_cnt	GICC_Channel
prev_db_amt	GICC_Channel
prev_db_cnt	GICC_Channel
prev_db_rvsl_amt	GICC_Channel
prev_db_rvsl_cnt	GICC_Channel
prev_net_adj_amt	Merchant_Delivery_Channel
prev_net_adj_cnt	Merchant_Delivery_Channel
prev_net_cr_amt	Merchant_Delivery_Channel
prev_net_cr_cnt	Merchant_Delivery_Channel

prev_net_db_amt	Merchant_Delivery_Channel
prev_net_db_cnt	Merchant_Delivery_Channel
prev_net_dc_adj_amt	Merchant_Delivery_Channel
prev_net_dc_adj_cnt	Merchant_Delivery_Channel
prev_net_dc_cr_amt	Merchant_Delivery_Channel
prev_net_dc_cr_cnt	Merchant_Delivery_Channel
prev_net_dc_db_amt	Merchant_Delivery_Channel
prev_net_dc_db_cnt	Merchant_Delivery_Channel
prev_net_setl_amt	GICC_Channel
pre_auth_adnl	Pre_Auth_Hold
prfx	Interchange_Prefix.xml
	Interchange_Prefix_OLTP.xml
	Prefix.xml
	Prefix_Block.xml
	Prefix_Block_OLTP.xml
	Prefix_OLTP.xml
prfx_blk_ts	Prefix_Block
	Prefix_Block_OLTP
prfx_lgth	System_Algorithm_Config.xml
	System_Algorithm_Config_OLTP
PrimaryKey	AudDtIPK
pri_dob	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
pri_govt_id	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
pri_nam	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prm_actvty_stat	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_addr_1	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prm_addr_2	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prm_city	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prm_clos_dat	Merchant_Master_File

	Merchant_Master_File_OLTP
prm_clos_rsn_cde	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cntct_email_addr	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cntct_nam	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cntct_phn_1	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cntct_phn_2	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cred_bur_scr	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cust_id	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prm_cust_mstr_amt	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cust_mstr_dat	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cust_mstr fld_1	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cust_mstr fld_2	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cust_num_1	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_cust_num_2	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_ecom_ind	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_email_addr	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prm_expect_mm_vol	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_expect_mm_vol_num	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_expect_yy_vol	Merchant_Master_File

	Merchant_Master_File_OLTP
prm_expect_yy_vol_num	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_fiid	Credit_Debit_Master_File.xml
	Credit_Debit_Master_File_OLTP.xml
	Merchant_Master_File.xml
	Merchant_Master_File_OLTP.xml
prm_first_actv_dat	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_fi_ind	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_flr_lmt	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_fltr_fld	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_last_actv_amt	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_last_actv_dat	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_norm_bus_hh_end	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_norm_bus_hh_strt	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_opn_dat	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_own_chng_dat	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_own_govt_id	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_own_nam	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_own_typ	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_pan	Credit_Debit_Master_File.xml
	Credit_Debit_Master_File_OLTP.xml
prm_postal_cde	Credit_Debit_Master_File

	Credit_Debit_Master_File_OLTP
prm_retl_addr_1	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_addr_2	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_bus_nam	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_city	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_clas	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_cntry	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_dba_nam	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_id	Merchant_Master_File.xml
	Merchant_Master_File_OLTP.xml
prm_retl_pstl_cde	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_retl_st	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_seasnl_cde	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sec_addr_1	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sec_addr_2	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sec_city	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sec_cntry	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sec_corp_nam	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sec_postal_cde	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sec_st	Merchant_Master_File

	Merchant_Master_File_OLTP
prm_setl_acct_detl_1	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_setl_acct_detl_2	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_sic_cde	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_st	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
prm_stat	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_store_num	Merchant_Master_File
	Merchant_Master_File_OLTP
prm_typ_good_serv	Merchant_Master_File
	Merchant_Master_File_OLTP
PrntSubTypeCd	RECEIPT.xml
PrntTypeCd	RECEIPT.xml
prnt_ind	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
ProcCodeTx	CTVRSF
ProcessNameTx	LCONF.xml
proc_cde	Acquirer_Txn_Allowed.xml
	Acquirer_Txn_Allowed_OLTP.xml
	ATM_OP_CDE
	ATM_OP_CDE_OLTP
	ATM_TC_Proc_Code
	ATM_Tran_Code_Proc_Code_OLTP
	GISO_IN_MSG_DEF.xml
	GISO_IN_MSG_DEF_OLTP.xml
	GISO_OUT_MSG_DEF.xml
	GISO_OUT_MSG_DEF_OLTP.xml
	HISO87_Proc_Txn.xml
	HISO87_Proc_Txn_OLTP.xml
	Interac_Admin
	ISO_PROC_CODE
	ISO_PROC_CODE_OLTP

	Issuer_Txn_Allowed.xml
	Issuer_Txn_Allowed_OLTP.xml
	POS_TC_Proc_Code
	POS_Tran_Code_Proc_Code_OLTP
	Proc_Code_ATM_TC.xml
	Proc_Code_ATM_Tran_Code_OLTP.xml
	PROC_CODE_ISO.xml
	PROC_CODE_ISO_OLTP.xml
	Proc_Code_POS_TC.xml
	Proc_Code_POS_Tran_Code_OLTP.xml
	Surcharge.xml
	Surcharge_OLTP.xml
proc_cde_extrn	ISO_PROC_CODE.xml
	ISO_PROC_CODE_OLTP.xml
	PROC_CODE_ISO
	PROC_CODE_ISO_OLTP
proc_cde_prfl	ATM_TC_Proc_Code.xml
	ATM_Tran_Code_Proc_Code_OLTP.xml
	HISO93_Interface
	HISO93_Interface_OLTP
	Interface
	Interface_OLTP
	ISO_PROC_CODE.xml
	ISO_PROC_CODE_OLTP.xml
	Merchant_Delivery_Channel
	POS_TC_Proc_Code.xml
	POS_Tran_Code_Proc_Code_OLTP.xml
	Proc_Code_ATM_TC.xml
	Proc_Code_ATM_Tran_Code_OLTP.xml
	PROC_CODE_ISO.xml
	PROC_CODE_ISO_OLTP.xml
	Proc_Code_POS_TC.xml
	Proc_Code_POS_Tran_Code_OLTP.xml
	Visa_Interface
	Visa_Interface_OLTP
ProdIndAdnITx	LCONF

ProdIndTx	LCONF
ProductID	WEBAPPS
prod_typ	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
proto_hdr_req	PRM_Interface
	PRM_Interface_OLTP
proto_intf	Security_Device_Config
pro_invld_resp	GISO_ACQ_MSG_HND
	GISO_ACQ_MSG_HND_OLTP
pro_saf_ind	GISO_ISS_MSG_HND
	GISO_ISS_MSG_HND_OLTP
pro_typ	Trace_Config.xml
pro_unmatched_rvsl	GISO_ACQ_MSG_HND
	GISO_ACQ_MSG_HND_OLTP
PrtcCd	EXTRCNCT
PrtcDfnd1Tx	EXTRCNCT
	LISTENER
PrtcDfnd2Tx	EXTRCNCT
	LISTENER
PrtcDfnd3Tx	EXTRCNCT
	LISTENER
PrtcOptnList	EXTRCNCT
	LISTENER
prtcpt_prcsr_id	Circuit_Interface
	Circuit_Interface_OLTP
prtcpt_prcsr_pswd	Circuit_Interface
	Circuit_Interface_OLTP
prty_rte_ind	Visa_Interface
	Visa_Interface_OLTP
PrvOnLnIndCd	ESATDD1
PrvOpnIndCd	ESATDD1
prvt_use_array	ATM_DD1
	ATM_PREV_TTL
PstlCdTx	ESATDS1
PstnDtTx	CTVRSF
	ESAPDT

	ESATDD1
PswdExpWarnDays	PswdGrp
PswdLifetime	PswdGrp
public_key_gen	Host_Public_Key_Security
	Host_Public_Key_Security_Primary
purch_amt	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
pvki	Admin_Card
pvk_scheme	NCR_PIN_Verification
	NCR_PIN_Verification_OLTP
pvv	Admin_Card
	Card
pvv_lgth	Prefix
	Prefix_OLTP
pv_keya_prfl	Prefix
	Prefix_OLTP
qry_nam	Perusal_Script.xml
	Perusal_Script_OLTP.xml
qry_typ	Perusal_Script.xml
	Perusal_Script_OLTP.xml
queue_tim_lmt	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
q_asgn_nam	FPS_Queue_Assign
	FPS_Queue_Assign_OLTP
q_delay_timr_lmt	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP
q_mgr_nam	FPS_Queue_Manager_OLTP
	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP.xml
q_reset_timr_lmt	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP
q_send_lmt	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP
q_timr_lmt	FPS_Queue_Profile
	FPS_Queue_Profile_OLTP

rbld_rspns	OLTP_Warmboot
rbld_sbmttd	OLTP_Warmboot
rcncl_slot_num	Interac_Base
	Interac_Base_OLTP
RcptPrflTx	ESATDS1
	RCPTRQRD.xml
	RECEIPT.xml
RcptRqrdPrflTx	ESATDS1
RcptTranAprvFlag	RCPTRQRD
RcptTranDenyFlag	RCPTRQRD
RcptTypeCd	RECEIPT.xml
rcpt_acq_txn_cde	ATM_REQ_RCPT.xml
	ATM_REQ_RCPT_OLTP.xml
rcpt_from_acct_typ	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
rcpt_lang	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
rcpt_prfl	ATM_DS1
	ATM_DS1_OLTP
	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
	ATM_REQ_RCPT.xml
	ATM_REQ_RCPT_OLTP.xml
rcpt_prnt_sub_typ	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
rcpt_prnt_typ	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
rcpt_rqrd_prfl	ATM_DS1
	ATM_DS1_OLTP
rcpt_sub_typ	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
rcpt_tmpl_data	ATM_RECEIPT
	ATM_RECEIPT_OLTP
rcpt_to_acct_typ	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
rcpt_txn_aprv_ind	ATM_REQ_RCPT

	ATM_REQ_RCPT_OLTP
rcpt_txn_deny_ind	ATM_REQ_RCPT
	ATM_REQ_RCPT_OLTP
rcpt_typ	ATM_RECEIPT.xml
	ATM_RECEIPT_OLTP.xml
rcv_bnk_id	Interface_FPS
	Interface_FPS_OLTP
rcv_id	BNFT_Interface
	BNFT_Interface_OLTP
	HISO87_Interface
	HISO87_Interface_OLTP
rcv_id_cde	BNFT_Interface
	BNFT_Interface_OLTP
	Discover_Interface
	Discover_Interface_OLTP
	SPAN2_Interface
	SPAN2_Interface_OLTP
rcv_inst_id	AS2805_Interface
	AS2805_Interface_OLTP
	CUP_Interface
	CUP_Interface_OLTP
rcv_ovrrd_inst_id	BIC_Interface
	BIC_Interface_OLTP
rcv_ovrrd_inst_id_flg	BIC_Interface
	BIC_Interface_OLTP
ReadOnly	Filters
	Roles
reclass_cde	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
RecNumTx	ATMCNFG.xml
RecTypeCd	ATMCNFG.xml
rec_crte_dat	Interac_Admin.xml
rec_crte_tim	Interac_Admin.xml
rec_dat_mdfy	Journal_Profile_Group
	Journal_Profile_Group_OLTP
rec_frmt	Journal

List of data elements

	Journal_Key_Seq
	Journal_Key_Seq2
rec_load_num	ATM_CONF.xml
rec_num	ATM_DD2.xml
	Card_Account.xml
	Journal_Continuation.xml
	Pre_Auth_Hold.xml
	Usage.xml
rec_num_bin	TBP_Daily.xml
	Trace.xml
rec_read_intrvl	Interface_Manager
rec_typ	ATM_SSB_BNA
	SPDH_ISO_Response_Text.xml
	SPDH_ISO_Response_Text_OLTP.xml
rec_typ_cde	ATM_CONF.xml
refer_thrhd_lmt	Authorization_Script
	Authorization_Script_OLTP
refr_id	Card
	Card_Block
	Card_Block_OLTP
	Check_Status
	Positive_Balance
	Prefix_Block
	Prefix_Block_OLTP
	Stop_Payment
refr_ts	Card
	Card_Block
	Card_Block_OLTP
	Check_Status
	Positive_Balance
	Prefix_Block
	Prefix_Block_OLTP
	Stop_Payment
regn_mbyte	Institution
reg_rptg	FPS_Payment_Submission
remt_nde_id	Interac_Admin

repeat_window	Interface_FPS Interface_FPS_OLTP
req_fld	GISO_IN_MSG_DEF GISO_IN_MSG_DEF_OLTP
req_in_bit_map	ISO_Message ISO_Message_OLTP
req_opt_out_bit_map	ISO_Message ISO_Message_OLTP
resp_cde	Interac_Admin SPDH_ISO_Response_Text.xml SPDH_ISO_Response_Text_OLTP.xml
resp_cond_fid_map	SPDH_Message SPDH_Message_OLTP
resp_cond_subfid6_map	SPDH_Message SPDH_Message_OLTP
resp_cond_subfid7_map	SPDH_Message SPDH_Message_OLTP
resp_cond_subfid8_map	SPDH_Message SPDH_Message_OLTP
resp_cond_subfid9_map	SPDH_Message SPDH_Message_OLTP
resp_fid_map	SPDH_Message SPDH_Message_OLTP
resp_mac_fid_map	SPDH_Message SPDH_Message_OLTP
resp_mac_subfid6_map	SPDH_Message SPDH_Message_OLTP
resp_mac_subfid7_map	SPDH_Message SPDH_Message_OLTP
resp_mac_subfid8_map	SPDH_Message SPDH_Message_OLTP
resp_mac_subfid9_map	SPDH_Message SPDH_Message_OLTP
resp_subfid6_map	SPDH_Message SPDH_Message_OLTP
resp_subfid7_map	SPDH_Message

resp_subfid8_map	SPDH_Message_OLTP
	SPDH_Message
resp_subfid9_map	SPDH_Message_OLTP
	SPDH_Message
resp_txt	SPDH_Message_OLTP
	SPDH_ISO_Response_Text
	SPDH_ISO_Response_Text_OLTP
restart_flg	Journal_Query_Config
restart_prd_adnl_data	Journal_Query_Config
restart_prd_opt	Journal_Query_Config
restart_tim	Journal_Query_Config
retn_posn_flg	Journal_Query_Config
retn_prd	Journal_Profile_Group
	Journal_Profile_Group_OLTP
retrv_ref_num	Interac_Admin
retrv_term_cnt_ind	ATM_DS1
	ATM_DS1_OLTP
rfrl_ind	Referral
	Referral_OLTP
rfrl_phn_num	Institution
	Institution_OLTP
RltdEvntIDTx	EVNTLOG
rmt_info	FPS_Payment_Submission
roc_chk	Prefix
	Prefix_OLTP
roc_chk_pre_scrn	Prefix
	Prefix_OLTP
roc_prfl	EMV_Reason_Online_Code_OLTP.xml
	EMV_Reason_Online_Code_Status.xml
	Prefix
	Prefix_OLTP
RoleID	FLTXROLE.xml
	Roles.xml
	RoIXPmGp.xml
	UsrXRole.xml
roll_kek2	AS2805_Config

	AS2805_Config_OLTP
root_flg	Script_Configuration
RowAccess	APPLCNFG
rpt_asgn_nam	Journal_Query_Config
rpt_hdr_script_nam	Journal_Query_Config_Output
rpt_trlr_script_nam	Journal_Query_Config_Output
RqstAdptClasTx	LISTENER
rqst_alt_act	HISO87_Interface
	HISO87_Interface_OLTP
rqst_dat	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
rqst_fid_map	SPDH_Message
	SPDH_Message_OLTP
rqst_mac_fid_map	SPDH_Message
	SPDH_Message_OLTP
rqst_mac_subfid6_map	SPDH_Message
	SPDH_Message_OLTP
rqst_mac_subfid7_map	SPDH_Message
	SPDH_Message_OLTP
rqst_mac_subfid8_map	SPDH_Message
	SPDH_Message_OLTP
rqst_mac_subfid9_map	SPDH_Message
	SPDH_Message_OLTP
rqst_subfid6_map	SPDH_Message
	SPDH_Message_OLTP
rqst_subfid7_map	SPDH_Message
	SPDH_Message_OLTP
rqst_subfid8_map	SPDH_Message
	SPDH_Message_OLTP
rqst_subfid9_map	SPDH_Message
	SPDH_Message_OLTP
RqUIDTx	RQUID.xml
rquid_id	ATM_RQUID.xml
rquid_user_data	ATM_RQUID
rsn_onl_cde	EMV_Reason_Online_Code_OLTP.xml
	EMV_Reason_Online_Code_Status.xml

rsn_onl_cde_descr	Reason_Online_Code_Description.xml
RspnMsgFrmtClasTx	Reason_Online_Code_Description
RspnMsgFrmtMthdTx	LISTENER
rte_aud_flg	LISTENER
	Route
	Route_OLTP
rte_cde	Acquirer_Issuer_Relation
	Acquirer_Issuer_Relation_OLTP
	Route.xml
	Route_OLTP.xml
rte_prfl	Institution
	Institution_ID_OLTP
rte_to_star	Star_Netwk_Rel_OLTP
	STAR_Network_Rel
rte_typ	FPS_Member
	FPS_Member_OLTP
	Prefix
	Prefix_OLTP
	System_Prefix
	System_Prefix_OLTP
rtf_del_on_send	Real_Time_Feed_Config
	Real_Time_Feed_Config_OLTP
rtf_frmt	Real_Time_Feed_Config
	Real_Time_Feed_Config_OLTP
rtrn_amt	Merchant_Delivery_Channel
rtrn_cnt	Merchant_Delivery_Channel
rtrn_lmt_amt	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
rtrn_lmt_cnt	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
rtrn_pmnt_id	FPS_Payment_Submission
rtrn_thrhd_act	Merchant_Delivery_Channel
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP

rtrn_typ	Script Script_Configuration Script_OLTP
RtryAtmpNum	EXTRCNCT
rttn	Account_Routing.xml Account_Routing_OLTP.xml Check_Status.xml
rt_rqst_typ	PRM_Interface PRM_Interface_OLTP
rvsl_msg_rsn_cde	AMEX_CAPN_Interface AMEX_CAPN_Interface_OLTP
rvsl_opt	HISO87_Interface HISO87_Interface_OLTP
rvsl_resp	Merchant_Delivery_Channel_Profil Merchant_Delivery_Chan_Prfl_OLTP SPDH_Configuration SPDH_Configuration_OLTP
saf_alarm_timr_lmt	Interac_Base Interac_Base_OLTP
saf_asgn_nam	Interface_Manager Interface_SAF Interface_SAF_OLTP SAF_Manager_OLTP
saf_cnt	Audit_Store_and_Forward_Config
saf_cnt_updt_intrvl	Interface_Manager
saf_cont_flg	Audit_Store_and_Forward
saf_delay_timr_id	Interface_Manager
saf_delay_timr_lmt	Audit_Store_and_Forward_Config Interface_Manager Interface_SAF SAF_Manager_OLTP
saf_delay_timr_lmt_slow	Interface_SAF SAF_Manager_OLTP
saf_max_pcmt_full	Interface_Manager
saf_max_rec_cnt	Interface_Manager
saf_mde	Interface_Manager

saf_mgr_nam	Interface_SAF Interface_SAF_OLTP SAF_Manager_OLTP.xml
saf_msg	Audit_Store_and_Forward Store_and_Forward
saf_nrml_pcmt_full	Interface_Manager
saf_outstnd_asgn_nam	Interface_Manager
saf_outstnd_cnt	Audit_Store_and_Forward_Config Interface_Station
saf_pcmt_full_err	Interface_Manager
saf_pcmt_full_warning	Interface_Manager
saf_pend_timr_flg	Audit_Store_and_Forward_Config
saf_pro_dat	Interac_Base
saf_rate	Interface_Manager
saf_rate_fast_ts	Interface_Manager
saf_rate_slow_ts	Interface_Manager
saf_rec_cnt	Interface_Manager
saf_rec_lmt	Interac_Base Interac_Base_OLTP
saf_repeat_flg	Store_and_Forward
saf_reset_timr_lmt	Interface_SAF SAF_Manager_OLTP
saf_send_cnt	Audit_Store_and_Forward
saf_send_lmt	Interface_SAF SAF_Manager_OLTP
saf_seq_num	Audit_Store_and_Forward.xml
saf_status	Audit_Store_and_Forward_Config
saf_timr_lmt	Audit_Store_and_Forward_Config Interface_Manager Interface_SAF SAF_Manager_OLTP
sat_peak1_end_tm	ATM_PEAK_LOAD ATM_PEAK_LOAD_OLTP
sat_peak1_load_grps	ATM_PEAK_LOAD ATM_PEAK_LOAD_OLTP
sat_peak1_strt_tm	ATM_PEAK_LOAD

	ATM_PEAK_LOAD_OLTP
sat_peak2_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sat_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sat_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sat_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
Sb1AmntOfChckNum	ESAPDT
	ESATDD1
Sb1DpstSqncNmbrNum	ESAPDT
	ESATDD1
Sb1NmbrOfChckNum	ESAPDT
	ESATDD1
Sb2AmntOfChckNum	ESAPDT
	ESATDD1
Sb2DpstSqncNmbrNum	ESAPDT
	ESATDD1
Sb2NmbrOfChckNum	ESAPDT
	ESATDD1
Sb3AmntOfChckNum	ESAPDT
	ESATDD1
Sb3DpstSqncNmbrNum	ESAPDT
	ESATDD1
Sb3NmbrOfChckNum	ESAPDT
	ESATDD1
Sb4AmntOfChckNum	ESAPDT
	ESATDD1
Sb4DpstSqncNmbrNum	ESAPDT
	ESATDD1
Sb4NmbrOfChckNum	ESAPDT
	ESATDD1
SbChkSprtCd	ESATDD1
SbjcTx	EVNTLOG
scndry_id	Pre_Auth_Hold.xml

script_apprv_cnt
script_delivered_flg
script_deny_cnt
script_descr
script_enabled_flg

script_nam

script_refer_cnt
script_txn_cnt
script_waiting_flg
SearchField
SearchValue
secure_msg_cnfdntl_key

secure_msg_cnfdntl_key_hdr

secure_msg_cnfdntl_key_kam

secure_msg_cnfdntl_vvk

secure_msg_key

secure_msg_key_chk_values

Usage.xml

Active_Script_Statistics
EMV_Script_Context
Active_Script_Statistics
Script_Configuration
Active_Script_Statistics
Authorization_Script
Authorization_Script_OLTP
Authorization_Script
Authorization_Script_OLTP
HISO87_Interface
HISO87_Interface_OLTP
Perusal_Script
Perusal_Script_OLTP
Real_Time_Feed_Config
Real_Time_Feed_Config_OLTP

Script.xml

Script_Configuration.xml

Script_OLTP.xml

Script_Source.xml

Active_Script_Statistics
Active_Script_Statistics
EMV_Script_Context
SrchFld
SrchFld
EMV_Security
EMV_Security_OLTP
EMV_Security
EMV_Security_OLTP
EMV_Security
EMV_Security_OLTP
EMV_Security
EMV_Security_OLTP
EMV_Security
EMV_Security_OLTP
EMV_Security

	EMV_Security_OLTP
secure_msg_key_hdr	EMV_Security
	EMV_Security_OLTP
secure_msg_key_kam	EMV_Security
	EMV_Security_OLTP
SecurityGroupID	SecGrp.xml
	Users
security_cde	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
sec_nam	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
sec_txn_lmt	FPS_Payment_Typ
	FPS_Payment_Typ_OLTP
sec_txn_lmt_prev	FPS_Payment_Typ
	FPS_Payment_Typ_OLTP
send_bnk_id	FPS_Payment_Submission
send_cnt	FPS_Payment_Submission
send_cntr_id	Cardnet_Interface
	Cardnet_Interface_OLTP
send_dat	FPID_History.xml
	FPS_Payment_Submission
send_fps_inst	FPID_History.xml
	FPS_Payment_Submission
send_pre_auth_compl	Visa_Interface
	Visa_Interface_OLTP
send_rqst_timeout	GISO_ACQ_MSG_HND
	GISO_ACQ_MSG_HND_OLTP
send_timr_lmt	FPS_Batch_Config
	FPS_Batch_Config_OLTP
send_unmatched_rvsl	GISO_ISS_MSG_HND
	GISO_ISS_MSG_HND_OLTP
	Interface
	Interface_Issuer_OLTP
sensor_array	ATM_DD1

Seq	AudDtlIPK.xml
	AuditDtl.xml
SeqNum	MSGCNTX.xml
seq_gen_num	GICC_Channel
seq_num	Banknet_Group_Timers.xml
	FPS_Payment_Submission.xml
	Merchant_Delivery_Channel
seq_num_char	Journal
	Journal_Continuation.xml
	Journal_Key_Seq.xml
	Journal_Key_Seq2.xml
	Referral.xml
	Referral_OLTP.xml
seq_num_prev	GICC_Channel
SessionExpireTS	ActSess
	ACTSESS2
SessionNum	ActSess.xml
	AuditTbl
SessionTimeout	ActSess
	ACTSESS2
	SecGrp
SessionTkn	ACTSESS2.xml
session_cnt	Equens_Interface
	Equens_Interface_OLTP
session_id	SIS_ASYNC_DEST_MAP.xml
session_max	Equens_Interface
	Equens_Interface_OLTP
session_num	Audit_Store_and_Forward.xml
setl_beg_ts	FPS_Cutover
setl_cyc_id	FPS_Cutover.xml
	Journal_Query_Config
setl_cyc_stat	FPS_Cutover
setl_cyc_typ	FPS_Cutover
setl_exp_ts	FPS_Cutover
setl_impact	Issuer_Txn_Allowed
	Issuer_Txn_Allowed_OLTP

setl_inst_id	AS2805_Interface AS2805_Interface_OLTP BIC_Interface BIC_Interface_OLTP FIS_Interface FIS_Interface_OLTP
setl_typ	AS2805_Interface AS2805_Interface_OLTP BIC_Interface BIC_Interface_OLTP BNFT_Interface BNFT_Interface_OLTP
severity	Event Event_OLTP
SeverityNum	EVENTLOG
severity_cde_extrn	IFX_Host_Action_Code_Int_Ext IFX_Host_Action_Cod_Int_Ext_OLTP
SFID	SrchFld.xml SrchXAdt.xml
SftwRIsTx	ESATDD1
sharing_group	ATM_PRFL ATM_PRFL_OLTP
shift_adj_amt	Merchant_Delivery_Channel
shift_adj_cnt	Merchant_Delivery_Channel
shift_cr_amt	Merchant_Delivery_Channel
shift_cr_cnt	Merchant_Delivery_Channel
shift_db_amt	Merchant_Delivery_Channel
shift_db_cnt	Merchant_Delivery_Channel
shift_dc_adj_amt	Merchant_Delivery_Channel
shift_dc_adj_cnt	Merchant_Delivery_Channel
shift_dc_cr_amt	Merchant_Delivery_Channel
shift_dc_cr_cnt	Merchant_Delivery_Channel
shift_dc_db_amt	Merchant_Delivery_Channel
shift_dc_db_cnt	Merchant_Delivery_Channel
shift_num	Journal Journal_Key_Seq

	Journal_Key_Seq2
	Merchant_Delivery_Channel
shift_ttl_supported	Merchant_Channel_Profile
	Merchant_Channel_Profile_OLTP
	Merchant_Delivery_Channel_Profil
	Merchant_Delivery_Chan_Prfl_OLTP
short_blz	BLZ_Map.xml
	BLZ_Map2_OLTP
	BLZ_Map_OLTP.xml
short_bnk_nam	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
short_brch_title	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
shrg_netwrk_cnct	Interface_Manager
ShrnGrpTx	CMPTPRFL
shr_grp_cde	Visa_Interface
	Visa_Interface_OLTP
sis_mq_object_name	SIS_ASYNC_DEST_MAP
sis_symbolic_name	SIS_ASYNC_DEST_MAP.xml
site_id	SIS_ASYNC_DEST_MAP.xml
	Totals_Entry2.xml
siv_bad_disp	Prefix
	Prefix_OLTP
siv_chk	Prefix
	Prefix_OLTP
siv_chk_typ	Prefix
	Prefix_OLTP
siv_not_prsn_disp	Prefix
	Prefix_OLTP
siv_prfl	Prefix
	Prefix_OLTP
sk_hdr	Host_Public_Key_Security
sk_host_pri_hdr	Host_Public_Key_Security_Primary
sk_host_pri_kam	Host_Public_Key_Security_Primary
sk_host_pri_keyx	Host_Public_Key_Security_Primary
sk_kam	Host_Public_Key_Security

sk_keyx	Host_Public_Key_Security
slow_percentage_lmt	Interac_Base
	Interac_Base_OLTP
sms_atm_msg_prfl	Visa_Interface
	Visa_Interface_OLTP
sms_pos_msg_prfl	Visa_Interface
	Visa_Interface_OLTP
smx_element	SMX
SnsrAryTx	ESATDD1
software_id	ATM_DD1
software_rls	ATM_DD1
some_bool_fld	dal_tbl
sort_cde	Ind_Sort_Code_Bic_OLTP
	Ind_Sort_Code_Directory.xml
	Ind_Sort_Code_Directory_OLTP.xml
sort_cde_rec	Ind_Sort_Code_Directory_Input
spf_chk_pre_scrn	Prefix
	Prefix_OLTP
spiood_lookup	SPDH_Configuration
	SPDH_Configuration_OLTP
SplyAryTx	ESATDD1
sprvsr_body	Ind_Sort_Code_Directory
	Ind_Sort_Code_Directory_OLTP
SrchAmntLmtCrncCd	SRCHPRFL
SrchAmntLmtIndCd	SRCHPRFL
SrchAmntLmtNum	SRCHPRFL
srch_order	System_Prefix.xml
	System_Prefix_OLTP
src_crncy_cde	Currency_Conversion_Rate.xml
	Currency_Conversion_Rate_OLTP.xml
	Linked_Currency.xml
	Linked_Currency_OLTP.xml
src_lgnt	System_Prefix.xml
	System_Prefix_OLTP.xml
src_rte_prfl	GISO_CRD_ACPT_RT
	GISO_CRD_ACPT_RT_OLTP

SrvclD	USRAULOG
srvc_nam	B24_filetyp_map.xml
	B24_filetyp_map_OLTP.xml
ssb1_check_amt	ATM_DD1
	ATM_PREV_TTL
ssb1_check_cnt	ATM_DD1
	ATM_PREV_TTL
ssb1_dep_seq_num	ATM_DD1
	ATM_PREV_TTL
ssb2_check_amt	ATM_DD1
	ATM_PREV_TTL
ssb2_check_cnt	ATM_DD1
	ATM_PREV_TTL
ssb2_dep_seq_num	ATM_DD1
	ATM_PREV_TTL
ssb3_check_amt	ATM_DD1
	ATM_PREV_TTL
ssb3_check_cnt	ATM_DD1
	ATM_PREV_TTL
ssb3_dep_seq_num	ATM_DD1
	ATM_PREV_TTL
ssb4_check_amt	ATM_DD1
	ATM_PREV_TTL
ssb4_check_cnt	ATM_DD1
	ATM_PREV_TTL
ssb4_dep_seq_num	ATM_DD1
	ATM_PREV_TTL
ssb_chk_suprt_ind	ATM_DD1
ssid	Event_Document.xml
	Exception_Log
SSIDOwnrIDTx	EVNTLOG
SSIDTx	EVNTLOG
SSIDVrsnTx	EVNTLOG
st	Institution
	Institution_OLTP
	Merchant

	Merchant_Delivery_Channel
	Merchant_OLTP
StartDate	Password
StartTime	SecGrp
star_bin_rec	Star_BIN_File_Updt
star_netwk_id	Star_Netwk_Rel_OLTP.xml
	STAR_Network_Rel.xml
star_ne_bin_rec	Star_NE_BIN_File_Updt
star_ne_netwk_id	Star_NE_Network_Rel.xml
	Star_NE_Network_Rel_OLTP.xml
StatConns	DATASRC
state_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn1_func_id	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn1_scrn_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn1_task	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn2_func_id	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn2_scrn_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn2_task	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn3_func_id	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn3_scrn_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn3_task	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn4_func_id	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn4_scrn_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn4_task	ATM_STATE_SCRN

	ATM_STATE_SCRN_OLTP
state_scrn5_func_id	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn5_scrn_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn5_task	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn6_func_id	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn6_scrn_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn6_task	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn7_func_id	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn7_scrn_num	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn7_task	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn_act_array	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn_cond	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
state_scrn_seq_num	ATM_STATE_SCRN.xml
	ATM_STATE_SCRN_OLTP.xml
state_scrn_task_buf	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
stat_cde_extrn	IFX_Host_Action_Code_Int_Ext
	IFX_Host_Action_Cod_Int_Ext_OLTP
sta_logon_typ	Interface_Station
StmnFrmtCd	STMPPRFL
StmnIgrnTxtCd	STMPPRFL
StmnLftMrgnNum	STMPPRFL
StmnLnsPrInchNum	STMPPRFL
StmnLnsPrPgNum	STMPPRFL
StmnRghtMrgnNum	STMPPRFL

stmtnt_data	ATM_STMNT_DATA
stmtnt_format	ATM_STMNT_PRNT ATM_STMNT_PRNT_OLTP
stmtnt_left_mrgn	ATM_STMNT_PRNT ATM_STMNT_PRNT_OLTP
stmtnt_lns_per_inch	ATM_STMNT_PRNT ATM_STMNT_PRNT_OLTP
stmtnt_lns_per_pg	ATM_STMNT_PRNT ATM_STMNT_PRNT_OLTP
stmtnt_prnt_prfl	ATM_DS1 ATM_DS1_OLTP ATM_STMNT_PRNT.xml ATM_STMNT_PRNT_OLTP.xml
stmtnt_right_mrgn	ATM_STMNT_PRNT ATM_STMNT_PRNT_OLTP
stmtnt_seq_num	ATM_STMNT_DATA.xml
stmtnt_txn_tm	ATM_STMNT_DATA
StmntData	STMTDATA
StmntPrntPrflTx	ESATDS1 STMPPRFL.xml
StmntSqncNmbrNum	STMTDATA.xml
stmt_num	Script.xml Script_OLTP
stmt_typ	Script Script_OLTP
stnd_in_auth_parm	AEGN_Interface AEGN_Interface_OLTP
stream_element	Stream Stream132 Stream_Binary
strt_ofst	Journal_Query_Config
st_mbyte	Merchant Merchant_Delivery_Channel
subsystem_id	Interac_Entry_Point
sub_brch_sfx	Ind_Sort_Code_Directory.xml Ind_Sort_Code_Directory_OLTP.xml

List of data elements

success_script_nam	Journal_Query_Config
sun_peak1_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sun_peak1_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sun_peak1_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sun_peak2_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sun_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sun_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
sun_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
supply_array	ATM_DD1
suppress_cnt_lmt	Event
	Event_OLTP
suppress_cnt_rmng	Event
suppress_rcpt	ATM_STATE_SCRN
	ATM_STATE_SCRN_OLTP
suppress_tim_lmt	Event
	Event_OLTP
suppress_ts	Event
suppress_typ	Event
	Event_OLTP
surch_fee_ind	Surcharge
	Surcharge_OLTP
surch_flat_fee	Surcharge
	Surcharge_OLTP
surch_max_ovrd	Surcharge
	Surcharge_OLTP
surch_min_txn_amt	Surcharge
	Surcharge_OLTP
surch_prcnt_fee	Surcharge
	Surcharge_OLTP

surch_rvsl_cde	Surcharge
	Surcharge_OLTP
sur_amt_ld_grp	ATM_DS1
	ATM_DS1_OLTP
sur_amt_lmt	ATM_SUR
	ATM_SUR_OLTP
sur_amt_lmt_curr	ATM_SUR
	ATM_SUR_OLTP
sur_amt_lmt_ind	ATM_DD1
sur_method	ATM_SUR
	ATM_SUR_OLTP
svc_ind	Security_Device_Config
SvrtNum	EVNTLOG
svs_mrch_num	SVS_Mrch_Num
	SVS_Mrch_Num_OLTP
swi_dat	Pulse_Switch_Date
swi_setl_dat	DIAS_Interface
	UAE_Interface
swi_setl_day	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
swi_setl_hour	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
swi_setl_min	Interface
	Interface_Acquirer_OLTP
	Interface_Issuer_OLTP
	Interface_OLTP
swi_setl_timr_id	Interface_Manager
swi_tim_zone_diff	Interface
	Interface_OLTP
sym_nam	Exception_Log
sym_pro_id	Trace.xml
sym_thrd_id	Trace.xml

SysAdminRoleProfl**TableName****tag_amt_flg****tag_id****tag_nam****TaskID****TaskIDTx****TblPrfxTx****TBMHoprThrs1Num****TBMHoprThrs2Num****TBMHoprThrs3Num****TBMHoprThrs4Num****TBMHoprThrs5Num****TBMHoprThrs6Num****TBMHoprThrs7Num****TBMHoprThrs8Num****TBMMxBIs1Num****TBMMxBIs2Num****TBMMxBIs3Num****TBMMxBIs4Num****TBMMxBIs5Num****TBMMxBIs6Num****TBMMxBIs7Num****TBMMxBIs8Num****TermAdrsTx****TermCntrTx****TermCntyTx****TermCrdtNum****TermCrncCd****TermCrncCdTx****SecGrp****AudDtlIPK.xml****AuditDtl.xml****Totals_Tag_Documentation****Totals_Tag_Documentation.xml****Totals_Tag_Documentation****Perms****TaskFlds.xml****TaskFnCs.xml****Tasks.xml****EVNTLOG****DATASRC****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****HPRPRFL****ESATDS1****ESATDS1****ESATDS1****CTVRSFAF****ESAPDT****ESATDD1****ATDCNFG****CTVRSFAF**

	ESAPDT
TermCtyTx	ESATDS1
TermDbtsNum	CTVRSF
	ESAPDT
	ESATDD1
TermIdTx	ATMLOG.xml
	BPDATA.xml
	CTVRSF
	ESAPDT.xml
	ESATDD1.xml
	ESATDD2.xml
	ESATDL.xml
	ESATDS1.xml
	IFXDATA.xml
	OPERID.xml
	STMTDATA.xml
TerminalObjIdTx	IFXDATA
TermInstIdTx	RECEIPT.xml
TermLctnIndCd	ESATDS1
TermMgmtExCnctIdTx	ATDCNFG
TermOwnrTx	ESATDS1
TermPrtcCd	ATDCNFG
TermSbPrtcCd	ATDCNFG
TermSrchMthdCd	SRCHPRFL
TermSrchPrflTx	ESATDS1
	SRCHPRFL.xml
TermStTx	ESATDS1
TermSuspAcct	CTVRSF
	ESATDS1
TermTypTx	ESATDS1
term_adrs	ATM_DS1
	ATM_DS1_OLTP
term_adrs_mbyte	ATM_DS1
	ATM_DS1_OLTP
term_bna_escr_notes_cnt	ATM_DD1
	ATM_PREV_TTL

List of data elements

term_bna_rjct_notes_cnt	ATM_DD1 ATM_PREV_TTL
term_bna_rtrn_notes_cnt	ATM_DD1 ATM_PREV_TTL
term_bna_vault_notes_cnt	ATM_DD1 ATM_PREV_TTL
term_branch	ATM_DS1 ATM_DS1_OLTP
term_branch_mbyte	ATM_DS1 ATM_DS1_OLTP
term_city	ATM_DS1 ATM_DS1_OLTP
term_city_mbyte	ATM_DS1 ATM_DS1_OLTP
term_cntr	ATM_DS1 ATM_DS1_OLTP
term_cntr_mbyte	ATM_DS1 ATM_DS1_OLTP
term_cnty	ATM_DS1 ATM_DS1_OLTP
term_cnty_mbyte	ATM_DS1 ATM_DS1_OLTP
term_credits	ATM_DD1 ATM_PREV_TTL
term_currency	ATM_PREV_TTL ATM_PRFL ATM_PRFL_OLTP
term_debits	ATM_DD1 ATM_PREV_TTL
term_descr	ATM_DS1 ATM_DS1_OLTP
term_descr_mbyte	ATM_DS1 ATM_DS1_OLTP
term_fiid	TERM_LN_FIID_MAP.xml TERM_LN_FIID_MAP_OLTP.xml
term_id	ATM_DD1.xml

	ATM_DD2.xml
	ATM_DIAL_UP_CMD.xml
	ATM_DS1.xml
	ATM_DS1_OLTP.xml
	ATM_IFXDATA.xml
	ATM_OPER.xml
	ATM_OPER_OLTP.xml
	ATM_PREV_TTL.xml
	ATM_SSB_BNA.xml
	ATM_SSB_CPL.xml
	ATM_STMNT_DATA.xml
	GICC_Acq_SGN.xml
	GICC_Iss_SGN.xml
	Interac_Admin
term_inact_prfl	ATM_DS1
	ATM_DS1_OLTP
	ATM_INACT.xml
	ATM_INACT_OLTP.xml
term_ind_array	ATM_DD1
term_lgnt	B24EPS_lgnt_map
	B24EPS_lgnt_map_OLTP
term_ln	TERM_LN_FIID_MAP.xml
	TERM_LN_FIID_MAP_OLTP.xml
term_loc_ind	ATM_PRFL
	ATM_PRFL_OLTP
term_mgt_ext_conn	ATM_PRFL
	ATM_PRFL_OLTP
term_obj_id	ATM_IFXDATA
term_ownr	ATM_DS1
	ATM_DS1_OLTP
term_ownr_mbyte	ATM_DS1
	ATM_DS1_OLTP
term_protocol	ATM_PRFL
	ATM_PRFL_OLTP
term_region	ATM_DS1
	ATM_DS1_OLTP

List of data elements

term_region_mbyte	ATM_DS1 ATM_DS1_OLTP
term_state	ATM_DS1 ATM_DS1_OLTP
term_state_mbyte	ATM_DS1 ATM_DS1_OLTP
term_sub_protocol	ATM_PRFL ATM_PRFL_OLTP
term_typ	ATM_CONSUMER_MEDIA.xml ATM_CONSUMER_MEDIA_OLTP.xml ATM_DS1 ATM_DS1_OLTP ATM_MBYTE_XLATE.xml ATM_MBYTE_XLATE_OLTP.xml ATM_OP_CDE.xml ATM_OP_CDE_OLTP.xml ATM_STATE_SCRN.xml ATM_STATE_SCRN_OLTP.xml
test_flg	EPSNET_Interface EPSNET_Interface_OLTP Interac_Base Interac_Base_OLTP
test_mde_flg	Cardnet_Interface Cardnet_Interface_OLTP
text	EXCPT
ThrdIDTx	EVNTLOG
thrhd_chk_amt	ATM_SSB_BIN ATM_SSB_BIN_OLTP
thrhd_chk_amt_cur_cde	ATM_SSB_BIN ATM_SSB_BIN_OLTP
thrhd_chk_dep_bin	ATM_SSB_BIN ATM_SSB_BIN_OLTP
thrhd_flr_lmt	Interface_Manager
thrhd_outstnd_rqst	Interface_Manager
thurs_peak1_end_tm	ATM_PEAK_LOAD ATM_PEAK_LOAD_OLTP

thurs_peak1_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
thurs_peak1_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
thurs_peak2_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
thurs_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
thurs_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
thurs_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tim	Stop_Payment
TimeOutNum	EXTRCNCT
timer_exp_ts	Banknet_Group_Timers
timr_id	Banknet_Group_Timers
	Interface_Station
timr_typ	Interface_Station
tim_ofst	Merchant
	Merchant_Delivery_Channel
	Merchant_OLTP
tkn0_lgth	Event
	Event_OLTP
tkn0_typ	Event
	Event_OLTP
tkn10_lgth	Event
	Event_OLTP
tkn10_typ	Event
	Event_OLTP
tkn11_lgth	Event
	Event_OLTP
tkn11_typ	Event
	Event_OLTP
tkn12_lgth	Event
	Event_OLTP
tkn12_typ	Event

	Event_OLTP
tkn13_lgth	Event
	Event_OLTP
tkn13_typ	Event
	Event_OLTP
tkn14_lgth	Event
	Event_OLTP
tkn14_typ	Event
	Event_OLTP
tkn15_lgth	Event
	Event_OLTP
tkn15_typ	Event
	Event_OLTP
tkn16_lgth	Event
	Event_OLTP
tkn16_typ	Event
	Event_OLTP
tkn17_lgth	Event
	Event_OLTP
tkn17_typ	Event
	Event_OLTP
tkn18_lgth	Event
	Event_OLTP
tkn18_typ	Event
	Event_OLTP
tkn19_lgth	Event
	Event_OLTP
tkn19_typ	Event
	Event_OLTP
tkn1_lgth	Event
	Event_OLTP
tkn1_typ	Event
	Event_OLTP
tkn2_lgth	Event
	Event_OLTP
tkn2_typ	Event

	Event_OLTP
tkn3_lgth	Event
	Event_OLTP
tkn3_typ	Event
	Event_OLTP
tkn4_lgth	Event
	Event_OLTP
tkn4_typ	Event
	Event_OLTP
tkn5_lgth	Event
	Event_OLTP
tkn5_typ	Event
	Event_OLTP
tkn6_lgth	Event
	Event_OLTP
tkn6_typ	Event
	Event_OLTP
tkn7_lgth	Event
	Event_OLTP
tkn7_typ	Event
	Event_OLTP
tkn8_lgth	Event
	Event_OLTP
tkn8_typ	Event
	Event_OLTP
tkn9_lgth	Event
	Event_OLTP
tkn9_typ	Event
	Event_OLTP
tkn_cnt	Event
	Event_OLTP
tkn_id	Token_Id_List.xml
tkn_id_buf	Token_Config
	Token_Config_OLTP
tkn_prfl	Token_Config.xml
	Token_Config_OLTP.xml

TMKSignSecObjIdTx	IFXDATA
TmOfstNum	CTVRSAP
	ESATDS1
tmout_cnt	Interface_Station
TmplDataTx	RECEIPT
tmx_element	TMX
ToAcntTypeCd	RECEIPT.xml
TotalEnvelopesNum	CTVRSAP
transit_bank_num	Merchant
	Merchant_OLTP
TranSqncNmbrNum	ESATDD1
	STMTDATA.xml
TranTm	STMTDATA
tran_dat_tim	Journal
	Journal_Key_Seq
	Journal_Key_Seq2.xml
	Referral
	Referral_OLTP
tran_ent_ts	ATM_DIAL_UP_CMD.xml
	ATM_SSB_CPL
trc_buf	Trace
trc_flg	Trace_Config
trc_hdr_flg	Trace_Config
trc_lvls	Trace_Config
trc_rsn_cde	Interac_Admin
trffc_flg	Interface_Station
trffc_typ	Banknet_Institution_Id
	Banknet_Institution_Id2
	Banknet_Institution_Id2_OLTP
	Banknet_Institution_Id_OLTP
trk1_algo_ofst	Prefix
	Prefix_OLTP
trk1_atc_lgth	Prefix
	Prefix_OLTP
trk1_atc_ofst	Prefix
	Prefix_OLTP

trk1_cv_lgth	Prefix
	Prefix_OLTP
trk1_cv_ofst	Prefix
	Prefix_OLTP
trk1_dat_ofst	Prefix
	Prefix_OLTP
trk1_dcv_lgth	Prefix
	Prefix_OLTP
trk1_dcv_ofst	Prefix
	Prefix_OLTP
trk1_max_lgth	Prefix
	Prefix_OLTP
trk1_mbr_ofst	Prefix
	Prefix_OLTP
trk1_min_lgth	Prefix
	Prefix_OLTP
trk1_pvv_ofst	Prefix
	Prefix_OLTP
trk1_sc_ofst	Prefix
	Prefix_OLTP
trk1_unpredict_num_ofst	Prefix
	Prefix_OLTP
trk2_algo_ofst	Prefix
	Prefix_OLTP
trk2_atc_lgth	Prefix
	Prefix_OLTP
trk2_atc_ofst	Prefix
	Prefix_OLTP
trk2_cv_lgth	Prefix
	Prefix_OLTP
trk2_cv_ofst	Prefix
	Prefix_OLTP
trk2_dat_ofst	Prefix
	Prefix_OLTP
trk2_dcv_lgth	Prefix
	Prefix_OLTP

List of data elements

trk2_dcv_ofst	Prefix Prefix_OLTP
trk2_max_lgth	Prefix Prefix_OLTP
trk2_mbr_ofst	Prefix Prefix_OLTP
trk2_min_lgth	Prefix Prefix_OLTP
trk2_pvv_ofst	Prefix Prefix_OLTP
trk2_pvv_ofst_2	Prefix Prefix_OLTP
trk2_sc_ofst	Prefix Prefix_OLTP
trk2_unpredict_num_ofst	Prefix Prefix_OLTP
trk3_algo_ofst	Prefix Prefix_OLTP
trk3_cv_lgth	Prefix Prefix_OLTP
trk3_cv_ofst	Prefix Prefix_OLTP
trk3_dat_ofst	Prefix Prefix_OLTP
trk3_max_lgth	Prefix Prefix_OLTP
trk3_mbr_ofst	Prefix Prefix_OLTP
trk3_min_lgth	Prefix Prefix_OLTP
trk3_pvv_ofst	Prefix Prefix_OLTP
trk3_sc_ofst	Prefix Prefix_OLTP
trk_outstnd_cnt_flg	Interface_Manager
trk_pref	Prefix

	Prefix_OLTP
TrmnBrncTx	CTVRSAP
	ESATDS1
TrmnRgnTx	CTVRSAP
	ESATDS1
TrnsAlwdTx	APCF
TrnsCodeTx	APCF.xml
trnsprt_key_loc	Prefix
	Prefix_OLTP
	Transport_Key.xml
	Transport_Key_OLTP.xml
ts	Exception_Log.xml
TSSLctrTx	ESATDS1
ts_q	FPS_Queue.xml
ttl_buf	Totals
	Totals_Entry
	Totals_Entry2
ttl_dat	Totals.xml
	Totals_Entry
	Totals_Entry2
ttl_delay_timr_lmt	Totals_Configuration
	Totals_Manager_Cnfg_OLTP
ttl_desc	Totals_Tag_Documentation
ttl_dir	Totals.xml
	Totals_Entry
	Totals_Entry2
ttl_endpoint_key	Totals.xml
	Totals_Entry
	Totals_Entry2
ttl_jrnl_stat	FPS_Cutover
ttl_mgr_nam	Totals_Configuration
	Totals_Manager_Cnfg_OLTP.xml
ttl_onl_asgn_nam	Totals_Configuration
	Totals_Configuration_OLTP
	Totals_Manager_Cnfg_OLTP
ttl_retn_prd	Totals_Configuration

	Totals_Manager_Cnfg_OLTP
ttl_tkn_cnt	Token_Config
	Token_Config_OLTP
ttl_ts	Totals_Entry.xml
	Totals_Entry2.xml
ttl_updt_intrvl	Totals_Configuration
	Totals_Manager_Cnfg_OLTP
ttl_usg	Totals_Tag_Documentation
tues_peak1_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tues_peak1_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tues_peak1_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tues_peak2_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tues_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tues_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tues_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
tvr_bit	EMV_Terminal_Vrfn_Results_Status
	EMV_Term_Vrfn_Results_OLTP.xml
	EMV_Term_Vrfn_Results_Order_OLTP
tvr_byte	EMV_Terminal_Vrfn_Results_Status
	EMV_Term_Vrfn_Results_OLTP.xml
	EMV_Term_Vrfn_Results_Order_OLTP
tvr_chk	Prefix
	Prefix_OLTP
tvr_chk_pre_scrn	Prefix
	Prefix_OLTP
tvr_prfl	EMV_Terminal_Vrfn_Results_Status.xml
	EMV_Term_Vrfn_Results_OLTP.xml
	EMV_Term_Vrfn_Results_Order_OLTP.xml
	Prefix

	Prefix_OLTP
txn_alwd	Acquirer_Txn_Allowed
	Acquirer_Txn_Allowed_OLTP
txn_alwd_01	Admin_Card
txn_alwd_02	Admin_Card
txn_alwd_03	Admin_Card
txn_alwd_04	Admin_Card
txn_alwd_05	Admin_Card
txn_alwd_06	Admin_Card
txn_alwd_07	Admin_Card
txn_alwd_08	Admin_Card
txn_alwd_09	Admin_Card
txn_alwd_10	Admin_Card
txn_alwd_11	Admin_Card
txn_alwd_12	Admin_Card
txn_alwd_13	Admin_Card
txn_alwd_14	Admin_Card
txn_alwd_15	Admin_Card
txn_alwd_16	Admin_Card
txn_alwd_17	Admin_Card
txn_alwd_18	Admin_Card
txn_alwd_19	Admin_Card
txn_alwd_20	Admin_Card
txn_alwd_21	Admin_Card
txn_alwd_22	Admin_Card
txn_alwd_23	Admin_Card
txn_alwd_24	Admin_Card
txn_alwd_25	Admin_Card
txn_alwd_26	Admin_Card
txn_alwd_27	Admin_Card
txn_alwd_28	Admin_Card
txn_alwd_29	Admin_Card
txn_alwd_30	Admin_Card
txn_alwd_31	Admin_Card
txn_alwd_32	Admin_Card
txn_alwd_33	Admin_Card

List of data elements

txn_alwd_34	Admin_Card
txn_alwd_35	Admin_Card
txn_alwd_36	Admin_Card
txn_alwd_37	Admin_Card
txn_alwd_38	Admin_Card
txn_alwd_39	Admin_Card
txn_alwd_40	Admin_Card
txn_alwd_41	Admin_Card
txn_alwd_42	Admin_Card
txn_alwd_43	Admin_Card
txn_alwd_44	Admin_Card
txn_alwd_45	Admin_Card
txn_alwd_46	Admin_Card
txn_alwd_47	Admin_Card
txn_alwd_48	Admin_Card
txn_alwd_49	Admin_Card
txn_alwd_50	Admin_Card
txn_alwd_not_on_us	Issuer_Txn_Allowed
	Issuer_Txn_Allowed_OLTP
txn_alwd_on_us	Issuer_Txn_Allowed
	Issuer_Txn_Allowed_OLTP
txn_cde	Acquirer_Issuer_Relation.xml
	Acquirer_Issuer_Relation_OLTP.xml
	Journal_Data_Suppression.xml
	Journal_Data_Suppression_OLTP.xml
	SPDH_Message.xml
	SPDH_Message_OLTP.xml
	SPDH_txn_cde_descr.xml
	SPDH_txn_cde_descr_OLTP.xml
txn_cde_descr	SPDH_txn_cde_descr
	SPDH_txn_cde_descr_OLTP
txn_orig_id_cde	SPAN2_Interface
	SPAN2_Interface_OLTP
txn_ref_num	FPID_History.xml
	FPS_Payment_Submission
txn_seq_num	Merchant_Delivery_Channel

txn_subtyp	ATM_TC_Proc_Code.xml ATM_Tran_Code_Proc_Code_OLTP.xml ISO_PROC_CODE.xml ISO_PROC_CODE_OLTP.xml POS_TC_Proc_Code.xml POS_Tran_Code_Proc_Code_OLTP.xml Proc_Code_ATM_TC Proc_Code_ATM_Tran_Code_OLTP PROC_CODE_ISO PROC_CODE_ISO_OLTP Proc_Code_POS_TC Proc_Code_POS_Tran_Code_OLTP
Type	LISTENER
UITimeout	SecGrp
ui_aud_sta_nam	Audit_Store_and_Forward_Config
ukdm_sppt_ind	Banknet_Configuration Banknet_Configuration_OLTP
uk_bnk_id	Ind_Sort_Code_Directory Ind_Sort_Code_Directory_OLTP
undr_act	Route Route_OLTP
undr_flr_alt1_adv1_cmpnt_id	Route Route_OLTP
undr_flr_alt1_adv1_nam	Route Route_OLTP
undr_flr_alt1_adv1_req	Route Route_OLTP
undr_flr_alt1_adv2_cmpnt_id	Route Route_OLTP
undr_flr_alt1_adv2_nam	Route Route_OLTP
undr_flr_alt1_adv2_req	Route Route_OLTP
undr_flr_alt1_auth_cmpnt_id	Route Route_OLTP
undr_flr_alt1_auth_nam	Route

	Route_OLTP
undr_flr_alt1_impact1_cmpnt_id	Route
	Route_OLTP
undr_flr_alt1_impact1_nam	Route
	Route_OLTP
undr_flr_alt1_impact2_cmpnt_id	Route
	Route_OLTP
undr_flr_alt1_impact2_nam	Route
	Route_OLTP
undr_flr_alt1_prescrn_cmpt_id	Route
	Route_OLTP
undr_flr_alt1_prescrn_nam	Route
	Route_OLTP
undr_flr_alt2_adv1_cmpnt_id	Route
	Route_OLTP
undr_flr_alt2_adv1_nam	Route
	Route_OLTP
undr_flr_alt2_adv1_req	Route
	Route_OLTP
undr_flr_alt2_adv2_cmpnt_id	Route
	Route_OLTP
undr_flr_alt2_adv2_nam	Route
	Route_OLTP
undr_flr_alt2_adv2_req	Route
	Route_OLTP
undr_flr_alt2_auth_cmpnt_id	Route
	Route_OLTP
undr_flr_alt2_auth_nam	Route
	Route_OLTP
undr_flr_alt2_impact1_cmpnt_id	Route
	Route_OLTP
undr_flr_alt2_impact1_nam	Route
	Route_OLTP
undr_flr_alt2_impact2_cmpnt_id	Route
	Route_OLTP
undr_flr_alt2_impact2_nam	Route

	Route_OLTP
undr_flr_alt2_prescreen_nam	Route
	Route_OLTP
undr_flr_alt2_prescrn_cmpt_id	Route
	Route_OLTP
undr_flr_pri_adv1_cmpnt_id	Route
	Route_OLTP
undr_flr_pri_adv1_nam	Route
	Route_OLTP
undr_flr_pri_adv1_req	Route
	Route_OLTP
undr_flr_pri_adv2_cmpnt_id	Route
	Route_OLTP
undr_flr_pri_adv2_nam	Route
	Route_OLTP
undr_flr_pri_adv2_req	Route
	Route_OLTP
undr_flr_pri_auth_cmpnt_id	Route
	Route_OLTP
undr_flr_pri_auth_nam	Route
	Route_OLTP
undr_flr_pri_impact1_cmpnt_id	Route
	Route_OLTP
undr_flr_pri_impact1_nam	Route
	Route_OLTP
undr_flr_pri_impact2_cmpnt_id	Route
	Route_OLTP
undr_flr_pri_impact2_nam	Route
	Route_OLTP
undr_flr_pri_prescrn_cmpnt_id	Route
	Route_OLTP
undr_flr_pri_prescrn_nam	Route
	Route_OLTP
UnqEvtntIDTx	EVNTLOG
updts	Card_Impacts
	PBAL_Impacts

List of data elements

upr_ver_num	Interac_Base
	Interac_Base_OLTP
UserActiveTS	Users
UserExpireTS	Users
UserField1Tx	LCONF.xml
UserField3Tx	LCONF
UserField4Tx	LCONF
UserFild1Tx	APCF.xml
UserID	ActSess.xml
	ACTSESS2.xml
	AuditTbl
	DATASRC
	Password.xml
	PswdHist.xml
	Ticket.xml
	Users.xml
	USRAULOG.xml
	USRXFILT.xml
	UsrXRole.xml
	WEBUSROPTS.xml
UserIdGropNmbrShort	APCF
UserIdGrpNmbrShort	LCONF
UserIdUserNmbrInt	APCF
	LCONF
UserPswdTx	DATASRC
UserStatusCode	Users
	UsrStat.xml
UserStatusDesc	UsrStat
user_fld1	BASE24_KEYF.xml
	CARD_ACCOUNT_MBYTE
	Card_Block
	EMV_Security
	Issuer_Txn_Allowed.xml
	Prefix_Block
	Security_Device_Config
user_id	OLTP_Warmboot

	Script_Configuration
user_prfl	Perusal_Script.xml
	Perusal_Script_OLTP.xml
	User_Perusal_Prfl_Relation
	User_Perusal_Prfl_Relation_OLTP
user_txt_area	ATM_DD1
	ATM_PREV_TTL
use_gicc_stan	GICC_Interface
	GICC_Interface_OLTP
use_init_crd_vrfy_rslts	Chip_Authentication
	Chip_Authentication_OLTP
use_last_out_setl_dat	SPAN2_Interface
	SPAN2_Interface_OLTP
use_pri_sta	GISO_Interface
	GISO_Interface_OLTP
usg_adnl	Usage
UsrDfndTx	RQUID
UsrDfndTxtArTx	ESAPDT
	ESATDD1
validate_data	ISO_FLD_DEFN
	ISO_FLD_DEFN_OLTP
ValidationTemplate	APPLCNFG
valid_acq_seq_gen_num	GICC_Interface
	GICC_Interface_OLTP
Value	FldVals.xml
VersionDescr	VERSIONS
VersionKey	VERSIONS.xml
VersionValue	VERSIONS
ver_ind	Discover_Interface
	Discover_Interface_OLTP
ver_num	EPSNET_Interface
	EPSNET_Interface_OLTP
visa_bin_rec	Visa_BIN_File_Updt
visa_logon_typ	Visa_Interface
	Visa_Interface_OLTP
visa_rgn_id	Visa_Interface

VndrNum	Visa_Interface_OLTP
vu_num	HSMCNFG
wait_confirm_stat	GICC_Channel
wbt_dest	Merchant_Delivery_Channel
wbt_sbmttd	DS_OLTP_Relation
wdl_amt_typ	OLTP_Warmboot
	ATM_PRFL
	ATM_PRFL_OLTP
WebAppURL	WEBAPPS
wed_peak1_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
wed_peak1_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
wed_peak1_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
wed_peak2_end_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
wed_peak2_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
wed_peak2_strt_tm	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
wed_stnd_load_grps	ATM_PEAK_LOAD
	ATM_PEAK_LOAD_OLTP
weight_fld	dal_tbl
wft_timr_lmt	Interface_Manager
wkend_end_pk_ld	ATM_PRFL
	ATM_PRFL_OLTP
wkend_strt_pk_ld	ATM_PRFL
	ATM_PRFL_OLTP
WkndEndPkLdTx	LTMRPRFL
WkndStrtPkLdTx	LTMRPRFL
WorkPhoneNum	Users
WorkstationID	ActSess
	ACTSESS2
	AuditTbl
wrkday_end_pk_ld	ATM_PRFL

wrkday_strt_pk_ld	ATM_PRFL_OLTP
	ATM_PRFL
	ATM_PRFL_OLTP
WrkdEndPkLdTx	LTMRPRFL
WrkdStrtPkLdTx	LTMRPRFL
wrk_phn	Credit_Debit_Master_File
	Credit_Debit_Master_File_OLTP
WthdAmntTypCd	ATDCNFG
xchng_data_both_idx	Interac_Interface
xchng_mac_both_idx	Interac_Interface
xchng_pin_both_idx	Interac_Interface
xfer_pt	GISO_Interface
	GISO_Interface_OLTP
xlate_encrypt_data	HISO87_Interface
	HISO87_Interface_OLTP
xnmm_timr_lmt	Banknet_Configuration
	Banknet_Configuration_OLTP
	Interface_Manager
yyyymmdd	TBP_Daily.xml
yyyymmddhhmmssllccc	Trace.xml
zka_drv_flg	Channel_Security
	Interchange_Security
	Interchange_Security_OLTP
zn_typ	LIS5_Interface
	LIS5_Interface_OLTP



ACI Worldwide

Offices in principal cities throughout the world.

www.aciworldwide.com

Americas +1 402 390 7600

Asia Pacific +65 6334 4843

Europe, Middle East,

Africa +44 (0) 1923 816393

© Copyright ACI Worldwide 2012

All information contained in this documentation, as well as the software described in it, is confidential and proprietary to ACI Worldwide, Inc., or one of its subsidiaries, is subject to a license agreement, and may be used or copied only in accordance with the terms of such license. Except as permitted by such license, no part of this documentation may be reproduced, stored in a retrieval system, or transmitted in any form or by electronic, mechanical, recording, or any other means, without the prior written permission of ACI Worldwide, Inc., or one of its subsidiaries.

ACI, ACI Worldwide, and the ACI product names used in this documentation are trademarks or registered trademarks of ACI Worldwide, Inc., or one of its subsidiaries.

Other companies' trademarks, service marks, or registered trademarks and service marks are trademarks, service marks, or registered trademarks and service marks of their respective companies.

About ACI Worldwide

ACI Worldwide powers electronic payments for financial institutions, retailers and processors around the world with the broadest, most integrated suite of electronic payment software in the market. More than 75 billion times each year, ACI's solutions process consumer payments. On an average day, ACI software manages more than US\$12 trillion in wholesale payments. And for more than 150 payments organisations worldwide, ACI software ensures people and businesses don't fall victim to financial crime. We are trusted globally based on our unrivaled understanding of payments and related processes. We have a definitive vision of how electronic payment systems will look in the future and we have the knowledge, scale and resources to deliver it. Since 1975, ACI has provided software solutions to the world's innovators. We welcome the opportunity to do the same for you.