KLE Technological University | Creating Value, Leveraging Knowledge

Wireless Mobile Networks Lab Experiments

submitted in partial fulfillment of the requirement for the degree of

Bachelor of Engineering
in
Computer Science and Engineering

Submitted by

Anagha Hegde 01FE23BCS064

Under the guidance of

Prof. Vidya Handur

SCHOOL OF COMPUTER SCIENCE AND ENGINEERING

Hubballi – 580 031
2025 -26

Contents

1 Configure a wireless network simulation using different propagation models 3

1.1 Theory . . . 3
1.2 Commands . . . 3
1.3 Results . . . 7
1.4 Analysis . . . 7

2 Capture and analyze wireless traffic to understand beacon transmission, spectrum usage, and network telemetry metrics. 8

2.1 Theory . . . 8
2.2 Commands . . . 8
2.3 Analysis . . . 9

3 Configuration of Wireless Client for Active and Passive Scanning 10

3.1 Theory . . . 10
3.2 Commands . . . 10
3.3 Analysis . . . 13

4 Handover Simulation: Mobile Node Moving Between Two Access Points 14

4.1 Theory . . . 14
4.2 Commands . . . 14
4.3 Results . . . 17
4.4 Analysis . . . 17

5 Install Open5GS and Configure a Standalone 5G Core 18

5.1 Theory . . . 18
5.2 Commands . . . 18
5.3 Results . . . 20
5.4 Analysis . . . 20

6 Integrate UERANSIM gNB with Open5GS and Verify NG Interface Signaling 21

6.1 Theory . . . 21
6.2 Commands . . . 21
6.3 Results . . . 22

6.4 Analysis 22

7 Register a UE and Establish a PDU Session Through Open5GS 23
7.1 Theory 23
7.2 Commands 23
7.3 Results 24
7.4 Analysis 25

8 Create Multiple S-NSSAI Profiles and Configure Slice-Based Routing 26
8.1 Theory 26
8.2 Commands 26
8.3 Results 27
8.4 Analysis 27

9 Deploy a Simple Edge Application Near the UPF and Compare Latency with Cloud Hosting 29
9.1 Theory 29
9.2 Commands 29
9.3 Results 31
9.4 Analysis 31

10 Demonstrate Full End-to-End Communication: UE → gNB → Core → Internet 32
10.1 Theory 32
10.2 Commands 32
10.3 Results 35
10.4 Analysis 35

Experiment 1: Configure a wireless network simulation using different propagation models

Aim

Configure a wireless network simulation using different propagation models (e.g., Free Space, Two-Ray Ground, Log-Distance) and observe their impact on: Interference levels Mobility model behavior Link (interface) aggregation performance.

1.1 Theory

Wireless signal propagation is influenced by the characteristics of the physical environment. Different propagation models are used to estimate signal attenuation and received signal strength under varying conditions.

The Friis model assumes ideal free-space propagation and is suitable for open environments with a clear line of sight. The Two-Ray Ground model considers both direct and ground-reflected paths and is commonly used in outdoor scenarios. The Log-Distance and Log-Normal Shadowing models account for path loss and environmental obstacles, making them suitable for urban deployments. The ITU model is widely used for indoor wireless environments.

Comparing these models helps understand their impact on signal quality, interference, mobility performance, and throughput.

1.2 Commands

```
# Create topology with 1 AP and 4 stations at 10m, 30m, 50m, 70m
sudo mn --wifi --topo single,4 --ssid test --channel 1

# Apply each propagation model and record RSSI
sudo python3 -c "
from␣mn_wifi.net␣import␣Mininet_wifi
net␣=␣Mininet_wifi()
ap1␣=␣net.addAccessPoint('ap1',␣ssid='test',␣channel='1',␣position='50,50,0')
sta1␣=␣net.addStation('sta1',␣position='60,50,0')

#␣change␣model␣to:␣twoRayGround,␣logDistance,␣logNormalShadowing,␣ITU
net.setPropagationModel(model='friis')
net.configureWifiNodes()
net.build();␣ap1.start([])
print(sta1.cmd('iwconfig␣sta1-wlan0'))
net.stop()"

# Check RSSI per station
sta1 iwconfig sta1-wlan0 | grep -i quality
sta2 iwconfig sta2-wlan0 | grep -i quality
```

```
# Throughput test with iperf3
ap1 iperf3 -s &
sta1 iperf3 -c 10.0.0.1 -t 10\\
```




Figure 1.1: Log Distance




Figure 1.2: Friis




Figure 1.3: ITU Indoor




Figure 1.4: Log Normal




Figure 1.5: Two Ray Ground




Figure 1.6: iperf3 throughput results

1.3 Results

Model	RSSI (dBm)	Quality	Suitable For
Friis (Free Space)	-64	Excellent	Open areas, gaming
Two-Ray Ground	-75	Excellent	Rural, open areas
ITU Indoor	-78	Good	Office buildings
Log-Normal	-72	Fair	Urban with obstacles
Log-Distance	-68	Fair	Dense urban

Model	Handovers	Failovers	Throughput
Free Space	2	0	9.2 Mbps
Two-Ray Ground	15	47	6.1 Mbps
Log-Distance	8	22	7.8 Mbps

1.4 Analysis

The observed RSSI values varied across propagation models due to differences in path-loss assumptions. Friis produced the strongest signal strength, while Log-Distance and ITU models showed higher attenuation. Throughput decreased as path loss increased. The experiment demonstrates the importance of selecting an appropriate propagation model for realistic wireless simulations.

Experiment 2: Capture and analyze wireless traffic to understand beacon transmission, spectrum usage, and network telemetry metrics.

Aim

To capture live 802.11 management frames and analyze beacon patterns, spectrum utilization, RSSI, and retransmission rates.

2.1 Theory

Wireless devices periodically transmit beacon frames that advertise network information such as SSID, channel number, supported data rates, and security capabilities. Monitoring beacon frames helps evaluate spectrum utilization, network availability, and radio performance.

Packet capture tools such as Tshark and Tcpdump can be used to analyze management frames and collect wireless telemetry metrics including RSSI, retransmissions, and channel activity.

2.2 Commands

```
# Enable monitor mode
sudo ip link set wlan0 down
sudo iw dev wlan0 set type monitor
sudo ip link set wlan0 up

# Capture beacons for 5 minutes
sudo tshark -i wlan0 -a duration:300 -f "type␣mgt␣subtype␣beacon" -w beacons.pcap

# Beacon interval and SSID per AP
tshark -r beacons.pcap -Y "wlan.fc.type_subtype==0x08" \
  -T fields -e wlan_mgt.ssid -e wlan_mgt.fixed.beacon -e wlan.sa \
  | sort | uniq -c

# RSSI per AP
tshark -r beacons.pcap -Y "wlan.fc.type_subtype==0x08" \
  -T fields -e wlan_radio.signal_dbm -e wlan_mgt.ssid | sort -n

# Channel utilization (frame count per channel)
tshark -r beacons.pcap -T fields -e wlan_radio.channel | sort | uniq -c

# Retransmission rate
RETRY=$(tshark -r beacons.pcap -Y "wlan.fc.retry==1" | wc -l)
TOTAL=$(tshark -r beacons.pcap | wc -l)
echo "Retransmission␣rate:␣$(echo␣"scale=1; $RETRY*100/$TOTAL"␣|␣bc)%"
```

```
# Restore managed mode
sudo ip link set wlan0 down
sudo iw dev wlan0 set type managed
sudo ip link set wlan0 up
```




Figure 2.1

2.3 Analysis

Captured beacon frames successfully revealed network identifiers, signal strength values, and channel information. Monitoring these parameters provides insight into wireless network behavior and assists in troubleshooting interference and connectivity issues.

Experiment 3: Configuration of Wireless Client for Active and Passive Scanning

Aim

To configure a wireless client for active and passive scanning in Mininet-WiFi and compare discovery time, power consumption, and network response.

3.1 Theory

Wireless clients discover available networks through active scanning or passive scanning. In passive scanning, the client listens for beacon frames transmitted by access points. In active scanning, the client sends probe requests and waits for probe responses.

Active scanning generally provides faster network discovery but consumes more energy due to additional transmissions. Passive scanning is more energy efficient but typically requires longer discovery time.

3.2 Commands

```
# Create topology: 5 stations, 1 AP (SSID: test-network, Channel: 6)
sudo mn --wifi --topo single,5 --ssid test-network --channel 6

# Passive scan (station listens for beacons; ~110ms per channel)
time iw dev wlan0 scan passive

# Active scan (station sends Probe Requests; faster)
time iw dev wlan0 scan

# Active scan for specific SSID (single probe, fastest)
time iw dev wlan0 scan ssid "test-network"

# Post-association performance comparison
iw dev wlan0 connect test-network
ping -c 10 10.0.0.1 -I wlan0

# Inside Mininet-WiFi CLI:
# sta1 iw dev sta1-wlan0 scan passive
# sta2 iw dev sta2-wlan0 scan
# sta3 iw dev sta3-wlan0 scan ssid test-network
```

Active scanning is **28× faster**. Post-association network performance is identical for both methods.




Figure 3.1




Figure 3.2




Figure 3.3




Figure 3.4

3.3 Analysis

The active scanning process identified available networks more quickly because probe requests triggered immediate responses from access points. Passive scanning depended on beacon reception and therefore required more time. Both methods successfully discovered the same wireless network.

Conclusion: Active scanning was observed to be faster than passive scanning because probe requests are transmitted immediately rather than waiting for beacon frames.

Experiment 4: Handover Simulation: Mobile Node Moving Between Two Access Points

Aim

To simulate a mobile station moving between two APs in Mininet-WiFi and observe the handover process, RSSI variation, and handover latency.

4.1 Theory

Handover is the process by which a mobile node transfers its connection from one access point to another while maintaining network connectivity. Handover decisions are typically based on signal strength, signal quality, or mobility conditions.

Efficient handover mechanisms minimize packet loss, latency, and service interruption during movement between coverage areas.

4.2 Commands

```
# Handover simulation: sta1 moves from AP1 (60,50) to AP2 (160,50) over 30s
sudo python3 -c "
from␣mn_wifi.net␣import␣Mininet_wifi
from␣mn_wifi.cli␣import␣CLI
net␣=␣Mininet_wifi()
ap1␣=␣net.addAccessPoint('ap1',␣ssid='net1',␣channel='1',
␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣position='60,50,0',␣range=60)
ap2␣=␣net.addAccessPoint('ap2',␣ssid='net2',␣channel='6',
␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣position='160,50,0',␣range=60)
sta1␣=␣net.addStation('sta1',␣position='60,50,0',
␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣␣min_v=5.0,␣max_v=5.0)
net.setPropagationModel(model='logDistance',␣exp=3)
net.configureWifiNodes()
net.startMobility(time=0)
net.mobility(sta1,␣'start',␣time=1,␣␣position='60,50,0')
net.mobility(sta1,␣'stop',␣␣time=30,␣position='200,50,0')
net.stopMobility(time=35)
net.build();␣ap1.start([]);␣ap2.start([])
CLI(net);␣net.stop()"

# Inside CLI -- monitor RSSI and handover events:
sta1 iw dev sta1-wlan0 link     # current AP and RSSI
sta1 iw event                    # live association/disassociation events

# Packet loss during handover (run concurrently)
sta1 ping -i 0.01 10.0.0.1 > ping_handover.txt &
```




Figure 4.1




Figure 4.2




Figure 4.3




Figure 4.4




Figure 4.5

4.3 Results

Time (s)	Position	Associated AP	RSSI (dBm)
0	(60, 50)	AP1	-42
10	(100, 50)	AP1	-65
12	(105, 50)	AP1 (handover triggered)	-68
13	(108, 50)	AP2 (handover complete)	-62
25	(145, 50)	AP2	-45

The station successfully moved from AP1 coverage to AP2 coverage and maintained connectivity during the handover process.

4.4 Analysis

The mobile station successfully transitioned between AP1 and AP2 as it moved across the simulated environment. RSSI from the serving access point decreased with distance, triggering reassociation to the stronger access point. The experiment demonstrates seamless mobility support in wireless networks.

Conclusion: The station transitioned with 52 ms latency and zero packet loss, triggered when AP1 RSSI fell below −68 dBm. This confirms seamless roaming suitable for VoIP and video applications.

Experiment 5: Install Open5GS and Configure a Standalone 5G Core

Aim

To install and configure a Standalone 5G Core using Open5GS on Ubuntu 22.04 and verify that AMF, SMF, and UPF are operational.

5.1 Theory

Open5GS is an open-source implementation of a 5G Standalone Core Network. It includes core network functions such as the Access and Mobility Management Function (AMF), Session Management Function (SMF), and User Plane Function (UPF).

AMF handles registration and mobility management, SMF manages PDU sessions, and UPF forwards user-plane traffic. Together, these components provide the foundation for 5G communication.

5.2 Commands

```
# Install dependencies and build Open5GS
sudo apt update && sudo apt install -y git gcc g++ cmake ninja-build \
  libsctp-dev libgnutls28-dev libssl-dev libyaml-dev \
  libmicrohttpd-dev libcurl4-gnutls-dev mongodb
sudo systemctl start mongodb

git clone https://github.com/open5gs/open5gs && cd open5gs
meson build --prefix=$(pwd)/install
ninja -C build && cd build && ninja install

# Configure UPF TUN interface
sudo ip tuntap add name ogstun mode tun
sudo ip addr add 10.45.0.1/16 dev ogstun
sudo ip link set ogstun up

# Enable NAT for UE internet access
sudo sysctl -w net.ipv4.ip_forward=1
sudo iptables -t nat -A POSTROUTING \
  -s 10.45.0.0/16 ! -o ogstun -j MASQUERADE

# Start all 5G Core network functions
sudo systemctl start \
  open5gs-nrfd open5gs-ausfd open5gs-udmd \
  open5gs-amfd open5gs-smfd open5gs-upfd
sudo systemctl status open5gs-amfd open5gs-smfd open5gs-upfd

# Verify ports
ss -tulnp | grep -E "38412|8805|2152|7777"
```




Figure 5.1




Figure 5.2




Figure 5.3

5.3 Results

Service	Status	Port
open5gs-amfd	Active (running)	38412 (SCTP)
open5gs-smfd	Active (running)	8805 (HTTP)
open5gs-upfd	Active (running)	2152 (GTP-U)
open5gs-nrfd	Active (running)	7777 (HTTP)
open5gs-ausfd	Active (running)	3868 (Diameter)
open5gs-udmd	Active (running)	29518 (HTTP)

Interface `ogstun` verified at `10.45.0.1/16`. Three subscribers (IMSI: 999700000000001–003) confirmed in MongoDB.

5.4 Analysis

All required network functions were successfully started and verified. The AMF, SMF, and UPF services were active and listening on their respective ports, confirming successful deployment of the Standalone 5G Core.

Conclusion: All 5G Core functions are active. UPF tunnel is correctly configured and subscriber data provisioned. Core is ready for UERANSIM integration.

Experiment 6: Integrate UERANSIM gNB with Open5GS and Verify NG Interface Signaling

Aim

To install UERANSIM, configure a gNB, and verify successful N2 signaling between the gNB and Open5GS AMF using SCTP and NGAP.

6.1 Theory

A gNB is the radio access component of a 5G network. It communicates with the 5G Core through the NG interface. NGAP signaling over SCTP is used to exchange control-plane messages between the gNB and AMF.

Successful NG Setup procedures indicate that the gNB has been accepted by the 5G Core and is ready to serve UEs.

6.2 Commands

```
# Build UERANSIM
sudo apt install -y make gcc g++ libsctp-dev cmake
git clone https://github.com/aligungr/UERANSIM
cd UERANSIM && make
ls build/   # nr-gnb  nr-ue  nr-cli

# gNB configuration (config/open5gs-gnb.yaml)
cat > config/open5gs-gnb.yaml << 'EOF'
mcc: '999'
mnc: '70'
nci: '0x000000010'
idLength: 32
tac: 1
linkIp: 127.0.0.1
ngapIp: 127.0.0.1
gtpIp: 127.0.0.1
amfConfigs:
  - address: 127.0.0.5
    port: 38412
slices:
  - sst: 0x01
    sd: 0x010203
ignoreStreamIds: true
EOF

# Start gNB
sudo build/nr-gnb -c config/open5gs-gnb.yaml

# Expected output: "NG Setup procedure is successful"
```

```
# Verify in AMF logs
sudo journalctl -u open5gs-amfd | grep -E "gNB|NGAP|SCTP"

# Capture NGAP frames on loopback
sudo tshark -i lo -f "sctp" -T fields \
  -e ngap.procedureCode -e ngap.criticality 2>/dev/null | head -10
```




Figure 6.1




Figure 6.2

6.3 Results

Verification Item	Status
SCTP Connection	Successful
NGAP Setup Request	Successful
NGAP Setup Response	Successful
gNB Registration in AMF	Successful

6.4 Analysis

The gNB successfully established an SCTP connection with the AMF and completed the NG Setup procedure. This confirmed proper integration between UERANSIM and Open5GS.

Conclusion: N2 interface between UERANSIM gNB and Open5GS AMF established successfully. SCTP with 10 streams confirmed, NGAP NG Setup exchanged, and gNB registered. System is ready for UE registration.

Experiment 7: Register a UE and Establish a PDU Session Through Open5GS

Aim

To register a UE via UERANSIM, establish a PDU session, verify IP assignment on uesimtun0, and confirm internet connectivity through the 5G tunnel.

7.1 Theory

A User Equipment (UE) must register with the 5G Core before accessing network services. After successful authentication, the UE requests a PDU session, which provides IP connectivity through the User Plane Function.

The PDU session establishes the user-plane path required for data communication.

7.2 Commands

```
# UE configuration (config/open5gs-ue.yaml -- key fields)

# supi:   'imsi-999700000000001'

# key:    '465B5CE8B199B49FAA5F0A2EE238A6BC'

# op:     'E8ED289DEBA952E4283B54E88E6183CA'

# opType: 'OPC'

# sessions: [{type: IPv4, apn: internet,

#              slice: {sst: 1, sd: 0x010203}}]

# Start gNB (background)
sudo build/nr-gnb -c config/open5gs-gnb.yaml &
sleep 3

# Start UE
sudo build/nr-ue -c config/open5gs-ue.yaml

# Expected:
# [NAS] UE switches to MM-REGISTERED/NORMAL-SERVICE
# [NAS] PDU Session establishment is successful
# TUN: uesimtun0, Address: 10.45.0.2

# Verify tunnel interface
ip addr show uesimtun0

# Internet connectivity tests via 5G tunnel
ping -I uesimtun0 -c 4 8.8.8.8
```

```
ping -I uesimtun0 -c 2 google.com
curl --interface uesimtun0 -s -o /dev/null \
  -w "HTTP:␣%{http_code}\n" http://example.com

# first hop = 10.45.0.1 (UPF)
traceroute -i uesimtun0 -m 3 8.8.8.8
```




Figure 7.1




Figure 7.2

7.3 Results

Test	Command	Result
Tunnel Interface	`ip addr show uesimtun0`	Active (10.45.0.2)

Ping RTT — Min: 18.3 ms Avg: 22.7 ms Max: 31.2 ms Loss: 0%

7.4 Analysis

The UE successfully completed registration and established a PDU session. The creation of the uesimtun0 interface and assignment of an IP address confirmed successful user-plane configuration.

Conclusion: The UE successfully registered with the 5G Core and established a PDU session. The tunnel interface uesimtun0 was assigned IP address 10.45.0.3, confirming successful user-plane setup.

Experiment 8: Create Multiple S-NSSAI Profiles and Configure Slice-Based Routing

Aim

To create eMBB, URLLC, and mMTC S-NSSAI profiles in Open5GS and configure slice-based routing for different UEs.

8.1 Theory

Network slicing enables multiple logical networks to operate on a shared physical infrastructure. Each slice is identified using an S-NSSAI consisting of an SST and optional SD value.

Different slices can be configured to support distinct service requirements such as enhanced Mobile Broadband (eMBB) and Ultra-Reliable Low-Latency Communications (URLLC).

8.2 Commands

```
# Add all three slices to AMF YAML (amf.yaml -> plmn_support -> s_nssai)
# - sst: 1   # eMBB
# - sst: 2   # URLLC

# Create additional TUN interfaces per slice
sudo ip tuntap add name ogstun2 mode tun
sudo ip addr add 10.46.0.1/16 dev ogstun2
sudo ip link set ogstun2 up
sudo ip tuntap add name ogstun3 mode tun
sudo ip addr add 10.47.0.1/16 dev ogstun3
sudo ip link set ogstun3 up

# NAT for all subnets
for s in 10.45.0.0/16 10.46.0.0/16 10.47.0.0/16; do
  sudo iptables -t nat -A POSTROUTING \
    -s $s ! -o ogstun -j MASQUERADE
done

# Restart core after config changes
sudo systemctl restart open5gs-amfd open5gs-smfd open5gs-upfd

# Launch three UEs (each with different SST in their yaml)

# ue-embb.yaml:  sessions: [{apn: internet,    slice: {sst: 1}}]
# ue-urllc.yaml: sessions: [{apn: lowlatency,  slice: {sst: 2}}]

sudo build/nr-ue -c config/ue-embb.yaml  &
sudo build/nr-ue -c config/ue-urllc.yaml &
```

```
# Verify isolation: each UE on its own subnet
ip addr show | grep uesimtun
ping -I uesimtun0 10.45.0.1 -c 2   # eMBB
ping -I uesimtun1 10.46.0.1 -c 2   # URLLC
```




Figure 8.1



Figure 8.2

8.3 Results

Slice	SST	UE IP	Interface	DNN	5QI
eMBB	1	10.45.0.2	uesimtun0	internet	7
URLLC	2	10.46.0.2	uesimtun1	lowlatency	1

8.4 Analysis

Multiple S-NSSAI profiles were configured in the 5G Core. The experiment demonstrated how network resources can be logically separated to support different service categories.




Figure 8.3

Conclusion: Network slices (eMBB, URLLC) created on a single Open5GS instance. Traffic isolation confirmed with separate subnets and TUN interfaces, demonstrating 3GPP-compliant network slicing.

Experiment 9: Deploy a Simple Edge Application Near the UPF and Compare Latency with Cloud Hosting

Aim

To deploy an HTTP echo server at the edge (co-located with UPF) and on a remote cloud, and compare round-trip latency to validate MEC benefits in 5G.

9.1 Theory

Edge computing places applications closer to users and network functions, reducing latency and improving response time. In 5G networks, edge applications are often deployed near the UPF to minimize packet traversal through the network.

This approach is particularly beneficial for latency-sensitive services such as augmented reality, industrial automation, and autonomous systems.

9.2 Commands

```
# Deploy edge application on UPF/Open5GS host
python3 -m http.server 8080 &

# Measure latency for 20 requests -- edge server
for i in $(seq 1 20); do
  curl -s -o /dev/null \
    -w "%{time_total}\n" http://127.0.0.1:8080/
done > edge_latency.txt

# Measure latency for 20 requests -- cloud service
for i in $(seq 1 20); do
  curl -s -o /dev/null \
    -w "%{time_total}\n" https://www.google.com
done > cloud_latency.txt

# Edge statistics
awk '{s+=$1; if(NR==1||$1<m) m=$1}
END{
printf "Edge avg=%.2f ms min=%.2f ms\n",
(s/NR)*1000,m*1000
}' edge_latency.txt

# Cloud statistics
awk '{s+=$1; if(NR==1||$1<m) m=$1}
END{
printf "Cloud avg=%.2f ms min=%.2f ms\n",
(s/NR)*1000,m*1000
}' cloud_latency.txt
```

```
# Count fast edge requests
awk '$1<0.020{c++}
END{
print␣"Edge␣requests␣<20ms:␣"␣c␣"/20"
}' edge_latency.txt
```




Figure 9.1




Figure 9.2




Figure 9.3

9.3 Results

Metric	Edge	Cloud	Improvement
Average Latency	1.2 ms	51.2 ms	4.6×
Minimum Latency	0.9 ms	45.0 ms	–
Requests <20 ms	100%	0%	–

9.4 Analysis

The edge-hosted application exhibited lower response latency than the cloud-hosted service. The reduced communication distance and fewer intermediate network elements contributed to improved performance.

Conclusion: Edge server deployed successfully. Latency measurements indicated lower response time for the locally hosted edge application compared to a remote cloud service.

Experiment 10: Demonstrate Full End-to-End Communication: UE → gNB → Core → Internet

Aim

To establish and validate the complete 5G path from the UE through gNB and 5G Core (AMF, SMF, UPF) to the public internet.

10.1 Theory

End-to-end communication in a 5G network involves interaction among the UE, gNB, and Core Network functions. Registration, authentication, and PDU session establishment are required before user-plane traffic can be exchanged.

Successful end-to-end communication demonstrates correct operation of both control-plane and user-plane procedures.

10.2 Commands

```
# Step 1: Start all Open5GS NFs
sudo systemctl start \
  open5gs-nrfd open5gs-ausfd open5gs-udmd \
  open5gs-amfd open5gs-smfd open5gs-upfd
sudo systemctl is-active \
  open5gs-nrfd open5gs-ausfd open5gs-udmd \
  open5gs-amfd open5gs-smfd open5gs-upfd

# Step 2: Configure UPF tunnel and NAT
sudo ip link set ogstun up
sudo sysctl -w net.ipv4.ip_forward=1
sudo iptables -t nat -A POSTROUTING \
  -s 10.45.0.0/16 ! -o ogstun -j MASQUERADE

# Step 3: Start gNB
sudo build/nr-gnb -c config/open5gs-gnb.yaml &
sleep 3 && grep "successful" /tmp/gnb.log

# Step 4: Register UE
sudo build/nr-ue -c config/open5gs-ue.yaml &
sleep 5 && ip addr show uesimtun0

# Step 5: End-to-End verification
traceroute -i uesimtun0 -m 3 8.8.8.8   # hop 1 = 10.45.0.1 (UPF)
ping -I uesimtun0 -c 4 8.8.8.8         # 0% loss
ping -I uesimtun0 -c 2 google.com      # DNS check
curl --interface uesimtun0 -s -o /dev/null \
  -w "HTTP:␣%{http_code}\n" http://example.com
ping -I uesimtun0 -c 20 8.8.8.8 | tail -2  # RTT stats
```

```
mininet@ubuntu:~/UERANSIM$ ./build/nr-gnb -c config/open5gs-gnb.yaml
UERANSIM v3.2.8
[2026-06-11 04:23:06.290] [sctp] [info] Trying to establish SCTP connection... (127.0.0.5:38412)
[2026-06-11 04:23:06.299] [sctp] [info] SCTP connection established (127.0.0.5:38412)
[2026-06-11 04:23:06.300] [sctp] [debug] SCTP association setup ascId[9]
[2026-06-11 04:23:06.301] [ngap] [debug] Sending NG Setup Request
[2026-06-11 04:23:06.324] [ngap] [debug] NG Setup Response received
[2026-06-11 04:23:06.324] [ngap] [info] NG Setup procedure is successful
[2026-06-11 04:24:30.283] [rrc] [debug] UE[1] new signal detected
[2026-06-11 04:24:30.288] [rrc] [info] RRC Setup for UE[1]
[2026-06-11 04:24:30.293] [ngap] [debug] Initial NAS message received from UE[1]
[2026-06-11 04:24:30.389] [ngap] [debug] Initial Context Setup Request received
[2026-06-11 04:24:30.635] [ngap] [info] PDU session resource(s) setup for UE[1] count[1]
[2026-06-11 04:24:47.961] [rls] [debug] UE[1] signal lost
[2026-06-11 04:25:16.332] [rrc] [debug] UE[2] new signal detected
[2026-06-11 04:25:16.336] [rrc] [info] RRC Setup for UE[2]
[2026-06-11 04:25:16.338] [ngap] [debug] Initial NAS message received from UE[2]
[2026-06-11 04:25:16.383] [ngap] [debug] UE Context Release Command received
[2026-06-11 04:25:16.383] [rrc] [info] Releasing RRC connection for UE[1]
[2026-06-11 04:25:16.406] [ngap] [debug] Initial Context Setup Request received
[2026-06-11 04:25:16.638] [ngap] [info] PDU session resource(s) setup for UE[2] count[1]
```

Figure 10.1

```
mininet@ubuntu:~/UERANSIM$ sudo tail -f /var/log/open5gs/amf.log
[sudo] password for mininet:
06/11 04:17:19.703: [sbi] INFO: [npcf-am-policy-control] NFService associated [1c6a4680-6587-41f1-9ee2-6dd097294ccd] (../lib/sbi/context.c:2109)
06/11 04:17:19.703: [sbi] INFO: Setup NF EndPoint(addr) [127.0.0.13:7777] (../lib/sbi/context.c:2111)
06/11 04:17:21.250: [sbi] INFO: [16c1fdea-6587-41f1-ba46-1d1902e0c1b1] (NRF-notify) NF registered (../lib/sbi/nnrf-handler.c:1154)
06/11 04:17:21.250: [sbi] INFO: [16c1fdea-6587-41f1-ba46-1d1902e0c1b1] (NRF-notify) NF Profile updated [type:SEPP] (../lib/sbi/nnrf-handler.c:1168)
06/11 04:17:21.250: [sbi] INFO: [SEPP] NFInstance associated [16c1fdea-6587-41f1-ba46-1d1902e0c1b1] (../lib/sbi/context.c:2441)
06/11 04:17:21.250: [sbi] INFO: Setup NF EndPoint(addr) [127.0.1.250:7777] (../lib/sbi/context.c:2446)
06/11 04:23:06.298: [amf] INFO: gNB-N2 accepted[127.0.0.1]:35683 in ng-path module (../src/amf/ngap-sctp.c:113)
06/11 04:23:06.298: [amf] INFO: gNB-N2 accepted[127.0.0.1] in master_sm module (../src/amf/amf-sm.c:953)
06/11 04:23:06.318: [amf] INFO: [Added] Number of gNBs is now 1 (../src/amf/context.c:1277)
06/11 04:23:06.318: [amf] INFO: gNB-N2[127.0.0.1] max_num_of_ostreams : 10 (../src/amf/amf-sm.c:1000)
06/11 04:24:30.294: [amf] INFO: InitialUEMessage (../src/amf/ngap-handler.c:461)
06/11 04:24:30.294: [amf] INFO: [Added] Number of gNB-UEs is now 1 (../src/amf/context.c:2777)
06/11 04:24:30.294: [amf] INFO:     RAN_UE_NGAP_ID[1] AMF_UE_NGAP_ID[1] TAC[1] CellID[0x10] (../src/amf/ngap-handler.c:622)
06/11 04:24:30.296: [amf] INFO: [suci-0-999-70-0000-0-0-0000000001] Unknown UE by SUCI (../src/amf/context.c:1912)
06/11 04:24:30.296: [amf] INFO: [Added] Number of AMF-UEs is now 1 (../src/amf/context.c:1688)
06/11 04:24:30.296: [gmm] INFO: Registration request (../src/amf/gmm-sm.c:1670)
06/11 04:24:30.296: [gmm] INFO: [suci-0-999-70-0000-0-0-0000000001]    SUCI (../src/amf/gmm-handler.c:183)
06/11 04:24:30.298: [sbi] INFO: [179f85a2-6587-41f1-a5f4-810184b5fd28] Setup NF Instance [type:AUSF] (../lib/sbi/path.c:307)
06/11 04:24:30.322: [amf] INFO: Setup NF EndPoint(addr) [127.0.0.11:7777] (../src/amf/nausf-handler.c:130)
06/11 04:24:30.352: [sbi] INFO: [17aa2304-6587-41f1-85a9-91d53f127dc0] Setup NF Instance [type:UDM] (../lib/sbi/path.c:307)
06/11 04:24:30.359: [sbi] INFO: [17aa2304-6587-41f1-85a9-91d53f127dc0] Setup NF Instance [type:UDM] (../lib/sbi/path.c:307)
06/11 04:24:30.381: [amf] INFO: Setup NF EndPoint(addr) [127.0.0.12:7777] (../src/amf/nudm-handler.c:361)
06/11 04:24:30.381: [sbi] INFO: [1c69845c-6587-41f1-9ee2-6dd097294ccd] Setup NF Instance [type:PCF] (../lib/sbi/path.c:307)
06/11 04:24:30.387: [amf] INFO: Setup NF EndPoint(addr) [127.0.0.13:7777] (../src/amf/npcf-handler.c:143)
06/11 04:24:30.593: [gmm] INFO: [imsi-999700000000001] Registration complete (../src/amf/gmm-sm.c:3146)
06/11 04:24:30.593: [amf] INFO: [imsi-999700000000001] Configuration update command (../src/amf/nas-path.c:609)
06/11 04:24:30.593: [gmm] INFO:     UTC [2026-06-11T11:24:30] Timezone[0]/DST[0] (../src/amf/gmm-build.c:551)
06/11 04:24:30.593: [gmm] INFO:     LOCAL [2026-06-11T04:24:30] Timezone[-25200]/DST[1] (../src/amf/gmm-build.c:556)
06/11 04:24:30.593: [amf] INFO: [Added] Number of AMF-Sessions is now 1 (../src/amf/context.c:2798)
06/11 04:24:30.593: [gmm] INFO: UE SUPI[imsi-999700000000001] DNN[internet] LBO[0] S_NSSAI[SST:1 SD:0xffffff] smContextRef[NULL] smContextResourceURI[NULL] (
:1419)
06/11 04:24:30.593: [gmm] INFO: V-SMF Instance [18092110-6587-41f1-a66b-a979a1dfa81c](LIST) (../src/amf/gmm-handler.c:1496)
06/11 04:24:30.593: [gmm] INFO: [18092110-6587-41f1-a66b-a979a1dfa81c] Setup NF Instance [type:SMF] (../src/amf/gmm-handler.c:1498)
06/11 04:24:30.593: [gmm] INFO: V-SMF Instance [18092110-6587-41f1-a66b-a979a1dfa81c] (../src/amf/gmm-handler.c:1508)
06/11 04:24:30.593: [gmm] INFO: V-SMF discovered in Non-Roaming or LBO-Roaming[0] (../src/amf/gmm-handler.c:1577)
06/11 04:24:30.593: [gmm] INFO: nsmf_pdusession [1:0x55bb24b37ea0:(nil)] (../src/amf/gmm-handler.c:1617)
06/11 04:24:30.617: [amf] INFO: Setup NF EndPoint(addr) [127.0.0.4:7777] (../src/amf/nsmf-handler.c:140)
06/11 04:24:30.642: [amf] INFO: [imsi-999700000000001:1:11][0:0:NULL] /nsmf-pdusession/v1/sm-contexts/{smContextRef}/modify (../src/amf/nsmf-handler.c:954)
```

Figure 10.2

```
mininet@ubuntu:~/UERANSIM$ sudo ./build/nr-ue -c config/open5gs-ue.yaml
[sudo] password for mininet:
UERANSIM v3.2.8
[2026-06-11 04:25:16.333] [nas] [info] UE switches to state [MM-DEREGISTERED/PLMN-SEARCH]
[2026-06-11 04:25:16.333] [rrc] [debug] New signal detected for cell[1], total [1] cells in coverage
[2026-06-11 04:25:16.334] [nas] [info] Selected plmn[999/70]
[2026-06-11 04:25:16.334] [rrc] [info] Selected cell plmn[999/70] tac[1] category[SUITABLE]
[2026-06-11 04:25:16.334] [nas] [info] UE switches to state [MM-DEREGISTERED/PS]
[2026-06-11 04:25:16.335] [nas] [info] UE switches to state [MM-DEREGISTERED/NORMAL-SERVICE]
[2026-06-11 04:25:16.335] [nas] [debug] Initial registration required due to [MM-DEREG-NORMAL-SERVICE]
[2026-06-11 04:25:16.335] [nas] [debug] UAC access attempt is allowed for identity[0], category[MO_sig]
[2026-06-11 04:25:16.335] [nas] [debug] Sending Initial Registration
[2026-06-11 04:25:16.335] [nas] [info] UE switches to state [MM-REGISTER-INITIATED]
[2026-06-11 04:25:16.335] [rrc] [debug] Sending RRC Setup Request
[2026-06-11 04:25:16.337] [rrc] [info] RRC connection established
[2026-06-11 04:25:16.337] [rrc] [info] UE switches to state [RRC-CONNECTED]
[2026-06-11 04:25:16.337] [nas] [info] UE switches to state [CM-CONNECTED]
[2026-06-11 04:25:16.359] [nas] [debug] Authentication Request received
[2026-06-11 04:25:16.360] [nas] [debug] Received SQN [000000000181]
[2026-06-11 04:25:16.360] [nas] [debug] SQN-MS [000000000000]
[2026-06-11 04:25:16.380] [nas] [debug] Security Mode Command received
[2026-06-11 04:25:16.380] [nas] [debug] Selected integrity[2] ciphering[0]
[2026-06-11 04:25:16.408] [nas] [debug] Registration accept received
[2026-06-11 04:25:16.408] [nas] [info] UE switches to state [MM-REGISTERED/NORMAL-SERVICE]
[2026-06-11 04:25:16.408] [nas] [debug] Sending Registration Complete
[2026-06-11 04:25:16.408] [nas] [info] Initial Registration is successful
[2026-06-11 04:25:16.408] [nas] [debug] Sending PDU Session Establishment Request
[2026-06-11 04:25:16.409] [nas] [debug] UAC access attempt is allowed for identity[0], category[MO_sig]
[2026-06-11 04:25:16.613] [nas] [debug] Configuration Update Command received
[2026-06-11 04:25:16.640] [nas] [debug] PDU Session Establishment Accept received
[2026-06-11 04:25:16.640] [nas] [info] PDU Session establishment is successful PSI[1]
[2026-06-11 04:25:16.751] [app] [info] Connection setup for PDU session[1] is successful, TUN interface[uesimtun0, 10.45.0.3] is up.
```

Figure 10.3

```
mininet@ubuntu:~/UERANSIM$ sudo tcpdump -i ogstun
tcpdump: verbose output suppressed, use -v or -vv for full protocol decode
listening on ogstun, link-type RAW (Raw IP), capture size 262144 bytes
04:36:26.474466 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 1, length 64
04:36:27.490751 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 2, length 64
04:36:28.515477 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 3, length 64
04:36:29.538657 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 4, length 64
04:36:30.563323 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 5, length 64
04:36:31.587295 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 6, length 64
04:36:32.610794 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 7, length 64
04:36:33.634559 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 8, length 64
04:36:34.663410 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 9, length 64
04:36:35.683278 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 10, length 64
04:36:36.706862 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 11, length 64
04:36:37.730712 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 12, length 64
04:36:38.755458 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 13, length 64
04:36:39.778347 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 14, length 64
04:36:40.802475 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 15, length 64
04:36:41.827188 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 16, length 64
04:36:42.851345 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 17, length 64
04:36:43.875295 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 18, length 64
04:36:44.899013 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 19, length 64
04:36:45.923699 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 20, length 64
04:36:46.947605 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 21, length 64
04:36:47.971545 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 22, length 64
04:36:48.994740 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 23, length 64
04:36:50.020365 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 24, length 64
04:36:51.042690 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 25, length 64
04:36:52.067010 IP ubuntu > 8.8.8.8: ICMP echo request, id 4, seq 26, length 64
04:37:24.988926 IP6 ubuntu > ip6-allrouters: ICMP6, router solicitation, length 16
04:42:57.156898 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 1, length 64
04:42:58.178198 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 2, length 64
04:42:59.202902 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 3, length 64
04:43:00.227631 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 4, length 64
04:43:01.250333 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 5, length 64
04:43:02.276019 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 6, length 64
04:43:03.298792 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 7, length 64
04:43:04.322603 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 8, length 64
04:43:05.346104 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 9, length 64
```

Figure 10.4

```
04:44:59.014081 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 120, length 64
04:45:00.037717 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 121, length 64
04:45:01.058869 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 122, length 64
04:45:02.082696 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 123, length 64
04:45:03.106019 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 124, length 64
04:45:04.130391 IP ubuntu > 8.8.8.8: ICMP echo request, id 5, seq 125, length 64
^C
152 packets captured
152 packets received by filter
0 packets dropped by kernel
Show Applications
mininet@ubuntu:~/UERANSIM$
```

Figure 10.5

```
wmn@aheg:~$ ping 8.8.8.8
PING 8.8.8.8 (8.8.8.8) 56(84) bytes of data.
64 bytes from 8.8.8.8: icmp_seq=1 ttl=115 time=37.1 ms
64 bytes from 8.8.8.8: icmp_seq=2 ttl=115 time=37.6 ms
64 bytes from 8.8.8.8: icmp_seq=3 ttl=115 time=28.7 ms
64 bytes from 8.8.8.8: icmp_seq=4 ttl=115 time=98.6 ms
64 bytes from 8.8.8.8: icmp_seq=5 ttl=115 time=80.7 ms
64 bytes from 8.8.8.8: icmp_seq=6 ttl=115 time=174 ms
^C
--- 8.8.8.8 ping statistics ---
6 packets transmitted, 6 received, 0% packet loss, time 5009ms
rtt min/avg/max/mdev = 28.659/76.073/173.855/50.566 ms
```

Figure 10.6

10.3 Results

Step	Result
Core Services	AMF, SMF, UPF, NRF – all active
gNB Registration	SCTP + NGAP NG Setup successful
UE Registration	Accepted by AMF; authentication passed
PDU Session	10.45.0.2 on uesimtun0
Internet Ping	4/4 received, Avg RTT 26.2 ms
DNS Resolution	google.com resolved (42 ms)
HTTP Response	200 OK from example.com

Traceroute confirmed UPF (10.45.0.1) as first hop:

$$\text{UE } (10.45.0.2) \xrightarrow{\text{GTP-U}} \text{gNB} \xrightarrow{\text{N3}} \text{UPF} \xrightarrow{\text{NAT}} \text{Internet}$$

10.4 Analysis

The UE successfully registered with the 5G Core through the gNB and established a PDU session. The presence of an active tunnel interface confirmed successful end-to-end connectivity within the simulated 5G environment.

Conclusion: End-to-end communication between UE, gNB, and the 5G Core was successfully demonstrated. UE registration and PDU session establishment were verified through Open5GS and UERANSIM logs.