

```
ROUTER#configure terminal
Enter configuration commands, one per line. End with CNTL/Z.
ROUTER(config)#interface ethernet 0/0
ROUTER(config-if)#no shutdown
ROUTER(config-if)#ip address 50.0.0.1 255.0.0.0
ROUTER(config-if)#exit
ROUTER(config)#exit
ROUTER#
*Aug 20 11:35:07.219: %SYS-5-CONFIG_I: Configured from console by console
ROUTER#show ip interface brief
Interface                IP-Address      OK? Method Status      Protocol
Ethernet0/0              50.0.0.1        YES manual up          up
Ethernet0/1              unassigned      YES TFTP  down        down
Ethernet0/2              unassigned      YES TFTP  down        down
Ethernet0/3              unassigned      YES TFTP  down        down
ROUTER#configure terminal
Enter configuration commands, one per line. End with CNTL/Z.
ROUTER(config)#username console password console
ROUTER(config)#line console 0
ROUTER(config-line)#password testconsole
ROUTER(config-line)#login
ROUTER(config-line)#exit
ROUTER(config)#enable secret enable
ROUTER(config)#exit
ROUTER#ena
*Aug 20 11:37:40.570: %SYS-5-CONFIG_I: Configured from console by console
ROUTER#enable
ROUTER#configure terminal
Enter configuration commands, one per line. End with CNTL/Z.
ROUTER(config)#line vty 0 4
ROUTER(config-line)#transport input telnet
ROUTER(config-line)#password telnet
ROUTER(config-line)#login
ROUTER(config-line)#exit
ROUTER(config)#exit
ROUTER#
*Aug 20 11:38:40.460: %SYS-5-CONFIG_I: Configured from console by console
```