

Important Problematic Questions for University Exam



Prepared By Mr. EBIN PM, AP, IESCE

1

MODULE 1

Q1:

A benchmark program is run on a 40 MHz processor. The executed program consists of 100,000 instruction executions, with the following instruction mix and clock cycle count:

Instruction Type	Instruction Count	Cycles per Instruction
Integer arithmetic	45.000	1
Data transfer	32.000	2
Floating point	15.000	2
Control transfer	8000	2

Determine the effective CPI, MIPS rate, and execution time for this program.

Prepared By Mr.EBIN PM, AP, IESCE

EDULINE

2

- MIPS rate = $f / \text{CPI} \times 10^6$
 $= 40 / 1.55 \times 10^6$
 $= 40 \times 10^6 / 1.55 \times 10^6$
 $= \mathbf{25.8}$

- Given $f = 40 \text{ MHz} \rightarrow \tau = 1/40$
 $T = I_c \times \text{CPI} \times \tau$
 $= 100000 \times 1.55 \times 1/40$
 $= 100000 \times 1.55 \times 0.025$
 $= 3875$
 $= \mathbf{3.875 \text{ ms}}$

Prepared By Mr.EBIN PM, AP, IESCE

EDULINE

5

Q2:

3 enhancement with the following speed up are proposed for a new architecture

- $\text{Speedup}_1 = 30$
- $\text{Speedup}_2 = 20$
- $\text{Speedup}_3 = 15$

If enhancement 1 and 2 are each usable for 25% of the time, what fraction of the time must enhancement 3 be used to achieve an overall speed up of 10 ?

Prepared By Mr.EBIN PM, AP, IESCE

EDULINE

6

Clock speed of the Processor = 40 MHz

Instruction Type	Instruction Count	Cycles per Instruction	cycles
Integer arithmetic	45,000	1	45000
Data transfer	32,000	2	64000
Floating point	15,000	2	30000
Control transfer	8000	2	16000

Prepared By Mr.EBIN PM, AP, IESCE

EDULINE

3

- Total no: of cycles required to execute complete program

$$\rightarrow 45000 + 64000 + 30000 + 16000$$

$$\rightarrow 155000 \text{ cycles}$$

$$C = 155000 \text{ cycles}$$

- Effective CPI = C/I_c

$$\rightarrow 155000 / 100000$$

$$CPI = 1.55$$

Prepared By Mr.EBIN PM, AP, IESCE

EDULINE

4

Ans:

$$\begin{aligned}
 \text{Speedup}_{\text{overall}} &= \left[\frac{1}{(1 - \text{Fraction}_{\text{enhanced}}) + \frac{\text{Fraction}_{\text{enhanced}}}{\text{Speedup}_{\text{enhanced}}}} \right] \\
 &= \left\{ (1 - (FE_1 + FE_2 + FE_3)) + \left[\frac{FE_1}{SE_1} + \frac{FE_2}{SE_2} + \frac{FE_3}{SE_3} \right] \right\}^{-1} \\
 10 &= \left\{ (1 - (0.25 + 0.25 + FE_3)) + \left[\frac{0.25}{30} + \frac{0.25}{20} + \frac{FE_3}{15} \right] \right\}^{-1} \\
 10 &= \left\{ (0.5 - FE_3) + \left[\frac{0.5 + 0.75 + FE_3}{60} \right] \right\}^{-1} \\
 10 &= \frac{60}{30 - 60FE_3 + 1.25 + 4FE_3} \\
 -56FE_3 &= 6 - 31.25 \\
 FE_3 &= -25.25 / -56 = \underline{\underline{0.45}}
 \end{aligned}$$

Prepared By Mr.EBIN PM, AP, IESCE

EDULINE

7

MODULE 2

Q: Consider the design of a 3 level memory hierarchy with following features

Memory level	Access time	Capacity	Cost/kbyte
Cache	t1= 25 ns	s1= 512 Kbytes	c1= \$1.25
Main memory	t2= unknown	s2= 32 Mbytes	c2= \$.2
Disk array	t3= 4 ms	s3= unknown	c3= \$0.0002

- Aim is to achieve effective memory access time $T_{\text{eff}}=850 \text{ ns}$

Cache hit ratio $h_1=0.98$

Main memory Hit ratio $h_2=0.99$

Disk array hit ratio $h_3=1$

Total cost is upper bounded by \$15000

Calculate the unknown specifications based on the given conditions ?

Prepared By Mr.EBIN PM, AP, IESCE

EDULINE

8

Q3:

Determine the frequency of the pipeline if the stage delays are $\tau_1 = 3\text{ns}$, $\tau_2 = \tau_3 = 5\text{ns}$ and $\tau_4 = 8\text{ns}$ and the latch delay is 1ns .

$$\tau_{\max} = 8\text{ns}$$

$$d = 1\text{ns}$$

$$\tau = \tau_{\max} + d = 8 \times 10^{-9} + 1 \times 10^{-9} = 9 \times 10^{-9}$$

$$f = \frac{1}{\tau} = \frac{1}{9 \times 10^{-9}} = 111.11\text{ MHz}$$

$$\begin{aligned}
 \bullet C_{\text{total}} &= c_1 s_1 + c_2 s_2 + c_3 s_3 \leq 15000 \\
 15000 &= 1.25 \times 512 + 2 \times 32000 + .0002 * s_3 \\
 15000 &= 640 + 6400 + .0002 * s_3 \\
 .0002 * s_3 &= 15000 - 640 - 6400 \\
 &= 7960 / .0002 \\
 &= 39800000 \times 10^{-6} \\
 s_3 &= 39.8
 \end{aligned}$$

EDULINE

9

Prepared By Mr.EBIN PM, AP, IESCE

$$\begin{aligned}
 T_{\text{eff}} &= h_1 t_1 + (1 - h_1) h_2 t_2 + (1 - h_1)(1 - h_2) h_3 t_3 \\
 T_{\text{eff}} &= h_1 t_1 + (1 - h_1) h_2 t_2 + (1 - h_1)(1 - h_2) h_3 t_3 \leq 850 \text{ ns} \\
 850 \times 10^{-9} &= .98 \times 25 \times 10^{-9} + .02 * .99 * t_2 + .02 * .01 * 1 * 4 * 10^{-3} \\
 850 \times 10^{-9} &= 24.5 \times 10^{-9} + .0198 t_2 + .0008 \times 10^{-3} \\
 .0198 t_2 &= 850 \times 10^{-9} - 24.5 \times 10^{-9} - .0008 \times 10^{-3} \\
 &= 825.5 \times 10^{-9} - .0008 \times 10^{-3} \\
 &= 825.5 \times 10^{-9} - 800 \times 10^{-9} \\
 &= 25.5 \times 10^{-9} \\
 &= 25.5 \times 10^{-9} / .0198 \\
 t_2 &= 1287 \times 10^{-9}
 \end{aligned}$$

EDULINE

10

Prepared By Mr.EBIN PM, AP, IESCE