

ELECTRICAL & COMMUNICATION ROUGH IN AND FIT OUT JSA RISK ASSESSMENT

Coding Legend									
Consequence:									
Minor	Green	Indicates low impact, minor consequences that are easily manageable.							
Moderate	Yellow	Indicates a moderate level of impact that may require additional controls.							
Major	Orange	Indicates serious consequences that could potentially lead to significant issues.							
Severe	Red	Indicates very serious consequences that could result in critical or catastrophic outcomes.							
Likelihood:									
Unlikely	Green	Indicates that the occurrence is not expected, but possible.							
Possible	Yellow	Indicates a fair chance of the event occurring, should be prepared for.							
Likely	Orange	Indicates a high chance of the event occurring, immediate attention needed.							
Risk Rating:									
Low	Green	Represents a low level of risk; monitoring is required, but immediate action may not be necessary.							
Medium	Yellow	Represents a moderate level of risk; it requires specific monitoring and planning to manage.							
High	Red	Represents a high level of risk; immediate action and intervention are necessary to mitigate risks.							
Task/Activity	Potential Hazard	Persons at Risk	Consequence	Likelihood	Initial Risk Rating	Mitigation Measures	Residual Consequence	Residual Likelihood	Residual Risk Rating
Plan and set up the job	Untrained workers; wrong tools; slips/trips	Workers, others	Major	Possible	High	White Card, licences and site induction required. Review SWMS/JSA, toolbox talk, site hazards and emergency procedures. Confirm fitness for work, suitable tools/PPE and secure the work area.	Moderate	Unlikely	Low
Access site; deliver and position materials	Weather; traffic; public access; manual handling; poor storage	Workers, public	Major	Possible	High	Follow site and environmental rules. Hydrate and use sun/rain controls. Confirm muster point. Use barriers/spotter near traffic, mechanical aids/team lifts and stable storage that keeps access clear.	Moderate	Unlikely	Low
Isolate electrical and other services	Shock/electrocution; unexpected energisation; hidden services	Workers, others	Severe	Possible	High	No live work. Identify all services, isolate, lock and danger-tag, test-before-touch and prove de-energised. Complete the decommissioning register. Licensed electrician only; use insulated tools and fibreglass access equipment.	Major	Unlikely	Medium
Remove existing equipment, cabling and fixings	Shock; sharp edges; tool injury; manual handling; asbestos	Workers	Severe	Possible	High	Verify isolation before removal. Use correct tools and PPE; support equipment before releasing fixings; use mechanical aids/team lifts. Stop, do not disturb and report any suspected asbestos.	Moderate	Unlikely	Low
Remove items or work at height	Falls; falling objects; fragile surfaces	Workers, public	Severe	Possible	High	Use work platform, barrier or restraint in that order. Follow the applicable scaffold/EWP SWMS, inspect equipment, establish exclusion zones/spotter and secure tools. Do not work on slippery, brittle or fragile surfaces.	Major	Unlikely	Medium
Use ladders; measure and cut materials	Ladder fall; falling objects; cuts; unsuitable materials	Workers, public	Major	Possible	High	Prefer inspected fibreglass platform ladders on level ground; maintain three points of contact and do not overreach. Secure extension ladders at 4:1. Barricade below, secure tools, verify materials and wear eye/hand protection.	Moderate	Unlikely	Low
Core drill, chase or cut walls	Hidden services; silica/dust; vibration; noise; tool injury; falling objects	Workers, others	Severe	Possible	High	Locate and isolate services before penetration. Use competent operators and inspected tools with guards, dust extraction/suppression and required respiratory, eye, hearing and hand PPE. Rotate tasks and establish a drop/exclusion zone.	Moderate	Unlikely	Low
Drill or cut at height/near traffic	Falls; dropped tools; vehicle impact	Workers, public	Severe	Possible	High	Select inspected platform/scaffold/EWP equipment and complete pre-starts. Use barriers, exclusion zones, tool lanyards and a spotter/traffic control where required. Keep clear access and do not overreach.	Major	Unlikely	Medium
Install/remove conduit, cable supports and tray	Shock; hidden services; manual handling; ceiling-space hazards	Workers	Severe	Possible	High	Confirm drawings and service locations; isolate, lock/tag and test-before-touch. Use insulated tools and fibreglass access equipment. Use safe lifting methods; ceiling access only after assessment of heat, structure and electrical hazards.	Major	Unlikely	Medium

ELECTRICAL & COMMUNICATION ROUGH IN AND FIT OUT JSA RISK ASSESSMENT

Work in ceilings or at height	Falls; heat stress; falling objects; fragile ceiling	Workers, public	Severe	Possible	High	Use a platform/barrier/restraint system and exclusion zone. Work from below where practicable; never stand on ceiling lining. Provide ventilation, hydration, rest breaks and a second person where access or conditions require it.	Major	Unlikely	Medium
Secure conduit and supports	Ladder fall; drilling into services; tool injury	Workers, others	Severe	Possible	High	Locate services and verify isolation before drilling. Use an inspected fibreglass platform ladder, correct anchors and guarded tools. Maintain stable access, barricade below and inspect fixings before loading.	Moderate	Unlikely	Low
Install cables, equipment and fittings	Tool injury; manual handling; work at height; contact with services	Workers	Severe	Possible	High	Competent workers to follow tool instructions. Isolate and check services before drilling. Use mechanical aids/team lifts, suitable fixings and safe access equipment; secure materials against movement or falling.	Moderate	Unlikely	Low
Terminate conductors and make connections	Shock/electrocution; arc flash; incorrect termination; fall	Workers	Severe	Possible	High	Licensed electrician only. No live work. Isolate, lock/tag and prove dead; identify conductors and use insulated tools. Terminate to drawings/manufacturer requirements, torque correctly, protect exposed ends and inspect before covers are fitted.	Major	Unlikely	Medium
Test electrical installation	Shock; arc flash; exposed live parts	Workers, others	Severe	Possible	High	Licensed and authorised persons only. De-energised tests first. For tests requiring voltage, conduct a specific risk assessment, barricade access, provide LV rescue kit, safety observer where required, insulated mat/tools and arc-rated PPE. Prove tester before and after use.	Major	Unlikely	Medium
Recommission and energise circuits	Unexpected energisation; shock; arc flash; unsafe equipment	Workers, others	Severe	Possible	High	Visually inspect, secure covers and make terminations safe. Complete AS/NZS 3000 and AS/NZS 3017 tests, account for personnel, remove locks/tags under authorisation, notify affected persons and energise in a controlled manner. Record results.	Major	Unlikely	Medium
Clean up and hand over	Residual energy; sharp waste; trips; manual handling	Workers, client, public	Major	Possible	High	Make all conductors and equipment safe. Check tools for damage, segregate and remove waste, use gloves and safe lifting methods, clear access routes, close permits/registers and communicate residual risks before handover.	Moderate	Unlikely	Low

SIGNATORIES OF THE JSA RISK ASSESSMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this JSA Risk Assessment which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this JSA Risk Assessment each individual acknowledges and confirms that they have read this JSA Risk Assessment in full, having raised any questions for items on this JSA Risk Assessment that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this JSA Risk Assessment. By signing this JSA Risk Assessment each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Full Name:		Date:		Signature:		Position:	
Full Name:		Date:		Signature:		Position:	
Full Name:		Date:		Signature:		Position:	