

EMERGENCY ELECTRICAL WORKS JSA RISK ASSESSMENT

Coding Legend									
Consequence:									
Minor	Green	Indicates low impact, minor consequences that are easily manageable.							
Moderate	Yellow	Indicates a moderate level of impact that may require additional controls.							
Major	Orange	Indicates serious consequences that could potentially lead to significant issues.							
Severe	Red	Indicates very serious consequences that could result in critical or catastrophic outcomes.							
Likelihood:									
Unlikely	Green	Indicates that the occurrence is not expected, but possible.							
Possible	Yellow	Indicates a fair chance of the event occurring, should be prepared for.							
Likely	Orange	Indicates a high chance of the event occurring, immediate attention needed.							
Risk Rating:									
Low	Green	Represents a low level of risk; monitoring is required, but immediate action may not be necessary.							
Medium	Yellow	Represents a moderate level of risk; it requires specific monitoring and planning to manage.							
High	Red	Represents a high level of risk; immediate action and intervention are necessary to mitigate risks.							
Task/Activity	Potential Hazard	Persons at Risk	Consequence	Likelihood	Initial Risk Rating	Mitigation Measures	Residual Consequence	Residual Likelihood	Residual Risk Rating
Receive call-out and mobilise	Incomplete details; time pressure; fatigue; lone work	Workers	Major	Possible	High	Confirm job, energisation, fire/water and access details. Use two persons where practicable, lone-worker check-ins and fatigue controls. Carry first aid, AED, extinguisher, LV rescue, LOTO, calibrated testers and PPE.	Moderate	Unlikely	Low
Arrive and secure the site	Public/traffic interface; slips; trips; falling objects	Workers, public	Major	Possible	High	Complete a dynamic risk assessment. Establish barriers, signs and exclusion zones; use a spotter/traffic control where required and maintain clear emergency access and egress.	Moderate	Unlikely	Low
Initial electrical safety assessment	Live parts; arc flash; unknown sources	Workers, others	Severe	Possible	High	Treat conductors as live until proven otherwise. Identify boards, isolation points and supplies; review drawings/permits, establish communications and exclusion zones, and appoint a safety observer where required.	Major	Unlikely	Medium
Check fire, smoke or water ingress	Electrical fire; shock through water; smoke inhalation	Workers, occupants	Severe	Possible	High	Do not enter smoke-affected or flooded areas until controlled. Coordinate with emergency services, isolate upstream where safe, use the correct extinguisher and never energise wet equipment before drying, testing or replacement.	Major	Unlikely	Medium
Apply LOTO and authorisations	Re-energisation; backfeed; wrong isolation point	Workers, others	Severe	Possible	High	Obtain permits/authority, isolate at the correct device, fit personal locks and danger tags, confirm no UPS/generator backfeed and verify de-energisation at the work location and supply point.	Major	Unlikely	Medium
Test for dead prove test prove	False negative; faulty tester; stored energy	Workers	Severe	Possible	High	Prove tester on a known live source; test all relevant phases and neutrals to earth; re-prove tester after use. Safely discharge stored energy and use insulated tools within an exclusion zone.	Major	Unlikely	Medium
Fault finding and diagnosis	Arc flash; short circuit; unexpected energisation	Workers	Severe	Possible	High	Prefer de-energised inspection. Use appropriate calibrated meters, stand aside when opening panels, do not defeat interlocks and wear arc-rated PPE where exposure remains. Stop and escalate unsafe conditions.	Major	Unlikely	Medium
Provide temporary power	Shock; incorrect earthing; overload	Workers, occupants	Severe	Possible	High	Licensed electrician only. Provide RCD protection, verify earthing/MEN integrity and load diversity, label and barricade temporary boards, test before energising and record the installation.	Major	Unlikely	Medium
Access equipment at height	Falls; dropped objects; unstable access	Workers, public	Severe	Possible	High	Select and inspect the correct ladder/EWP. Maintain three points of contact, use fall protection where required, secure tools, establish an exclusion zone and stop in adverse weather.	Major	Unlikely	Medium
Work in cupboards, risers or plant rooms	Restricted access; poor light; sharp edges; clutter	Workers	Major	Possible	High	Provide task lighting, keep doors and escape routes clear, stage materials outside congested spaces, maintain housekeeping and wear eye and cut-resistant hand protection. Report damaged panels/sharp edges.	Moderate	Unlikely	Low

Manage cables during make-safe	Trips; mechanical damage; exposed conductors	Workers, public	Severe	Possible	High	Route cables in covers/trays away from traffic. Cap or terminate exposed conductors, inspect temporary runs, remove unused leads and reinstate permanent cable routes after the make-safe work.	Moderate	Unlikely	Low
Repair or replace components	Wrong parts; heat damage; loose connections	Workers, occupants	Severe	Possible	High	Use compliant parts, do not energise melted or heat-damaged equipment, torque connections to manufacturer specifications, verify against wiring rules and record component and repair details.	Moderate	Unlikely	Low
Re-energise and verify	Shock; arc flash; equipment failure	Workers, occupants	Severe	Possible	High	Clear personnel, communicate energisation and switch in a controlled sequence. Complete polarity, insulation resistance, earth continuity and RCD tests; monitor for noise, odour, heat or abnormal operation.	Major	Unlikely	Medium
Allow occupant/public re-entry	Residual hazards; unauthorised access; exposed parts	Occupants, public	Severe	Possible	High	Reinstate covers and guards and confirm no exposed live parts. Remove barriers only when safe, secure restricted areas, brief the client on remaining isolations and apply temporary warnings where needed.	Moderate	Unlikely	Low
Document and hand over	Missing records; unreported defects; incomplete follow-up	Workers, client	Major	Possible	High	Update registers and record isolation points, tests, repairs, non-conformances and residual risks. Provide the make-safe report, identify follow-up actions/parts and securely retain compliance records.	Moderate	Unlikely	Low

SIGNATORIES OF THE JSA RISK ASSESSMENT

The signed and dated personnel listed below have cooperated in the consultation and development of this JSA Risk Assessment which has been approved by the Person/s Conducting a Business or Undertaking (PCBU). In signing this JSA Risk Assessment each individual acknowledges and confirms that they have read this JSA Risk Assessment in full, having raised any questions for items on this JSA Risk Assessment that require clarification, and confirms that they are competent, skilled and knowledgeable for the task assigned to them. Every person acknowledges that they have received the relevant training and qualifications where required, before carrying out any work contained in this JSA Risk Assessment. By signing this JSA Risk Assessment each individual agrees to work safely, to follow any safe work instructions which are provided, and agrees to use all Personal Protective Equipment where appropriate.

Full Name:		Date:		Signature:		Position:	
Full Name:		Date:		Signature:		Position:	
Full Name:		Date:		Signature:		Position:	
Full Name:		Date:		Signature:		Position:	