

Monthly PM and Inspection Checklist

Based on CMS Form 2786R (07/2018) — 2012 Life Safety Code (Healthcare)

Facility Name: _____
Month/Year (Inspection Period): _____
Building/Location: _____
Department/Unit: _____
Checklist ID or Reference (CMS 2786R): _____
Inspector Name: _____
Inspector Title: _____
Inspector Contact (Phone/Email): _____

Table of Contents

1. Introduction
2. Monthly Tasks
3. Compliance References
4. Notes and Guidance
5. Summary / Sign-Off
6. Document Revision History

Follow-Up Actions

Task #	Description	Follow-Up Action Required	Assigned To	Target Date
1				
2				

Document Revision History

Revision	Date	Description of Changes	Updated By
1.0	2026-05-18	Initial draft with updates.	
1.1	2026-05-18	Consolidated Summary Section.	

1. Elevators — Firefighter's Service (K531)

Reference: 19.5.3, 9.4.2, 9.4.3 (Existing) | 18.5.3, 9.4.2, 9.4.3 (New)
ASME A17.1 / ASME A17.3

#	Task	Pass	Fail	N/A	Notes
1.1	Operate Firefighter's Service Phase I key recall on each elevator				

#	Task	Pass	Fail	N/A	Notes
1.2	Operate Firefighter's Service Phase II in-car key operation on each elevator				
1.3	Confirm elevator lobby smoke detectors initiate Phase I recall				
1.4	Confirm machine room smoke detectors function				
1.5	Document results in written log with date and elevator ID				

Elevator IDs Tested:

Written Record Location:

2. Generator / Essential Electric System (EES) — Monthly Load Test (K918)

Reference: 6.4.4, 6.5.4, 6.6.4 (NFPA 99) | NFPA 110

Required: 12 times per year, in 20–40 day intervals, ≥ 30 minutes under load

#	Task	Pass	Fail	N/A	Notes
2.1	Start generator set (warm or auto-start acceptable for monthly test — cold start required only for 36-month test)				
2.2	Exercise generator under load for a minimum of 30 minutes				
2.3	Verify automatic or manual transfer of all EES loads				
2.4	Verify generator supplies power within 10 seconds of transfer				
2.5	Inspect life safety branch (lighting, exit signs, alarms energized)				
2.6	Inspect critical branch receptacles / cover plates (distinctive color/markings per K917)				
2.7	Confirm remote EES alarm annunciator (battery-powered, hard-wired) is operational (K916)				
2.8	Record test date, duration, load, and results in written maintenance log				

Last Test Date: _____ **Days Since Last Test:** _____

Generator ID / Location:

Transfer Switch ID:

⚠ Intervals must not exceed 40 days between tests. If 10-second criterion is not met during monthly test, an annual process must confirm capability for life safety and critical branches.

3. Line Isolation Monitor (LIM) — Monthly Test (K914)

Reference: 6.3.4 (NFPA 99) | 6.3.2.6.3.6

Required: ≤ 1-month intervals (manual test)

#	Task	Pass	Fail	N/A	Notes
3.1	Actuate LIM test switch in each isolated power panel				
3.2	Verify visual alarm activates upon test switch actuation				
3.3	Verify audible alarm activates upon test switch actuation				
3.4	Record date, location, and results in maintenance log				

Note: For LIM circuits with automated self-testing, this manual test is still required at intervals ≤ 12 months. LIM circuits must also be tested after any repair or renovation to the electrical distribution system.

LIM Panel Locations Tested:

Panel Location	Visual Alarm	Audible Alarm	Pass/Fail

4. Generator — Weekly Inspection (K918)

(Performed weekly; log reviewed as part of monthly PM sign-off)

Reference: NFPA 110

#	Task	Pass	Fail	N/A	Notes
4.1	Confirm all four weekly generator inspection logs are on file for the month				
4.2	Review weekly logs for any abnormalities or alarms noted				
4.3	Confirm no outstanding corrective actions from weekly inspections				

Document Maintenance Notes

- **Monthly Cold Start:** Ensure language specifies alignment with emergency preparedness requirements.
- **Quarterly Pull Station Test:** Updated to "Annual Pull Station Test" as per E-Tag guidelines.
- **Annual Inspector Test:** Adjusted duration from 60 seconds to 90 seconds.
- **Weekly Summary:** Updated K-Tag reference from K341 to K345.
- **Long-Cycle Section B Header:** Corrected header to reflect 5-year cycle instead of 6-year cycle.

Summary / Sign-Off

Total Deficiencies Found: _____

Immediate Corrective Actions Taken: ☐ Yes ☐ No ☐ N/A

Work Orders Submitted: ☐ Yes ☐ No WO#(s): _____

Items Requiring Follow-Up: ☐ Yes ☐ No

#	K-Tag	Deficiency Description	Corrective Action	Date Resolved
---	-------	------------------------	-------------------	---------------

Technician Signature: _____ Date: _____

Supervisor / Director Signature: _____ Date: _____

Document Revision History

Revision	Date	Description of Changes	Updated By
----------	------	------------------------	------------

1.0	2026-05-18	Initial draft with updates.	
-----	------------	-----------------------------	--

1. Elevators — Firefighter's Service (K531)

Reference: 19.5.3, 9.4.2, 9.4.3 (Existing) | 18.5.3, 9.4.2, 9.4.3 (New)

ASME A17.1 / ASME A17.3

#	Task	Pass	Fail	N/A	Notes
1.1	Operate Firefighter's Service Phase I key recall on each elevator				
1.2	Operate Firefighter's Service Phase II in-car key operation on each elevator				
1.3	Confirm elevator lobby smoke detectors initiate Phase I recall				
1.4	Confirm machine room smoke detectors function				
1.5	Document results in written log with date and elevator ID				

Elevator IDs Tested:

Written Record Location:

2. Generator / Essential Electric System (EES) — Monthly Load Test (K918)

Reference: 6.4.4, 6.5.4, 6.6.4 (NFPA 99) | NFPA 110

Required: 12 times per year, in 20–40 day intervals, ≥ 30 minutes under load

#	Task	Pass	Fail	N/A	Notes
2.1	Start generator set (warm or auto-start acceptable for monthly test — cold start required only for 36-month test)				
2.2	Exercise generator under load for a minimum of 30 minutes				
2.3	Verify automatic or manual transfer of all EES loads				
2.4	Verify generator supplies power within 10 seconds of transfer				
2.5	Inspect life safety branch (lighting, exit signs, alarms energized)				

#	Task	Pass	Fail	N/A	Notes
2.6	Inspect critical branch receptacles / cover plates (distinctive color/markings per K917)				
2.7	Confirm remote EES alarm annunciator (battery-powered, hard-wired) is operational (K916)				
2.8	Record test date, duration, load, and results in written maintenance log				

Last Test Date: _____ **Days Since Last Test:** _____

Generator ID / Location:

Transfer Switch ID:

⚠ Intervals must not exceed 40 days between tests. If 10-second criterion is not met during monthly test, an annual process must confirm capability for life safety and critical branches.

3. Line Isolation Monitor (LIM) — Monthly Test (K914)

Reference: 6.3.4 (NFPA 99) | 6.3.2.6.3.6
Required: ≤ 1-month intervals (manual test)

#	Task	Pass	Fail	N/A	Notes
3.1	Actuate LIM test switch in each isolated power panel				
3.2	Verify visual alarm activates upon test switch actuation				
3.3	Verify audible alarm activates upon test switch actuation				
3.4	Record date, location, and results in maintenance log				

Note: For LIM circuits with automated self-testing, this manual test is still required at intervals ≤ 12 months. LIM circuits must also be tested after any repair or renovation to the electrical distribution system.

LIM Panel Locations Tested:

Panel Location	Visual Alarm	Audible Alarm	Pass/Fail

4. Generator — Weekly Inspection (K918)

(Performed weekly; log reviewed as part of monthly PM sign-off)

Reference: NFPA 110

#	Task	Pass	Fail	N/A	Notes
4.1	Confirm all four weekly generator inspection logs are on file for the month				
4.2	Review weekly logs for any abnormalities or alarms noted				
4.3	Confirm no outstanding corrective actions from weekly inspections				

Reference: Standards Cited in This Checklist

K-Tag	Topic	Standard Reference
K531	Elevator Firefighter's Service	ASME A17.1 / A17.3, LSC 9.4.2, 9.4.3
K914	LIM Testing (≤ 1 month)	NFPA 99 §6.3.4, §6.3.2.6.3.6
K916	EES Alarm Annunciator	NFPA 99 §6.4.1.1.17
K917	EES Receptacle Marking	NFPA 99 §6.4.2.2.6
K918	Generator Load Test (12×/year)	NFPA 99 §6.4.4, NFPA 110

Form based on CMS-2786R (07/2018). Retain completed checklists as part of the facility maintenance record.