



Programming Fundamentals

LAB # 4

Instructions:

- You have to submit CPP files of the program in a folder, named your Registration Number.
 - You have to upload your lab tasks on CMS.
 - All program codes should be written in C/C++. Students should use Visual studio compiler for coding.
 - Indent and comment your code.
 - Use meaningful variable names
 - Plan your code carefully on a piece of paper before you implement it.
-

Task 1: (No Return Type No Parameter)

Write the following function and implement these functions in a sample program.

1. void table()
// this function will get a number and print its table 1 to 10.
2. void divisor():
//to print all the divisor of number that is prompted from the user.
3. Void sorting():
//to sort the numbers in decreasing order.
4. Void power();
*//to takes two positive integers a and b as input from the user and displays the value of ab.
(Note: Do not use any built-in function for this purpose). a and b can be negative.*
5. Void Numbersperate():
//take input from user and separate it. Number can be any digit.
6. Void convert();
//Take C string and convert upper to lower case and vice versa.
7. Void findreverse()
//find the reverse of number entered by the user.
8. Void findpalindrome()
//Number is palindrome or not.
9. void Numbernumberlength()
 - Read words from word_frequency.txt.
 - Count the number of words and store each word's length in word_length.txt.
 - Display the longest word's length on the console.

Example:

word_frequency.txt

This course will also enable the students to
develop practical applications

Word_length.txt

Word Count: 10
Max Word Length: 12

Sample Output for the whole task:

Press T for printing table
Press D for divisors
Press S for sorting
Press A for power
Press N to separate number.
Press C to convert String
Press P for palindrome
Press R to find reverse Number
Press L for Numbernumberlength

*Enter your choice: N
Enter a Number: 45785
Separated number: 4 5 7 8 5*

*Do you want to continue(Y/N): Y
Enter your choice: P
Enter the value of a: -2
Enter the value of b: -3
-2 to the power of -3 is -0.125*

*Do you want to continue(Y/N): N
Program terminated...*

End of LAB 4 😊