FLAGS Register				
Bits	3	2	1	0
Purpose	Borrow	Carry	Underflow	Overflow

General Instruction Structure		
Bits	15 - 4	3 - 0
Purpose	OPERAND	OPCODE

15 - 12	11 - 8	7	6	5	4	3 - 0		
Unused		Unused				OPCODE	Instruction	Hex
N/A		x				b'0000'	NOP	0x00
Unused		!Immediate	LOGIC / !ARITH	Don't care	SUB			
Unused		0	0	X	0	b'0001'	ADD Imp	0x01
Unused		0	0	X	1	b'0001'	SUB Imp	0x11
Value B	Value A	!Immediate	LOGIC / !ARITH	Don't Care	SUB			
#	#	1	0	X	0	b'0001'	ADD #	0x##81
#	#	1	0	X	1	b'0001'	SUB #	0x##91
Unused		!Immediate	LOGIC / !ARITH	LOGIC OPERATION				
N/A		0	1	0	0	b'0001'	AND Imp	0x41
N/A		0	1	0	1	b'0001'	OR Imp	0x51
N/A		0	1	1	0	b'0001'	XOR Imp	0x61
Value B	Value A	!Immediate	LOGIC / !ARITH	LOGIC OPERATION				
#	#	1	1	0	0	b'0001'	AND #	0x##C1
#	#	1	1	0	1	b'0001'	OR #	0x##D1
#	#	1	1	1	0	b'0001'	XOR #	0x##E1
Unused		Don't Care	Don't Care	SHIFT	DEC / !INC			
N/A		X	X	0	0	b'0010'	INC	0x02
N/A		X	X	0	1	b'0010'	DEC	0x12
Unused		Don't Care	Don't Care	SHIFT	R / !L			
N/A		X	X	1	0	b'0010'	LSH	0x22
N/A		X	X	1	1	b'0010'	RSH	0x32
Unused		Literal Value #						
N/A		#				b'0011'	LDA #	0x#3
N/A		#				b'0100'	LDB #	0x#4
Unused		Borrow	Carry	Underflow	Overflow			
N/A		s / !c	s / !c	s / !c	s / !c	b'0101'	SFLG	0xc5
Unused		Don't Care	Don't Care	Don't Care	Don't Care			
N/A		x	x	x	x	b'0110'	HLT	0xX6
Unused		Don't Care	Abs / !Ind	Composite $	REG_B / !REG_A			
N/A		x	0	0	0	b'0111'	JMPA ind	0x07
N/A		x	0	0	1	b'0111'	JMPB ind	0x17
N/A		x	0	1	x	b'0111'	JMPAB ind	0x27
N/A		x	1	0	0	b'0111'	JMPA	0x47
N/A		x	1	0	1	b'0111'	JMPB	0x57
N/A		x	1	1	x	b'0111'	JMPAB	0x67
Memory Address [$]								
$						b'1000'	JMP $	0x$$$8
$						b'1001	STA $	0x$$$9
Memory Address [$]								
$						b'1010'	LDA $	0x$$$A
$						b'1011'	LDB $	0x$$$B
Literal Value								
#						b'1100'	JMP #	0x###C
#						b'1101'	BRZ #	0x###D
#						b'1110'	BRO #	0x###E
#						b'1111'	BRU #	0x###F