1. The Power Foundation (Create the Rails)

Do this before plugging in any sensors.

From	*To*	*Wire Color*	*Purpose*
Left 3V Pin	**Left Red Rail (+)**	Red	Creates **3.3V Zone** (Safe)
Left GND Pin	**Left Blue Rail (-)**	Black	Creates Left Ground
Right 5V Pin	**Right Red Rail (+)**	Red	Creates **5V Zone** (High Power)
Right GND Pin	**Right Blue Rail (-)**	Black	Creates Right Ground

2. MicroSD Card Module

Place on Left Breadboard (near data pins).

SD Pin	*Connect To*	*Wire Color*	*Crucial Note*
VCC	**RIGHT Red Rail (+)**	**Red**	**CROSS OVER!** Must reach 5V.
GND	**Left Blue Rail (-)**	Black	Local Ground
CS	**Pin 15**	Orange	Located on Right side
MOSI	**25**	White	Pin above 'SO'
MISO	26	Blue	
SCK	**2**	Yellow	Labeled "CL"

3. GPS Module (NEO-6M)

Place on Left Breadboard.

GPS Pin	*Connect To*	*Wire Color*	*Crucial Note*
VCC	**Left Red Rail (+)**	Red	Uses 3.3V -br
GND	**Left Blue Rail (-)**	Black	Local Ground - red
TXD	**Pin 16**	Green	Connects to Right side-or
RXD	**Pin 14**	Yellow	Connects to Right side -ye
PPS	*(Nothing)*	-	Leave Empty

4. NFC Module (PN532)

Place on Left Breadboard.

NFC Pin	*Connect To*	*Wire Color*	*Crucial Note*
VCC	**Left Red Rail (+)**	Red	Uses 3.3V - dam
GND	**Left Blue Rail (-)**	Black	Local Ground -whi
SDA	**Pin 5**	White	Shares row with Pin 5 - blue
SCL	**Pin 4**	Yellow	Shares row with Pin 4 -green

5. Buzzer Module

Place on Left Breadboard.

Buzzer Pin	***Connect To***	***Wire Color***	***Crucial Note***
VCC	**Left Red Rail (+)**	Red	Uses 3.3V
GND	**Left Blue Rail (-)**	Black	Local Ground
I/O	**Pin 13**	Green	Connects to Right side