

ICG Online Assignment (B1)

Printing Multiple Expressions

Time: 40 Mins Total Marks: 10

Problem

In this online, you are required to extend the grammar to support **printing values of multiple expressions with a single println statement**. Thus, your program should support the following syntax.

```
int a, b;  
a=2; b=3;  
println(a+b, 2+3*4, a*2+3); //printing of multiple comma separated expressions
```

Task

1. Extend the current grammar to support **printing values of multiple expressions with a single println statement**. The expressions will be comma (,) separated. Like the offline, you need to work only with integer type variables. There will be no syntax or semantic errors in the given input program.
2. Update your ICG code to generate assembly code for this new rule/syntax. The assembly code output by your program must correctly be assembled with 'fasm'. Subsequently, the binary produced by 'fasm' from your assembly code must produce the expected output for the input program.

Mark Distribution

- Extending the grammar to support printing values of multiple expressions. (5)
- Code generation for printing values of multiple expressions. (5)

Find a sample input-output in the next page.

Sample Input-Output

Input Program	Generated Sample Assembly (print library omitted)
<pre> 1 int a, b; 2 int main(){ 3 int x, y; 4 a = 10; 5 b = 20; 6 x = 100; 7 y = 200; 8 println(a, b, x, y); 9 println(a*2+b, x+y-10, 3+3*7); 10 println(a==b, a&&b, a++, -a); 11 return 0; 12 }</pre>	<pre> format ELF executable 3 entry main segment readable writeable a dd 1 DUP (0) b dd 1 DUP (0) segment readable executable main: PUSH EBP MOV EBP, ESP SUB ESP, 4 SUB ESP, 4 .L1: MOV EAX, 10 ; Line 4 MOV [a], EAX .L2: MOV EAX, 20 ; Line 5 MOV [b], EAX .L3: MOV EAX, 100 ; Line 6 MOV [EBP-4], EAX .L4: MOV EAX, 200 ; Line 7 MOV [EBP-8], EAX .L5: MOV EAX, [a] ; Line 8 CALL print_number MOV EAX, [b] ; Line 8 CALL print_number MOV EAX, [EBP-4] ; Line 8 CALL print_number MOV EAX, [EBP-8] ; Line 8 CALL print_number .L6: MOV EAX, 2 ; Line 9 MOV ECX, EAX MOV EAX, [a] ; Line 9 CWD MUL ECX PUSH EAX MOV EAX, [b] ; Line 9 MOV EDX, EAX POP EAX ; Line 9 ADD EAX, EDX CALL print_number MOV EAX, [EBP-8] ; Line 9 MOV EDX, EAX MOV EAX, [EBP-4] ; Line 9 ADD EAX, EDX PUSH EAX</pre>
Expected Output (from the generated binary by fasm)	
<pre> 10 20 100 200 40 290 24 0 1 10 -11</pre>	

```

MOV EAX, 10 ; Line 9
MOV EDX, EAX
POP EAX ; Line 9
SUB EAX, EDX
CALL print_number
MOV EAX, 7 ; Line 9
MOV ECX, EAX
MOV EAX, 3 ; Line 9
CWD
MUL ECX
MOV EDX, EAX
MOV EAX, 3 ; Line 9
ADD EAX, EDX
CALL print_number
.L7:
MOV EAX, [b] ; Line 10
MOV EDX, EAX
MOV EAX, [a] ; Line 10
CMP EAX, EDX
JE .L8
JMP .L10
.L8:
MOV EAX, 1 ; Line 10
JMP .L9
.L10:
MOV EAX, 0
.L9:
CALL print_number
MOV EAX, [a] ; Line 10
CMP EAX, 0
JNE .L11
JMP .L14
.L11:
MOV EAX, [b] ; Line 10
CMP EAX, 0
JNE .L12
JMP .L14
.L12:
MOV EAX, 1 ; Line 10
JMP .L13
.L14:
MOV EAX, 0
.L13:
CALL print_number
MOV EAX, [a] ; Line 10
PUSH EAX
INC EAX
MOV [a], EAX
POP EAX ; Line 10
CALL print_number
MOV EAX, [a] ; Line 10
NEG EAX
CALL print_number
.L15:

```

	<pre>MOV EAX, 0 ; Line 11 JMP .L17 .L16: .L17: ADD ESP, 8 POP EBP MOV EAX, 1 XOR EBX, EBX INT 0x80 POP EBP RET</pre>
--	--