Analysis of CIR and Heston Model

Chilukuri Krishna Teja   VKS Deepak Reddy   Sumanth NR

Indian Institute of Technology Hyderabad

November 13, 2022

Introduction

Stochastic Differential Equations(SDEs) and Ito Doeblin Formula

Stochastic Differential Equation

An SDE is a differential equation that contains a stochastic term

$$dX_t = \mu(X_t, t)dt + \sigma(X_t, t)dW_t$$

where μ is called the **drift term** and σ is called the **diffusion term**.

Theorem (Ito Doeblin Formula)

Let $f(t, X)$ be a continuous function in time t and X where X is a Random Variable that is continuous in t. Then, the Ito Doeblin Formula is given by

$$df(t, X) = \left(f_t + \frac{1}{2} f_{XX} \right) dt + f_X \, dX$$

Ito's Integral

Ito's Integral is defined as follows

$$I_t := I(t) = \int_0^t \Delta(s)dW_s$$

where $\Delta(s)$ is an adopted process and W_s is a Brownian motion. It has the following properties

1. $I(t)$ is a continuous process.
2. $I(t)$ is a martingale.
3. Zero Mean Property $\mathbb{E}\left[\int_0^t \Delta(s)dW_s\right] = 0$
4. Ito Isometry $\mathbb{E}\left[\int_0^t \Delta(s)dW_s\right]^2 = \mathbb{E}\left[\int_0^t \Delta(s)^2 dW_s\right] = t$

CIR Model

Rate Models

Introduced by Oldrich Vasicek (1977) to model interest rates.

$$dr_t = \kappa(\theta - r_t)dt + \sigma dW_t$$

where κ is the **mean reversion rate**, θ is the **long term mean** and σ is the **volatility** of the interest rate.

The model can be easily solved and the closed form solution is given by

$$r_t \sim \mathcal{N}\left(e^{-\kappa t}r_0 + \theta\left(1 - e^{-\kappa t}\right), \frac{\sigma^2}{2\kappa}\left(1 - e^{-2\kappa t}\right)\right)$$

The main disadvantage is that the interest rate can become negative.

CIR Model

The **CIR** model was introduced by John Carrington **Cox**, Jonathan Edwards **Ingersoll** and Stephen Alan **Ross** (1985) and follows the following SDE.

$$dr_t = \kappa(\theta - r_t)dt + \sigma\sqrt{r_t}dW_t$$

where

- r_t is the **interest rate** at time t
- κ is the **speed of mean reversion**
- θ is the **long term mean**
- σ is the **volatility coefficient**
- W_t is a **Brownian Motion**

with initial rate r_0 given.

Proposition

The exact solution of CIR is given by

$$r_t = e^{-\kappa t} r_0 + \theta \left(1 - e^{-\kappa t}\right) + \sigma e^{-\kappa t} \int_0^t e^{\kappa s} \sqrt{r_t} dW_s$$

Proof.

$$dr_t = \kappa(\theta - r_t)dt + \sigma \sqrt{r_t} dW_t$$

$$e^{\kappa t} dr_t + \kappa e^{\kappa t} r_t dt = \kappa \theta e^{\kappa t} dt + \sigma e^{\kappa t} \sqrt{r_t} dW_t$$

$$\implies d\left(e^{\kappa t} r_t\right) = \kappa \theta e^{\kappa t} dt + \sigma e^{\kappa t} \sqrt{r_t} dW_t \quad \text{(Ito Doeblin Formula)}$$

$$\implies \int_0^t d\left(e^{\kappa s} r_s\right) = \int_0^t \theta \kappa e^{\kappa s} ds + \int_0^t \sigma e^{\kappa s} \sqrt{r_s} dW_s$$

$$\therefore \ r_t = e^{-\kappa t} r_0 + \theta \left(1 - e^{-\kappa t}\right) + \sigma \int_0^t e^{\kappa s} \sqrt{r_s} dW_s$$

Proposition

The expectation of r_t is given by

$$\mathbb{E}\left[r_t\right] = e^{-\kappa t}r_0 + \theta\left(1 - e^{-\kappa t}\right)$$

Proof.

$$\mathbb{E}\left[r_t\right] = \mathbb{E}\left[e^{-\kappa t}r_0 + \theta\left(1 - e^{-\kappa t}\right) + \sigma\int_0^t e^{\kappa s}\sqrt{r_s}\,dW_s\right]$$

$$= e^{-\kappa t}r_0 + \theta\left(1 - e^{-\kappa t}\right) + \mathbb{E}\left[\sigma\int_0^t e^{\kappa s}\sqrt{r_s}\,dW_s\right]$$

$$\therefore \mathbb{E}\left[r_t\right] = e^{-\kappa t}r_0 + \theta\left(1 - e^{-\kappa t}\right)$$

Note that $\lim\limits_{t\to\infty}\mathbb{E}\left[r_t\right] = \theta$ (**long term mean**).

Proposition

The variance of r_t is given by

$$Var[r_t] = \frac{\sigma^2}{\kappa} r_0 \left(e^{-\kappa t} - e^{-2\kappa t} \right) + \frac{\theta \sigma^2}{2\kappa} \left(1 - e^{-\kappa t} \right)^2$$

Proof.

$$\begin{aligned}
\text{Var}[r_t] &= \mathbb{E}\left[r_t^2 \right] - \mathbb{E}[r_t]^2 \\
&= \mathbb{E}\left[\left(e^{-\kappa t} r_0 + \theta \left(1 - e^{-\kappa t} \right) + \sigma e^{-\kappa t} \int_0^t e^{\kappa s} \sqrt{r_s} dW_s \right)^2 \right] - \mathbb{E}[r_t]^2 \\
&= \mathbb{E}\left[\left(\mathbb{E}[r_t] + \sigma e^{-\kappa t} \int_0^t e^{\kappa s} \sqrt{r_s} dW_s \right)^2 \right] - \mathbb{E}[r_t]^2 \\
&= 2\mathbb{E}\left[\mathbb{E}[r_t] \, \sigma e^{-\kappa t} \int_0^t e^{\kappa s} \sqrt{r_s} dW_s \right] + \mathbb{E}\left[\left(\sigma e^{-\kappa t} \int_0^t e^{\kappa s} \sqrt{r_s} dW_s \right)^2 \right]
\end{aligned}$$

Proof.

$$
= 2\, \mathbb{E}\left[r_t\right] e^{-\kappa t} \cdot 0 + \mathbb{E}\left[\left(\sigma e^{-\kappa t} \int_0^t e^{\kappa s} \sqrt{r_s}\, dW_s\right)^2\right]
$$

$$
= \mathbb{E}\left[\sigma^2 e^{-2\kappa t} \int_0^t e^{2\kappa s} r_s\, ds\right] \quad \text{(Iso Isometry)}
$$

$$
= \sigma^2 e^{-2\kappa t} \int_0^t e^{2\kappa s} \mathbb{E}\left[r_s\right] ds
$$

$$
= \sigma^2 e^{-2\kappa t} \int_0^t e^{2\kappa s} \left(e^{-\kappa s} r_0 + \theta \left(1 - e^{-\kappa s}\right)\right) ds
$$

$$
= \frac{\sigma^2}{\kappa} e^{-2\kappa t} r_0 \left(e^{\kappa s} - 1\right) + \theta \sigma^2 e^{-2\kappa t} \int_0^t \left(e^{2\kappa s} - e^{\kappa s}\right) ds
$$

$$
= \frac{\sigma^2}{\kappa} r_0 \left(e^{-\kappa t} - e^{-2\kappa t}\right) + \frac{\theta \sigma^2}{2\kappa} \left(1 - e^{-\kappa t}\right)^2
$$

Method of Moments of Ito Integral

$$I_t = \int_0^t \Delta_s dW_s \quad \text{and} \quad \mathbb{E}\left[I_t\right] = 0 \quad \text{(Zero Mean Property)}$$

$$\mathbb{E}\left[I_t^2\right] = \mathbb{E}\left[\int_0^t \Delta^2(s)ds\right] \quad \text{(Ito Isometry)}$$

Proposition

$$\mathbb{E}\left[I_t^3\right] = 0$$

Proof.

$$X_t^n = n\int_0^t X_s^{n-1}dX_s + \frac{n(n-1)}{2}\int_0^t X_s^{n-2}ds \quad \text{(Ito Doeblin Formula)}$$

$$\mathbb{E}\left[\int_0^t I_s^2 \Delta(t)dW_t\right] = 0 \implies \mathbb{E}\left[I_t^3\right] = 0 + 3\int_0^t \mathbb{E}\left[I_s\right]ds = 0$$

3^{rd} Moment of r_t

$$\mathbb{E}\left[r_t^3\right] = \mathbb{E}\left[\left(A_t + B_t I_t\right)^3\right]$$

where $A_t = e^{-\kappa t} r_0 + \theta\left(1 - e^{-\kappa t}\right)$ $B_t = \sigma e^{-\kappa t}$ and
$I_t = \displaystyle\int_0^t e^{\kappa s}\sqrt{r_s}\,dW_s$

$$
\begin{aligned}
\mathbb{E}\left[r_t^3\right] &= \mathbb{E}\left[\left(A_t + B_t I_t\right)^3\right] \\
&= A_t^3 + 3A_t^2 B_t \mathbb{E}\left[I_t\right] + 3A_t B_t^2 \mathbb{E}\left[I_t^2\right] + B_t^3 \mathbb{E}\left[I_t^3\right] \\
&= A_t^3 + 3A_t B_t^2 \mathbb{E}\left[I_t^2\right] \\
&= A_t\left(A_t^2 + B_t^2 \int_0^t e^{2\kappa s}\mathbb{E}\left[r_s\right]ds\right) \\
&= \mathbb{E}\left[r_t\right]\left(\mathbb{E}\left[r_t\right]^2 + \mathsf{Var}\left[r_t\right]\right)
\end{aligned}
$$

Heston Model

Introduction to Heston Model

Improvement to Black Scholes Model.

Developed by Steven Heston in 1993.

- The stock price follows a general Brownian motion
- The stochastic process of the volatility is a CIR process

Some important assumptions

- Interest Rate is constant
- No dividends
- European Style Options
- Frictionless Market

Stochastic Differential Equation

Heston SDE

The Heston model is given by

$$dS_t = \mu S_t dt + \sqrt{v_t} S_t dW_t^x \qquad\qquad S_0 > 0$$
$$dv_t = \kappa(\theta - v_t)dt + \sigma\sqrt{v_t}dW_t^v \qquad\qquad v_0 > 0$$

where W_t^x and W_t^v are Brownian motions with correlation ρ where

$$dW_t^x dW_t^v = \rho dt \quad |\rho| \leq 1$$

- μ is the **drift**
- κ is the **speed of mean reversion**
- θ is the **long term mean**
- σ is the **volatility coefficient**
- ρ is the **correlation coefficient**

Garsinov Theorem

The stock price and variance are under the historical measure $\mathbb{P}$.

By applying the Girsanov theorem one can find
a probability measure $\mathbb{Q}$ such that we can represent
the stock price in the form

$$dS_t = rS_t dt + \sqrt{v_t} S_t d\tilde{W}_t^x, S_0 > 0,$$
$$dv_t = \kappa(\theta - v_t)dt + \sigma\sqrt{v_t} dW_t^v, v_0 > 0$$

where,

$$\tilde{W}_t^x = \left(W_t^x + \frac{\mu - r}{\sqrt{v_t}} \right)$$

Euler-Maruyama Method

Numerical Method to solve Stochastic Differential Equations.
Divide the interval $[0, T]$ into N equal sub-intervals of length $\Delta t = \frac{T}{N}$

$$0 = t_0 < t_1 < \cdots < t_N = T \qquad \Delta t = \frac{T}{N} = t_{n+1} - t_n$$

An SDE

$$dX_t = r(t, X_t)dt + \sigma(t, W_t)dW_t \quad X_0 = 0$$

can be approximated by Euler-Maruyama method, given by

$$X_{n+1} = X_n + r(t_n, X_n)\Delta t + \sigma(t_n, X_n)\Delta W_n$$

where $\Delta W_n \sim \mathcal{N}\left(0, \sqrt{\Delta t}\right)$

Discretized Heston Model

Discretized Heston Model

The Heston model is given by

$$S_{t+1} = S_t + rS_t\Delta t + \sqrt{v_t}Z_x\sqrt{\Delta t}$$
$$v_{t+1} = v_t + \kappa(\theta - v_t)\Delta t + \sigma Z_v\sqrt{\Delta t}$$

where $Z_x, Z_v \sim \mathcal{N}(0, 1)$ with correlation ρ So, we can write Z_x, Z_v as

$$Z_x = \rho Z_1 + \sqrt{1 - \rho^2}Z_2$$
$$Z_v = Z_1$$

where $Z_1, Z_2 \sim \mathcal{N}(0, 1)$ are independent.

Method of Moments

We define
$$Q_{t+1} := \frac{S_{t+1}}{S_t} = 1 + r + \sqrt{v_t} Z_s$$

Sample Moments of Q_{t+1} are given by

$$\mathbb{E}\left[Q_{t+1}\right] = (1+r)$$
$$\mathbb{E}\left[Q_{t+1}^2\right] = (1+r)^2 + \mathbb{E}\left[v_t\right]$$
$$\mathbb{E}\left[Q_{t+1}^3\right] = (1+r)^3 + 3(1+r)\mathbb{E}\left[v_t\right]$$
$$\mathbb{E}\left[Q_{t+1}^4\right] = (1+r)^4 + 6(1+r)^2\mathbb{E}\left[v_t\right] + 3\mathbb{E}\left[v_t^2\right]$$
$$\mathbb{E}\left[Q_{t+1}^5\right] = (1+r)^5 + 10(1+r)^3\mathbb{E}\left[v_t\right] + 15(1+r)\mathbb{E}\left[v_t^2\right]$$

Improvement of Heston Model

Rate of interest changes once every 3 months.

An improvement of the Heston model is given by a piecewise constant interest rate model.

Here, we assume that the interest rate is constant for 3 months and use CIR Model to estimate the new rate.