

Amiga A4000TX

Hardware, processors, memory, storage, USB, operating system and component versions.

68060 rev 5

2 MiB Chip + 624 MiB Fast

AGA + ZZ9000

XACP / ARM Core1

10.0.0.40

Scope and evidence

Inventory of the real A4000TX at **10.0.0.40**, collected over its AmigaBridge connection on **7 October 2026** (Mac clock). This is a live hardware/OS inventory, supported by prior installation records and clearly identified manufacturer specifications.

No persistent Amiga configuration, firmware or installed application was changed. Read-only queries and two small native inventory programs were staged in RAM;; their outputs were copied to this Mac. The disk inquiries were limited to mounted devices and used INQUIRY and READ CAPACITY. No media scan, format, repair, benchmark, reboot or audio playback was performed.

“Live” means reported by this running machine. “Owner” means supplied in the conversation. “Specification” describes a product family, not a physical inspection. “Prior verification” records earlier tests, not a new test today. Unidentified revisions, serials and chip markings remain unknown. This report is an inventory, not a full disk backup.

Collected: 2026-10-07T20:47:14+00:00 . Free-memory, task, socket and disk-usage figures are snapshots taken at different points during collection, while ScummVM was running. 1 MiB = 1,048,576 bytes; 1 GiB = 1,073,741,824 bytes; decimal GB = 1,000,000,000 bytes.

System at a glance

Area	Verified result
Host	A4000TX (owner identification); active 68060 revision 5; AGA PAL 50 Hz
Memory	2 MiB Chip + 624 MiB Fast mapped (256 + 112 + 256 MiB)

Area	Verified result
Graphics / ARM	ZZ9000; Workbench 1920 × 800 at 8 bits/pixel; firmware register \$0113; prior XX19c/XACP activation and ARM execution
Storage	64.030 GB CF device with System: and HDD50Gig;; 31.243 GB SD-to-CF device with SD032G;; DF0: empty
USB	Freeway Triton Z3 driver 1.01; Poseidon 4.5; three-port high-speed root hub; no external USB device enumerated
Network	X-Surf 100, Roadshow 1.15; 10.0.0.40/24; bridge TCP 2345 connected
OS	Kickstart 47.115 / Exec 47.13; disk version 47.2; workbench.library 47.33 (2021)
Inventory coverage	77 loaded library/class/audio entries; 28 loaded devices; 494 installed-component version queries; 2,763 SYS: file records

Hardware, processors and chips

Item	Identification	Evidence	Limits
Motherboard	Amiga A4000TX	Owner identification; AGA and memory/expansion configuration corroborate it	PCB revision, assembly date and serial not remotely established
Accelerator	Terrible Fire TF4060	Owner identification; 68060, ehide driver and AutoConfig serial 4060 corroborate	Board revision, FPGA/CPLD firmware and actual CPU MHz unknown
Main CPU	Motorola-compatible 68060, revision 5	Live CPU and ShowConfig	Full/LC/EC package marking and mask/date codes require physical inspection
FPU and MMU	68060 MMU; FPU capability reported	Live CPU/Exec capability flags	OS labels FPU "68882"; this is not evidence of a separate active 68882 chip
CPU caches	Instruction cache/burst; data cache/copyback; superscalar, store buffer, branch cache enabled	Live CPU command	No clock-changing or cache-changing command run
AGA Alice	AGA PAL Alice R2, ID \$0023	Live ShowConfig	Physical package/date code unknown
AGA Lisa	AGA Lisa, ID \$00F8	Live ShowConfig	No physical package/date-code inspection
Paula audio/I/O	Paula audio driver active; native audio.device loaded	Live OS/driver evidence	Exact Paula revision/package not read electronically
CIA A / CIA B	ciaa.resource and ciab.resource registered	Live Exec resources	Resource names confirm OS interfaces; no individual chip date/revision read

Item	Identification	Evidence	Limits
Other motherboard logic	Buster / Ramsey / Gary and supporting clock, RTC and glue logic	Expected A4000-class architecture, not individually inventoried	Exact silicon, revisions, programmable-logic versions and clock oscillator markings unknown
ZZ9000	MNT ZZ9000 in Zorro III mode	Live AutoConfig IDs 28014/4 and 28014/5	Physical PCB revision and serial unavailable
ZZ9000 processor/FPGA	Xilinx Zynq XC7Z020: dual ARM Cortex-A9, nominal 666 MHz; FPGA fabric	Manufacturer specification; prior ARM Core1 execution verified	Core count, silicon stepping and physical markings not freshly probed
ZZ9000 DDR3	1 GB onboard DDR3 per manufacturer; 256 MiB exposed as Amiga Fast RAM	Specification plus live RAM AutoConfig	The remaining DDR is not automatically additional AmigaOS RAM
Ethernet	Individual Computers X-Surf 100, ShowConfig identifies Rev 3 ZII/ZIII	Live AutoConfig and active network driver	Current device reports 100,000,000 bit/s; PHY/controller chip markings unverified
IDE controller	Individual Computers Buddha IDE; buddha.device and 2nd.buddha.device 52.110	Live AutoConfig, drivers and mounted drives	Board flash build date and exact PCB revision not obtained
USB controller	Freeway Triton Lite (owner model), Zorro III EHCI/PIO driver active	Live driver/tasks; supplied-driver AutoConfig matching	Underlying EHCI silicon and FPGA revision not identified
USB root hub descriptor	Philips ISP1520, VID 0471, PID 3526; 3 ports	Live Poseidon descriptors and startup log	Root-hub identity may be supplied by the driver; not proof of the host-controller chip marking
Native floppy	DF0: trackdisk.device unit 0, no disk	Live mounted device and Info	Manufacturer/model and DD/HD mechanism not identified
External MIDI	Roland MT-32 intended via native serial MIDI adapter	Owner information; CAMD configuration previously verified	MT-32 disconnected; no end-to-end physical test
ZZ9000AX audio add-on	Driver and audio modes installed; Music Unit preference selects it	Live files and saved preferences	Physical daughterboard presence and playback remain unconfirmed

ZZ9000 processor and DDR3 specifications: MNT Research product documentation. Accelerator-family context: Terrible Fire's TF4060 design announcement. The accelerator's advertised maximum clock is not treated as this machine's measured CPU clock.

Physical inspection still needed: motherboard/accelerator/card PCB revisions, CPU mask and date codes, RAM chip brands and populated module sizes, Buster/Ramsey/Gary/Paula/CIA revisions, PSU model/ratings, battery condition, fan models, cabling, monitor make/model and unexposed peripheral serials. No reliable remote temperature, voltage, fan-speed or SMART data was obtained.

Memory and address map

Region	Inclusive range	Capacity	Priority	Attributes	Evidence
Accelerator-range Fast RAM	\$08000000-\$17FFFFFF	256 MiB	40	\$0505	TF4060 attribution consistent with owner hardware and address map
Motherboard-range Fast RAM	\$01000000-\$07FFFFFF	112 MiB	30	\$0505	Motherboard attribution inferred from A4000 address range
ZZ9000 Fast RAM	\$50000000-\$5FFFFFFF	256 MiB	20	\$0405	Directly matched to AutoConfig 28014/5
Chip RAM	\$00001000-\$001FFFFF	2 MiB physical; 2,093,056 bytes reported	-10	\$0703	First 4 KiB excluded from OS-reported total

Fast RAM total: **654,311,424 bytes = 624 MiB**. Chip RAM reported total: **2,093,056 bytes**. At the initial snapshot, Fast RAM free was 596,232,368 bytes (568.61 MiB) and Chip RAM free was 1,889,728 bytes (1.80 MiB). These live totals supersede the earlier owner estimate of 284 MB Fast RAM.

Exec memory headers begin 32 bytes into each listed region. The address ranges above describe the map; allocation metadata accounts for the small difference in usable memory. Priority 40/30/20/-10 establishes the OS allocation preference, not measured memory speed.

The ZZ9000's 128 MiB graphics/register aperture is an address window, not another 128 MiB to add to system RAM. Its onboard DDR3, ARM workspace, graphics buffers and exposed 256 MiB Amiga Fast RAM are overlapping uses of the same card memory. Do not add the full card DDR3 specification to the 624 MiB OS total.

Expansion boards and identifiers

Identification	Decimal IDs	Hex IDs	Base	ConfigDev bytes	ROM type	Flags	Serial field
Probable TF4060 / IDE function; model supplied by owner; serial field 4060 supports attribution	5080 / 148	\$13D8 / \$94	\$00E90000	65536	c1	02	4060
MNT ZZ9000 graphics / registers	28014 / 4	\$6D6E / \$04	\$40000000	134217728	9b	02	0
MNT ZZ9000 Fast RAM	28014 / 5	\$6D6E / \$05	\$50000000	268435456	a4	0a	0
Individual Computers Buddha IDE	4626 / 0	\$1212 / \$00	\$00EA0000	65536	d1	02	6
Freeway Triton Zorro III USB (ID pair matched in supplied driver)	5191 / 30	\$1447 / \$1E	\$60000000	16777216	80	02	20230604

Identification	Decimal IDs	Hex IDs	Base	ConfigDev bytes	ROM type	Flags	Serial field
Individual Computers X-Surf 100	4626 / 100	\$1212 / \$64	\$64000000	65536	82	02	12

The X-Surf entry has a 64 KiB ConfigDev subsize, while ShowConfig describes a 64 MiB Zorro III aperture. These are different size fields, not contradictory RAM totals. AutoConfig serial fields can contain model/build constants; "4060", "6", "12" and "20230604" are preserved verbatim and are not asserted to be unique manufacturing serial numbers or dates.

Freeway identification was strengthened by inspecting the supplied driver: at file offset \$0928 it loads manufacturer \$1447 (5191) and product \$1E (30), then calls expansion.library FindConfigDev. ShowConfig’s older boards database cannot name that entry. The \$13D8/\$94 entry is retained as a probable TF4060 function rather than a fully resolved database match.

Physical drives, partitions and filesystems

Driver / unit	Reported identity	Revision	Capacity geometry	Raw capacity	Mounted volumes	Type
buddha.device / 0	SDCFXS-064G (INQUIRY fields "SDCFXS-0" + "64G")	HDX1	125,059,072 × 512	64,030,244,864 bytes / 59.6328 GiB	System: and HDD50Gig:	CompactFlash; model matches SanDisk Extreme family
2nd.buddha.device / 0	FC-1307 / SD to CF Adapter	"Rev " (literal truncated field)	61,022,208 × 512	31,243,370,496 bytes / 29.0977 GiB	SD032G:	SD card behind adapter; underlying SD maker/model/serial not exposed

The CF identification is based on the live drive model and SanDisk’s SDCFXS product specification. Inquiry data is translated through the Buddha IDE driver. No drive serial was returned by the optional VPD query; firmware strings may be truncated. The SD adapter identifies itself rather than the card behind it. Both devices are solid-state media; the label "HDD50Gig" does not identify a rotating hard drive.

Volume	DOS device	Driver	Filesystem	Registered version	Usable GiB	Used GiB	Free GiB	State
System:	BDH0:	buddha.device / 0	PFS3 / \$50465303	19.2	3.749	0.030	3.719	validated; 0 errors
HDD50Gig:	BDH1:	buddha.device / 0	PFS3 / \$50465303	19.2	52.143	9.605	42.538	validated; 0 errors
SD032G:	SDH0:	2nd.buddha.device / 0	International FFS / DOS\3 / \$444F5303	47.4	29.096	2.001	27.095	validated; 0 errors

Mounted-volume figures are filesystem-reported usable space. Raw device capacity and cylinder extents include space the filesystem does not report as usable; these figures should not be substituted for one another. FileSystem.resource reports PFS3 19.2 and FFS 47.4; this identifies registered handlers, not a byte-for-byte verification of each disk's RDB handler image.

Partition	Cylinders	Heads × sectors/track	Extent GiB	Sectors/block	Buffers	MaxTransfer	Mask
BDH0	2–7742	16 × 68	4.0160	1 (default)	150	\$00FFFFFF	\$7FFFFFFE
BDH1	7743–114942	16 × 68	55.6152	8	150	\$00FFFFFF	\$7FFFFFFE
SDH0	2–39727	6 × 256	29.0962	2	80	\$0001FE00	\$7FFFFFFE

DF0: is mounted through trackdisk.device unit 0 with a 2-head, 80-cylinder, 11-sector default geometry (880 KiB DD layout); no disk was present. This does not establish the drive's manufacturer or whether the mechanism supports HD media. RAM: is a dynamic memory filesystem, not a separate physical drive. No optical drive, SFS volume or USB mass-storage volume was mounted at this snapshot.

USB ports and attached devices

The **Freeway Triton Zorro III controller is active**. The live startup log reports a root hub with **three ports**, successfully configured, with QuickIO enabled. The driver is `freewaytritonz3usb.device 1.01 (2022.05.16)` ; Poseidon is `4.5 (14.10.2014)` . The host task and PIO transfer task are present.

Property	Observed value
Hub descriptor	Philips Semiconductors ISP1520
Vendor / product	0471 / 3526
USB version / reported speed	USB 2.00 / high-speed
Device address / class	Address 1; class 9, subclass 0, protocol 1 (single-TT hub)
Serial / device revision	n/a / 0000
External devices now	None enumerated
Driver mode	Zorro III EHCI / PIO
Stack persistence	S:User-Startup runs ENVARC:PsdStackloader

Property	Observed value
FAT media support	L:fat95 3.18, dated 1 March 2013; loaded when needed

The descriptor’s self-powered/0 mA fields do not measure available port current. The reported three ports do not identify which case connector corresponds to each port, nor prove every physical socket under load. The supplier’s Freeway specification describes three USB connectors and USB 2.0 support; USB signalling speed is not actual Amiga file-transfer throughput.

The available Poseidon log contains severity-0 startup messages and no higher-severity errors. Its informal “blame” and “laugh” messages are normal class-loading text. USB storage was successfully used earlier according to the owner, but no storage stick is attached now. The earlier DrawBridge/USB floppy is historical and is not a mounted native floppy or USB mass-storage device in this snapshot.

Ports and I/O coverage

Interface	Identification / present evidence	Current use / verification limit
Freeway USB	Three root-hub ports; owner identifies Triton Lite	Controller enumerated; no external device attached; individual socket wiring not inspected
X-Surf Ethernet	Active x-surf-100.device / unit 0	Live Ethernet link carrying the bridge connection
ZZ9000 Ethernet	Connector is part of the manufacturer specification	Not the active Roadshow interface; no live ZZ9000 network driver observed
ZZ9000 USB	Separate USB storage connector in the manufacturer specification	Not covered by Freeway/Poseidon enumeration; no mounted volume from it
ZZ9000 firmware microSD	BOOT.bin storage recorded in the previous firmware update	Separate from SD032G;; zzsd.device 43.20 is resident with open count 0; no mounted DOS volume
ZZ9000 digital video / native video capture	RTG Workbench and native ScummVM screens exist	Physical connector/cable, capture-board revision and monitor EDID not read
Buddha IDE	buddha.device / 0 and 2nd.buddha.device / 0	Two physical storage devices currently mounted
TF4060 IDE	ehide.device 1.2 (21 April 2024) resident	Open count 0; no mounted DOS volume through this driver
Native serial / MIDI	Configured CAMD internal serial port	Intended MT-32 path; instrument disconnected and physical transfer untested
Native floppy	DF0: via trackdisk.device / 0	No disk; drive mechanism and connector cabling unverified

Interface	Identification / present evidence	Current use / verification limit
Keyboard, mouse, joystick and parallel	OS keyboard/input/gameport interfaces present	Physical device models, chosen connector types, port occupancy and parallel hardware not inventoried

ZZ9000 auxiliary-port capabilities are from MNT documentation. Its firmware microSD is distinct from the Buddha-connected SD card. No unsupported inference is made from installed drivers to attached peripherals.

Networking and remote access

Property	Live result
Interface	x-surf-100; device x-surf-100.device unit 0
Driver	1.16 (3 September 2018)
MAC address	28:CD:4C:FF:F2:B2
IPv4 / mask	10.0.0.40 / 255.255.255.0
Binding	Dynamic (DHCP), according to Roadshow
Gateway	10.0.0.1
DNS	10.0.0.1 listed twice: dynamic and static
MTU / reported link speed	1500 bytes / 100,000,000 bits/s
TCP/IP stack	Roadshow 1.15; bsdsocket.library 4.364 (1 September 2023), 68020+ build
Roadie	1.3.9 (20 December 2021)
Listening TCP socket	0.0.0.0:2345
Connected bridge client	10.0.0.21:63432 → 10.0.0.40:2345
UDP sockets	None shown at snapshot
SFTP/FTP server	No separate listening SFTP/FTP socket shown; earlier file-transfer setup is not evidence of a running server now

The detailed snapshot reports **886 buffer overruns**, 1 dropped packet in its aggregate field, and separate in/out drop counters of 0/2. These counters have different meanings and are preserved verbatim. Connectivity is working; one cumulative snapshot cannot establish when the overruns occurred or whether they are

increasing. A later comparison under a controlled transfer would clarify whether tuning is useful. No counters were reset.

The DHCP lease date displayed as 10/10/2033 is not a reliable wall-clock reference because the Amiga clock differs from the Mac. The duplicate DNS address is a configuration redundancy, not proof of a service failure.

Audio and MIDI configuration

Component	Installed / loaded version
ahi.device	ahi.device 4.180 (10/31/1997) ©1994-1997 Martin Blom. 68060 version.
AHI preferences	AHI preferences 4.5 (01/05/1998)
Paula output	paula.audio 4.23 (12/06/1998)
ZZ9000AX output	zz9000ax.audio 4.19 (01/03/2023)
File output	filesave.audio 2.10 (10/25/1998)
MHI ZZ9000	mhizz9000.library 1.13 (01/03/2023)
CAMD	camd.library 37.14 (04/01/1993)
MidiPorts preferences	MIDI Port Prefs 1.0 (07/28/1992)

Saved `ENVARC:Sys/ahi.prefs` settings, decoded using the AHI preference structure and the installed AudioModes definitions:

Unit	Mode ID	Saved output mode	Frequency Hz	Channel field
Music Unit (255)	0xCAFE0001	ZZ9000AX:16 bit Stereo	32000	0
0	0x0002000C	Paula:Fast 8 bit mono	8000	1
1	0x0002000C	Paula:Fast 8 bit mono	8000	1
2	0x0002000C	Paula:Fast 8 bit mono	8000	1
3	0x0002000C	Paula:Fast 8 bit mono	8000	1

These are **saved preferences**, not a claim about every application’s active mixer format. ScummVM’s AHI mixer task, ahi.device and paula.audio were loaded during the audit. The Music Unit selects ZZ9000AX, but software installation and a preference selection do not establish that the AX daughterboard is physically fitted or audible.

The prior ScummVM setup enabled CAMD’s internal serial port and verified the in.0/out.0 clusters. ScummVM is configured for CAMD/native MT-32. The owner said the Roland is not connected; no MIDI notes were sent during this audit and no physical MT-32 response is claimed.

Operating system, libraries and dates

Layer	Reported version / date	Interpretation
Kickstart	47.115	Live ROM/system version; owner identifies OS release as 3.2.3
Exec	47.13 (1 January 2025)	Loaded system kernel
Intuition	47.53 (27 November 2024)	Loaded ROM/system component
DOS	47.30	Loaded header; no ID date exposed
Disk version	47.2 (10 April 2021)	version.library on disk and in memory
Workbench library	47.33 (31 March 2021)	Loaded and installed older disk component
SetPatch	47.4 (4 August 2020)	Installed executable
68060.library	47.2 (6 July 2022)	Loaded CPU support
mmu.library	47.10 (26 August 2025)	Loaded MMU support
MUI	muimaster.library 19.35 (12 February 1997)	Loaded version
AmiSSL	amisslmaster 5.23 / amissl_v353 5.23 (17 September 2025)	Installed; not present in initial loaded-library snapshot
Icon library	51.4 header; ID 51.4.600 (TC020)	Third-party replacement; header and full build identifier differ

OS consistency finding: this machine combines 2024/2025 ROM components with 2021 Workbench/disk components. The owner’s “OS 3.2.3” label should therefore be recorded alongside the actual versions, rather than used to certify a complete matching disk update. A future comparison against the owner’s registered 3.2.3 installation media can establish which disk files need updating; this audit has not installed or replaced them.

Clock finding: the Mac reported 7 October 2026; the Amiga Date command returned `Thursday 09-Oct-25 16:20:43` . Numerous files also retain 1980 or archive-era timestamps. An embedded \$VER date describes a component build/release; a filesystem timestamp describes stored metadata. Neither establishes installation date, hardware manufacture date or the age of this particular machine. Dates are preserved in their original formats in the CSVs.

The tables distinguish loaded header versions, embedded ID strings and `Version FILE FULL` results. For example, ZZ9000.card’s loaded header says 1.0 while its embedded/file version says 1.13. That does not mean the wrong card firmware is running.

Graphics, ARM firmware and previous tests

Item	Result / status
Native display	AGA PAL; 50 Hz VBlank; E-clock 709,379 Hz (not CPU clock)
Workbench screen	1920 × 800 × 8 bits/pixel
ScummVM screen	320 × 200 × 8 bits/pixel; active during audit
RTG core	rtg.library 43.538; Picasso96API.library 2.455; emulation.library 41.525 (29 July 2023)
Monitor driver	Picasso96 43.25 (07/29/2023) © 2023 iComp
ZZ9000 card driver	ZZ9000.card 1.13 (10/04/2022)
Current firmware register	\$0113 at ZZ9000 base \$40000000
Installed firmware record	BOOT_XX19c.bin, XACP 1.7; previous update and reboot/handshake verified
Firmware SHA-256	2b6a4224d4645694ef4d186baae14a86c100f4ce9e15033262a814cc239e7305
Patch suffix caveat	Register \$0113 identifies the 1.19 family; XX19c suffix comes from the recorded installed artifact, not fresh full-flash readback

Prior hardware tests recorded ZZBenchGUI 1.3 ARM Core1 execution and XACP dispatch, followed by owner-confirmed ZZQuake display. The protocol and firmware project is XACP-ZZ9000. These tests establish usable ARM execution through XACP; they do not establish source-level ARM debugging support.

Prior ZZBench metric	68060	ARM Core1
Integer MIPS	53.36	1061.77
Floating-point MWIPS	42.77	917.31

The earlier benchmark displayed ARM DDR read/write/copy as 0.0 MB/s; that subtest remains unresolved and is not presented as a valid memory-health or bandwidth result. No benchmark was rerun for this inventory.

Applications, startup and running services

Application/service	Location	Version	Evidence
AmigaBridge	SD032G:amiga-bridge/amiga-bridge	150,204 bytes; build/version from prior records: 1.20	Live AMIGABRIDGE port and TCP connection; Version FILE found no standard tag
Bridge network watcher	C:bridge-netwatch; S:Start-Amiga-Bridge-Auto	Custom native helper; no standard version tag	Live SIXIES.BRIDGE.NETWATCH port/task; starts bridge when interface has an IP
Roadie	HDD50Gig:Roadie	1.3.9 (2021-12-20)	Live ROADIE port/task
ScummVM	HDD50Gig:Games/ScummVM	AGA 68060 package 2.5.1.40; executable identifies 2.5.1, built 4 September 2026	Running; CAMD/MT-32 configured; no games added by our installation
ZZQuake	HDD50Gig:Games/ZZQuake	1.0; shareware Quake data	Prior installed/owner-confirmed display; not running at snapshot
ZZBenchGUI	SD032G:Drivers/XACP/ZZBench/ZZBenchGUI_v1.3	1.3	Prior native 68k/ARM test results retained
ZZ9000 firmware payload	SD032G:Drivers/XACP/BOOT_XX19c.bin	XX19c / XACP 1.7	Staged artifact and previous installation record
ARexx	SYS:System/RexxMast; rexxsyslib.library	47.2 library (19 August 2019)	RexxMaster task and REXX/AREXX public ports present

AmigaBridge originates from geekychris/amiga_mcp with workspace adaptations; the separate bridge-netwatch helper was built for this installation. The bridge’s uptime tool reported 18 minutes 33 seconds at the initial snapshot; source inspection shows this counts from bridge initialization, not system boot. The Mac-side dashboard is at localhost:55010 and the real Amiga listens on TCP 2345. Simulator/emulator results are not used as hardware evidence.

Startup currently invokes Roadshow networking, Poseidon’s saved stack loader, RexxMast and the bridge network watcher. The watcher checks for an active interface/address and avoids duplicate bridge processes. Its previous controlled restart tests passed; a cold-boot or Roadie disconnect/reconnect test is not newly certified by this report.

Confirmed stale startup entries: `S:User-Startup` runs `SYS:C/StikyRMB` , which is absent; `S:Startup-Sequence` runs `HDD50Gig:VisualPrefs` , which is absent. These lines may produce launch errors. Their intended replacements/paths should be checked before any edit.

Findings and recommendations

Priority	Finding	Recommended follow-up
Review	Clock differs by almost a year	Set the correct date/time and check RTC persistence when convenient; confirm the Mac date too before changing either clock.
Review	Mixed ROM and Workbench/disk component generations	Compare installed disk files with the owner’s 3.2.3 update manifest before doing a coordinated update.
Review	Missing StikyRMB and VisualPrefs startup targets	Locate the intended programs and correct or remove stale startup entries after checking their purpose.
Observe	X-Surf cumulative overruns	Compare counters before/after a controlled transfer; investigate only if overruns continue to grow or performance suffers.
Confirm	AHI Music Unit selects ZZ9000AX	Confirm AX hardware/output exists before relying on that preference; current ScummVM path uses loaded Paula audio.
Document	CPU clock, board revisions and physical chip markings unknown	Record component labels/photos during a future powered-off inspection; no need to infer them from benchmark speed.
Reconcile	Earlier Fast RAM estimate was 284 MB	Use the live 624 MiB map for the system record, retaining attribution caveats for the two non-ZZ banks.
Retest later	ZZBench ARM DDR subtest showed zero	Treat its memory-bandwidth result as unvalidated; CPU/XACP execution was verified separately.

Positive observations: bridge connected, network interface up, ARexx running, AHI/Paula loaded, Freeway controller/root hub configured, and mounted persistent filesystems validated with zero reported errors. These are operational snapshots, not exhaustive hardware stress tests.

Complete loaded libraries, classes and devices

77 library-list entries and 28 device-list entries captured directly from Exec. Open count 0 means the object is resident but currently unused; it is not an error. USB class-provided device entries can exist without attached hardware. The bridge overview initially saw 76 libraries; ShowConfig subsequently loaded boards.library, giving 77 in the native snapshot.

Kind	Name	Header version	Opens	Base	Embedded ID / date
LIB	rexsyslib.library	47.2	10	0x08777ef4	rexsyslib 47.2 (19.8.2019)
LIB	hid.class	4.4	1	0x088a7898	hid 4.4 (13.2.10) © 2002-2010 by Chris Hodges
LIB	utility.library	47.3	107	0x08000428	utility 47.3 (3.2.2020)
LIB	graphics.library	47.10	1	0x0800f940	graphics 47.10 (31.10.2021)
LIB	layers.library	46.2	1	0x08014314	layers 46.2 (18.12.2019)
LIB	keymap.library	47.1	1	0x08014828	keymap 47.1 (28.7.2019)
LIB	intuition.library	47.53	1	0x080161dc	intuition 47.53 (27.11.2024)
LIB	dos.library	47.30	78	0x080470d8	
LIB	mmu.library	47.10	1	0x08141ae8	mmu.library 47.10 (26.8.2025) (c) 1999-2025 The MMU.lib development group, THOR
LIB	68060.library	47.2	1	0x08047aa0	68060.library 47.2 (6.7.2022) (c) 1999-2022 The MMU.lib development group, THOR
LIB	680x0.library	46.1	1	0x08047890	680x0.library 46.1 (04.07.2016) (c) 1999-2016 The MMU.lib development group, THOR
LIB	version.library	47.2	0	0x080e2c40	version 47.2 (10.4.2021)
LIB	icon.library	51.4	15	0x087710d4	icon.library 51.4.600 (TC020)
LIB	diskfont.library	47.1	0	0x081255e0	diskfont 47.1 (29.6.2020)
LIB	locale.library	47.26	0	0x08123f08	locale 47.26 (11.4.2021)
LIB	iffparse.library	45.3	12	0x08123b10	iffparse 45.3 (18.9.2018)
LIB	gadtools.library	47.17	18	0x08361f50	gadtools 47.17 (16.7.2021)
LIB	ZZ9000.card	1.0	1	0x08143fd4	\$VER ZZ9000.card+blitter 1.13 (04.10.2022)
LIB	workbench.library	47.33	13	0x087e8b7c	workbench.library 47.33 (31.3.2021)
LIB	mathieedoubbas.library	47.2	7	0x08120200	
LIB	asl.library	47.9	4	0x0877be0c	asl 47.9 (31.3.2021)
LIB	commodities.library	45.2	0	0x087ee41c	commodities 45.2 (20.9.2018)
LIB	usergroup.library	4.31	1	0x08867dcc	usergroup.library 4.31 (13.8.2023)
LIB	datatypes.library	47.3	0	0x08874258	datatypes.library 47.3 (26.3.2021)
LIB	poseidon.library	4.5	2	0x0889f440	poseidon 4.5 (14.10.14) © 2002-2014 by Chris Hodges

Kind	Name	Header version	Opens	Base	Embedded ID / date
LIB	asixeth.class	4.5	1	0x0889ee30	asixeth 4.5 (12.03.13) © 2007-2013 by Harry Sintonen and Chris Hodges
LIB	camdusbmidi.class	4.5	1	0x088a8c6c	camdusbmidi 4.5 (14.10.14) © 2006-2010 by Chris Hodges
LIB	cdcacm.class	4.5	1	0x087ef568	cdcacm 4.5 (3.9.10) © 2002-2010 by Chris Hodges
LIB	dm9601eth.class	4.5	1	0x0889ea08	dm9601eth 4.5 (14.10.14) © 2006-2010 by Harry Sintonen and Chris Hodges
LIB	egalaxtouch.class	4.5	1	0x0889f760	egalaxtouch 4.5 (14.10.14) © 2004-2010 by Chris Hodges
LIB	hub.class	4.5	1	0x08867ed8	hub 4.5 (14.10.14) © 2002-2010 by Chris Hodges
LIB	massstorage.class	4.5	1	0x0891a078	massstorage 4.5 (14.10.14) © 2002-2010 by Chris Hodges
LIB	moschipeth.class	4.5	1	0x088a9650	moschipeth 4.5 (14.10.14) © 2009-2010 by Harry Sintonen and Chris Hodges
LIB	pegasus.class	4.5	1	0x088d2420	pegasus 4.5 (14.10.14) © 2006-2010 by Harry Sintonen and Chris Hodges
LIB	printer.class	4.5	1	0x0889f0d8	printer 4.5 (14.10.14) © 2002-2010 by Chris Hodges
LIB	rtl8150eth.class	4.5	1	0x088d26c8	rtl8150eth 4.5 (14.10.14) © 2009-2010 by Harry Sintonen and Chris Hodges
LIB	serialcp210x.class	4.5	1	0x088a9b68	serialcp210x 4.5 (6.11.12) © 2007-2010 by Chris Hodges
LIB	serialpl2303.class	4.5	1	0x088d29c0	serialpl2303 4.5 (6.11.12) © 2002-2010 by Chris Hodges
LIB	usbaudio.audio	4.5	1	0x0892c8f4	usbaudio 4.5 (14.10.14) © 2008-2010 by Chris Hodges
LIB	usbaudio.class	4.5	1	0x0892c808	usbaudio 4.5 (14.10.14) © 2008-2010 by Chris Hodges
LIB	usbvideo.vhi	1.5	1	0x0892ca10	usbvideo 4.5 (23.7.11) © 2009-2010 by Chris Hodges
LIB	usbvideo.class	4.5	1	0x0892c978	usbvideo 4.5 (23.7.11) © 2009-2010 by Chris Hodges
LIB	adaptecxchg.class	4.5	1	0x0892ca98	adaptecxchg 4.5 (5.7.13) © 2013 by Chris Hodges
LIB	bootkeyboard.class	4.5	1	0x089326c0	bootkeyboard 4.5 (14.10.14) © 2002-2010 by Chris Hodges
LIB	bootmouse.class	4.5	1	0x08932838	bootmouse 4.5 (14.10.14) © 2002-2010 by Chris Hodges
LIB	dfu.class	4.5	1	0x0893b098	dfu 4.5 (14.10.14) © 2002-2010 by Chris Hodges
LIB	ethwrap.class	4.5	1	0x0893b1e8	ethwrap 4.5 (14.10.14) © 2006-2010 by Harry Sintonen and Chris Hodges
LIB	ptp.class	4.5	1	0x08949558	ptp 4.5 (14.10.14) © 2008-2010 by Chris Hodges
LIB	simplemidi.class	4.5	1	0x0893f460	simplemidi 4.5 (14.10.14) © 2005-2010 by Chris Hodges
LIB	rawwrap.class	4.5	1	0x0893f5e0	rawwrap 4.5 (14.10.14) © 2002-2010 by Chris Hodges

Kind	Name	Header version	Opens	Base	Embedded ID / date
LIB	picture.datatype	47.5	2	0x08f451e4	picture.datatype 47.5 (22.5.2020)
LIB	png.datatype	47.3	1	0x08f44c80	png.datatype 47.3 (7.5.2020)
LIB	screennotify.library	1.0	4	0x08f5e0c4	\$VER: screennotify.library 1.0 (26.3.95)
LIB	muimaster.library	19.35	1	0x08f4575c	\$VER: muimaster.library 19.35 (12.02.97) ©1992-1997 Stefan Stuntz
LIB	muigfx.library	19.9	1	0x08f430f4	\$VER: muigfx.library 19.9 (12.02.97) ©1992-1997 Stefan Stuntz
LIB	muilowlevel.library	19.9	4	0x08f45058	\$VER: muilowlevel.library 19.9 (12.02.97) ©1992-1997 Stefan Stuntz
LIB	muirexx.library	19.9	1	0x08f4fc90	\$VER: muirexx.library 19.9 (12.02.97) ©1992-1997 Stefan Stuntz
LIB	bullet.library	46.4	0	0x08f4ff1c	bullet 46.4 (12.11.2019)
LIB	mathffp.library	46.1	3	0x08f54690	mathffp 46.1 (4.8.2019)
LIB	mathtrans.library	47.1	1	0x08f547c8	mathtrans 47.1 (13.2.2020)
LIB	ilbm.datatype	47.4	1	0x08f56738	ilbm.datatype 47.4 (3.3.2021)
LIB	mathieeedoubtrans.library	47.2	3	0x08f68818	
LIB	wizard.library	42.100	1	0x08f5fd90	\$VER: wizard.library 42.100 (20-Apr-00)
LIB	ab3zlib.library	1.0	1	0x08f695e0	ab3zlib.library 1.0 (03/30/2016)
LIB	mathieeesingbas.library	47.1	2	0x08f69668	
LIB	bsdsocket.library	4.364	2	0x087fa82c	bsdsocket.library 4.364 (1.9.2023) Roadshow 1.15 68020+ version
LIB	camd.library	37.14	0	0x0908b2f4	camd 37.14 (1.4.93)
LIB	paula.audio	4.23	1	0x090303dc	paula.audio 4.23 (06.12.98)
LIB	boards.library	3.55	0	0x093e90ac	\$VER: boards.library 3.55 (24-Jan-2021) maintained by Marcus Gerards (marcus.gerards@gmail.com)
LIB	expansion.library	47.4	13	0x000016cc	expansion 47.4 (1.1.2025)
LIB	cybergraphics.library	42.7	7	0x087d0bd8	cybergraphics.library 42.7 (8.3.02) emulation of original © by phase5 digital products
LIB	cgxvideo.library	42.1	0	0x08361d60	cgxvideo.library 42.1 (10.2.00) emulation of original © by phase5 digital products
LIB	vilintuisup.library	2.9	0	0x08361e5c	vilintuisup.library
LIB	emulation.library	41.525	1	0x081359cc	emulation.library 41.525 (29.7.2023)
LIB	Picasso96API.library	2.455	1	0x08f43244	Picasso96API.library 2.455 (29.7.2023)

Kind	Name	Header version	Opens	Base	Embedded ID / date
LIB	rtg.library	43.538	1	0x08770adc	rtg.library 43.538 (29.7.2023)
LIB	exec.library	47.13	5	0x080008bc	exec 47.13 (1.1.2025)
DEV	gameport.device	47.1	1	0x08014374	gameport 47.1 (4.8.2019)
DEV	timer.device	46.1	38	0x0801450c	timer 46.1 (4.8.2019)
DEV	keyboard.device	47.1	4	0x080146ac	keyboard 47.1 (28.7.2019)
DEV	input.device	47.1	9	0x080148f4	input 47.1 (21.7.2019)
DEV	ramdrive.device	46.2	1	0x08015c00	ramdrive 46.2 (26.12.2019)
DEV	trackdisk.device	47.14	1	0x08015c84	
DEV	ehide.device	1.2	0	0x0802a9f4	ehide 1.2 (21.4.2024) TF IDE Driver (4ef446b) © 2024 Erik Hemming
DEV	zzsd.device	43.20	0	0x0802eb64	zzsd.device 43.20 (12 Apr 2026)
DEV	2nd.buddha.device	52.110	1	0x0803284c	Buddha_IDE
DEV	buddha.device	52.110	2	0x08034dcc	Buddha_IDE
DEV	console.device	46.1	4	0x087ed088	console 46.1 (4.8.2019)
DEV	x-surf-100.device	1.16	1	0x0886f14c	\$VER: x-surf-100.device 1.16 (3.9.2018) Copyright © 1999-2000 H. Prüssing, 2007-2018 iComp GmbH
DEV	usbasixeth.device	4.5	1	0x087eebb4	asixeth 4.5 (12.03.13) © 2007-2013 by Harry Sintonen and Chris Hodges
DEV	usbmodem.device	4.5	1	0x08778a2c	cdcacm 4.5 (3.9.10) © 2002-2010 by Chris Hodges
DEV	dm9601eth.device	4.5	1	0x087eeb24	dm9601eth 4.5 (14.10.14) © 2006-2010 by Harry Sintonen and Chris Hodges
DEV	usbcsdi.device	4.5	1	0x08812cfc	massstorage 4.5 (14.10.14) © 2002-2010 by Chris Hodges
DEV	usbmoschipeth.device	4.5	1	0x08812d54	moschipeth 4.5 (14.10.14) © 2009-2010 by Harry Sintonen and Chris Hodges
DEV	usbpegasus.device	4.5	1	0x0889ec7c	pegasus 4.5 (14.10.14) © 2006-2010 by Harry Sintonen and Chris Hodges
DEV	usbparallel.device	4.5	1	0x0889ed5c	printer 4.5 (14.10.14) © 2002-2010 by Chris Hodges
DEV	rtl8150eth.device	4.5	1	0x0889f184	rtl8150eth 4.5 (14.10.14) © 2009-2010 by Harry Sintonen and Chris Hodges
DEV	serialcp210x.device	4.5	1	0x088d293c	serialcp210x 4.5 (6.11.12) © 2007-2010 by Chris Hodges
DEV	serialpl2303.device	4.5	1	0x089228a4	serialpl2303 4.5 (6.11.12) © 2002-2010 by Chris Hodges
DEV	usbethwrap.device	4.5	1	0x0892cb84	ethwrap 4.5 (14.10.14) © 2006-2010 by Harry Sintonen and Chris Hodges

Kind	Name	Header version	Opens	Base	Embedded ID / date
DEV	usbraw.device	4.5	1	0x08932a3c	rawwrap 4.5 (14.10.14) © 2002-2010 by Chris Hodges
DEV	freewaytritonz3usb.device	1.1	1	0x0894b744	freewaytritonusb 1.01 (2022.05.16) ©2022 by Chris Hodges, adapted by Matthias Hampel
DEV	clipboard.device	45.4	1	0x0913ef84	clipboard 45.4 (17.9.2019)
DEV	ahi.device	4.180	1	0x0907cce4	ahi.device 4.180 (31.10.97)
DEV	audio.device	47.1	1	0x09392e5c	audio 47.1 (4.8.2019)

CSV: Loaded libraries and devices.

Evidence files and reproducibility

The companion ZIP includes this HTML report, CSV/JSON inventories, raw read-only query output and the native probe sources. It excludes Amiga OS binaries, game assets and third-party driver binaries. The report opens locally without network dependencies and includes filters for the large tables. Browser Print / Save as PDF can print the narrative and loaded-library inventory; the 494-row installed table is intentionally omitted from print and remains in HTML/CSV.

Artifact	Purpose
hardware-inventory.csv	Hardware identification with evidence and unknowns
expansion-boards.csv	Six AutoConfig entries and raw IDs
memory-map.csv	RAM ranges and allocation priorities
volumes.csv	Persistent volume capacity/usage and filesystems
loaded-libraries-and-devices.csv	Native Exec inventory and embedded ID strings
installed-component-versions.csv	494 Version FILE FULL results with file metadata
system-files.csv	2,763 files under SYS: with sizes/dates/protection
audio-preferences.json	Saved AHI unit settings
native.tsv / filesystems.tsv	Raw native probe results
live-overview.json	Timestamped bridge overview

Artifact	Purpose
inventory.c / filesystems.c	Read-only native probe source
report-data.json	Machine-readable summary
SHA256SUMS.txt	Checksums for bundled evidence

Collection limits: no full disk image or sector scan; no per-chip physical inspection; no raw flash/RDB checksum audit; no new ARexx execution/source-debugging test; no exhaustive executable inventory of HDD50Gig: or SD032G:. The inventory does not prove that every installed library is ABI-compatible or every hardware port works under load.