

- Step 1. You are at the welcome screen of Cisco Cyber Vision. Below the Welcome message, click **Security overview**. This dashboard shows the past 30 days of security widgets such as vulnerable devices and devices ranked by risk score. In the lab the widgets may be sparse — that is expected.
- Step 2. Now click **Operational overview**. Compare the two dashboards. Note the Protocol Distribution widget and the Most Critical Events widget that are unique to the Operational view.
- Step 3. From the navigation drop-down at the top center, choose **Explore**, then select the **All data** preset, then click **Map** from the dropdown menu under Dashboard. The map renders all components within the chosen preset filter.
- Step 4. Click the plus button to zoom in on the map.
- Step 5. On the map, click the double bordered Schneider Icon  to review information of this device. Review the slide-out details: tags, identification, address info, and properties. Close the panel.
- Step 6. In the view toggle at the top, switch from **Map** to **Activity list**. You should now see one row per communication relationship. Click the first row to inspect the activity details on the right.
- Step 7. Switch back to **Map** view. Click a **blue line** coming from the Dell line to display the communication summary between these devices. Click the **Flows** button at the bottom right to view packet-level details, then close the window.