Open Access

Make Your Own Computer Vision Camera Using Raspberry Pi

LS100 — Module 01A · Video Data

Last updated: 2026-10-15

Authored by **Souvik Mandal, Ph.D.**

Project Leader & Instructor, Computational Behavioral Sciences, LS100, FAS, Harvard University | Linkedin ID: souvik-mandal-phd

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

Published Oct 15, 2026

1. Introduction: From Small Computer to Research Camera

A computer vision camera is not only a lens pointed at the world. It is a complete system that records visual data, stores it, and often begins analyzing it immediately. Raspberry Pi makes this idea accessible because it combines a small Linux computer, a camera interface, Python support, and flexible hardware input and output in a format that is inexpensive, portable, and easy to reconfigure.

For behavioral sciences, this makes Raspberry Pi especially attractive. A Raspberry Pi camera system can be mounted near a bird feeder, placed beside an animal arena, attached to a tripod in a classroom, or integrated into a custom enclosure for long-term observation. It can act as a recorder, a networked field device, or the front end of a computer vision pipeline.

This guide introduces the logic of choosing the right Raspberry Pi and the right camera for a behavioral research task. The most important question is not simply which hardware is most powerful. It is which combination preserves the information your study needs.

2. What Is a Raspberry Pi?

Raspberry Pi is a family of compact single-board computers. Unlike a microcontroller, which is usually designed for simple control tasks, a Raspberry Pi runs a full operating system, supports Python and other programming languages, can store files, connect to networks, and run computer vision software directly.

Several features make Raspberry Pi useful for behavioral video work:

- It runs Linux, which makes it well suited for scripting, automation, and remote access.
- It supports Python libraries commonly used in image and video analysis.
- It includes a CSI camera interface for direct connection to official Raspberry Pi camera modules.

- It can be deployed as a lightweight, dedicated recording system rather than as a full desktop computer.
- It can interact with other hardware such as infrared lights, sensors, storage devices, and network services.

In other words, Raspberry Pi is not just a camera controller. It can be the small computer at the center of an entire visual data collection system.

3. Which Raspberry Pi Computer Should You Choose?

Before choosing a camera module, it helps to choose the Raspberry Pi computer itself. All official Raspberry Pi cameras work with Raspberry Pi computers that have CSI camera connectors, but the boards differ substantially in computing power, connector type, thermal behavior, and how suitable they are for local computer vision processing.

Raspberry Pi Computer	Camera Connector Situation	Strengths	Best Use Cases	Main Limitations
Raspberry Pi Zero 2 W	One mini 22-pin CSI connector	Very small, low power, inexpensive, easy to hide in compact spaces	Lightweight recording at a feeder, small remote observation rigs, simple streaming or capture tasks	Limited RAM and processing power; not ideal for demanding on-device computer vision
Raspberry Pi 4 Model B	One standard 15-pin CSI connector	Mature platform, more power than Zero 2 W, good for recording and moderate processing	General-purpose recording, classroom prototypes, remote monitoring, light computer vision workflows	Only one camera connector; less headroom than Pi 5 for heavy local inference

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

Raspberry Pi Computer	Camera Connector Situation	Strengths	Best Use Cases	Main Limitations
Raspberry Pi 5	Two mini 22-pin camera/ display connectors	Highest processing power, dual camera support, best choice for demanding local workflows	On-device computer vision, higher-throughput capture, multi-camera experiments, real-time processing	Higher power draw; often benefits from active cooling
Compute Module 4	Camera support depends on carrier or IO board, commonly with two mini 22-pin connectors	Strong embedded flexibility, good for custom enclosures and product-like builds	Custom camera housings, permanent installations, integrated field devices, dual-camera embedded rigs	More setup complexity than standard Raspberry Pi boards

Two practical points matter immediately. First, Raspberry Pi 4 uses the larger 15-pin camera connector, whereas Raspberry Pi 5, Raspberry Pi Zero boards, and Compute Module IO boards use the smaller 22-pin connector. Second, even if a camera is electrically compatible, the board may not be equally suitable for the computational workload you want to run.

4. Official Raspberry Pi Camera Modules and Compatibility

Official Raspberry Pi camera modules are broadly compatible with Raspberry Pi computers that have CSI connectors. The main differences are not basic compatibility, but optical behavior, motion handling, lens flexibility, and how well each camera fits a particular scientific purpose.

In the table below, “Yes” means the camera can be used with that Raspberry Pi family. For Raspberry Pi 5, Raspberry Pi Zero 2 W, and most Compute Module IO boards, this usually requires the smaller 22-pin camera cable or an adapter.

Camera Module	Key Strengths	Pi 5	Pi 4	Zero 2 W	CM4	Best For	Less Suitable For

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

Camera Module	Key Strengths	Pi 5	Pi 4	Zero 2 W	CM4	Best For	Less Suitable For
Camera Module 3	12 MP, autofocus, compact, standard field of view, HDR support	Yes	Yes	Yes	Yes	General-purpose research recording, tabletop tasks, feeder cameras in daylight, classroom demonstrations	Very fast motion where rolling-shutter distortion matters, custom long-lens work
Camera Module 3 Wide	12 MP, autofocus, wide field of view	Yes	Yes	Yes	Yes	Room coverage, cage or arena monitoring, group interaction scenes, wider context recording	Cases where subjects are small and distant and need tight framing
Camera Module 3 NoIR / NoIR Wide	Infrared-sensitive variants for use with IR illumination	Yes	Yes	Yes	Yes	Night observation, low-light feeder studies, dark enclosures with infrared lighting	Natural-color daylight recording where infrared sensitivity is not needed

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

Camera Module	Key Strengths	Pi 5	Pi 4	Zero 2 W	CM4	Best For	Less Suitable For
High Quality Camera	12.3 MP, interchangeable lenses, strong optical flexibility, external trigger support	Yes	Yes	Yes	Yes	Custom optics, telephoto views, controlled recording setups, experiments needing lens choice	Ultra-compact builds, very fast motion where global shutter is essential
Global Shutter Camera	Minimal motion distortion, short exposures, external trigger support, sync-friendly	Yes	Yes	Yes	Yes	Fast motion, biomechanics, human athletics, wing beats, synchronized machine vision	High-resolution wide-scene imaging where fine spatial detail is more important than shutter behavior
AI Camera	12.3 MP intelligent vision sensor with on-sensor neural network acceleration	Yes	Yes	Yes	Yes	Low-latency object detection, edge AI prototypes, automated feeder alerts, embedded smart-camera workflows	Projects that need full flexibility in offline model design or traditional interchangeable optics

This comparison highlights an important principle. “Compatible” does not mean “equally well matched.” A Camera Module 3 may connect perfectly to a Raspberry Pi Zero 2 W, but if the project demands real-time detection and local decision-making, a Raspberry Pi 5 may still be the more appropriate computer.

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

5. Matching Hardware to Research Purpose

The most useful way to choose hardware is to begin with the biological or behavioral question. What are you trying to see? How fast does the subject move? How much light is available? Do you need local detection on the device, or can you record first and analyze later?

Research Scenario	Suggested Raspberry Pi	Suggested Camera	Why This Combination Works	Main Tradeoff
Bird species detection at a feeder in daylight	**Pi 5** if running local detection, **Pi 4** if mostly recording	**AI Camera** for local alerts, or **Camera Module 3** for record-first workflows	Good balance of resolution and field use; AI Camera is useful when the device should react on its own	AI workflow adds complexity; Camera Module 3 needs later analysis
Bird feeder observation at night or dawn	**Pi 4** or **Pi 5**	**Camera Module 3 NoIR** with IR illumination	Infrared sensitivity is more important here than natural daylight color	Requires infrared lighting and careful illumination design
Tracking human athletes or fast limb motion	**Pi 5**	**Global Shutter Camera**	Global shutter reduces distortion and supports short exposures for fast movement	Lower native resolution than the 12 MP modules
Recording posture or interaction in a room or arena	**Pi 4** or **Pi 5**	**Camera Module 3 Wide**	Wider field of view captures more of the space without custom optics	Subjects may appear smaller in the frame
Longer-distance subject framing or custom optics	**Pi 5** or **CM4**	**High Quality Camera** with a suitable lens	External lens choice gives much better control over magnification and framing	Larger, less plug-and-play, and more demanding to configure well

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

Tiny embedded smart camera in a custom enclosure	**CM4** or **Zero 2 W**	**Camera Module 3**, **NoIR**, or **AI Camera** depending task	Strong fit for purpose-built devices and low-profile installations	More engineering tradeoffs around thermals, power, and housing

This scenario view is often more informative than any single specification. For example, a fast human athletics study may value shutter behavior more than megapixel count, whereas a feeder study may value low power, wireless convenience, or on-device alerts more than raw resolution.

6. Low Light, Frame Rate, and Shutter Requirements

Raspberry Pi camera choices become much clearer when you ask three questions together:

- How much light will be available?
- How fast does the subject move?
- Will the system record first or analyze on the device?

If the scene is dim and the subject moves slowly, a Camera Module 3 or HQ Camera may work well, especially if the experiment can tolerate moderate frame rates. If the subject moves quickly, then short shutter times become more important, and short shutter times need more light. In those cases, the Global Shutter Camera often becomes much more attractive, particularly when paired with strong illumination.

For night observation, a NoIR camera with infrared lighting is often more useful than simply increasing ISO and accepting noisy video. For local, always-on detection systems, the AI Camera or a Raspberry Pi 5 paired with another camera may be the better choice. Hardware choice is therefore always a balance between optics, motion, lighting, compute power, and analytic goals.

7. Practical Compatibility Notes

Several practical issues matter before assembly begins:

- **Connector size:** Raspberry Pi 4 uses the larger 15-pin CSI connector, while Raspberry Pi 5, Raspberry Pi Zero models, and most Compute Module IO boards use the smaller 22-pin connector.
- **Cable choice:** Official cameras usually ship with a standard cable, but smaller boards often require a standard-to-mini cable or adapter.
- **Cooling:** Raspberry Pi 5 is powerful, but real-time computer vision workloads may require active cooling.
- **Storage:** Long video recordings quickly become large, so fast SD cards or external SSDs may matter.

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

- **Lenses:** HQ and Global Shutter cameras are especially useful when your experiment requires a specific field of view or magnification.
- **Lighting:** No camera choice can fully rescue poor lighting. Experimental illumination remains part of the measurement design.

8. A Recommended Starter Build for LS100

For most LS100 students, the simplest and most flexible starting point is:

- **Raspberry Pi 5** with **4 GB or 8 GB RAM**
- **Camera Module 3** for standard framing, or **Camera Module 3 Wide** for room or arena coverage
- **Official Raspberry Pi power supply**
- **microSD card** of at least 64 GB
- **Active cooling** if you plan to run sustained local processing on Raspberry Pi 5

This build is not the only good option, but it is the most forgiving. It supports modern software well, gives enough computing headroom for experimentation, and still keeps the system relatively simple. If your study requires night vision, replace the standard Camera Module 3 with a **NoIR** variant and add infrared illumination. If it requires very fast motion capture, replace it with the **Global Shutter Camera**.

9. Hardware You Will Need

The table below lists the minimum parts needed to assemble a working Raspberry Pi computer vision camera, along with optional additions that become useful in research settings.

Component	Required?	Why It Matters	Recommended Starting Choice
Raspberry Pi computer	Yes	The main computer that records and may analyze video	**Pi 5** for most students; **Pi 4** if mostly recording; **Zero 2 W** for very small deployments
Camera module	Yes	Determines field of view, motion handling, and low-light behavior	**Camera Module 3** or **Camera Module 3 Wide**

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

Component	Required?	Why It Matters	Recommended Starting Choice
CSI camera cable	Yes	Physically connects the camera to the board	Standard 15-pin cable for **Pi 4**; standard-to-mini 22-pin cable for **Pi 5**, **Zero 2 W**, and many **CM4** setups
microSD card	Yes	Holds the operating system and often short recordings	64 GB or larger, preferably a fast U3/V30 card
Power supply	Yes	Prevents instability during capture or processing	Official Raspberry Pi supply matched to the board
Cooling	Often	Helps prevent thermal throttling during sustained use	Active cooler or ventilated case for **Pi 5**
Mount or tripod	Strongly recommended	Stabilizes the camera and makes framing reproducible	Small tripod, clamp, or fixed bracket
Keyboard, mouse, and monitor	Optional	Useful for first setup if not working headless	Only needed for direct setup
Network access	Strongly recommended	Makes updating, remote login, and file transfer easier	Wi-Fi or Ethernet
Infrared light	Optional	Needed for dark recording with NoIR cameras	IR illuminator for night observation
External SSD	Optional	Useful for long or high-bitrate recordings	Especially useful on Pi 5

10. Step 1: Choose Your Build Path

Before assembly, choose one of these simple starting paths:

- **General-purpose daylight build:** Pi 5 + Camera Module 3 or Camera Module 3 Wide

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

- **Night observation build:** Pi 5 or Pi 4 + Camera Module 3 NoIR + infrared light
- **Fast-motion build:** Pi 5 + Global Shutter Camera + stronger illumination

The steps below are nearly identical across these options. The main differences are the camera module, cable type, and the lighting requirements.

11. Step 2: Assemble the Hardware

1. Power the Raspberry Pi fully off before connecting the camera.
2. Insert the microSD card if you have already prepared it, or set it aside for later if you will flash the operating system first.
3. Open the CSI camera connector latch gently.
4. Insert the ribbon cable evenly and fully. On the Raspberry Pi side, the metal contacts face away from the connector flap. On the camera side, the cable should be seated firmly according to the board markings, with the contacts aligned correctly.
5. Close the connector latch carefully so the ribbon cable is held in place.
6. Mount the camera in a stable orientation. For a feeder or small enclosure, a fixed bracket is often best. For testing indoors, a tabletop tripod is usually enough.
7. If you are using a Pi 5 and expect sustained processing, install the active cooler or use a ventilated case.
8. Connect power only after the cable is seated and the camera is mounted securely.

The most common early build failure is a mis-seated ribbon cable, especially when switching between 15-pin and 22-pin connectors. If the camera is not detected later, the cable should be the first thing you re-check.

12. Step 3: Install Raspberry Pi OS

The simplest setup path is to use **Raspberry Pi Imager** on your laptop or desktop computer.

1. Open Raspberry Pi Imager.
2. Choose your Raspberry Pi board.
3. Choose **Raspberry Pi OS (64-bit)** for Pi 4, Pi 5, or CM4. For Zero 2 W, Raspberry Pi OS Lite is often a good choice if you want a lightweight remote setup.
4. Select your microSD card.
5. Use the advanced settings menu to pre-configure:
    - hostname
    - username and password
    - Wi-Fi credentials
    - SSH access
    - locale and keyboard settings
6. Flash the card, eject it safely, and insert it into the Raspberry Pi.

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

For research deployments, enabling SSH during imaging is extremely useful because it allows the Raspberry Pi to be managed remotely without a dedicated screen or keyboard.

13. Step 4: First Boot and Basic Setup

Boot the Raspberry Pi and allow the initial setup to complete. Then update the system:

```
sudo apt update
sudo apt full-upgrade -y
sudo reboot
```

After rebooting, confirm that the system is healthy and reachable over the network if you plan to run it headless.

Current Raspberry Pi OS versions usually auto-detect official camera modules, so in most cases you do not need to manually enable a legacy camera interface. Using an up-to-date operating system is more important than older camera-enabling workflows.

14. Step 5: Verify That the Camera Is Detected

Once the system is updated, test whether Raspberry Pi can see the camera:

```
rpicam-hello --list-cameras
```

If the camera is detected correctly, you can launch a live preview:

```
rpicam-hello -t 0
```

For a headless setup without a display, capture a still image directly instead:

```
rpicam-still -n -o first_test.jpg
```

If this step fails, do not move forward yet. Re-check the ribbon cable, connector type, power stability, and whether the camera module matches the board-side cable.

15. Step 6: Capture Your First Still Image and Video Clip

Once the camera is recognized, create a first test still image:

```
rpicam-still -o first_still.jpg
```

Then capture a short video clip:

```
rpicam-vid -t 5000 -o first_clip.h264
```

These two files are your first quality-control checkpoint. Review them carefully for:

- framing
- focus

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

- lighting
- motion blur
- background clutter

For behavioral research, the first successful capture is not just a proof that the camera works. It is the first chance to judge whether the visual information needed by the study is actually present.

16. Step 7: Test the Camera from Python

If you want students to move quickly from hardware setup into Python workflows, a minimal **Picamera2** test is useful. Install the library if needed:

```
sudo apt install -y python3-picamera2
```

Then create a short test script such as:

```
from picamera2 import Picamera2
from time import sleep

camera = Picamera2()
camera.configure(camera.create_still_configuration())
camera.start()
sleep(2)
camera.capture_file("python_test.jpg")
camera.stop()
```

Run it with:

```
python3 camera_test.py
```

This step matters because it confirms that the camera is not only physically connected, but also available from a Python workflow, which is how many LS100 students will later interact with it.

17. Step 8: Build a Recording Setup That Supports Measurement

A camera build becomes a research tool only when the recording setup is stable enough to support repeated observation. Before collecting real data, establish a repeatable capture arrangement.

Use this checklist:

- Fix the camera position so it does not shift between sessions.
- Keep lighting as stable as possible across recordings.
- Decide whether autofocus is helpful or whether a stable fixed focus is better.
- Include enough contrast between the subject and the background.
- Avoid unnecessary background motion such as leaves, screens, or moving shadows if they may interfere with analysis.

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

- Record a pilot clip and inspect it at the frame level before starting the full experiment.

For many behavioral studies, a visually beautiful image is less important than a stable, analyzable one.

18. Step 9: Starter Recording Profiles by Use Case

The table below gives practical starting points rather than strict prescriptions. These are intended as first test configurations that students can refine after reviewing pilot recordings.

Use Case	Suggested Hardware	Starting Recording Goal	What to Check First
Daylight bird feeder recording	Pi 4 or Pi 5 + Camera Module 3	Clear subject framing, stable daylight exposure, moderate frame rate	Can the bird fill enough of the frame for later detection or classification?
Night feeder observation	Pi 4 or Pi 5 + Camera Module 3 NoIR + IR light	Reliable visibility without visible-light disturbance	Is the IR illumination even, and does the subject remain identifiable?
Room or arena interaction recording	Pi 4 or Pi 5 + Camera Module 3 Wide	Wide coverage with enough detail for posture or movement interpretation	Are subjects large enough in the frame for later tracking?
Human athletics or fast limb motion	Pi 5 + Global Shutter Camera	Short exposure and reduced motion distortion	Is there enough light to support fast capture without blur?
Long-distance framing or lens-controlled setup	Pi 5 or CM4 + HQ Camera	Optical control over magnification and scene coverage	Does the chosen lens provide enough detail without making the scene too narrow?

19. Step 10: Troubleshooting Common Problems

Problem	Likely Cause	What to Try

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/

Camera not detected	Ribbon cable misaligned, wrong cable type, connector not fully seated	Re-seat the cable carefully, confirm 15-pin versus 22-pin cable type, update Raspberry Pi OS
Image is very dark or noisy	Not enough light, unsuitable exposure settings, wrong camera for the lighting conditions	Add light, reduce frame rate if possible, use NoIR plus IR illumination for dark settings
Fast motion looks smeared or bent	Rolling shutter distortion or shutter too slow	Use stronger light, shorten exposure, or move to the Global Shutter Camera
Pi 5 becomes hot or slows down	Thermal throttling during sustained processing	Add active cooling, improve airflow, reduce on-device workload
Files become too large	Resolution, frame rate, or recording duration too high	Use shorter pilot clips, lower frame rate where acceptable, move long recordings to external storage
Tracking later fails	Subject too small, low contrast, cluttered background, unstable camera position	Reframe the scene, improve lighting, simplify the background, stabilize the mount

20. From Prototype to Research Device

At this stage, students should have a working Raspberry Pi camera, a first still image, a first video clip, and a basic Python test. That is enough to begin asking the next scientific question: is this recording setup good enough for the behavior I want to study?

The best next step is not to collect a large dataset immediately. It is to run short pilot recordings, review them frame by frame, and decide whether the current build preserves the relevant visual information. If it does, the system can move into experimental use. If it does not, the needed changes are usually clear: more light, a wider view, a longer lens, a different camera module, or a higher-powered Raspberry Pi.

Downloaded from: https://souvikmandal.info/teaching-learning/ls100/module-01a-video-data/