# Rajalakshmi Engineering College

Name: Sowmya R

Email: 241501207@rajalakshmi.edu.in

Roll no: 241501207 Phone: 9677182021

Branch: REC

Department: I AI & ML FC

Batch: 2028

Degree: B.E - AI & ML



## NeoColab\_REC\_CS23231\_DATA STRUCTURES

REC\_DS using C\_Week 4\_COD\_Question 3

Attempt : 1 Total Mark : 10 Marks Obtained : 10

Section 1: Coding

#### 1. Problem Statement

Write a program to implement a queue using an array and pointers. The program should provide the following functionalities:

Insert an element into the queue. Delete an element from the queue. Display the elements in the queue.

The queue has a maximum capacity of 5 elements. If the queue is full and an insertion is attempted, a "Queue is full" message should be displayed. If the queue is empty and a deletion is attempted, a "Queue is empty" message should be displayed.

## Input Format

Each line contains an integer representing the chosen option from 1 to 3.

Option 1: Insert an element into the queue followed by an integer representing the element to be inserted, separated by a space.

Option 2: Delete an element from the queue.

Option 3: Display the elements in the queue.

### **Output Format**

For option 1 (insertion):-

- 1. The program outputs: "<data> is inserted in the queue." if the data is successfully inserted.
- 2. "Queue is full." if the queue is already full and cannot accept more elements.

For option 2 (deletion):-

- 1. The program outputs: "Deleted number is: <data>" if an element is successfully deleted and returns the value of the deleted element.
- 2. "Queue is empty." if the queue is empty no elements can be deleted.

For option 3 (display):-

- 1. The program outputs: "Elements in the queue are: <element1> <element2> ... <elementN>" where <element1>, <element2>, ..., <elementN> represent the elements present in the queue.
- 2. "Queue is empty." if the queue is empty no elements can be displayed.

For invalid options, the program outputs: "Invalid option."

Refer to the sample output for the formatting specifications.

Sample Test Case

Input: 1 10

```
Output: 10 is inserted in the queue.
     Elements in the queue are: 10
     Invalid option.
     Answer
     #include <stdio.h>
     #include <stdlib.h>
     #define max 5
     int queue[max];
     int front = -1, rear = -1;
    int insertq(int *data) {
       if ((rear + 1) \% max == front) {
         return 0; // Queue is full
       if (front == -1) {
         front = rear = 0;
       } else {
         rear = (rear + 1) \% max;
return 1;
       queue[rear] = *data;
     int delq() {
       if (front == -1) {
         printf("Queue is empty.\n");
         return -1;
       }
       int data = queue[front];
       if (front == rear) {
front = (front + 1) % max;
```

24,150,1201

```
printf("Deleted number is: %d\n", data);
  return data;
void display() {
  if (front == -1) {
     printf("Queue is empty.\n");
    return;
  }
  printf("Elements in the queue are:");
  int i = front;
  while (1) {
    printf(" %d", queue[i]);
    if (i == rear) break;
    i = (i + 1) \% max;
  printf("\n");
}
int main()
  int data, reply, option;
  while (1)
    if (scanf("%d", &option) != 1)
       break;
     switch (option)
       case 1:
         if (scanf("%d", &data) != 1)
            break;
         reply = insertq(&data);
         if (reply == 0)
            printf("Queue is full.\n");
         else
            printf("%d is inserted in the queue.\n", data);
         break:
       case 2:
                      Called without arguments
          delq(); //
         break;
       case 3:
```

```
24/501201
                                                                         24/501201
             display();
             break;
          default:
             printf("Invalid option.\n");
             break;
        }
      }
      return 0;
    Status: Correct
                                                                  Marks: 10/10
                                                247501207
                                                                         241501201
241501201
                        24/501201
247501201
                                                241501201
                                                                         24/501201
                        241501201
```

247501201

241501201

241501201

247501201