JT-4000 Controller

Studio 87. Free and open source (AGPL-3.0-or-later).

Intro

JT-4000 Controller sends and receives the MIDI messages (CC and NRPN) of the Behringer JT-4000 MICRO, so you can control the synth from your DAW, automate it, and see its settings change in the plugin. It is an early build: the editor is a searchable list of every control.

Quick start

- On the Behringer JT-4000 MICRO, turn on MIDI CC receive and transmit (and NRPN where the device has the option).
- Insert the plugin on a MIDI track whose output goes to the Behringer JT-4000 MICRO, and send the track's MIDI to the device. Set the plugin's MIDI channel to the one the device listens on.
- Move a value in the list: the matching message is sent to the device. Turn a knob on the device: the value moves in the plugin.
- Use the group menu and the search box to find a control. Send all sends every value to the device at once.
- Every control is an automatable parameter in your DAW.

Honest status

- The map has 22 entries (Osc, Filter, LFO1, LFO2, Mod, General). It was written from the maker's documentation, nothing was invented.
- None of the 22 controls has been tested on the real device. Every control is marked "not tested on hardware yet" in the list. A range that the documentation does not print is assumed to be 0 to 127 and is marked that way.
- No SysEx and no patch librarian yet. Nothing is sent that is not in the map.
- Incoming messages from the device are consumed by the plugin and never echoed back. At most 16 values are sent per audio block so the device is not flooded.

Window

- Resize by dragging any edge or corner; the shape stays the same. Hover a control for its address (CC or NRPN number).
- Free and open source. The plugin collects no data and never touches the network.