TRoss 303 — Acid Bass for Max for Live

TRoss 303 is a TB-303 style bass synthesizer with a built-in 303-style step sequencer, 64-pattern memory, pattern chaining and a random pattern creator. The sound comes from the **Lemus ro-mono-303** engine: a part-by-part circuit model of the original voice board (pitch and slide, VCO, the four-pole transistor ladder filter, envelopes, accent sweep, VCA and output stage), compiled into the device so it sounds the same as the Lemus plugin.



The device panel (preview rendering).

1. Installing

Unzip the download. You get a folder **TRoss 303** containing the device, the panel script and the engine for Mac (*tross303~.mxo*) and Windows (*tross303~.mxe64*). Keep these files together in the same folder, and drag the whole folder into the **User Library** in Live's browser. Then drag **TRoss 303.amxd** onto a MIDI track.

macOS: files downloaded from the web are quarantined, and Live won't load the engine until the quarantine flag is removed. Run this once in Terminal (adjust the path to where the folder is):

```
xattr -dr com.apple.quarantine ~/Music/Ableton/User\ Library/TRoss\ 303
```

Single-file device: to make one self-contained .amxd (for example to share or sell), open the device in the Max editor, press **Freeze Device** in the toolbar, and save. Freezing embeds the panel script and both engine files.

Requirements: Ableton Live 11 or 12 with Max for Live (Max 8.6 or newer), macOS 11+ (Apple Silicon or Intel) or Windows 10/11 64-bit.

2. Sound controls

Control	What it does
TUNING	Fine pitch, about a fifth either way (centre = in tune).
CUT OFF	Filter cutoff of the 4-pole ladder.
RESO	Resonance. High settings give the classic squelch.
ENV MOD	How far the filter envelope sweeps the cutoff.
DECAY	Filter envelope decay time (accented notes always use the short decay, like the original).
ACCENT	How strongly accented steps (and MIDI notes with velocity 100+) hit the filter and VCA.
VOLUME	Output level.
WAVE	Saw or square oscillator.
CUT MAX	How high the CUT OFF knob reaches at full (1200-3000 Hz). Real units differ: 2300 Hz is a typical one, lower is darker.
TRANSP	Transposes the sequencer's notes, in semitones (-24 to +24).
SEQ	Turns the built-in sequencer on or off. With it off, the device is a MIDI-played 303 voice.

Every control is a Live parameter: you can automate it, map it to MIDI or a Push, and it's saved with your set.

3. Playing from MIDI

MIDI notes on the track play the voice too, the way Roland's own TB-03/TD-3 take MIDI: **velocity 100 or more is an accent** (velocity is otherwise ignored), and a note that starts while another is still held **slides** to its pitch without retriggering. Overlap notes in a clip to get slides. While you hold MIDI notes they take over from the sequencer.

4. The sequencer

The sequencer follows Live's transport: press Play in Live and it starts from step 1 of the current pattern (or of the chain), in sync with Live's tempo; press Stop and it stops. Each pattern has up to 16 steps, and every step has five lanes:

Lane	How to edit	Meaning
NOTE	Click and drag up/down. Clicking a rest step makes it a note. Alt-click turns it back into a rest.	C to C' (the 303's 13 keys).
OCT	Click to cycle: none, UP, DN.	One octave up or down.
ACCENT	Click to toggle.	Accented step: louder, brighter, faster filter sweep.
SLIDE	Click to toggle.	Glides from this step into the next one, without retriggering.
TIME	Click to cycle: note (dot), tie (dash), rest (empty).	Tie holds the previous note through this step. A tie after a rest plays nothing.

The LEDs above the steps show which step is playing (when the pattern you're editing is the one playing). **LEN** –/+ sets the pattern length, 1 to 16 steps; steps past the end are greyed out.

5. Pattern memory

Like the TB-303 there are **64 patterns**: 4 groups (**I-IV**) × 8 patterns (**1-8**) × 2 sections (**A/B**). Pick a group, a pattern and a section to select one; the panel shows **EDIT** (the pattern you're editing) and **PLAY** (the one playing). As on the original, a new selection made while playing takes over when the current pattern reaches its end, so changes stay in time.

Button	What it does
COPY / PASTE	Copy the selected pattern, then paste it into another one.
CLEAR	Clears the selected pattern (all rests, 16 steps).
UNDO	Undoes the last change to the selected pattern (random, clear, paste or an edit). Press again to redo.

All 64 patterns and the chain are saved inside your Live set, and each instance of the device has its own.

6. Pattern chaining

A chain plays up to 16 patterns in order and loops (for example I-1A, I-1A, I-1B, I-2A). Press **EDIT** (next to CHAIN) and click pattern buttons to add them to the end of the chain; the current group and section are used, and clicking A or B adds that section. Press EDIT again to stop adding. **CHAIN** turns chain playback on or off, and **CLR** empties the chain. With chain playback on, the sequencer plays the chain from its first entry each time Live starts.

7. Random pattern creator

RANDOM writes a new acid line into the selected pattern. UNDO brings back the previous one. The controls next to it shape what it makes:

Control	What it does
SCALE / ROOT	Notes stay in this key. *Acid* is a root-heavy minor-seventh set, the classic sound; *Chromatic* uses every note.

DENSITY	How many steps play rather than rest (downbeats play a little more often, so lines keep a pulse).
ACCENT	Chance of an accent on each step.
SLIDE	Chance of a slide on each step.
OCTAVE	How many steps get an octave UP or DOWN.
LOCK	Keeps a lane as it is when re-rolling: for example lock NOTE and OCT and press RANDOM again to re-roll only the rhythm, accents and slides.

8. About, credits and license

Click the **i** button at the top right for the About window; click the Gumroad link to open the store.

TRoss 303 by Ticco Ross — ticcoross@gmail.com — https://ticcoross.gumroad.com/

The sound engine is **Lemus ro-mono-303** (https://github.com/lemus-dev/lemus, version 0.1.3), used unchanged. Lemus and TRoss 303 are free software under the **GNU Affero General Public License v3**: the complete source code of this device is at https://github.com/Spunkmeyer77/TRoss303. TB-303 is a trademark of Roland Corporation; this product is not affiliated with or endorsed by Roland.